Please note that Cypress is an Infineon Technologies Company.
The document following this cover page is marked as “Cypress” document as this is the company that originally developed the product. Please note that Infineon will continue to offer the product to new and existing customers as part of the Infineon product portfolio.

Continuity of document content
The fact that Infineon offers the following product as part of the Infineon product portfolio does not lead to any changes to this document. Future revisions will occur when appropriate, and any changes will be set out on the document history page.

Continuity of ordering part numbers
Infineon continues to support existing part numbers. Please continue to use the ordering part numbers listed in the datasheet for ordering.

CY8C4Axx

PSoC® Analog Coprocessor Registers Technical Reference Manual (TRM)

Document No. 002-10405 Rev. *B

January 9, 2019

Cypress Semiconductor
198 Champion Court
San Jose, CA 95134-1709
www.cypress.com

Copyrights

© Cypress Semiconductor Corporation, 2015-2019. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you under its copyright rights in the Software, a personal, non-exclusive, nontransferable license (without the right to sublicense) (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units. Cypress also grants you a personal, non-exclusive, nontransferable, license (without the right to sublicense) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely to the minimum extent that is necessary for you to exercise your rights under the copyright license granted in the previous sentence. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and Company shall and hereby does release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. Company shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.

Contents

Section 2: Register Mapping **32**

1. AROUTE Registers **36**

1.1 Register Details 36
1.1.1 ART_CTRL 38
1.1.2 ART_SARMUXVPLUS_SW 39
1.1.3 ART_SARMUXVPLUS_SW_CLR 41
1.1.4 ART_SARMUXVMINUS_SW 43
1.1.5 ART_SARMUXVMINUS_SW_CLR 45
1.1.6 ART_SARMUXCOREIO0_SW 47
1.1.7 ART_SARMUXCOREIO0_SW_CLR 48
1.1.8 ART_SARMUXCOREIO1_SW 49
1.1.9 ART_SARMUXCOREIO1_SW_CLR 50
1.1.10 ART_SARMUXCOREIO2_SW 51
1.1.11 ART_SARMUXCOREIO2_SW_CLR 52
1.1.12 ART_SARMUXCOREIO3_SW 53
1.1.13 ART_SARMUXCOREIO3_SW_CLR 54
1.1.14 ART_SARAROUTEVREF_SW 55
1.1.15 ART_SARAROUTEVREF_SW_CLR 56
1.1.16 ART_SARAROUTEVDDA_SW 57
1.1.17 ART_SARAROUTEVDDA_SW_CLR 58
1.1.18 ART_SARMUX_SW_HW_CTRL 59
1.1.19 ART_SARMUXVPLUS_SW_STATUS 60
1.1.20 ART_SARMUXVMINUS_SW_STATUS 61
1.1.21 ART_UAB0VIN00_SW 62
1.1.22 ART_UAB0VIN00_SW_CLR 63
1.1.23 ART_UAB0VIN01_SW 64
1.1.24 ART_UAB0VIN01_SW_CLR 65
1.1.25 ART_UAB0VIN02_SW 66
1.1.26 ART_UAB0VIN02_SW_CLR 67
1.1.27 ART_UAB0VIN03_SW 68
1.1.28 ART_UAB0VIN03_SW_CLR 69
1.1.29 ART_UAB0VIN10_SW 70
1.1.30 ART_UAB0VIN10_SW_CLR 71
1.1.31 ART_UAB0VIN11_SW 72
1.1.32 ART_UAB0VIN11_SW_CLR 73
1.1.33 ART_UAB0VIN12_SW 74
1.1.34 ART_UAB0VIN12_SW_CLR 75
1.1.35 ART_UAB0VIN13_SW 76
1.1.36 ART_UAB0VIN13_SW_CLR 77
1.1.37 ART_CTB0VREF_SW 78
1.1.38 ART_CTB0VREF_SW_CLR 79
1.1.39 ART_UAB0VREF_SW 80

1.1.40 ART_UAB0VREF_SW_CLR 82
1.1.41 ART_UAB1VIN00_SW 84
1.1.42 ART_UAB1VIN00_SW_CLR 85
1.1.43 ART_UAB1VIN01_SW 86
1.1.44 ART_UAB1VIN01_SW_CLR 87
1.1.45 ART_UAB1VIN02_SW 88
1.1.46 ART_UAB1VIN02_SW_CLR 89
1.1.47 ART_UAB1VIN03_SW 90
1.1.48 ART_UAB1VIN03_SW_CLR 91
1.1.49 ART_UAB1VIN10_SW 92
1.1.50 ART_UAB1VIN10_SW_CLR 93
1.1.51 ART_UAB1VIN11_SW 94
1.1.52 ART_UAB1VIN11_SW_CLR 95
1.1.53 ART_UAB1VIN12_SW 96
1.1.54 ART_UAB1VIN12_SW_CLR 97
1.1.55 ART_UAB1VIN13_SW 98
1.1.56 ART_UAB1VIN13_SW_CLR 99
1.1.57 ART_CTB1VREF_SW 100
1.1.58 ART_CTB1VREF_SW_CLR 101

2. Cortex M0+ (CM0+) Registers 102

2.1 Register Details 102
2.1.1 CM0P_DWT_PID4 104
2.1.2 CM0P_DWT_PID0 105
2.1.3 CM0P_DWT_PID1 106
2.1.4 CM0P_DWT_PID2 107
2.1.5 CM0P_DWT_PID3 108
2.1.6 CM0P_DWT_CID0 109
2.1.7 CM0P_DWT_CID1 110
2.1.8 CM0P_DWT_CID2 111
2.1.9 CM0P_DWT_CID3 112
2.1.10 CM0P_BP_PID4 113
2.1.11 CM0P_BP_PID0 114
2.1.12 CM0P_BP_PID1 115
2.1.13 CM0P_BP_PID2 116
2.1.14 CM0P_BP_PID3 117
2.1.15 CM0P_BP_CID0 118
2.1.16 CM0P_BP_CID1 119
2.1.17 CM0P_BP_CID2 120
2.1.18 CM0P_BP_CID3 121
2.1.19 CM0P_SYST_CSR 122
2.1.20 CM0P_SYST_RVR 124
2.1.21 CM0P_SYST_CVR 125
2.1.22 CM0P_SYST_CALIB 126
2.1.23 CM0P_ISER 127
2.1.24 CM0P_ICER 128
2.1.25 CM0P_ISPR 129
2.1.26 CM0P_ICPR 130
2.1.27 CM0P_IPR0 131
2.1.28 CM0P_IPR1 132
2.1.29 CM0P_IPR2 133
2.1.30 CM0P_IPR3 134
2.1.31 CM0P_IPR4 135
2.1.32 CM0P_IPR5 136

2.1.33 CM0P_IPR6 137
2.1.34 CM0P_IPR7 138
2.1.35 CM0P_CPUID 139
2.1.36 CM0P_ICSR 140
2.1.37 CM0P_AIRCR 142
2.1.38 CM0P_SCR 143
2.1.39 CM0P_CCR 144
2.1.40 CM0P_SHPR2 145
2.1.41 CM0P_SHPR3 146
2.1.42 CM0P_SHCSR 147
2.1.43 CM0P_SCS_PID4 148
2.1.44 CM0P_SCS_PID0 149
2.1.45 CM0P_SCS_PID1 150
2.1.46 CM0P_SCS_PID2 151
2.1.47 CM0P_SCS_PID3 152
2.1.48 CM0P_SCS_CID0 153
2.1.49 CM0P_SCS_CID1 154
2.1.50 CM0P_SCS_CID2 155
2.1.51 CM0P_SCS_CID3 156
2.1.52 CM0P_ROM_SCS 157
2.1.53 CM0P_ROM_DWT 158
2.1.54 CM0P_ROM_BPU 159
2.1.55 CM0P_ROM_END 160
2.1.56 CM0P_ROM_CSMT 161
2.1.57 CM0P_ROM_PID4 162
2.1.58 CM0P_ROM_PID0 163
2.1.59 CM0P_ROM_PID1 164
2.1.60 CM0P_ROM_PID2 165
2.1.61 CM0P_ROM_PID3 166
2.1.62 CM0P_ROM_CID0 167
2.1.63 CM0P_ROM_CID1 168
2.1.64 CM0P_ROM_CID2 169
2.1.65 CM0P_ROM_CID3 170

3. TCPWM - Individual Counter (CNT) Registers 171

3.1 Register Details 171
3.1.1 TCPWM_CNT0_CTRL 177
3.1.2 TCPWM_CNT0_STATUS 180
3.1.3 TCPWM_CNT0_COUNTER 181
3.1.4 TCPWM_CNT0_CC 182
3.1.5 TCPWM_CNT0_CC_BUFF 183
3.1.6 TCPWM_CNT0_PERIOD 184
3.1.7 TCPWM_CNT0_PERIOD_BUFF 185
3.1.8 TCPWM_CNT0_TR_CTRL0 186
3.1.9 TCPWM_CNT0_TR_CTRL1 188
3.1.10 TCPWM_CNT0_TR_CTRL2 190
3.1.11 TCPWM_CNT0_INTR 192
3.1.12 TCPWM_CNT0_INTR_SET 193
3.1.13 TCPWM_CNT0_INTR_MASK 194
3.1.14 TCPWM_CNT0_INTR_MASKED 195
3.1.15 TCPWM_CNT1_CTRL 196
3.1.16 TCPWM_CNT1_STATUS 199
3.1.17 TCPWM_CNT1_COUNTER 200
3.1.18 TCPWM_CNT1_CC 201

3.1.19 TCPWM_CNT1_CC_BUFF 202
3.1.20 TCPWM_CNT1_PERIOD 203
3.1.21 TCPWM_CNT1_PERIOD_BUFF 204
3.1.22 TCPWM_CNT1_TR_CTRL0 205
3.1.23 TCPWM_CNT1_TR_CTRL1 207
3.1.24 TCPWM_CNT1_TR_CTRL2 209
3.1.25 TCPWM_CNT1_INTR 211
3.1.26 TCPWM_CNT1_INTR_SET 212
3.1.27 TCPWM_CNT1_INTR_MASK 213
3.1.28 TCPWM_CNT1_INTR_MASKED 214
3.1.29 TCPWM_CNT2_CTRL 215
3.1.30 TCPWM_CNT2_STATUS 218
3.1.31 TCPWM_CNT2_COUNTER 219
3.1.32 TCPWM_CNT2_CC 220
3.1.33 TCPWM_CNT2_CC_BUFF 221
3.1.34 TCPWM_CNT2_PERIOD 222
3.1.35 TCPWM_CNT2_PERIOD_BUFF 223
3.1.36 TCPWM_CNT2_TR_CTRL0 224
3.1.37 TCPWM_CNT2_TR_CTRL1 226
3.1.38 TCPWM_CNT2_TR_CTRL2 228
3.1.39 TCPWM_CNT2_INTR 230
3.1.40 TCPWM_CNT2_INTR_SET 231
3.1.41 TCPWM_CNT2_INTR_MASK 232
3.1.42 TCPWM_CNT2_INTR_MASKED 233
3.1.43 TCPWM_CNT3_CTRL 234
3.1.44 TCPWM_CNT3_STATUS 237
3.1.45 TCPWM_CNT3_COUNTER 238
3.1.46 TCPWM_CNT3_CC 239
3.1.47 TCPWM_CNT3_CC_BUFF 240
3.1.48 TCPWM_CNT3_PERIOD 241
3.1.49 TCPWM_CNT3_PERIOD_BUFF 242
3.1.50 TCPWM_CNT3_TR_CTRL0 243
3.1.51 TCPWM_CNT3_TR_CTRL1 245
3.1.52 TCPWM_CNT3_TR_CTRL2 247
3.1.53 TCPWM_CNT3_INTR 249
3.1.54 TCPWM_CNT3_INTR_SET 250
3.1.55 TCPWM_CNT3_INTR_MASK 251
3.1.56 TCPWM_CNT3_INTR_MASKED 252
3.1.57 TCPWM_CNT4_CTRL 253
3.1.58 TCPWM_CNT4_STATUS 256
3.1.59 TCPWM_CNT4_COUNTER 257
3.1.60 TCPWM_CNT4_CC 258
3.1.61 TCPWM_CNT4_CC_BUFF 259
3.1.62 TCPWM_CNT4_PERIOD 260
3.1.63 TCPWM_CNT4_PERIOD_BUFF 261
3.1.64 TCPWM_CNT4_TR_CTRL0 262
3.1.65 TCPWM_CNT4_TR_CTRL1 264
3.1.66 TCPWM_CNT4_TR_CTRL2 266
3.1.67 TCPWM_CNT4_INTR 268
3.1.68 TCPWM_CNT4_INTR_SET 269
3.1.69 TCPWM_CNT4_INTR_MASK 270
3.1.70 TCPWM_CNT4_INTR_MASKED 271
3.1.71 TCPWM_CNT5_CTRL 272
3.1.72 TCPWM_CNT5_STATUS 275

3.1.73 TCPWM_CNT5_COUNTER 276
3.1.74 TCPWM_CNT5_CC 277
3.1.75 TCPWM_CNT5_CC_BUFF 278
3.1.76 TCPWM_CNT5_PERIOD 279
3.1.77 TCPWM_CNT5_PERIOD_BUFF 280
3.1.78 TCPWM_CNT5_TR_CTRL0 281
3.1.79 TCPWM_CNT5_TR_CTRL1 283
3.1.80 TCPWM_CNT5_TR_CTRL2 285
3.1.81 TCPWM_CNT5_INTR 287
3.1.82 TCPWM_CNT5_INTR_SET 288
3.1.83 TCPWM_CNT5_INTR_MASK 289
3.1.84 TCPWM_CNT5_INTR_MASKED 290
3.1.85 TCPWM_CNT6_CTRL 291
3.1.86 TCPWM_CNT6_STATUS 294
3.1.87 TCPWM_CNT6_COUNTER 295
3.1.88 TCPWM_CNT6_CC 296
3.1.89 TCPWM_CNT6_CC_BUFF 297
3.1.90 TCPWM_CNT6_PERIOD 298
3.1.91 TCPWM_CNT6_PERIOD_BUFF 299
3.1.92 TCPWM_CNT6_TR_CTRL0 300
3.1.93 TCPWM_CNT6_TR_CTRL1 302
3.1.94 TCPWM_CNT6_TR_CTRL2 304
3.1.95 TCPWM_CNT6_INTR 306
3.1.96 TCPWM_CNT6_INTR_SET 307
3.1.97 TCPWM_CNT6_INTR_MASK 308
3.1.98 TCPWM_CNT6_INTR_MASKED 309
3.1.99 TCPWM_CNT7_CTRL 310
3.1.100 TCPWM_CNT7_STATUS 313
3.1.101 TCPWM_CNT7_COUNTER 314
3.1.102 TCPWM_CNT7_CC 315
3.1.103 TCPWM_CNT7_CC_BUFF 316
3.1.104 TCPWM_CNT7_PERIOD 317
3.1.105 TCPWM_CNT7_PERIOD_BUFF 318
3.1.106 TCPWM_CNT7_TR_CTRL0 319
3.1.107 TCPWM_CNT7_TR_CTRL1 321
3.1.108 TCPWM_CNT7_TR_CTRL2 323
3.1.109 TCPWM_CNT7_INTR 325
3.1.110 TCPWM_CNT7_INTR_SET 326
3.1.111 TCPWM_CNT7_INTR_MASK 327
3.1.112 TCPWM_CNT7_INTR_MASKED 328

4. CPU Sub System (CPUSS) Registers 329

4.1 Register Details 329
4.1.1 CPUSS_SYSREQ 330
4.1.2 CPUSS_SYSARG 332
4.1.3 CPUSS_FLASH_CTL 333
4.1.4 CPUSS_ROM_CTL 335
4.1.5 CPUSS_RAM_CTL 336
4.1.6 CPUSS_DMAC_CTL 337
4.1.7 CPUSS_SL_CTL0 338
4.1.8 CPUSS_SL_CTL1 339

5. CapSense Sigma Delta (CSD) Registers 340

5.1 Register Details 340

5.1.1 CSD_CONFIG 342
5.1.2 CSD_SPARE 345
5.1.3 CSD_STATUS 346
5.1.4 CSD_STAT_SEQ 347
5.1.5 CSD_STAT_CNTS 348
5.1.6 CSD_RESULT_VAL1 349
5.1.7 CSD_RESULT_VAL2 350
5.1.8 CSD_ADC_RES 351
5.1.9 CSD_INTR 352
5.1.10 CSD_INTR_SET 353
5.1.11 CSD_INTR_MASK 354
5.1.12 CSD_INTR_MASKED 355
5.1.13 CSD_HSCMP 356
5.1.14 CSD_AMBUF 357
5.1.15 CSD_REFGEN 358
5.1.16 CSD_CSDCMP 360
5.1.17 CSD_IDACA 362
5.1.18 CSD_IDACB 365
5.1.19 CSD_SW_RES 368
5.1.20 CSD_SENSE_PERIOD 370
5.1.21 CSD_SENSE_DUTY 372
5.1.22 CSD_SW_HS_P_SEL 374
5.1.23 CSD_SW_HS_N_SEL 376
5.1.24 CSD_SW_SHIELD_SEL 377
5.1.25 CSD_SW_AMUXBUF_SEL 379
5.1.26 CSD_SW_BYP_SEL 381
5.1.27 CSD_SW_CMP_P_SEL 382
5.1.28 CSD_SW_CMP_N_SEL 384
5.1.29 CSD_SW_REFGEN_SEL 385
5.1.30 CSD_SW_FW_MOD_SEL 386
5.1.31 CSD_SW_FW_TANK_SEL 388
5.1.32 CSD_SW_DSI_SEL 390
5.1.33 CSD_SEQ_TIME 391
5.1.34 CSD_SEQ_INIT_CNT 392
5.1.35 CSD_SEQ_NORM_CNT 393
5.1.36 CSD_ADC_CTL 394
5.1.37 CSD_SEQ_START 395
5.1.38 CSD_TRIM_CTRL 397

6. CTB Registers 398

6.1 Register Details 398
6.1.1 CTB0_CTB_CTRL 400
6.1.2 CTB0_OA_RES0_CTRL 401
6.1.3 CTB0_OA_RES1_CTRL 403
6.1.4 CTB0_COMP_STAT 405
6.1.5 CTB0_INTR 406
6.1.6 CTB0_INTR_SET 407
6.1.7 CTB0_INTR_MASK 408
6.1.8 CTB0_INTR_MASKED 409
6.1.9 CTB0_OA0_SW 410
6.1.10 CTB0_OA0_SW_CLEAR 412
6.1.11 CTB0_OA1_SW 414
6.1.12 CTB0_OA1_SW_CLEAR 416
6.1.13 CTB0_CTBBUS_SW 418

6.1.14 CTB0_CTBBUS_SW_CLEAR 420
6.1.15 CTB0_CTB_SW_HW_CTRL 422
6.1.16 CTB0_CTB_SW_STATUS 424
6.1.17 CTB0_OA0_OFFSET_TRIM 427
6.1.18 CTB0_OA0_SLOPE_OFFSET_TRIM 428
6.1.19 CTB0_OA0_COMP_TRIM 429
6.1.20 CTB0_OA1_OFFSET_TRIM 430
6.1.21 CTB0_OA1_SLOPE_OFFSET_TRIM 431
6.1.22 CTB0_OA1_COMP_TRIM 432
6.1.23 CTB0_RMP_TRIM 433
6.1.24 CTB1_CTB_CTRL 434
6.1.25 CTB1_OA_RES0_CTRL 435
6.1.26 CTB1_OA_RES1_CTRL 437
6.1.27 CTB1_COMP_STAT 439
6.1.28 CTB1_INTR 440
6.1.29 CTB1_INTR_SET 441
6.1.30 CTB1_INTR_MASK 442
6.1.31 CTB1_INTR_MASKED 443
6.1.32 CTB1_OA0_SW 444
6.1.33 CTB1_OA0_SW_CLEAR 446
6.1.34 CTB1_OA1_SW 448
6.1.35 CTB1_OA1_SW_CLEAR 450
6.1.36 CTB1_CTBBUS_SW 452
6.1.37 CTB1_CTBBUS_SW_CLEAR 454
6.1.38 CTB1_CTB_SW_HW_CTRL 456
6.1.39 CTB1_CTB_SW_STATUS 458
6.1.40 CTB1_OA0_OFFSET_TRIM 461
6.1.41 CTB1_OA0_SLOPE_OFFSET_TRIM 462
6.1.42 CTB1_OA0_COMP_TRIM 463
6.1.43 CTB1_OA1_OFFSET_TRIM 464
6.1.44 CTB1_OA1_SLOPE_OFFSET_TRIM 465
6.1.45 CTB1_OA1_COMP_TRIM 466
6.1.46 CTB1_RMP_TRIM 467

7. Direct-Memory Access Registers 468

7.1 Register Details 468
7.1.1 DMAC_CTL 469
7.1.2 DMAC_STATUS 470
7.1.3 DMAC_STATUS_SRC_ADDR 472
7.1.4 DMAC_STATUS_DST_ADDR 473
7.1.5 DMAC_STATUS_CH_ACT 474
7.1.6 DMAC_CH_CTL0 475
7.1.7 DMAC_CH_CTL1 477
7.1.8 DMAC_CH_CTL2 479
7.1.9 DMAC_CH_CTL3 481
7.1.10 DMAC_CH_CTL4 483
7.1.11 DMAC_CH_CTL5 485
7.1.12 DMAC_CH_CTL6 487
7.1.13 DMAC_CH_CTL7 489
7.1.14 DMAC_INTR 491
7.1.15 DMAC_INTR_SET 492
7.1.16 DMAC_INTR_MASK 493
7.1.17 DMAC_INTR_MASKED 494

8. Direct-Memory Access Descriptor Registers 495

8.1 Register Details 495
8.1.1 DMAC_DESCR0_PING_SRC 497
8.1.2 DMAC_DESCR0_PING_DST 498
8.1.3 DMAC_DESCR0_PING_CTL 499
8.1.4 DMAC_DESCR0_PING_STATUS 503
8.1.5 DMAC_DESCR0_PONG_SRC 505
8.1.6 DMAC_DESCR0_PONG_DST 506
8.1.7 DMAC_DESCR0_PONG_CTL 507
8.1.8 DMAC_DESCR0_PONG_STATUS 509
8.1.9 DMAC_DESCR1_PING_SRC 510
8.1.10 DMAC_DESCR1_PING_DST 511
8.1.11 DMAC_DESCR1_PING_CTL 512
8.1.12 DMAC_DESCR1_PING_STATUS 516
8.1.13 DMAC_DESCR1_PONG_SRC 518
8.1.14 DMAC_DESCR1_PONG_DST 519
8.1.15 DMAC_DESCR1_PONG_CTL 520
8.1.16 DMAC_DESCR1_PONG_STATUS 522
8.1.17 DMAC_DESCR2_PING_SRC 523
8.1.18 DMAC_DESCR2_PING_DST 524
8.1.19 DMAC_DESCR2_PING_CTL 525
8.1.20 DMAC_DESCR2_PING_STATUS 529
8.1.21 DMAC_DESCR2_PONG_SRC 531
8.1.22 DMAC_DESCR2_PONG_DST 532
8.1.23 DMAC_DESCR2_PONG_CTL 533
8.1.24 DMAC_DESCR2_PONG_STATUS 535
8.1.25 DMAC_DESCR3_PING_SRC 536
8.1.26 DMAC_DESCR3_PING_DST 537
8.1.27 DMAC_DESCR3_PING_CTL 538
8.1.28 DMAC_DESCR3_PING_STATUS 542
8.1.29 DMAC_DESCR3_PONG_SRC 544
8.1.30 DMAC_DESCR3_PONG_DST 545
8.1.31 DMAC_DESCR3_PONG_CTL 546
8.1.32 DMAC_DESCR3_PONG_STATUS 548
8.1.33 DMAC_DESCR4_PING_SRC 549
8.1.34 DMAC_DESCR4_PING_DST 550
8.1.35 DMAC_DESCR4_PING_CTL 551
8.1.36 DMAC_DESCR4_PING_STATUS 555
8.1.37 DMAC_DESCR4_PONG_SRC 557
8.1.38 DMAC_DESCR4_PONG_DST 558
8.1.39 DMAC_DESCR4_PONG_CTL 559
8.1.40 DMAC_DESCR4_PONG_STATUS 561
8.1.41 DMAC_DESCR5_PING_SRC 562
8.1.42 DMAC_DESCR5_PING_DST 563
8.1.43 DMAC_DESCR5_PING_CTL 564
8.1.44 DMAC_DESCR5_PING_STATUS 568
8.1.45 DMAC_DESCR5_PONG_SRC 570
8.1.46 DMAC_DESCR5_PONG_DST 571
8.1.47 DMAC_DESCR5_PONG_CTL 572
8.1.48 DMAC_DESCR5_PONG_STATUS 574
8.1.49 DMAC_DESCR6_PING_SRC 575
8.1.50 DMAC_DESCR6_PING_DST 576
8.1.51 DMAC_DESCR6_PING_CTL 577
8.1.52 DMAC_DESCR6_PING_STATUS 581

8.1.53 DMAC_DESCR6_PONG_SRC 583
8.1.54 DMAC_DESCR6_PONG_DST 584
8.1.55 DMAC_DESCR6_PONG_CTL 585
8.1.56 DMAC_DESCR6_PONG_STATUS 587
8.1.57 DMAC_DESCR7_PING_SRC 588
8.1.58 DMAC_DESCR7_PING_DST 589
8.1.59 DMAC_DESCR7_PING_CTL 590
8.1.60 DMAC_DESCR7_PING_STATUS 594
8.1.61 DMAC_DESCR7_PONG_SRC 596
8.1.62 DMAC_DESCR7_PONG_DST 597
8.1.63 DMAC_DESCR7_PONG_CTL 598
8.1.64 DMAC_DESCR7_PONG_STATUS 600

9. Deep Sleep Amplifier Bias (DSAB) Registers 601

9.1 Register Details 601
9.1.1 PASS_DSAB_DSAB_CTRL 602
9.1.2 PASS_DSAB_DSAB_DFT 604

10. GPIO - Common Registers 605

10.1 Register Details 605
10.1.1 GPIO_INTR_CAUSE 606

11. GPIO - Port Specific Registers 607

11.1 Register Details 607
11.1.1 GPIO_PRT0_DR 609
11.1.2 GPIO_PRT0_PS 610
11.1.3 GPIO_PRT0_PC 612
11.1.4 GPIO_PRT0_INTR_CFG 614
11.1.5 GPIO_PRT0_INTR 616
11.1.6 GPIO_PRT0_PC2 618
11.1.7 GPIO_PRT0_DR_SET 620
11.1.8 GPIO_PRT0_DR_CLR 621
11.1.9 GPIO_PRT0_DR_INV 622
11.1.10 GPIO_PRT1_DR 623
11.1.11 GPIO_PRT1_PS 624
11.1.12 GPIO_PRT1_PC 626
11.1.13 GPIO_PRT1_INTR_CFG 628
11.1.14 GPIO_PRT1_INTR 630
11.1.15 GPIO_PRT1_PC2 632
11.1.16 GPIO_PRT1_DR_SET 634
11.1.17 GPIO_PRT1_DR_CLR 635
11.1.18 GPIO_PRT1_DR_INV 636
11.1.19 GPIO_PRT2_DR 637
11.1.20 GPIO_PRT2_PS 638
11.1.21 GPIO_PRT2_PC 640
11.1.22 GPIO_PRT2_INTR_CFG 642
11.1.23 GPIO_PRT2_INTR 644
11.1.24 GPIO_PRT2_PC2 646
11.1.25 GPIO_PRT2_DR_SET 648
11.1.26 GPIO_PRT2_DR_CLR 649
11.1.27 GPIO_PRT2_DR_INV 650
11.1.28 GPIO_PRT3_DR 651
11.1.29 GPIO_PRT3_PS 652

11.1.30 GPIO_PRT3_PC 654
11.1.31 GPIO_PRT3_INTR_CFG 656
11.1.32 GPIO_PRT3_INTR 658
11.1.33 GPIO_PRT3_PC2 660
11.1.34 GPIO_PRT3_DR_SET 662
11.1.35 GPIO_PRT3_DR_CLR 663
11.1.36 GPIO_PRT3_DR_INV 664
11.1.37 GPIO_PRT4_DR 665
11.1.38 GPIO_PRT4_PS 666
11.1.39 GPIO_PRT4_PC 667
11.1.40 GPIO_PRT4_INTR_CFG 669
11.1.41 GPIO_PRT4_INTR 671
11.1.42 GPIO_PRT4_PC2 672
11.1.43 GPIO_PRT4_DR_SET 673
11.1.44 GPIO_PRT4_DR_CLR 674
11.1.45 GPIO_PRT4_DR_INV 675
11.1.46 GPIO_PRT5_DR 676
11.1.47 GPIO_PRT5_PS 677
11.1.48 GPIO_PRT5_PC 678
11.1.49 GPIO_PRT5_INTR_CFG 680
11.1.50 GPIO_PRT5_INTR 682
11.1.51 GPIO_PRT5_PC2 684
11.1.52 GPIO_PRT5_DR_SET 685
11.1.53 GPIO_PRT5_DR_CLR 686
11.1.54 GPIO_PRT5_DR_INV 687

12. High Speed IO Matrix (HSIOM) Registers 688

12.1 Register Details 688
12.1.1 HSIOM_AMUX_SPLIT_CTL0 689
12.1.2 HSIOM_AMUX_SPLIT_CTL1 691
12.1.3 HSIOM_AMUX_SPLIT_CTL2 693

13. HSIOM - Port Specific Registers 695

13.1 Register Details 695
13.1.1 HSIOM_PORT_SEL0 696
13.1.2 HSIOM_PORT_SEL1 698
13.1.3 HSIOM_PORT_SEL2 700
13.1.4 HSIOM_PORT_SEL3 702
13.1.5 HSIOM_PORT_SEL4 704
13.1.6 HSIOM_PORT_SEL5 706

14. LCD Registers 708

14.1 Register Details 708
14.1.1 LCD_ID 709
14.1.2 LCD_DIVIDER 710
14.1.3 LCD_CONTROL 711
14.1.4 LCD_DATA00 713
14.1.5 LCD_DATA01 714
14.1.6 LCD_DATA02 715
14.1.7 LCD_DATA03 716
14.1.8 LCD_DATA04 717
14.1.9 LCD_DATA05 718
14.1.10 LCD_DATA06 719

14.1.11 LCD_DATA07 720
14.1.12 LCD_DATA10 721
14.1.13 LCD_DATA11 722
14.1.14 LCD_DATA12 723
14.1.15 LCD_DATA13 724
14.1.16 LCD_DATA14 725
14.1.17 LCD_DATA15 726
14.1.18 LCD_DATA16 727
14.1.19 LCD_DATA17 728

15. Low Power Comparator (LPCOMP) Registers 729

15.1 Register Details 729
15.1.1 LPCOMP_ID 730
15.1.2 LPCOMP_CONFIG 731
15.1.3 LPCOMP_INTR 734
15.1.4 LPCOMP_INTR_SET 735
15.1.5 LPCOMP_INTR_MASK 736
15.1.6 LPCOMP_INTR_MASKED 737
15.1.7 LPCOMP_TRIM1 738
15.1.8 LPCOMP_TRIM2 739
15.1.9 LPCOMP_TRIM3 740
15.1.10 LPCOMP_TRIM4 741

16. PASS MMIO Registers 742

16.1 Register Details 742
16.1.1 PASS_INTR_CAUSE 743
16.1.2 PASS_TRIG_SYNC 744
16.1.3 PASS_SAR_TRIG_SEL 745
16.1.4 PASS_PASS_CTRL 746
16.1.5 PASS_PRB_CTRL 747
16.1.6 PASS_PRB_REF0 748
16.1.7 PASS_PRB_REF1 749
16.1.8 PASS_PRB_REF2 750
16.1.9 PASS_PRB_REF3 751
16.1.10 PASS_LNFE_CTRL 752
16.1.11 PASS_LNFE_SW 753
16.1.12 PASS_DSAB_TRIM 754
16.1.13 PASS_PRB_TRIM 755

17. Peripheral Interconnect (PERI) Registers 756

17.1 Register Details 756
17.1.1 PERI_DIV_CMD 758
17.1.2 PERI_PCLK_CTL0 760
17.1.3 PERI_PCLK_CTL1 761
17.1.4 PERI_PCLK_CTL2 762
17.1.5 PERI_PCLK_CTL3 763
17.1.6 PERI_PCLK_CTL4 764
17.1.7 PERI_PCLK_CTL5 765
17.1.8 PERI_PCLK_CTL6 766
17.1.9 PERI_PCLK_CTL7 767
17.1.10 PERI_PCLK_CTL8 768
17.1.11 PERI_PCLK_CTL9 769
17.1.12 PERI_PCLK_CTL10 770

17.1.13 PERI_PCLK_CTL11 771
17.1.14 PERI_PCLK_CTL12 772
17.1.15 PERI_PCLK_CTL13 773
17.1.16 PERI_PCLK_CTL14 774
17.1.17 PERI_PCLK_CTL15 775
17.1.18 PERI_PCLK_CTL16 776
17.1.19 PERI_DIV_16_CTL0 777
17.1.20 PERI_DIV_16_CTL1 778
17.1.21 PERI_DIV_16_CTL2 779
17.1.22 PERI_DIV_16_CTL3 780
17.1.23 PERI_DIV_16_CTL4 781
17.1.24 PERI_DIV_16_CTL5 782
17.1.25 PERI_DIV_16_CTL6 783
17.1.26 PERI_DIV_16_5_CTL0 784
17.1.27 PERI_DIV_16_5_CTL1 786
17.1.28 PERI_DIV_16_5_CTL2 788
17.1.29 PERI_DIV_24_5_CTL 790
17.1.30 PERI_TR_CTL 792

18. PRGIO_PRTO Registers 794

18.1 Register Details 794
18.1.1 PRGIO_PRT0_CTL 795
18.1.2 PRGIO_PRT0_SYNC_CTL 797
18.1.3 PRGIO_PRT0_LUT_SEL0 798
18.1.4 PRGIO_PRT0_LUT_SEL1 800
18.1.5 PRGIO_PRT0_LUT_SEL2 802
18.1.6 PRGIO_PRT0_LUT_SEL3 804
18.1.7 PRGIO_PRT0_LUT_SEL4 806
18.1.8 PRGIO_PRT0_LUT_SEL5 808
18.1.9 PRGIO_PRT0_LUT_SEL6 810
18.1.10 PRGIO_PRT0_LUT_SEL7 812
18.1.11 PRGIO_PRT0_LUT_CTL0 814
18.1.12 PRGIO_PRT0_LUT_CTL1 816
18.1.13 PRGIO_PRT0_LUT_CTL2 818
18.1.14 PRGIO_PRT0_LUT_CTL3 820
18.1.15 PRGIO_PRT0_LUT_CTL4 822
18.1.16 PRGIO_PRT0_LUT_CTL5 824
18.1.17 PRGIO_PRT0_LUT_CTL6 826
18.1.18 PRGIO_PRT0_LUT_CTL7 828
18.1.19 PRGIO_PRT0_DU_SEL 830
18.1.20 PRGIO_PRT0_DU_CTL 832
18.1.21 PRGIO_PRT0_DATA 833

19. CoreSight ROM Table Registers 834

19.1 Register Details 834
19.1.1 ROMTABLE_ADDR 835
19.1.2 ROMTABLE_DID 836
19.1.3 ROMTABLE_PID4 837
19.1.4 ROMTABLE_PID5 838
19.1.5 ROMTABLE_PID6 839
19.1.6 ROMTABLE_PID7 840
19.1.7 ROMTABLE_PID0 841
19.1.8 ROMTABLE_PID1 842
19.1.9 ROMTABLE_PID2 843

19.1.10 ROMTABLE_PID3 844
19.1.11 ROMTABLE_CID0 845
19.1.12 ROMTABLE_CID1 846
19.1.13 ROMTABLE_CID2 847
19.1.14 ROMTABLE_CID3 848

20. SAR Registers **849**

20.1 Register Details 849
20.1.1 SAR_CTRL 852
20.1.2 SAR_SAMPLE_CTRL 855
20.1.3 SAR_SAMPLE_TIME01 858
20.1.4 SAR_SAMPLE_TIME23 859
20.1.5 SAR_RANGE_THRES 860
20.1.6 SAR_RANGE_COND 861
20.1.7 SAR_CHAN_EN 862
20.1.8 SAR_START_CTRL 863
20.1.9 SAR_CHAN_CONFIG0 864
20.1.10 SAR_CHAN_CONFIG1 867
20.1.11 SAR_CHAN_CONFIG2 870
20.1.12 SAR_CHAN_CONFIG3 873
20.1.13 SAR_CHAN_CONFIG4 876
20.1.14 SAR_CHAN_CONFIG5 879
20.1.15 SAR_CHAN_CONFIG6 882
20.1.16 SAR_CHAN_CONFIG7 885
20.1.17 SAR_CHAN_CONFIG8 888
20.1.18 SAR_CHAN_CONFIG9 891
20.1.19 SAR_CHAN_CONFIG10 894
20.1.20 SAR_CHAN_CONFIG11 897
20.1.21 SAR_CHAN_CONFIG12 900
20.1.22 SAR_CHAN_CONFIG13 903
20.1.23 SAR_CHAN_CONFIG14 906
20.1.24 SAR_CHAN_CONFIG15 909
20.1.25 SAR_CHAN_WORK0 912
20.1.26 SAR_CHAN_WORK1 913
20.1.27 SAR_CHAN_WORK2 914
20.1.28 SAR_CHAN_WORK3 915
20.1.29 SAR_CHAN_WORK4 916
20.1.30 SAR_CHAN_WORK5 917
20.1.31 SAR_CHAN_WORK6 918
20.1.32 SAR_CHAN_WORK7 919
20.1.33 SAR_CHAN_WORK8 920
20.1.34 SAR_CHAN_WORK9 921
20.1.35 SAR_CHAN_WORK10 922
20.1.36 SAR_CHAN_WORK11 923
20.1.37 SAR_CHAN_WORK12 924
20.1.38 SAR_CHAN_WORK13 925
20.1.39 SAR_CHAN_WORK14 926
20.1.40 SAR_CHAN_WORK15 927
20.1.41 SAR_CHAN_RESULT0 928
20.1.42 SAR_CHAN_RESULT1 929
20.1.43 SAR_CHAN_RESULT2 930
20.1.44 SAR_CHAN_RESULT3 931
20.1.45 SAR_CHAN_RESULT4 932
20.1.46 SAR_CHAN_RESULT5 933

20.1.47 SAR_CHAN_RESULT6 934
20.1.48 SAR_CHAN_RESULT7 935
20.1.49 SAR_CHAN_RESULT8 936
20.1.50 SAR_CHAN_RESULT9 937
20.1.51 SAR_CHAN_RESULT10 938
20.1.52 SAR_CHAN_RESULT11 939
20.1.53 SAR_CHAN_RESULT12 940
20.1.54 SAR_CHAN_RESULT13 941
20.1.55 SAR_CHAN_RESULT14 942
20.1.56 SAR_CHAN_RESULT15 943
20.1.57 SAR_CHAN_WORK_UPDATED 944
20.1.58 SAR_CHAN_RESULT_UPDATED 945
20.1.59 SAR_CHAN_WORK_NEWVALUE 946
20.1.60 SAR_CHAN_RESULT_NEWVALUE 947
20.1.61 SAR_INTR 948
20.1.62 SAR_INTR_SET 950
20.1.63 SAR_INTR_MASK 952
20.1.64 SAR_INTR_MASKED 954
20.1.65 SAR_SATURATE_INTR 956
20.1.66 SAR_SATURATE_INTR_SET 957
20.1.67 SAR_SATURATE_INTR_MASK 958
20.1.68 SAR_SATURATE_INTR_MASKED 959
20.1.69 SAR_RANGE_INTR 960
20.1.70 SAR_RANGE_INTR_SET 961
20.1.71 SAR_RANGE_INTR_MASK 962
20.1.72 SAR_RANGE_INTR_MASKED 963
20.1.73 SAR_INTR_CAUSE 964
20.1.74 SAR_INJ_CHAN_CONFIG 966
20.1.75 SAR_INJ_RESULT 968
20.1.76 SAR_STATUS 969
20.1.77 SAR_AVG_STAT 970
20.1.78 SAR_MUX_SWITCH0 971
20.1.79 SAR_MUX_SWITCH_CLEAR0 974
20.1.80 SAR_MUX_SWITCH_HW_CTRL 977
20.1.81 SAR_MUX_SWITCH_STATUS 979
20.1.82 SAR_PUMP_CTRL 981
20.1.83 SAR_ANA_TRIM 982

21. Serial Communication Block (SCB) Registers 983

21.1 Register Details 983
21.1.1 SCB0_CTRL 989
21.1.2 SCB0_STATUS 992
21.1.3 SCB0_SPI_CTRL 993
21.1.4 SCB0_SPI_STATUS 996
21.1.5 SCB0_UART_CTRL 998
21.1.6 SCB0_UART_TX_CTRL 999
21.1.7 SCB0_UART_RX_CTRL 1000
21.1.8 SCB0_UART_RX_STATUS 1003
21.1.9 SCB0_UART_FLOW_CTRL 1004
21.1.10 SCB0_I2C_CTRL 1006
21.1.11 SCB0_I2C_STATUS 1009
21.1.12 SCB0_I2C_M_CMD 1011
21.1.13 SCB0_I2C_S_CMD 1013
21.1.14 SCB0_I2C_CFG 1014

21.1.15 SCB0_TX_CTRL 1016
21.1.16 SCB0_TX_FIFO_CTRL 1017
21.1.17 SCB0_TX_FIFO_STATUS 1018
21.1.18 SCB0_TX_FIFO_WR 1019
21.1.19 SCB0_RX_CTRL 1020
21.1.20 SCB0_RX_FIFO_CTRL 1021
21.1.21 SCB0_RX_FIFO_STATUS 1022
21.1.22 SCB0_RX_MATCH 1023
21.1.23 SCB0_RX_FIFO_RD 1024
21.1.24 SCB0_RX_FIFO_RD_SILENT 1025
21.1.25 SCB0_EZ_DATA0 1026
21.1.26 SCB0_EZ_DATA1 1027
21.1.27 SCB0_EZ_DATA2 1028
21.1.28 SCB0_EZ_DATA3 1029
21.1.29 SCB0_EZ_DATA4 1030
21.1.30 SCB0_EZ_DATA5 1031
21.1.31 SCB0_EZ_DATA6 1032
21.1.32 SCB0_EZ_DATA7 1033
21.1.33 SCB0_EZ_DATA8 1034
21.1.34 SCB0_EZ_DATA9 1035
21.1.35 SCB0_EZ_DATA10 1036
21.1.36 SCB0_EZ_DATA11 1037
21.1.37 SCB0_EZ_DATA12 1038
21.1.38 SCB0_EZ_DATA13 1039
21.1.39 SCB0_EZ_DATA14 1040
21.1.40 SCB0_EZ_DATA15 1041
21.1.41 SCB0_EZ_DATA16 1042
21.1.42 SCB0_EZ_DATA17 1043
21.1.43 SCB0_EZ_DATA18 1044
21.1.44 SCB0_EZ_DATA19 1045
21.1.45 SCB0_EZ_DATA20 1046
21.1.46 SCB0_EZ_DATA21 1047
21.1.47 SCB0_EZ_DATA22 1048
21.1.48 SCB0_EZ_DATA23 1049
21.1.49 SCB0_EZ_DATA24 1050
21.1.50 SCB0_EZ_DATA25 1051
21.1.51 SCB0_EZ_DATA26 1052
21.1.52 SCB0_EZ_DATA27 1053
21.1.53 SCB0_EZ_DATA28 1054
21.1.54 SCB0_EZ_DATA29 1055
21.1.55 SCB0_EZ_DATA30 1056
21.1.56 SCB0_EZ_DATA31 1057
21.1.57 SCB0_INTR_CAUSE 1058
21.1.58 SCB0_INTR_I2C_EC 1059
21.1.59 SCB0_INTR_I2C_EC_MASK 1061
21.1.60 SCB0_INTR_I2C_EC_MASKED 1062
21.1.61 SCB0_INTR_SPI_EC 1063
21.1.62 SCB0_INTR_SPI_EC_MASK 1065
21.1.63 SCB0_INTR_SPI_EC_MASKED 1066
21.1.64 SCB0_INTR_M 1067
21.1.65 SCB0_INTR_M_SET 1069
21.1.66 SCB0_INTR_M_MASK 1070
21.1.67 SCB0_INTR_M_MASKED 1071
21.1.68 SCB0_INTR_S 1072

21.1.69 SCB0_INTR_S_SET 1074
21.1.70 SCB0_INTR_S_MASK 1076
21.1.71 SCB0_INTR_S_MASKED 1078
21.1.72 SCB0_INTR_TX 1080
21.1.73 SCB0_INTR_TX_SET 1082
21.1.74 SCB0_INTR_TX_MASK 1084
21.1.75 SCB0_INTR_TX_MASKED 1086
21.1.76 SCB0_INTR_RX 1088
21.1.77 SCB0_INTR_RX_SET 1090
21.1.78 SCB0_INTR_RX_MASK 1092
21.1.79 SCB0_INTR_RX_MASKED 1094
21.1.80 SCB1_CTRL 1096
21.1.81 SCB1_STATUS 1100
21.1.82 SCB1_SPI_CTRL 1101
21.1.83 SCB1_SPI_STATUS 1104
21.1.84 SCB1_UART_CTRL 1105
21.1.85 SCB1_UART_TX_CTRL 1106
21.1.86 SCB1_UART_RX_CTRL 1107
21.1.87 SCB1_UART_RX_STATUS 1110
21.1.88 SCB1_UART_FLOW_CTRL 1111
21.1.89 SCB1_I2C_CTRL 1113
21.1.90 SCB1_I2C_STATUS 1116
21.1.91 SCB1_I2C_M_CMD 1118
21.1.92 SCB1_I2C_S_CMD 1120
21.1.93 SCB1_I2C_CFG 1121
21.1.94 SCB1_TX_CTRL 1123
21.1.95 SCB1_TX_FIFO_CTRL 1124
21.1.96 SCB1_TX_FIFO_STATUS 1125
21.1.97 SCB1_TX_FIFO_WR 1126
21.1.98 SCB1_RX_CTRL 1127
21.1.99 SCB1_RX_FIFO_CTRL 1128
21.1.100 SCB1_RX_FIFO_STATUS 1129
21.1.101 SCB1_RX_MATCH 1130
21.1.102 SCB1_RX_FIFO_RD 1131
21.1.103 SCB1_RX_FIFO_RD_SILENT 1132
21.1.104 SCB1_EZ_DATA0 1133
21.1.105 SCB1_EZ_DATA1 1134
21.1.106 SCB1_EZ_DATA2 1135
21.1.107 SCB1_EZ_DATA3 1136
21.1.108 SCB1_EZ_DATA4 1137
21.1.109 SCB1_EZ_DATA5 1138
21.1.110 SCB1_EZ_DATA6 1139
21.1.111 SCB1_EZ_DATA7 1140
21.1.112 SCB1_EZ_DATA8 1141
21.1.113 SCB1_EZ_DATA9 1142
21.1.114 SCB1_EZ_DATA10 1143
21.1.115 SCB1_EZ_DATA11 1144
21.1.116 SCB1_EZ_DATA12 1145
21.1.117 SCB1_EZ_DATA13 1146
21.1.118 SCB1_EZ_DATA14 1147
21.1.119 SCB1_EZ_DATA15 1148
21.1.120 SCB1_EZ_DATA16 1149
21.1.121 SCB1_EZ_DATA17 1150
21.1.122 SCB1_EZ_DATA18 1151

21.1.123 SCB1_EZ_DATA19 1152
21.1.124 SCB1_EZ_DATA20 1153
21.1.125 SCB1_EZ_DATA21 1154
21.1.126 SCB1_EZ_DATA22 1155
21.1.127 SCB1_EZ_DATA23 1156
21.1.128 SCB1_EZ_DATA24 1157
21.1.129 SCB1_EZ_DATA25 1158
21.1.130 SCB1_EZ_DATA26 1159
21.1.131 SCB1_EZ_DATA27 1160
21.1.132 SCB1_EZ_DATA28 1161
21.1.133 SCB1_EZ_DATA29 1162
21.1.134 SCB1_EZ_DATA30 1163
21.1.135 SCB1_EZ_DATA31 1164
21.1.136 SCB1_INTR_CAUSE 1165
21.1.137 SCB1_INTR_I2C_EC 1166
21.1.138 SCB1_INTR_I2C_EC_MASK 1168
21.1.139 SCB1_INTR_I2C_EC_MASKED 1169
21.1.140 SCB1_INTR_SPI_EC 1170
21.1.141 SCB1_INTR_SPI_EC_MASK 1172
21.1.142 SCB1_INTR_SPI_EC_MASKED 1173
21.1.143 SCB1_INTR_M 1174
21.1.144 SCB1_INTR_M_SET 1176
21.1.145 SCB1_INTR_M_MASK 1177
21.1.146 SCB1_INTR_M_MASKED 1178
21.1.147 SCB1_INTR_S 1179
21.1.148 SCB1_INTR_S_SET 1181
21.1.149 SCB1_INTR_S_MASK 1183
21.1.150 SCB1_INTR_S_MASKED 1185
21.1.151 SCB1_INTR_TX 1187
21.1.152 SCB1_INTR_TX_SET 1189
21.1.153 SCB1_INTR_TX_MASK 1191
21.1.154 SCB1_INTR_TX_MASKED 1193
21.1.155 SCB1_INTR_RX 1195
21.1.156 SCB1_INTR_RX_SET 1197
21.1.157 SCB1_INTR_RX_MASK 1199
21.1.158 SCB1_INTR_RX_MASKED 1201
21.1.159 SCB2_CTRL 1203
21.1.160 SCB2_STATUS 1206
21.1.161 SCB2_SPI_CTRL 1207
21.1.162 SCB2_SPI_STATUS 1210
21.1.163 SCB2_UART_CTRL 1212
21.1.164 SCB2_UART_TX_CTRL 1213
21.1.165 SCB2_UART_RX_CTRL 1214
21.1.166 SCB2_UART_RX_STATUS 1217
21.1.167 SCB2_UART_FLOW_CTRL 1218
21.1.168 SCB2_I2C_CTRL 1220
21.1.169 SCB2_I2C_STATUS 1223
21.1.170 SCB2_I2C_M_CMD 1225
21.1.171 SCB2_I2C_S_CMD 1227
21.1.172 SCB2_I2C_CFG 1228
21.1.173 SCB2_TX_CTRL 1230
21.1.174 SCB2_TX_FIFO_CTRL 1231
21.1.175 SCB2_TX_FIFO_STATUS 1232
21.1.176 SCB2_TX_FIFO_WR 1233

21.1.177 SCB2_RX_CTRL 1234
21.1.178 SCB2_RX_FIFO_CTRL 1235
21.1.179 SCB2_RX_FIFO_STATUS 1236
21.1.180 SCB2_RX_MATCH 1237
21.1.181 SCB2_RX_FIFO_RD 1238
21.1.182 SCB2_RX_FIFO_RD_SILENT 1239
21.1.183 SCB2_EZ_DATA0 1240
21.1.184 SCB2_EZ_DATA1 1241
21.1.185 SCB2_EZ_DATA2 1242
21.1.186 SCB2_EZ_DATA3 1243
21.1.187 SCB2_EZ_DATA4 1244
21.1.188 SCB2_EZ_DATA5 1245
21.1.189 SCB2_EZ_DATA6 1246
21.1.190 SCB2_EZ_DATA7 1247
21.1.191 SCB2_EZ_DATA8 1248
21.1.192 SCB2_EZ_DATA9 1249
21.1.193 SCB2_EZ_DATA10 1250
21.1.194 SCB2_EZ_DATA11 1251
21.1.195 SCB2_EZ_DATA12 1252
21.1.196 SCB2_EZ_DATA13 1253
21.1.197 SCB2_EZ_DATA14 1254
21.1.198 SCB2_EZ_DATA15 1255
21.1.199 SCB2_EZ_DATA16 1256
21.1.200 SCB2_EZ_DATA17 1257
21.1.201 SCB2_EZ_DATA18 1258
21.1.202 SCB2_EZ_DATA19 1259
21.1.203 SCB2_EZ_DATA20 1260
21.1.204 SCB2_EZ_DATA21 1261
21.1.205 SCB2_EZ_DATA22 1262
21.1.206 SCB2_EZ_DATA23 1263
21.1.207 SCB2_EZ_DATA24 1264
21.1.208 SCB2_EZ_DATA25 1265
21.1.209 SCB2_EZ_DATA26 1266
21.1.210 SCB2_EZ_DATA27 1267
21.1.211 SCB2_EZ_DATA28 1268
21.1.212 SCB2_EZ_DATA29 1269
21.1.213 SCB2_EZ_DATA30 1270
21.1.214 SCB2_EZ_DATA31 1271
21.1.215 SCB2_INTR_CAUSE 1272
21.1.216 SCB2_INTR_I2C_EC 1273
21.1.217 SCB2_INTR_I2C_EC_MASK 1275
21.1.218 SCB2_INTR_I2C_EC_MASKED 1276
21.1.219 SCB2_INTR_SPI_EC 1277
21.1.220 SCB2_INTR_SPI_EC_MASK 1279
21.1.221 SCB2_INTR_SPI_EC_MASKED 1280
21.1.222 SCB2_INTR_M 1281
21.1.223 SCB2_INTR_M_SET 1283
21.1.224 SCB2_INTR_M_MASK 1284
21.1.225 SCB2_INTR_M_MASKED 1285
21.1.226 SCB2_INTR_S 1286
21.1.227 SCB2_INTR_S_SET 1288
21.1.228 SCB2_INTR_S_MASK 1290
21.1.229 SCB2_INTR_S_MASKED 1292
21.1.230 SCB2_INTR_TX 1294

21.1.231 SCB2_INTR_TX_SET 1296
21.1.232 SCB2_INTR_TX_MASK 1298
21.1.233 SCB2_INTR_TX_MASKED 1300
21.1.234 SCB2_INTR_RX 1302
21.1.235 SCB2_INTR_RX_SET 1304
21.1.236 SCB2_INTR_RX_MASK 1306
21.1.237 SCB2_INTR_RX_MASKED 1308

22. Supervisory Flash (SFLASH) Registers 1310

22.1 Register Details 1310
22.1.1 SFLASH_PROT_ROW0 1319
22.1.2 SFLASH_PROT_ROW1 1320
22.1.3 SFLASH_PROT_ROW2 1321
22.1.4 SFLASH_PROT_ROW3 1322
22.1.5 SFLASH_PROT_ROW4 1323
22.1.6 SFLASH_PROT_ROW5 1324
22.1.7 SFLASH_PROT_ROW6 1325
22.1.8 SFLASH_PROT_ROW7 1326
22.1.9 SFLASH_PROT_ROW8 1327
22.1.10 SFLASH_PROT_ROW9 1328
22.1.11 SFLASH_PROT_ROW10 1329
22.1.12 SFLASH_PROT_ROW11 1330
22.1.13 SFLASH_PROT_ROW12 1331
22.1.14 SFLASH_PROT_ROW13 1332
22.1.15 SFLASH_PROT_ROW14 1333
22.1.16 SFLASH_PROT_ROW15 1334
22.1.17 SFLASH_PROT_ROW16 1335
22.1.18 SFLASH_PROT_ROW17 1336
22.1.19 SFLASH_PROT_ROW18 1337
22.1.20 SFLASH_PROT_ROW19 1338
22.1.21 SFLASH_PROT_ROW20 1339
22.1.22 SFLASH_PROT_ROW21 1340
22.1.23 SFLASH_PROT_ROW22 1341
22.1.24 SFLASH_PROT_ROW23 1342
22.1.25 SFLASH_PROT_ROW24 1343
22.1.26 SFLASH_PROT_ROW25 1344
22.1.27 SFLASH_PROT_ROW26 1345
22.1.28 SFLASH_PROT_ROW27 1346
22.1.29 SFLASH_PROT_ROW28 1347
22.1.30 SFLASH_PROT_ROW29 1348
22.1.31 SFLASH_PROT_ROW30 1349
22.1.32 SFLASH_PROT_ROW31 1350
22.1.33 SFLASH_PROT_ROW32 1351
22.1.34 SFLASH_PROT_ROW33 1352
22.1.35 SFLASH_PROT_ROW34 1353
22.1.36 SFLASH_PROT_ROW35 1354
22.1.37 SFLASH_PROT_ROW36 1355
22.1.38 SFLASH_PROT_ROW37 1356
22.1.39 SFLASH_PROT_ROW38 1357
22.1.40 SFLASH_PROT_ROW39 1358
22.1.41 SFLASH_PROT_ROW40 1359
22.1.42 SFLASH_PROT_ROW41 1360
22.1.43 SFLASH_PROT_ROW42 1361
22.1.44 SFLASH_PROT_ROW43 1362

22.1.45 SFLASH_PROT_ROW44 1363
22.1.46 SFLASH_PROT_ROW45 1364
22.1.47 SFLASH_PROT_ROW46 1365
22.1.48 SFLASH_PROT_ROW47 1366
22.1.49 SFLASH_PROT_ROW48 1367
22.1.50 SFLASH_PROT_ROW49 1368
22.1.51 SFLASH_PROT_ROW50 1369
22.1.52 SFLASH_PROT_ROW51 1370
22.1.53 SFLASH_PROT_ROW52 1371
22.1.54 SFLASH_PROT_ROW53 1372
22.1.55 SFLASH_PROT_ROW54 1373
22.1.56 SFLASH_PROT_ROW55 1374
22.1.57 SFLASH_PROT_ROW56 1375
22.1.58 SFLASH_PROT_ROW57 1376
22.1.59 SFLASH_PROT_ROW58 1377
22.1.60 SFLASH_PROT_ROW59 1378
22.1.61 SFLASH_PROT_ROW60 1379
22.1.62 SFLASH_PROT_ROW61 1380
22.1.63 SFLASH_PROT_ROW62 1381
22.1.64 SFLASH_PROT_ROW63 1382
22.1.65 SFLASH_PROT_PROTECTION 1383
22.1.66 SFLASH_AV_PAIRS_8B0 1384
22.1.67 SFLASH_AV_PAIRS_8B1 1385
22.1.68 SFLASH_AV_PAIRS_8B2 1386
22.1.69 SFLASH_AV_PAIRS_8B3 1387
22.1.70 SFLASH_AV_PAIRS_8B4 1388
22.1.71 SFLASH_AV_PAIRS_8B5 1389
22.1.72 SFLASH_AV_PAIRS_8B6 1390
22.1.73 SFLASH_AV_PAIRS_8B7 1391
22.1.74 SFLASH_AV_PAIRS_8B8 1392
22.1.75 SFLASH_AV_PAIRS_8B9 1393
22.1.76 SFLASH_AV_PAIRS_8B10 1394
22.1.77 SFLASH_AV_PAIRS_8B11 1395
22.1.78 SFLASH_AV_PAIRS_8B12 1396
22.1.79 SFLASH_AV_PAIRS_8B13 1397
22.1.80 SFLASH_AV_PAIRS_8B14 1398
22.1.81 SFLASH_AV_PAIRS_8B15 1399
22.1.82 SFLASH_AV_PAIRS_8B16 1400
22.1.83 SFLASH_AV_PAIRS_8B17 1401
22.1.84 SFLASH_AV_PAIRS_8B18 1402
22.1.85 SFLASH_AV_PAIRS_8B19 1403
22.1.86 SFLASH_AV_PAIRS_8B20 1404
22.1.87 SFLASH_AV_PAIRS_8B21 1405
22.1.88 SFLASH_AV_PAIRS_8B22 1406
22.1.89 SFLASH_AV_PAIRS_8B23 1407
22.1.90 SFLASH_AV_PAIRS_8B24 1408
22.1.91 SFLASH_AV_PAIRS_8B25 1409
22.1.92 SFLASH_AV_PAIRS_8B26 1410
22.1.93 SFLASH_AV_PAIRS_8B27 1411
22.1.94 SFLASH_AV_PAIRS_8B28 1412
22.1.95 SFLASH_AV_PAIRS_8B29 1413
22.1.96 SFLASH_AV_PAIRS_8B30 1414
22.1.97 SFLASH_AV_PAIRS_8B31 1415
22.1.98 SFLASH_AV_PAIRS_8B32 1416

22.1.99 SFLASH_AV_PAIRS_8B33 1417
22.1.100 SFLASH_AV_PAIRS_8B34 1418
22.1.101 SFLASH_AV_PAIRS_8B35 1419
22.1.102 SFLASH_AV_PAIRS_8B36 1420
22.1.103 SFLASH_AV_PAIRS_8B37 1421
22.1.104 SFLASH_AV_PAIRS_8B38 1422
22.1.105 SFLASH_AV_PAIRS_8B39 1423
22.1.106 SFLASH_AV_PAIRS_8B40 1424
22.1.107 SFLASH_AV_PAIRS_8B41 1425
22.1.108 SFLASH_AV_PAIRS_8B42 1426
22.1.109 SFLASH_AV_PAIRS_8B43 1427
22.1.110 SFLASH_AV_PAIRS_8B44 1428
22.1.111 SFLASH_AV_PAIRS_8B45 1429
22.1.112 SFLASH_AV_PAIRS_8B46 1430
22.1.113 SFLASH_AV_PAIRS_8B47 1431
22.1.114 SFLASH_AV_PAIRS_8B48 1432
22.1.115 SFLASH_AV_PAIRS_8B49 1433
22.1.116 SFLASH_AV_PAIRS_8B50 1434
22.1.117 SFLASH_AV_PAIRS_8B51 1435
22.1.118 SFLASH_AV_PAIRS_8B52 1436
22.1.119 SFLASH_AV_PAIRS_8B53 1437
22.1.120 SFLASH_AV_PAIRS_8B54 1438
22.1.121 SFLASH_AV_PAIRS_8B55 1439
22.1.122 SFLASH_AV_PAIRS_8B56 1440
22.1.123 SFLASH_AV_PAIRS_8B57 1441
22.1.124 SFLASH_AV_PAIRS_8B58 1442
22.1.125 SFLASH_AV_PAIRS_8B59 1443
22.1.126 SFLASH_AV_PAIRS_8B60 1444
22.1.127 SFLASH_AV_PAIRS_8B61 1445
22.1.128 SFLASH_AV_PAIRS_8B62 1446
22.1.129 SFLASH_AV_PAIRS_8B63 1447
22.1.130 SFLASH_AV_PAIRS_8B64 1448
22.1.131 SFLASH_AV_PAIRS_8B65 1449
22.1.132 SFLASH_AV_PAIRS_8B66 1450
22.1.133 SFLASH_AV_PAIRS_8B67 1451
22.1.134 SFLASH_AV_PAIRS_8B68 1452
22.1.135 SFLASH_AV_PAIRS_8B69 1453
22.1.136 SFLASH_AV_PAIRS_8B70 1454
22.1.137 SFLASH_AV_PAIRS_8B71 1455
22.1.138 SFLASH_AV_PAIRS_8B72 1456
22.1.139 SFLASH_AV_PAIRS_8B73 1457
22.1.140 SFLASH_AV_PAIRS_8B74 1458
22.1.141 SFLASH_AV_PAIRS_8B75 1459
22.1.142 SFLASH_AV_PAIRS_8B76 1460
22.1.143 SFLASH_AV_PAIRS_8B77 1461
22.1.144 SFLASH_AV_PAIRS_8B78 1462
22.1.145 SFLASH_AV_PAIRS_8B79 1463
22.1.146 SFLASH_AV_PAIRS_8B80 1464
22.1.147 SFLASH_AV_PAIRS_8B81 1465
22.1.148 SFLASH_AV_PAIRS_8B82 1466
22.1.149 SFLASH_AV_PAIRS_8B83 1467
22.1.150 SFLASH_AV_PAIRS_8B84 1468
22.1.151 SFLASH_CSDV2_CSD1_ADC_TRIM1 1469
22.1.152 SFLASH_AV_PAIRS_8B85 1470

22.1.153 SFLASH_CSDV2_CSD1_ADC_TRIM2 1471
22.1.154 SFLASH_AV_PAIRS_8B86 1472
22.1.155 SFLASH_AV_PAIRS_8B87 1473
22.1.156 SFLASH_AV_PAIRS_8B88 1474
22.1.157 SFLASH_AV_PAIRS_8B89 1475
22.1.158 SFLASH_AV_PAIRS_8B90 1476
22.1.159 SFLASH_AV_PAIRS_8B91 1477
22.1.160 SFLASH_AV_PAIRS_8B92 1478
22.1.161 SFLASH_AV_PAIRS_8B93 1479
22.1.162 SFLASH_AV_PAIRS_8B94 1480
22.1.163 SFLASH_AV_PAIRS_8B95 1481
22.1.164 SFLASH_AV_PAIRS_8B96 1482
22.1.165 SFLASH_AV_PAIRS_8B97 1483
22.1.166 SFLASH_AV_PAIRS_8B98 1484
22.1.167 SFLASH_AV_PAIRS_8B99 1485
22.1.168 SFLASH_AV_PAIRS_8B100 1486
22.1.169 SFLASH_AV_PAIRS_8B101 1487
22.1.170 SFLASH_AV_PAIRS_8B102 1488
22.1.171 SFLASH_AV_PAIRS_8B103 1489
22.1.172 SFLASH_AV_PAIRS_8B104 1490
22.1.173 SFLASH_AV_PAIRS_8B105 1491
22.1.174 SFLASH_AV_PAIRS_8B106 1492
22.1.175 SFLASH_AV_PAIRS_8B107 1493
22.1.176 SFLASH_AV_PAIRS_8B108 1494
22.1.177 SFLASH_AV_PAIRS_8B109 1495
22.1.178 SFLASH_AV_PAIRS_8B110 1496
22.1.179 SFLASH_AV_PAIRS_8B111 1497
22.1.180 SFLASH_AV_PAIRS_8B112 1498
22.1.181 SFLASH_AV_PAIRS_8B113 1499
22.1.182 SFLASH_AV_PAIRS_8B114 1500
22.1.183 SFLASH_AV_PAIRS_8B115 1501
22.1.184 SFLASH_AV_PAIRS_8B116 1502
22.1.185 SFLASH_AV_PAIRS_8B117 1503
22.1.186 SFLASH_AV_PAIRS_8B118 1504
22.1.187 SFLASH_AV_PAIRS_8B119 1505
22.1.188 SFLASH_AV_PAIRS_8B120 1506
22.1.189 SFLASH_AV_PAIRS_8B121 1507
22.1.190 SFLASH_AV_PAIRS_8B122 1508
22.1.191 SFLASH_AV_PAIRS_8B123 1509
22.1.192 SFLASH_AV_PAIRS_8B124 1510
22.1.193 SFLASH_AV_PAIRS_8B125 1511
22.1.194 SFLASH_AV_PAIRS_8B126 1512
22.1.195 SFLASH_AV_PAIRS_8B127 1513
22.1.196 SFLASH_AV_PAIRS_32B0 1514
22.1.197 SFLASH_AV_PAIRS_32B1 1515
22.1.198 SFLASH_AV_PAIRS_32B2 1516
22.1.199 SFLASH_AV_PAIRS_32B3 1517
22.1.200 SFLASH_AV_PAIRS_32B4 1518
22.1.201 SFLASH_AV_PAIRS_32B5 1519
22.1.202 SFLASH_AV_PAIRS_32B6 1520
22.1.203 SFLASH_AV_PAIRS_32B7 1521
22.1.204 SFLASH_AV_PAIRS_32B8 1522
22.1.205 SFLASH_AV_PAIRS_32B9 1523
22.1.206 SFLASH_AV_PAIRS_32B10 1524

22.1.207 SFLASH_AV_PAIRS_32B11 1525
22.1.208 SFLASH_AV_PAIRS_32B12 1526
22.1.209 SFLASH_AV_PAIRS_32B13 1527
22.1.210 SFLASH_AV_PAIRS_32B14 1528
22.1.211 SFLASH_AV_PAIRS_32B15 1529
22.1.212 SFLASH_CPUSS_WOUNDING 1530
22.1.213 SFLASH_SILICON_ID 1531
22.1.214 SFLASH_CPUSS_PRIV_RAM 1532
22.1.215 SFLASH_CPUSS_PRIV_ROM_BROM 1533
22.1.216 SFLASH_CPUSS_PRIV_FLASH 1534
22.1.217 SFLASH_CPUSS_PRIV_ROM_SROM 1535
22.1.218 SFLASH_HIB_KEY_DELAY 1536
22.1.219 SFLASH_DPSLP_KEY_DELAY 1537
22.1.220 SFLASH_SWD_CONFIG 1538
22.1.221 SFLASH_SWD_LISTEN 1539
22.1.222 SFLASH_FLASH_START 1540
22.1.223 SFLASH_CSDV2_CSD0_ADC_TRIM1 1541
22.1.224 SFLASH_CSDV2_CSD0_ADC_TRIM2 1542
22.1.225 SFLASH_SAR_TEMP_MULTIPLIER 1543
22.1.226 SFLASH_SAR_TEMP_OFFSET 1544
22.1.227 SFLASH_SKIP_CHECKSUM 1545
22.1.228 SFLASH_INITIAL_PWR_BG_TRIM1 1546
22.1.229 SFLASH_INITIAL_PWR_BG_TRIM1_INV 1547
22.1.230 SFLASH_INITIAL_PWR_BG_TRIM2 1548
22.1.231 SFLASH_INITIAL_PWR_BG_TRIM2_INV 1549
22.1.232 SFLASH_INITIAL_SPCIF_TRIM_M0_DAC0 1550
22.1.233 SFLASH_INITIAL_SPCIF_TRIM_M0_DAC0_INV 1551
22.1.234 SFLASH_PROT_VIRGINKEY0 1552
22.1.235 SFLASH_PROT_VIRGINKEY1 1553
22.1.236 SFLASH_PROT_VIRGINKEY2 1554
22.1.237 SFLASH_PROT_VIRGINKEY3 1555
22.1.238 SFLASH_PROT_VIRGINKEY4 1556
22.1.239 SFLASH_PROT_VIRGINKEY5 1557
22.1.240 SFLASH_PROT_VIRGINKEY6 1558
22.1.241 SFLASH_PROT_VIRGINKEY7 1559
22.1.242 SFLASH_DIE_LOT0 1560
22.1.243 SFLASH_DIE_LOT1 1561
22.1.244 SFLASH_DIE_LOT2 1562
22.1.245 SFLASH_DIE_WAFER 1563
22.1.246 SFLASH_DIE_X 1564
22.1.247 SFLASH_DIE_Y 1565
22.1.248 SFLASH_DIE_SORT 1566
22.1.249 SFLASH_DIE_MINOR 1567
22.1.250 SFLASH_PE_TE_DATA0 1568
22.1.251 SFLASH_PE_TE_DATA1 1569
22.1.252 SFLASH_PE_TE_DATA2 1570
22.1.253 SFLASH_PE_TE_DATA3 1571
22.1.254 SFLASH_PE_TE_DATA4 1572
22.1.255 SFLASH_PE_TE_DATA5 1573
22.1.256 SFLASH_PE_TE_DATA6 1574
22.1.257 SFLASH_PE_TE_DATA7 1575
22.1.258 SFLASH_PE_TE_DATA8 1576
22.1.259 SFLASH_PE_TE_DATA9 1577
22.1.260 SFLASH_PE_TE_DATA10 1578

22.1.261 SFLASH_PE_TE_DATA11 1579
22.1.262 SFLASH_PE_TE_DATA12 1580
22.1.263 SFLASH_PE_TE_DATA13 1581
22.1.264 SFLASH_PE_TE_DATA14 1582
22.1.265 SFLASH_PE_TE_DATA15 1583
22.1.266 SFLASH_PE_TE_DATA16 1584
22.1.267 SFLASH_PE_TE_DATA17 1585
22.1.268 SFLASH_PE_TE_DATA18 1586
22.1.269 SFLASH_PE_TE_DATA19 1587
22.1.270 SFLASH_PE_TE_DATA20 1588
22.1.271 SFLASH_PE_TE_DATA21 1589
22.1.272 SFLASH_PE_TE_DATA22 1590
22.1.273 SFLASH_PE_TE_DATA23 1591
22.1.274 SFLASH_PE_TE_DATA24 1592
22.1.275 SFLASH_PE_TE_DATA25 1593
22.1.276 SFLASH_PE_TE_DATA26 1594
22.1.277 SFLASH_PE_TE_DATA27 1595
22.1.278 SFLASH_PE_TE_DATA28 1596
22.1.279 SFLASH_PE_TE_DATA29 1597
22.1.280 SFLASH_PE_TE_DATA30 1598
22.1.281 SFLASH_PE_TE_DATA31 1599
22.1.282 SFLASH_PP 1600
22.1.283 SFLASH_E 1601
22.1.284 SFLASH_P 1602
22.1.285 SFLASH_EA_E 1603
22.1.286 SFLASH_EA_P 1604
22.1.287 SFLASH_ES_E 1605
22.1.288 SFLASH_ES_P_EO 1606
22.1.289 SFLASH_IMO_TRIM_USBMODE_24 1607
22.1.290 SFLASH_IMO_TRIM_USBMODE_48 1608
22.1.291 SFLASH_IMO_TCTRIM_LT0 1609
22.1.292 SFLASH_IMO_TCTRIM_LT1 1610
22.1.293 SFLASH_IMO_TCTRIM_LT2 1611
22.1.294 SFLASH_IMO_TCTRIM_LT3 1612
22.1.295 SFLASH_IMO_TCTRIM_LT4 1613
22.1.296 SFLASH_IMO_TCTRIM_LT5 1614
22.1.297 SFLASH_IMO_TCTRIM_LT6 1615
22.1.298 SFLASH_IMO_TCTRIM_LT7 1616
22.1.299 SFLASH_IMO_TCTRIM_LT8 1617
22.1.300 SFLASH_IMO_TCTRIM_LT9 1618
22.1.301 SFLASH_IMO_TCTRIM_LT10 1619
22.1.302 SFLASH_IMO_TCTRIM_LT11 1620
22.1.303 SFLASH_IMO_TCTRIM_LT12 1621
22.1.304 SFLASH_IMO_TCTRIM_LT13 1622
22.1.305 SFLASH_IMO_TCTRIM_LT14 1623
22.1.306 SFLASH_IMO_TCTRIM_LT15 1624
22.1.307 SFLASH_IMO_TCTRIM_LT16 1625
22.1.308 SFLASH_IMO_TCTRIM_LT17 1626
22.1.309 SFLASH_IMO_TCTRIM_LT18 1627
22.1.310 SFLASH_IMO_TCTRIM_LT19 1628
22.1.311 SFLASH_IMO_TCTRIM_LT20 1629
22.1.312 SFLASH_IMO_TCTRIM_LT21 1630
22.1.313 SFLASH_IMO_TCTRIM_LT22 1631
22.1.314 SFLASH_IMO_TCTRIM_LT23 1632

22.1.315 SFLASH_IMO_TCTRIM_LT24 1633
22.1.316 SFLASH_IMO_TRIM_LT0 1634
22.1.317 SFLASH_IMO_TRIM_LT1 1635
22.1.318 SFLASH_IMO_TRIM_LT2 1636
22.1.319 SFLASH_IMO_TRIM_LT3 1637
22.1.320 SFLASH_IMO_TRIM_LT4 1638
22.1.321 SFLASH_IMO_TRIM_LT5 1639
22.1.322 SFLASH_IMO_TRIM_LT6 1640
22.1.323 SFLASH_IMO_TRIM_LT7 1641
22.1.324 SFLASH_IMO_TRIM_LT8 1642
22.1.325 SFLASH_IMO_TRIM_LT9 1643
22.1.326 SFLASH_IMO_TRIM_LT10 1644
22.1.327 SFLASH_IMO_TRIM_LT11 1645
22.1.328 SFLASH_IMO_TRIM_LT12 1646
22.1.329 SFLASH_IMO_TRIM_LT13 1647
22.1.330 SFLASH_IMO_TRIM_LT14 1648
22.1.331 SFLASH_IMO_TRIM_LT15 1649
22.1.332 SFLASH_IMO_TRIM_LT16 1650
22.1.333 SFLASH_IMO_TRIM_LT17 1651
22.1.334 SFLASH_IMO_TRIM_LT18 1652
22.1.335 SFLASH_IMO_TRIM_LT19 1653
22.1.336 SFLASH_IMO_TRIM_LT20 1654
22.1.337 SFLASH_IMO_TRIM_LT21 1655
22.1.338 SFLASH_IMO_TRIM_LT22 1656
22.1.339 SFLASH_IMO_TRIM_LT23 1657
22.1.340 SFLASH_IMO_TRIM_LT24 1658
22.1.341 SFLASH_CHECKSUM 1659

23. SPC Interface (SPCIF) Registers 1660

23.1 Register Details 1660
23.1.1 SPCIF_GEOMETRY 1661
23.1.2 SPCIF_INTR 1662
23.1.3 SPCIF_INTR_SET 1663
23.1.4 SPCIF_INTR_MASK 1664
23.1.5 SPCIF_INTR_MASKED 1665

24. System Resources Sub System Registers 1666

24.1 Register Details 1666
24.1.1 PWR_CONTROL 1667
24.1.2 PWR_KEY_DELAY 1669
24.1.3 TST_MODE 1670
24.1.4 CLK_SELECT 1671
24.1.5 CLK_ILO_CONFIG 1673
24.1.6 CLK_IMO_CONFIG 1674
24.1.7 WDT_DISABLE_KEY 1675
24.1.8 WDT_COUNTER 1676
24.1.9 WDT_MATCH 1677
24.1.10 SRSS_INTR 1678
24.1.11 SRSS_INTR_SET 1679
24.1.12 SRSS_INTR_MASK 1680
24.1.13 RES_CAUSE 1681
24.1.14 CLK_IMO_SELECT 1682
24.1.15 CLK_IMO_TRIM1 1683
24.1.16 CLK_IMO_TRIM2 1684

24.1.17 CLK_IMO_TRIM3 1685

25. Timer, Counter, PWM (TCPWM) Registers 1686

25.1 Register Details 1686
25.1.1 TCPWM_CTRL 1687
25.1.2 TCPWM_CMD 1688
25.1.3 TCPWM_INTR_CAUSE 1689

26. PERI Trigger Group Control Registers 1690

26.1 Register Details 1690
26.1.1 PERI_TR_GROUP0_TR_OUT_CTL0 1692
26.1.2 PERI_TR_GROUP0_TR_OUT_CTL1 1693
26.1.3 PERI_TR_GROUP0_TR_OUT_CTL2 1694
26.1.4 PERI_TR_GROUP0_TR_OUT_CTL3 1695
26.1.5 PERI_TR_GROUP0_TR_OUT_CTL4 1696
26.1.6 PERI_TR_GROUP0_TR_OUT_CTL5 1697
26.1.7 PERI_TR_GROUP0_TR_OUT_CTL6 1698
26.1.8 PERI_TR_GROUP0_TR_OUT_CTL7 1699
26.1.9 PERI_TR_GROUP1_TR_OUT_CTL0 1700
26.1.10 PERI_TR_GROUP1_TR_OUT_CTL1 1701
26.1.11 PERI_TR_GROUP1_TR_OUT_CTL2 1702
26.1.12 PERI_TR_GROUP1_TR_OUT_CTL3 1703
26.1.13 PERI_TR_GROUP1_TR_OUT_CTL4 1704
26.1.14 PERI_TR_GROUP1_TR_OUT_CTL5 1705
26.1.15 PERI_TR_GROUP1_TR_OUT_CTL6 1706
26.1.16 PERI_TR_GROUP2_TR_OUT_CTL0 1707
26.1.17 PERI_TR_GROUP2_TR_OUT_CTL1 1708
26.1.18 PERI_TR_GROUP2_TR_OUT_CTL2 1709
26.1.19 PERI_TR_GROUP2_TR_OUT_CTL3 1710
26.1.20 PERI_TR_GROUP3_TR_OUT_CTL0 1711
26.1.21 PERI_TR_GROUP3_TR_OUT_CTL1 1712
26.1.22 PERI_TR_GROUP3_TR_OUT_CTL2 1713
26.1.23 PERI_TR_GROUP3_TR_OUT_CTL3 1714
26.1.24 PERI_TR_GROUP4_TR_OUT_CTL0 1715
26.1.25 PERI_TR_GROUP4_TR_OUT_CTL1 1716
26.1.26 PERI_TR_GROUP4_TR_OUT_CTL2 1717
26.1.27 PERI_TR_GROUP4_TR_OUT_CTL3 1718
26.1.28 PERI_TR_GROUP4_TR_OUT_CTL4 1719
26.1.29 PERI_TR_GROUP4_TR_OUT_CTL5 1720
26.1.30 PERI_TR_GROUP4_TR_OUT_CTL6 1721
26.1.31 PERI_TR_GROUP4_TR_OUT_CTL7 1722
26.1.32 PERI_TR_GROUP4_TR_OUT_CTL8 1723
26.1.33 PERI_TR_GROUP4_TR_OUT_CTL9 1724
26.1.34 PERI_TR_GROUP4_TR_OUT_CTL10 1725
26.1.35 PERI_TR_GROUP4_TR_OUT_CTL11 1726
26.1.36 PERI_TR_GROUP4_TR_OUT_CTL12 1727
26.1.37 PERI_TR_GROUP4_TR_OUT_CTL13 1728
26.1.38 PERI_TR_GROUP4_TR_OUT_CTL14 1729
26.1.39 PERI_TR_GROUP4_TR_OUT_CTL15 1730
26.1.40 PERI_TR_GROUP4_TR_OUT_CTL16 1731
26.1.41 PERI_TR_GROUP4_TR_OUT_CTL17 1732
26.1.42 PERI_TR_GROUP4_TR_OUT_CTL18 1733
26.1.43 PERI_TR_GROUP4_TR_OUT_CTL19 1734
26.1.44 PERI_TR_GROUP4_TR_OUT_CTL20 1735

26.1.45 PERI_TR_GROUP4_TR_OUT_CTL21 1736
26.1.46 PERI_TR_GROUP4_TR_OUT_CTL22 1737
26.1.47 PERI_TR_GROUP4_TR_OUT_CTL23 1738

27. UAB Registers **1739**

27.1 Register Details 1739
27.1.1 UAB_UAB_CTRL 1742
27.1.2 UAB_INTR 1743
27.1.3 UAB_INTR_SET 1745
27.1.4 UAB_INTR_MASK 1746
27.1.5 UAB_INTR_MASKED 1747
27.1.6 UAB_OA0_CTRL 1748
27.1.7 UAB_CAP_CTRL0 1750
27.1.8 UAB_CAP_ABCF0_VAL 1752
27.1.9 UAB_CAP_AB0_VAL_NXT 1753
27.1.10 UAB_CAP_CF0_VAL_NXT 1754
27.1.11 UAB_STARTUP_DELAY0 1755
27.1.12 UAB_SUBSAMPLE_CTRL0 1756
27.1.13 UAB_SW_STATIC0 1757
27.1.14 UAB_SW_MODBIT_SRC0 1759
27.1.15 UAB_SW_CA0_IN0 1760
27.1.16 UAB_SW_CA0_IN1 1761
27.1.17 UAB_SW_CA0_TOP 1762
27.1.18 UAB_SW_CB0_IN0 1763
27.1.19 UAB_SW_CB0_IN1 1764
27.1.20 UAB_SW_CB0_TOP 1765
27.1.21 UAB_SW_CC0_IN0 1766
27.1.22 UAB_SW_CC0_IN1 1767
27.1.23 UAB_SW_CC0_TOP 1768
27.1.24 UAB_SW_CF0_BOT 1769
27.1.25 UAB_SW_OTHER0 1770
27.1.26 UAB_SW_BOOST_CTRL0 1771
27.1.27 UAB_SRAM0_CTRL 1772
27.1.28 UAB_STAT0 1773
27.1.29 UAB_SRAM00 1774
27.1.30 UAB_SRAM01 1775
27.1.31 UAB_SRAM02 1776
27.1.32 UAB_SRAM03 1777
27.1.33 UAB_SRAM04 1778
27.1.34 UAB_SRAM05 1779
27.1.35 UAB_SRAM06 1780
27.1.36 UAB_SRAM07 1781
27.1.37 UAB_SRAM08 1782
27.1.38 UAB_SRAM09 1783
27.1.39 UAB_SRAM010 1784
27.1.40 UAB_SRAM011 1785
27.1.41 UAB_SRAM012 1786
27.1.42 UAB_SRAM013 1787
27.1.43 UAB_SRAM014 1788
27.1.44 UAB_SRAM015 1789
27.1.45 UAB_OA1_CTRL 1790
27.1.46 UAB_CAP_CTRL1 1792
27.1.47 UAB_CAP_ABCF1_VAL 1794
27.1.48 UAB_CAP_AB1_VAL_NXT 1795

27.1.49 UAB_CAP_CF1_VAL_NXT 1796
27.1.50 UAB_STARTUP_DELAY1 1797
27.1.51 UAB_SUBSAMPLE_CTRL1 1798
27.1.52 UAB_SW_STATIC1 1799
27.1.53 UAB_SW_MODBIT_SRC1 1801
27.1.54 UAB_SW_CA1_IN0 1802
27.1.55 UAB_SW_CA1_IN1 1803
27.1.56 UAB_SW_CA1_TOP 1804
27.1.57 UAB_SW_CB1_IN0 1805
27.1.58 UAB_SW_CB1_IN1 1806
27.1.59 UAB_SW_CB1_TOP 1807
27.1.60 UAB_SW_CC1_IN0 1808
27.1.61 UAB_SW_CC1_IN1 1809
27.1.62 UAB_SW_CC1_TOP 1810
27.1.63 UAB_SW_CF1_BOT 1811
27.1.64 UAB_SW_OTHER1 1812
27.1.65 UAB_SW_BOOST_CTRL1 1813
27.1.66 UAB_SRAM1_CTRL 1814
27.1.67 UAB_STAT1 1815
27.1.68 UAB_SRAM10 1816
27.1.69 UAB_SRAM11 1817
27.1.70 UAB_SRAM12 1818
27.1.71 UAB_SRAM13 1819
27.1.72 UAB_SRAM14 1820
27.1.73 UAB_SRAM15 1821
27.1.74 UAB_SRAM16 1822
27.1.75 UAB_SRAM17 1823
27.1.76 UAB_SRAM18 1824
27.1.77 UAB_SRAM19 1825
27.1.78 UAB_SRAM110 1826
27.1.79 UAB_SRAM111 1827
27.1.80 UAB_SRAM112 1828
27.1.81 UAB_SRAM113 1829
27.1.82 UAB_SRAM114 1830
27.1.83 UAB_SRAM115 1831
27.1.84 UAB_DECM_CTRL 1832
27.1.85 UAB_DC0_CTRL 1833
27.1.86 UAB_DC0_TRIG 1835
27.1.87 UAB_DC0_OVR 1836
27.1.88 UAB_DC0_A0 1837
27.1.89 UAB_DC0_A1 1838
27.1.90 UAB_DC0_DEC_CNT 1839
27.1.91 UAB_DC0_TMP 1840
27.1.92 UAB_DC0_D0 1841
27.1.93 UAB_DC0_D1 1842
27.1.94 UAB_DC0_RES 1843
27.1.95 UAB_DC1_CTRL 1844
27.1.96 UAB_DC1_TRIG 1846
27.1.97 UAB_DC1_OVR 1847
27.1.98 UAB_DC1_A0 1848
27.1.99 UAB_DC1_A1 1849
27.1.100 UAB_DC1_DEC_CNT 1850
27.1.101 UAB_DC1_TMP 1851
27.1.102 UAB_DC1_D0 1852

27.1.103 UAB_DC1_D1 1853
27.1.104 UAB_DC1_RES 1854
27.1.105 UAB_CAP_TRIM0 1855
27.1.106 UAB_CAP_TRIM1 1856
27.1.107 UAB_OA_TRIM0 1857
27.1.108 UAB_OA_TRIM1 1858

28. Watch Crystal Oscillator (WCO) Registers 1859

28.1 Register Details 1859
28.1.1 WCO_CONFIG 1860
28.1.2 WCO_DPLL 1862
28.1.3 WCO_WDT_CTRLOW 1864
28.1.4 WCO_WDT_CTRHIGH 1865
28.1.5 WCO_WDT_MATCH 1866
28.1.6 WCO_WDT_CONFIG 1867
28.1.7 WCO_WDT_CONTROL 1869
28.1.8 WCO_WDT_CLKEN 1871
28.1.9 WCO_TRIM 1872

Revision History 1874

Register Mapping

The Register Mapping section discusses the registers and lists all the registers in mapping tables, in address order. For Architecture details, refer to CY8C4Axx PSoC® Analog Coprocessor Architecture Technical Reference Manual (TRM).

Register General Conventions

The register conventions specific to this section and the Register Reference chapter are listed in this table.

Convention	Description	Explanation
RW	Read/Write	These bits can be both read and written.
R	Read only	These bits can only be read. Writing has no effect on the bit value.
W	Write only	These bits can only be written. Reading the bit returns the reset value.
RW1C	Read/Write ‘1’ to clear	These bits can be read as well as cleared by writing ‘1’. Writing ‘0’ has no effect on the bit value.
RW0C	Read/Write ‘0’ to clear	These bits can be read as well as cleared by writing ‘0’. Writing ‘1’ has no effect on the bit value.
RW1S	Read/Write ‘1’ to set	These bits can be read as well as set by writing ‘1’. Writing ‘0’ has no effect on the bit value.
None / Reserved	Reserved bits	Keep these bits at the default value
‘x’ in a register /bit field name	Multiple instances	Multiple instances/address ranges of the same register/bit field

Acronyms

This table lists the acronyms used in this document

Table 3-1. Acronyms

Symbol	Unit of Measure
ABUS	analog output bus
AC	alternating current
ADC	analog-to-digital converter
AHB	AMBA (advanced microcontroller bus architecture) high-performance bus, an ARM data transfer bus
API	application programming interface
APOR	analog power-on reset
BC	broadcast clock
BOM	bill of materials
BR	bit rate
BRA	bus request acknowledge
BRQ	bus request
CAN	controller area network
CI	carry in
CMP	compare
CO	carry out
CPU	central processing unit

Table 3-1. Acronyms

Symbol	Unit of Measure
CRC	cyclic redundancy check
CSD	CapSense sigma delta
CT	continuous time
CTBm	continuous time block-mini
DAC	digital-to-analog converter
DC	direct current
DI	digital or data input
DMA	direct memory access
DNL	differential nonlinearity
DO	digital or data output
DSI	digital signal interface
DSM	deep-sleep mode
ECO	external crystal oscillator
EEPROM	electrically erasable programmable read only memory
EMIF	external memory interface
FB	feedback
FIFO	first in first out
FSR	full scale range
GPIO	general purpose I/O
HCI	host-controller interface
HFCLK	high-frequency clock
I^2C	inter-integrated circuit
IDE	integrated development environment
ILO	internal low-speed oscillator
IMO	internal main oscillator
INL	integral nonlinearity
I/O	input/output
IOR	I/O read
IOW	I/O write
IRES	initial power on reset
IRA	interrupt request acknowledge
IRQ	interrupt request
ISR	interrupt service routine
IVR	interrupt vector read
L2CAP	logical link control and adaptation protocol
LPCOMP	low-power comparator
LRb	last received bit
LRB	last received byte
LSb	least significant bit
LSB	least significant byte
LUT	lookup table
MISO	master-in-slave-out
MMIO	memory mapped input/output
MOSI	master-out-slave-in

Table 3-1. Acronyms

Symbol	Unit of Measure
MSb	most significant bit
MSB	most significant byte
PC	program counter
PCH	program counter high
PCL	program counter low
PD	power down
PGA	programmable gain amplifier
PM	power management
PMA	PSoC memory arbiter
POR	power-on reset
PPOR	precision power-on reset
PRS	pseudo random sequence
PSoC®	Programmable System-on-Chip
PSRR	power supply rejection ratio
PSSDC	power system sleep duty cycle
PWM	pulse width modulator
RAM	random-access memory
RETI	return from interrupt
RF	radio frequency
ROM	read only memory
RW	read/write
SAR	successive approximation register
SC	switched capacitor
SCB	serial communication block
SIE	serial interface engine
SIO	special I/O
SE0	single-ended zero
SNR	signal-to-noise ratio
SOF	start of frame
SOI	start of instruction
SP	stack pointer
SPD	sequential phase detector
SPI	serial peripheral interconnect
SPIM	serial peripheral interconnect master
SPIS	serial peripheral interconnect slave
SRAM	static random-access memory
SRSS	system resources sub-system
SROM	supervisory read only memory
SSADC	single slope ADC
SSC	supervisory system call
SYSCLK	system clock
SWD	single wire debug
TC	terminal count
TD	transaction descriptors

Table 3-1. Acronyms

Symbol	Unit of Measure
UART	universal asynchronous receiver/transmitter
UDB	universal digital block
USB	universal serial bus
USBIO	USB I/O
WCO	watch crystal oscillator
WDT	watchdog timer
WDR	watchdog reset
XRES	external reset
XRES_N	external reset, active low

1 AROUTE Registers

This section discusses the AROUTE registers. It lists all the registers in mapping tables, in address order.

1.1 Register Details

Register Name	Address
ART_CTRL	0x40380000
ART_SARMUXVPLUS_SW	0x40380010
ART_SARMUXVPLUS_SW_CLR	0x40380014
ART_SARMUXVMINUS_SW	0x40380018
ART_SARMUXVMINUS_SW_CLR	0x4038001C
ART_SARMUXCOREIO0_SW	0x40380020
ART_SARMUXCOREIO0_SW_CLR	0x40380024
ART_SARMUXCOREIO1_SW	0x40380028
ART_SARMUXCOREIO1_SW_CLR	0x4038002C
ART_SARMUXCOREIO2_SW	0x40380030
ART_SARMUXCOREIO2_SW_CLR	0x40380034
ART_SARMUXCOREIO3_SW	0x40380038
ART_SARMUXCOREIO3_SW_CLR	0x4038003C
ART_SARAROUTEVREF_SW	0x40380040
ART_SARAROUTEVREF_SW_CLR	0x40380044
ART_SARAROUTEVDDA_SW	0x40380048
ART_SARAROUTEVDDA_SW_CLR	0x4038004C
ART_SARMUX_SW_HW_CTRL	0x40380060
ART_SARMUXVPLUS_SW_STATUS	0x40380064
ART_SARMUXVMINUS_SW_STATUS	0x40380068
ART_UAB0VIN00_SW	0x40380100
ART_UAB0VIN00_SW_CLR	0x40380104
ART_UAB0VIN01_SW	0x40380108
ART_UAB0VIN01_SW_CLR	0x4038010C
ART_UAB0VIN02_SW	0x40380110
ART_UAB0VIN02_SW_CLR	0x40380114
ART_UAB0VIN03_SW	0x40380118

Register Name	Address
ART_UAB0VIN03_SW_CLR	0x4038011C
ART_UAB0VIN10_SW	0x40380120
ART_UAB0VIN10_SW_CLR	0x40380124
ART_UAB0VIN11_SW	0x40380128
ART_UAB0VIN11_SW_CLR	0x4038012C
ART_UAB0VIN12_SW	0x40380130
ART_UAB0VIN12_SW_CLR	0x40380134
ART_UAB0VIN13_SW	0x40380138
ART_UAB0VIN13_SW_CLR	0x4038013C
ART_CTB0VREF_SW	0x40380140
ART_CTB0VREF_SW_CLR	0x40380144
ART_UAB0VREF_SW	0x40380148
ART_UAB0VREF_SW_CLR	0x4038014C
ART_UAB1VIN00_SW	0x40380180
ART_UAB1VIN00_SW_CLR	0x40380184
ART_UAB1VIN01_SW	0x40380188
ART_UAB1VIN01_SW_CLR	0x4038018C
ART_UAB1VIN02_SW	0x40380190
ART_UAB1VIN02_SW_CLR	0x40380194
ART_UAB1VIN03_SW	0x40380198
ART_UAB1VIN03_SW_CLR	0x4038019C
ART_UAB1VIN10_SW	0x403801A0
ART_UAB1VIN10_SW_CLR	0x403801A4
ART_UAB1VIN11_SW	0x403801A8
ART_UAB1VIN11_SW_CLR	0x403801AC
ART_UAB1VIN12_SW	0x403801B0
ART_UAB1VIN12_SW_CLR	0x403801B4
ART_UAB1VIN13_SW	0x403801B8
ART_UAB1VIN13_SW_CLR	0x403801BC
ART_CTB1VREF_SW	0x403801C0
ART_CTB1VREF_SW_CLR	0x403801C4

1.1.1 ART_CTRL

global AROUTE control

Address: 0x40380000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	ENABLED	DEEPSLEEP_ON	None [29:24]					

Bits	Name	Description
31	ENABLED	- 0: AROUTE disabled (put analog in power down, open all switches) - 1: AROUTE enabled Default Value: 0
30	DEEPSLEEP_ON	- 0: AROUTE disabled off during DeepSleep power mode - 1: AROUTE remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0

1.1.2 ART_SARMUXVPLUS_SW

sarmux_vplus switch control

Address: 0x40380010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	SMP_U1O1	SMP_U1O0	SMP_C1O1	SMP_C1O0	SMP_U0O1	SMP_U0O0	SMP_C0O1	SMP_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						SMP_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							RW1S
HW Access	None							RW1C
Name	None [31:25]							SMP_SRP

Bits	Name	Description
24	SMP_SRP	connect sarmux_vplus to sar_vplus Default Value: 0
17	SMP_AU1	connect sarmux_vplus to acore_u1 Default Value: 0
7	SMP_U1O1	connect sarmux_vplus to uab1_vout1 Default Value: 0
6	SMP_U1O0	connect sarmux_vplus to uab1_vout0 Default Value: 0
5	SMP_C1O1	connect sarmux_vplus to ctb1_vout1 Default Value: 0
4	SMP_C1O0	connect sarmux_vplus to ctb1_vout0 Default Value: 0
3	SMP_U0O1	connect sarmux_vplus to uab0_vout1 Default Value: 0
2	SMP_U0O0	connect sarmux_vplus to uab0_vout0 Default Value: 0

1.1.2 ART_SARMUXVPLUS_SW (continued)

1	SMP_C0O1	connect sarmux_vplus to ctb0_vout1 Default Value: 0
0	SMP_C0O0	connect sarmux_vplus to ctb0_vout0 Default Value: 0

1.1.3 ART_SARMUXVPLUS_SW_CLR

sarmux_vplus switch control clear

Address: 0x40380014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	SMP_U1O1	SMP_U1O0	SMP_C1O1	SMP_C1O0	SMP_U0O1	SMP_U0O0	SMP_C0O1	SMP_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						SMP_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							RW1C
HW Access	None							A
Name	None [31:25]							SMP_SRP

Bits	Name	Description
24	SMP_SRP	clear sarmux_vplus to sar_vplus Default Value: 0
17	SMP_AU1	clear sarmux_vplus to acore_u1 Default Value: 0
7	SMP_U1O1	clear sarmux_vplus to uab1_vout1 Default Value: 0
6	SMP_U1O0	clear sarmux_vplus to uab1_vout0 Default Value: 0
5	SMP_C1O1	clear sarmux_vplus to ctb1_vout1 Default Value: 0
4	SMP_C1O0	clear sarmux_vplus to ctb1_vout0 Default Value: 0
3	SMP_U0O1	clear sarmux_vplus to uab0_vout1 Default Value: 0
2	SMP_U0O0	clear sarmux_vplus to uab0_vout0 Default Value: 0

1.1.3 ART_SARMUXVPLUS_SW_CLR (continued)

1	SMP_C0O1	clear sarmux_vplus to ctb0_vout1 Default Value: 0
0	SMP_C0O0	clear sarmux_vplus to ctb0_vout0 Default Value: 0

1.1.4 ART_SARMUXVMINUS_SW

sarmux_vminus switch control

Address: 0x40380018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	SMM_U1O1	SMM_U1O0	SMM_C1O1	SMM_C1O0	SMM_U0O1	SMM_U0O0	SMM_C0O1	SMM_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					SMM_AU2	None	SMM_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None					RW1S	None
HW Access	RW1C	None					RW1C	None
Name	VSSA_SRM	None [30:26]					SMM_SRM	None

Bits	Name	Description
31	VSSA_SRM	connect vssa to sar_vminus Default Value: 0
25	SMM_SRM	connect sarmux_vminus to sar_vminus Default Value: 0
18	SMM_AU2	connect sarmux_vminus to acore_u2 Default Value: 0
16	SMM_AU0	connect sarmux_vminus to acore_u0 Default Value: 0
7	SMM_U1O1	connect sarmux_vminus to uab1_vout1 Default Value: 0
6	SMM_U1O0	connect sarmux_vminus to uab1_vout0 Default Value: 0
5	SMM_C1O1	connect sarmux_vminus to ctb1_vout1 Default Value: 0
4	SMM_C1O0	connect sarmux_vminus to ctb1_vout0 Default Value: 0

1.1.4 ART_SARMUXVMINUS_SW (continued)

3	SMM_U0O1	connect sarmux_vminus to uab0_vout1 Default Value: 0
2	SMM_U0O0	connect sarmux_vminus to uab0_vout0 Default Value: 0
1	SMM_C0O1	connect sarmux_vminus to ctb0_vout1 Default Value: 0
0	SMM_C0O0	connect sarmux_vminus to ctb0_vout0 Default Value: 0

1.1.5 ART_SARMUXVMINUS_SW_CLR

sarmux_vminus switch control clear

Address: 0x4038001C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	SMM_U1O1	SMM_U1O0	SMM_C1O1	SMM_C1O0	SMM_U0O1	SMM_U0O0	SMM_C0O1	SMM_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					SMM_AU2	None	SMM_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	None					RW1C	None
HW Access	A	None					A	None
Name	VSSA_SRM	None [30:26]					SMM_SRM	None

Bits	Name	Description
31	VSSA_SRM	clear vssa to sar_vminus Default Value: 0
25	SMM_SRM	clear sarmux_vminus to sar_vminus Default Value: 0
18	SMM_AU2	clear sarmux_vminus to acore_u2 Default Value: 0
16	SMM_AU0	clear sarmux_vminus to acore_u0 Default Value: 0
7	SMM_U1O1	clear sarmux_vminus to uab1_vout1 Default Value: 0
6	SMM_U1O0	clear sarmux_vminus to uab1_vout0 Default Value: 0
5	SMM_C1O1	clear sarmux_vminus to ctb1_vout1 Default Value: 0
4	SMM_C1O0	clear sarmux_vminus to ctb1_vout0 Default Value: 0

1.1.5 ART_SARMUXVMINUS_SW_CLR (continued)

3	SMM_U0O1	clear sarmux_vminus to uab0_vout1 Default Value: 0
2	SMM_U0O0	clear sarmux_vminus to uab0_vout0 Default Value: 0
1	SMM_C0O1	clear sarmux_vminus to ctb0_vout1 Default Value: 0
0	SMM_C0O0	clear sarmux_vminus to ctb0_vout0 Default Value: 0

1.1.6 ART_SARMUXCOREIO0_SW

sarmux_coreio0 switch control

Address: 0x40380020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None			RW1S
HW Access	None			RW1C	None			RW1C
Name	None [7:5]			SMC0_C1O0	None [3:1]			SMC0_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	
HW Access	None					RW1C	None	
Name	None [23:19]					SMC0_AU2	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1S	RW1S
HW Access	None						RW1C	RW1C
Name	None [31:26]						SMC0_SRM	SMC0_SRP

Bits	Name	Description
25	SMC0_SRM	connect sarmux_coreio0 to sar_vminus Default Value: 0
24	SMC0_SRP	connect sarmux_coreio0 to sar_vplus Default Value: 0
18	SMC0_AU2	connect sarmux_coreio0 to acore_u2 Default Value: 0
4	SMC0_C1O0	connect sarmux_coreio0 to ctb1_vout0 Default Value: 0
0	SMC0_C0O0	connect sarmux_coreio0 to ctb0_vout0 Default Value: 0

1.1.7 ART_SARMUXCOREIO0_SW_CLR

sarmux_coreio0 switch control clear

Address: 0x40380024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None			RW1C
HW Access	None			A	None			A
Name	None [7:5]			SMC0_C1O0	None [3:1]			SMC0_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	
HW Access	None					A	None	
Name	None [23:19]					SMC0_AU2	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [31:26]						SMC0_SRM	SMC0_SRP

Bits	Name	Description
25	SMC0_SRM	clear sarmux_coreio0 to sar_vminus Default Value: 0
24	SMC0_SRP	clear sarmux_coreio0 to sar_vplus Default Value: 0
18	SMC0_AU2	clear sarmux_coreio0 to acore_u2 Default Value: 0
4	SMC0_C1O0	clear sarmux_coreio0 to ctb1_vout0 Default Value: 0
0	SMC0_C0O0	clear sarmux_coreio0 to ctb0_vout0 Default Value: 0

1.1.8 ART_SARMUXCOREIO1_SW

sarmux_coreio1 switch control

Address: 0x40380028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1S	None			RW1S	None
HW Access	None		RW1C	None			RW1C	None
Name	None [7:6]		SMC1_C1O1	None [4:2]			SMC1_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1S	RW1S
HW Access	None						RW1C	RW1C
Name	None [31:26]						SMC1_SRM	SMC1_SRP

Bits	Name	Description
25	SMC1_SRM	connect sarmux_coreio1 to sar_vminus Default Value: 0
24	SMC1_SRP	connect sarmux_coreio1 to sar_vplus Default Value: 0
5	SMC1_C1O1	connect sarmux_coreio1 to ctb1_vout1 Default Value: 0
1	SMC1_C0O1	connect sarmux_coreio1 to ctb0_vout1 Default Value: 0

1.1.9 ART_SARMUXCOREIO1_SW_CLR

sarmux_coreio1 switch control clear

Address: 0x4038002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None			RW1C	None
HW Access	None		A	None			A	None
Name	None [7:6]		SMC1_C1O1	None [4:2]			SMC1_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [31:26]						SMC1_SRM	SMC1_SRP

Bits	Name	Description
25	SMC1_SRM	clear sarmux_coreio1 to sar_vminus Default Value: 0
24	SMC1_SRP	clear sarmux_coreio1 to sar_vplus Default Value: 0
5	SMC1_C1O1	clear sarmux_coreio1 to ctb1_vout1 Default Value: 0
1	SMC1_C0O1	clear sarmux_coreio1 to ctb0_vout1 Default Value: 0

1.1.10 ART_SARMUXCOREIO2_SW

sarmux_coreio2 switch control

Address: 0x40380030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1S	None			RW1S	None	
HW Access	None	RW1C	None			RW1C	None	
Name	None	SMC2_U1O0	None [5:3]			SMC2_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW1S
HW Access	None							RW1C
Name	None [23:17]							SMC2_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1S	RW1S
HW Access	None						RW1C	RW1C
Name	None [31:26]						SMC2_SRM	SMC2_SRP

Bits	Name	Description
25	SMC2_SRM	connect sarmux_coreio2 to sar_vminus Default Value: 0
24	SMC2_SRP	connect sarmux_coreio2 to sar_vplus Default Value: 0
16	SMC2_AU0	connect sarmux_coreio2 to acore_u0 Default Value: 0
6	SMC2_U1O0	connect sarmux_coreio2 to uab1_vout0 Default Value: 0
2	SMC2_U0O0	connect sarmux_coreio2 to uab0_vout0 Default Value: 0

1.1.11 ART_SARMUXCOREIO2_SW_CLR

sarmux_coreio2 switch control clear

Address: 0x40380034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	None			RW1C	None	
HW Access	None	A	None			A	None	
Name	None	SMC2_U1O0	None [5:3]			SMC2_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW1C
HW Access	None							A
Name	None [23:17]							SMC2_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [31:26]						SMC2_SRM	SMC2_SRP

Bits	Name	Description
25	SMC2_SRM	clear sarmux_coreio2 to sar_vminus Default Value: 0
24	SMC2_SRP	clear sarmux_coreio2 to sar_vplus Default Value: 0
16	SMC2_AU0	clear sarmux_coreio2 to acore_u0 Default Value: 0
6	SMC2_U1O0	clear sarmux_coreio2 to uab1_vout0 Default Value: 0
2	SMC2_U0O0	clear sarmux_coreio2 to uab0_vout0 Default Value: 0

1.1.12 ART_SARMUXCOREIO3_SW

sarmux_coreio3 switch control

Address: 0x40380038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	None			RW1S	None		
HW Access	RW1C	None			RW1C	None		
Name	SMC3_U1O1	None [6:4]			SMC3_U0O1	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						SMC3_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1S	RW1S
HW Access	None						RW1C	RW1C
Name	None [31:26]						SMC3_SRM	SMC3_SRP

Bits	Name	Description
25	SMC3_SRM	connect sarmux_coreio3 to sar_vminus Default Value: 0
24	SMC3_SRP	connect sarmux_coreio3 to sar_vplus Default Value: 0
17	SMC3_AU1	connect sarmux_coreio3 to acore_u1 Default Value: 0
7	SMC3_U1O1	connect sarmux_coreio3 to uab1_vout1 Default Value: 0
3	SMC3_U0O1	connect sarmux_coreio3 to uab0_vout1 Default Value: 0

1.1.13 ART_SARMUXCOREIO3_SW_CLR

sarmux_coreio3 switch control clear

Address: 0x4038003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	None			RW1C	None		
HW Access	A	None			A	None		
Name	SMC3_U1O1	None [6:4]			SMC3_U0O1	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						SMC3_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [31:26]						SMC3_SRM	SMC3_SRP

Bits	Name	Description
25	SMC3_SRM	clear sarmux_coreio3 to sar_vminus Default Value: 0
24	SMC3_SRP	clear sarmux_coreio3 to sar_vplus Default Value: 0
17	SMC3_AU1	clear sarmux_coreio3 to acore_u1 Default Value: 0
7	SMC3_U1O1	clear sarmux_coreio3 to uab1_vout1 Default Value: 0
3	SMC3_U0O1	clear sarmux_coreio3 to uab0_vout1 Default Value: 0

1.1.14 ART_SARAROUTEVREF_SW

sar_aroute_vref switch control

Address: 0x40380040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					SRV_AU2	None	SRV_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	SRV_AU2	connect sar_aroute_vref to acore_u2 Default Value: 0
16	SRV_AU0	connect sar_aroute_vref to acore_u0 Default Value: 0

1.1.15 ART_SARAROUTEVREF_SW_CLR

sar_aroute_vref switch control clear

Address: 0x40380044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					SRV_AU2	None	SRV_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	SRV_AU2	clear sar_aroute_vref to acore_u2 Default Value: 0
16	SRV_AU0	clear sar_aroute_vref to acore_u0 Default Value: 0

1.1.16 ART_SARAROUTEVDDA_SW

sar_aroute_vdda switch control

Address: 0x40380048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	RW1S
HW Access	None						RW1C	RW1C
Name	None [23:18]						VDA_AU1	VDA_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	VDA_AU1	connect sar_aroute_vdda to acore_u1 Default Value: 0
16	VDA_AU0	connect sar_aroute_vdda to acore_u0 Default Value: 0

1.1.17 ART_SARAROUTEVDDA_SW_CLR

sar_aroute_vdda switch control clear

Address: 0x4038004C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [23:18]						VDA_AU1	VDA_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	VDA_AU1	clear sar_aroute_vdda to acore_u1 Default Value: 0
16	VDA_AU0	clear sar_aroute_vdda to acore_u0 Default Value: 0

1.1.18 ART_SARMUX_SW_HW_CTRL

AROUTE SARMUX VPLUS/VMINUS hardware control

Address: 0x40380060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	SW_U1O1	SW_U1O0	SW_C1O1	SW_C1O0	SW_U0O1	SW_U0O0	SW_C0O1	SW_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							SW_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	SW_VSSA	None [30:24]						

Bits	Name	Description
31	SW_VSSA	Default Value: 0
16	SW_AU0	Default Value: 0
7	SW_U1O1	Default Value: 0
6	SW_U1O0	Default Value: 0
5	SW_C1O1	Default Value: 0
4	SW_C1O0	Default Value: 0
3	SW_U0O1	Default Value: 0
2	SW_U0O0	Default Value: 0
1	SW_C0O1	Default Value: 0
0	SW_C0O0	Default Value: 0

1.1.19 ART_SARMUXVPLUS_SW_STATUS

AROUTE SARMUX VPLUS switch control status

Address: 0x40380064

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	SW_U1O1	SW_U1O0	SW_C1O1	SW_C1O0	SW_U0O1	SW_U0O0	SW_C0O1	SW_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						R	None
HW Access	None						W	None
Name	None [23:18]						SW_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							SW_SRP

Bits	Name	Description
24	SW_SRP	connect sarmux_vplus to sar_vplus Default Value: 0
17	SW_AU1	connect sarmux_vplus to acore_u1 Default Value: 0
7	SW_U1O1	Default Value: 0
6	SW_U1O0	Default Value: 0
5	SW_C1O1	Default Value: 0
4	SW_C1O0	Default Value: 0
3	SW_U0O1	Default Value: 0
2	SW_U0O0	Default Value: 0
1	SW_C0O1	Default Value: 0
0	SW_C0O0	see corresponding bit in ART_SARVPLUS_SW Default Value: 0

1.1.20 ART_SARMUXVMINUS_SW_STATUS

AROUTE SAR VMINUS switch control status

Address: 0x40380068

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	SW_U1O1	SW_U1O0	SW_C1O1	SW_C1O0	SW_U0O1	SW_U0O0	SW_C0O1	SW_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					R	None	R
HW Access	None					W	None	W
Name	None [23:19]					SW_AU2	None	SW_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	R	None					R	None
HW Access	W	None					W	None
Name	SW_VSSA	None [30:26]					SW_SRM	None

Bits	Name	Description
31	SW_VSSA	Default Value: 0
25	SW_SRM	Default Value: 0
18	SW_AU2	Default Value: 0
16	SW_AU0	Default Value: 0
7	SW_U1O1	Default Value: 0
6	SW_U1O0	Default Value: 0
5	SW_C1O1	Default Value: 0
4	SW_C1O0	Default Value: 0
3	SW_U0O1	Default Value: 0
2	SW_U0O0	Default Value: 0
1	SW_C0O1	Default Value: 0
0	SW_C0O0	see corresponding bit in ART_SARVMINUS_SW Default Value: 0

1.1.21 ART_UAB0VIN00_SW

uab0_vin00 switch control

Address: 0x40380100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1S	None				RW1S	None
HW Access	None	RW1C	None				RW1C	None
Name	None	U0I00_U1O0	None [5:2]				U0I00_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U0I00_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U0I00_AU1	connect uab0_vin00 to acore_u1 Default Value: 0
6	U0I00_U1O0	connect uab0_vin00 to uab1_vout0 Default Value: 0
1	U0I00_C0O1	connect uab0_vin00 to ctb0_vout1 Default Value: 0

1.1.22 ART_UAB0VIN00_SW_CLR

uab0_vin00 switch control clear

Address: 0x40380104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	None				RW1C	None
HW Access	None	A	None				A	None
Name	None	U0I00_U1O0	None [5:2]				U0I00_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U0I00_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U0I00_AU1	clear uab0_vin00 to acore_u1 Default Value: 0
6	U0I00_U1O0	clear uab0_vin00 to uab1_vout0 Default Value: 0
1	U0I00_C0O1	clear uab0_vin00 to ctb0_vout1 Default Value: 0

1.1.23 ART_UAB0VIN01_SW

uab0_vin01 switch control

Address: 0x40380108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	None	RW1S	None				RW1S
HW Access	RW1C	None	RW1C	None				RW1C
Name	U0I01_U1O1	None	U0I01_C1O1	None [4:1]				U0I01_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U0I01_AU2	None	U0I01_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U0I01_AU2	connect uab0_vin01 to acore_u2 Default Value: 0
16	U0I01_AU0	connect uab0_vin01 to acore_u0 Default Value: 0
7	U0I01_U1O1	connect uab0_vin01 to uab1_vout1 Default Value: 0
5	U0I01_C1O1	connect uab0_vin01 to ctb1_vout1 Default Value: 0
0	U0I01_C0O0	connect uab0_vin01 to ctb0_vout0 Default Value: 0

1.1.24 ART_UAB0VIN01_SW_CLR

uab0_vin01 switch control clear

Address: 0x4038010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	None	RW1C	None				RW1C
HW Access	A	None	A	None				A
Name	U0I01_U1O1	None	U0I01_C1O1	None [4:1]				U0I01_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U0I01_AU2	None	U0I01_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U0I01_AU2	clear uab0_vin01 to acore_u2 Default Value: 0
16	U0I01_AU0	clear uab0_vin01 to acore_u0 Default Value: 0
7	U0I01_U1O1	clear uab0_vin01 to uab1_vout1 Default Value: 0
5	U0I01_C1O1	clear uab0_vin01 to ctb1_vout1 Default Value: 0
0	U0I01_C0O0	clear uab0_vin01 to ctb0_vout0 Default Value: 0

1.1.25 ART_UAB0VIN02_SW

uab0_vin02 switch control

Address: 0x40380110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	RW1S	None		
HW Access	None			RW1C	RW1C	None		
Name	None [7:5]			U0I02_C1O0	U0I02_U0O1	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U0I02_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None						
HW Access	RW1C	None						
Name	U0I02_C0C2	None [30:24]						

Bits	Name	Description
31	U0I02_C0C2	connect uab0_vin02 to ctb0_ctbus2 Default Value: 0
17	U0I02_AU1	connect uab0_vin02 to acore_u1 Default Value: 0
4	U0I02_C1O0	connect uab0_vin02 to ctb1_vout0 Default Value: 0
3	U0I02_U0O1	connect uab0_vin02 to uab0_vout1 Default Value: 0

1.1.26 ART_UAB0VIN02_SW_CLR

uab0_vin02 switch control clear

Address: 0x40380114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	None		
HW Access	None			A	A	None		
Name	None [7:5]			U0I02_C1O0	U0I02_U0O1	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U0I02_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	None						
HW Access	A	None						
Name	U0I02_C0C2	None [30:24]						

Bits	Name	Description
31	U0I02_C0C2	clear uab0_vin02 to ctb0_ctbus2 Default Value: 0
17	U0I02_AU1	clear uab0_vin02 to acore_u1 Default Value: 0
4	U0I02_C1O0	clear uab0_vin02 to ctb1_vout0 Default Value: 0
3	U0I02_U0O1	clear uab0_vin02 to uab0_vout1 Default Value: 0

1.1.27 ART_UAB0VIN03_SW

uab0_vin03 switch control

Address: 0x40380118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1S	None			RW1S	RW1S	None
HW Access	None	RW1C	None			RW1C	RW1C	None
Name	None	U0I03_U1O0	None [5:3]			U0I03_U0O0	U0I03_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U0I03_AU2	None	U0I03_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	RW1S	None					
HW Access	RW1C	RW1C	None					
Name	U0I03_C0C1	U0I03_U0I10	None [29:24]					

Bits	Name	Description
31	U0I03_C0C1	connect uab0_vin03 to ctb0_ctbus1 Default Value: 0
30	U0I03_U0I10	connect uab0_vin03 to uab0_vin10 Default Value: 0
18	U0I03_AU2	connect uab0_vin03 to acore_u2 Default Value: 0
16	U0I03_AU0	connect uab0_vin03 to acore_u0 Default Value: 0
6	U0I03_U1O0	connect uab0_vin03 to uab1_vout0 Default Value: 0
2	U0I03_U0O0	connect uab0_vin03 to uab0_vout0 Default Value: 0
1	U0I03_C0O1	connect uab0_vin03 to ctb0_vout1 Default Value: 0

1.1.28 ART_UAB0VIN03_SW_CLR

uab0_vin03 switch control clear

Address: 0x4038011C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	None			RW1C	RW1C	None
HW Access	None	A	None			A	A	None
Name	None	U0I03_U1O0	None [5:3]			U0I03_U0O0	U0I03_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U0I03_AU2	None	U0I03_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	RW1C	None					
HW Access	A	A	None					
Name	U0I03_C0C1	U0I03_U0I10	None [29:24]					

Bits	Name	Description
31	U0I03_C0C1	clear uab0_vin03 to ctb0_ctbus1 Default Value: 0
30	U0I03_U0I10	clear uab0_vin03 to uab0_vin10 Default Value: 0
18	U0I03_AU2	clear uab0_vin03 to acore_u2 Default Value: 0
16	U0I03_AU0	clear uab0_vin03 to acore_u0 Default Value: 0
6	U0I03_U1O0	clear uab0_vin03 to uab1_vout0 Default Value: 0
2	U0I03_U0O0	clear uab0_vin03 to uab0_vout0 Default Value: 0
1	U0I03_C0O1	clear uab0_vin03 to ctb0_vout1 Default Value: 0

1.1.29 ART_UAB0VIN10_SW

uab0_vin10 switch control

Address: 0x40380120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	None	RW1S	None	RW1S	None		RW1S
HW Access	RW1C	None	RW1C	None	RW1C	None		RW1C
Name	U0I10_U1O1	None	U0I10_C1O1	None	U0I10_U0O1	None [2:1]		U0I10_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U0I10_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None						
HW Access	RW1C	None						
Name	U0I10_C0C0	None [30:24]						

Bits	Name	Description
31	U0I10_C0C0	connect uab0_vin10 to ctb0_ctbus0 Default Value: 0
17	U0I10_AU1	connect uab0_vin10 to acore_u1 Default Value: 0
7	U0I10_U1O1	connect uab0_vin10 to uab1_vout1 Default Value: 0
5	U0I10_C1O1	connect uab0_vin10 to ctb1_vout1 Default Value: 0
3	U0I10_U0O1	connect uab0_vin10 to uab0_vout1 Default Value: 0
0	U0I10_C0O0	connect uab0_vin10 to ctb0_vout0 Default Value: 0

1.1.30 ART_UAB0VIN10_SW_CLR

uab0_vin10 switch control clear

Address: 0x40380124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	None	RW1C	None	RW1C	None		RW1C
HW Access	A	None	A	None	A	None		A
Name	U0I10_U1O1	None	U0I10_C1O1	None	U0I10_U0O1	None [2:1]		U0I10_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U0I10_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	None						
HW Access	A	None						
Name	U0I10_C0C0	None [30:24]						

Bits	Name	Description
31	U0I10_C0C0	clear uab0_vin10 to ctb0_ctbus0 Default Value: 0
17	U0I10_AU1	clear uab0_vin10 to acore_u1 Default Value: 0
7	U0I10_U1O1	clear uab0_vin10 to uab1_vout1 Default Value: 0
5	U0I10_C1O1	clear uab0_vin10 to ctb1_vout1 Default Value: 0
3	U0I10_U0O1	clear uab0_vin10 to uab0_vout1 Default Value: 0
0	U0I10_C0O0	clear uab0_vin10 to ctb0_vout0 Default Value: 0

1.1.31 ART_UAB0VIN11_SW

uab0_vin11 switch control

Address: 0x40380128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	None	
HW Access	None			RW1C	None	RW1C	None	
Name	None [7:5]			U0I11_C1O0	None	U0I11_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U0I11_AU2	None	U0I11_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None						
HW Access	RW1C	None						
Name	U0I11_C0C3	None [30:24]						

Bits	Name	Description
31	U0I11_C0C3	connect uab0_vin11 to ctb0_ctbus3 Default Value: 0
18	U0I11_AU2	connect uab0_vin11 to acore_u2 Default Value: 0
16	U0I11_AU0	connect uab0_vin11 to acore_u0 Default Value: 0
4	U0I11_C1O0	connect uab0_vin11 to ctb1_vout0 Default Value: 0
2	U0I11_U0O0	connect uab0_vin11 to uab0_vout0 Default Value: 0

1.1.32 ART_UAB0VIN11_SW_CLR

uab0_vin11 switch control clear

Address: 0x4038012C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	None	
HW Access	None			A	None	A	None	
Name	None [7:5]			U0I11_C1O0	None	U0I11_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U0I11_AU2	None	U0I11_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	None						
HW Access	A	None						
Name	U0I11_C0C3	None [30:24]						

Bits	Name	Description
31	U0I11_C0C3	clear uab0_vin11 to ctb0_ctbus3 Default Value: 0
18	U0I11_AU2	clear uab0_vin11 to acore_u2 Default Value: 0
16	U0I11_AU0	clear uab0_vin11 to acore_u0 Default Value: 0
4	U0I11_C1O0	clear uab0_vin11 to ctb1_vout0 Default Value: 0
2	U0I11_U0O0	clear uab0_vin11 to uab0_vout0 Default Value: 0

1.1.33 ART_UAB0VIN12_SW

uab0_vin12 switch control

Address: 0x40380130

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1S	None				RW1S	None
HW Access	None	RW1C	None				RW1C	None
Name	None	U0I12_U1O0	None [5:2]				U0I12_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U0I12_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U0I12_AU1	connect uab0_vin12 to acore_u1 Default Value: 0
6	U0I12_U1O0	connect uab0_vin12 to uab1_vout0 Default Value: 0
1	U0I12_C0O1	connect uab0_vin12 to ctb0_vout1 Default Value: 0

1.1.34 ART_UAB0VIN12_SW_CLR

uab0_vin12 switch control clear

Address: 0x40380134

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	None				RW1C	None
HW Access	None	A	None				A	None
Name	None	U0I12_U1O0	None [5:2]				U0I12_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U0I12_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U0I12_AU1	clear uab0_vin12 to acore_u1 Default Value: 0
6	U0I12_U1O0	clear uab0_vin12 to uab1_vout0 Default Value: 0
1	U0I12_C0O1	clear uab0_vin12 to ctb0_vout1 Default Value: 0

1.1.35 ART_UAB0VIN13_SW

uab0_vin13 switch control

Address: 0x40380138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	None	RW1S	None				RW1S
HW Access	RW1C	None	RW1C	None				RW1C
Name	U0I13_U1O1	None	U0I13_C1O1	None [4:1]				U0I13_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U0I13_AU2	None	U0I13_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U0I13_AU2	connect uab0_vin13 to acore_u2 Default Value: 0
16	U0I13_AU0	connect uab0_vin13 to acore_u0 Default Value: 0
7	U0I13_U1O1	connect uab0_vin13 to uab1_vout1 Default Value: 0
5	U0I13_C1O1	connect uab0_vin13 to ctb1_vout1 Default Value: 0
0	U0I13_C0O0	connect uab0_vin13 to ctb0_vout0 Default Value: 0

1.1.36 ART_UAB0VIN13_SW_CLR

uab0_vin13 switch control clear

Address: 0x4038013C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	None	RW1C	None				RW1C
HW Access	A	None	A	None				A
Name	U0I13_U1O1	None	U0I13_C1O1	None [4:1]				U0I13_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U0I13_AU2	None	U0I13_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U0I13_AU2	clear uab0_vin13 to acore_u2 Default Value: 0
16	U0I13_AU0	clear uab0_vin13 to acore_u0 Default Value: 0
7	U0I13_U1O1	clear uab0_vin13 to uab1_vout1 Default Value: 0
5	U0I13_C1O1	clear uab0_vin13 to ctb1_vout1 Default Value: 0
0	U0I13_C0O0	clear uab0_vin13 to ctb0_vout0 Default Value: 0

1.1.37 ART_CTB0VREF_SW

ctb0_vref0 switch control

Address: 0x40380140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [7:4]				C0V0_V3	C0V0_V2	C0V0_V1	C0V0_V0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [23:20]				C0V1_V3	C0V1_V2	C0V1_V1	C0V1_V0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	C0V1_V3	connect ctb0_vref1 to vref3 Default Value: 0
18	C0V1_V2	connect ctb0_vref1 to vref2 Default Value: 0
17	C0V1_V1	connect ctb0_vref1 to vref1 Default Value: 0
16	C0V1_V0	connect ctb0_vref1 to vref0 Default Value: 0
3	C0V0_V3	connect ctb0_vref0 to vref3 Default Value: 0
2	C0V0_V2	connect ctb0_vref0 to vref2 Default Value: 0
1	C0V0_V1	connect ctb0_vref0 to vref1 Default Value: 0
0	C0V0_V0	connect ctb0_vref0 to vref0 Default Value: 0

1.1.38 ART_CTB0VREF_SW_CLR

ctb0_vref0 switch control clear

Address: 0x40380144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				C0V0_V3	C0V0_V2	C0V0_V1	C0V0_V0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [23:20]				C0V1_V3	C0V1_V2	C0V1_V1	C0V1_V0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	C0V1_V3	clear ctb0_vref1 to vref3 Default Value: 0
18	C0V1_V2	clear ctb0_vref1 to vref2 Default Value: 0
17	C0V1_V1	clear ctb0_vref1 to vref1 Default Value: 0
16	C0V1_V0	clear ctb0_vref1 to vref0 Default Value: 0
3	C0V0_V3	clear ctb0_vref0 to vref3 Default Value: 0
2	C0V0_V2	clear ctb0_vref0 to vref2 Default Value: 0
1	C0V0_V1	clear ctb0_vref0 to vref1 Default Value: 0
0	C0V0_V0	clear ctb0_vref0 to vref0 Default Value: 0

1.1.39 ART_UAB0VREF_SW

uab0_vref00 switch control

Address: 0x40380148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [7:4]				U0V00_V3	U0V00_V2	U0V00_V1	U0V00_V0

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [15:12]				U0V01_V3	U0V01_V2	U0V01_V1	U0V01_V0

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [23:20]				U0V10_V3	U0V10_V2	U0V10_V1	U0V10_V0

Bits	31	30	29	28	27	26	25	24
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [31:28]				U0V11_V3	U0V11_V2	U0V11_V1	U0V11_V0

Bits	Name	Description
27	U0V11_V3	connect uab0_vref11 to vref3 Default Value: 0
26	U0V11_V2	connect uab0_vref11 to vref2 Default Value: 0
25	U0V11_V1	connect uab0_vref11 to vref1 Default Value: 0
24	U0V11_V0	connect uab0_vref11 to vref0 Default Value: 0
19	U0V10_V3	connect uab0_vref10 to vref3 Default Value: 0
18	U0V10_V2	connect uab0_vref10 to vref2 Default Value: 0
17	U0V10_V1	connect uab0_vref10 to vref1 Default Value: 0
16	U0V10_V0	connect uab0_vref10 to vref0 Default Value: 0

1.1.39 ART_UAB0VREF_SW (continued)

11	U0V01_V3	connect uab0_vref01 to vref3 Default Value: 0
10	U0V01_V2	connect uab0_vref01 to vref2 Default Value: 0
9	U0V01_V1	connect uab0_vref01 to vref1 Default Value: 0
8	U0V01_V0	connect uab0_vref01 to vref0 Default Value: 0
3	U0V00_V3	connect uab0_vref00 to vref3 Default Value: 0
2	U0V00_V2	connect uab0_vref00 to vref2 Default Value: 0
1	U0V00_V1	connect uab0_vref00 to vref1 Default Value: 0
0	U0V00_V0	connect uab0_vref00 to vref0 Default Value: 0

1.1.40 ART_UAB0VREF_SW_CLR

uab0_vref00 switch control clear

Address: 0x4038014C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				U0V00_V3	U0V00_V2	U0V00_V1	U0V00_V0

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [15:12]				U0V01_V3	U0V01_V2	U0V01_V1	U0V01_V0

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [23:20]				U0V10_V3	U0V10_V2	U0V10_V1	U0V10_V0

Bits	31	30	29	28	27	26	25	24
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [31:28]				U0V11_V3	U0V11_V2	U0V11_V1	U0V11_V0

Bits	Name	Description
27	U0V11_V3	clear uab0_vref11 to vref3 Default Value: 0
26	U0V11_V2	clear uab0_vref11 to vref2 Default Value: 0
25	U0V11_V1	clear uab0_vref11 to vref1 Default Value: 0
24	U0V11_V0	clear uab0_vref11 to vref0 Default Value: 0
19	U0V10_V3	clear uab0_vref10 to vref3 Default Value: 0
18	U0V10_V2	clear uab0_vref10 to vref2 Default Value: 0
17	U0V10_V1	clear uab0_vref10 to vref1 Default Value: 0
16	U0V10_V0	clear uab0_vref10 to vref0 Default Value: 0

1.1.40 ART_UAB0VREF_SW_CLR (continued)

11	U0V01_V3	clear uab0_vref01 to vref3 Default Value: 0
10	U0V01_V2	clear uab0_vref01 to vref2 Default Value: 0
9	U0V01_V1	clear uab0_vref01 to vref1 Default Value: 0
8	U0V01_V0	clear uab0_vref01 to vref0 Default Value: 0
3	U0V00_V3	clear uab0_vref00 to vref3 Default Value: 0
2	U0V00_V2	clear uab0_vref00 to vref2 Default Value: 0
1	U0V00_V1	clear uab0_vref00 to vref1 Default Value: 0
0	U0V00_V0	clear uab0_vref00 to vref0 Default Value: 0

1.1.41 ART_UAB1VIN00_SW

uab1_vin00 switch control

Address: 0x40380180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1S	None		RW1S	None	
HW Access	None		RW1C	None		RW1C	None	
Name	None [7:6]		U1I00_C1O1	None [4:3]		U1I00_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U1I00_AU2	None	U1I00_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U1I00_AU2	connect uab1_vin00 to acore_u2 Default Value: 0
16	U1I00_AU0	connect uab1_vin00 to acore_u0 Default Value: 0
5	U1I00_C1O1	connect uab1_vin00 to ctb1_vout1 Default Value: 0
2	U1I00_U0O0	connect uab1_vin00 to uab0_vout0 Default Value: 0

1.1.42 ART_UAB1VIN00_SW_CLR

uab1_vin00 switch control clear

Address: 0x40380184

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None		RW1C	None	
HW Access	None		A	None		A	None	
Name	None [7:6]		U1I00_C1O1	None [4:3]		U1I00_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U1I00_AU2	None	U1I00_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U1I00_AU2	clear uab1_vin00 to acore_u2 Default Value: 0
16	U1I00_AU0	clear uab1_vin00 to acore_u0 Default Value: 0
5	U1I00_C1O1	clear uab1_vin00 to ctb1_vout1 Default Value: 0
2	U1I00_U0O0	clear uab1_vin00 to uab0_vout0 Default Value: 0

1.1.43 ART_UAB1VIN01_SW

uab1_vin01 switch control

Address: 0x40380188

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	RW1S	None	RW1S	None
HW Access	None			RW1C	RW1C	None	RW1C	None
Name	None [7:5]			U1I01_C1O0	U1I01_U0O1	None	U1I01_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U1I01_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U1I01_AU1	connect uab1_vin01 to acore_u1 Default Value: 0
4	U1I01_C1O0	connect uab1_vin01 to ctb1_vout0 Default Value: 0
3	U1I01_U0O1	connect uab1_vin01 to uab0_vout1 Default Value: 0
1	U1I01_C0O1	connect uab1_vin01 to ctb0_vout1 Default Value: 0

1.1.44 ART_UAB1VIN01_SW_CLR

uab1_vin01 switch control clear

Address: 0x4038018C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	None	RW1C	None
HW Access	None			A	A	None	A	None
Name	None [7:5]			U1I01_C1O0	U1I01_U0O1	None	U1I01_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U1I01_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U1I01_AU1	clear uab1_vin01 to acore_u1 Default Value: 0
4	U1I01_C1O0	clear uab1_vin01 to ctb1_vout0 Default Value: 0
3	U1I01_U0O1	clear uab1_vin01 to uab0_vout1 Default Value: 0
1	U1I01_C0O1	clear uab1_vin01 to ctb0_vout1 Default Value: 0

1.1.45 ART_UAB1VIN02_SW

uab1_vin02 switch control

Address: 0x40380190

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	None						RW1S
HW Access	RW1C	None						RW1C
Name	U1I02_U1O1	None [6:1]						U1I02_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U1I02_AU2	None	U1I02_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None						
HW Access	RW1C	None						
Name	U1I02_C1C2	None [30:24]						

Bits	Name	Description
31	U1I02_C1C2	connect uab1_vin02 to ctb1_ctbus2 Default Value: 0
18	U1I02_AU2	connect uab1_vin02 to acore_u2 Default Value: 0
16	U1I02_AU0	connect uab1_vin02 to acore_u0 Default Value: 0
7	U1I02_U1O1	connect uab1_vin02 to uab1_vout1 Default Value: 0
0	U1I02_C0O0	connect uab1_vin02 to ctb0_vout0 Default Value: 0

1.1.46 ART_UAB1VIN02_SW_CLR

uab1_vin02 switch control clear

Address: 0x40380194

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	None						RW1C
HW Access	A	None						A
Name	U1I02_U1O1	None [6:1]						U1I02_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U1I02_AU2	None	U1I02_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	None						
HW Access	A	None						
Name	U1I02_C1C2	None [30:24]						

Bits	Name	Description
31	U1I02_C1C2	clear uab1_vin02 to ctb1_ctbus2 Default Value: 0
18	U1I02_AU2	clear uab1_vin02 to acore_u2 Default Value: 0
16	U1I02_AU0	clear uab1_vin02 to acore_u0 Default Value: 0
7	U1I02_U1O1	clear uab1_vin02 to uab1_vout1 Default Value: 0
0	U1I02_C0O0	clear uab1_vin02 to ctb0_vout0 Default Value: 0

1.1.47 ART_UAB1VIN03_SW

uab1_vin03 switch control

Address: 0x40380198

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1S	RW1S	None		RW1S	None	
HW Access	None	RW1C	RW1C	None		RW1C	None	
Name	None	U1I03_U1O0	U1I03_C1O1	None [4:3]		U1I03_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U1I03_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	RW1S	None					
HW Access	RW1C	RW1C	None					
Name	U1I03_C1C1	U1I03_U1I10	None [29:24]					

Bits	Name	Description
31	U1I03_C1C1	connect uab1_vin03 to ctb1_ctbus1 Default Value: 0
30	U1I03_U1I10	connect uab1_vin03 to uab1_vin10 Default Value: 0
17	U1I03_AU1	connect uab1_vin03 to acore_u1 Default Value: 0
6	U1I03_U1O0	connect uab1_vin03 to uab1_vout0 Default Value: 0
5	U1I03_C1O1	connect uab1_vin03 to ctb1_vout1 Default Value: 0
2	U1I03_U0O0	connect uab1_vin03 to uab0_vout0 Default Value: 0

1.1.48 ART_UAB1VIN03_SW_CLR

uab1_vin03 switch control clear

Address: 0x4038019C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	RW1C	None		RW1C	None	
HW Access	None	A	A	None		A	None	
Name	None	U1I03_U1O0	U1I03_C1O1	None [4:3]		U1I03_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U1I03_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	RW1C	None					
HW Access	A	A	None					
Name	U1I03_C1C1	U1I03_U1I10	None [29:24]					

Bits	Name	Description
31	U1I03_C1C1	clear uab1_vin03 to ctb1_ctbus1 Default Value: 0
30	U1I03_U1I10	clear uab1_vin03 to uab1_vin10 Default Value: 0
17	U1I03_AU1	clear uab1_vin03 to acore_u1 Default Value: 0
6	U1I03_U1O0	clear uab1_vin03 to uab1_vout0 Default Value: 0
5	U1I03_C1O1	clear uab1_vin03 to ctb1_vout1 Default Value: 0
2	U1I03_U0O0	clear uab1_vin03 to uab0_vout0 Default Value: 0

1.1.49 ART_UAB1VIN10_SW

uab1_vin10 switch control

Address: 0x403801A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	None		RW1S	RW1S	None	RW1S	None
HW Access	RW1C	None		RW1C	RW1C	None	RW1C	None
Name	U1I10_U1O1	None [6:5]		U1I10_C1O0	U1I10_U0O1	None	U1I10_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U1I10_AU2	None	U1I10_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None						
HW Access	RW1C	None						
Name	U1I10_C1C0	None [30:24]						

Bits	Name	Description
31	U1I10_C1C0	connect uab1_vin10 to ctb1_ctbus0 Default Value: 0
18	U1I10_AU2	connect uab1_vin10 to acore_u2 Default Value: 0
16	U1I10_AU0	connect uab1_vin10 to acore_u0 Default Value: 0
7	U1I10_U1O1	connect uab1_vin10 to uab1_vout1 Default Value: 0
4	U1I10_C1O0	connect uab1_vin10 to ctb1_vout0 Default Value: 0
3	U1I10_U0O1	connect uab1_vin10 to uab0_vout1 Default Value: 0
1	U1I10_C0O1	connect uab1_vin10 to ctb0_vout1 Default Value: 0

1.1.50 ART_UAB1VIN10_SW_CLR

uab1_vin10 switch control clear

Address: 0x403801A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	None		RW1C	RW1C	None	RW1C	None
HW Access	A	None		A	A	None	A	None
Name	U1I10_U1O1	None [6:5]		U1I10_C1O0	U1I10_U0O1	None	U1I10_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U1I10_AU2	None	U1I10_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	None						
HW Access	A	None						
Name	U1I10_C1C0	None [30:24]						

Bits	Name	Description
31	U1I10_C1C0	clear uab1_vin10 to ctb1_ctbus0 Default Value: 0
18	U1I10_AU2	clear uab1_vin10 to acore_u2 Default Value: 0
16	U1I10_AU0	clear uab1_vin10 to acore_u0 Default Value: 0
7	U1I10_U1O1	clear uab1_vin10 to uab1_vout1 Default Value: 0
4	U1I10_C1O0	clear uab1_vin10 to ctb1_vout0 Default Value: 0
3	U1I10_U0O1	clear uab1_vin10 to uab0_vout1 Default Value: 0
1	U1I10_C0O1	clear uab1_vin10 to ctb0_vout1 Default Value: 0

1.1.51 ART_UAB1VIN11_SW

uab1_vin11 switch control

Address: 0x403801A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1S	None					RW1S
HW Access	None	RW1C	None					RW1C
Name	None	U1I11_U1O0	None [5:1]					U1I11_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U1I11_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None						
HW Access	RW1C	None						
Name	U1I11_C1C3	None [30:24]						

Bits	Name	Description
31	U1I11_C1C3	connect uab1_vin11 to ctb1_ctbus3 Default Value: 0
17	U1I11_AU1	connect uab1_vin11 to acore_u1 Default Value: 0
6	U1I11_U1O0	connect uab1_vin11 to uab1_vout0 Default Value: 0
0	U1I11_C0O0	connect uab1_vin11 to ctb0_vout0 Default Value: 0

1.1.52 ART_UAB1VIN11_SW_CLR

uab1_vin11 switch control clear

Address: 0x403801AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	None					RW1C
HW Access	None	A	None					A
Name	None	U1I11_U1O0	None [5:1]					U1I11_C0O0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U1I11_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	None						
HW Access	A	None						
Name	U1I11_C1C3	None [30:24]						

Bits	Name	Description
31	U1I11_C1C3	clear uab1_vin11 to ctb1_ctbus3 Default Value: 0
17	U1I11_AU1	clear uab1_vin11 to acore_u1 Default Value: 0
6	U1I11_U1O0	clear uab1_vin11 to uab1_vout0 Default Value: 0
0	U1I11_C0O0	clear uab1_vin11 to ctb0_vout0 Default Value: 0

1.1.53 ART_UAB1VIN12_SW

uab1_vin12 switch control

Address: 0x403801B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1S	None		RW1S	None	
HW Access	None		RW1C	None		RW1C	None	
Name	None [7:6]		U1I12_C1O1	None [4:3]		U1I12_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	None	RW1S
HW Access	None					RW1C	None	RW1C
Name	None [23:19]					U1I12_AU2	None	U1I12_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U1I12_AU2	connect uab1_vin12 to acore_u2 Default Value: 0
16	U1I12_AU0	connect uab1_vin12 to acore_u0 Default Value: 0
5	U1I12_C1O1	connect uab1_vin12 to ctb1_vout1 Default Value: 0
2	U1I12_U0O0	connect uab1_vin12 to uab0_vout0 Default Value: 0

1.1.54 ART_UAB1VIN12_SW_CLR

uab1_vin12 switch control clear

Address: 0x403801B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None		RW1C	None	
HW Access	None		A	None		A	None	
Name	None [7:6]		U1I12_C1O1	None [4:3]		U1I12_U0O0	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	None	RW1C
HW Access	None					A	None	A
Name	None [23:19]					U1I12_AU2	None	U1I12_AU0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	U1I12_AU2	clear uab1_vin12 to acore_u2 Default Value: 0
16	U1I12_AU0	clear uab1_vin12 to acore_u0 Default Value: 0
5	U1I12_C1O1	clear uab1_vin12 to ctb1_vout1 Default Value: 0
2	U1I12_U0O0	clear uab1_vin12 to uab0_vout0 Default Value: 0

1.1.55 ART_UAB1VIN13_SW

uab1_vin13 switch control

Address: 0x403801B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	RW1S	None	RW1S	None
HW Access	None			RW1C	RW1C	None	RW1C	None
Name	None [7:5]			U1I13_C1O0	U1I13_U0O1	None	U1I13_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1S	None
HW Access	None						RW1C	None
Name	None [23:18]						U1I13_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U1I13_AU1	connect uab1_vin13 to acore_u1 Default Value: 0
4	U1I13_C1O0	connect uab1_vin13 to ctb1_vout0 Default Value: 0
3	U1I13_U0O1	connect uab1_vin13 to uab0_vout1 Default Value: 0
1	U1I13_C0O1	connect uab1_vin13 to ctb0_vout1 Default Value: 0

1.1.56 ART_UAB1VIN13_SW_CLR

uab1_vin13 switch control clear

Address: 0x403801BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	None	RW1C	None
HW Access	None			A	A	None	A	None
Name	None [7:5]			U1I13_C1O0	U1I13_U0O1	None	U1I13_C0O1	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW1C	None
HW Access	None						A	None
Name	None [23:18]						U1I13_AU1	None

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	U1I13_AU1	clear uab1_vin13 to acore_u1 Default Value: 0
4	U1I13_C1O0	clear uab1_vin13 to ctb1_vout0 Default Value: 0
3	U1I13_U0O1	clear uab1_vin13 to uab0_vout1 Default Value: 0
1	U1I13_C0O1	clear uab1_vin13 to ctb0_vout1 Default Value: 0

1.1.57 ART_CTB1VREF_SW

ctb1_vref0 switch control

Address: 0x403801C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [7:4]				C1V0_V3	C1V0_V2	C1V0_V1	C1V0_V0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [23:20]				C1V1_V3	C1V1_V2	C1V1_V1	C1V1_V0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	C1V1_V3	connect ctb1_vref1 to vref3 Default Value: 0
18	C1V1_V2	connect ctb1_vref1 to vref2 Default Value: 0
17	C1V1_V1	connect ctb1_vref1 to vref1 Default Value: 0
16	C1V1_V0	connect ctb1_vref1 to vref0 Default Value: 0
3	C1V0_V3	connect ctb1_vref0 to vref3 Default Value: 0
2	C1V0_V2	connect ctb1_vref0 to vref2 Default Value: 0
1	C1V0_V1	connect ctb1_vref0 to vref1 Default Value: 0
0	C1V0_V0	connect ctb1_vref0 to vref0 Default Value: 0

1.1.58 ART_CTB1VREF_SW_CLR

ctb1_vref0 switch control clear

Address: 0x403801C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				C1V0_V3	C1V0_V2	C1V0_V1	C1V0_V0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [23:20]				C1V1_V3	C1V1_V2	C1V1_V1	C1V1_V0

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	C1V1_V3	clear ctb1_vref1 to vref3 Default Value: 0
18	C1V1_V2	clear ctb1_vref1 to vref2 Default Value: 0
17	C1V1_V1	clear ctb1_vref1 to vref1 Default Value: 0
16	C1V1_V0	clear ctb1_vref1 to vref0 Default Value: 0
3	C1V0_V3	clear ctb1_vref0 to vref3 Default Value: 0
2	C1V0_V2	clear ctb1_vref0 to vref2 Default Value: 0
1	C1V0_V1	clear ctb1_vref0 to vref1 Default Value: 0
0	C1V0_V0	clear ctb1_vref0 to vref0 Default Value: 0

2 Cortex M0+ (CM0+) Registers

This section discusses the CM0+ registers. It lists all the registers in mapping tables, in address order.

2.1 Register Details

Register Name	Address
CM0P_DWT_PID4	0xE0001FD0
CM0P_DWT_PID0	0xE0001FE0
CM0P_DWT_PID1	0xE0001FE4
CM0P_DWT_PID2	0xE0001FE8
CM0P_DWT_PID3	0xE0001FEC
CM0P_DWT_CID0	0xE0001FF0
CM0P_DWT_CID1	0xE0001FF4
CM0P_DWT_CID2	0xE0001FF8
CM0P_DWT_CID3	0xE0001FFC
CM0P_BP_PID4	0xE0002FD0
CM0P_BP_PID0	0xE0002FE0
CM0P_BP_PID1	0xE0002FE4
CM0P_BP_PID2	0xE0002FE8
CM0P_BP_PID3	0xE0002FEC
CM0P_BP_CID0	0xE0002FF0
CM0P_BP_CID1	0xE0002FF4
CM0P_BP_CID2	0xE0002FF8
CM0P_BP_CID3	0xE0002FFC
CM0P_SYST_CSR	0xE000E010
CM0P_SYST_RVR	0xE000E014
CM0P_SYST_CVR	0xE000E018
CM0P_SYST_CALIB	0xE000E01C
CM0P_ISER	0xE000E100
CM0P_ICER	0xE000E180
CM0P_ISPR	0xE000E200
CM0P_ICPR	0xE000E280
CM0P_IPR0	0xE000E400

Register Name	Address
CM0P_IPR1	0xE000E404
CM0P_IPR2	0xE000E408
CM0P_IPR3	0xE000E40C
CM0P_IPR4	0xE000E410
CM0P_IPR5	0xE000E414
CM0P_IPR6	0xE000E418
CM0P_IPR7	0xE000E41C
CM0P_CPUID	0xE000ED00
CM0P_ICSR	0xE000ED04
CM0P_AIRCR	0xE000ED0C
CM0P_SCR	0xE000ED10
CM0P_CCR	0xE000ED14
CM0P_SHPR2	0xE000ED1C
CM0P_SHPR3	0xE000ED20
CM0P_SHCSR	0xE000ED24
CM0P_SCS_PID4	0xE000EFD0
CM0P_SCS_PID0	0xE000EFE0
CM0P_SCS_PID1	0xE000EFE4
CM0P_SCS_PID2	0xE000EFE8
CM0P_SCS_PID3	0xE000EFEC
CM0P_SCS_CID0	0xE000EFF0
CM0P_SCS_CID1	0xE000EFF4
CM0P_SCS_CID2	0xE000EFF8
CM0P_SCS_CID3	0xE000EFFC
CM0P_ROM_SCS	0xE00FF000
CM0P_ROM_DWT	0xE00FF004
CM0P_ROM_BPU	0xE00FF008
CM0P_ROM_END	0xE00FF00C
CM0P_ROM_CSMT	0xE00FFFCC
CM0P_ROM_PID4	0xE00FFFD0
CM0P_ROM_PID0	0xE00FFFE0
CM0P_ROM_PID1	0xE00FFFE4
CM0P_ROM_PID2	0xE00FFFE8
CM0P_ROM_PID3	0xE00FFFEC
CM0P_ROM_CID0	0xE00FFFF0
CM0P_ROM_CID1	0xE00FFFF4
CM0P_ROM_CID2	0xE00FFFF8
CM0P_ROM_CID3	0xE00FFFFC

2.1.1 CM0P_DWT_PID4

Watchpoint Unit CoreSight ROM Table Peripheral ID #4

Address: 0xE0001FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

2.1.2 CM0P_DWT_PID0

Watchpoint Unit CoreSight ROM Table Peripheral ID #0

Address: 0xE0001FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 10

2.1.3 CM0P_DWT_PID1

Watchpoint Unit CoreSight ROM Table Peripheral ID #1

Address: 0xE0001FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

2.1.4 CM0P_DWT_PID2

Watchpoint Unit CoreSight ROM Table Peripheral ID #2

Address: 0xE0001FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

2.1.5 CM0P_DWT_PID3

Watchpoint Unit CoreSight ROM Table Peripheral ID #3

Address: 0xE0001FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

2.1.6 CM0P_DWT_CID0

Watchpoint Unit CoreSight ROM Table Component ID #0

Address: 0xE0001FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

2.1.7 CM0P_DWT_CID1

Watchpoint Unit CoreSight ROM Table Component ID #1

Address: 0xE0001FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

2.1.8 CM0P_DWT_CID2

Watchpoint Unit CoreSight ROM Table Component ID #2

Address: 0xE0001FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

2.1.9 CM0P_DWT_CID3

Watchpoint Unit CoreSight ROM Table Component ID #3

Address: 0xE0001FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

2.1.10 CM0P_BP_PID4

Breakpoint Unit CoreSight ROM Table Peripheral ID #4

Address: 0xE0002FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

2.1.11 CM0P_BP_PID0

Breakpoint Unit CoreSight ROM Table Peripheral ID #0

Address: 0xE0002FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 11

2.1.12 CM0P_BP_PID1

Breakpoint Unit CoreSight ROM Table Peripheral ID #1

Address: 0xE0002FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

2.1.13 CM0P_BP_PID2

Breakpoint Unit CoreSight ROM Table Peripheral ID #2

Address: 0xE0002FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

2.1.14 CM0P_BP_PID3

Breakpoint Unit CoreSight ROM Table Peripheral ID #3

Address: 0xE0002FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

2.1.15 CM0P_BP_CID0

Breakpoint Unit CoreSight ROM Table Component ID #0

Address: 0xE0002FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

2.1.16 CM0P_BP_CID1

Breakpoint Unit CoreSight ROM Table Component ID #1

Address: 0xE0002FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

2.1.17 CM0P_BP_CID2

Breakpoint Unit CoreSight ROM Table Component ID #2

Address: 0xE0002FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

2.1.18 CM0P_BP_CID3

Breakpoint Unit CoreSight ROM Table Component ID #3

Address: 0xE0002FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

2.1.19 CM0P_SYST_CSR

SysTick Control & Status

Address: 0xE000E010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [7:3]					CLK-SOURCE	TICKINT	ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							RW
Name	None [23:17]							COUNT-FLAG

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	COUNTFLAG	Indicates whether the counter has counted to "0" since the last read of this register: '0': counter has not counted to "0". '1': counter has counted to "0". COUNTFLAG is set to '1' by a count transition from "1" to "0". COUNTFLAG is cleared to '0' by a read of this register, and by any write to the SYST_CVR register. Default Value: 0
2	CLKSOURCE	Indicates the SysTick counter clock source: '0': SysTick uses the low frequency clock "clk_lf". For this mode to function, "clk_lf" should be less than half the frequency of "clk_sys". Note that "clk_lf" is generated by a low accuracy ILO (Internal Low power Oscillator). '1': SysTick uses the system/processor clock "clk_sys". Default Value: 0

2.1.19 CM0P_SYST_CSR (continued)

1	TICKINT	Indicates whether counting to "0" causes the status of the SysTick exception to change to pending: '0': count to "0" does not affect the SysTick exception status. '1': count to "0" changes the SysTick exception status to pending. Changing the value of the counter to "0" by writing zero to the SYST_CVR register to "0" never changes the status of the SysTick exception. Default Value: 0
0	ENABLE	Indicates the enabled status of the SysTick counter: '0': counter is disabled. '1': counter is operating. Default Value: 0

2.1.20 CM0P_SYST_RVR

SysTick Reload Value

Address: 0xE000E014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RELOAD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RELOAD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	RELOAD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 0	RELOAD	The value to load into the SYST_CVR register when the counter reaches 0. Default Value: X

2.1.21 CM0P_SYST_CVR

SysTick Current Value

Address: 0xE000E018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CURRENT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CURRENT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	CURRENT [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 0	CURRENT	Current counter value. This is the value of the counter at the time it is sampled. Default Value: X

2.1.22 CM0P_SYST_CALIB

SysTick Calibration Value

Address: 0xE000E01C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	TENMS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	TENMS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	TENMS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	None	RW	None					
Name	NOREF	SKEW	None [29:24]					

Bits	Name	Description
31	NOREF	Indicates whether a implementation defined reference clock is provided: '0': the reference clock is provided. '1': the reference clock is not provided. When this bit is '1', the SYST_CSR.CLKSOURCE is forced to '1' and cannot be cleared to '0'. Default Value: 0
30	SKEW	Indicates whether the 10ms calibration value is exact: '0': 10ms calibration value is exact. '1': 10ms calibration value is inexact, because of the clock frequency. If clk_lf is selected as the source of SysTick, this field contains '1' else '0'. Default Value: X
23 : 0	TENMS	Holds a reload value to be used for 10ms (100Hz) timing, subject to system clock skew errors. If clk_lf is selected as the source for SysTick, reload value is 0x147 (327 decimal). If clk_sys is selected as the source for SysTick, this field value is 0x00. Default Value: X

2.1.23 CM0P_ISER

Interrupt Set-Enable Register

Address: 0xE000E100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	R							
Name	SETENA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	R							
Name	SETENA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	R							
Name	SETENA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	R							
Name	SETENA [31:24]							

Bits	Name	Description
31 : 0	SETENA	Enables, or reads the enabled state of one or more interrupts. Each bit corresponds to the same numbered interrupt. Refer the Architecture Technical Reference Manual to know the interrupt source assigned to each of the interrupt line. Default Value: 0

2.1.24 CM0P_ICER

Interrupt Clear Enable Register

Address: 0xE000E180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	R							
Name	CLRENA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	R							
Name	CLRENA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C							
HW Access	R							
Name	CLRENA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C							
HW Access	R							
Name	CLRENA [31:24]							

Bits	Name	Description
31 : 0	CLRENA	Disables, or reads the enabled state of one or more interrupts. Each bit corresponds to the same numbered interrupt. Refer the Architecture Technical Reference Manual to know the interrupt source assigned to each of the interrupt line. Default Value: 0

2.1.25 CM0P_ISPR

Interrupt Set-Pending Register

Address: 0xE000E200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	R							
Name	SETPEND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	R							
Name	SETPEND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	R							
Name	SETPEND [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	R							
Name	SETPEND [31:24]							

Bits	Name	Description
31 : 0	SETPEND	Changes the state of one or more interrupts to pending. Each bit corresponds to the same numbered interrupt. Refer the Architecture Technical Reference Manual to know the interrupt source assigned to each of the interrupt line. Default Value: 0

2.1.26 CM0P_ICPR

Interrupt Clear-Pending Register

Address: 0xE000E280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [31:24]							

Bits	Name	Description
31 : 0	CLRPEND	Changes the state of one or more interrupts to not pending. Each bit corresponds to the same numbered interrupt. Refer the Architecture Technical Reference Manual to know the interrupt source assigned to each of the interrupt line. Default Value: 0

2.1.27 CM0P_IPR0

Interrupt Priority Registers

Address: 0xE000E400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.28 CM0P_IPR1

Interrupt Priority Registers

Address: 0xE000E404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.29 CM0P_IPR2

Interrupt Priority Registers

Address: 0xE000E408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.30 CM0P_IPR3

Interrupt Priority Registers

Address: 0xE000E40C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.31 CM0P_IPR4

Interrupt Priority Registers

Address: 0xE000E410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.32 CM0P_IPR5

Interrupt Priority Registers

Address: 0xE000E414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.33 CM0P_IPR6

Interrupt Priority Registers

Address: 0xE000E418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.34 CM0P_IPR7

Interrupt Priority Registers

Address: 0xE000E41C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

2.1.35 CM0P_CPUID

CPUID Register

Address: 0xE000ED00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	None				None			
Name	PARTNO [7:4]				REVISION [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	PARTNO [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R				R			
HW Access	None				None			
Name	VARIANT [23:20]				CONSTANT [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	IMPLEMENTER [31:24]							

Bits	Name	Description
31 : 24	IMPLEMENTER	Implementer code for ARM. Default Value: 65
23 : 20	VARIANT	Indicates major revision Default Value: 0
19 : 16	CONSTANT	Indicates the architecture, ARMv6-M Default Value: 12
15 : 4	PARTNO	Indicates part number, Cortex-M0+ Default Value: 3168
3 : 0	REVISION	Indicates minor revision Default Value: 1

2.1.36 CM0P_ICSR

Interrupt Control State Register

Address: 0xE000ED04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VECTACTIVE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R				None			R
HW Access	RW				None			RW
Name	VECTPENDING [15:12]				None [11:9]			VECTAC-TIVE

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	None	R				
HW Access	RW	RW	None	RW				
Name	ISRPRE-EMPT	ISRPEND-ING	None	VECTPENDING [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None		RW1S	RW1C	RW1S	RW1C	None
HW Access	RW	None		RW	R	RW	R	None
Name	NMIPEND-SET	None [30:29]		PENDSV-SET	PENDSV-CLR	PENDST-SETb	PENDST-CLR	None

Bits	Name	Description
31	NMIPENDSET	Activates an NMI exception or reads back the current state. Because NMI is the highest priority exception, it activates as soon as it is registered. Default Value: 0
28	PENDSVSET	Sets a pending PendSV interrupt or reads back the current state. Use this normally to request a context switch. Writing PENDSVSET and PENDSVCLR to '1' concurrently is UNPREDICT-ABLE. Default Value: 0
27	PENDSVCLR	Clears a pending PendSV interrupt. Default Value: 0
26	PENDSTSETb	Sets a pending SysTick or reads back the current state. Writing PENDSTSET and PENDSTCLR to '1' concurrently is UNPREDICTABLE. Default Value: 0
25	PENDSTCLR	Clears a pending SysTick, whether set here or by the timer hardware. Default Value: 0

2.1.36 CM0P_ICSR (continued)

23	ISRPREEMPT	Indicates whether a pending exception will be serviced on exit from debug halt state. Default Value: 0
22	ISRPENDING	Indicates if an external configurable, NVIC generated, interrupt is pending. Default Value: 0
20 : 12	VECTPENDING	The exception number for the highest priority pending exception. 0= No pending exceptions. The pending state includes the effect of memory-mapped enable and mask registers. It does not include the PRIMASK special-purpose register qualifier. Default Value: 0
8 : 0	VECTACTIVE	The exception number for the current executing exception. 0= Thread mode. This is the same value as IPSR[8:0] Default Value: 0

2.1.37 CM0P_AIRCR

Application Interrupt and Reset Control Register

Address: 0xE000ED0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1S	RW1C	None
HW Access	None					R	R	None
Name	None [7:3]					SYSRESE-TREQ	VECTCL-RACTIVE	None

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	None	None						
Name	ENDIAN-NESS	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	VECTKEY [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	VECTKEY [31:24]							

Bits	Name	Description
31 : 16	VECTKEY	Vector Key. The value 0x05FA must be written to this register, otherwise the register write is UN-PREDICTABLE. Readback value is UNKNOWN. Default Value: X
15	ENDIANNESS	Indicates the memory system data endianness: 0 little endian 1 big endian. Default Value: 0
2	SYSRESETREQ	System Reset Request. Writing 1 to this bit asserts a signal to request a reset by the external system. This will cause a full system reset of the CPU and all other components in the device. Default Value: 0
1	VECTCLRACTIVE	Clears all active state information for fixed and configurable exceptions. The effect of writing a 1 to this bit if the processor is not halted in Debug state is UNPREDICTABLE. Default Value: 0

2.1.38 CM0P_SCR

System Control Register

Address: 0xE000ED10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	None
HW Access	None			R	None	R	R	None
Name	None [7:5]			SEVON-PEND	None	SLEEP-DEEP	SLEEPON-EXIT	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	SEVONPEND	Determines whether an interrupt transition from inactive state to pending state is a wakeup event: 0: transitions from inactive to pending are not wakeup events. 1: transitions from inactive to pending are wakeup events. Default Value: 0
2	SLEEPDEEP	An implementation can use this bit to select DeepSleep power mode upon execution of WFI/ WFE: 0: Select Sleep mode 1: Select DeepSleep Default Value: 0
1	SLEEPONEXIT	Determines whether, on an exit from an ISR that returns to the base level of execution priority, the processor enters a sleep state: 0 do not enter sleep state. 1 enter sleep state. Default Value: 0

2.1.39 CM0P_CCR

Configuration and Control Register

Address: 0xE000ED14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	None		
HW Access	None				None	None		
Name	None [7:4]				UNALIGN_ TRP	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	None
HW Access	None						None	None
Name	None [15:10]						STKALIGN	None

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	STKALIGN	1: On exception entry, the SP used prior to the exception is adjusted to be 8-byte aligned and the context to restore it is saved. The SP is restored on the associated exception return. Default Value: 1
3	UNALIGN_TRP	1: unaligned word and halfword accesses generate a HardFault exception. Default Value: 1

2.1.40 CM0P_SHPR2

System Handler Priority Register 2

Address: 0xE000ED1C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_11 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_11	Priority of system handler 11, SVCall Default Value: 0

2.1.41 CM0P_SHPR3

System Handler Priority Register 3

Address: 0xE000ED20

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_14 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_15 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_15	Priority of system handler 15, SysTick Default Value: 0
23 : 22	PRI_14	Priority of system handler 14, PendSV Default Value: 0

2.1.42 CM0P_SHCSR

System Handler Control and State Register

Address: 0xE000ED24

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW	None						
HW Access	RW	None						
Name	SVCALL-PENDED	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	SVCALLPENDED	0 SVCall is not pending. 1 SVCall is pending. This bit reflects the pending state on a read, and updates the pending state, to the value written, on a write. (Pending state bits are set to 1 when an exception occurs, and are cleared to 0 when an exception becomes active.) Default Value: 0

2.1.43 CM0P_SCS_PID4

System Control Space ROM Table Peripheral ID #4

Address: 0xE000EFD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

2.1.44 CM0P_SCS_PID0

System Control Space ROM Table Peripheral ID #0

Address: 0xE000EFE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 8

2.1.45 CM0P_SCS_PID1

System Control Space ROM Table Peripheral ID #1

Address: 0xE000EFE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

2.1.46 CM0P_SCS_PID2

System Control Space ROM Table Peripheral ID #2

Address: 0xE000EFE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

2.1.47 CM0P_SCS_PID3

System Control Space ROM Table Peripheral ID #3

Address: 0xE000EFEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

2.1.48 CM0P_SCS_CID0

System Control Space ROM Table Component ID #0

Address: 0xE000EFF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

2.1.49 CM0P_SCS_CID1

System Control Space ROM Table Component ID #1

Address: 0xE000EFF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

2.1.50 CM0P_SCS_CID2

System Control Space ROM Table Component ID #2

Address: 0xE000EFF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

2.1.51 CM0P_SCS_CID3

System Control Space ROM Table Component ID #3

Address: 0xE000EFFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

2.1.52 CM0P_ROM_SCS

CM0+ CoreSight ROM Table Peripheral #0

Address: 0xE00FF000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to SCS ROM Table Default Value: 4293980163

2.1.53 CM0P_ROM_DWT

CM0+ CoreSight ROM Table Peripheral #1

Address: 0xE00FF004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to DWT ROM Table Default Value: 4293926915

2.1.54 CM0P_ROM_BPU

CM0+ CoreSight ROM Table Peripheral #2

Address: 0xE00FF008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to BPU ROM Table Default Value: 4293931011

2.1.55 CM0P_ROM_END

CM0+ CoreSight ROM Table End Marker

Address: 0xE00FF00C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	End marker in peripheral list Default Value: 0

2.1.56 CM0P_ROM_CSMT

CM0+ CoreSight ROM Table Memory Type

Address: 0xE00FFFCC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Memory Type Default Value: 1

2.1.57 CM0P_ROM_PID4

CM0+ CoreSight ROM Table Peripheral ID #4

Address: 0xE00FFFD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

2.1.58 CM0P_ROM_PID0

CM0+ CoreSight ROM Table Peripheral ID #0

Address: 0xE00FFFE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 192

2.1.59 CM0P_ROM_PID1

CM0+ CoreSight ROM Table Peripheral ID #1

Address: 0xE00FFFE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 180

2.1.60 CM0P_ROM_PID2

CM0+ CoreSight ROM Table Peripheral ID #2

Address: 0xE00FFFE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

2.1.61 CM0P_ROM_PID3

CM0+ CoreSight ROM Table Peripheral ID #3

Address: 0xE00FFFEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

2.1.62 CM0P_ROM_CID0

CM0+ CoreSight ROM Table Component ID #0

Address: 0xE00FFFF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

2.1.63 CM0P_ROM_CID1

CM0+ CoreSight ROM Table Component ID #1

Address: 0xE00FFFF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 16

2.1.64 CM0P_ROM_CID2

CM0+ CoreSight ROM Table Component ID #2

Address: 0xE00FFFF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

2.1.65 CM0P_ROM_CID3

CM0+ CoreSight ROM Table Component ID #3

Address: 0xE00FFFFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

3 TCPWM - Individual Counter (CNT) Registers

This section discusses the CNT registers. It lists all the registers in mapping tables, in address order.

3.1 Register Details

Register Name	Address
TCPWM_CNT0_CTRL	0x40010100
TCPWM_CNT0_STATUS	0x40010104
TCPWM_CNT0_COUNTER	0x40010108
TCPWM_CNT0_CC	0x4001010C
TCPWM_CNT0_CC_BUFF	0x40010110
TCPWM_CNT0_PERIOD	0x40010114
TCPWM_CNT0_PERIOD_BUFF	0x40010118
TCPWM_CNT0_TR_CTRL0	0x40010120
TCPWM_CNT0_TR_CTRL1	0x40010124
TCPWM_CNT0_TR_CTRL2	0x40010128
TCPWM_CNT0_INTR	0x40010130
TCPWM_CNT0_INTR_SET	0x40010134
TCPWM_CNT0_INTR_MASK	0x40010138
TCPWM_CNT0_INTR_MASKED	0x4001013C
TCPWM_CNT1_CTRL	0x40010140
TCPWM_CNT1_STATUS	0x40010144
TCPWM_CNT1_COUNTER	0x40010148
TCPWM_CNT1_CC	0x4001014C
TCPWM_CNT1_CC_BUFF	0x40010150
TCPWM_CNT1_PERIOD	0x40010154
TCPWM_CNT1_PERIOD_BUFF	0x40010158
TCPWM_CNT1_TR_CTRL0	0x40010160
TCPWM_CNT1_TR_CTRL1	0x40010164
TCPWM_CNT1_TR_CTRL2	0x40010168
TCPWM_CNT1_INTR	0x40010170
TCPWM_CNT1_INTR_SET	0x40010174
TCPWM_CNT1_INTR_MASK	0x40010178

Register Name	Address
TCPWM_CNT1_INTR_MASKED	0x4001017C
TCPWM_CNT2_CTRL	0x40010180
TCPWM_CNT2_STATUS	0x40010184
TCPWM_CNT2_COUNTER	0x40010188
TCPWM_CNT2_CC	0x4001018C
TCPWM_CNT2_CC_BUFF	0x40010190
TCPWM_CNT2_PERIOD	0x40010194
TCPWM_CNT2_PERIOD_BUFF	0x40010198
TCPWM_CNT2_TR_CTRL0	0x400101A0
TCPWM_CNT2_TR_CTRL1	0x400101A4
TCPWM_CNT2_TR_CTRL2	0x400101A8
TCPWM_CNT2_INTR	0x400101B0
TCPWM_CNT2_INTR_SET	0x400101B4
TCPWM_CNT2_INTR_MASK	0x400101B8
TCPWM_CNT2_INTR_MASKED	0x400101BC
TCPWM_CNT3_CTRL	0x400101C0
TCPWM_CNT3_STATUS	0x400101C4
TCPWM_CNT3_COUNTER	0x400101C8
TCPWM_CNT3_CC	0x400101CC
TCPWM_CNT3_CC_BUFF	0x400101D0
TCPWM_CNT3_PERIOD	0x400101D4
TCPWM_CNT3_PERIOD_BUFF	0x400101D8
TCPWM_CNT3_TR_CTRL0	0x400101E0
TCPWM_CNT3_TR_CTRL1	0x400101E4
TCPWM_CNT3_TR_CTRL2	0x400101E8
TCPWM_CNT3_INTR	0x400101F0
TCPWM_CNT3_INTR_SET	0x400101F4
TCPWM_CNT3_INTR_MASK	0x400101F8
TCPWM_CNT3_INTR_MASKED	0x400101FC
TCPWM_CNT4_CTRL	0x40010200
TCPWM_CNT4_STATUS	0x40010204
TCPWM_CNT4_COUNTER	0x40010208
TCPWM_CNT4_CC	0x4001020C
TCPWM_CNT4_CC_BUFF	0x40010210
TCPWM_CNT4_PERIOD	0x40010214
TCPWM_CNT4_PERIOD_BUFF	0x40010218
TCPWM_CNT4_TR_CTRL0	0x40010220
TCPWM_CNT4_TR_CTRL1	0x40010224
TCPWM_CNT4_TR_CTRL2	0x40010228
TCPWM_CNT4_INTR	0x40010230
TCPWM_CNT4_INTR_SET	0x40010234
TCPWM_CNT4_INTR_MASK	0x40010238

Register Name	Address
TCPWM_CNT4_INTR_MASKED	0x4001023C
TCPWM_CNT5_CTRL	0x40010240
TCPWM_CNT5_STATUS	0x40010244
TCPWM_CNT5_COUNTER	0x40010248
TCPWM_CNT5_CC	0x4001024C
TCPWM_CNT5_CC_BUFF	0x40010250
TCPWM_CNT5_PERIOD	0x40010254
TCPWM_CNT5_PERIOD_BUFF	0x40010258
TCPWM_CNT5_TR_CTRL0	0x40010260
TCPWM_CNT5_TR_CTRL1	0x40010264
TCPWM_CNT5_TR_CTRL2	0x40010268
TCPWM_CNT5_INTR	0x40010270
TCPWM_CNT5_INTR_SET	0x40010274
TCPWM_CNT5_INTR_MASK	0x40010278
TCPWM_CNT5_INTR_MASKED	0x4001027C
TCPWM_CNT6_CTRL	0x40010280
TCPWM_CNT6_STATUS	0x40010284
TCPWM_CNT6_COUNTER	0x40010288
TCPWM_CNT6_CC	0x4001028C
TCPWM_CNT6_CC_BUFF	0x40010290
TCPWM_CNT6_PERIOD	0x40010294
TCPWM_CNT6_PERIOD_BUFF	0x40010298
TCPWM_CNT6_TR_CTRL0	0x400102A0
TCPWM_CNT6_TR_CTRL1	0x400102A4
TCPWM_CNT6_TR_CTRL2	0x400102A8
TCPWM_CNT6_INTR	0x400102B0
TCPWM_CNT6_INTR_SET	0x400102B4
TCPWM_CNT6_INTR_MASK	0x400102B8
TCPWM_CNT6_INTR_MASKED	0x400102BC
TCPWM_CNT7_CTRL	0x400102C0
TCPWM_CNT7_STATUS	0x400102C4
TCPWM_CNT7_COUNTER	0x400102C8
TCPWM_CNT7_CC	0x400102CC
TCPWM_CNT7_CC_BUFF	0x400102D0
TCPWM_CNT7_PERIOD	0x400102D4
TCPWM_CNT7_PERIOD_BUFF	0x400102D8
TCPWM_CNT7_TR_CTRL0	0x400102E0
TCPWM_CNT7_TR_CTRL1	0x400102E4
TCPWM_CNT7_TR_CTRL2	0x400102E8
TCPWM_CNT7_INTR	0x400102F0
TCPWM_CNT7_INTR_SET	0x400102F4
TCPWM_CNT7_INTR_MASK	0x400102F8

Register Name	Address
TCPWM_CNT7_INTR_MASKED	0x400102FC

Register Name	Address
TCPWM_CNT0_CTRL	0x40010100
TCPWM_CNT0_STATUS	0x40010104
TCPWM_CNT0_COUNTER	0x40010108
TCPWM_CNT0_CC	0x4001010C
TCPWM_CNT0_CC_BUFF	0x40010110
TCPWM_CNT0_PERIOD	0x40010114
TCPWM_CNT0_PERIOD_BUFF	0x40010118
TCPWM_CNT0_TR_CTRL0	0x40010120
TCPWM_CNT0_TR_CTRL1	0x40010124
TCPWM_CNT0_TR_CTRL2	0x40010128
TCPWM_CNT0_INTR	0x40010130
TCPWM_CNT0_INTR_SET	0x40010134
TCPWM_CNT0_INTR_MASK	0x40010138
TCPWM_CNT0_INTR_MASKED	0x4001013C
TCPWM_CNT1_CTRL	0x40010140
TCPWM_CNT1_STATUS	0x40010144
TCPWM_CNT1_COUNTER	0x40010148
TCPWM_CNT1_CC	0x4001014C
TCPWM_CNT1_CC_BUFF	0x40010150
TCPWM_CNT1_PERIOD	0x40010154
TCPWM_CNT1_PERIOD_BUFF	0x40010158
TCPWM_CNT1_TR_CTRL0	0x40010160
TCPWM_CNT1_TR_CTRL1	0x40010164
TCPWM_CNT1_TR_CTRL2	0x40010168
TCPWM_CNT1_INTR	0x40010170
TCPWM_CNT1_INTR_SET	0x40010174
TCPWM_CNT1_INTR_MASK	0x40010178
TCPWM_CNT1_INTR_MASKED	0x4001017C
TCPWM_CNT2_CTRL	0x40010180
TCPWM_CNT2_STATUS	0x40010184
TCPWM_CNT2_COUNTER	0x40010188
TCPWM_CNT2_CC	0x4001018C
TCPWM_CNT2_CC_BUFF	0x40010190
TCPWM_CNT2_PERIOD	0x40010194
TCPWM_CNT2_PERIOD_BUFF	0x40010198
TCPWM_CNT2_TR_CTRL0	0x400101A0
TCPWM_CNT2_TR_CTRL1	0x400101A4
TCPWM_CNT2_TR_CTRL2	0x400101A8
TCPWM_CNT2_INTR	0x400101B0
TCPWM_CNT2_INTR_SET	0x400101B4

Register Name	Address
TCPWM_CNT2_INTR_MASK	0x400101B8
TCPWM_CNT2_INTR_MASKED	0x400101BC
TCPWM_CNT3_CTRL	0x400101C0
TCPWM_CNT3_STATUS	0x400101C4
TCPWM_CNT3_COUNTER	0x400101C8
TCPWM_CNT3_CC	0x400101CC
TCPWM_CNT3_CC_BUFF	0x400101D0
TCPWM_CNT3_PERIOD	0x400101D4
TCPWM_CNT3_PERIOD_BUFF	0x400101D8
TCPWM_CNT3_TR_CTRL0	0x400101E0
TCPWM_CNT3_TR_CTRL1	0x400101E4
TCPWM_CNT3_TR_CTRL2	0x400101E8
TCPWM_CNT3_INTR	0x400101F0
TCPWM_CNT3_INTR_SET	0x400101F4
TCPWM_CNT3_INTR_MASK	0x400101F8
TCPWM_CNT3_INTR_MASKED	0x400101FC
TCPWM_CNT4_CTRL	0x40010200
TCPWM_CNT4_STATUS	0x40010204
TCPWM_CNT4_COUNTER	0x40010208
TCPWM_CNT4_CC	0x4001020C
TCPWM_CNT4_CC_BUFF	0x40010210
TCPWM_CNT4_PERIOD	0x40010214
TCPWM_CNT4_PERIOD_BUFF	0x40010218
TCPWM_CNT4_TR_CTRL0	0x40010220
TCPWM_CNT4_TR_CTRL1	0x40010224
TCPWM_CNT4_TR_CTRL2	0x40010228
TCPWM_CNT4_INTR	0x40010230
TCPWM_CNT4_INTR_SET	0x40010234
TCPWM_CNT4_INTR_MASK	0x40010238
TCPWM_CNT4_INTR_MASKED	0x4001023C
TCPWM_CNT5_CTRL	0x40010240
TCPWM_CNT5_STATUS	0x40010244
TCPWM_CNT5_COUNTER	0x40010248
TCPWM_CNT5_CC	0x4001024C
TCPWM_CNT5_CC_BUFF	0x40010250
TCPWM_CNT5_PERIOD	0x40010254
TCPWM_CNT5_PERIOD_BUFF	0x40010258
TCPWM_CNT5_TR_CTRL0	0x40010260
TCPWM_CNT5_TR_CTRL1	0x40010264
TCPWM_CNT5_TR_CTRL2	0x40010268
TCPWM_CNT5_INTR	0x40010270
TCPWM_CNT5_INTR_SET	0x40010274

Register Name	Address
TCPWM_CNT5_INTR_MASK	0x40010278
TCPWM_CNT5_INTR_MASKED	0x4001027C
TCPWM_CNT6_CTRL	0x40010280
TCPWM_CNT6_STATUS	0x40010284
TCPWM_CNT6_COUNTER	0x40010288
TCPWM_CNT6_CC	0x4001028C
TCPWM_CNT6_CC_BUFF	0x40010290
TCPWM_CNT6_PERIOD	0x40010294
TCPWM_CNT6_PERIOD_BUFF	0x40010298
TCPWM_CNT6_TR_CTRL0	0x400102A0
TCPWM_CNT6_TR_CTRL1	0x400102A4
TCPWM_CNT6_TR_CTRL2	0x400102A8
TCPWM_CNT6_INTR	0x400102B0
TCPWM_CNT6_INTR_SET	0x400102B4
TCPWM_CNT6_INTR_MASK	0x400102B8
TCPWM_CNT6_INTR_MASKED	0x400102BC
TCPWM_CNT7_CTRL	0x400102C0
TCPWM_CNT7_STATUS	0x400102C4
TCPWM_CNT7_COUNTER	0x400102C8
TCPWM_CNT7_CC	0x400102CC
TCPWM_CNT7_CC_BUFF	0x400102D0
TCPWM_CNT7_PERIOD	0x400102D4
TCPWM_CNT7_PERIOD_BUFF	0x400102D8
TCPWM_CNT7_TR_CTRL0	0x400102E0
TCPWM_CNT7_TR_CTRL1	0x400102E4
TCPWM_CNT7_TR_CTRL2	0x400102E8
TCPWM_CNT7_INTR	0x400102F0
TCPWM_CNT7_INTR_SET	0x400102F4
TCPWM_CNT7_INTR_MASK	0x400102F8
TCPWM_CNT7_INTR_MASKED	0x400102FC

3.1.1 TCPWM_CNT0_CTRL

Counter control register

Address: 0x40010100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.1 TCPWM_CNT0_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.1 TCPWM_CNT0_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.2 TCPWM_CNT0_STATUS

Counter status register

Address: 0x40010104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.3 TCPWM_CNT0_COUNTER

Counter count register

Address: 0x40010108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.4 TCPWM_CNT0_CC

Counter compare/capture register

Address: 0x4001010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.5 TCPWM_CNT0_CC_BUFF

Counter buffered compare/capture register

Address: 0x40010110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.6 TCPWM_CNT0_PERIOD

Counter period register

Address: 0x40010114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.7 TCPWM_CNT0_PERIOD_BUFF

Counter buffered period register

Address: 0x40010118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.8 TCPWM_CNT0_TR_CTRL0

Counter trigger control register 0

Address: 0x40010120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.8 TCPWM_CNT0_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.9 TCPWM_CNT0_TR_CTRL1

Counter trigger control register 1

Address: 0x40010124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.9 TCPWM_CNT0_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.10 TCPWM_CNT0_TR_CTRL2

Counter trigger control register 2

Address: 0x40010128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.10 TCPWM_CNT0_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.11 TCPWM_CNT0_INTR

Interrupt request register.

Address: 0x40010130

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.12 TCPWM_CNT0_INTR_SET

Interrupt set request register.

Address: 0x40010134

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.13 TCPWM_CNT0_INTR_MASK

Interrupt mask register.

Address: 0x40010138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.14 TCPWM_CNT0_INTR_MASKED

Interrupt masked request register

Address: 0x4001013C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3.1.15 TCPWM_CNT1_CTRL

Counter control register

Address: 0x40010140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.15 TCPWM_CNT1_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.15 TCPWM_CNT1_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.16 TCPWM_CNT1_STATUS

Counter status register

Address: 0x40010144

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.17 TCPWM_CNT1_COUNTER

Counter count register

Address: 0x40010148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.18 TCPWM_CNT1_CC

Counter compare/capture register

Address: 0x4001014C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.19 TCPWM_CNT1_CC_BUFF

Counter buffered compare/capture register

Address: 0x40010150

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.20 TCPWM_CNT1_PERIOD

Counter period register

Address: 0x40010154

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.21 TCPWM_CNT1_PERIOD_BUFF

Counter buffered period register

Address: 0x40010158

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.22 TCPWM_CNT1_TR_CTRL0

Counter trigger control register 0

Address: 0x40010160

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.22 TCPWM_CNT1_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.23 TCPWM_CNT1_TR_CTRL1

Counter trigger control register 1

Address: 0x40010164

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.23 TCPWM_CNT1_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.24 TCPWM_CNT1_TR_CTRL2

Counter trigger control register 2

Address: 0x40010168

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.24 TCPWM_CNT1_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.25 TCPWM_CNT1_INTR

Interrupt request register.

Address: 0x40010170

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.26 TCPWM_CNT1_INTR_SET

Interrupt set request register.

Address: 0x40010174

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.27 TCPWM_CNT1_INTR_MASK

Interrupt mask register.

Address: 0x40010178

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.28 TCPWM_CNT1_INTR_MASKED

Interrupt masked request register

Address: 0x4001017C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3.1.29 TCPWM_CNT2_CTRL

Counter control register

Address: 0x40010180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.29 TCPWM_CNT2_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.29 TCPWM_CNT2_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.30 TCPWM_CNT2_STATUS

Counter status register

Address: 0x40010184

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.31 TCPWM_CNT2_COUNTER

Counter count register

Address: 0x40010188

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.32 TCPWM_CNT2_CC

Counter compare/capture register

Address: 0x4001018C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.33 TCPWM_CNT2_CC_BUFF

Counter buffered compare/capture register

Address: 0x40010190

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.34 TCPWM_CNT2_PERIOD

Counter period register

Address: 0x40010194

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.35 TCPWM_CNT2_PERIOD_BUFF

Counter buffered period register

Address: 0x40010198

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.36 TCPWM_CNT2_TR_CTRL0

Counter trigger control register 0

Address: 0x400101A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.36 TCPWM_CNT2_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.37 TCPWM_CNT2_TR_CTRL1

Counter trigger control register 1

Address: 0x400101A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.37 TCPWM_CNT2_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.38 TCPWM_CNT2_TR_CTRL2

Counter trigger control register 2

Address: 0x400101A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.38 TCPWM_CNT2_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.39 TCPWM_CNT2_INTR

Interrupt request register.

Address: 0x400101B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.40 TCPWM_CNT2_INTR_SET

Interrupt set request register.

Address: 0x400101B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.41 TCPWM_CNT2_INTR_MASK

Interrupt mask register.

Address: 0x400101B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.42 TCPWM_CNT2_INTR_MASKED

Interrupt masked request register

Address: 0x400101BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3.1.43 TCPWM_CNT3_CTRL

Counter control register

Address: 0x400101C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.43 TCPWM_CNT3_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.43 TCPWM_CNT3_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.44 TCPWM_CNT3_STATUS

Counter status register

Address: 0x400101C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.45 TCPWM_CNT3_COUNTER

Counter count register

Address: 0x400101C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.46 TCPWM_CNT3_CC

Counter compare/capture register

Address: 0x400101CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.47 TCPWM_CNT3_CC_BUFF

Counter buffered compare/capture register

Address: 0x400101D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.48 TCPWM_CNT3_PERIOD

Counter period register

Address: 0x400101D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.49 TCPWM_CNT3_PERIOD_BUFF

Counter buffered period register

Address: 0x400101D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.50 TCPWM_CNT3_TR_CTRL0

Counter trigger control register 0

Address: 0x400101E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.50 TCPWM_CNT3_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.51 TCPWM_CNT3_TR_CTRL1

Counter trigger control register 1

Address: 0x400101E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.51 TCPWM_CNT3_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.52 TCPWM_CNT3_TR_CTRL2

Counter trigger control register 2

Address: 0x400101E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.52 TCPWM_CNT3_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.53 TCPWM_CNT3_INTR

Interrupt request register.

Address: 0x400101F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.54 TCPWM_CNT3_INTR_SET

Interrupt set request register.

Address: 0x400101F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.55 TCPWM_CNT3_INTR_MASK

Interrupt mask register.

Address: 0x400101F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.56 TCPWM_CNT3_INTR_MASKED

Interrupt masked request register

Address: 0x400101FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3.1.57 TCPWM_CNT4_CTRL

Counter control register

Address: 0x40010200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.57 TCPWM_CNT4_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.57 TCPWM_CNT4_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.58 TCPWM_CNT4_STATUS

Counter status register

Address: 0x40010204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.59 TCPWM_CNT4_COUNTER

Counter count register

Address: 0x40010208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.60 TCPWM_CNT4_CC

Counter compare/capture register

Address: 0x4001020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.61 TCPWM_CNT4_CC_BUFF

Counter buffered compare/capture register

Address: 0x40010210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.62 TCPWM_CNT4_PERIOD

Counter period register

Address: 0x40010214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.63 TCPWM_CNT4_PERIOD_BUFF

Counter buffered period register

Address: 0x40010218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.64 TCPWM_CNT4_TR_CTRL0

Counter trigger control register 0

Address: 0x40010220

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.64 TCPWM_CNT4_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.65 TCPWM_CNT4_TR_CTRL1

Counter trigger control register 1

Address: 0x40010224

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.65 TCPWM_CNT4_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.66 TCPWM_CNT4_TR_CTRL2

Counter trigger control register 2

Address: 0x40010228

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.66 TCPWM_CNT4_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.67 TCPWM_CNT4_INTR

Interrupt request register.

Address: 0x40010230

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.68 TCPWM_CNT4_INTR_SET

Interrupt set request register.

Address: 0x40010234

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.69 TCPWM_CNT4_INTR_MASK

Interrupt mask register.

Address: 0x40010238

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.70 TCPWM_CNT4_INTR_MASKED

Interrupt masked request register

Address: 0x4001023C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3.1.71 TCPWM_CNT5_CTRL

Counter control register

Address: 0x40010240

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.71 TCPWM_CNT5_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.71 TCPWM_CNT5_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.72 TCPWM_CNT5_STATUS

Counter status register

Address: 0x40010244

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.73 TCPWM_CNT5_COUNTER

Counter count register

Address: 0x40010248

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.74 TCPWM_CNT5_CC

Counter compare/capture register

Address: 0x4001024C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.75 TCPWM_CNT5_CC_BUFF

Counter buffered compare/capture register

Address: 0x40010250

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.76 TCPWM_CNT5_PERIOD

Counter period register

Address: 0x40010254

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.77 TCPWM_CNT5_PERIOD_BUFF

Counter buffered period register

Address: 0x40010258

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.78 TCPWM_CNT5_TR_CTRL0

Counter trigger control register 0

Address: 0x40010260

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.78 TCPWM_CNT5_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.79 TCPWM_CNT5_TR_CTRL1

Counter trigger control register 1

Address: 0x40010264

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.79 TCPWM_CNT5_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.80 TCPWM_CNT5_TR_CTRL2

Counter trigger control register 2

Address: 0x40010268

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.80 TCPWM_CNT5_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.81 TCPWM_CNT5_INTR

Interrupt request register.

Address: 0x40010270

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.82 TCPWM_CNT5_INTR_SET

Interrupt set request register.

Address: 0x40010274

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.83 TCPWM_CNT5_INTR_MASK

Interrupt mask register.

Address: 0x40010278

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.84 TCPWM_CNT5_INTR_MASKED

Interrupt masked request register

Address: 0x4001027C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3.1.85 TCPWM_CNT6_CTRL

Counter control register

Address: 0x40010280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.85 TCPWM_CNT6_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.85 TCPWM_CNT6_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.86 TCPWM_CNT6_STATUS

Counter status register

Address: 0x40010284

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.87 TCPWM_CNT6_COUNTER

Counter count register

Address: 0x40010288

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.88 TCPWM_CNT6_CC

Counter compare/capture register

Address: 0x4001028C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.89 TCPWM_CNT6_CC_BUFF

Counter buffered compare/capture register

Address: 0x40010290

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.90 TCPWM_CNT6_PERIOD

Counter period register

Address: 0x40010294

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.91 TCPWM_CNT6_PERIOD_BUFF

Counter buffered period register

Address: 0x40010298

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.92 TCPWM_CNT6_TR_CTRL0

Counter trigger control register 0

Address: 0x400102A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.92 TCPWM_CNT6_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.93 TCPWM_CNT6_TR_CTRL1

Counter trigger control register 1

Address: 0x400102A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.93 TCPWM_CNT6_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.94 TCPWM_CNT6_TR_CTRL2

Counter trigger control register 2

Address: 0x400102A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.94 TCPWM_CNT6_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.95 TCPWM_CNT6_INTR

Interrupt request register.

Address: 0x400102B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.96 TCPWM_CNT6_INTR_SET

Interrupt set request register.

Address: 0x400102B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.97 TCPWM_CNT6_INTR_MASK

Interrupt mask register.

Address: 0x400102B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.98 TCPWM_CNT6_INTR_MASKED

Interrupt masked request register

Address: 0x400102BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3.1.99 TCPWM_CNT7_CTRL

Counter control register

Address: 0x400102C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

3.1.99 TCPWM_CNT7_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

3.1.99 TCPWM_CNT7_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

3.1.100 TCPWM_CNT7_STATUS

Counter status register

Address: 0x400102C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

3.1.101 TCPWM_CNT7_COUNTER

Counter count register

Address: 0x400102C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

3.1.102 TCPWM_CNT7_CC

Counter compare/capture register

Address: 0x400102CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

3.1.103 TCPWM_CNT7_CC_BUFF

Counter buffered compare/capture register

Address: 0x400102D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

3.1.104 TCPWM_CNT7_PERIOD

Counter period register

Address: 0x400102D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

3.1.105 TCPWM_CNT7_PERIOD_BUFF

Counter buffered period register

Address: 0x400102D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

3.1.106 TCPWM_CNT7_TR_CTRL0

Counter trigger control register 0

Address: 0x400102E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

3.1.106 TCPWM_CNT7_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

3.1.107 TCPWM_CNT7_TR_CTRL1

Counter trigger control register 1

Address: 0x400102E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

3.1.107 TCPWM_CNT7_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

3.1.108 TCPWM_CNT7_TR_CTRL2

Counter trigger control register 2

Address: 0x400102E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

3.1.108 TCPWM_CNT7_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

3.1.109 TCPWM_CNT7_INTR

Interrupt request register.

Address: 0x400102F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

3.1.110 TCPWM_CNT7_INTR_SET

Interrupt set request register.

Address: 0x400102F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

3.1.111 TCPWM_CNT7_INTR_MASK

Interrupt mask register.

Address: 0x400102F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

3.1.112 TCPWM_CNT7_INTR_MASKED

Interrupt masked request register

Address: 0x400102FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

4 CPU Sub System (CPUSS) Registers

This section discusses the CPUSS registers. It lists all the registers in mapping tables, in address order.

4.1 Register Details

Register Name	Address
CPUSS_SYSREQ	0x40100004
CPUSS_SYSARG	0x40100008
CPUSS_FLASH_CTL	0x40100030
CPUSS_ROM_CTL	0x40100034
CPUSS_RAM_CTL	0x40100038
CPUSS_DMAC_CTL	0x4010003C
CPUSS_SL_CTL0	0x40100100
CPUSS_SL_CTL1	0x40100104

4.1.1 CPUSS_SYSREQ

SYSCALL control register

Address: 0x40100004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	SYSCALL_COMMAND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	SYSCALL_COMMAND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	R	R	RW	RW	None		
HW Access	R	A	RW	A	R	None		
Name	SYSCALL_REQ	HMASTER_0	ROM_ACCESS_EN	PRIVI-LEGED	DIS_RESET_VECT_REL	None [26:24]		

Bits	Name	Description
31	SYSCALL_REQ	CPU/DAP writes a '1' to this field to request a SystemCall. The HMASTER_0 field indicates the source of the write access. Setting this field to '1' immediate results in a NMI. The SystemCall NMI interrupt handler sets this field to '0' after servicing the request. Default Value: 0
30	HMASTER_0	Indicates the source of the write access to the SYSREQ register. '0': CPU write access. '1': DAP write access. HW sets this field when the SYSREQ register is written to and SYSCALL_REQ is '0' (the last time it is set is when SW sets SYSCALL_REQ from '0' to '1'). Default Value: 0
29	ROM_ACCESS_EN	Indicates that executing from Boot ROM is enabled. HW sets this field to '1', on reset or when the SystemCall NMI vector is fetched from Boot ROM. HW sets this field to '0', when the CPU is NOT executing from either Boot or System ROM. This bit is used for debug purposes only. Default Value: 1

4.1.1 CPUSS_SYSREQ (continued)

28	PRIVILEGED	Indicates whether the system is in privileged ('1') or user mode ('0'). Only CPU SW executing from ROM can set this field to '1' when ROM_ACCESS_EN is '1' (the CPU is executing a SystemCall NMI interrupt handler). Any other write to this field sets it to '0'. Default Value: 1
27	DIS_RESET_VECT_REL	Disable Reset Vector fetch relocation: '0': CPU accesses to locations 0x0000:0000 - 0x0000:0007 are redirected to ROM. '1': CPU accesses to locations 0x0000:0000 - 0x0000:0007 are made to flash. Note that this field defaults to '0' on reset, ensuring actual reset vector fetches are always made to ROM. Note that this field does not affect DAP accesses. Default Value: 0
15 : 0	SYSCALL_COMMAND	Opcode of the system call being requested. Default Value: 0

4.1.2 CPUSS_SYSARG

SYSARG control register

Address: 0x40100008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [31:24]							

Bits	Name	Description
31 : 0	SYSCALL_ARG	Argument to System Call specified in SYSREQ. Semantics of argument depends on system call made. Typically a pointer to a parameter block. Default Value: 0

4.1.3 CPUSS_FLASH_CTL

FLASH control register

Address: 0x40100030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			PREF_EN	None [3:2]		FLASH_WS [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW1C
Name	None [15:9]							FLASH_INVALIDATE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU has priority "1": DW/DMA has priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0
8	FLASH_INVALIDATE	1': Invalidates the content of the flash controller's buffers. Default Value: 0
4	PREF_EN	Prefetch enable: '0': disabled. This is a desirable seeting when FLASH_WS is "0" or when predictable execution behavior is required. '1': enabled. Default Value: 0

4.1.3 CPUSS_FLASH_CTL (continued)

1 : 0	FLASH_WS	Amount of ROM wait states: "0": 0 wait states (fast flash: [0, 24] MHz system frequency, slow flash: [0, 16] MHz system frequency) "1": 1 wait state (fast flash: [24, 48] MHz system frequency, slow flash: [16, 32] MHz system frequency) "2": 2 wait states (slow flash: [32, 48] MHz system frequency) "3": undefined Default Value: 0

4.1.4 CPUSS_ROM_CTL

ROM control register

Address: 0x40100034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							ROM_WS

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	ROM_WS	Amount of ROM wait states: '0': 0 wait state '1': 1 wait state Default Value: 0

4.1.5 CPUSS_RAM_CTL

RAM control register

Address: 0x40100038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU has priority "1": DW/DMA has priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

4.1.6 CPUSS_DMAC_CTL

DMA controller register

Address: 0x4010003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU has priority "1": DW/DMA has priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

4.1.7 CPUSS_SL_CTL0

Slave control register

Address: 0x40100100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU priority "1": DMA priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

4.1.8 CPUSS_SL_CTL1

Slave control register

Address: 0x40100104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU priority "1": DMA priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

5 CapSense Sigma Delta (CSD) Registers

This section discusses the CSD registers. It lists all the registers in mapping tables, in address order.

5.1 Register Details

Register Name	Address
CSD_CONFIG	0x400C0000
CSD_SPARE	0x400C0004
CSD_STATUS	0x400C0080
CSD_STAT_SEQ	0x400C0084
CSD_STAT_CNTS	0x400C0088
CSD_RESULT_VAL1	0x400C00D0
CSD_RESULT_VAL2	0x400C00D4
CSD_ADC_RES	0x400C00E0
CSD_INTR	0x400C00F0
CSD_INTR_SET	0x400C00F4
CSD_INTR_MASK	0x400C00F8
CSD_INTR_MASKED	0x400C00FC
CSD_HSCMP	0x400C0180
CSD_AMBUF	0x400C0184
CSD_REFGEN	0x400C0188
CSD_CSDCMP	0x400C018C
CSD_IDACA	0x400C01C0
CSD_IDACB	0x400C01C4
CSD_SW_RES	0x400C01F0
CSD_SENSE_PERIOD	0x400C0200
CSD_SENSE_DUTY	0x400C0204
CSD_SW_HS_P_SEL	0x400C0280
CSD_SW_HS_N_SEL	0x400C0284
CSD_SW_SHIELD_SEL	0x400C0288
CSD_SW_AMUXBUF_SEL	0x400C0290
CSD_SW_BYP_SEL	0x400C0294
CSD_SW_CMP_P_SEL	0x400C02A0

Register Name	Address
CSD_SW_CMP_N_SEL	0x400C02A4
CSD_SW_REFGEN_SEL	0x400C02A8
CSD_SW_FW_MOD_SEL	0x400C02B0
CSD_SW_FW_TANK_SEL	0x400C02B4
CSD_SW_DSI_SEL	0x400C02C0
CSD_SEQ_TIME	0x400C0300
CSD_SEQ_INIT_CNT	0x400C0310
CSD_SEQ_NORM_CNT	0x400C0314
CSD_ADC_CTL	0x400C0320
CSD_SEQ_START	0x400C0340
CSD_TRIM_CTRL	0x400C0F00

5.1.1 CSD_CONFIG

Configuration and Control

Address: 0x400C0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None			
HW Access	None	R			None			
Name	None	FILTER_DELAY [6:4]			None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW	None	RW	None		RW	
HW Access	None	R	None	R	None		R	
Name	None	CHARGE_MODE	None	SENSE_EN	None [11:10]		SHIELD_DELAY [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW	RW	None	
HW Access	None				R	R	None	
Name	None [23:20]				CSX_DUAL_CNT	MUTUAL_CAP	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None		RW	RW	RW	RW
HW Access	R	R	None		R	R	R	R
Name	ENABLE	LP_MODE	None [29:28]		DSI_SENSE_EN	SAMPLE_SYNC	DSI_SAMPLE_EN	DSI_COUNT_SEL

Bits	Name	Description
31	ENABLE	Enables CapSense block. 0: All CapSense components will be OFF and switches will be open 1: All CapSense components will be ON and switches will be controlled by firmware or the Sequencer Default Value: 0
30	LP_MODE	Selects power mode for the CSD components (REFGEN, AMBUF, CSDCMP, HSCMP): 0: High Power mode 1: Low Power mode Default Value: 0
27	DSI_SENSE_EN	Enables the use of the dsi_sense_in input instead of the internally generated clock to drive SenseClk and ShieldClk signals. This bit is not applicable for PSoC Analog Coprocessor. 1: SenseClk is driven directly by DSI 0: SenseClk is driven by PRS/divide-by-2/DIRECT_CLOCK Default Value: 0

5.1.1 CSD_CONFIG (continued)

26	SAMPLE_SYNC	Enables double synchronizing of sample input from DSI (only relevant when DSI_SAMPLE_EN=1). This bit is not applicable for PSoC Analog Coprocessor. Default Value: 1
25	DSI_SAMPLE_EN	Enables the use of the dsi_sample_in input instead of the comparator output to strobe COUNTER. This bit is not applicable for PSoC Analog Coprocessor. 0: Counter will count the samples generated by CSD modulator 1: Counter will count the samples generated by DSI Default Value: 0
24	DSI_COUNT_SEL	Select dsi_count bus signal. This bit is not applicable for PSoC Analog Coprocessor. Default Value: 0 **0x0: CSD_RESULT:** Depending on the dsi_count_val_sel input either output RESULT_VAL1.VALUE (0) or RESULT_VAL2.VALUE (1) on the dsi_count bus. Note that dsi_count_val_sel is not synchronized, i.e. it controls the mux combinatorially. **0x1: ADC_RESULT:** Output ADC_RES.VIN_CNT on the dsi_count bus.
19	CSX_DUAL_CNT	Enables the use of two counters for MUTUAL cap sensing mode (CSX), do not use when MUTUAL_CAP=0. Default Value: 0 **0x0: ONE:** Use one counter for both phases (source and sink). **0x1: TWO:** Use two counters, separate count for when SenseClk is high and when SenseClk is low.
18	MUTUAL_CAP	Selects self-cap or mutual cap mode of operation. 0: Self-Capacitiance mode 1: Mutual-Capacitance mode Default Value: 0 **0x0: SELFCAP:** Enables Self-cap mode **0x1: MUTUALCAP:** Enables Mutual-cap mode
14	CHARGE_MODE	Enables charging of the Cmod/Csh_tank capacitor using the GPIO digital output buffer. Default Value: 0 **0x0: CHARGE_OFF:** Cmod/Csh_tank capacitor is precharged through CSD internal switches. **0x1: CHARGE_IO:** Use csd_charge to enable the GPIO Driver to charge capacitor. The capacitor must be sensed with HSCMP using the appropriate switches (HMPM or HMPT).
12	SENSE_EN	Enables the sense modulator output. 0: all switches, static or dynamic, are open and IDAC in CSD mode is off 1: switches and IDAC can be closed/on as per MMIO setting and CSD sequencer. Default Value: 0
9 : 8	SHIELD_DELAY	Configures the delay between ShieldClk and SenseClk signal. Default Value: 0 **0x0: OFF:** Delay line is off; SenseClk = shield clock **0x1: D5NS:** Shield clock is delayed by 5ns delay with respect to sensor clock

5.1.1 CSD_CONFIG (continued)

		0x2: D10NS: Shield clock is delayed by 10ns delay with respect to sensor clock **0x3: D20NS:** Shield clock is delayed by 20ns delay with respect to sensor clock
6 : 4	FILTER_DELAY	Enables digital filtering on the CSD comparator output. When set to 0 the digital filter is off. When set to any other value the digital filter ignores the output of CSDCOMP for FILTER_DELAY (SampleClk) cycles after the start of each measurement and from the first comparator trip to the end of each measurement. Default Value: 0

5.1.2 CSD_SPARE

Spare MMIO

Address: 0x400C0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				RW			
Name	None [7:4]				SPARE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SPARE	Spare MMIO Default Value: 0

5.1.3 CSD_STATUS

Status Register

Address: 0x400C0080

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				RW	RW	RW	RW
Name	None [7:4]				CSDCMP_OUT	HSCMP_OUT	CSD_SENSE	CSD_CHARGE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	CSDCMP_OUT	This field is used to monitor the output status of CSDCOMP. Default Value: 0
2	HSCMP_OUT	This field is used to monitor the output status of HSCOMP. Default Value: 0 **0x0: C_LT_VREF:** Vin < Vref **0x1: C_GT_VREF:** Vin > Vref
1	CSD_SENSE	This field is used to monitor the status of SenseClk signal. Default Value: 0
0	CSD_CHARGE	This field is used to monitor the status of Cmod/Ctank capacitors during charging/discharging by the GPIO pin. Default Value: 0

5.1.4 CSD_STAT_SEQ

Current Sequencer status

Address: 0x400C0084

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R		
HW Access	None					RW		
Name	None [7:3]					SEQ_STATE [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					R		
HW Access	None					RW		
Name	None [23:19]					ADC_STATE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18 : 16	ADC_STATE	Specifies ADC sequencer current state (only relevant after SEQ_STATE has reached SAMPLE_NORM and ADC sequencer has started). Default Value: 0
2 : 0	SEQ_STATE	Specifes CSD sequencer current state. Default Value: 0

5.1.5 CSD_STAT_CNTS

Current status counts

Address: 0x400C0088

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	NUM_CONV [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	NUM_CONV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	NUM_CONV	Specifies the current number of conversions remaining when in Sample_* states. This counter is also used in AutoZero* states to count the remaining AutoZero cycles. Default Value: 0

5.1.6 CSD_RESULT_VAL1

Result CSD/CSX accumulation counter value 1

Address: 0x400C00D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	BAD_CONVS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BAD_CONVS	Number of 'bad' conversion for which the CSD comparator did not trigger within the normal time window, either because Vref was not crossed at all, or if the Vref was already crossed before the window started. This counter is reset when the sequencer is started and will saturate at 255 when more than 255 conversions are bad. Default Value: 0
15 : 0	VALUE	Specifies the raw count value for current conversion. In case of mutual-capacitance measurement and if dual counter is enabed, this counter counts only when SenseClk is high. Default Value: 0

5.1.7 CSD_RESULT_VAL2

Result CSX accumulation counter value 2

Address: 0x400C00D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	VALUE	Specifies the raw count value of second counter when mutual capacitance measurement with dual counter is enabled. This counter counts only when SenseClk is low. Default Value: 0

5.1.8 CSD_ADC_RES

ADC measurement

Address: 0x400C00E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VIN_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	VIN_CNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							RW
Name	None [23:17]							HSCMP_POL

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	RW	RW	None					
Name	ADC_ABORT	ADC_OVERFLOW	None [29:24]					

Bits	Name	Description
31	ADC_ABORT	This flag is set when the ADC sequencer was aborted before tripping HSCMP. Default Value: 0
30	ADC_OVERFLOW	This flag is set when the ADC counter overflows. This is an indication to the firmware that the IDACB current level is too low. Default Value: 0
16	HSCMP_POL	Polarity used for IDACB for the last ADC result. 0: IDACB was in source mode 1: IDACB was in sink mode Default Value: 0
15 : 0	VIN_CNT	Specifies ADC counter value. The ADC counter value is equal to the time required to charge/discharge CREF1 and CREF2 capacitors from Vin to Vref. Default Value: 0

5.1.9 CSD_INTR

CSD Interrupt Request Register

Address: 0x400C00F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1C	RW1C	None
HW Access	None					RW1S	RW1S	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							RW1S
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	Interrupt register for ADC sequencer. This bit is set when ADC sequencer completes either calibration or input voltage measurement. Default Value: 0
2	INIT	Interrupt register for CSD sequencer. This bit is set when coarse initialization or sample initialization is complete. Default Value: 0
1	SAMPLE	Interrupt register for CSD sequencer. This bit is set when the normal sample state is complete. Default Value: 0

5.1.10 CSD_INTR_SET

CSD Interrupt set register

Address: 0x400C00F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1S	RW1S	None
HW Access	None					A	A	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1S
HW Access	None							A
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	This register when set to '1' asserts an interrupt for software debugging. Default Value: 0
2	INIT	This register when set to '1' asserts an interrupt for software debugging. Default Value: 0
1	SAMPLE	This register when set to '1' asserts an interrupt for software debugging. Default Value: 0

5.1.11 CSD_INTR_MASK

CSD Interrupt mask register

Address: 0x400C00F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	None
HW Access	None					R	R	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	Mask bit for corresponding bit in INTR register. Default Value: 0
2	INIT	Mask bit for corresponding bit in INTR register. Default Value: 0
1	SAMPLE	Mask bit for corresponding bit in INTR register. Default Value: 0

5.1.12 CSD_INTR_MASKED

CSD Interrupt masked register

Address: 0x400C00FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R	R	None
HW Access	None					W	W	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	Logical 'AND' of corresponding request and mask bits. Default Value: 0
2	INIT	Logical 'AND' of corresponding request and mask bits. Default Value: 0
1	SAMPLE	Logical 'AND' of corresponding request and mask bits. Default Value: 0

5.1.13 CSD_HSCMP

High Speed Comparator configuration

Address: 0x400C0180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [7:5]			HSCMP_INVERT	None [3:1]			HSCMP_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	AZ_EN	None [30:24]						

Bits	Name	Description
31	AZ_EN	Enables or Disables Auto-Zero for HSCOMP. 0: Disable AutoZero 1: Enable AutoZero Default Value: 0
4	HSCMP_INVERT	Inverts the output of HSCMP before it is used to control switches and the CSD sequencer. This bit does not affect the ADC sequencer or the STATUS.HSCMP_OUT. Default Value: 0
0	HSCMP_EN	Enables or Disables HSCOMP. Default Value: 0 **0x0: OFF:** HSCOMP is disabled. **0x1: ON:** HSCOMP is enabled. CONFIG.LP_MODE determines the power mode level.

5.1.14 CSD_AMBUF

Reference Generator configuration

Address: 0x400C0184

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	PWR_MODE	This field specifies the AMUXBUFFER power level. Default Value: 0 **0x0: OFF:** AMUXBUFFER is disabled. **0x1: NORM:** AMUXBUFFER is enabled. CONFIG.LP_MODE determines the power mode level. **0x2: HI:** Enable AMUX buffer. Power level can be configured as high or low power depending on CONFIG.LP_MODE.

5.1.15 CSD_REFGEN

Reference Generator configuration

Address: 0x400C0188

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None			RW
HW Access	None	R	R	R	None			R
Name	None	RES_EN	VDDA_EN	BYPASS	None [3:1]			REFGEN_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			GAIN [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	RW	None		RW				
HW Access	R	None		R				
Name	VREFLO_INT	None [22:21]		VREFLO_SEL [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	VREFLO_INT	This field selects the output of the resistor string tap to either Vreflo or Vreflo_int. 0: Output of resistor string is Vreflo 1: Output of resistor string is Vreflo_int Default Value: 0
20 : 16	VREFLO_SEL	Selects resistor string tap for Vreflo/Vreflo_int. 0: minimum vout 31: maximum vout = vrefhi (only works if the resistor string is enabled; RES_EN=1) Default Value: 0
12 : 8	GAIN	Specifies resistor string tap for feedback. 0: minimum vout 31: maximum vout = vrefhi -> gain=1 Default Value: 0
6	RES_EN	Enables or Disables resistor string. 0: Open switch on top of the resistor string (Vreflo=Vssa). 1: Connect VREFHI to the resistor string. Default Value: 0

5.1.15 CSD_REFGEN (continued)

5	VDDA_EN	This field when set closes Vdda switch to top of resistor string. Default Value: 0
4	BYPASS	This field when set bypasses the selected input reference unbuffered to Vrefhi. Default Value: 0
0	REFGEN_EN	Enables/Disables Reference Generator (REFGEN). Default Value: 0 **0x0: OFF:** REFGEN is disabled. **0x1: ON:** REFGEN is enabled. CONFIG.LP_MODE determines the power mode level.

5.1.16 CSD_CSDCMP

CSD Comparator configuration

Address: 0x400C018C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		None			RW
HW Access	None		R		None			R
Name	None [7:6]		POLARITY_SEL [5:4]		None [3:1]			CSDCMP_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						CMP_PHASE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW	None			
HW Access	R	None	R	R	None			
Name	AZ_EN	None	FEEDBACK_MODE	CMP_MODE	None [27:24]			

Bits	Name	Description
31	AZ_EN	Enables or Disables Auto-Zero for CSDCOMP. 0: Disable AutoZero 1: Enable AutoZero Default Value: 0
29	FEEDBACK_MODE	This field controls whether the direct output from CSDCOMP or the flopped version of CSD-COMP is used for CapSense operations. The selected signal controls the IDAC(s) during CapSense operation and in general purpose mode the signal goes out on the dsi_sample_out. Default Value: 0 **0x0: FLOP:** Use feedback from sampling flip-flop (used in most modes). **0x1: COMP:** Use feedback from comparator directly.
28	CMP_MODE	Selects which signal to output on dsi_sample_out. This field is not applicable for PSoC 4000S. Default Value: 0

5.1.16 CSD_CSDCMP (continued)

		0x0: CSD: CSD mode: Outputs the filtered sample signal on dsi_sample_out. **0x1: GP:** General Purpose mode: Outputs the unfiltered sample, unfiltered comparator output, either asynchronous or flopped.
9 : 8	CMP_PHASE	This field is used to select in what phase(s) the CSDCOMP is active. This field also determines when a bad conversion is detected i.e. at the beginning and/or at the end of the comparator active phase. Default Value: 0 **0x0: FULL:** Comparator is active from start of Phi2 and kept active into Phi1. This mode is used for regular self-cap scanning. **0x1: PHI1:** Comparator is active during Phi1 only. This mode is not used currently. **0x2: PHI2:** Comparator is active during Phi2 only. This mode is used for low-EMI scanning. **0x3: PHI1_2:** Comparator is activated at the start of both Phi1 and Phi2 (non-overlap should be enabled). This mode is used for mutual-cap sensing.
5 : 4	POLARITY_SEL	This field selects which IDAC polarity to use to detect CSDCMP triggering. Default Value: 0 **0x0: IDACA_POL:** Use idaca_pol (firmware setting with CSX and optionally DSI mixed in) to determine the direction, this is the most common use-case, used for normal CSD and normal CSX **0x1: IDACB_POL:** Use idacb_pol (firmware setting with optional DSI mixed in) to determine the direction, this is only used for normal CSD if IDACB is used i.s.o. IDACA (not common) **0x2: DUAL_POL:** Use the expression (SenseClk? idaca_pol : idacb_pol) to determine the direction, this is only useful for the CSX with DUAL_IDAC use-case
0	CSDCMP_EN	This field is used to enable or disable CSD Comparator. Default Value: 0 **0x0: OFF:** Disable CSDCOMP. **0x1: ON:** Enable CSDCOMP. CONFIG.LP_MODE determines the power mode level.

5.1.17 CSD_IDACA

IDACA Configuration

Address: 0x400C01C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW						
HW Access	R	R						
Name	POL_DYN	VAL [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [15:12]				BAL_MODE [11:10]		POLARITY [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW	None	RW		RW	
HW Access	R		R	None	R		R	
Name	RANGE [23:22]		DSI_CTRL_EN	None	LEG2_MODE [19:18]		LEG1_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						LEG2_EN	LEG1_EN

Bits	Name	Description
25	LEG2_EN	Output enable for leg 2 to CSDBUSA Default Value: 0
24	LEG1_EN	Output enable for leg 1 to CSDBUSA Default Value: 0
23 : 22	RANGE	IDAC multiplier Default Value: 0 **0x0: IDAC_LO:** 1 LSB = 37.5 nA **0x1: IDAC_MED:** 1 LSB = 300 nA **0x2: IDAC_HI:** 1 LSB = 2400 nA

5.1.17 CSD_IDACA (continued)

21	DSI_CTRL_EN	Mix DSI inputs with MMIO controls or not (before getting mixed with CSD controls if enabled). 0: no DSI control IDACA_POLARITY = IDACA.POLARITY IDACA_LEG1_EN = IDACA.LEG1_EN IDACA_LEG2_EN = IDACA.LEG2_EN 1: Mix MMIO with DSI control IDACA_POLARITY = IDACA.POLARITY EXOR dsi_idaca_pol IDACA_LEG1_EN = IDACA.LEG1_EN AND dsi_idaca_leg1_en IDACA_LEG2_EN = IDACA.LEG2_EN AND dsi_idaca_leg2_en Default Value: 0
19 : 18	LEG2_MODE	This fiels controls the usage mode of LEG2 Default Value: 0 **0x0: GP_STATIC:** General Purpose static mode: LEG2 is controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer. **0x1: GP:** General Purpose dynamic mode: LEG2 is controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled. **0x2: CSD_STATIC:** CSD static mode: LEG2 can only be ON when the CSD Sequencer is in the Sample_init or Sample_norm state. In those states LEG2 is controlled by LEG2_EN, SenseClk and the CSD configuration. Polarity is controlled by the CSD configuration and operation. In addition leg2 enable and polarity can optionally be mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer. **0x3: CSD:** CSD dynamic mode: LEG2 can only be ON when the CSD Sequencer is in the Sample_init or Sample_norm state. In those states LEG2 is controlled by LEG2_EN, the CSD configuration, SenseClk and the flopped CSDCMP output (CSDCMP_OUT_FF). In addition leg2 enable can optionally be mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled.
17 : 16	LEG1_MODE	This field controls the usage mode of LEG1 and the polarity bit. Default Value: 0 **0x0: GP_STATIC:** General Purpose static mode: LEG1 and POLARITY are controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer. **0x1: GP:** General Purpose dynamic mode: LEG1 and POLARITY are controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled. **0x2: CSD_STATIC:** CSD static mode: LEG1 can only be ON when the CSD Sequencer is in the Sample_init or Sample_norm state. In those states LEG1 is controlled by LEG1_EN, SenseClk and the CSD configuration. Polarity is controlled by the CSD configuration and operation. In addition leg1 enable and polarity can optionally be mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer.

5.1.17 CSD_IDACA (continued)

		0x3: CSD: CSD dynamic mode: LEG1 can only be ON when the CSD Sequencer is in the Sample_init or Sample_norm state. In thoses states LEG1 is controlled by LEG1_EN, the CSD configuration, SenseClk and the flopped CSDCMP output (CSDCMP_OUT_FF). Polarity is controlled by the CSD configuration and operation. In addition leg1 enable and polarity can optionally be mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled.
11 : 10	BAL_MODE	This field specified the duration for which IDAC is enabled. Default Value: 0
		0x0: FULL: IDAC is enabled from start of Phi2 until disabled by CSDCMP. This mode is used for regular self-cap scanning.
		0x1: PHI1: IDAC is enabled from start of Phi1 and disabled by CSDCMP or at the end of Phi1. This mode is used for mutual-cap sensing with dual IDAC.
		0x2: PHI2: IDAC is enabled from start of Phi2 and disabled by CSDCMP or at end of Phi2. This mode is used for Low EMI self-cap scanning or mutual-cap scanning with dual IDAC.
		0x3: PHI1_2: IDAC is enabled from start of both Phi1 and Phi2 and disabled by CSDCMP or at end of Phi1 or Phi2 (if non-overlap enabled). This mode is not currently used.
9 : 8	POLARITY	Selects the polarity of the IDAC (sensing operation). Normally, the actual polarity depends on this bit and is optionally mixed with DSI (DSI_CTRL_EN) and CSD configuration(LEG1_MODE==CSD). However, in mutual-cap mode with one IDAC (config.mutual_cap=1 & config.csx_dual_idac=0) the polarity of the IDAC is controlled by SenseClk. Default Value: 0
		0x0: VSSA_SRC: IDAC sources current.
		0x1: VDDA_SNK: IDAC sinks current.
		0x2: SENSE: The polarity of the IDAC will follow the SenseClk signal (POL_DYN bit should be set). The intended usage is for CSX using a single IDAC.
		0x3: SENSE_INV: The polarity of the IDAC will follow the inverted SenseClk signal (POL_DYN bit should be set). The intended usage is for CSX using a single IDAC.
7	POL_DYN	This field specifies IDAC polarity. Default Value: 0
		0x0: STATIC: IDAC polarity is static. Polarity is expected to be stable, so to save power this avoids the shunting of the unused polarity, at the expense of response time.
		0x1: DYNAMIC: Dynamic polarity. Polarity is expected to change frequently (e.g. invert after every SenseClk phase), so to improve response time this keeps the shunt of the unused polarity on at the expense of power.
6 : 0	VAL	Current value setting for this IDAC (7 bits). Default Value: 0

5.1.18 CSD_IDACB

IDACB Configuration

Address: 0x400C01C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW						
HW Access	R	R						
Name	POL_DYN	VAL [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [15:12]				BAL_MODE [11:10]		POLARITY [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW	None	RW		RW	
HW Access	R		R	None	R		R	
Name	RANGE [23:22]		DSI_CTRL_EN	None	LEG2_MODE [19:18]		LEG1_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [31:27]					LEG3_EN	LEG2_EN	LEG1_EN

Bits	Name	Description
26	LEG3_EN	Output enable for leg 3 to CSDBUSC, only allowed when RANGE = IDAC_LO. When this bit is set, other legs should be OFF. Note that leg 3 can only be used for ADC mode, not GP mode. Which means that leg 3 can only be on when the ADC Sequencer is in the ADC_measure or Calib_measure state. In those states leg 3 is controlled by the ADC configuration and the HSCMP output. In addition this leg 3 enable bit can optionally be mixed with DSI (see DSI_CTRL_EN). When LEG3_EN=1 also the IDACB polarity is controlled by the ADC sequencer. Default Value: 0
25	LEG2_EN	Output enable for leg 2 to CSDBUSB or CSDBUSA Default Value: 0
24	LEG1_EN	Output enable for leg 1 to CSDBUSB or CSDBUSA Default Value: 0
23 : 22	RANGE	IDAC multiplier Default Value: 0 **0x0: IDAC_LO:** 1 LSB = 37.5 nA

5.1.18 CSD_IDACB (continued)

		0x1: IDAC_MED: 1 LSB = 300 nA **0x2: IDAC_HI:** 1 LSB = 2400 nA
21	DSI_CTRL_EN	Mix DSI inputs with MMIO controls or not (before getting mixed with CSD controls if enabled) 0: no DSI control IDACB_POLARITY = IDACB.POLARITY IDACB_LEG1_EN = IDACB.LEG1_EN IDACB_LEG2_EN = IDACB.LEG2_EN IDACB_LEG3_EN = IDACB.LEG3_EN 1: Mix MMIO with DSI control IDACB_POLARITY = IDACB.POLARITY EXOR dsi_idacb_pol IDACB_LEG1_EN = IDACB.LEG1_EN AND dsi_idacb_leg1_en IDACB_LEG2_EN = IDACB.LEG2_EN AND dsi_idacb_leg2_en IDACB_LEG3_EN = IDACB.LEG3_EN AND dsi_idacb_leg3_en Default Value: 0
19 : 18	LEG2_MODE	Controls the usage mode of LEG2 Default Value: 0 **0x0: GP_STATIC:** same as corresponding IDACA.LEG2_MODE **0x1: GP:** same as corresponding IDACA.LEG2_MODE **0x2: CSD_STATIC:** same as corresponding IDACA.LEG2_MODE **0x3: CSD:** same as corresponding IDACA.LEG2_MODE
17 : 16	LEG1_MODE	Controls the usage mode of LEG1 and the Polarity bit Default Value: 0 **0x0: GP_STATIC:** same as corresponding IDACA.LEG1_MODE **0x1: GP:** same as corresponding IDACA.LEG1_MODE **0x2: CSD_STATIC:** same as corresponding IDACA.LEG1_MODE **0x3: CSD:** same as corresponding IDACA.LEG1_MODE
11 : 10	BAL_MODE	same as corresponding IDACA Balancing mode Default Value: 0 **0x0: FULL:** same as corresponding IDACA Balancing mode **0x1: PHI1:** same as corresponding IDACA Balancing mode **0x2: PHI2:** same as corresponding IDACA Balancing mode **0x3: PHI1_2:** same as corresponding IDACA Balancing mode

5.1.18 CSD_IDACB (continued)

9 : 8	POLARITY	Selects the polarity of the IDAC (sensing operation). Normally the actual polarity depends on this bit and is optionally mixed with DSI (see DSI_CTRL_EN) and with the CSD configuration (if LEG1_EN=1 and LEG1_MODE=CSD) and operation. In mutual cap modethe polarity of the IDAC is controlled by SenseClk. If LEG3_EN=1 (the other two legs must be off) then the ADC sequencer controls the IDACB polarity and is optionally mixed with DSI. Default Value: 0 **0x0: VSSA_SRC:** IDAC will source current. **0x1: VDDA_SNK:** IDAC will sink current. **0x2: SENSE:** The polarity of the IDAC will follow the SenseClk signal (POL_DYN bit should be set too). The intended usage is for mutual-cap sensing using a single IDAC. **0x3: SENSE_INV:** The polarity of the IDAC will follow the inverted SenseClk signal (POL_DYN bit should be set too). The intended usage is for mutual-cap sensing using a single IDAC.
7	POL_DYN	This field specifies IDAC polarity. Default Value: 0 **0x0: STATIC:** Static polarity. Polarity is expected to be stable, so to save power this avoids the shunting of the unused polarity, at the expense of response time. **0x1: DYNAMIC:** Dynamic polarity. Polarity is expected to change frequently (e.g. invert after every SenseClk phase), so to improve response time this keeps the shunt of the unused polarity on at the expense of power.
6 : 0	VAL	Current value setting for this IDAC (7 bits). Default Value: 0

5.1.19 CSD_SW_RES

Switch Resistance configuration

Address: 0x400C01F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	RES_HCBG [7:6]		RES_HCBV [5:4]		RES_HCAG [3:2]		RES_HCAV [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [23:20]				RES_F2PT [19:18]		RES_F1PM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 18	RES_F2PT	Selects resistance for the corresponding switch Default Value: 0
17 : 16	RES_F1PM	Selects resistance or low EMI for the corresponding switch Default Value: 0 **0x0: LOW:** Low **0x1: MED:** Medium **0x2: HIGH:** High **0x3: RESERVED:** Reserved
7 : 6	RES_HCBG	Selects resistance or low EMI for the corresponding switch Default Value: 0
5 : 4	RES_HCBV	Selects resistance or low EMI for the corresponding switch Default Value: 0

5.1.19 CSD_SW_RES (continued)

3 : 2	RES_HCAG	Selects resistance or low EMI for the corresponding switch Default Value: 0
1 : 0	RES_HCAV	Selects resistance or low EMI (slow ramp) for the HCAV switch. Default Value: 0 **0x0: LOW:** Low **0x1: MED:** Medium **0x2: HIGH:** High **0x3: LOWEMI:** Low EMI

5.1.20 CSD_SENSE_PERIOD

Sense clock period

Address: 0x400C0200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SENSE_DIV [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SENSE_DIV [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				None	RW		
HW Access	R				None	R		
Name	LFSR_SCALE [23:20]				None	LFSR_SIZE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW1S
HW Access	None						R	RW1C
Name	None [31:26]						SEL_LFSR_MSB	LFSR_CLEAR

Bits	Name	Description
25	SEL_LFSR_MSB	Use the MSB of configured LSFR size as SenseClk signal. Intended to be used only with bit 8 or 12-bit LFSR size for generating PRS SenseClk. Default Value: 0
24	LFSR_CLEAR	This field when set, forces the LFSR to it's initial state (all ones). This bit is automatically cleared by hardware after the LFSR is cleared, which is at the next SampleClk positive edge. This bit should be set whenever the LFSR is used. Note that the LFSR will also get reset to all ones during the AutoZero_1/2 states. Default Value: 0
23 : 20	LFSR_SCALE	This field specifies the left shift value by which the LFSR output is scaled before adding to SENSE_DIV. This dithering is disabled when SEL_LSFR_MSB is set. The clock divider to be used = (SENSE_DIV+1) + (SEL_LSFR_MSB ? 0 : (LFSR_OUT<_SCALE)). Note that the clock divider including the dithering term must fit in 12 bits, otherwise the result is undefined. Default Value: 0

5.1.20 CSD_SENSE_PERIOD (continued)

18 : 16	LFSR_SIZE	This field selects the number of bits to be used in the LSFR to provide the clock dithering variation on the base period. Whenever the LFSR is used (non zero value in this field) the LFSR_CLEAR bit should also be set. Default Value: 0 **0x0: OFF:** Don't use clock dithering (=spreadspectrum) (LFSR output value is zero) **0x1: 2B:** 2-bit LFSR (G(x)=X^2+X+1, period= 3), range [-1, 1] **0x2: 3B:** 3-bit LFSR (G(x)=X^3+X+1, period= 7), range [-3, 3] **0x3: 4B:** 4-bit LFSR (G(x)=X^4+X+1, period= 15), range [-7, 7] **0x4: 5B:** 5-bit LFSR (G(x)=X^5+X^2+1, period= 31), range [-15, 15] **0x5: 8B:** 8-bit LFSR (G(x)=X^8+X^4+X^3+X^2+1, period= 255) **0x6: 12B:** 12-bit LFSR (G(x)=X^12+X^9+X^3+X^2+1, period=4095)
11 : 0	SENSE_DIV	This field specifies the period of SenseClk interms of SampleClk period. The value in this register is the base divider. If clock dithering is enabled, the actual period changes depending on the LFSR value. Default Value: 0

5.1.21 CSD_SENSE_DUTY

Sense clock duty cycle

Address: 0x400C0204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SENSE_WIDTH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SENSE_WIDTH [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW	RW	None	RW
HW Access	None				R	R	None	R
Name	None [23:20]				OVERLAP_PHI2	OVERLAP_PHI1	None	SENSE_POL

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	OVERLAP_PHI2	Same as OVERLAP_PHI1 but for Phi2 (csd_sense=1). Default Value: 0
18	OVERLAP_PHI1	This field specifies whether Ph1 signal is non-overlapping signal or 'NOT' of SenseClk. 0: Non-overlap for Phi1, the Phi1 signal is SenseClk inverted except that the signal goes low 1 SampleClk before SenseClk goes high. This mode is used for low EMI sensing and mutual-cap sensing with static GPIO. 1: Overlap for Phi1, the Phi1 signal is csd_sense inverted. This mode is used for normal self-cap sensing with GPIO switching. The GPIO internal circuit ensures that the switches are non-overlapping. Default Value: 0
16	SENSE_POL	This field specifies the polarity of the SenseClk 0 = start with low phase (Regular Self-cap scanning) 1 = start with high phase Default Value: 0

5.1.21 CSD_SENSE_DUTY (continued)

11 : 0	SENSE_WIDTH	This field defines the length of the first phase of the SenseClk in terms of SampleClk cycles. A value of 0 disables this feature and the duty cycle of SenseClk will be 50%, which is equal to SENSE_WIDTH = (SENSE_DIV+1)/2, or when clock dithering is used that becomes [(SENSE_DIV+1) + (LFSR_OUT << LSFR_SCALE)]/2. At all times it must be assured that the phases are at least 2 SampleClk cycles (1 for non overlap), if this rule is violated the result is undefined. Default Value: 0

5.1.22 CSD_SW_HS_P_SEL

HSCMP Pos input switch Waveform selection

Address: 0x400C0280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [7:5]			SW_HMPT	None [3:1]			SW_HMPM

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [15:13]			SW_HMMA	None [11:9]			SW_HMPS

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_HMCA	None [19:17]			SW_HMMB

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_HMRH	None [27:25]			SW_HMCB

Bits	Name	Description
28	SW_HMRH	This field controls the corresponding switch Default Value: 0
24	SW_HMCB	This field controls the corresponding switch Default Value: 0
20	SW_HMCA	This field controls the corresponding switch Default Value: 0
16	SW_HMMB	This field controls the corresponding switch Default Value: 0
12	SW_HMMA	This field controls the corresponding switch Default Value: 0
8	SW_HMPS	This field controls the corresponding switch Default Value: 0
4	SW_HMPT	This field controls the corresponding switch Default Value: 0

5.1.22 CSD_SW_HS_P_SEL (continued)

0	SW_HMPM	This field controls the corresponding switch 0: static open 1: static closed Default Value: 0

5.1.23 CSD_SW_HS_N_SEL

HSCMP Neg input switch Waveform selection

Address: 0x400C0284

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_HCCD	None [19:17]			SW_HCCC

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_HCRL [30:28]			None	SW_HCRH [26:24]		

Bits	Name	Description
30 : 28	SW_HCRL	Select waveform for corresponding switch Default Value: 0
26 : 24	SW_HCRH	Selects waveform for corresponding switch 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0
20	SW_HCCD	This field controls the corresponding switch Default Value: 0
16	SW_HCCC	This field controls the corresponding switch 0: static open 1: static closed Default Value: 0

5.1.24 CSD_SW_SHIELD_SEL

Shielding switches Waveform selection

Address: 0x400C0288

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_HCAG [6:4]			None	SW_HCAV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_HCBG [14:12]			None	SW_HCBV [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_HCCG	None [19:17]			SW_HCCV

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20	SW_HCCG	Set corresponding switch If the ADC is enabled then this switch is directly controlled by the ADC sequencer. Default Value: 0
16	SW_HCCV	Set corresponding switch Default Value: 0
14 : 12	SW_HCBG	Select waveform for corresponding switch Default Value: 0
10 : 8	SW_HCBV	Select waveform for corresponding switch Default Value: 0
6 : 4	SW_HCAG	Select waveform for corresponding switch Default Value: 0

5.1.24 CSD_SW_SHIELD_SEL (continued)

2 : 0	SW_HCAV	Selects waveform for corresponding switch 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0

5.1.25 CSD_SW_AMUXBUF_SEL

Amuxbuffer switches Waveform selection

Address: 0x400C0290

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			
HW Access	None			R	None			
Name	None [7:5]			SW_IRBY	None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [15:13]			SW_ICA	None [11:9]			SW_IRLB

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [23:21]			SW_IRLI	None	SW_ICB [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_IRL	None [27:25]			SW_IRH

Bits	Name	Description
28	SW_IRL	This field controls the corresponding switch Default Value: 0
24	SW_IRH	This field controls the corresponding switch Default Value: 0
20	SW_IRLI	This field controls the corresponding switch Default Value: 0
18 : 16	SW_ICB	Selects waveform for corresponding switch 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0
12	SW_ICA	This field controls the corresponding switch Default Value: 0

5.1.25 CSD_SW_AMUXBUF_SEL (continued)

8	SW_IRLB	This field controls the corresponding switch Default Value: 0
4	SW_IRBY	This field controls the corresponding switch 0: static open 1: static closed Default Value: 0

5.1.26 CSD_SW_BYP_SEL

AMUXBUS bypass switches Waveform selection

Address: 0x400C0294

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None			
HW Access	None			R	None			
Name	None [15:13]			SW_BYA	None [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_CBCC	None [19:17]			SW_BYB

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20	SW_CBCC	This field controls the corresponding switch. If the ADC is enabled then this switch is directly controlled by the ADC sequencer. Default Value: 0
16	SW_BYB	This field controls the corresponding switch. 0: static open 1: static closed Default Value: 0
12	SW_BYA	This field controls the corresponding switch. 0: static open 1: static closed Default Value: 0

5.1.27 CSD_SW_CMP_P_SEL

CSDCMP Pos Switch Waveform selection

Address: 0x400C02A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_SFPT [6:4]			None	SW_SFPM [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [15:13]			SW_SFMA	None	SW_SFPS [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_SFCA	None [19:17]			SW_SFMB

Bits	31	30	29	28	27	26	25	24
SW Access	None							RW
HW Access	None							R
Name	None [31:25]							SW_SFCB

Bits	Name	Description
24	SW_SFCB	This field controls the corresponding switch. Default Value: 0
20	SW_SFCA	This field controls the corresponding switch. Default Value: 0
16	SW_SFMB	This field controls the corresponding switch. Default Value: 0
12	SW_SFMA	This field controls the corresponding switch. 0: static open 1: static closed Default Value: 0
10 : 8	SW_SFPS	Selects waveform for corresponding switch Default Value: 0
6 : 4	SW_SFPT	Selects waveform for corresponding switch Default Value: 0

5.1.27 CSD_SW_CMP_P_SEL (continued)

2 : 0	SW_SFPM	Selects waveform for corresponding switch 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0

5.1.28 CSD_SW_CMP_N_SEL

CSDCMP Neg Switch Waveform selection

Address: 0x400C02A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_SCRL [30:28]			None	SW_SCRH [26:24]		

Bits	Name	Description
30 : 28	SW_SCRL	Selects waveform for corresponding switch Default Value: 0
26 : 24	SW_SCRH	Selects waveform for corresponding switch 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0

5.1.29 CSD_SW_REFGEN_SEL

Reference Generator Switch Waveform selection

Address: 0x400C02A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [7:5]			SW_IBCB	None [3:1]			SW_IAIB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							SW_SGMB

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_SGR	None [27:25]			SW_SGRE

Bits	Name	Description
28	SW_SGR	This field controls the corresponding switch. Default Value: 0
24	SW_SGRE	This field controls the corresponding switch. Default Value: 0
16	SW_SGMB	This field controls the corresponding switch. Default Value: 0
4	SW_IBCB	This field controls the corresponding switch. Default Value: 0
0	SW_IAIB	This field controls the corresponding switch. 0: static open 1: static closed Default Value: 0

5.1.30 CSD_SW_FW_MOD_SEL

Full Wave Cmod Switch Waveform selection

Address: 0x400C02B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							SW_F1PM

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:11]					SW_F1MA [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [23:21]			SW_C1CC	None	SW_F1CA [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_C1F1	None [27:25]			SW_C1CD

Bits	Name	Description
28	SW_C1F1	This field controls the corresponding switch. Default Value: 0
24	SW_C1CD	This field controls the corresponding switch. Default Value: 0
20	SW_C1CC	This field controls the corresponding switch. Default Value: 0
18 : 16	SW_F1CA	Selects waveform for corresponding switch Default Value: 0
10 : 8	SW_F1MA	Selects waveform for corresponding switch 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0

5.1.30 CSD_SW_FW_MOD_SEL (continued)

0	SW_F1PM	This field controls the corresponding switch. 0: static open 1: static closed Default Value: 0

5.1.31 CSD_SW_FW_TANK_SEL

Full Wave Csh_tank Switch Waveform selection

Address: 0x400C02B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			
HW Access	None			R	None			
Name	None [7:5]			SW_F2PT	None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_F2CA [14:12]			None	SW_F2MA [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [23:21]			SW_C2CC	None	SW_F2CB [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_C2F2	None [27:25]			SW_C2CD

Bits	Name	Description
28	SW_C2F2	This field controls the corresponding switch. Default Value: 0
24	SW_C2CD	This field controls the corresponding switch. Default Value: 0
20	SW_C2CC	This field controls the corresponding switch. Default Value: 0
18 : 16	SW_F2CB	Selects waveform for corresponding switch Default Value: 0
14 : 12	SW_F2CA	Selects waveform for corresponding switch Default Value: 0

5.1.31 CSD_SW_FW_TANK_SEL (continued)

10 : 8	SW_F2MA	Selects waveform for corresponding switch 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0
4	SW_F2PT	This field controls the corresponding switch. 0: static open 1: static closed Default Value: 0

5.1.32 CSD_SW_DSI_SEL

DSI output switch control Waveform selection

Address: 0x400C02C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	DSI_CMOD [6:4]			None	DSI_CSH_TANK [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 4	DSI_CMOD	This field select waveform for dsi_cmod signal. This field is not applicable for PSoC Analog Co-processor. Default Value: 0
2 : 0	DSI_CSH_TANK	This field selects waveform for dsi_csh_tank signal. This field is not applicable for PSoC Analog Coprocessor. Default Value: 0

5.1.33 CSD_SEQ_TIME

Sequencer Timing

Address: 0x400C0300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	AZ_TIME [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	AZ_TIME	This field specifies the AutoZero duration in terms of SenseClk cycles. Default Value: 0

5.1.34 CSD_SEQ_INIT_CNT

Sequencer Initial conversion and sample counts

Address: 0x400C0310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CONV_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CONV_CNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CONV_CNT	This field specifies the number of conversions per sample (i.e. duration of sensor scanning) during Sample_Init state. If set to 0, the Sample_init state will be skipped. Default Value: 0

5.1.35 CSD_SEQ_NORM_CNT

Sequencer Normal conversion and sample counts

Address: 0x400C0314

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CONV_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CONV_CNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CONV_CNT	This field specifies the number of conversions per sample (i.e. duraation of sensor scanning) during Sample_Norm state. If set to 0, the Sample_Norm state will be skipped. Default Value: 0

5.1.36 CSD_ADC_CTL

ADC Control

Address: 0x400C0320

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADC_TIME [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ADC_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ADC_MODE	Enables ADC measurement. When enabled the ADC sequencer will be started when the CSD sequencer goes to the SAMPLE_NORM state. Default Value: 0 **0x0: OFF:** No ADC measurement **0x1: VREF_CNT:** Count time A to bring Cref1 + Cref2 up from Vssa to Vrefhi with IDACB. **0x2: VREF_BY2_CNT:** Count time B to bring Cref1 + Cref2 back up to Vrefhi with IDACB (after bringing them down for time A/2 cycles with IDACB sinking). **0x3: VIN_CNT:** Determine HSCMP polarity and count time C to source/sink Cref1 + Cref2 from Vin to Vrefhi.
7 : 0	ADC_TIME	This field specifies the duration for which ADC captures the input voltage or discharges the CREF1 and CREF2 capacitors. The duration is specified interms of SenseClk cycles. Default Value: 0

5.1.37 CSD_SEQ_START

Sequencer start

Address: 0x400C0340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW1C	None	RW	RW1S
HW Access	None			R	A	None	R	RW1C
Name	None [7:5]			DSI_START_EN	ABORT	None	SEQ_MODE	START

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						AZ1_SKIP	AZ0_SKIP

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	AZ1_SKIP	This field enables or disables the AutoZero_1 state. 0: AutoZero_0 state is disabled 1: AutoZero_1 state is enabled Default Value: 0
8	AZ0_SKIP	This field enables or disables the AutoZero_0 state. 0: AutoZero_0 state is disabled 1: AutoZero_1 state is enabled Default Value: 0
4	DSI_START_EN	When this bit is set, a positive edge on dsi_start will start the CSD sequencer and if enabled also the ADC sequencer. This field is not applicable for PSoC Analog Coprocessor. Default Value: 0
3	ABORT	This field when set to '1' aborts the CSD and ADC sequencers operation and clears the START bit. This bit always read as 0. Default Value: 0

5.1.37 CSD_SEQ_START (continued)

1	SEQ_MODE	This field specifies the sequencer mode. 0: Regular CSD scan + optional ADC 1: Coarse initialization, the Sequencer will go to the INIT_COARSE state. Default Value: 0
0	START	This field when set to '1' starts the CSD sequencer. The sequencer will clear this bit when it is completes one cycle of operation. Default Value: 0

5.1.38 CSD_TRIM_CTRL

Trim control

Address: 0x400C0F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		None		RW	
HW Access	None		R		None		R	
Name	None [7:6]		DELAY_HYS [5:4]		None [3:2]		DELAY_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	DELAY_HYS	Hystersis input for Shield Delay block. Risk mitigation only; no test program or calpairs are needed for this Default Value: 2
1 : 0	DELAY_TRIM	Trim input for Shield Delay block. Risk mitigation only; no test program or calpairs are needed for this Default Value: 2

6 CTB Registers

This section discusses the CTB registers. It lists all the registers in mapping tables, in address order.

6.1 Register Details

Register Name	Address
CTB0_CTB_CTRL	0x40300000
CTB0_OA_RES0_CTRL	0x40300004
CTB0_OA_RES1_CTRL	0x40300008
CTB0_COMP_STAT	0x4030000C
CTB0_INTR	0x40300020
CTB0_INTR_SET	0x40300024
CTB0_INTR_MASK	0x40300028
CTB0_INTR_MASKED	0x4030002C
CTB0_OA0_SW	0x40300080
CTB0_OA0_SW_CLEAR	0x40300084
CTB0_OA1_SW	0x40300088
CTB0_OA1_SW_CLEAR	0x4030008C
CTB0_CTBBUS_SW	0x40300090
CTB0_CTBBUS_SW_CLEAR	0x40300094
CTB0_CTB_SW_HW_CTRL	0x403000C0
CTB0_CTB_SW_STATUS	0x403000C4
CTB0_OA0_OFFSET_TRIM	0x40300F00
CTB0_OA0_SLOPE_OFFSET_TRIM	0x40300F04
CTB0_OA0_COMP_TRIM	0x40300F08
CTB0_OA1_OFFSET_TRIM	0x40300F0C
CTB0_OA1_SLOPE_OFFSET_TRIM	0x40300F10
CTB0_OA1_COMP_TRIM	0x40300F14
CTB0_RMP_TRIM	0x40300F18
CTB1_CTB_CTRL	0x40310000
CTB1_OA_RES0_CTRL	0x40310004
CTB1_OA_RES1_CTRL	0x40310008
CTB1_COMP_STAT	0x4031000C

Register Name	Address
CTB1_INTR	0x40310020
CTB1_INTR_SET	0x40310024
CTB1_INTR_MASK	0x40310028
CTB1_INTR_MASKED	0x4031002C
CTB1_OA0_SW	0x40310080
CTB1_OA0_SW_CLEAR	0x40310084
CTB1_OA1_SW	0x40310088
CTB1_OA1_SW_CLEAR	0x4031008C
CTB1_CTBBUS_SW	0x40310090
CTB1_CTBBUS_SW_CLEAR	0x40310094
CTB1_CTB_SW_HW_CTRL	0x403100C0
CTB1_CTB_SW_STATUS	0x403100C4
CTB1_OA0_OFFSET_TRIM	0x40310F00
CTB1_OA0_SLOPE_OFFSET_TRIM	0x40310F04
CTB1_OA0_COMP_TRIM	0x40310F08
CTB1_OA1_OFFSET_TRIM	0x40310F0C
CTB1_OA1_SLOPE_OFFSET_TRIM	0x40310F10
CTB1_OA1_COMP_TRIM	0x40310F14
CTB1_RMP_TRIM	0x40310F18

6.1.1 CTB0_CTB_CTRL

global CTB and power control

Address: 0x40300000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				SPARE [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	ENABLED	DEEPSLEEP_ON	None [29:24]					

Bits	Name	Description
31	ENABLED	- 0: CTB disabled (put analog in power down, open all switches) - 1: CTB enabled Default Value: 0
30	DEEPSLEEP_ON	- 0: CTB disabled off during DeepSleep power mode - 1: CTB remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0
19 : 16	SPARE	Reserved bit Default Value: 0

6.1.2 CTB0_OA_RES0_CTRL

Opamp0 and resistor0 control

Address: 0x40300004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA0_DSI_LEVEL	OA0_DSI_BYPASS	OA0_HYST_EN	OA0_COMP_EN	None	OA0_DRIVE_STR_SEL	OA0_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA0_PUMP_EN	None	OA0_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	RW			
HW Access	None		R	R	R			
Name	None [23:22]		RES0_TAP_OVR	RES0_SWAP	RES0_TAP [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW			RW			
HW Access	R	R			R			
Name	VALID_SEL0_EN	VALID_SEL0 [30:28]			C0_FB [27:24]			

Bits	Name	Description
31	VALID_SEL0_EN	Enable UAB Valid selection (UAB mode), otherwise ignore UAB Valid. Note that enabling UAB Valid selection also disables DeepSleep comparator operation. Default Value: 0
30 : 28	VALID_SEL0	Select which UAB Valid to use to sample the comparator output. This should match the UAB analog output connected to this comparator. The comparator output gets sampled at the negative edge of the selected UAB Valid signal. 0=UAB0 half 0 Valid output 1=UAB0 half 1 Valid output Default Value: 0
27 : 24	C0_FB	Feed back Cap value Default Value: 0
21	RES0_TAP_OVR	1 - Override the control from hardware and close the switch connecting the resistor ladder tap point to the bottom of the ladder Default Value: 0

6.1.2 CTB0_OA_RES0_CTRL (continued)

20	RES0_SWAP	Swap Top and Bottom resistor value Default Value: 0
19 : 16	RES0_TAP	PGA gain (resistor tap point): 0= gain 1.0 (disconnects resistor) 1= gain 1.42 2= gain 2.0 3= gain 2.78 4= gain 4.0 5= gain 5.82 6= gain 8.0 7= gain 10.67 8= gain 16.0 9= gain 21.33 10= gain 32.0 Default Value: 0
11	OA0_PUMP_EN	Opamp0 pump enable Default Value: 0
9 : 8	OA0_COMPINT	Opamp0 comparator edge detect for output and interrupt Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
7	OA0_DSI_LEVEL	Opamp0 comparator output : 0=pulse, 1=level Default Value: 0
6	OA0_DSI_BYPASS	Opamp0 bypass comparator output synchronization: 0=synchronize (level or pulse), 1=bypass (output async) Default Value: 0
5	OA0_HYST_EN	Opamp0 hysteresis enable (10mV) Default Value: 0
4	OA0_COMP_EN	Opamp0 comparator enable Default Value: 0
2	OA0_DRIVE_STR_SEL	Opamp0 output strength select 0=1x, 1=10x Default Value: 0
1 : 0	OA0_PWR_MODE	Opamp0 power level: 0: OFF 1: Low Power 2: Medium Power 3: High Power Default Value: 0

6.1.3 CTB0_OA_RES1_CTRL

Opamp1 and resistor1 control

Address: 0x40300008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA1_DSI_LEVEL	OA1_DSI_BYPASS	OA1_HYST_EN	OA1_COMP_EN	None	OA1_DRIVE_STR_SEL	OA1_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA1_PUMP_EN	None	OA1_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	RW			
HW Access	None		R	R	R			
Name	None [23:22]		RES1_TAP_OVR	RES1_SWAP	RES1_TAP [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW			RW			
HW Access	R	R			R			
Name	VALID_SEL1_EN	VALID_SEL1 [30:28]			C1_FB [27:24]			

Bits	Name	Description
31	VALID_SEL1_EN	Enable UAB Valid selection (UAB mode), otherwise ignore UAB Valid. Note that enabling UAB Valid selection also disables DeepSleep comparator operation. Default Value: 0
30 : 28	VALID_SEL1	Select which UAB Valid to use to sample the comparator output. This should match the UAB analog output connected to this comparator. The comparator output gets sampled at the negative edge of the selected UAB Valid signal. 0=UAB0 half 0 Valid output 1=UAB0 half 1 Valid output Default Value: 0
27 : 24	C1_FB	Feed back Cap value Default Value: 0
21	RES1_TAP_OVR	1 - Override the control from hardware and close the switch connecting the resistor ladder tap point to the bottom of the ladder Default Value: 0

6.1.3 CTB0_OA_RES1_CTRL (continued)

20	RES1_SWAP	Swap Top and Bottom resistor value Default Value: 0
19 : 16	RES1_TAP	PGA gain (resistor tap point): 0= gain 1.0 (disconnects resistor) 1= gain 1.42 2= gain 2.0 3= gain 2.78 4= gain 4.0 5= gain 5.82 6= gain 8.0 7= gain 10.67 8= gain 16.0 9= gain 21.33 10= gain 32.0 Default Value: 0
11	OA1_PUMP_EN	Opamp1 pump enable Default Value: 0
9 : 8	OA1_COMPINT	Opamp1 comparator edge detect for output and interrupt Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
7	OA1_DSI_LEVEL	Opamp1 comparator output : 0=pulse, 1=level Default Value: 0
6	OA1_DSI_BYPASS	Opamp1 bypass comparator output synchronization: 0=synchronize (level or pulse), 1=bypass (output async) Default Value: 0
5	OA1_HYST_EN	Opamp1 hysteresis enable (10mV) Default Value: 0
4	OA1_COMP_EN	Opamp1 comparator enable Default Value: 0
2	OA1_DRIVE_STR_SEL	Opamp1 output strength select 0=1x, 1=10x Default Value: 0
1 : 0	OA1_PWR_MODE	Opamp1 power level: 0: OFF 1: Low Power 2: Medium Power 3: High Power Default Value: 0

6.1.4 CTB0_COMP_STAT

Comparator status

Address: 0x4030000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							OA0_COMP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							W
Name	None [23:17]							OA1_COMP

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	OA1_COMP	Opamp1 current comparator status Default Value: 0
0	OA0_COMP	Opamp0 current comparator status Default Value: 0

6.1.5 CTB0_INTR

Interrupt request register

Address: 0x40300020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						COMP1	COMP0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1	Comparator 1 Interrupt: hardware sets this interrupt when comparator 1 triggers. Write with '1' to clear bit. Default Value: 0
0	COMP0	Comparator 0 Interrupt: hardware sets this interrupt when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

6.1.6 CTB0_INTR_SET

Interrupt request set register

Address: 0x40300024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						COMP1_SET	COMP0_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	COMP0_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

6.1.7 CTB0_INTR_MASK

Interrupt request mask

Address: 0x40300028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						COMP1_MASK	COMP0_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	COMP0_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

6.1.8 CTB0_INTR_MASKED

Interrupt request masked

Address: 0x4030002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						COMP1_MASKED	COMP0_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	COMP0_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

6.1.9 CTB0_OA0_SW

Opamp0 switch control

Address: 0x40300080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA0P_A70	OA0P_A60	OA0P_A50	OA0P_A40	OA0P_A30	OA0P_A20	OA0P_A10	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	None	RW1S	None	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	None	RW1C	None	RW1C	RW1C
Name	OA0M_A51	OA0M_A41	OA0M_A31	None	OA0M_A11	None	OA0P_A90	OA0P_A80

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA0O_D81	OA0O_D71	OA0O_D51	OA0O_D31	OA0M_A91	OA0M_A81	OA0M_A71	OA0M_A61

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	None	RES0_R81	RES0_R71	RES0_R61	RES0_R41	RES0_R31	RES0_R11	RES0_R01

Bits	Name	Description
30	RES0_R81	Resistor0 tap to Opamp0 positive terminal Default Value: 0
29	RES0_R71	Resistor0 tap to Opamp0 negative terminal Default Value: 0
28	RES0_R61	Resistor0 bottom to VSSA Default Value: 0
27	RES0_R41	Resistor0 bottom to Opamp1 negative terminal Default Value: 0
26	RES0_R31	Resistor0 bottom to Opamp0 negative terminal Default Value: 0
25	RES0_R11	Resistor0 bottom to Opamp1 output Default Value: 0
24	RES0_R01	Resistor0 bottom to Pin P1 Default Value: 0
23	OA0O_D81	Opamp0 output switch to short 1x with 10x drive Default Value: 0

6.1.9 CTB0_OA0_SW (continued)

22	OA0O_D71	Opamp0 output to vref0 Default Value: 0
21	OA0O_D51	Opamp0 output to ctbbus2 Default Value: 0
20	OA0O_D31	Opamp0 output to ctbbus0 Default Value: 0
19	OA0M_A91	Opamp0 negative terminal to pin P2 Default Value: 0
18	OA0M_A81	Opamp0 negative terminal to Opamp0 bottom Default Value: 0
17	OA0M_A71	Opamp0 negative terminal to vref0 Default Value: 0
16	OA0M_A61	Opamp0 negative terminal to ctbbus3 Default Value: 0
15	OA0M_A51	Opamp0 negative terminal to ctbbus2 Default Value: 0
14	OA0M_A41	Opamp0 negative terminal to ctbbus1 Default Value: 0
13	OA0M_A31	Opamp0 negative terminal to ctbbus0 Default Value: 0
11	OA0M_A11	Opamp0 negative terminal to pin P1 Default Value: 0
9	OA0P_A90	Opamp0 positive terminal to uabin1 Default Value: 0
8	OA0P_A80	Opamp0 positive terminal to uabin0 Default Value: 0
7	OA0P_A70	Opamp0 positive terminal to vref0 Default Value: 0
6	OA0P_A60	Opamp0 positive terminal to ctbbus3 Default Value: 0
5	OA0P_A50	Opamp0 positive terminal to ctbbus2 Default Value: 0
4	OA0P_A40	Opamp0 positive terminal to ctbbus1 Default Value: 0
3	OA0P_A30	Opamp0 positive terminal to ctbbus0 Default Value: 0
2	OA0P_A20	Opamp0 positive terminal to pin P0 Default Value: 0
1	OA0P_A10	Opamp0 positive terminal to pin P1 Default Value: 0
0	OA0P_A00	Opamp0 positive terminal to amuxbusa Default Value: 0

6.1.10 CTB0_OA0_SW_CLEAR

Opamp0 switch control clear

Address: 0x40300084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA0P_A70	OA0P_A60	OA0P_A50	OA0P_A40	OA0P_A30	OA0P_A20	OA0P_A10	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	None	RW1C	None	RW1C	RW1C
HW Access	A	A	A	None	A	None	A	A
Name	OA0M_A51	OA0M_A41	OA0M_A31	None	OA0M_A11	None	OA0P_A90	OA0P_A80

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA0O_D81	OA0O_D71	OA0O_D51	OA0O_D31	OA0M_A91	OA0M_A81	OA0M_A71	OA0M_A61

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None	A	A	A	A	A	A	A
Name	None	RES0_R81	RES0_R71	RES0_R61	RES0_R41	RES0_R31	RES0_R11	RES0_R01

Bits	Name	Description
30	RES0_R81	see corresponding bit in OA0_SW Default Value: 0
29	RES0_R71	see corresponding bit in OA0_SW Default Value: 0
28	RES0_R61	see corresponding bit in OA0_SW Default Value: 0
27	RES0_R41	see corresponding bit in OA0_SW Default Value: 0
26	RES0_R31	see corresponding bit in OA0_SW Default Value: 0
25	RES0_R11	see corresponding bit in OA0_SW Default Value: 0
24	RES0_R01	see corresponding bit in OA0_SW Default Value: 0
23	OA0O_D81	see corresponding bit in OA0_SW Default Value: 0

6.1.10 CTB0_OA0_SW_CLEAR (continued)

22	OA0O_D71	see corresponding bit in OA0_SW Default Value: 0
21	OA0O_D51	see corresponding bit in OA0_SW Default Value: 0
20	OA0O_D31	see corresponding bit in OA0_SW Default Value: 0
19	OA0M_A91	see corresponding bit in OA0_SW Default Value: 0
18	OA0M_A81	see corresponding bit in OA0_SW Default Value: 0
17	OA0M_A71	see corresponding bit in OA0_SW Default Value: 0
16	OA0M_A61	see corresponding bit in OA0_SW Default Value: 0
15	OA0M_A51	see corresponding bit in OA0_SW Default Value: 0
14	OA0M_A41	see corresponding bit in OA0_SW Default Value: 0
13	OA0M_A31	see corresponding bit in OA0_SW Default Value: 0
11	OA0M_A11	see corresponding bit in OA0_SW Default Value: 0
9	OA0P_A90	see corresponding bit in OA0_SW Default Value: 0
8	OA0P_A80	see corresponding bit in OA0_SW Default Value: 0
7	OA0P_A70	see corresponding bit in OA0_SW Default Value: 0
6	OA0P_A60	see corresponding bit in OA0_SW Default Value: 0
5	OA0P_A50	see corresponding bit in OA0_SW Default Value: 0
4	OA0P_A40	see corresponding bit in OA0_SW Default Value: 0
3	OA0P_A30	see corresponding bit in OA0_SW Default Value: 0
2	OA0P_A20	see corresponding bit in OA0_SW Default Value: 0
1	OA0P_A10	see corresponding bit in OA0_SW Default Value: 0
0	OA0P_A00	see corresponding bit in OA0_SW Default Value: 0

6.1.11 CTB0_OA1_SW

Opamp1 switch control

Address: 0x40300088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA1P_A73	OA1P_A63	OA1P_A53	OA1P_A43	OA1P_A33	OA1P_A23	OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
Name	OA1M_A52	OA1M_A42	OA1M_A32	OA1M_A22	None [11:10]		OA1P_A93	OA1P_A83

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA1O_D72	OA1O_D62	OA1O_D52	OA1O_D42	OA1M_A92	OA1M_A82	OA1M_A72	OA1M_A62

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	RES1_R92	RES1_R82	RES1_R72	RES1_R62	RES1_R52	RES1_R32	RES1_R02	OA1O_D82

Bits	Name	Description
31	RES1_R92	Resistor1 tap to Opamp0 positive terminal Default Value: 0
30	RES1_R82	Resistor1 tap to Opamp1 positive terminal Default Value: 0
29	RES1_R72	Resistor1 tap to Opamp1 negative terminal Default Value: 0
28	RES1_R62	Resistor1 bottom to VSSA Default Value: 0
27	RES1_R52	Resistor1 bottom to Resistor0 bottom Default Value: 0
26	RES1_R32	Resistor1 bottom to Opamp1 negative terminal Default Value: 0
25	RES1_R02	Resistor1 bottom to pin P4 Default Value: 0
24	OA1O_D82	Opamp1 output switch to short 1x with 10x drive Default Value: 0

6.1.11 CTB0_OA1_SW (continued)

23	OA1O_D72	Opamp1 output to vref1 Default Value: 0
22	OA1O_D62	Opamp1 output to ctbbus3 Default Value: 0
21	OA1O_D52	Opamp1 output to ctbbus2 Default Value: 0
20	OA1O_D42	Opamp1 output to ctbbus1 Default Value: 0
19	OA1M_A92	Opamp1 negative terminal to pin P3 Default Value: 0
18	OA1M_A82	Opamp1 negative terminal to Opamp1 bottom Default Value: 0
17	OA1M_A72	Opamp1 negative terminal to vref1 Default Value: 0
16	OA1M_A62	Opamp1 negative terminal to ctbbus3 Default Value: 0
15	OA1M_A52	Opamp1 negative terminal to ctbbus2 Default Value: 0
14	OA1M_A42	Opamp1 negative terminal to ctbbus1 Default Value: 0
13	OA1M_A32	Opamp1 negative terminal to ctbbus0 Default Value: 0
12	OA1M_A22	Opamp1 negative terminal to pin P4 Default Value: 0
9	OA1P_A93	Opamp1 positive terminal to uabin1 Default Value: 0
8	OA1P_A83	Opamp1 positive terminal to uabin0 Default Value: 0
7	OA1P_A73	Opamp1 positive terminal to vref1 Default Value: 0
6	OA1P_A63	Opamp1 positive terminal to ctbbus3 Default Value: 0
5	OA1P_A53	Opamp1 positive terminal to ctbbus2 Default Value: 0
4	OA1P_A43	Opamp1 positive terminal to ctbbus1 Default Value: 0
3	OA1P_A33	Opamp1 positive terminal to ctbbus0 Default Value: 0
2	OA1P_A23	Opamp1 positive terminal to pin P4 Default Value: 0
1	OA1P_A13	Opamp1 positive terminal to pin P5 Default Value: 0
0	OA1P_A03	Opamp1 positive terminal to amuxbusb Default Value: 0

6.1.12 CTB0_OA1_SW_CLEAR

Opamp1 switch control clear

Address: 0x4030008C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA1P_A73	OA1P_A63	OA1P_A53	OA1P_A43	OA1P_A33	OA1P_A23	OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	A	A	A	A	None		A	A
Name	OA1M_A52	OA1M_A42	OA1M_A32	OA1M_A22	None [11:10]		OA1P_A93	OA1P_A83

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA1O_D72	OA1O_D62	OA1O_D52	OA1O_D42	OA1M_A92	OA1M_A82	OA1M_A72	OA1M_A62

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	RES1_R92	RES1_R82	RES1_R72	RES1_R62	RES1_R52	RES1_R32	RES1_R02	OA1O_D82

Bits	Name	Description
31	RES1_R92	see corresponding bit in OA1_SW Default Value: 0
30	RES1_R82	see corresponding bit in OA1_SW Default Value: 0
29	RES1_R72	see corresponding bit in OA1_SW Default Value: 0
28	RES1_R62	see corresponding bit in OA1_SW Default Value: 0
27	RES1_R52	see corresponding bit in OA1_SW Default Value: 0
26	RES1_R32	see corresponding bit in OA1_SW Default Value: 0
25	RES1_R02	see corresponding bit in OA1_SW Default Value: 0
24	OA1O_D82	see corresponding bit in OA1_SW Default Value: 0

6.1.12 CTB0_OA1_SW_CLEAR (continued)

23	OA1O_D72	see corresponding bit in OA1_SW Default Value: 0
22	OA1O_D62	see corresponding bit in OA1_SW Default Value: 0
21	OA1O_D52	see corresponding bit in OA1_SW Default Value: 0
20	OA1O_D42	see corresponding bit in OA1_SW Default Value: 0
19	OA1M_A92	see corresponding bit in OA1_SW Default Value: 0
18	OA1M_A82	see corresponding bit in OA1_SW Default Value: 0
17	OA1M_A72	see corresponding bit in OA1_SW Default Value: 0
16	OA1M_A62	see corresponding bit in OA1_SW Default Value: 0
15	OA1M_A52	see corresponding bit in OA1_SW Default Value: 0
14	OA1M_A42	see corresponding bit in OA1_SW Default Value: 0
13	OA1M_A32	see corresponding bit in OA1_SW Default Value: 0
12	OA1M_A22	see corresponding bit in OA1_SW Default Value: 0
9	OA1P_A93	see corresponding bit in OA1_SW Default Value: 0
8	OA1P_A83	see corresponding bit in OA1_SW Default Value: 0
7	OA1P_A73	see corresponding bit in OA1_SW Default Value: 0
6	OA1P_A63	see corresponding bit in OA1_SW Default Value: 0
5	OA1P_A53	see corresponding bit in OA1_SW Default Value: 0
4	OA1P_A43	see corresponding bit in OA1_SW Default Value: 0
3	OA1P_A33	see corresponding bit in OA1_SW Default Value: 0
2	OA1P_A23	see corresponding bit in OA1_SW Default Value: 0
1	OA1P_A13	see corresponding bit in OA1_SW Default Value: 0
0	OA1P_A03	see corresponding bit in OA1_SW Default Value: 0

6.1.13 CTB0_CTBBUS_SW

CTB bus switch control

Address: 0x40300090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	CB0_P07	CB0_P06	CB0_P05	CB0_P04	CB0_P03	CB0_P02	CB0_P01	CB0_P00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	CB2_P26	CB2_P24	CB2_P22	CB2_P20	CB1_P17	CB1_P15	CB1_P13	CB1_P11

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	CB3_G63	CB2_G53	CB1_G43	CB0_G33	CB3_P37	CB3_P35	CB3_P33	CB3_P31

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [31:29]			CB2_G50	CB3_G61	CB2_G52	CB1_G41	CB0_G32

Bits	Name	Description
28	CB2_G50	ctbbus2 ctbbus3 Default Value: 0
27	CB3_G61	ctbbus3 sarbus1 Default Value: 0
26	CB2_G52	ctbbus2 sarbus0 Default Value: 0
25	CB1_G41	ctbbus1 sarbus1 Default Value: 0
24	CB0_G32	ctbbus0 sarbus0 Default Value: 0
23	CB3_G63	ctbbus3 right neighbor Default Value: 0
22	CB2_G53	ctbbus2 right neighbor Default Value: 0
21	CB1_G43	ctbbus1 right neighbor Default Value: 0

6.1.13 CTB0_CTBBUS_SW (continued)

20	CB0_G33	ctbbus0 right neighbor Default Value: 0
19	CB3_P37	P7 ctbbus3 Default Value: 0
18	CB3_P35	P5 ctbbus3 Default Value: 0
17	CB3_P33	P3 ctbbus3 Default Value: 0
16	CB3_P31	P1 ctbbus3 Default Value: 0
15	CB2_P26	P6 ctbbus2 Default Value: 0
14	CB2_P24	P4 ctbbus2 Default Value: 0
13	CB2_P22	P2 ctbbus2 Default Value: 0
12	CB2_P20	P0 ctbbus2 Default Value: 0
11	CB1_P17	P7 ctbbus1 Default Value: 0
10	CB1_P15	P5 ctbbus1 Default Value: 0
9	CB1_P13	P3 ctbbus1 Default Value: 0
8	CB1_P11	P1 ctbbus1 Default Value: 0
7	CB0_P07	P7 ctbbus0 Default Value: 0
6	CB0_P06	P6 ctbbus0 Default Value: 0
5	CB0_P05	P5 ctbbus0 Default Value: 0
4	CB0_P04	P4 ctbbus0 Default Value: 0
3	CB0_P03	P3 ctbbus0 Default Value: 0
2	CB0_P02	P2 ctbbus0 Default Value: 0
1	CB0_P01	P1 ctbbus0 Default Value: 0
0	CB0_P00	P0 ctbbus0 Default Value: 0

6.1.14 CTB0_CTBBUS_SW_CLEAR

CTB bus switch control clear

Address: 0x40300094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	CB0_P07	CB0_P06	CB0_P05	CB0_P04	CB0_P03	CB0_P02	CB0_P01	CB0_P00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	CB2_P26	CB2_P24	CB2_P22	CB2_P20	CB1_P17	CB1_P15	CB1_P13	CB1_P11

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	CB3_G63	CB2_G53	CB1_G43	CB0_G33	CB3_P37	CB3_P35	CB3_P33	CB3_P31

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None			A	A	A	A	A
Name	None [31:29]			CB2_G50	CB3_G61	CB2_G52	CB1_G41	CB0_G32

Bits	Name	Description
28	CB2_G50	see corresponding bit in CTBBUS_SW Default Value: 0
27	CB3_G61	see corresponding bit in CTBBUS_SW Default Value: 0
26	CB2_G52	see corresponding bit in CTBBUS_SW Default Value: 0
25	CB1_G41	see corresponding bit in CTBBUS_SW Default Value: 0
24	CB0_G32	see corresponding bit in CTBBUS_SW Default Value: 0
23	CB3_G63	see corresponding bit in CTBBUS_SW Default Value: 0
22	CB2_G53	see corresponding bit in CTBBUS_SW Default Value: 0
21	CB1_G43	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.14 CTB0_CTBBUS_SW_CLEAR (continued)

20	CB0_G33	see corresponding bit in CTBBUS_SW Default Value: 0
19	CB3_P37	see corresponding bit in CTBBUS_SW Default Value: 0
18	CB3_P35	see corresponding bit in CTBBUS_SW Default Value: 0
17	CB3_P33	see corresponding bit in CTBBUS_SW Default Value: 0
16	CB3_P31	see corresponding bit in CTBBUS_SW Default Value: 0
15	CB2_P26	see corresponding bit in CTBBUS_SW Default Value: 0
14	CB2_P24	see corresponding bit in CTBBUS_SW Default Value: 0
13	CB2_P22	see corresponding bit in CTBBUS_SW Default Value: 0
12	CB2_P20	see corresponding bit in CTBBUS_SW Default Value: 0
11	CB1_P17	see corresponding bit in CTBBUS_SW Default Value: 0
10	CB1_P15	see corresponding bit in CTBBUS_SW Default Value: 0
9	CB1_P13	see corresponding bit in CTBBUS_SW Default Value: 0
8	CB1_P11	see corresponding bit in CTBBUS_SW Default Value: 0
7	CB0_P07	see corresponding bit in CTBBUS_SW Default Value: 0
6	CB0_P06	see corresponding bit in CTBBUS_SW Default Value: 0
5	CB0_P05	see corresponding bit in CTBBUS_SW Default Value: 0
4	CB0_P04	see corresponding bit in CTBBUS_SW Default Value: 0
3	CB0_P03	see corresponding bit in CTBBUS_SW Default Value: 0
2	CB0_P02	see corresponding bit in CTBBUS_SW Default Value: 0
1	CB0_P01	see corresponding bit in CTBBUS_SW Default Value: 0
0	CB0_P00	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.15 CTB0_CTB_SW_HW_CTRL

CTB bus switch control status

Address: 0x403000C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	P7_HW_CTRL01	P6_HW_CTRL01	P5_HW_CTRL01	P4_HW_CTRL01	P3_HW_CTRL01	P2_HW_CTRL01	P1_HW_CTRL01	P0_HW_CTRL01

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	P7_HW_CTRL23	P6_HW_CTRL23	P5_HW_CTRL23	P4_HW_CTRL23	P3_HW_CTRL23	P2_HW_CTRL23	P1_HW_CTRL23	P0_HW_CTRL23

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						SARBUS1_HW_CTRL	SARBUS0_HW_CTRL

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	SARBUS1_HW_CTRL	sarbus1 switches (G41, G61) Default Value: 0
16	SARBUS0_HW_CTRL	sarbus0 switches (G32, G52) Default Value: 0
15	P7_HW_CTRL23	for P37 Default Value: 0
14	P6_HW_CTRL23	for P26 Default Value: 0
13	P5_HW_CTRL23	for P35 Default Value: 0
12	P4_HW_CTRL23	for P24 Default Value: 0
11	P3_HW_CTRL23	for P33, D52, D62 Default Value: 0

6.1.15 CTB0_CTB_SW_HW_CTRL (continued)

10	P2_HW_CTRL23	for P22, D51 Default Value: 0
9	P1_HW_CTRL23	for P31 Default Value: 0
8	P0_HW_CTRL23	for P20 Default Value: 0
7	P7_HW_CTRL01	for P07, P17 Default Value: 0
6	P6_HW_CTRL01	for P06 Default Value: 0
5	P5_HW_CTRL01	for P05, P15 Default Value: 0
4	P4_HW_CTRL01	for P04 Default Value: 0
3	P3_HW_CTRL01	for P03, P13 Default Value: 0
2	P2_HW_CTRL01	for P02 Default Value: 0
1	P1_HW_CTRL01	for P01, P11 Default Value: 0
0	P0_HW_CTRL01	for P00 Default Value: 0

6.1.16 CTB0_CTB_SW_STATUS

CTB bus switch control status

Address: 0x403000C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	CB0_P07_STAT	CB0_P06_STAT	CB0_P05_STAT	CB0_P04_STAT	CB0_P03_STAT	CB0_P02_STAT	CB0_P01_STAT	CB0_P00_STAT

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	CB2_P26_STAT	CB2_P24_STAT	CB2_P22_STAT	CB2_P20_STAT	CB1_P17_STAT	CB1_P15_STAT	CB1_P13_STAT	CB1_P11_STAT

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	CB3_G63_STAT	CB2_G53_STAT	CB1_G43_STAT	CB0_G33_STAT	CB3_P37_STAT	CB3_P35_STAT	CB3_P33_STAT	CB3_P31_STAT

Bits	31	30	29	28	27	26	25	24
SW Access	None	R	R	R	R	R	R	R
HW Access	None	W	W	W	W	W	W	W
Name	None	OA1O_D62_STAT	OA1O_D52_STAT	OA0O_D51_STAT	CB3_G61_STAT	CB2_G52_STAT	CB1_G41_STAT	CB0_G32_STAT

Bits	Name	Description
30	OA1O_D62_STAT	see OA1O_D62 bit in OA1_SW Default Value: 0
29	OA1O_D52_STAT	see OA1O_D52 bit in OA1_SW Default Value: 0
28	OA0O_D51_STAT	see OA0O_D51 bit in OA0_SW Default Value: 0
27	CB3_G61_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
26	CB2_G52_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
25	CB1_G41_STAT	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.16 CTB0_CTB_SW_STATUS (continued)

24	CB0_G32_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
23	CB3_G63_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
22	CB2_G53_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
21	CB1_G43_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
20	CB0_G33_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
19	CB3_P37_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
18	CB3_P35_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
17	CB3_P33_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
16	CB3_P31_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
15	CB2_P26_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
14	CB2_P24_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
13	CB2_P22_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
12	CB2_P20_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
11	CB1_P17_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
10	CB1_P15_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
9	CB1_P13_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
8	CB1_P11_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
7	CB0_P07_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
6	CB0_P06_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
5	CB0_P05_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
4	CB0_P04_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
3	CB0_P03_STAT	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.16 CTB0_CTB_SW_STATUS (continued)

2	CB0_P02_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
1	CB0_P01_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
0	CB0_P00_STAT	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.17 CTB0_OA0_OFFSET_TRIM

Opamp0 trim control

Address: 0x40300F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_OFFSET_TRIM	Opamp0 offset trim Default Value: 0

6.1.18 CTB0_OA0_SLOPE_OFFSET_TRIM

Opamp0 trim control

Address: 0x40300F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_SLOPE_OFFSET_TRIM	Opamp0 slope offset drift trim Default Value: 0

6.1.19 CTB0_OA0_COMP_TRIM

Opamp0 trim control

Address: 0x40300F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA0_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA0_COMP_TRIM	Opamp0 Compensation Capacitor Trim Default Value: 0

6.1.20 CTB0_OA1_OFFSET_TRIM

Opamp1 trim control

Address: 0x40300F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_OFFSET_TRIM	Opamp1 offset trim Default Value: 0

6.1.21 CTB0_OA1_SLOPE_OFFSET_TRIM

Opamp1 trim control

Address: 0x40300F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_SLOPE_OFFSET_TRIM	Opamp1 slope offset drift trim Default Value: 0

6.1.22 CTB0_OA1_COMP_TRIM

Opamp1 trim control

Address: 0x40300F14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA1_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA1_COMP_TRIM	Opamp1 Compensation Capacitor Trim Default Value: 0

6.1.23 CTB0_RMP_TRIM

Risk Mitigation bits

Address: 0x40300F18

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				RMP_TRIM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	RMP_TRIM	Risk Mitigation Trim bits Default Value: 0

6.1.24 CTB1_CTB_CTRL

global CTB and power control

Address: 0x40310000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				SPARE [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	ENABLED	DEEPSLEEP_ON	None [29:24]					

Bits	Name	Description
31	ENABLED	- 0: CTB disabled (put analog in power down, open all switches) - 1: CTB enabled Default Value: 0
30	DEEPSLEEP_ON	- 0: CTB disabled off during DeepSleep power mode - 1: CTB remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0
19 : 16	SPARE	Reserved bit Default Value: 0

6.1.25 CTB1_OA_RES0_CTRL

Opamp0 and resistor0 control

Address: 0x40310004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA0_DSI_LEVEL	OA0_DSI_BYPASS	OA0_HYST_EN	OA0_COMP_EN	None	OA0_DRIVE_STR_SEL	OA0_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA0_PUMP_EN	None	OA0_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	RW			
HW Access	None		R	R	R			
Name	None [23:22]		RES0_TAP_OVR	RES0_SWAP	RES0_TAP [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW			RW			
HW Access	R	R			R			
Name	VALID_SEL0_EN	VALID_SEL0 [30:28]			C0_FB [27:24]			

Bits	Name	Description
31	VALID_SEL0_EN	Enable UAB Valid selection (UAB mode), otherwise ignore UAB Valid. Note that enabling UAB Valid selection also disables DeepSleep comparator operation. Default Value: 0
30 : 28	VALID_SEL0	Select which UAB Valid to use to sample the comparator output. This should match the UAB analog output connected to this comparator. The comparator output gets sampled at the negative edge of the selected UAB Valid signal. 0=UAB0 half 0 Valid output 1=UAB0 half 1 Valid output Default Value: 0
27 : 24	C0_FB	Feed back Cap value Default Value: 0
21	RES0_TAP_OVR	1 - Override the control from hardware and close the switch connecting the resistor ladder tap point to the bottom of the ladder Default Value: 0

6.1.25 CTB1_OA_RES0_CTRL (continued)

20	RES0_SWAP	Swap Top and Bottom resistor value Default Value: 0
19 : 16	RES0_TAP	PGA gain (resistor tap point): 0= gain 1.0 (disconnects resistor) 1= gain 1.42 2= gain 2.0 3= gain 2.78 4= gain 4.0 5= gain 5.82 6= gain 8.0 7= gain 10.67 8= gain 16.0 9= gain 21.33 10= gain 32.0 Default Value: 0
11	OA0_PUMP_EN	Opamp0 pump enable Default Value: 0
9 : 8	OA0_COMPINT	Opamp0 comparator edge detect for output and interrupt Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
7	OA0_DSI_LEVEL	Opamp0 comparator output : 0=pulse, 1=level Default Value: 0
6	OA0_DSI_BYPASS	Opamp0 bypass comparator output synchronization: 0=synchronize (level or pulse), 1=bypass (output async) Default Value: 0
5	OA0_HYST_EN	Opamp0 hysteresis enable (10mV) Default Value: 0
4	OA0_COMP_EN	Opamp0 comparator enable Default Value: 0
2	OA0_DRIVE_STR_SEL	Opamp0 output strength select 0=1x, 1=10x Default Value: 0
1 : 0	OA0_PWR_MODE	Opamp0 power level: 0: OFF 1: Low Power 2: Medium Power 3: High Power Default Value: 0

6.1.26 CTB1_OA_RES1_CTRL

Opamp1 and resistor1 control

Address: 0x40310008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA1_DSI_LEVEL	OA1_DSI_BYPASS	OA1_HYST_EN	OA1_COMP_EN	None	OA1_DRIVE_STR_SEL	OA1_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA1_PUMP_EN	None	OA1_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	RW			
HW Access	None		R	R	R			
Name	None [23:22]		RES1_TAP_OVR	RES1_SWAP	RES1_TAP [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW			RW			
HW Access	R	R			R			
Name	VALID_SEL1_EN	VALID_SEL1 [30:28]			C1_FB [27:24]			

Bits	Name	Description
31	VALID_SEL1_EN	Enable UAB Valid selection (UAB mode), otherwise ignore UAB Valid. Note that enabling UAB Valid selection also disables DeepSleep comparator operation. Default Value: 0
30 : 28	VALID_SEL1	Select which UAB Valid to use to sample the comparator output. This should match the UAB analog output connected to this comparator. The comparator output gets sampled at the negative edge of the selected UAB Valid signal. 0=UAB0 half 0 Valid output 1=UAB0 half 1 Valid output Default Value: 0
27 : 24	C1_FB	Feed back Cap value Default Value: 0
21	RES1_TAP_OVR	1 - Override the control from hardware and close the switch connecting the resistor ladder tap point to the bottom of the ladder Default Value: 0

6.1.26 CTB1_OA_RES1_CTRL (continued)

20	RES1_SWAP	Swap Top and Bottom resistor value Default Value: 0
19 : 16	RES1_TAP	PGA gain (resistor tap point): 0= gain 1.0 (disconnects resistor) 1= gain 1.42 2= gain 2.0 3= gain 2.78 4= gain 4.0 5= gain 5.82 6= gain 8.0 7= gain 10.67 8= gain 16.0 9= gain 21.33 10= gain 32.0 Default Value: 0
11	OA1_PUMP_EN	Opamp1 pump enable Default Value: 0
9 : 8	OA1_COMPINT	Opamp1 comparator edge detect for output and interrupt Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
7	OA1_DSI_LEVEL	Opamp1 comparator output : 0=pulse, 1=level Default Value: 0
6	OA1_DSI_BYPASS	Opamp1 bypass comparator output synchronization: 0=synchronize (level or pulse), 1=bypass (output async) Default Value: 0
5	OA1_HYST_EN	Opamp1 hysteresis enable (10mV) Default Value: 0
4	OA1_COMP_EN	Opamp1 comparator enable Default Value: 0
2	OA1_DRIVE_STR_SEL	Opamp1 output strength select 0=1x, 1=10x Default Value: 0
1 : 0	OA1_PWR_MODE	Opamp1 power level: 0: OFF 1: Low Power 2: Medium Power 3: High Power Default Value: 0

6.1.27 CTB1_COMP_STAT

Comparator status

Address: 0x4031000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							OA0_COMP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							W
Name	None [23:17]							OA1_COMP

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	OA1_COMP	Opamp1 current comparator status Default Value: 0
0	OA0_COMP	Opamp0 current comparator status Default Value: 0

6.1.28 CTB1_INTR

Interrupt request register

Address: 0x40310020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						COMP1	COMP0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1	Comparator 1 Interrupt: hardware sets this interrupt when comparator 1 triggers. Write with '1' to clear bit. Default Value: 0
0	COMP0	Comparator 0 Interrupt: hardware sets this interrupt when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

6.1.29 CTB1_INTR_SET

Interrupt request set register

Address: 0x40310024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						COMP1_SET	COMP0_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	COMP0_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

6.1.30 CTB1_INTR_MASK

Interrupt request mask

Address: 0x40310028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						COMP1_MASK	COMP0_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	COMP0_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

6.1.31 CTB1_INTR_MASKED

Interrupt request masked

Address: 0x4031002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						COMP1_MASKED	COMP0_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	COMP0_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

6.1.32 CTB1_OA0_SW

Opamp0 switch control

Address: 0x40310080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA0P_A70	OA0P_A60	OA0P_A50	OA0P_A40	OA0P_A30	OA0P_A20	OA0P_A10	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	None	RW1S	None	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	None	RW1C	None	RW1C	RW1C
Name	OA0M_A51	OA0M_A41	OA0M_A31	None	OA0M_A11	None	OA0P_A90	OA0P_A80

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA0O_D81	OA0O_D71	OA0O_D51	OA0O_D31	OA0M_A91	OA0M_A81	OA0M_A71	OA0M_A61

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	None	RES0_R81	RES0_R71	RES0_R61	RES0_R41	RES0_R31	RES0_R11	RES0_R01

Bits	Name	Description
30	RES0_R81	Resistor0 tap to Opamp0 positive terminal Default Value: 0
29	RES0_R71	Resistor0 tap to Opamp0 negative terminal Default Value: 0
28	RES0_R61	Resistor0 bottom to VSSA Default Value: 0
27	RES0_R41	Resistor0 bottom to Opamp1 negative terminal Default Value: 0
26	RES0_R31	Resistor0 bottom to Opamp0 negative terminal Default Value: 0
25	RES0_R11	Resistor0 bottom to Opamp1 output Default Value: 0
24	RES0_R01	Resistor0 bottom to Pin P1 Default Value: 0
23	OA0O_D81	Opamp0 output switch to short 1x with 10x drive Default Value: 0

6.1.32 CTB1_OA0_SW (continued)

22	OA0O_D71	Opamp0 output to vref0 Default Value: 0
21	OA0O_D51	Opamp0 output to ctbbus2 Default Value: 0
20	OA0O_D31	Opamp0 output to ctbbus0 Default Value: 0
19	OA0M_A91	Opamp0 negative terminal to pin P2 Default Value: 0
18	OA0M_A81	Opamp0 negative terminal to Opamp0 bottom Default Value: 0
17	OA0M_A71	Opamp0 negative terminal to vref0 Default Value: 0
16	OA0M_A61	Opamp0 negative terminal to ctbbus3 Default Value: 0
15	OA0M_A51	Opamp0 negative terminal to ctbbus2 Default Value: 0
14	OA0M_A41	Opamp0 negative terminal to ctbbus1 Default Value: 0
13	OA0M_A31	Opamp0 negative terminal to ctbbus0 Default Value: 0
11	OA0M_A11	Opamp0 negative terminal to pin P1 Default Value: 0
9	OA0P_A90	Opamp0 positive terminal to uabin1 Default Value: 0
8	OA0P_A80	Opamp0 positive terminal to uabin0 Default Value: 0
7	OA0P_A70	Opamp0 positive terminal to vref0 Default Value: 0
6	OA0P_A60	Opamp0 positive terminal to ctbbus3 Default Value: 0
5	OA0P_A50	Opamp0 positive terminal to ctbbus2 Default Value: 0
4	OA0P_A40	Opamp0 positive terminal to ctbbus1 Default Value: 0
3	OA0P_A30	Opamp0 positive terminal to ctbbus0 Default Value: 0
2	OA0P_A20	Opamp0 positive terminal to pin P0 Default Value: 0
1	OA0P_A10	Opamp0 positive terminal to pin P1 Default Value: 0
0	OA0P_A00	Opamp0 positive terminal to amuxbusa Default Value: 0

6.1.33 CTB1_OA0_SW_CLEAR

Opamp0 switch control clear

Address: 0x40310084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA0P_A70	OA0P_A60	OA0P_A50	OA0P_A40	OA0P_A30	OA0P_A20	OA0P_A10	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	None	RW1C	None	RW1C	RW1C
HW Access	A	A	A	None	A	None	A	A
Name	OA0M_A51	OA0M_A41	OA0M_A31	None	OA0M_A11	None	OA0P_A90	OA0P_A80

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA0O_D81	OA0O_D71	OA0O_D51	OA0O_D31	OA0M_A91	OA0M_A81	OA0M_A71	OA0M_A61

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None	A	A	A	A	A	A	A
Name	None	RES0_R81	RES0_R71	RES0_R61	RES0_R41	RES0_R31	RES0_R11	RES0_R01

Bits	Name	Description
30	RES0_R81	see corresponding bit in OA0_SW Default Value: 0
29	RES0_R71	see corresponding bit in OA0_SW Default Value: 0
28	RES0_R61	see corresponding bit in OA0_SW Default Value: 0
27	RES0_R41	see corresponding bit in OA0_SW Default Value: 0
26	RES0_R31	see corresponding bit in OA0_SW Default Value: 0
25	RES0_R11	see corresponding bit in OA0_SW Default Value: 0
24	RES0_R01	see corresponding bit in OA0_SW Default Value: 0
23	OA0O_D81	see corresponding bit in OA0_SW Default Value: 0

6.1.33 CTB1_OA0_SW_CLEAR (continued)

22	OA0O_D71	see corresponding bit in OA0_SW Default Value: 0
21	OA0O_D51	see corresponding bit in OA0_SW Default Value: 0
20	OA0O_D31	see corresponding bit in OA0_SW Default Value: 0
19	OA0M_A91	see corresponding bit in OA0_SW Default Value: 0
18	OA0M_A81	see corresponding bit in OA0_SW Default Value: 0
17	OA0M_A71	see corresponding bit in OA0_SW Default Value: 0
16	OA0M_A61	see corresponding bit in OA0_SW Default Value: 0
15	OA0M_A51	see corresponding bit in OA0_SW Default Value: 0
14	OA0M_A41	see corresponding bit in OA0_SW Default Value: 0
13	OA0M_A31	see corresponding bit in OA0_SW Default Value: 0
11	OA0M_A11	see corresponding bit in OA0_SW Default Value: 0
9	OA0P_A90	see corresponding bit in OA0_SW Default Value: 0
8	OA0P_A80	see corresponding bit in OA0_SW Default Value: 0
7	OA0P_A70	see corresponding bit in OA0_SW Default Value: 0
6	OA0P_A60	see corresponding bit in OA0_SW Default Value: 0
5	OA0P_A50	see corresponding bit in OA0_SW Default Value: 0
4	OA0P_A40	see corresponding bit in OA0_SW Default Value: 0
3	OA0P_A30	see corresponding bit in OA0_SW Default Value: 0
2	OA0P_A20	see corresponding bit in OA0_SW Default Value: 0
1	OA0P_A10	see corresponding bit in OA0_SW Default Value: 0
0	OA0P_A00	see corresponding bit in OA0_SW Default Value: 0

6.1.34 CTB1_OA1_SW

Opamp1 switch control

Address: 0x40310088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA1P_A73	OA1P_A63	OA1P_A53	OA1P_A43	OA1P_A33	OA1P_A23	OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
Name	OA1M_A52	OA1M_A42	OA1M_A32	OA1M_A22	None [11:10]		OA1P_A93	OA1P_A83

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	OA1O_D72	OA1O_D62	OA1O_D52	OA1O_D42	OA1M_A92	OA1M_A82	OA1M_A72	OA1M_A62

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	RES1_R92	RES1_R82	RES1_R72	RES1_R62	RES1_R52	RES1_R32	RES1_R02	OA1O_D82

Bits	Name	Description
31	RES1_R92	Resistor1 tap to Opamp0 positive terminal Default Value: 0
30	RES1_R82	Resistor1 tap to Opamp1 positive terminal Default Value: 0
29	RES1_R72	Resistor1 tap to Opamp1 negative terminal Default Value: 0
28	RES1_R62	Resistor1 bottom to VSSA Default Value: 0
27	RES1_R52	Resistor1 bottom to Resistor0 bottom Default Value: 0
26	RES1_R32	Resistor1 bottom to Opamp1 negative terminal Default Value: 0
25	RES1_R02	Resistor1 bottom to pin P4 Default Value: 0
24	OA1O_D82	Opamp1 output switch to short 1x with 10x drive Default Value: 0

6.1.34 CTB1_OA1_SW (continued)

23	OA1O_D72	Opamp1 output to vref1 Default Value: 0
22	OA1O_D62	Opamp1 output to ctbbus3 Default Value: 0
21	OA1O_D52	Opamp1 output to ctbbus2 Default Value: 0
20	OA1O_D42	Opamp1 output to ctbbus1 Default Value: 0
19	OA1M_A92	Opamp1 negative terminal to pin P3 Default Value: 0
18	OA1M_A82	Opamp1 negative terminal to Opamp1 bottom Default Value: 0
17	OA1M_A72	Opamp1 negative terminal to vref1 Default Value: 0
16	OA1M_A62	Opamp1 negative terminal to ctbbus3 Default Value: 0
15	OA1M_A52	Opamp1 negative terminal to ctbbus2 Default Value: 0
14	OA1M_A42	Opamp1 negative terminal to ctbbus1 Default Value: 0
13	OA1M_A32	Opamp1 negative terminal to ctbbus0 Default Value: 0
12	OA1M_A22	Opamp1 negative terminal to pin P4 Default Value: 0
9	OA1P_A93	Opamp1 positive terminal to uabin1 Default Value: 0
8	OA1P_A83	Opamp1 positive terminal to uabin0 Default Value: 0
7	OA1P_A73	Opamp1 positive terminal to vref1 Default Value: 0
6	OA1P_A63	Opamp1 positive terminal to ctbbus3 Default Value: 0
5	OA1P_A53	Opamp1 positive terminal to ctbbus2 Default Value: 0
4	OA1P_A43	Opamp1 positive terminal to ctbbus1 Default Value: 0
3	OA1P_A33	Opamp1 positive terminal to ctbbus0 Default Value: 0
2	OA1P_A23	Opamp1 positive terminal to pin P4 Default Value: 0
1	OA1P_A13	Opamp1 positive terminal to pin P5 Default Value: 0
0	OA1P_A03	Opamp1 positive terminal to amuxbusb Default Value: 0

6.1.35 CTB1_OA1_SW_CLEAR

Opamp1 switch control clear

Address: 0x4031008C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA1P_A73	OA1P_A63	OA1P_A53	OA1P_A43	OA1P_A33	OA1P_A23	OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	A	A	A	A	None		A	A
Name	OA1M_A52	OA1M_A42	OA1M_A32	OA1M_A22	None [11:10]		OA1P_A93	OA1P_A83

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	OA1O_D72	OA1O_D62	OA1O_D52	OA1O_D42	OA1M_A92	OA1M_A82	OA1M_A72	OA1M_A62

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	RES1_R92	RES1_R82	RES1_R72	RES1_R62	RES1_R52	RES1_R32	RES1_R02	OA1O_D82

Bits	Name	Description
31	RES1_R92	see corresponding bit in OA1_SW Default Value: 0
30	RES1_R82	see corresponding bit in OA1_SW Default Value: 0
29	RES1_R72	see corresponding bit in OA1_SW Default Value: 0
28	RES1_R62	see corresponding bit in OA1_SW Default Value: 0
27	RES1_R52	see corresponding bit in OA1_SW Default Value: 0
26	RES1_R32	see corresponding bit in OA1_SW Default Value: 0
25	RES1_R02	see corresponding bit in OA1_SW Default Value: 0
24	OA1O_D82	see corresponding bit in OA1_SW Default Value: 0

6.1.35 CTB1_OA1_SW_CLEAR (continued)

23	OA1O_D72	see corresponding bit in OA1_SW Default Value: 0
22	OA1O_D62	see corresponding bit in OA1_SW Default Value: 0
21	OA1O_D52	see corresponding bit in OA1_SW Default Value: 0
20	OA1O_D42	see corresponding bit in OA1_SW Default Value: 0
19	OA1M_A92	see corresponding bit in OA1_SW Default Value: 0
18	OA1M_A82	see corresponding bit in OA1_SW Default Value: 0
17	OA1M_A72	see corresponding bit in OA1_SW Default Value: 0
16	OA1M_A62	see corresponding bit in OA1_SW Default Value: 0
15	OA1M_A52	see corresponding bit in OA1_SW Default Value: 0
14	OA1M_A42	see corresponding bit in OA1_SW Default Value: 0
13	OA1M_A32	see corresponding bit in OA1_SW Default Value: 0
12	OA1M_A22	see corresponding bit in OA1_SW Default Value: 0
9	OA1P_A93	see corresponding bit in OA1_SW Default Value: 0
8	OA1P_A83	see corresponding bit in OA1_SW Default Value: 0
7	OA1P_A73	see corresponding bit in OA1_SW Default Value: 0
6	OA1P_A63	see corresponding bit in OA1_SW Default Value: 0
5	OA1P_A53	see corresponding bit in OA1_SW Default Value: 0
4	OA1P_A43	see corresponding bit in OA1_SW Default Value: 0
3	OA1P_A33	see corresponding bit in OA1_SW Default Value: 0
2	OA1P_A23	see corresponding bit in OA1_SW Default Value: 0
1	OA1P_A13	see corresponding bit in OA1_SW Default Value: 0
0	OA1P_A03	see corresponding bit in OA1_SW Default Value: 0

6.1.36 CTB1_CTBBUS_SW

CTB bus switch control

Address: 0x40310090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	CB0_P07	CB0_P06	CB0_P05	CB0_P04	CB0_P03	CB0_P02	CB0_P01	CB0_P00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	CB2_P26	CB2_P24	CB2_P22	CB2_P20	CB1_P17	CB1_P15	CB1_P13	CB1_P11

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	CB3_G63	CB2_G53	CB1_G43	CB0_G33	CB3_P37	CB3_P35	CB3_P33	CB3_P31

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [31:29]			CB2_G50	CB3_G61	CB2_G52	CB1_G41	CB0_G32

Bits	Name	Description
28	CB2_G50	ctbbus2 ctbbus3 Default Value: 0
27	CB3_G61	ctbbus3 sarbus1 Default Value: 0
26	CB2_G52	ctbbus2 sarbus0 Default Value: 0
25	CB1_G41	ctbbus1 sarbus1 Default Value: 0
24	CB0_G32	ctbbus0 sarbus0 Default Value: 0
23	CB3_G63	ctbbus3 right neighbor Default Value: 0
22	CB2_G53	ctbbus2 right neighbor Default Value: 0
21	CB1_G43	ctbbus1 right neighbor Default Value: 0

6.1.36 CTB1_CTBBUS_SW (continued)

20	CB0_G33	ctbbus0 right neighbor Default Value: 0
19	CB3_P37	P7 ctbbus3 Default Value: 0
18	CB3_P35	P5 ctbbus3 Default Value: 0
17	CB3_P33	P3 ctbbus3 Default Value: 0
16	CB3_P31	P1 ctbbus3 Default Value: 0
15	CB2_P26	P6 ctbbus2 Default Value: 0
14	CB2_P24	P4 ctbbus2 Default Value: 0
13	CB2_P22	P2 ctbbus2 Default Value: 0
12	CB2_P20	P0 ctbbus2 Default Value: 0
11	CB1_P17	P7 ctbbus1 Default Value: 0
10	CB1_P15	P5 ctbbus1 Default Value: 0
9	CB1_P13	P3 ctbbus1 Default Value: 0
8	CB1_P11	P1 ctbbus1 Default Value: 0
7	CB0_P07	P7 ctbbus0 Default Value: 0
6	CB0_P06	P6 ctbbus0 Default Value: 0
5	CB0_P05	P5 ctbbus0 Default Value: 0
4	CB0_P04	P4 ctbbus0 Default Value: 0
3	CB0_P03	P3 ctbbus0 Default Value: 0
2	CB0_P02	P2 ctbbus0 Default Value: 0
1	CB0_P01	P1 ctbbus0 Default Value: 0
0	CB0_P00	P0 ctbbus0 Default Value: 0

6.1.37 CTB1_CTBBUS_SW_CLEAR

CTB bus switch control clear

Address: 0x40310094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	CB0_P07	CB0_P06	CB0_P05	CB0_P04	CB0_P03	CB0_P02	CB0_P01	CB0_P00

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	CB2_P26	CB2_P24	CB2_P22	CB2_P20	CB1_P17	CB1_P15	CB1_P13	CB1_P11

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	CB3_G63	CB2_G53	CB1_G43	CB0_G33	CB3_P37	CB3_P35	CB3_P33	CB3_P31

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None			A	A	A	A	A
Name	None [31:29]			CB2_G50	CB3_G61	CB2_G52	CB1_G41	CB0_G32

Bits	Name	Description
28	CB2_G50	see corresponding bit in CTBBUS_SW Default Value: 0
27	CB3_G61	see corresponding bit in CTBBUS_SW Default Value: 0
26	CB2_G52	see corresponding bit in CTBBUS_SW Default Value: 0
25	CB1_G41	see corresponding bit in CTBBUS_SW Default Value: 0
24	CB0_G32	see corresponding bit in CTBBUS_SW Default Value: 0
23	CB3_G63	see corresponding bit in CTBBUS_SW Default Value: 0
22	CB2_G53	see corresponding bit in CTBBUS_SW Default Value: 0
21	CB1_G43	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.37 CTB1_CTBBUS_SW_CLEAR (continued)

20	CB0_G33	see corresponding bit in CTBBUS_SW Default Value: 0
19	CB3_P37	see corresponding bit in CTBBUS_SW Default Value: 0
18	CB3_P35	see corresponding bit in CTBBUS_SW Default Value: 0
17	CB3_P33	see corresponding bit in CTBBUS_SW Default Value: 0
16	CB3_P31	see corresponding bit in CTBBUS_SW Default Value: 0
15	CB2_P26	see corresponding bit in CTBBUS_SW Default Value: 0
14	CB2_P24	see corresponding bit in CTBBUS_SW Default Value: 0
13	CB2_P22	see corresponding bit in CTBBUS_SW Default Value: 0
12	CB2_P20	see corresponding bit in CTBBUS_SW Default Value: 0
11	CB1_P17	see corresponding bit in CTBBUS_SW Default Value: 0
10	CB1_P15	see corresponding bit in CTBBUS_SW Default Value: 0
9	CB1_P13	see corresponding bit in CTBBUS_SW Default Value: 0
8	CB1_P11	see corresponding bit in CTBBUS_SW Default Value: 0
7	CB0_P07	see corresponding bit in CTBBUS_SW Default Value: 0
6	CB0_P06	see corresponding bit in CTBBUS_SW Default Value: 0
5	CB0_P05	see corresponding bit in CTBBUS_SW Default Value: 0
4	CB0_P04	see corresponding bit in CTBBUS_SW Default Value: 0
3	CB0_P03	see corresponding bit in CTBBUS_SW Default Value: 0
2	CB0_P02	see corresponding bit in CTBBUS_SW Default Value: 0
1	CB0_P01	see corresponding bit in CTBBUS_SW Default Value: 0
0	CB0_P00	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.38 CTB1_CTB_SW_HW_CTRL

CTB bus switch control status

Address: 0x403100C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	P7_HW_CTRL01	P6_HW_CTRL01	P5_HW_CTRL01	P4_HW_CTRL01	P3_HW_CTRL01	P2_HW_CTRL01	P1_HW_CTRL01	P0_HW_CTRL01

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	P7_HW_CTRL23	P6_HW_CTRL23	P5_HW_CTRL23	P4_HW_CTRL23	P3_HW_CTRL23	P2_HW_CTRL23	P1_HW_CTRL23	P0_HW_CTRL23

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						SARBUS1_HW_CTRL	SARBUS0_HW_CTRL

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	SARBUS1_HW_CTRL	sarbus1 switches (G41, G61) Default Value: 0
16	SARBUS0_HW_CTRL	sarbus0 switches (G32, G52) Default Value: 0
15	P7_HW_CTRL23	for P37 Default Value: 0
14	P6_HW_CTRL23	for P26 Default Value: 0
13	P5_HW_CTRL23	for P35 Default Value: 0
12	P4_HW_CTRL23	for P24 Default Value: 0
11	P3_HW_CTRL23	for P33, D52, D62 Default Value: 0

6.1.38 CTB1_CTB_SW_HW_CTRL (continued)

10	P2_HW_CTRL23	for P22, D51 Default Value: 0
9	P1_HW_CTRL23	for P31 Default Value: 0
8	P0_HW_CTRL23	for P20 Default Value: 0
7	P7_HW_CTRL01	for P07, P17 Default Value: 0
6	P6_HW_CTRL01	for P06 Default Value: 0
5	P5_HW_CTRL01	for P05, P15 Default Value: 0
4	P4_HW_CTRL01	for P04 Default Value: 0
3	P3_HW_CTRL01	for P03, P13 Default Value: 0
2	P2_HW_CTRL01	for P02 Default Value: 0
1	P1_HW_CTRL01	for P01, P11 Default Value: 0
0	P0_HW_CTRL01	for P00 Default Value: 0

6.1.39 CTB1_CTB_SW_STATUS

CTB bus switch control status

Address: 0x403100C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	CB0_P07_STAT	CB0_P06_STAT	CB0_P05_STAT	CB0_P04_STAT	CB0_P03_STAT	CB0_P02_STAT	CB0_P01_STAT	CB0_P00_STAT

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	CB2_P26_STAT	CB2_P24_STAT	CB2_P22_STAT	CB2_P20_STAT	CB1_P17_STAT	CB1_P15_STAT	CB1_P13_STAT	CB1_P11_STAT

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	CB3_G63_STAT	CB2_G53_STAT	CB1_G43_STAT	CB0_G33_STAT	CB3_P37_STAT	CB3_P35_STAT	CB3_P33_STAT	CB3_P31_STAT

Bits	31	30	29	28	27	26	25	24
SW Access	None	R	R	R	R	R	R	R
HW Access	None	W	W	W	W	W	W	W
Name	None	OA1O_D62_STAT	OA1O_D52_STAT	OA0O_D51_STAT	CB3_G61_STAT	CB2_G52_STAT	CB1_G41_STAT	CB0_G32_STAT

Bits	Name	Description
30	OA1O_D62_STAT	see OA1O_D62 bit in OA1_SW Default Value: 0
29	OA1O_D52_STAT	see OA1O_D52 bit in OA1_SW Default Value: 0
28	OA0O_D51_STAT	see OA0O_D51 bit in OA0_SW Default Value: 0
27	CB3_G61_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
26	CB2_G52_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
25	CB1_G41_STAT	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.39 CTB1_CTB_SW_STATUS (continued)

24	CB0_G32_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
23	CB3_G63_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
22	CB2_G53_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
21	CB1_G43_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
20	CB0_G33_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
19	CB3_P37_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
18	CB3_P35_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
17	CB3_P33_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
16	CB3_P31_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
15	CB2_P26_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
14	CB2_P24_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
13	CB2_P22_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
12	CB2_P20_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
11	CB1_P17_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
10	CB1_P15_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
9	CB1_P13_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
8	CB1_P11_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
7	CB0_P07_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
6	CB0_P06_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
5	CB0_P05_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
4	CB0_P04_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
3	CB0_P03_STAT	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.39 CTB1_CTB_SW_STATUS (continued)

2	CB0_P02_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
1	CB0_P01_STAT	see corresponding bit in CTBBUS_SW Default Value: 0
0	CB0_P00_STAT	see corresponding bit in CTBBUS_SW Default Value: 0

6.1.40 CTB1_OA0_OFFSET_TRIM

Opamp0 trim control

Address: 0x40310F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_OFFSET_TRIM	Opamp0 offset trim Default Value: 0

6.1.41 CTB1_OA0_SLOPE_OFFSET_TRIM

Opamp0 trim control

Address: 0x40310F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_SLOPE_OFFSET_TRIM	Opamp0 slope offset drift trim Default Value: 0

6.1.42 CTB1_OA0_COMP_TRIM

Opamp0 trim control

Address: 0x40310F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA0_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA0_COMP_TRIM	Opamp0 Compensation Capacitor Trim Default Value: 0

6.1.43 CTB1_OA1_OFFSET_TRIM

Opamp1 trim control

Address: 0x40310F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_OFFSET_TRIM	Opamp1 offset trim Default Value: 0

6.1.44 CTB1_OA1_SLOPE_OFFSET_TRIM

Opamp1 trim control

Address: 0x40310F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_SLOPE_OFFSET_TRIM	Opamp1 slope offset drift trim Default Value: 0

6.1.45 CTB1_OA1_COMP_TRIM

Opamp1 trim control

Address: 0x40310F14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA1_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA1_COMP_TRIM	Opamp1 Compensation Capacitor Trim Default Value: 0

6.1.46 CTB1_RMP_TRIM

Risk Mitigation bits

Address: 0x40310F18

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				RMP_TRIM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	RMP_TRIM	Risk Mitigation Trim bits Default Value: 0

7 Direct-Memory Access Registers

This section discusses the Direct-Memory Access registers. It lists all the registers in mapping tables, in address order.

7.1 Register Details

Register Name	Address
DMAC_CTL	0x40101000
DMAC_STATUS	0x40101010
DMAC_STATUS_SRC_ADDR	0x40101014
DMAC_STATUS_DST_ADDR	0x40101018
DMAC_STATUS_CH_ACT	0x4010101C
DMAC_CH_CTL0	0x40101080
DMAC_CH_CTL1	0x40101084
DMAC_CH_CTL2	0x40101088
DMAC_CH_CTL3	0x4010108C
DMAC_CH_CTL4	0x40101090
DMAC_CH_CTL5	0x40101094
DMAC_CH_CTL6	0x40101098
DMAC_CH_CTL7	0x4010109C
DMAC_INTR	0x401017F0
DMAC_INTR_SET	0x401017F4
DMAC_INTR_MASK	0x401017F8
DMAC_INTR_MASKED	0x401017FC

7.1.1 DMAC_CTL

Control register

Address: 0x40101000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLED	None [30:24]						

Bits	Name	Description
31	ENABLED	0': DMA is disabled: - INTR register is set to "0". - DW/DMA functionality is aborted. - DW/DMA controller input/pending triggers are de-activated. - DW/DMA controller output triggers are de-activated. Disabling the DMA has the same effect as an active "rst_sys_act_n" reset in DeepSleep power mode. To prevent a loss of active (pending) DW/DMA triggers when disabling the DMA or when transitioning from Active to DeepSleep power mode, the STATUS.ACTIVE and STATUS_CH_ACTIVE.CH fields can be used. '1': DMA is enabled. Default Value: 0

7.1.2 DMAC_STATUS

Status register

Address: 0x40101010

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					R		
HW Access	None					W		
Name	None [23:19]					CH_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R		None	R		
HW Access	W	W	W		None	W		
Name	ACTIVE	PING_PONG	PRIO [29:28]		None	STATE [26:24]		

Bits	Name	Description
31	ACTIVE	Specifies if there is a currently active (pending) channel in the data transfer engine: 0: no currently active channel. 1: currently active channel. Default Value: 0
30	PING_PONG	Specifies whether the PING descriptor (0) or PONG descriptor (1) of the channel is currently in use. Default Value: Undefined
29 : 28	PRIO	Specifies the priority of the currently active channel. Default Value: Undefined
26 : 24	STATE	State of the data transfer engine. 0: DEFAULT state. 1: Loading descriptor (SRC, DST, CONTROL and STATUS words). 2: Loading data element from source location. 3: Storing data element to destination location. 4: Storing descriptor (STATUS word). 5: Wait for trigger de-activation. 6: Storing descriptor with error response (STATUS word). Default Value: 0

7.1.2 DMAC_STATUS (continued)

18 : 16	CH_ADDR	Specifies the channel number of the currently active channel. If channel 7 is active, STATUS.ACTIVE is '1' and STATUS.CH_ADDR is "7". Default Value: Undefined
15 : 0	DATA_NR	Specifies the index of the currently active data transfer. This value increases from "0" to CONTROL.DATA_NR. Default Value: Undefined

7.1.3 DMAC_STATUS_SRC_ADDR

Source address status register

Address: 0x40101014

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address or current address of source location of currently active channel. The specific address information is cycle dependent. This is field is provided for debug purposes. Functionally, no assumption should be made on whether the base or current address is provided. The specifics of the currently active channel are available through STATUS. Note while reading the STATUS, STATUS_SRC and STATUS_DST registers, the transfer engine may have moved from one active channel to another. Default Value: Undefined

7.1.4 DMAC_STATUS_DST_ADDR

Destination address register

Address: 0x40101018

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address or current address of destination location of currently active channel. The specific address information is cycle dependent. This is field is provided for debug purposes. Functionally, no assumption should be made on whether the base or current address is provided. The specifics of the currently active channel are available through STATUS. Note while reading the STATUS, STATUS_SRC and STATUS_DST registers, the transfer engine may have moved from one active channel to another. Default Value: Undefined

7.1.5 DMAC_STATUS_CH_ACT

Channel activation status register

Address: 0x4010101C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	CH	Channel activation status. Bit i is associated to channel i. Software reads this field to get information on all actively pending channels (either in pending or in the data transfer engine). Default Value: 0

7.1.6 DMAC_CH_CTL0

Channel control register

Address: 0x40101080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.6 DMAC_CH_CTL0 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.7 DMAC_CH_CTL1

Channel control register

Address: 0x40101084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.7 DMAC_CH_CTL1 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.8 DMAC_CH_CTL2

Channel control register

Address: 0x40101088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.8 DMAC_CH_CTL2 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.9 DMAC_CH_CTL3

Channel control register

Address: 0x4010108C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.9 DMAC_CH_CTL3 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.10 DMAC_CH_CTL4

Channel control register

Address: 0x40101090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.10 DMAC_CH_CTL4 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.11 DMAC_CH_CTL5

Channel control register

Address: 0x40101094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.11 DMAC_CH_CTL5 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.12 DMAC_CH_CTL6

Channel control register

Address: 0x40101098

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.12 DMAC_CH_CTL6 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.13 DMAC_CH_CTL7

Channel control register

Address: 0x4010109C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	0: channel disabled. The channels trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. 1: channel enabled. Software sets this field to 1 to enable a specific channel. Hardware sets this field to 0 on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channels descriptor structure). Default Value: 0

7.1.13 DMAC_CH_CTL7 (continued)

30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to 1. Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING (0) and PONG (1). This field identifies the descriptor structure that is currently in use by the controller. Default Value: 0
29 : 28	PRIO	Channel priority, with 0 representing the highest priority and 3 representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.14 DMAC_INTR

Interrupt register

Address: 0x401017F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	CH	Set to '1', when event is detected. Write INTR field with '1', to clear bit. Write INTR_SET field with '1', to set bit. Default Value: 0

7.1.15 DMAC_INTR_SET

Interrupt set register

Address: 0x401017F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	CH	Write INTR_SET field with '1' to set corresponding INTR field (a write of '0' has no effect). Default Value: 0

7.1.16 DMAC_INTR_MASK

Interrupt mask register

Address: 0x401017F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	CH	Mask for corresponding field in INTR register. Default Value: 0

7.1.17 DMAC_INTR_MASKED

Interrupt masked register

Address: 0x401017FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	CH	Logical and of corresponding request and mask fields. Default Value: 0

8 Direct-Memory Access Descriptor Registers

This section discusses the Direct-Memory Access Descriptor registers. It lists all the registers in mapping tables, in address order.

8.1 Register Details

Register Name	Address
DMAC_DESCR0_PING_SRC	0x40101800
DMAC_DESCR0_PING_DST	0x40101804
DMAC_DESCR0_PING_CTL	0x40101808
DMAC_DESCR0_PING_STATUS	0x4010180C
DMAC_DESCR0_PONG_SRC	0x40101810
DMAC_DESCR0_PONG_DST	0x40101814
DMAC_DESCR0_PONG_CTL	0x40101818
DMAC_DESCR0_PONG_STATUS	0x4010181C
DMAC_DESCR1_PING_SRC	0x40101820
DMAC_DESCR1_PING_DST	0x40101824
DMAC_DESCR1_PING_CTL	0x40101828
DMAC_DESCR1_PING_STATUS	0x4010182C
DMAC_DESCR1_PONG_SRC	0x40101830
DMAC_DESCR1_PONG_DST	0x40101834
DMAC_DESCR1_PONG_CTL	0x40101838
DMAC_DESCR1_PONG_STATUS	0x4010183C
DMAC_DESCR2_PING_SRC	0x40101840
DMAC_DESCR2_PING_DST	0x40101844
DMAC_DESCR2_PING_CTL	0x40101848
DMAC_DESCR2_PING_STATUS	0x4010184C
DMAC_DESCR2_PONG_SRC	0x40101850
DMAC_DESCR2_PONG_DST	0x40101854
DMAC_DESCR2_PONG_CTL	0x40101858
DMAC_DESCR2_PONG_STATUS	0x4010185C
DMAC_DESCR3_PING_SRC	0x40101860
DMAC_DESCR3_PING_DST	0x40101864
DMAC_DESCR3_PING_CTL	0x40101868

Register Name	Address
DMAC_DESCR3_PING_STATUS	0x4010186C
DMAC_DESCR3_PONG_SRC	0x40101870
DMAC_DESCR3_PONG_DST	0x40101874
DMAC_DESCR3_PONG_CTL	0x40101878
DMAC_DESCR3_PONG_STATUS	0x4010187C
DMAC_DESCR4_PING_SRC	0x40101880
DMAC_DESCR4_PING_DST	0x40101884
DMAC_DESCR4_PING_CTL	0x40101888
DMAC_DESCR4_PING_STATUS	0x4010188C
DMAC_DESCR4_PONG_SRC	0x40101890
DMAC_DESCR4_PONG_DST	0x40101894
DMAC_DESCR4_PONG_CTL	0x40101898
DMAC_DESCR4_PONG_STATUS	0x4010189C
DMAC_DESCR5_PING_SRC	0x401018A0
DMAC_DESCR5_PING_DST	0x401018A4
DMAC_DESCR5_PING_CTL	0x401018A8
DMAC_DESCR5_PING_STATUS	0x401018AC
DMAC_DESCR5_PONG_SRC	0x401018B0
DMAC_DESCR5_PONG_DST	0x401018B4
DMAC_DESCR5_PONG_CTL	0x401018B8
DMAC_DESCR5_PONG_STATUS	0x401018BC
DMAC_DESCR6_PING_SRC	0x401018C0
DMAC_DESCR6_PING_DST	0x401018C4
DMAC_DESCR6_PING_CTL	0x401018C8
DMAC_DESCR6_PING_STATUS	0x401018CC
DMAC_DESCR6_PONG_SRC	0x401018D0
DMAC_DESCR6_PONG_DST	0x401018D4
DMAC_DESCR6_PONG_CTL	0x401018D8
DMAC_DESCR6_PONG_STATUS	0x401018DC
DMAC_DESCR7_PING_SRC	0x401018E0
DMAC_DESCR7_PING_DST	0x401018E4
DMAC_DESCR7_PING_CTL	0x401018E8
DMAC_DESCR7_PING_STATUS	0x401018EC
DMAC_DESCR7_PONG_SRC	0x401018F0
DMAC_DESCR7_PONG_DST	0x401018F4
DMAC_DESCR7_PONG_CTL	0x401018F8
DMAC_DESCR7_PONG_STATUS	0x401018FC

8.1.1 DMAC_DESCR0_PING_SRC

Ping source address

Address: 0x40101800

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.2 DMAC_DESCR0_PING_DST

Ping destination address

Address: 0x40101804

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.3 DMAC_DESCR0_PING_CTL

Ping control word

Address: 0x40101808

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.3 DMAC_DESCR0_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.3 DMAC_DESCR0_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.3 DMAC_DESCR0_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.4 DMAC_DESCR0_PING_STATUS

Ping status word

Address: 0x4010180C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.4 DMAC_DESCR0_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.5 DMAC_DESCR0_PONG_SRC

Pong source address

Address: 0x40101810

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.6 DMAC_DESCR0_PONG_DST

Pong destination address

Address: 0x40101814

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.7 DMAC_DESCR0_PONG_CTL

Pong control word

Address: 0x40101818

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.7 DMAC_DESCR0_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.8 DMAC_DESCR0_PONG_STATUS

Pong status word

Address: 0x4010181C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.9 DMAC_DESCR1_PING_SRC

Ping source address

Address: 0x40101820

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.10 DMAC_DESCR1_PING_DST

Ping destination address

Address: 0x40101824

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.11 DMAC_DESCR1_PING_CTL

Ping control word

Address: 0x40101828

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.11 DMAC_DESCR1_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.11 DMAC_DESCR1_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.11 DMAC_DESCR1_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.12 DMAC_DESCR1_PING_STATUS

Ping status word

Address: 0x4010182C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.12 DMAC_DESCR1_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.13 DMAC_DESCR1_PONG_SRC

Pong source address

Address: 0x40101830

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.14 DMAC_DESCR1_PONG_DST

Pong destination address

Address: 0x40101834

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.15 DMAC_DESCR1_PONG_CTL

Pong control word

Address: 0x40101838

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.15 DMAC_DESCR1_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.16 DMAC_DESCR1_PONG_STATUS

Pong status word

Address: 0x4010183C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.17 DMAC_DESCR2_PING_SRC

Ping source address

Address: 0x40101840

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.18 DMAC_DESCR2_PING_DST

Ping destination address

Address: 0x40101844

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.19 DMAC_DESCR2_PING_CTL

Ping control word

Address: 0x40101848

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.19 DMAC_DESCR2_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.19 DMAC_DESCR2_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.19 DMAC_DESCR2_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.20 DMAC_DESCR2_PING_STATUS

Ping status word

Address: 0x4010184C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.20 DMAC_DESCR2_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.21 DMAC_DESCR2_PONG_SRC

Pong source address

Address: 0x40101850

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.22 DMAC_DESCR2_PONG_DST

Pong destination address

Address: 0x40101854

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.23 DMAC_DESCR2_PONG_CTL

Pong control word

Address: 0x40101858

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.23 DMAC_DESCR2_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.24 DMAC_DESCR2_PONG_STATUS

Pong status word

Address: 0x4010185C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.25 DMAC_DESCR3_PING_SRC

Ping source address

Address: 0x40101860

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.26 DMAC_DESCR3_PING_DST

Ping destination address

Address: 0x40101864

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.27 DMAC_DESCR3_PING_CTL

Ping control word

Address: 0x40101868

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.27 DMAC_DESCR3_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.27 DMAC_DESCR3_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.27 DMAC_DESCR3_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.28 DMAC_DESCR3_PING_STATUS

Ping status word

Address: 0x4010186C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.28 DMAC_DESCR3_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.29 DMAC_DESCR3_PONG_SRC

Pong source address

Address: 0x40101870

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.30 DMAC_DESCR3_PONG_DST

Pong destination address

Address: 0x40101874

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.31 DMAC_DESCR3_PONG_CTL

Pong control word

Address: 0x40101878

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.31 DMAC_DESCR3_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.32 DMAC_DESCR3_PONG_STATUS

Pong status word

Address: 0x4010187C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.33 DMAC_DESCR4_PING_SRC

Ping source address

Address: 0x40101880

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.34 DMAC_DESCR4_PING_DST

Ping destination address

Address: 0x40101884

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.35 DMAC_DESCR4_PING_CTL

Ping control word

Address: 0x40101888

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.35 DMAC_DESCR4_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.35 DMAC_DESCR4_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.35 DMAC_DESCR4_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.36 DMAC_DESCR4_PING_STATUS

Ping status word

Address: 0x4010188C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.36 DMAC_DESCR4_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.37 DMAC_DESCR4_PONG_SRC

Pong source address

Address: 0x40101890

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.38 DMAC_DESCR4_PONG_DST

Pong destination address

Address: 0x40101894

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.39 DMAC_DESCR4_PONG_CTL

Pong control word

Address: 0x40101898

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.39 DMAC_DESCR4_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.40 DMAC_DESCR4_PONG_STATUS

Pong status word

Address: 0x4010189C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.41 DMAC_DESCR5_PING_SRC

Ping source address

Address: 0x401018A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.42 DMAC_DESCR5_PING_DST

Ping destination address

Address: 0x401018A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.43 DMAC_DESCR5_PING_CTL

Ping control word

Address: 0x401018A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.43 DMAC_DESCR5_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.43 DMAC_DESCR5_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.43 DMAC_DESCR5_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.44 DMAC_DESCR5_PING_STATUS

Ping status word

Address: 0x401018AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.44 DMAC_DESCR5_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.45 DMAC_DESCR5_PONG_SRC

Pong source address

Address: 0x401018B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.46 DMAC_DESCR5_PONG_DST

Pong destination address

Address: 0x401018B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.47 DMAC_DESCR5_PONG_CTL

Pong control word

Address: 0x401018B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.47 DMAC_DESCR5_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.48 DMAC_DESCR5_PONG_STATUS

Pong status word

Address: 0x401018BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.49 DMAC_DESCR6_PING_SRC

Ping source address

Address: 0x401018C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.50 DMAC_DESCR6_PING_DST

Ping destination address

Address: 0x401018C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.51 DMAC_DESCR6_PING_CTL

Ping control word

Address: 0x401018C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.51 DMAC_DESCR6_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.51 DMAC_DESCR6_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.51 DMAC_DESCR6_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.52 DMAC_DESCR6_PING_STATUS

Ping status word

Address: 0x401018CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.52 DMAC_DESCR6_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.53 DMAC_DESCR6_PONG_SRC

Pong source address

Address: 0x401018D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.54 DMAC_DESCR6_PONG_DST

Pong destination address

Address: 0x401018D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.55 DMAC_DESCR6_PONG_CTL

Pong control word

Address: 0x401018D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.55 DMAC_DESCR6_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.56 DMAC_DESCR6_PONG_STATUS

Pong status word

Address: 0x401018DC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.57 DMAC_DESCR7_PING_SRC

Ping source address

Address: 0x401018E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.58 DMAC_DESCR7_PING_DST

Ping destination address

Address: 0x401018E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.59 DMAC_DESCR7_PING_CTL

Ping control word

Address: 0x401018E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.59 DMAC_DESCR7_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptors STATUS word is 1): 0: A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). 1: A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. 2: A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CHi_CTL.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	1: On completion of the current descriptor structure, the current descriptor identifier CHi_CTL.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	1: Transfer is preemptable. In DMA mode (OPCODE is 1 or 2), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	1: On completion of the current descriptor structure, the interrupt cause field of the channel is set to 1 (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	1: On completion of the current descriptor structure, the VALID bit of the descriptors STATUS word is set to 0. Default Value: Undefined

8.1.59 DMAC_DESCR7_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controllers data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agents trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. 0: Do not wait for de-activation (for pulse sensitive triggers). 1: Wait for up to 4 cycles. 2: Wait for up to 8 cycles. 3: Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. 0: No increment, typically used for receive (RX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. 0 : No increment, typically used for transmit (TX) FIFO structures. 1: Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: 0: As specified by DATA_SIZE. 1: Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.59 DMAC_DESCR7_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: 0: Byte (8 bits). 1: Halfword (16 bits). 2: Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made 0) - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made 0) - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made 0) - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made 0) - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is 0) each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is 1 or 2) each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.60 DMAC_DESCR7_PING_STATUS

Ping status word

Address: 0x401018EC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	0: Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to 1). 1: Valid. Hardware set this field to 0 when a descriptor is done, but only if CONTROL.INV_DESCR is 1. Software sets this field to 1 when a descriptor is initialized. Default Value: Undefined

8.1.60 DMAC_DESCR7_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). 0/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to 1. STATUS.VALID is NOT affected. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to 0/NO_ERROR during descriptor initialization. 1/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to 1 if CONTROL.SET_CAUSE is 1. STATUS.VALID is set to 0 if CONTROL.INV_DESCR is 1. CHi_CTL.ENABLED is NOT affected. CHi_CTL.PING_PONG is updated if CONTROL.FLIPPING is 1. 2/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 3/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 4/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 5/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to 1. STATUS.VALID is set 0. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). 6/INVALID_DESCR: Invalid descriptor (STATUS.VALID is 0). This occurs when an activated channel has an invalid descriptor. CHi_CTL.ENABLED is set to 0. CHi_CTL.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be 1). At descriptor initialization, SW should set this field to 0. This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.61 DMAC_DESCR7_PONG_SRC

Pong source address

Address: 0x401018F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.62 DMAC_DESCR7_PONG_DST

Pong destination address

Address: 0x401018F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.63 DMAC_DESCR7_PONG_CTL

Pong control word

Address: 0x401018F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.63 DMAC_DESCR7_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.64 DMAC_DESCR7_PONG_STATUS

Pong status word

Address: 0x401018FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

9 Deep Sleep Amplifier Bias (DSAB) Registers

This section discusses the DSAB registers. It lists all the registers in mapping tables, in address order.

9.1 Register Details

Register Name	Address
PASS_DSAB_DSAB_CTRL	0x403F0E00
PASS_DSAB_DSAB_DFT	0x403F0E04

9.1.1 PASS_DSAB_DSAB_CTRL

global DSAB control

Address: 0x403F0E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		CURRENT_SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SEL_OUT [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				REF_SWAP_EN [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None		RW	None			RW
HW Access	R	None		R	None			R
Name	ENABLED	None [30:29]		STARTUP_RM	None [27:25]			BYPASS_MODE_EN

Bits	Name	Description
31	ENABLED	## ############### Default Value: 0
28	STARTUP_RM	Risk mitigation control 1 - Force start the startup circuit Default Value: 0
24	BYPASS_MODE_EN	0 - DSAB PTAT generator is powered from DSAB regulator: VDDA must be at least 2.4V 1 - DSAB PTAT generator is pwoered directly from VDDA: VDDA cannot exceed 4.0V Default Value: 0
19 : 16	REF_SWAP_EN	This field (along with SEL_OUT and ENABLED) provides bitwise selection of the current sources that drive the DSAB ZTC and PTAT outputs. See SEL_OUT field for truth tables. Default Value: 0
11 : 8	SEL_OUT	## ############### Default Value: 0

9.1.1 PASS_DSAB_DSAB_CTRL (continued)

5 : 0	CURRENT_SEL	DSAB DAC control field Nominal DSAB Output Current = CURRENT_SEL * 0.075 uA Default Value: 0

9.1.2 PASS_DSAB_DSAB_DFT

DFT bits

Address: 0x403F0E04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				EN_DFT [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	EN_DFT	- 0: DSAB DFT disabled - 1: DSAB DFT enabled (connect output to amuxbus) 0001 - PTAT<0> 0010 - PTAT<1> 0011 - PTAT<1:0> 0100 - PTAT<2> 0111 - PTAT<2:0> 1000 - PTAT<3> 1111 - PTAT<3:0> 1001 - DSAB Reg Out Default Value: 0

10 GPIO - Common Registers

This section discusses the GPIO registers. It lists all the registers in mapping tables, in address order.

10.1 Register Details

Register Name	Address
GPIO_INTR_CAUSE	0x40041000

10.1.1 GPIO_INTR_CAUSE

Interrupt port cause register

Address: 0x40041000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R					
HW Access	None		W					
Name	None [7:6]		PORT_INT [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	PORT_INT	Each IO port has an associated bit field in this register. The bit field reflects the IO port's interrupt line (bit field i reflects "gpio_interrupts[i]" for IO port i). The register is used when the system uses a shared/combined interrupt line "gpio_interrupt". The SW ISR reads the register to determine which IO port(s) is responsible for the shared/combined interrupt line "gpio_interrupt". Once, the IO port(s) is determined, the IO port's INTR register is read to determine the IO pad(s) in the IO port that caused the interrupt. Default Value: 0

11 GPIO - Port Specific Registers

This section discusses the GPIO Port registers. It lists all the registers in mapping tables, in address order.

11.1 Register Details

Register Name	Address
GPIO_PRT0_DR	0x40040000
GPIO_PRT0_PS	0x40040004
GPIO_PRT0_PC	0x40040008
GPIO_PRT0_INTR_CFG	0x4004000C
GPIO_PRT0_INTR	0x40040010
GPIO_PRT0_PC2	0x40040018
GPIO_PRT0_DR_SET	0x40040040
GPIO_PRT0_DR_CLR	0x40040044
GPIO_PRT0_DR_INV	0x40040048
GPIO_PRT1_DR	0x40040100
GPIO_PRT1_PS	0x40040104
GPIO_PRT1_PC	0x40040108
GPIO_PRT1_INTR_CFG	0x4004010C
GPIO_PRT1_INTR	0x40040110
GPIO_PRT1_PC2	0x40040118
GPIO_PRT1_DR_SET	0x40040140
GPIO_PRT1_DR_CLR	0x40040144
GPIO_PRT1_DR_INV	0x40040148
GPIO_PRT2_DR	0x40040200
GPIO_PRT2_PS	0x40040204
GPIO_PRT2_PC	0x40040208
GPIO_PRT2_INTR_CFG	0x4004020C
GPIO_PRT2_INTR	0x40040210
GPIO_PRT2_PC2	0x40040218
GPIO_PRT2_DR_SET	0x40040240
GPIO_PRT2_DR_CLR	0x40040244
GPIO_PRT2_DR_INV	0x40040248

Register Name	Address
GPIO_PRT3_DR	0x40040300
GPIO_PRT3_PS	0x40040304
GPIO_PRT3_PC	0x40040308
GPIO_PRT3_INTR_CFG	0x4004030C
GPIO_PRT3_INTR	0x40040310
GPIO_PRT3_PC2	0x40040318
GPIO_PRT3_DR_SET	0x40040340
GPIO_PRT3_DR_CLR	0x40040344
GPIO_PRT3_DR_INV	0x40040348
GPIO_PRT4_DR	0x40040400
GPIO_PRT4_PS	0x40040404
GPIO_PRT4_PC	0x40040408
GPIO_PRT4_INTR_CFG	0x4004040C
GPIO_PRT4_INTR	0x40040410
GPIO_PRT4_PC2	0x40040418
GPIO_PRT4_DR_SET	0x40040440
GPIO_PRT4_DR_CLR	0x40040444
GPIO_PRT4_DR_INV	0x40040448
GPIO_PRT5_DR	0x40040500
GPIO_PRT5_PS	0x40040504
GPIO_PRT5_PC	0x40040508
GPIO_PRT5_INTR_CFG	0x4004050C
GPIO_PRT5_INTR	0x40040510
GPIO_PRT5_PC2	0x40040518
GPIO_PRT5_DR_SET	0x40040540
GPIO_PRT5_DR_CLR	0x40040544
GPIO_PRT5_DR_INV	0x40040548

11.1.1 GPIO_PRT0_DR

Port output data register

Address: 0x40040000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

11.1.2 GPIO_PRT0_PS

Port IO pad state register

Address: 0x40040004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

11.1.2 GPIO_PRT0_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

11.1.3 GPIO_PRT0_PC

Port configuration register

Address: 0x40040008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This bit should always be 0. Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0

11.1.3 GPIO_PRT0_PC (continued)

14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. **0x7: PD_PU:** Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

11.1.4 GPIO_PRT0_INTR_CFG

Port interrupt configuration register

Address: 0x4004000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Sets which edge will trigger an IRQ for glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

11.1.4 GPIO_PRT0_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

11.1.5 GPIO_PRT0_INTR

Port interrupt status register

Address: 0x40040010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

11.1.5 GPIO_PRT0_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

11.1.6 GPIO_PRT0_PC2

Port configuration register 2

Address: 0x40040018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

11.1.6 GPIO_PRT0_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

11.1.7 GPIO_PRT0_DR_SET

Port output data set register

Address: 0x40040040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

11.1.8 GPIO_PRT0_DR_CLR

Port output data clear register

Address: 0x40040044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

11.1.9 GPIO_PRT0_DR_INV

Port output data invert register

Address: 0x40040048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

11.1.10 GPIO_PRT1_DR

Port output data register

Address: 0x40040100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

11.1.11 GPIO_PRT1_PS

Port IO pad state register

Address: 0x40040104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

11.1.11 GPIO_PRT1_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

11.1.12 GPIO_PRT1_PC

Port configuration register

Address: 0x40040108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This bit should always be 0. Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0

11.1.12 GPIO_PRT1_PC (continued)

14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. **0x7: PD_PU:** Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

11.1.13 GPIO_PRT1_INTR_CFG

Port interrupt configuration register

Address: 0x4004010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Sets which edge will trigger an IRQ for glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

11.1.13 GPIO_PRT1_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

11.1.14 GPIO_PRT1_INTR

Port interrupt status register

Address: 0x40040110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

11.1.14 GPIO_PRT1_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

11.1.15 GPIO_PRT1_PC2

Port configuration register 2

Address: 0x40040118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

11.1.15 GPIO_PRT1_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

11.1.16 GPIO_PRT1_DR_SET

Port output data set register

Address: 0x40040140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

11.1.17 GPIO_PRT1_DR_CLR

Port output data clear register

Address: 0x40040144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

11.1.18 GPIO_PRT1_DR_INV

Port output data invert register

Address: 0x40040148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

11.1.19 GPIO_PRT2_DR

Port output data register

Address: 0x40040200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

11.1.20 GPIO_PRT2_PS

Port IO pad state register

Address: 0x40040204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

11.1.20 GPIO_PRT2_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

11.1.21 GPIO_PRT2_PC

Port configuration register

Address: 0x40040208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This bit should always be 0. Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0

11.1.21 GPIO_PRT2_PC (continued)

14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. **0x7: PD_PU:** Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

11.1.22 GPIO_PRT2_INTR_CFG

Port interrupt configuration register

Address: 0x4004020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Sets which edge will trigger an IRQ for glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

11.1.22 GPIO_PRT2_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

11.1.23 GPIO_PRT2_INTR

Port interrupt status register

Address: 0x40040210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

11.1.23 GPIO_PRT2_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

11.1.24 GPIO_PRT2_PC2

Port configuration register 2

Address: 0x40040218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

11.1.24 GPIO_PRT2_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

11.1.25 GPIO_PRT2_DR_SET

Port output data set register

Address: 0x40040240

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

11.1.26 GPIO_PRT2_DR_CLR

Port output data clear register

Address: 0x40040244

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

11.1.27 GPIO_PRT2_DR_INV

Port output data invert register

Address: 0x40040248

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

11.1.28 GPIO_PRT3_DR

Port output data register

Address: 0x40040300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

11.1.29 GPIO_PRT3_PS

Port IO pad state register

Address: 0x40040304

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

11.1.29 GPIO_PRT3_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

11.1.30 GPIO_PRT3_PC

Port configuration register

Address: 0x40040308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This bit should always be 0. Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0

11.1.30 GPIO_PRT3_PC (continued)

14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. **0x7: PD_PU:** Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

11.1.31 GPIO_PRT3_INTR_CFG

Port interrupt configuration register

Address: 0x4004030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Sets which edge will trigger an IRQ for glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

11.1.31 GPIO_PRT3_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

11.1.32 GPIO_PRT3_INTR

Port interrupt status register

Address: 0x40040310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

11.1.32 GPIO_PRT3_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

11.1.33 GPIO_PRT3_PC2

Port configuration register 2

Address: 0x40040318

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

11.1.33 GPIO_PRT3_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

11.1.34 GPIO_PRT3_DR_SET

Port output data set register

Address: 0x40040340

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

11.1.35 GPIO_PRT3_DR_CLR

Port output data clear register

Address: 0x40040344

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

11.1.36 GPIO_PRT3_DR_INV

Port output data invert register

Address: 0x40040348

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

11.1.37 GPIO_PRT4_DR

Port output data register

Address: 0x40040400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW	RW
Name	None [7:2]						DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

11.1.38 GPIO_PRT4_PS

Port IO pad state register

Address: 0x40040404

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0
0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

11.1.39 GPIO_PRT4_PC

Port configuration register

Address: 0x40040408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW			RW		
HW Access	None		R			R		
Name	None [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This bit should always be 0. Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0

11.1.39 GPIO_PRT4_PC (continued)

0x0: OFF:
Mode 0 (analog mode): Output buffer off (high Z). Input buffer off.

0x1: INPUT:
Mode 1: Output buffer off (high Z). Input buffer on.

0x2: 0_PU:
Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on.

0x3: PD_1:
Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on.

0x4: 0_Z:
Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on.

0x5: Z_1:
Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on.

0x6: 0_1:
Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on.

0x7: PD_PU:
Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

11.1.40 GPIO_PRT4_INTR_CFG

Port interrupt configuration register

Address: 0x4004040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [7:4]				EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Sets which edge will trigger an IRQ for glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0

11.1.40 GPIO_PRT4_INTR_CFG (continued)

0x0: DISABLE:
Disabled

0x1: RISING:
Rising edge

0x2: FALLING:
Falling edge

0x3: BOTH:
Both rising and falling edges

11.1.41 GPIO_PRT4_INTR

Port interrupt status register

Address: 0x40040410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [7:2]						DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None						R	R
HW Access	None						W	W
Name	None [23:18]						PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

11.1.42 GPIO_PRT4_PC2

Port configuration register 2

Address: 0x40040418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

11.1.43 GPIO_PRT4_DR_SET

Port output data set register

Address: 0x40040440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

11.1.44 GPIO_PRT4_DR_CLR

Port output data clear register

Address: 0x40040444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

11.1.45 GPIO_PRT4_DR_INV

Port output data invert register

Address: 0x40040448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

11.1.46 GPIO_PRT5_DR

Port output data register

Address: 0x40040500

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				RW	RW	RW	RW
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

11.1.47 GPIO_PRT5_PS

Port IO pad state register

Address: 0x40040504

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0
0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

11.1.48 GPIO_PRT5_PC

Port configuration register

Address: 0x40040508

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			RW
HW Access	None				R			R
Name	None [15:12]				DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This bit should always be 0. Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0

11.1.48 GPIO_PRT5_PC (continued)

2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. **0x7: PD_PU:** Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

11.1.49 GPIO_PRT5_INTR_CFG

Port interrupt configuration register

Address: 0x4004050C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Sets which edge will trigger an IRQ for glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0

11.1.49 GPIO_PRT5_INTR_CFG (continued)

3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

11.1.50 GPIO_PRT5_INTR

Port interrupt status register

Address: 0x40040510

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [23:20]				PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0

11.1.50 GPIO_PRT5_INTR (continued)

1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

11.1.51 GPIO_PRT5_PC2

Port configuration register 2

Address: 0x40040518

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

11.1.52 GPIO_PRT5_DR_SET

Port output data set register

Address: 0x40040540

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

11.1.53 GPIO_PRT5_DR_CLR

Port output data clear register

Address: 0x40040544

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

11.1.54 GPIO_PRT5_DR_INV

Port output data invert register

Address: 0x40040548

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

12 High Speed IO Matrix (HSIOM) Registers

This section discusses the HSIOM common registers. It lists all the registers in mapping tables, in address order.

12.1 Register Details

Register Name	Address
HSIOM_AMUX_SPLIT_CTL0	0x40022100
HSIOM_AMUX_SPLIT_CTL1	0x40022104
HSIOM_AMUX_SPLIT_CTL2	0x40022108

12.1.1 HSIOM_AMUX_SPLIT_CTL0

AMUX splitter cell control

Address: 0x40022100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_BB_S0	SWITCH_BB_SR	SWITCH_BB_SL	None	SWITCH_AA_S0	SWITCH_AA_SR	SWITCH_AA_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

12.1.1 HSIOM_AMUX_SPLIT_CTL0 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

12.1.2 HSIOM_AMUX_SPLIT_CTL1

AMUX splitter cell control

Address: 0x40022104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_BB_S0	SWITCH_BB_SR	SWITCH_BB_SL	None	SWITCH_AA_S0	SWITCH_AA_SR	SWITCH_AA_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

12.1.2 HSIOM_AMUX_SPLIT_CTL1 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

12.1.3 HSIOM_AMUX_SPLIT_CTL2

AMUX splitter cell control

Address: 0x40022108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_BB_S0	SWITCH_BB_SR	SWITCH_BB_SL	None	SWITCH_AA_S0	SWITCH_AA_SR	SWITCH_AA_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

12.1.3 HSIOM_AMUX_SPLIT_CTL2 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

13 HSIOM - Port Specific Registers

This section discusses the HSIOM Port Specific registers. It lists all the registers in mapping tables, in address order.

13.1 Register Details

Register Name	Address
HSIOM_PORT_SEL0	0x40020000
HSIOM_PORT_SEL1	0x40020100
HSIOM_PORT_SEL2	0x40020200
HSIOM_PORT_SEL3	0x40020300
HSIOM_PORT_SEL4	0x40020400
HSIOM_PORT_SEL5	0x40020500

13.1.1 HSIOM_PORT_SEL0

Port selection register

Address: 0x40020000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

13.1.1 HSIOM_PORT_SEL0 (continued)

0x0: GPIO:
SW controlled GPIO.

0x1: GPIO_DSI:
Not applicable

0x2: DSI_DSI:
Not applicable

0x3: DSI_GPIO:
Not applicable

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

13.1.2 HSIOM_PORT_SEL1

Port selection register

Address: 0x40020100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

13.1.2 HSIOM_PORT_SEL1 (continued)

0x0: GPIO:
SW controlled GPIO.

0x1: GPIO_DSI:
Not applicable

0x2: DSI_DSI:
Not applicable

0x3: DSI_GPIO:
Not applicable

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

13.1.3 HSIOM_PORT_SEL2

Port selection register

Address: 0x40020200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

13.1.3 HSIOM_PORT_SEL2 (continued)

0x0: GPIO:
SW controlled GPIO.

0x1: GPIO_DSI:
Not applicable

0x2: DSI_DSI:
Not applicable

0x3: DSI_GPIO:
Not applicable

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

13.1.4 HSIOM_PORT_SEL3

Port selection register

Address: 0x40020300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

13.1.4 HSIOM_PORT_SEL3 (continued)

0x0: GPIO:
SW controlled GPIO.

0x1: GPIO_DSI:
Not applicable

0x2: DSI_DSI:
Not applicable

0x3: DSI_GPIO:
Not applicable

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

13.1.5 HSIOM_PORT_SEL4

Port selection register

Address: 0x40020400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO. **0x1: GPIO_DSI:** Not applicable **0x2: DSI_DSI:** Not applicable **0x3: DSI_GPIO:** Not applicable **0x4: CSD_SENSE:** CSD sense connection (analog mode) **0x5: CSD_SHIELD:** CSD shield connection (analog mode)

13.1.5 HSIOM_PORT_SEL4 (continued)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

13.1.6 HSIOM_PORT_SEL5

Port selection register

Address: 0x40020500

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO. **0x1: GPIO_DSI:** Not applicable **0x2: DSI_DSI:** Not applicable **0x3: DSI_GPIO:** Not applicable

13.1.6 HSIOM_PORT_SEL5 (continued)

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

14 LCD Registers

This section discusses the LCD registers. It lists all the registers in mapping tables, in address order.

14.1 Register Details

Register Name	Address
LCD_ID	0x400B0000
LCD_DIVIDER	0x400B0004
LCD_CONTROL	0x400B0008
LCD_DATA00	0x400B0100
LCD_DATA01	0x400B0104
LCD_DATA02	0x400B0108
LCD_DATA03	0x400B010C
LCD_DATA04	0x400B0110
LCD_DATA05	0x400B0114
LCD_DATA06	0x400B0118
LCD_DATA07	0x400B011C
LCD_DATA10	0x400B0200
LCD_DATA11	0x400B0204
LCD_DATA12	0x400B0208
LCD_DATA13	0x400B020C
LCD_DATA14	0x400B0210
LCD_DATA15	0x400B0214
LCD_DATA16	0x400B0218
LCD_DATA17	0x400B021C

14.1.1 LCD_ID

ID & Revision

Address: 0x400B0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	REVISION [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	REVISION [31:24]							

Bits	Name	Description
31 : 16	REVISION	The version number is 0x0001 Default Value: 1
15 : 0	ID	The ID of LCD controller peripheral is 0xF0F0 Default Value: 61680

14.1.2 LCD_DIVIDER

LCD Divider Register

Address: 0x400B0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SUBFR_DIV [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	SUBFR_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DEAD_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DEAD_DIV [31:24]							

Bits	Name	Description
31 : 16	DEAD_DIV	Length of the dead time period in cycles. When set to zero, no dead time period exists. Default Value: 0
15 : 0	SUBFR_DIV	Input clock frequency divide value, to generate the 1/4 sub-frame period. The sub-frame period is 4*(SUBFR_DIV+1) cycles long. Default Value: 0

14.1.3 LCD_CONTROL

LCD Configuration Register

Address: 0x400B0008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW	RW	RW	RW	RW
HW Access	None	R		R	R	R	R	R
Name	None	BIAS [6:5]		OP_MODE	TYPE	LCD_MODE	HS_EN	LS_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				COM_NUM [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	LS_EN_STAT	None [30:24]						

Bits	Name	Description
31	LS_EN_STAT	LS enable status bit. This bit is a copy of LS_EN that is synchronized to the low speed clock domain and back to the system clock domain. Firmware can use this bit to observe whether LS_EN has taken effect in the low speed clock domain. Firmware should never change the configuration for the LS generator without ensuring this bit is 0. The following procedure should be followed to disable the LS generator: 1. If LS_EN=0 we are done. Exit the procedure. 2. Check that LS_EN_STAT=1. If not, wait until it is. This will catch the case of a recent enable (LS_EN=1) that has not taken effect yet. 3. Set LS_EN=0. 4. Wait until LS_EN_STAT=0. Default Value: 0

14.1.3 LCD_CONTROL (continued)

11 : 8	COM_NUM	The number of COM connections minus 2. So: 0: 2 COM's 1: 3 COM's ... 13: 15 COM's 14: 16 COM's 15: undefined Default Value: 0
6 : 5	BIAS	PWM bias selection Default Value: 0 **0x0: HALF:** 1/2 Bias **0x1: THIRD:** 1/3 Bias **0x2: FOURTH:** 1/4 Bias (not supported by LS generator) **0x3: FIFTH:** 1/5 Bias (not supported by LS generator)
4	OP_MODE	Driving mode configuration Default Value: 0 **0x0: PWM:** PWM Mode **0x1: CORRELATION:** Digital Correlation Mode
3	TYPE	LCD driving waveform type configuration. Default Value: 0 **0x0: TYPE_A:** Type A - Each frame addresses each COM pin only once with a balanced (DC=0) waveform. **0x1: TYPE_B:** Type B - Each frame addresses each COM pin twice in sequence with a positive and negative waveform that together are balanced (DC=0).
2	LCD_MODE	HS/LS Mode selection Default Value: 0 **0x0: LS:** Select Low Speed (32kHz) Generator (Works in Active, Sleep and DeepSleep power modes). **0x1: HS:** Select High Speed (system clock) Generator (Works in Active and Sleep power modes only).
1	HS_EN	High speed (HS) generator enable 1: enable 0: disable Default Value: 0
0	LS_EN	Low speed (LS) generator enable 1: enable 0: disable Default Value: 0

14.1.4 LCD_DATA00

LCD Pin Data Registers

Address: 0x400B0100

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.5 LCD_DATA01

LCD Pin Data Registers

Address: 0x400B0104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.6 LCD_DATA02

LCD Pin Data Registers

Address: 0x400B0108

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.7 LCD_DATA03

LCD Pin Data Registers

Address: 0x400B010C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.8 LCD_DATA04

LCD Pin Data Registers

Address: 0x400B0110

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.9 LCD_DATA05

LCD Pin Data Registers

Address: 0x400B0114

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.10 LCD_DATA06

LCD Pin Data Registers

Address: 0x400B0118

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.11 LCD_DATA07

LCD Pin Data Registers

Address: 0x400B011C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

14.1.12 LCD_DATA10

LCD Pin Data Registers

Address: 0x400B0200

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

14.1.13 LCD_DATA11

LCD Pin Data Registers

Address: 0x400B0204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

14.1.14 LCD_DATA12

LCD Pin Data Registers

Address: 0x400B0208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

14.1.15 LCD_DATA13

LCD Pin Data Registers

Address: 0x400B020C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

14.1.16 LCD_DATA14

LCD Pin Data Registers

Address: 0x400B0210

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

14.1.17 LCD_DATA15

LCD Pin Data Registers

Address: 0x400B0214

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

14.1.18 LCD_DATA16

LCD Pin Data Registers

Address: 0x400B0218

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

14.1.19 LCD_DATA17

LCD Pin Data Registers

Address: 0x400B021C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

15 Low Power Comparator (LPCOMP) Registers

This section discusses the LPCOMP registers. It lists all the registers in mapping tables, in address order.

15.1 Register Details

Register Name	Address
LPCOMP_ID	0x400E0000
LPCOMP_CONFIG	0x400E0004
LPCOMP_INTR	0x400E0010
LPCOMP_INTR_SET	0x400E0014
LPCOMP_INTR_MASK	0x400E0018
LPCOMP_INTR_MASKED	0x400E001C
LPCOMP_TRIM1	0x400EFF00
LPCOMP_TRIM2	0x400EFF04
LPCOMP_TRIM3	0x400EFF08
LPCOMP_TRIM4	0x400EFF0C

15.1.1 LPCOMP_ID

ID & Revision

Address: 0x400E0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	REVISION [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	REVISION [31:24]							

Bits	Name	Description
31 : 16	REVISION	the version number is 0x0001 Default Value: 1
15 : 0	ID	the ID of LPCOMP peripheral is 0xE0E0 Default Value: 57568

15.1.2 LPCOMP_CONFIG

LPCOMP Configuration Register

Address: 0x400E0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	R	RW		RW	RW	RW	
HW Access	R	RW	R		R	R	R	
Name	ENABLE1	OUT1	INTTYPE1 [5:4]		FILTER1	HYST1	MODE1 [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW	R	RW		RW	RW	RW	
HW Access	R	RW	R		R	R	R	
Name	ENABLE2	OUT2	INTTYPE2 [13:12]		FILTER2	HYST2	MODE2 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	None		RW	RW
HW Access	None		R	R	None		R	R
Name	None [23:22]		DSI_LEVEL2	DSI_BYPASS2	None [19:18]		DSI_LEVEL1	DSI_BYPASS1

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	DSI_LEVEL2	Reserved bit - It should be set to 0. Default Value: 0
20	DSI_BYPASS2	Reserved bit - It should be set to 0. Default Value: 0
17	DSI_LEVEL1	Reserved bit - It should be set to 0. Default Value: 0
16	DSI_BYPASS1	Reserved bit - It should be set to 0. Default Value: 0
15	ENABLE2	Enable Comparator 1 Default Value: 0
14	OUT2	Current output value of the Comparator 1 Default Value: 0
13 : 12	INTTYPE2	Sets which edge in the Comparator 1 output triggers an interrupt Default Value: 0

15.1.2 LPCOMP_CONFIG (continued)

		0x0: DISABLE: Disabled, no interrupts will be generated **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
11	FILTER2	Reserved bit - It should be set to 0. Default Value: 0
10	HYST2	10mV hysteresis for Comparator 1 0: Enable Hysteresis 1: Disable Hysteresis Default Value: 0
9 : 8	MODE2	Sets the operating mode for Comparator 1 Default Value: 0 **0x0: SLOW:** Slow operating mode **0x1: FAST:** Fast operating mode (Highest block current) **0x2: ULP:** Ultra low power operating mode (lowest block current)
7	ENABLE1	Enable Comparator 0 Default Value: 0
6	OUT1	Current output value of the Comparator 0 Default Value: 0
5 : 4	INTTYPE1	Sets which edge in the Comparator 0 output triggers an interrupt Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be generated **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
3	FILTER1	Reserved bit - It should be set to 0. Default Value: 0
2	HYST1	10mV hysteresis for Comparator 0 0: Enable Hysteresis 1: Disable Hysteresis Default Value: 0
1 : 0	MODE1	Sets the operating mode for Comparator 0 Default Value: 0 **0x0: SLOW:** Slow operating mode

15.1.2 LPCOMP_CONFIG (continued)

0x1: FAST:
Fast operating mode (Highest block current)

0x2: ULP:
Ultra low power operating mode (lowest block current)

15.1.3 LPCOMP_INTR

LPCOMP Interrupt request register

Address: 0x400E0010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						COMP2	COMP1

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2	Comparator 1 Interrupt: Hardware sets this bit when comparator 1 triggers. Write with '1' to clear bit. Default Value: 0
0	COMP1	Comparator 0 Interrupt: Hardware sets this bit when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

15.1.4 LPCOMP_INTR_SET

LPCOMP Interrupt set register

Address: 0x400E0014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						COMP2	COMP1

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2	Write with '1' to set COMP2 bit in the interrupt request register. This triggers Comparator 1 interrupt. Default Value: 0
0	COMP1	Write with '1' to set COMP1 bit in the interrupt request register. This triggers Comparator 0 interrupt. Default Value: 0

15.1.5 LPCOMP_INTR_MASK

LPCOMP Interrupt request mask

Address: 0x400E0018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						COMP2_MASK	COMP1_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2_MASK	Interrupt mask bit for Comparator 1 Default Value: 0
0	COMP1_MASK	Interrupt mask bit for Comparator 0 Default Value: 0

15.1.6 LPCOMP_INTR_MASKED

LPCOMP Interrupt request masked

Address: 0x400E001C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						COMP2_MASKED	COMP1_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2_MASKED	Logical AND of the Comparator 1 interrupt request register bit and the interrupt mask bit. Default Value: 0
0	COMP1_MASKED	Logical AND of the Comparator 0 interrupt request register bit and the interrupt mask bit. Default Value: 0

15.1.7 LPCOMP_TRIM1

LPCOMP Trim Register

Address: 0x400EFF00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP1_TRIMA [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP1_TRIMA	Trim A for Comparator 0. These bits are used to correct/trim the comparator offset (Coarse tuning bits) . Trim A bits[3:0] control the amount of offset and Trim A bit[4] controls the polarity of offset ('1' indicates positive offset and '0' indicates negative offset). Default Value: 0

15.1.8 LPCOMP_TRIM2

LPCOMP Trim Register

Address: 0x400EFF04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP1_TRIMB [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP1_TRIMB	Trim B for Comparator #1 Default Value: 0

15.1.9 LPCOMP_TRIM3

LPCOMP Trim Register

Address: 0x400EFF08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP2_TRIMA [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP2_TRIMA	Trim A for Comparator 1. These bits are used to correct/trim the comparator offset (Coarse tuning bits) . Trim A bits[3:0] control the amount of offset and Trim A bit[4] controls the polarity of offset ('1' indicates positive offset and '0' indicates negative offset). Default Value: 0

15.1.10 LPCOMP_TRIM4

LPCOMP Trim Register

Address: 0x400EFF0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP2_TRIMB [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP2_TRIMB	Trim B for Comparator 1. These bits are used to correct/trim the comparator offset (fine tuning bits). These bits must be tuned after tuning Trim A bits for the comparator. Default Value: 0

16 PASS MMIO Registers

This section discusses the Programmable Analog Sub System Memory Mapped IO (PASS MMIO) registers. It lists all the registers in mapping tables, in address order.

16.1 Register Details

Register Name	Address
PASS_INTR_CAUSE	0x403F0000
PASS_TRIG_SYNC	0x403F0100
PASS_SAR_TRIG_SEL	0x403F0104
PASS_PASS_CTRL	0x403F0108
PASS_PRB_CTRL	0x403F0200
PASS_PRB_REF0	0x403F0204
PASS_PRB_REF1	0x403F0208
PASS_PRB_REF2	0x403F020C
PASS_PRB_REF3	0x403F0210
PASS_LNFE_CTRL	0x403F0300
PASS_LNFE_SW	0x403F0304
PASS_DSAB_TRIM	0x403F0F00
PASS_PRB_TRIM	0x403F0F04

16.1.1 PASS_INTR_CAUSE

Interrupt cause register

Address: 0x403F0000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CTB1_INT	CTB0_INT

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							UAB0_INT

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	UAB0_INT	UAB0 interrupt pending Default Value: 0
1	CTB1_INT	CTB1 interrupt pending Default Value: 0
0	CTB0_INT	CTB0 interrupt pending Default Value: 0

16.1.2 PASS_TRIG_SYNC

Trigger synchronization bypass

Address: 0x403F0100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW					
HW Access	None		R					
Name	None [15:14]		DSI_SYNC0_EN [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
13 : 8	DSI_SYNC0_EN	Synchronize DSI input 1 (0: bypass synchronization) Default Value: 0

16.1.3 PASS_SAR_TRIG_SEL

Trigger select for SAR

Address: 0x403F0104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW				
HW Access	None			R				
Name	None [31:29]			TRIG_SEL [28:24]				

Bits	Name	Description
28 : 24	TRIG_SEL	Trigger select 0=UAB0 half 0 trigger output 1=UAB0 half 1 trigger output 2=UAB1 half 0 trigger output 3=UAB1 half 1 trigger output 4=UAB2 half 0 trigger output 5=UAB2 half 1 trigger output 6=UAB3 half 0 trigger output 7=UAB3 half 1 trigger output 8-30 = generic trigger inputs 0-22 31=SAR trigger output For PASS4B only values 0-1 and 8-13 and 31 are legal. Default Value: 8

16.1.4 PASS_PASS_CTRL

PASS control

Address: 0x403F0108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						PMPCLK_SRC	PMPCLK_BYP

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RMB_BITS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	RMB_BITS	Risk mitigation bits Default Value: 0
1	PMPCLK_SRC	- 0: Pump clk is clk_hf - 1: Pump clk is direct from SRSS Default Value: 0
0	PMPCLK_BYP	- 0: Pump clk is clk_hf/2 - 1: Pump clk is selected from PMPCLK_SRC Default Value: 0

16.1.5 PASS_PRB_CTRL

global PRB control

Address: 0x403F0200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			VDDA_ENABLE	None [3:2]		VBGR_BUF_GAIN [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	ENABLED	DEEPSLEEP_ON	None [29:24]					

Bits	Name	Description
31	ENABLED	- 0: PRB IP disabled (put analog in power down, open all switches) - 1: PRB IP enabled Default Value: 0
30	DEEPSLEEP_ON	- 0: PRB IP disabled off during DeepSleep power mode - 1: PRB IP remains enabled during DeepSleep power mode (if ENABLED=1) Only VDDA reference is available in DeepSleep power mode Default Value: 0
4	VDDA_ENABLE	- 0: VDDA references disabled (open switch at bottom of resistor ladder) - 1: VDDA references enabled (close switch at bottom of resistor ladder) This feature is available in DeepSleep power mode Default Value: 0
1 : 0	VBGR_BUF_GAIN	- 0: buffer off - 1: gain of 1 - 2: gain of 2 - 3: reserved This feature is not available in DeepSleep power mode Default Value: 0

16.1.6 PASS_PRB_REF0

VREF0 control

Address: 0x403F0204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				None		RW	RW
HW Access	R				None		R	R
Name	VREF0_SEL [7:4]				None [3:2]		VREF0_SUP_SEL	VREF0_ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	VREF0_SEL	Level select, VTOP= VSUP * (VREF_SEL+1)/16 (15: VTOP=VSUP) Default Value: 0
1	VREF0_SUP_SEL	Supply select 0: VSUP= VGBR * gain, 1: VSUP= VDDA Default Value: 0
0	VREF0_ENABLE	0=disconnect, 1= connect & enable resistor string Default Value: 0

16.1.7 PASS_PRB_REF1

VREF1 control

Address: 0x403F0208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				None		RW	RW
HW Access	R				None		R	R
Name	VREF1_SEL [7:4]				None [3:2]		VREF1_SUP_SEL	VREF1_ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	VREF1_SEL	Level select, VTOP= VSUP * (VREF_SEL+1)/16 (15: VTOP=VSUP) Default Value: 0
1	VREF1_SUP_SEL	Supply select 0: VSUP= VGBR * gain, 1: VSUP= VDDA Default Value: 0
0	VREF1_ENABLE	0=disconnect, 1= connect & enable resistor string Default Value: 0

16.1.8 PASS_PRB_REF2

VREF2 control

Address: 0x403F020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				None		RW	RW
HW Access	R				None		R	R
Name	VREF2_SEL [7:4]				None [3:2]		VREF2_SUP_SEL	VREF2_ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	VREF2_SEL	Level select, VTOP= VSUP * (VREF_SEL+1)/16 (15: VTOP=VSUP) Default Value: 0
1	VREF2_SUP_SEL	Supply select 0: VSUP= VGBR * gain, 1: VSUP= VDDA Default Value: 0
0	VREF2_ENABLE	0=disconnect, 1= connect & enable resistor string Default Value: 0

16.1.9 PASS_PRB_REF3

VREF3 control

Address: 0x403F0210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				None		RW	RW
HW Access	R				None		R	R
Name	VREF3_SEL [7:4]				None [3:2]		VREF3_SUP_SEL	VREF3_ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	VREF3_SEL	Level select, VTOP= VSUP * (VREF_SEL+1)/16 (15: VTOP=VSUP) Default Value: 0
1	VREF3_SUP_SEL	Supply select 0: VSUP= VGBR * gain, 1: VSUP= VDDA Default Value: 0
0	VREF3_ENABLE	0=disconnect, 1= connect & enable resistor string Default Value: 0

16.1.10 PASS_LNFE_CTRL

global LNFE control

Address: 0x403F0300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	ENABLED	DEEPSLEEP_ON	None [29:24]					

Bits	Name	Description
31	ENABLED	- 0: LNFE IP disabled (put analog in power down, open all switches) - 1: LNFE IP enabled Default Value: 0
30	DEEPSLEEP_ON	- 0: LNFE IP disabled off during DeepSleep power mode - 1: LNFE IP remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0

16.1.11 PASS_LNFE_SW

LNFE switch control

Address: 0x403F0304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						LE	LB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	LE	Connect NPN Emitter to pin Default Value: 0
0	LB	Connect NPN Base to pin Default Value: 0

16.1.12 PASS_DSAB_TRIM

DSAB Trim bits

Address: 0x403F0F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW			
HW Access	None		R		R			
Name	None [7:6]		DSAB_RMB_BITS [5:4]		IBIAS_TRIM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	DSAB_RMB_BITS	Risk mitigation bits Default Value: 0
3 : 0	IBIAS_TRIM	1111=lowest, 0000=highest Default Value: 0

16.1.13 PASS_PRB_TRIM

PRB Trim bits

Address: 0x403F0F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		VBGR_BUF_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						PRB_RMB_BITS [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	PRB_RMB_BITS	Risk mitigation bits Default Value: 0
5 : 0	VBGR_BUF_TRIM	6 bits signed value [-32..31], ~1mV per step Default Value: 0

17 Peripheral Interconnect (PERI) Registers

This section discusses the Clock Dividers and Peripheral Interconnect (PERI) registers. It lists all the registers in mapping tables, in address order.

17.1 Register Details

Register Name	Address
PERI_DIV_CMD	0x40000000
PERI_PCLK_CTL0	0x40000100
PERI_PCLK_CTL1	0x40000104
PERI_PCLK_CTL2	0x40000108
PERI_PCLK_CTL3	0x4000010C
PERI_PCLK_CTL4	0x40000110
PERI_PCLK_CTL5	0x40000114
PERI_PCLK_CTL6	0x40000118
PERI_PCLK_CTL7	0x4000011C
PERI_PCLK_CTL8	0x40000120
PERI_PCLK_CTL9	0x40000124
PERI_PCLK_CTL10	0x40000128
PERI_PCLK_CTL11	0x4000012C
PERI_PCLK_CTL12	0x40000130
PERI_PCLK_CTL13	0x40000134
PERI_PCLK_CTL14	0x40000138
PERI_PCLK_CTL15	0x4000013C
PERI_PCLK_CTL16	0x40000140
PERI_DIV_16_CTL0	0x40000300
PERI_DIV_16_CTL1	0x40000304
PERI_DIV_16_CTL2	0x40000308
PERI_DIV_16_CTL3	0x4000030C
PERI_DIV_16_CTL4	0x40000310
PERI_DIV_16_CTL5	0x40000314
PERI_DIV_16_CTL6	0x40000318
PERI_DIV_16_5_CTL0	0x40000400
PERI_DIV_16_5_CTL1	0x40000404

Register Name	Address
PERI_DIV_16_5_CTL2	0x40000408
PERI_DIV_24_5_CTL	0x40000500
PERI_TR_CTL	0x40000600

17.1.1 PERI_DIV_CMD

Divider command register

Address: 0x40000000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW					
HW Access	R		R					
Name	SEL_TYPE [7:6]		SEL_DIV [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW					
HW Access	R		R					
Name	PA_SEL_TYPE [15:14]		PA_SEL_DIV [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	RW1C	RW1C	None					
Name	ENABLE	DISABLE	None [29:24]					

Bits	Name	Description

17.1.1 PERI_DIV_CMD (continued)

31	ENABLE	Clock divider enable command (mutually exclusive with DISABLE). Typically, SW sets this field to '1' to enable a divider and HW sets this field to '0' to indicate that divider enabling has completed. When a divider is enabled, its integer and fractional (if present) counters are initialized to "0". If a divider is to be re-enabled using different integer and fractional divider values, the SW should follow these steps: 0: Disable the divider using the DIV_CMD.DISABLE field. 1: Configure the divider's DIV_XXX_CTL register. 2: Enable the divider using the DIV_CMD_ENABLE field. The SEL_DIV and SEL_TYPE fields specify which divider is to be enabled. The enabled divider may be phase aligned to either "clk_hf" (typical usage) or to ANY enabled divider. The PA_SEL_DIV and P_SEL_TYPE fields specify the reference divider. The HW sets the ENABLE field to '0' when the enabling is performed and the HW set the DIV_XXX_CTL.EN field of the divider to '1' when the enabling is performed. Note that enabling with phase alignment to a low frequency divider takes time. E.g. To align to a divider that generates a clock of "clk_hf"/n (with n being the integer divider value INT_DIV+1), up to n cycles may be required to perform alignment. Phase alignment to "clk_hf" takes affect immediately. SW can set this field to '0' during phase alignment to abort the enabling process. Default Value: 0
30	DISABLE	Clock divider disable command (mutually exlusive with ENABLE). SW sets this field to '1' and HW sets this field to '0'. The SEL_DIV and SEL_TYPE fields specify which divider is to be disabled. The HW sets the DISABLE field to '0' immediately and the HW sets the DIV_XXX_CTL.EN field of the divider to '0' immediately. Default Value: 0
15 : 14	PA_SEL_TYPE	Specifies the divider type of the divider to which phase alignment is performed for the clock enable command: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
13 : 8	PA_SEL_DIV	(PA_SEL_TYPE, PA_SEL_DIV) pecifies the divider to which phase alignment is performed for the clock enable command. Any enabled divider can be used as reference. This allows all dividers to be aligned with each other, even when they are enabled at different times. If PA_SEL_DIV is "63" and "PA_SEL_TYPE" is "3", "clk_hf" is used as reference. Default Value: 63
7 : 6	SEL_TYPE	Specifies the divider type of the divider on which the command is performed: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
5 : 0	SEL_DIV	(SEL_TYPE, SEL_DIV) specifies the divider on which the command (DISABLE/ENABLE) is performed. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock signal(s) are generated. Default Value: 63

17.1.2 PERI_PCLK_CTL0

Programmable clock control register

Address: 0x40000100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.3 PERI_PCLK_CTL1

Programmable clock control register

Address: 0x40000104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.4 PERI_PCLK_CTL2

Programmable clock control register

Address: 0x40000108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.5 PERI_PCLK_CTL3

Programmable clock control register

Address: 0x4000010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.6 PERI_PCLK_CTL4

Programmable clock control register

Address: 0x40000110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.7 PERI_PCLK_CTL5

Programmable clock control register

Address: 0x40000114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.8 PERI_PCLK_CTL6

Programmable clock control register

Address: 0x40000118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.9 PERI_PCLK_CTL7

Programmable clock control register

Address: 0x4000011C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.10 PERI_PCLK_CTL8

Programmable clock control register

Address: 0x40000120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.11 PERI_PCLK_CTL9

Programmable clock control register

Address: 0x40000124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.12 PERI_PCLK_CTL10

Programmable clock control register

Address: 0x40000128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.13 PERI_PCLK_CTL11

Programmable clock control register

Address: 0x4000012C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.14 PERI_PCLK_CTL12

Programmable clock control register

Address: 0x40000130

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.15 PERI_PCLK_CTL13

Programmable clock control register

Address: 0x40000134

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.16 PERI_PCLK_CTL14

Programmable clock control register

Address: 0x40000138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.17 PERI_PCLK_CTL15

Programmable clock control register

Address: 0x4000013C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.18 PERI_PCLK_CTL16

Programmable clock control register

Address: 0x40000140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one HFCLK cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

17.1.19 PERI_DIV_16_CTL0

Divider control register (for 16.0 divider)

Address: 0x40000300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.20 PERI_DIV_16_CTL1

Divider control register (for 16.0 divider)

Address: 0x40000304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.21 PERI_DIV_16_CTL2

Divider control register (for 16.0 divider)

Address: 0x40000308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.22 PERI_DIV_16_CTL3

Divider control register (for 16.0 divider)

Address: 0x4000030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.23 PERI_DIV_16_CTL4

Divider control register (for 16.0 divider)

Address: 0x40000310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.24 PERI_DIV_16_CTL5

Divider control register (for 16.0 divider)

Address: 0x40000314

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.25 PERI_DIV_16_CTL6

Divider control register (for 16.0 divider)

Address: 0x40000318

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.26 PERI_DIV_16_5_CTL0

Divider control register (for 16.5 divider)

Address: 0x40000400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 HFCLK cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.26 PERI_DIV_16_5_CTL0 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.27 PERI_DIV_16_5_CTL1

Divider control register (for 16.5 divider)

Address: 0x40000404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 HFCLK cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.27 PERI_DIV_16_5_CTL1 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.28 PERI_DIV_16_5_CTL2

Divider control register (for 16.5 divider)

Address: 0x40000408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 HFCLK cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.28 PERI_DIV_16_5_CTL2 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.29 PERI_DIV_24_5_CTL

Divider control register (for 24.5 divider)

Address: 0x40000500

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT24_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT24_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	INT24_DIV [31:24]							

Bits	Name	Description
31 : 8	INT24_DIV	Integer division by (1+INT24_DIV). Allows for integer divisions in the range [1, 16,777,216]. Note: combined with fractional division, this divider type allows for a division in the range [1, 16,777,216 31/32] in 1/32 increments. For the generation of a divided clock, the integer division range is restricted to [2, 16,777,216 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 16,777,216]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 HFCLK cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.29 PERI_DIV_24_5_CTL (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

17.1.30 PERI_TR_CTL

Trigger control register

Address: 0x40000600

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW						
HW Access	None	R						
Name	None	TR_SEL [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				TR_GROUP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	TR_COUNT [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	RW1C	R	None					
Name	TR_ACT	TR_OUT	None [29:24]					

Bits	Name	Description
31	TR_ACT	SW sets this field to '1' by to activate (set to '1') a trigger as identified by TR_SEL and TR_OUT for TR_COUNT cycles. HW sets this field to '0' when the cycle counter is decremented to "0". Note: a TR_COUNT value of 255 is a special case and trigger activation is under direct control of the TR_ACT field (the counter is not decremented). Default Value: 0
30	TR_OUT	Specifies whether trigger activation is for a specific input or ouput trigger of the trigger multiplexer. Activation of a specific input trigger, will result in activation of all output triggers that have the specific input trigger selected through their TR_OUT_CTL.SEL field. Activation of a specific output trigger, will result in activation of the specified TR_SEL output trigger only. '0': TR_SEL selection and trigger activation is for an input trigger to the trigger multiplexer. '1': TR_SEL selection and trigger activation is for an output trigger from the trigger multiplexer. Default Value: 0
23 : 16	TR_COUNT	Amount of cycles a specific trigger is activated. During activation (TR_ACT is '1'), HW decrements this field to "0" using a cycle counter. During activation, SW should not modify this register field. A value of 255 is a special case: HW does NOT decrement this field to "0" and trigger activation is under direct control of TR_ACT: when TR_ACT is '1' the trigger is activated and when TR_ACT is '0' the trigger is deactivated. Default Value: 0

17.1.30 PERI_TR_CTL (continued)

11 : 8	TR_GROUP	Specifies the trigger group. Default Value: 0
6 : 0	TR_SEL	Specifies the activated trigger when TR_ACT is '1'. TR_OUT specifies whether the activated trigger is an input trigger or output trigger to the trigger multiplexer. During activation (TR_ACT is '1'), SW should not modify this register field. If the specified trigger is not present, the trigger activation has no effect. Default Value: 0

18 PRGIO_PRTO Registers

This section discusses the PRGIO_PRT registers. It lists all the registers in mapping tables, in address order.

18.1 Register Details

Register Name	Address
PRGIO_PRT0_CTL	0x40050000
PRGIO_PRT0_SYNC_CTL	0x40050010
PRGIO_PRT0_LUT_SEL0	0x40050020
PRGIO_PRT0_LUT_SEL1	0x40050024
PRGIO_PRT0_LUT_SEL2	0x40050028
PRGIO_PRT0_LUT_SEL3	0x4005002C
PRGIO_PRT0_LUT_SEL4	0x40050030
PRGIO_PRT0_LUT_SEL5	0x40050034
PRGIO_PRT0_LUT_SEL6	0x40050038
PRGIO_PRT0_LUT_SEL7	0x4005003C
PRGIO_PRT0_LUT_CTL0	0x40050040
PRGIO_PRT0_LUT_CTL1	0x40050044
PRGIO_PRT0_LUT_CTL2	0x40050048
PRGIO_PRT0_LUT_CTL3	0x4005004C
PRGIO_PRT0_LUT_CTL4	0x40050050
PRGIO_PRT0_LUT_CTL5	0x40050054
PRGIO_PRT0_LUT_CTL6	0x40050058
PRGIO_PRT0_LUT_CTL7	0x4005005C
PRGIO_PRT0_DU_SEL	0x400500C0
PRGIO_PRT0_DU_CTL	0x400500C4
PRGIO_PRT0_DATA	0x400500F0

18.1.1 PRGIO_PRT0_CTL

Control register

Address: 0x40050000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	BYPASS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			CLOCK_SRC [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	RW
HW Access	R	None					R	R
Name	ENABLED	None [30:26]					PIPELINE_EN	HLD_OVR

Bits	Name	Description
31	ENABLED	Enable for programmable IO. Should only be set to '1' when the programmable IO is completely configured: '0': Disabled (signals are bypassed; behavior as if BYPASS is 0xFF). When disabled, the block (data unit and LUTs) reset is activated. If the IP is disabled: - The PIPELINE_EN register field should be set to '1', to ensure low power consumption by preventing combinatorial loops. - The CLOCK_SRC register field should be set to "20"-"30" (clock is constant '0'), to ensure low power consumption. '1': Enabled. Once enabled, it takes 3 "clk_block" clock cycles till the block reset is de-activated and the block becomes fully functional. This ensures that the IO pins' input synchronizer states are flushed when the block is fully functional. Default Value: 0
25	PIPELINE_EN	Enable for pipeline register: '0': Disabled (register is bypassed). '1': Enabled. Default Value: 1

18.1.1 PRGIO_PRT0_CTL (continued)

24	HLD_OVR	IO cell hold override functionality. In DeepSleep power mode, the HSIOM holds the IO cell output and output enable signals by default. This is undesirable if the PRGIO is supposed to deliver DeepSleep output functionality on these IO pads. This field is used to control the hold override functionality from the PRGIO: GPIO hold-override functionality in DeepSleep: '0': The HSIOM controls the GPIO functionality in DeepSleep '1': In bypass mode (ENABLED is '0' or BYPASS[i] is '1'), the HSIOM controls GPIO. In NON bypass mode (ENABLED is '1' and BYPASS[i] is '0'), the PRGIO controls the GPIO functionality in DeepSleep power mode. Default Value: Undefined
12 : 8	CLOCK_SRC	Clock ("clk_block") and reset ("rst_block_n") source selection: "0": io_data_in[0]/'1'. ... "7": io_data_in[7]/'1'. "8": chip_data[0]/'1'. ... "15": chip_data[7]/'1'. "16": clk_prgio/rst_sys_act_n. Used for Active mode synchronous logic on "clk_prgio". This selection is intended for synchronous operation on a PCLK specified clock frequency ("clock_prgio"). Note that the block's clocked elements are frequency aligned, but NOT phase aligned to "clk_sys". This selection asserts reset in any power mode other than Active i.e. PRGIO is active only in Active power mode with clock from peripheral divider "17": clk_prgio/rst_sys_dpslp_n. Used for DeepSleep mode synchronous logic on "clk_prgio" (note that "clk_prgio" is NOT available in DeepSleep power mode). This selection is intended for synchronous operation on a PCLK specified clock frequency ("clock_prgio"). This selection enables PRGIO in all power modes with clock from peripheral divider but the clock will not be active in DeepSleep power mode (i.e only asynchronous/combinational logics will work in DeepSleep). "19": clk_lf/rst_lf_dpslp_n (note that "clk_lf" is only available in DeepSleep power mode). This selection is intended for synchronous operation on"clk_lf". Note that the block's clocked elements are frequency aligned, but NOT phase aligned to other "clk_lf" clocked elements. This selection enables PRGIO in all power modes with clock from ILO (clk_lf) synchronous operations in DeepSleep will use clk_lf. "20"-"30": Clock source is constant '0'. Any of these clock sources should be selected when the IP is disabled to ensure low power consumption. "31": clk_sys/'1'. This selection is NOT intended for "clk_sys" operation, but for asynchronous operation: three "clk_sys" cycles after enabling the IP, the IP is fully functional (reset is de-activated). To be used for asynchronous (clockless) block functionality. Default Value: 20
7 : 0	BYPASS	Bypass of the programmable IO - BYPASS[i] is for IO pin i. '0': No bypass '1': Bypass Default Value: Undefined

18.1.2 PRGIO_PRT0_SYNC_CTL

Synchronization control register

Address: 0x40050010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	IO_SYNC_EN [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CHIP_SYNC_EN [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	CHIP_SYNC_EN	Synchronization of the chip input signals to "clk_block", one bit for each input: CHIP_SYNC_EN[i] is for input i. '0': No synchronization. '1': Synchronization. Default Value: Undefined
7 : 0	IO_SYNC_EN	Synchronization of the IO pin input signals to "clk_block", one bit for each IO pin: IO_SYNC_EN[i] is for IO pin i. '0': No synchronization. '1': Synchronization. Default Value: Undefined

18.1.3 PRGIO_PRT0_LUT_SEL0

LUT component input selection

Address: 0x40050020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.3 PRGIO_PRT0_LUT_SEL0 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.4 PRGIO_PRT0_LUT_SEL1

LUT component input selection

Address: 0x40050024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.4 PRGIO_PRT0_LUT_SEL1 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.5 PRGIO_PRT0_LUT_SEL2

LUT component input selection

Address: 0x40050028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.5 PRGIO_PRT0_LUT_SEL2 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.6 PRGIO_PRT0_LUT_SEL3

LUT component input selection

Address: 0x4005002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.6 PRGIO_PRT0_LUT_SEL3 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.7 PRGIO_PRT0_LUT_SEL4

LUT component input selection

Address: 0x40050030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.7 PRGIO_PRT0_LUT_SEL4 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.8 PRGIO_PRT0_LUT_SEL5

LUT component input selection

Address: 0x40050034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.8 PRGIO_PRT0_LUT_SEL5 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.9 PRGIO_PRT0_LUT_SEL6

LUT component input selection

Address: 0x40050038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.9 PRGIO_PRT0_LUT_SEL6 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.10 PRGIO_PRT0_LUT_SEL7

LUT component input selection

Address: 0x4005003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.10 PRGIO_PRT0_LUT_SEL7 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

18.1.11 PRGIO_PRT0_LUT_CTL0

LUT component control register

Address: 0x40050040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.11 PRGIO_PRT0_LUT_CTL0 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.12 PRGIO_PRT0_LUT_CTL1

LUT component control register

Address: 0x40050044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.12 PRGIO_PRT0_LUT_CTL1 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.13 PRGIO_PRT0_LUT_CTL2

LUT component control register

Address: 0x40050048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.13 PRGIO_PRT0_LUT_CTL2 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.14 PRGIO_PRT0_LUT_CTL3

LUT component control register

Address: 0x4005004C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.14 PRGIO_PRT0_LUT_CTL3 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.15 PRGIO_PRT0_LUT_CTL4

LUT component control register

Address: 0x40050050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.15 PRGIO_PRT0_LUT_CTL4 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.16 PRGIO_PRT0_LUT_CTL5

LUT component control register

Address: 0x40050054

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.16 PRGIO_PRT0_LUT_CTL5 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.17 PRGIO_PRT0_LUT_CTL6

LUT component control register

Address: 0x40050058

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.17 PRGIO_PRT0_LUT_CTL6 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.18 PRGIO_PRT0_LUT_CTL7

LUT component control register

Address: 0x4005005C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatoral output, no feedback. tr_out = LUT[{tr2_in, tr1_in, tr0_in}]. "1": Combinatorial output, feedback. tr_out = LUT[{lut_reg, tr1_in, tr0_in}]. On clock: lut_reg <= tr_in2. "2": Sequential output, no feedback. temp = LUT[{tr2_in, tr1_in, tr0_in}]. tr_out = lut_reg. On clock: lut_reg <= temp. "3": Register with asynchronous set and reset. tr_out = lut_reg. enable = (tr2_in ^ LUT[4]) | LUT[5]. set = enable & (tr1_in ^ LUT[2]) & LUT[3]. clr = enable & (tr0_in ^ LUT[0]) & LUT[1]. Asynchronously (no clock required): lut_reg <= if (clr) '0' else if (set) '1' Default Value: Undefined

18.1.18 PRGIO_PRT0_LUT_CTL7 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal(tr_out) and the next sequential state (lut_reg). Default Value: Undefined

18.1.19 PRGIO_PRT0_DU_SEL

Data unit component input selection

Address: 0x400500C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DU_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				DU_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				DU_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None		RW	
HW Access	None		R		None		R	
Name	None [31:30]		DU_DATA1_SEL [29:28]		None [27:26]		DU_DATA0_SEL [25:24]	

Bits	Name	Description
29 : 28	DU_DATA1_SEL	Data unit input data "data1_in" source selection. Encoding is the same as for DU_DATA0_SEL. Default Value: Undefined
25 : 24	DU_DATA0_SEL	Data unit input data "data0_in" source selection: "0": Constant "0". "1": chip_data[7:0]. "2": io_data_in[7:0]. "3": PRGIO_PRTx_DATA.DATA register field. Default Value: Undefined
19 : 16	DU_TR2_SEL	Data unit input signal "tr2_in" source selection. Encoding is the same as for DU_TR0_SEL. Default Value: Undefined
11 : 8	DU_TR1_SEL	Data unit input signal "tr1_in" source selection. Encoding is the same as for DU_TR0_SEL. Default Value: Undefined

18.1.19 PRGIO_PRT0_DU_SEL (continued)

3 : 0	DU_TR0_SEL	Data unit input signal "tr0_in" source selection: "0": Constant '0'. "1": Constant '1'. "2": Data unit output. "10-3": LUT 7 - 0 outputs. Otherwise: Undefined. Default Value: Undefined

18.1.20 PRGIO_PRT0_DU_CTL

Data unit component control register

Address: 0x400500C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					DU_SIZE [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				DU_OPC [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 8	DU_OPC	Data unit opcode specifies the data unit operation: "1": INCR "2": DECR "3": INCR_WRAP "4": DECR_WRAP "5": INCR_DECR "6": INCR_DECR_WRAP "7": ROR "8": SHR "9": AND_OR "10": SHR_MAJ3 "11": SHR_EQL. Otherwise: Undefined. Default Value: Undefined
2 : 0	DU_SIZE	Size/width of the data unit data operands (in bits) is DU_SIZE+1. E.g., if DU_SIZE is 7, the width is 8 bits. Default Value: Undefined

18.1.21 PRGIO_PRT0_DATA

Data register

Address: 0x400500F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	Data unit input data source. Default Value: Undefined

19 CoreSight ROM Table Registers

This section discusses the ROM Table registers. It lists all the registers in mapping tables, in address order.

19.1 Register Details

Register Name	Address
ROMTABLE_ADDR	0xF0000000
ROMTABLE_DID	0xF0000FCC
ROMTABLE_PID4	0xF0000FD0
ROMTABLE_PID5	0xF0000FD4
ROMTABLE_PID6	0xF0000FD8
ROMTABLE_PID7	0xF0000FDC
ROMTABLE_PID0	0xF0000FE0
ROMTABLE_PID1	0xF0000FE4
ROMTABLE_PID2	0xF0000FE8
ROMTABLE_PID3	0xF0000FEC
ROMTABLE_CID0	0xF0000FF0
ROMTABLE_CID1	0xF0000FF4
ROMTABLE_CID2	0xF0000FF8
ROMTABLE_CID3	0xF0000FFC

19.1.1 ROMTABLE_ADDR

Link to Cortex M0 ROM Table.

Address: 0xF0000000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						R	R
Name	None [7:2]						FORMAT_32BIT	PRESENT

Bits	15	14	13	12	11	10	9	8
SW Access	R				None			
HW Access	R				None			
Name	ADDR_OFFSET [15:12]				None [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	ADDR_OFFSET [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	ADDR_OFFSET [31:24]							

Bits	Name	Description
31 : 12	ADDR_OFFSET	Address offset of the Cortex-M0 ROM Table base address (0xe00f:f000) wrt. Cypress chip specific ROM Table base address (0xf000:0000). ADDR_OFFSET[19:0] = 0xe00f:f - 0xf000:0 = 0xf00f:f. Default Value: 983295
1	FORMAT_32BIT	ROM Table format: '0: 8-bit format. '1': 32-bit format. Default Value: 1
0	PRESENT	Entry present. Default Value: 1

19.1.2 ROMTABLE_DID

Device Type Identifier register.

Address: 0xF0000FCC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 1

19.1.3 ROMTABLE_PID4

Peripheral Identification Register 4.

Address: 0xF0000FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	COUNT [7:4]				JEP_CONTINUATION [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	COUNT	Size of ROM Table is 2^COUNT * 4 KByte. Default Value: 0
3 : 0	JEP_CONTINUATION	JEP106 continuation code. This value is product specific and specified as part of the product definition in the CPUSS.JEPCONTINUATION parameter. Default Value: Undefined

19.1.4 ROMTABLE_PID5

Peripheral Identification Register 5.

Address: 0xF0000FD4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

19.1.5 ROMTABLE_PID6

Peripheral Identification Register 6.

Address: 0xF0000FD8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

19.1.6 ROMTABLE_PID7

Peripheral Identification Register 7.

Address: 0xF0000FDC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

19.1.7 ROMTABLE_PID0

Peripheral Identification Register 0.

Address: 0xF0000FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	PN_MIN [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	PN_MIN	JEP106 part number. 4 lsbs of CPUSS.PARTNUMBER parameter. These part numbers are maintained in spec 40-9500. Default Value: Undefined

19.1.8 ROMTABLE_PID1

Peripheral Identification Register 1.

Address: 0xF0000FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	JEPID_MIN [7:4]				PN_MAJ [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	JEPID_MIN	JEP106 vendor id. 4 lsbs of CPUSS.JEPID parameter. This number is maintained in spec 40-9500. Default Value: Undefined
3 : 0	PN_MAJ	JEP106 part number. 4 msbs of CPUSS.PARTNUMBER parameter. These part numbers are maintained in spec 40-9500. Default Value: Undefined

19.1.9 ROMTABLE_PID2

Peripheral Identification Register 2.

Address: 0xF0000FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				None	R		
HW Access	R				None	R		
Name	REV [7:4]				None	JEPID_MAJ [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	REV	Major REVision number (chip specific). Identifies the design iteration of the component. For first tape out: 0x1. This field is implemented in RTL by an ECO-able tie-off structure and is incremented on subsequent tape outs. Default Value: Undefined
2 : 0	JEPID_MAJ	JEP106 vendor id. 4 msbs of CPUSS.JEPID parameter. This number is maintained in spec 40-9500. Default Value: Undefined

19.1.10 ROMTABLE_PID3

Peripheral Identification Register 3.

Address: 0xF0000FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	REV_AND [7:4]				CM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	REV_AND	Minor REVision number (chip specific). For first tape out: 0x1. This field is implemented in RTL by an ECO-able tie-off structure and is incremented on subsequent tape outs. Default Value: Undefined
3 : 0	CM	Customer modified field. This field is used to track modifications to the original component design as a result of componenet IP reuse. Default Value: 0

19.1.11 ROMTABLE_CID0

Component Identification Register 0.

Address: 0xF0000FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 0 of 4-byte component identification 0xB105:100D. Default Value: 13

19.1.12 ROMTABLE_CID1

Component Identification Register 1.

Address: 0xF0000FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 1 of 4-byte component identification 0xB105:100D. Component class: "ROM Table". Default Value: 16

19.1.13 ROMTABLE_CID2

Component Identification Register 2.

Address: 0xF0000FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 2 of 4-byte component identification 0xB105:100D. Default Value: 5

19.1.14 ROMTABLE_CID3

Component Identification Register 3.

Address: 0xF0000FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 3 of 4-byte component identification 0xB105:100D. Default Value: 177

20 SAR Registers

This section discusses the SAR registers. It lists all the registers in mapping tables, in address order.

20.1 Register Details

Register Name	Address
SAR_CTRL	0x403A0000
SAR_SAMPLE_CTRL	0x403A0004
SAR_SAMPLE_TIME01	0x403A0010
SAR_SAMPLE_TIME23	0x403A0014
SAR_RANGE_THRES	0x403A0018
SAR_RANGE_COND	0x403A001C
SAR_CHAN_EN	0x403A0020
SAR_START_CTRL	0x403A0024
SAR_CHAN_CONFIG0	0x403A0080
SAR_CHAN_CONFIG1	0x403A0084
SAR_CHAN_CONFIG2	0x403A0088
SAR_CHAN_CONFIG3	0x403A008C
SAR_CHAN_CONFIG4	0x403A0090
SAR_CHAN_CONFIG5	0x403A0094
SAR_CHAN_CONFIG6	0x403A0098
SAR_CHAN_CONFIG7	0x403A009C
SAR_CHAN_CONFIG8	0x403A00A0
SAR_CHAN_CONFIG9	0x403A00A4
SAR_CHAN_CONFIG10	0x403A00A8
SAR_CHAN_CONFIG11	0x403A00AC
SAR_CHAN_CONFIG12	0x403A00B0
SAR_CHAN_CONFIG13	0x403A00B4
SAR_CHAN_CONFIG14	0x403A00B8
SAR_CHAN_CONFIG15	0x403A00BC
SAR_CHAN_WORK0	0x403A0100
SAR_CHAN_WORK1	0x403A0104
SAR_CHAN_WORK2	0x403A0108

Register Name	Address
SAR_CHAN_WORK3	0x403A010C
SAR_CHAN_WORK4	0x403A0110
SAR_CHAN_WORK5	0x403A0114
SAR_CHAN_WORK6	0x403A0118
SAR_CHAN_WORK7	0x403A011C
SAR_CHAN_WORK8	0x403A0120
SAR_CHAN_WORK9	0x403A0124
SAR_CHAN_WORK10	0x403A0128
SAR_CHAN_WORK11	0x403A012C
SAR_CHAN_WORK12	0x403A0130
SAR_CHAN_WORK13	0x403A0134
SAR_CHAN_WORK14	0x403A0138
SAR_CHAN_WORK15	0x403A013C
SAR_CHAN_RESULT0	0x403A0180
SAR_CHAN_RESULT1	0x403A0184
SAR_CHAN_RESULT2	0x403A0188
SAR_CHAN_RESULT3	0x403A018C
SAR_CHAN_RESULT4	0x403A0190
SAR_CHAN_RESULT5	0x403A0194
SAR_CHAN_RESULT6	0x403A0198
SAR_CHAN_RESULT7	0x403A019C
SAR_CHAN_RESULT8	0x403A01A0
SAR_CHAN_RESULT9	0x403A01A4
SAR_CHAN_RESULT10	0x403A01A8
SAR_CHAN_RESULT11	0x403A01AC
SAR_CHAN_RESULT12	0x403A01B0
SAR_CHAN_RESULT13	0x403A01B4
SAR_CHAN_RESULT14	0x403A01B8
SAR_CHAN_RESULT15	0x403A01BC
SAR_CHAN_WORK_UPDATED	0x403A0200
SAR_CHAN_RESULT_UPDATED	0x403A0204
SAR_CHAN_WORK_NEWVALUE	0x403A0208
SAR_CHAN_RESULT_NEWVALUE	0x403A020C
SAR_INTR	0x403A0210
SAR_INTR_SET	0x403A0214
SAR_INTR_MASK	0x403A0218
SAR_INTR_MASKED	0x403A021C
SAR_SATURATE_INTR	0x403A0220
SAR_SATURATE_INTR_SET	0x403A0224
SAR_SATURATE_INTR_MASK	0x403A0228
SAR_SATURATE_INTR_MASKED	0x403A022C
SAR_RANGE_INTR	0x403A0230

Register Name	Address
SAR_RANGE_INTR_SET	0x403A0234
SAR_RANGE_INTR_MASK	0x403A0238
SAR_RANGE_INTR_MASKED	0x403A023C
SAR_INTR_CAUSE	0x403A0240
SAR_INJ_CHAN_CONFIG	0x403A0280
SAR_INJ_RESULT	0x403A0290
SAR_STATUS	0x403A02A0
SAR_AVG_STAT	0x403A02A4
SAR_MUX_SWITCH0	0x403A0300
SAR_MUX_SWITCH_CLEAR0	0x403A0304
SAR_MUX_SWITCH_HW_CTRL	0x403A0340
SAR_MUX_SWITCH_STATUS	0x403A0348
SAR_PUMP_CTRL	0x403A0380
SAR_ANA_TRIM	0x403A0F00

20.1.1 SAR_CTRL

Analog control register.

Address: 0x403A0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW			None			
HW Access	R	R			None			
Name	VREF_BYP_CAP_EN	VREF_SEL [6:4]			None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW	None	RW			None
HW Access	R		R	None	R			None
Name	PWR_CTRL_VREF [15:14]		SAR_HW_CTRL_NEGVREF	None	NEG_SEL [11:9]			None

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	RW			
HW Access	None		R	R	R			
Name	None [23:22]		REFBUF_EN	BOOSTPUMP_EN	SPARE [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW	RW	RW	None	RW	
HW Access	R	R	R	R	R	None	R	
Name	ENABLED	SWITCH_DISABLE	DSI_MODE	DSI_SYNC_CONFIG	DEEPSLEEP_ON	None	ICONT_LV [25:24]	

Bits	Name	Description
31	ENABLED	- 0: SAR disabled (put analog in power down and stop clocks), also can clear FW_TRIGGER and INJ_START_EN (if not tailgaiting) on write. - 1: SAR enabled. Default Value: 0
30	SWITCH_DISABLE	Disable SAR sequencer from enabling routing switches (firmware can always close switches independent of this control) - 0: Normal mode, SAR sequencer changes switches according to pin address in channel configurations - 1: Switches disabled, SAR sequencer does not enable any switches, it is the responsibility of the firmware to set the switches to route the signal to be converted through the SARMUX Default Value: 0

20.1.1 SAR_CTRL (continued)

29	DSI_MODE	SAR sequencer takes configuration from DSI signals (note this also has the same effect as SWITCH_DISABLE==1) - 0: Normal mode, SAR sequencer operates according to CHAN_EN enables and CHAN_CONFIG channel configurations - 1: CHAN_EN, INJ_START_EN and channel configurations in CHAN_CONFIG and INJ_CHAN_CONFIG are ignored Default Value: 0
28	DSI_SYNC_CONFIG	Reserved bit Default Value: 1
27	DEEPSLEEP_ON	- 0: SARMUX disabled off during DeepSleep power mode - 1: SARMUX remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0
25 : 24	ICONT_LV	SARADC low power mode. Default Value: 0 **0x0: NORMAL_PWR:** normal power (default), max clk_sar is 18MHz. **0x1: HALF_PWR:** 1/2 power mode, max clk_sar is 9MHz. **0x2: MORE_PWR:** 1.333 power mode, max clk_sar is 18MHz. **0x3: QUARTER_PWR:** 1/4 power mode, max clk_sar is 4.5MHz.
21	REFBUF_EN	1 - Enable the SARREFBUF. This bit needs to be set when SAR is enabled and needs reference buffer. Default Value: 0
20	BOOSTPUMP_EN	SARADC internal pump: 0=disabled: pump output is VDDA, 1=enabled: pump output is boosted. Default Value: 0
19 : 16	SPARE	Reserved bits Default Value: 0
15 : 14	PWR_CTRL_VREF	VREF buffer low power mode. Default Value: 0 **0x0: NORMAL_PWR:** normal power (default), bypass cap, max clk_sar is 18MHz. **0x1: HALF_PWR:** deprecated **0x2: THIRD_PWR:** 2X power, no bypass cap, max clk_sar is 1.8MHz **0x3: QUARTER_PWR:** deprecated
13	SAR_HW_CTRL_NEGVREF	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for VREF to NEG switch. Default Value: 0
11 : 9	NEG_SEL	SARADC internal NEG selection for Single ended conversion Default Value: 0

20.1.1 SAR_CTRL (continued)

		0x0: VSSA_KELVIN: NEG input of SARADC is connected to "vssa_kelvin", gives more precision around zero. Note this opens both SARADC internal switches, therefore use this value to insert a break-before-make cycle on those switches when SWITCH_DISABLE is high. **0x1: ART_VSSA:** NEG input of SARADC is connected to VSSA in AROUTE close to the SARADC **0x2: P1:** NEG input of SARADC is connected to P1 pin of SARMUX **0x3: P3:** NEG input of SARADC is connected to P3 pin of SARMUX **0x4: P5:** NEG input of SARADC is connected to P5 pin of SARMUX **0x5: P7:** NEG input of SARADC is connected to P7 pin of SARMUX **0x6: ACORE:** NEG input of SARADC is connected to an ACORE in AROUTE **0x7: VREF:** NEG input of SARADC is shorted with VREF input of SARADC.
7	VREF_BYP_CAP_EN	VREF bypass cap enable for when VREF buffer is on Default Value: 0
6 : 4	VREF_SEL	SARADC internal VREF selection. Default Value: 0 **0x0: VREF0:** VREF0 from PRB (VREF buffer on) **0x1: VREF1:** VREF1 from PRB (VREF buffer on) **0x2: VREF2:** VREF2 from PRB (VREF buffer on) **0x3: VREF_AROUTE:** VREF from AROUTE (VREF buffer on) **0x4: VBGR:** 1.024V from BandGap (VREF buffer on) **0x5: VREF_EXT:** External precision Vref direct from a pin (low impedance path). **0x6: VDDA_DIV_2:** Vdda/2 (VREF buffer on) **0x7: VDDA:** Vdda.

20.1.2 SAR_SAMPLE_CTRL

Sample control register.

Address: 0x403A0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW			RW	RW	RW	RW
HW Access	R	R			R	R	R	R
Name	AVG_SHIFT	AVG_CNT [6:4]			DIFFERENTIAL_SIGNED	SINGLE_ENDED_SIGNED	LEFT_ALIGN	SUB_RESOLUTION

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							AVG_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	None		RW	RW	RW	RW
HW Access	R	R	None		R	R	R	R
Name	REPEAT_INVALID	UAB_SCAN_MODE	None [21:20]		DSI_SYNC_TRIGGER	DSI_TRIGGER_LEVEL	DSI_TRIGGER_EN	CONTINU-OUS

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None	RW	RW	RW		
HW Access	R	R	None	R	R	R		
Name	EOS_DSI_OUT_EN	TRIGGER_OUT_EN	None	VALID_IGNORE	VALID_SEL_EN	VALID_SEL [26:24]		

Bits	Name	Description
31	EOS_DSI_OUT_EN	Enable to output EOS_INTR Default Value: 0
30	TRIGGER_OUT_EN	SAR output trigger enable (used for UAB synchronization). To ensure multiple UABs starting at the same trigger it is recommended to use this bit to temporarily disable the trigger output until all those UABs are set to run (UAB.SRAM_CTRL.RUN=1). Default Value: 0
28	VALID_IGNORE	Ignore UAB valid signal, including the dynamic/Hardware from AROUTE and the static Valid selection from the VALID_SEL fields above Default Value: 0
27	VALID_SEL_EN	Enable static UAB Valid selection (override Hardware) Default Value: 0

20.1.2 SAR_SAMPLE_CTRL (continued)

26 : 24	VALID_SEL	Static UAB Valid select 0=UAB0 half 0 Valid output 1=UAB0 half 1 Valid output Default Value: 0
23	REPEAT_INVALID	For unscheduled UAB_SCAN_MODE only, do the following if an invalid sample is received: - 0: use the last known valid sample for that channel and clear the NEWVALUE flag - 1: repeat the conversions until a valid sample is received (caveat: could be never if the UAB valid window is incorrectly schedule w.r.t. SAR sampling) Default Value: 0
22	UAB_SCAN_MODE	Select whether UABs are scheduled or unscheduled. When no UAB is scanned this selection is ignored. Default Value: 0 **0x0: UNSCHEDULED:** Unscheduled UABs: one or more of the UABs scanned by the SAR is not scheduled, for each channel that scans a UAB the SAR will wait for a positive edge on the trigger output of that UAB. Caveat: in this mode the length of SAR scan can be variable. **0x1: SCHEDULED:** Scheduled UABs: All UABs scanned by the SAR are assumed to be properly scheduled, i.e. their output is assumed to be valid when sampled by the SAR and the SAR does not wait. In this mode the length of the SAR scan is constant. This mode requires that the SAR scans strictly periodically, i.e. the SAR has to either run continuously or has to be triggered by a periodic hardware trigger. It also requires that the end of the UAB valid phase is precisely aligned with the end of the SAR sample period (using UAB.STARTUP_DELAY). Normally this scheduling is done by Creator.
19	DSI_SYNC_TRIGGER	- 0: bypass clock domain synchronisation of the hardware trigger signal. - 1: synchronize the hardware trigger signal to the SAR clock domain, if needed an edge detect is done in the peripheral clock domain. Default Value: 1
18	DSI_TRIGGER_LEVEL	- 0: Hardware trigger signal is a pulse input, a positive edge detected on the trigger signal triggers a new scan. - 1: Hardware trigger signal is a level input, as long as the trigger signal remains high the SAR will do continuous scans. Default Value: 0
17	DSI_TRIGGER_EN	- 0: firmware trigger only: disable hardware trigger. - 1: enable hardware trigger (e.g. from TCPWM, GPIO). Default Value: 0
16	CONTINUOUS	- 0: Wait for next FW_TRIGGER (one shot) or hardware trigger (e.g. from TPWM for periodic triggering) before scanning enabled channels. - 1: Continuously scan enabled channels, ignore triggers. Default Value: 0
8	AVG_MODE	Averaging mode Default Value: 0 **0x0: ACCUNDUMP:** Accumulate and Dump (1st order accumulate and dump filter): a channel will be sampled back to back and averaged **0x1: INTERLEAVED:** Interleaved: Each scan (trigger) one sample is taken per channel and averaged over several scans.
7	AVG_SHIFT	Averaging shifting: after averaging the result is shifted right to fit in the sample resolution. Default Value: 0

20.1.2 SAR_SAMPLE_CTRL (continued)

6 : 4	AVG_CNT	Averaging Count for channels that have averaging enabled (AVG_EN). A channel will be sampled (1<<(AVG_CNT+1)) = [2..256] times. - In ACCUNDUMP mode (1st order accumulate and dump filter) a channel will be sampled back to back, the average result is calculated and stored and then the next enabled channel is sampled. If shifting is not enabled (AVG_SHIFT=0) then the result is forced to shift right so that is fits in 16 bits, so right shift is done by max(0,AVG_CNT-3). - In INTERLEAVED mode one sample is taken per triggered scan, only in the scan where the final averaging count is reached a valid average is calculated and stored in the RESULT register (by definition the same scan for all the channels that have averaging enabled). In all other scans the RESULT register for averaged channels will have an invalid result and the intermediate accumulated value is stored in the 16-bit WORK register. In this mode make sure that the averaging count is low enough to ensure that the intermediate value does not exceed 16-bits otherwise the MSBs will be lost. So for a 12-bit resolution the averaging count should be set to 16 or less (AVG_CNT=<3). Default Value: 0
3	DIFFERENTIAL_SIGNED	Output data from a differential conversion as a signed value when DIFFERENTIAL_EN or NEG_ADDR_EN is set to 1 Default Value: 1 **0x0: UNSIGNED:** result data is unsigned (zero extended if needed) **0x1: SIGNED:** Default: result data is signed (sign extended if needed)
2	SINGLE_ENDED_SIGNED	Output data from a single ended conversion as a signed value Default Value: 0 **0x0: UNSIGNED:** Default: result data is unsigned (zero extended if needed) **0x1: SIGNED:** result data is signed (sign extended if needed)
1	LEFT_ALIGN	Left align data in data[15:0], default data is right aligned in data[11:0], with sign extension to 16 bits if the channel is differential. Default Value: 0
0	SUB_RESOLUTION	Conversion resolution for channels that have sub-resolution enabled (RESOLUTION=1) (otherwise resolution is 12-bit). Default Value: 0 **0x0: 8B:** 8-bit. **0x1: 10B:** 10-bit.

20.1.3 SAR_SAMPLE_TIME01

Sample time specification ST0 and ST1

Address: 0x403A0010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						SAMPLE_TIME0 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						SAMPLE_TIME1 [25:24]	

Bits	Name	Description
25 : 16	SAMPLE_TIME1	Sample time1 Default Value: 4
9 : 0	SAMPLE_TIME0	Sample time0 (aperture) in ADC clock cycles. Note that actual sample time is half a clock less than specified here. The minimum sample time is 194ns, which is 3.5 cycles (4 in this field) with an 18MHz clock. Minimum legal value in this register is 2. Default Value: 4

20.1.4 SAR_SAMPLE_TIME23

Sample time specification ST2 and ST3

Address: 0x403A0014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME2 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						SAMPLE_TIME2 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME3 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						SAMPLE_TIME3 [25:24]	

Bits	Name	Description
25 : 16	SAMPLE_TIME3	Sample time3 Default Value: 4
9 : 0	SAMPLE_TIME2	Sample time2 Default Value: 4

20.1.5 SAR_RANGE_THRES

Global range detect threshold register.

Address: 0x403A0018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RANGE_LOW [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RANGE_LOW [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	RANGE_HIGH [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	RANGE_HIGH [31:24]							

Bits	Name	Description
31 : 16	RANGE_HIGH	High threshold for range detect. Default Value: 0
15 : 0	RANGE_LOW	Low threshold for range detect. Default Value: 0

20.1.6 SAR_RANGE_COND

Global range detect mode register.

Address: 0x403A001C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	RANGE_COND [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	RANGE_COND	Range condition select. Default Value: 0 **0x0: BELOW:** result < RANGE_LOW **0x1: INSIDE:** RANGE_LOW <= result < RANGE_HIGH **0x2: ABOVE:** RANGE_HIGH <= result **0x3: OUTSIDE:** result < RANGE_LOW || RANGE_HIGH <= result

20.1.7 SAR_CHAN_EN

Enable bits for the channels

Address: 0x403A0020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CHAN_EN [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CHAN_EN [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_EN	Channel enable. - 0: the corresponding channel is disabled. - 1: the corresponding channel is enabled, it will be included in the next scan. Default Value: 0

20.1.8 SAR_START_CTRL

Start control register (firmware trigger).

Address: 0x403A0024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1S
HW Access	None							RW1C
Name	None [7:1]							FW_TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	FW_TRIGGER	When firmware writes a 1 here it will trigger the next scan of enabled channels, hardware clears this bit when the scan started with this trigger is completed. If scanning continuously the trigger is ignored and hardware clears this bit after the next scan is done. This bit is also cleared when the SAR is disabled. Default Value: 0

20.1.9 SAR_CHAN_CONFIG0

Channel configuration register.

Address: 0x403A0080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.9 SAR_CHAN_CONFIG0 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.9 SAR_CHAN_CONFIG0 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.10 SAR_CHAN_CONFIG1

Channel configuration register.

Address: 0x403A0084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.10 SAR_CHAN_CONFIG1 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.10 SAR_CHAN_CONFIG1 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.11 SAR_CHAN_CONFIG2

Channel configuration register.

Address: 0x403A0088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.11 SAR_CHAN_CONFIG2 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.11 SAR_CHAN_CONFIG2 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.12 SAR_CHAN_CONFIG3

Channel configuration register.

Address: 0x403A008C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.12 SAR_CHAN_CONFIG3 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.12 SAR_CHAN_CONFIG3 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.13 SAR_CHAN_CONFIG4

Channel configuration register.

Address: 0x403A0090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.13 SAR_CHAN_CONFIG4 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.13 SAR_CHAN_CONFIG4 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.14 SAR_CHAN_CONFIG5

Channel configuration register.

Address: 0x403A0094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.14 SAR_CHAN_CONFIG5 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.14 SAR_CHAN_CONFIG5 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.15 SAR_CHAN_CONFIG6

Channel configuration register.

Address: 0x403A0098

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.15 SAR_CHAN_CONFIG6 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.15 SAR_CHAN_CONFIG6 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.16 SAR_CHAN_CONFIG7

Channel configuration register.

Address: 0x403A009C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.16 SAR_CHAN_CONFIG7 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.16 SAR_CHAN_CONFIG7 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.17 SAR_CHAN_CONFIG8

Channel configuration register.

Address: 0x403A00A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.17 SAR_CHAN_CONFIG8 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.17 SAR_CHAN_CONFIG8 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.18 SAR_CHAN_CONFIG9

Channel configuration register.

Address: 0x403A00A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.18 SAR_CHAN_CONFIG9 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.18 SAR_CHAN_CONFIG9 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.19 SAR_CHAN_CONFIG10

Channel configuration register.

Address: 0x403A00A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.19 SAR_CHAN_CONFIG10 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.19 SAR_CHAN_CONFIG10 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.20 SAR_CHAN_CONFIG11

Channel configuration register.

Address: 0x403A00AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.20 SAR_CHAN_CONFIG11 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.20 SAR_CHAN_CONFIG11 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.21 SAR_CHAN_CONFIG12

Channel configuration register.

Address: 0x403A00B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.21 SAR_CHAN_CONFIG12 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.21 SAR_CHAN_CONFIG12 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.22 SAR_CHAN_CONFIG13

Channel configuration register.

Address: 0x403A00B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.22 SAR_CHAN_CONFIG13 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.22 SAR_CHAN_CONFIG13 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.23 SAR_CHAN_CONFIG14

Channel configuration register.

Address: 0x403A00B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.23 SAR_CHAN_CONFIG14 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.23 SAR_CHAN_CONFIG14 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.24 SAR_CHAN_CONFIG15

Channel configuration register.

Address: 0x403A00BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	POS_PORT_ADDR [6:4]			None	POS_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	NEG_PORT_ADDR [22:20]			None	NEG_PIN_ADDR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						RW
HW Access	R	None						R
Name	DSI_OUT_ EN	None [30:25]						NEG_ADD R_EN

Bits	Name	Description
31	DSI_OUT_EN	Data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is available for output to pins. HSIOM_PORT_SELx should be set to route the SAR result and the channel number to the pins. Refer device datasheet to know the pins on which the data is available. Default Value: 0
24	NEG_ADDR_EN	1 - The NEG_PIN_ADDR and NEG_PORT_ADDR determines what drives the Vminus pin. This is a variation of differential mode with no even-odd pair limitation 0 - The NEG_SEL determines what drives the Vminus pin. Default Value: 0
22 : 20	NEG_PORT_ADDR	Address of the neg port that contains the pin to be sampled by this channel. Default Value: 0

20.1.24 SAR_CHAN_CONFIG15 (continued)

		0x0: SARMUX: SARMUX pins. **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: RESERVED1:** Unused fields
18 : 16	NEG_PIN_ADDR	Address of the neg pin to be sampled by this channel. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution is used for this channel. Default Value: 0 **0x0: MAXRES:** The maximum resolution is used for this channel **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. If differential is enabled then POS_PIN_ADDR[0] is ignored and considered to be 0, i.e. POS_PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. POS_PORT_ADDR is used to identify the port that contains the pins. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (POS_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	POS_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel (connected to Vplus) Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2)

20.1.24 SAR_CHAN_CONFIG15 (continued)

		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	POS_PIN_ADDR	Address of the pin to be sampled by this channel (connected to Vplus) Default Value: 0

20.1.25 SAR_CHAN_WORK0

Channel working data register

Address: 0x403A0100

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.26 SAR_CHAN_WORK1

Channel working data register

Address: 0x403A0104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.27 SAR_CHAN_WORK2

Channel working data register

Address: 0x403A0108

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.28 SAR_CHAN_WORK3

Channel working data register

Address: 0x403A010C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.29 SAR_CHAN_WORK4

Channel working data register

Address: 0x403A0110

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.30 SAR_CHAN_WORK5

Channel working data register

Address: 0x403A0114

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.31 SAR_CHAN_WORK6

Channel working data register

Address: 0x403A0118

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.32 SAR_CHAN_WORK7

Channel working data register

Address: 0x403A011C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.33 SAR_CHAN_WORK8

Channel working data register

Address: 0x403A0120

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.34 SAR_CHAN_WORK9

Channel working data register

Address: 0x403A0124

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.35 SAR_CHAN_WORK10

Channel working data register

Address: 0x403A0128

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.36 SAR_CHAN_WORK11

Channel working data register

Address: 0x403A012C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.37 SAR_CHAN_WORK12

Channel working data register

Address: 0x403A0130

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.38 SAR_CHAN_WORK13

Channel working data register

Address: 0x403A0134

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.39 SAR_CHAN_WORK14

Channel working data register

Address: 0x403A0138

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.40 SAR_CHAN_WORK15

Channel working data register

Address: 0x403A013C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None			R	None		
HW Access	W	None			W	None		
Name	CHAN_WORK_UPDATED_MIR	None [30:28]			CHAN_WORK_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_WORK_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_UPDATED register Default Value: 0
27	CHAN_WORK_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_NEWVALUE register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

20.1.41 SAR_CHAN_RESULT0

Channel result data register

Address: 0x403A0180

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.42 SAR_CHAN_RESULT1

Channel result data register

Address: 0x403A0184

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.43 SAR_CHAN_RESULT2

Channel result data register

Address: 0x403A0188

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.44 SAR_CHAN_RESULT3

Channel result data register

Address: 0x403A018C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.45 SAR_CHAN_RESULT4

Channel result data register

Address: 0x403A0190

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.46 SAR_CHAN_RESULT5

Channel result data register

Address: 0x403A0194

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.47 SAR_CHAN_RESULT6

Channel result data register

Address: 0x403A0198

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.48 SAR_CHAN_RESULT7

Channel result data register

Address: 0x403A019C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.49 SAR_CHAN_RESULT8

Channel result data register

Address: 0x403A01A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.50 SAR_CHAN_RESULT9

Channel result data register

Address: 0x403A01A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.51 SAR_CHAN_RESULT10

Channel result data register

Address: 0x403A01A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.52 SAR_CHAN_RESULT11

Channel result data register

Address: 0x403A01AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.53 SAR_CHAN_RESULT12

Channel result data register

Address: 0x403A01B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.54 SAR_CHAN_RESULT13

Channel result data register

Address: 0x403A01B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.55 SAR_CHAN_RESULT14

Channel result data register

Address: 0x403A01B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.56 SAR_CHAN_RESULT15

Channel result data register

Address: 0x403A01BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None	R	None		
HW Access	W	W	W	None	W	None		
Name	CHAN_RESULT_UPDATED_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None	CHAN_RESULT_NEWVALUE_MIR	None [26:24]		

Bits	Name	Description
31	CHAN_RESULT_UPDATED_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_UPDATED register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
27	CHAN_RESULT_NEWVALUE_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_NEWVALUE register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

20.1.57 SAR_CHAN_WORK_UPDATED

Channel working data register 'updated' bits

Address: 0x403A0200

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_UPDATED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_UPDATED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_WORK_UPDATED	If set the corresponding WORK register was updated, i.e. was already sampled during the current scan and, in case of Interleaved averaging, reached the averaging count. If this bit is low then either the channel is not enabled or the averaging count is not yet reached for Interleaved averaging. Default Value: 0

20.1.58 SAR_CHAN_RESULT_UPDATED

Channel result data register 'updated' bits

Address: 0x403A0204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_UPDATED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_UPDATED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_RESULT_UPDATED	If set the corresponding RESULT register was updated, i.e. was sampled during the previous scan and, in case of Interleaved averaging, reached the averaging count. If this bit is low then either the channel is not enabled or the averaging count is not yet reached for Interleaved averaging. Default Value: 0

20.1.59 SAR_CHAN_WORK_NEWVALUE

Channel working data register 'new value' bits

Address: 0x403A0208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_NEWVALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_NEWVALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_WORK_NEWVALUE	If set the corresponding WORK data received a new value, i.e. was already sampled during the current scan and data was valid. In case of a UAB this New Value bit reflects the value of UAB.valid output, for anything else the data is always valid. In case of averaging this New Value bit is an OR of all the valid bits received by each conversion. Default Value: 0

20.1.60 SAR_CHAN_RESULT_NEWVALUE

Channel result data register 'new value' bits

Address: 0x403A020C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_NEWVALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_NEWVALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_RESULT_NEWVALUE	If set the corresponding RESULT data received a new value, i.e. was sampled during the last scan and data was valid. In case of a UAB this New Value bit reflects the value of UAB.valid output, for anything else the data is always valid. In case of averaging this New Value bit is an OR of all the valid bits received by each conversion. Default Value: 0

20.1.61 SAR_INTR

Interrupt request register.

Address: 0x403A0210

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	INJ_COLLISION_INTR	INJ_RANGE_INTR	INJ_SATURATE_INTR	INJ_EOC_INTR	DSI_COLLISION_INTR	FW_COLLISION_INTR	OVERFLOW_INTR	EOS_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_INTR	Injection Collision Interrupt: hardware sets this interrupt when the injection trigger signal is asserted (INJ_START_EN==1 && INJ_TAILGATING==0) while the SAR is BUSY. Raising this interrupt is delayed to when the sampling of the injection channel has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the injection channel was sampled later than was intended. Write with '1' to clear bit. Default Value: 0
6	INJ_RANGE_INTR	Injection Range detect Interrupt: hardware sets this interrupt if the injection conversion result (after averaging) met the condition specified by the SAR_RANGE registers. Write with '1' to clear bit. Default Value: 0
5	INJ_SATURATE_INTR	Injection Saturation Interrupt: hardware sets this interrupt if an injection conversion result (before averaging) is either 0x000 or 0xFFF (for 12-bit resolution), this is an indication that the ADC likely saturated. Write with '1' to clear bit. Default Value: 0
4	INJ_EOC_INTR	Injection End of Conversion Interrupt: hardware sets this interrupt after completing the conversion for the injection channel (irrespective of if tailgating was used). Write with '1' to clear bit. Default Value: 0

20.1.61 SAR_INTR (continued)

3	DSI_COLLISION_INTR	DSI Collision Interrupt: hardware sets this interrupt when the hardware trigger signal is asserted while the SAR is BUSY. Raising this interrupt is delayed to when the scan caused by the trigger has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the channels were sampled later than was intended (jitter). Write with '1' to clear bit. Default Value: 0
2	FW_COLLISION_INTR	Firmware Collision Interrupt: hardware sets this interrupt when FW_TRIGGER is asserted while the SAR is BUSY. Raising this interrupt is delayed to when the scan caused by the FW_TRIGGER has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the channels were sampled later than was intended (jitter). Write with '1' to clear bit. Default Value: 0
1	OVERFLOW_INTR	Overflow Interrupt: hardware sets this interrupt when it sets a new EOS_INTR while that bit was not yet cleared by the firmware. Write with '1' to clear bit. Default Value: 0
0	EOS_INTR	End Of Scan Interrupt: hardware sets this interrupt after completing a scan of all the enabled channels. Write with '1' to clear bit. Default Value: 0

20.1.62 SAR_INTR_SET

Interrupt set request register

Address: 0x403A0214

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	INJ_COLLISION_SET	INJ_RANGE_SET	INJ_SATURATE_SET	INJ_EOC_SET	DSI_COLLISION_SET	FW_COLLISION_SET	OVERFLOW_SET	EOS_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	INJ_RANGE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	INJ_SATURATE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	INJ_EOC_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	DSI_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	FW_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	OVERFLOW_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

20.1.62 SAR_INTR_SET (continued)

0	EOS_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

20.1.63 SAR_INTR_MASK

Interrupt mask register.

Address: 0x403A0218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INJ_COLLISION_MASK	INJ_RANGE_MASK	INJ_SATURATE_MASK	INJ_EOC_MASK	DSI_COLLISION_MASK	FW_COLLISION_MASK	OVERFLOW_MASK	EOS_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	INJ_RANGE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	INJ_SATURATE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	INJ_EOC_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	DSI_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	FW_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	OVERFLOW_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

20.1.63 SAR_INTR_MASK (continued)

0	EOS_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

20.1.64 SAR_INTR_MASKED

Interrupt masked request register

Address: 0x403A021C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	INJ_COLLISION_MASKED	INJ_RANGE_MASKED	INJ_SATURATE_MASKED	INJ_EOC_MASKED	DSI_COLLISION_MASKED	FW_COLLISION_MASKED	OVERFLOW_MASKED	EOS_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
6	INJ_RANGE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
5	INJ_SATURATE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
4	INJ_EOC_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
3	DSI_COLLISION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
2	FW_COLLISION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
1	OVERFLOW_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

20.1.64 SAR_INTR_MASKED (continued)

0	EOS_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

20.1.65 SAR_SATURATE_INTR

Saturate interrupt request register.

Address: 0x403A0220

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	SATURATE_INTR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	RW1S							
Name	SATURATE_INTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_INTR	Saturate Interrupt: hardware sets this interrupt for each channel if a conversion result (before averaging) of that channel is either 0x000 or 0xFFF (for 12-bit resolution), this is an indication that the ADC likely saturated. Write with '1' to clear bit. Default Value: 0

20.1.66 SAR_SATURATE_INTR_SET

Saturate interrupt set request register

Address: 0x403A0224

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	SATURATE_SET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	A							
Name	SATURATE_SET [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

20.1.67 SAR_SATURATE_INTR_MASK

Saturate interrupt mask register.

Address: 0x403A0228

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SATURATE_MASK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	SATURATE_MASK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

20.1.68 SAR_SATURATE_INTR_MASKED

Saturate interrupt masked request register

Address: 0x403A022C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	SATURATE_MASKED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	SATURATE_MASKED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

20.1.69 SAR_RANGE_INTR

Range detect interrupt request register.

Address: 0x403A0230

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	RANGE_INTR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	RW1S							
Name	RANGE_INTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_INTR	Range detect Interrupt: hardware sets this interrupt for each channel if the conversion result (after averaging) of that channel met the condition specified by the SAR_RANGE registers. Write with '1' to clear bit. Default Value: 0

20.1.70 SAR_RANGE_INTR_SET

Range detect interrupt set request register

Address: 0x403A0234

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	RANGE_SET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	A							
Name	RANGE_SET [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

20.1.71 SAR_RANGE_INTR_MASK

Range detect interrupt mask register.

Address: 0x403A0238

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RANGE_MASK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RANGE_MASK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

20.1.72 SAR_RANGE_INTR_MASKED

Range interrupt masked request register

Address: 0x403A023C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RANGE_MASKED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RANGE_MASKED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

20.1.73 SAR_INTR_CAUSE

Interrupt cause register

Address: 0x403A0240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	INJ_COLLISION_MASKED_MIR	INJ_RANGE_MASKED_MIR	INJ_SATURATE_MASKED_MIR	INJ_EOC_MASKED_MIR	DSI_COLLISION_MASKED_MIR	FW_COLLISION_MASKED_MIR	OVERFLOW_MASKED_MIR	EOS_MASKED_MIR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	RANGE_MASKED_RED	SATURATE_MASKED_RED	None [29:24]					

Bits	Name	Description
31	RANGE_MASKED_RED	Reduction OR of all SAR_RANGE_INTR_MASKED bits Default Value: 0
30	SATURATE_MASKED_RED	Reduction OR of all SAR_SATURATION_INTR_MASKED bits Default Value: 0
7	INJ_COLLISION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
6	INJ_RANGE_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
5	INJ_SATURATE_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
4	INJ_EOC_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0

20.1.73 SAR_INTR_CAUSE (continued)

3	DSI_COLLISION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
2	FW_COLLISION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
1	OVERFLOW_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
0	EOS_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0

20.1.74 SAR_INJ_CHAN_CONFIG

Injection channel configuration register.

Address: 0x403A0280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	INJ_PORT_ADDR [6:4]			None	INJ_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		INJ_SAMPLE_TIME_SEL [13:12]		None	INJ_AVG_EN	INJ_RESOLUTION	INJ_DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	RW	None					
HW Access	RW1C	R	None					
Name	INJ_START_EN	INJ_TAILGATING	None [29:24]					

Bits	Name	Description
31	INJ_START_EN	Set by firmware to enable the injection channel. If INJ_TAILGATING is not set this bit also functions as trigger for this channel. Cleared by hardware after this channel has been sampled (i.e. this channel is always one shot even if CONTINUOUS is set). Also cleared if the SAR is disabled. Default Value: 0
30	INJ_TAILGATING	Injection channel tailgating. - 0: no tailgating for this channel, SAR is immediately triggered when the INJ_START_EN bit is set. - 1: injection channel tailgating. The addressed pin is sampled after the next trigger and after all enabled channels have been scanned. Default Value: 0
13 : 12	INJ_SAMPLE_TIME_SEL	Injection sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	INJ_AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0

20.1.74 SAR_INJ_CHAN_CONFIG (continued)

9	INJ_RESOLUTION	Resolution for this channel. Default Value: 0 **0x0: 12B:** 12-bit resolution is used for this channel. **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	INJ_DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (INJ_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	INJ_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** Not available in PSoC Analog Coprocessor **0x4: CTB3:** Not available in PSoC Analog Coprocessor **0x6: AROUTE_VIRT:** AROUTE virtual port **0x7: SARMUX_VIRT:** SARMUX virtual port
2 : 0	INJ_PIN_ADDR	Address of the pin to be sampled by this injection channel. If differential is enabled then INJ_PIN_ADDR[0] is ignored and considered to be 0, i.e. INJ_PIN_ADDR points to the even pin of a pin pair. Default Value: 0

20.1.75 SAR_INJ_RESULT

Injection channel result register

Address: 0x403A0290

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	INJ_RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	INJ_RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	R	R	None		
HW Access	W	W	W	W	W	None		
Name	INJ_EOC_INTR_MIR	INJ_RANGE_INTR_MIR	INJ_SATURATE_INTR_MIR	INJ_COLLISION_INTR_MIR	INJ_NEWVALUE	None [26:24]		

Bits	Name	Description
31	INJ_EOC_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
30	INJ_RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
29	INJ_SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
28	INJ_COLLISION_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
27	INJ_NEWVALUE	The data in this register received a new value (only relevant for UAB, this bit shows the value of the UAB valid bit) Default Value: 0
15 : 0	INJ_RESULT	SAR conversion result of the channel. Default Value: Undefined

20.1.76 SAR_STATUS

Current status of internal SAR registers (mostly for debug)

Address: 0x403A02A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CUR_CHAN [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	BUSY	SW_VREF_NEG	None [29:24]					

Bits	Name	Description
31	BUSY	If high then the SAR is busy with a conversion. This bit is always high when CONTINUOUS is set. Firmware should wait for this bit to be low before putting the SAR in power down. Default Value: 0
30	SW_VREF_NEG	the current switch status, including sequencer controls, of the switch in the SARADC that shorts NEG with VREF input (see NEG_SEL). Default Value: 0
4 : 0	CUR_CHAN	current channel being sampled (channel 16 indicates the injection channel), only valid if BUSY. Default Value: 0

20.1.77 SAR_AVG_STAT

Current averaging status (for debug)

Address: 0x403A02A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	CUR_AVG_ACCU [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CUR_AVG_ACCU [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R	None			R			
HW Access	W	None			W			
Name	INTRLV_BUSY	None [22:20]			CUR_AVG_ACCU [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	CUR_AVG_CNT [31:24]							

Bits	Name	Description
31 : 24	CUR_AVG_CNT	the current value of the averaging counter. Note that the value shown is updated after the sampling time and therefore runs ahead of the accumulator update. Default Value: 0
23	INTRLV_BUSY	If high then the SAR is in the middle of Interleaved averaging spanning several scans. While this bit is high the Firmware should not make any changes to the configuration registers otherwise some results may be incorrect. Note that the CUR_AVG_CNT status register below gives an indication how many more scans need to be done to complete the Interleaved averaging. This bit can be cleared by changing the averaging mode to ACCUNDUMP or by disabling the SAR. Default Value: 0
19 : 0	CUR_AVG_ACCU	the current value of the averaging accumulator Default Value: 0

20.1.78 SAR_MUX_SWITCH0

SARMUX Firmware switch controls

Address: 0x403A0300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_FW_P7_VPLUS	MUX_FW_P6_VPLUS	MUX_FW_P5_VPLUS	MUX_FW_P4_VPLUS	MUX_FW_P3_VPLUS	MUX_FW_P2_VPLUS	MUX_FW_P1_VPLUS	MUX_FW_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_FW_P7_VMINUS	MUX_FW_P6_VMINUS	MUX_FW_P5_VMINUS	MUX_FW_P4_VMINUS	MUX_FW_P3_VMINUS	MUX_FW_P2_VMINUS	MUX_FW_P1_VMINUS	MUX_FW_P0_VMINUS

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_FW_SARBUS1_VPLUS	MUX_FW_SARBUS0_VPLUS	MUX_FW_AMUXBUSB_VMINUS	MUX_FW_AMUXBUSA_VMINUS	MUX_FW_AMUXBUSB_VPLUS	MUX_FW_AMUXBUSA_VPLUS	MUX_FW_TEMP_VPLUS	MUX_FW_VSSA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [31:30]		MUX_FW_P7_COREIO3	MUX_FW_P6_COREIO2	MUX_FW_P5_COREIO1	MUX_FW_P4_COREIO0	MUX_FW_SARBUS1_VMINUS	MUX_FW_SARBUS0_VMINUS

Bits	Name	Description
29	MUX_FW_P7_COREIO3	Firmware control: 0=open, 1=close switch between P7 and coreio3 signal. Write with '1' to set bit. Default Value: 0
28	MUX_FW_P6_COREIO2	Firmware control: 0=open, 1=close switch between P6 and coreio2 signal. Write with '1' to set bit. Default Value: 0
27	MUX_FW_P5_COREIO1	Firmware control: 0=open, 1=close switch between P5 and coreio1 signal. Write with '1' to set bit. Default Value: 0
26	MUX_FW_P4_COREIO0	Firmware control: 0=open, 1=close switch between P4 and coreio0 signal. Write with '1' to set bit. Default Value: 0
25	MUX_FW_SARBUS1_VMINUS	Firmware control: 0=open, 1=close switch between sarbus1 and vminus signal. Write with '1' to set bit. Default Value: 0

20.1.78 SAR_MUX_SWITCH0 (continued)

24	MUX_FW_SARBUS0_VMINUS	Firmware control: 0=open, 1=close switch between sarbus0 and vminus signal. Write with '1' to set bit. Default Value: 0
23	MUX_FW_SARBUS1_VPLUS	Firmware control: 0=open, 1=close switch between sarbus1 and vplus signal. Write with '1' to set bit. Default Value: 0
22	MUX_FW_SARBUS0_VPLUS	Firmware control: 0=open, 1=close switch between sarbus0 and vplus signal. Write with '1' to set bit. Default Value: 0
21	MUX_FW_AMUXBUSB_VMINUS	Firmware control: 0=open, 1=close switch between amuxbusb and vminus signal. Write with '1' to set bit. Default Value: 0
20	MUX_FW_AMUXBUSA_VMINUS	Firmware control: 0=open, 1=close switch between amuxbusa and vminus signal. Write with '1' to set bit. Default Value: 0
19	MUX_FW_AMUXBUSB_VPLUS	Firmware control: 0=open, 1=close switch between amuxbusb and vplus signal. Write with '1' to set bit. Default Value: 0
18	MUX_FW_AMUXBUSA_VPLUS	Firmware control: 0=open, 1=close switch between amuxbusa and vplus signal. Write with '1' to set bit. Default Value: 0
17	MUX_FW_TEMP_VPLUS	Firmware control: 0=open, 1=close switch between temperature sensor and vplus signal, also powers on the temperature sensor. Write with '1' to set bit. Default Value: 0
16	MUX_FW_VSSA_VMINUS	Firmware control: 0=open, 1=close switch between vssa_kelvin and vminus signal. Write with '1' to set bit. Default Value: 0
15	MUX_FW_P7_VMINUS	Firmware control: 0=open, 1=close switch between pin P7 and vminus signal. Write with '1' to set bit. Default Value: 0
14	MUX_FW_P6_VMINUS	Firmware control: 0=open, 1=close switch between pin P6 and vminus signal. Write with '1' to set bit. Default Value: 0
13	MUX_FW_P5_VMINUS	Firmware control: 0=open, 1=close switch between pin P5 and vminus signal. Write with '1' to set bit. Default Value: 0
12	MUX_FW_P4_VMINUS	Firmware control: 0=open, 1=close switch between pin P4 and vminus signal. Write with '1' to set bit. Default Value: 0
11	MUX_FW_P3_VMINUS	Firmware control: 0=open, 1=close switch between pin P3 and vminus signal. Write with '1' to set bit. Default Value: 0
10	MUX_FW_P2_VMINUS	Firmware control: 0=open, 1=close switch between pin P2 and vminus signal. Write with '1' to set bit. Default Value: 0
9	MUX_FW_P1_VMINUS	Firmware control: 0=open, 1=close switch between pin P1 and vminus signal. Write with '1' to set bit. Default Value: 0

20.1.78 SAR_MUX_SWITCH0 (continued)

8	MUX_FW_P0_VMINUS	Firmware control: 0=open, 1=close switch between pin P0 and vminus signal. Write with '1' to set bit. Default Value: 0
7	MUX_FW_P7_VPLUS	Firmware control: 0=open, 1=close switch between pin P7 and vplus signal. Write with '1' to set bit. Default Value: 0
6	MUX_FW_P6_VPLUS	Firmware control: 0=open, 1=close switch between pin P6 and vplus signal. Write with '1' to set bit. Default Value: 0
5	MUX_FW_P5_VPLUS	Firmware control: 0=open, 1=close switch between pin P5 and vplus signal. Write with '1' to set bit. Default Value: 0
4	MUX_FW_P4_VPLUS	Firmware control: 0=open, 1=close switch between pin P4 and vplus signal. Write with '1' to set bit. Default Value: 0
3	MUX_FW_P3_VPLUS	Firmware control: 0=open, 1=close switch between pin P3 and vplus signal. Write with '1' to set bit. Default Value: 0
2	MUX_FW_P2_VPLUS	Firmware control: 0=open, 1=close switch between pin P2 and vplus signal. Write with '1' to set bit. Default Value: 0
1	MUX_FW_P1_VPLUS	Firmware control: 0=open, 1=close switch between pin P1 and vplus signal. Write with '1' to set bit. Default Value: 0
0	MUX_FW_P0_VPLUS	Firmware control: 0=open, 1=close switch between pin P0 and vplus signal. Write with '1' to set bit. Default Value: 0

20.1.79 SAR_MUX_SWITCH_CLEAR0

SARMUX Firmware switch control clear

Address: 0x403A0304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_FW_P7_VPLUS	MUX_FW_P6_VPLUS	MUX_FW_P5_VPLUS	MUX_FW_P4_VPLUS	MUX_FW_P3_VPLUS	MUX_FW_P2_VPLUS	MUX_FW_P1_VPLUS	MUX_FW_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_FW_P7_VMINUS	MUX_FW_P6_VMINUS	MUX_FW_P5_VMINUS	MUX_FW_P4_VMINUS	MUX_FW_P3_VMINUS	MUX_FW_P2_VMINUS	MUX_FW_P1_VMINUS	MUX_FW_P0_VMINUS

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_FW_SARBUS1_VPLUS	MUX_FW_SARBUS0_VPLUS	MUX_FW_AMUXBUSB_VMINUS	MUX_FW_AMUXBUSA_VMINUS	MUX_FW_AMUXBUSB_VPLUS	MUX_FW_AMUXBUSA_VPLUS	MUX_FW_TEMP_VPLUS	MUX_FW_VSSA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None		A	A	A	A	A	A
Name	None [31:30]		MUX_FW_P7_COREIO3	MUX_FW_P6_COREIO2	MUX_FW_P5_COREIO1	MUX_FW_P4_COREIO0	MUX_FW_SARBUS1_VMINUS	MUX_FW_SARBUS0_VMINUS

Bits	Name	Description
29	MUX_FW_P7_COREIO3	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
28	MUX_FW_P6_COREIO2	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
27	MUX_FW_P5_COREIO1	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
26	MUX_FW_P4_COREIO0	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
25	MUX_FW_SARBUS1_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

20.1.79 SAR_MUX_SWITCH_CLEAR0 (continued)

24	MUX_FW_SARBUS0_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
23	MUX_FW_SARBUS1_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
22	MUX_FW_SARBUS0_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
21	MUX_FW_AMUXBUSB_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
20	MUX_FW_AMUXBUSA_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
19	MUX_FW_AMUXBUSB_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
18	MUX_FW_AMUXBUSA_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
17	MUX_FW_TEMP_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
16	MUX_FW_VSSA_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
15	MUX_FW_P7_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
14	MUX_FW_P6_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
13	MUX_FW_P5_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
12	MUX_FW_P4_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
11	MUX_FW_P3_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
10	MUX_FW_P2_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
9	MUX_FW_P1_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
8	MUX_FW_P0_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
7	MUX_FW_P7_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
6	MUX_FW_P6_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
5	MUX_FW_P5_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
4	MUX_FW_P4_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
3	MUX_FW_P3_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

20.1.79 SAR_MUX_SWITCH_CLEAR0 (continued)

2	MUX_FW_P2_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
1	MUX_FW_P1_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
0	MUX_FW_P0_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

20.1.80 SAR_MUX_SWITCH_HW_CTRL

SARMUX switch hardware control

Address: 0x403A0340

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	MUX_HW_CTRL_P7	MUX_HW_CTRL_P6	MUX_HW_CTRL_P5	MUX_HW_CTRL_P4	MUX_HW_CTRL_P3	MUX_HW_CTRL_P2	MUX_HW_CTRL_P1	MUX_HW_CTRL_P0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	None		RW	RW	RW	RW
HW Access	R	R	None		R	R	R	R
Name	MUX_HW_CTRL_SARBUS1	MUX_HW_CTRL_SARBUS0	None [21:20]		MUX_HW_CTRL_AMUXBUSB	MUX_HW_CTRL_AMUXBUSA	MUX_HW_CTRL_TEMP	MUX_HW_CTRL_VSSA

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	MUX_HW_CTRL_SARBUS1	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for sarbus1 switches. Default Value: 0
22	MUX_HW_CTRL_SARBUS0	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for sarbus0 switches. Default Value: 0
19	MUX_HW_CTRL_AMUXBUSB	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for amuxbusb switches. Default Value: 0
18	MUX_HW_CTRL_AMUXBUSA	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for amuxbusa switches. Default Value: 0
17	MUX_HW_CTRL_TEMP	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for temp switch. Default Value: 0

20.1.80 SAR_MUX_SWITCH_HW_CTRL (continued)

16	MUX_HW_CTRL_VSSA	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for vssa switch. Default Value: 0
7	MUX_HW_CTRL_P7	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P7 switches. Default Value: 0
6	MUX_HW_CTRL_P6	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P6 switches. Default Value: 0
5	MUX_HW_CTRL_P5	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P5 switches. Default Value: 0
4	MUX_HW_CTRL_P4	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P4 switches. Default Value: 0
3	MUX_HW_CTRL_P3	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P3 switches. Default Value: 0
2	MUX_HW_CTRL_P2	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P2 switches. Default Value: 0
1	MUX_HW_CTRL_P1	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P1 switches. Default Value: 0
0	MUX_HW_CTRL_P0	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P0 switches. Default Value: 0

20.1.81 SAR_MUX_SWITCH_STATUS

SARMUX switch status

Address: 0x403A0348

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_FW_P7_VPLUS	MUX_FW_P6_VPLUS	MUX_FW_P5_VPLUS	MUX_FW_P4_VPLUS	MUX_FW_P3_VPLUS	MUX_FW_P2_VPLUS	MUX_FW_P1_VPLUS	MUX_FW_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_FW_P7_VMINUS	MUX_FW_P6_VMINUS	MUX_FW_P5_VMINUS	MUX_FW_P4_VMINUS	MUX_FW_P3_VMINUS	MUX_FW_P2_VMINUS	MUX_FW_P1_VMINUS	MUX_FW_P0_VMINUS

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_FW_SARBUS1_VPLUS	MUX_FW_SARBUS0_VPLUS	MUX_FW_AMUXBUSB_VMINUS	MUX_FW_AMUXBUSA_VMINUS	MUX_FW_AMUXBUSB_VPLUS	MUX_FW_AMUXBUSA_VPLUS	MUX_FW_TEMP_VPLUS	MUX_FW_VSSA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None						R	R
HW Access	None						W	W
Name	None [31:26]						MUX_FW_SARBUS1_VMINUS	MUX_FW_SARBUS0_VMINUS

Bits	Name	Description
25	MUX_FW_SARBUS1_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
24	MUX_FW_SARBUS0_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
23	MUX_FW_SARBUS1_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
22	MUX_FW_SARBUS0_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
21	MUX_FW_AMUXBUSB_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0

20.1.81 SAR_MUX_SWITCH_STATUS (continued)

20	MUX_FW_AMUXBUSA_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
19	MUX_FW_AMUXBUSB_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
18	MUX_FW_AMUXBUSA_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
17	MUX_FW_TEMP_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
16	MUX_FW_VSSA_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
15	MUX_FW_P7_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
14	MUX_FW_P6_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
13	MUX_FW_P5_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
12	MUX_FW_P4_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
11	MUX_FW_P3_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
10	MUX_FW_P2_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
9	MUX_FW_P1_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
8	MUX_FW_P0_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
7	MUX_FW_P7_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
6	MUX_FW_P6_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
5	MUX_FW_P5_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
4	MUX_FW_P4_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
3	MUX_FW_P3_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
2	MUX_FW_P2_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
1	MUX_FW_P1_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
0	MUX_FW_P0_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0

20.1.82 SAR_PUMP_CTRL

Switch pump control

Address: 0x403A0380

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							CLOCK_SEL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLED	None [30:24]						

Bits	Name	Description
31	ENABLED	0=disabled: pump output is VDDA_PUMP, 1=enabled: pump output is boosted. Default Value: 0
0	CLOCK_SEL	Clock select: 0=external clock, 1=internal clock (deprecated). Default Value: 0

20.1.83 SAR_ANA_TRIM

Analog trim register.

Address: 0x403A0F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW		
HW Access	None				R	R		
Name	None [7:4]				TRIMUNIT	CAP_TRIM [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	TRIMUNIT	Attenuation cap trimming Default Value: 0
2 : 0	CAP_TRIM	Attenuation cap trimming Default Value: 0

21 Serial Communication Block (SCB) Registers

This section discusses the SCB registers. It lists all the registers in mapping tables, in address order.

21.1 Register Details

Register Name	Address
SCB0_CTRL	0x40070000
SCB0_STATUS	0x40070004
SCB0_SPI_CTRL	0x40070020
SCB0_SPI_STATUS	0x40070024
SCB0_UART_CTRL	0x40070040
SCB0_UART_TX_CTRL	0x40070044
SCB0_UART_RX_CTRL	0x40070048
SCB0_UART_RX_STATUS	0x4007004C
SCB0_UART_FLOW_CTRL	0x40070050
SCB0_I2C_CTRL	0x40070060
SCB0_I2C_STATUS	0x40070064
SCB0_I2C_M_CMD	0x40070068
SCB0_I2C_S_CMD	0x4007006C
SCB0_I2C_CFG	0x40070070
SCB0_TX_CTRL	0x40070200
SCB0_TX_FIFO_CTRL	0x40070204
SCB0_TX_FIFO_STATUS	0x40070208
SCB0_TX_FIFO_WR	0x40070240
SCB0_RX_CTRL	0x40070300
SCB0_RX_FIFO_CTRL	0x40070304
SCB0_RX_FIFO_STATUS	0x40070308
SCB0_RX_MATCH	0x40070310
SCB0_RX_FIFO_RD	0x40070340
SCB0_RX_FIFO_RD_SILENT	0x40070344
SCB0_EZ_DATA0	0x40070400
SCB0_EZ_DATA1	0x40070404
SCB0_EZ_DATA2	0x40070408

Register Name	Address
SCB0_EZ_DATA3	0x4007040C
SCB0_EZ_DATA4	0x40070410
SCB0_EZ_DATA5	0x40070414
SCB0_EZ_DATA6	0x40070418
SCB0_EZ_DATA7	0x4007041C
SCB0_EZ_DATA8	0x40070420
SCB0_EZ_DATA9	0x40070424
SCB0_EZ_DATA10	0x40070428
SCB0_EZ_DATA11	0x4007042C
SCB0_EZ_DATA12	0x40070430
SCB0_EZ_DATA13	0x40070434
SCB0_EZ_DATA14	0x40070438
SCB0_EZ_DATA15	0x4007043C
SCB0_EZ_DATA16	0x40070440
SCB0_EZ_DATA17	0x40070444
SCB0_EZ_DATA18	0x40070448
SCB0_EZ_DATA19	0x4007044C
SCB0_EZ_DATA20	0x40070450
SCB0_EZ_DATA21	0x40070454
SCB0_EZ_DATA22	0x40070458
SCB0_EZ_DATA23	0x4007045C
SCB0_EZ_DATA24	0x40070460
SCB0_EZ_DATA25	0x40070464
SCB0_EZ_DATA26	0x40070468
SCB0_EZ_DATA27	0x4007046C
SCB0_EZ_DATA28	0x40070470
SCB0_EZ_DATA29	0x40070474
SCB0_EZ_DATA30	0x40070478
SCB0_EZ_DATA31	0x4007047C
SCB0_INTR_CAUSE	0x40070E00
SCB0_INTR_I2C_EC	0x40070E80
SCB0_INTR_I2C_EC_MASK	0x40070E88
SCB0_INTR_I2C_EC_MASKED	0x40070E8C
SCB0_INTR_SPI_EC	0x40070EC0
SCB0_INTR_SPI_EC_MASK	0x40070EC8
SCB0_INTR_SPI_EC_MASKED	0x40070ECC
SCB0_INTR_M	0x40070F00
SCB0_INTR_M_SET	0x40070F04
SCB0_INTR_M_MASK	0x40070F08
SCB0_INTR_M_MASKED	0x40070F0C
SCB0_INTR_S	0x40070F40
SCB0_INTR_S_SET	0x40070F44

Register Name	Address
SCB0_INTR_S_MASK	0x40070F48
SCB0_INTR_S_MASKED	0x40070F4C
SCB0_INTR_TX	0x40070F80
SCB0_INTR_TX_SET	0x40070F84
SCB0_INTR_TX_MASK	0x40070F88
SCB0_INTR_TX_MASKED	0x40070F8C
SCB0_INTR_RX	0x40070FC0
SCB0_INTR_RX_SET	0x40070FC4
SCB0_INTR_RX_MASK	0x40070FC8
SCB0_INTR_RX_MASKED	0x40070FCC
SCB1_CTRL	0x40080000
SCB1_STATUS	0x40080004
SCB1_SPI_CTRL	0x40080020
SCB1_SPI_STATUS	0x40080024
SCB1_UART_CTRL	0x40080040
SCB1_UART_TX_CTRL	0x40080044
SCB1_UART_RX_CTRL	0x40080048
SCB1_UART_RX_STATUS	0x4008004C
SCB1_UART_FLOW_CTRL	0x40080050
SCB1_I2C_CTRL	0x40080060
SCB1_I2C_STATUS	0x40080064
SCB1_I2C_M_CMD	0x40080068
SCB1_I2C_S_CMD	0x4008006C
SCB1_I2C_CFG	0x40080070
SCB1_TX_CTRL	0x40080200
SCB1_TX_FIFO_CTRL	0x40080204
SCB1_TX_FIFO_STATUS	0x40080208
SCB1_TX_FIFO_WR	0x40080240
SCB1_RX_CTRL	0x40080300
SCB1_RX_FIFO_CTRL	0x40080304
SCB1_RX_FIFO_STATUS	0x40080308
SCB1_RX_MATCH	0x40080310
SCB1_RX_FIFO_RD	0x40080340
SCB1_RX_FIFO_RD_SILENT	0x40080344
SCB1_EZ_DATA0	0x40080400
SCB1_EZ_DATA1	0x40080404
SCB1_EZ_DATA2	0x40080408
SCB1_EZ_DATA3	0x4008040C
SCB1_EZ_DATA4	0x40080410
SCB1_EZ_DATA5	0x40080414
SCB1_EZ_DATA6	0x40080418
SCB1_EZ_DATA7	0x4008041C

Register Name	Address
SCB1_EZ_DATA8	0x40080420
SCB1_EZ_DATA9	0x40080424
SCB1_EZ_DATA10	0x40080428
SCB1_EZ_DATA11	0x4008042C
SCB1_EZ_DATA12	0x40080430
SCB1_EZ_DATA13	0x40080434
SCB1_EZ_DATA14	0x40080438
SCB1_EZ_DATA15	0x4008043C
SCB1_EZ_DATA16	0x40080440
SCB1_EZ_DATA17	0x40080444
SCB1_EZ_DATA18	0x40080448
SCB1_EZ_DATA19	0x4008044C
SCB1_EZ_DATA20	0x40080450
SCB1_EZ_DATA21	0x40080454
SCB1_EZ_DATA22	0x40080458
SCB1_EZ_DATA23	0x4008045C
SCB1_EZ_DATA24	0x40080460
SCB1_EZ_DATA25	0x40080464
SCB1_EZ_DATA26	0x40080468
SCB1_EZ_DATA27	0x4008046C
SCB1_EZ_DATA28	0x40080470
SCB1_EZ_DATA29	0x40080474
SCB1_EZ_DATA30	0x40080478
SCB1_EZ_DATA31	0x4008047C
SCB1_INTR_CAUSE	0x40080E00
SCB1_INTR_I2C_EC	0x40080E80
SCB1_INTR_I2C_EC_MASK	0x40080E88
SCB1_INTR_I2C_EC_MASKED	0x40080E8C
SCB1_INTR_SPI_EC	0x40080EC0
SCB1_INTR_SPI_EC_MASK	0x40080EC8
SCB1_INTR_SPI_EC_MASKED	0x40080ECC
SCB1_INTR_M	0x40080F00
SCB1_INTR_M_SET	0x40080F04
SCB1_INTR_M_MASK	0x40080F08
SCB1_INTR_M_MASKED	0x40080F0C
SCB1_INTR_S	0x40080F40
SCB1_INTR_S_SET	0x40080F44
SCB1_INTR_S_MASK	0x40080F48
SCB1_INTR_S_MASKED	0x40080F4C
SCB1_INTR_TX	0x40080F80
SCB1_INTR_TX_SET	0x40080F84
SCB1_INTR_TX_MASK	0x40080F88

Register Name	Address
SCB1_INTR_TX_MASKED	0x40080F8C
SCB1_INTR_RX	0x40080FC0
SCB1_INTR_RX_SET	0x40080FC4
SCB1_INTR_RX_MASK	0x40080FC8
SCB1_INTR_RX_MASKED	0x40080FCC
SCB2_CTRL	0x40090000
SCB2_STATUS	0x40090004
SCB2_SPI_CTRL	0x40090020
SCB2_SPI_STATUS	0x40090024
SCB2_UART_CTRL	0x40090040
SCB2_UART_TX_CTRL	0x40090044
SCB2_UART_RX_CTRL	0x40090048
SCB2_UART_RX_STATUS	0x4009004C
SCB2_UART_FLOW_CTRL	0x40090050
SCB2_I2C_CTRL	0x40090060
SCB2_I2C_STATUS	0x40090064
SCB2_I2C_M_CMD	0x40090068
SCB2_I2C_S_CMD	0x4009006C
SCB2_I2C_CFG	0x40090070
SCB2_TX_CTRL	0x40090200
SCB2_TX_FIFO_CTRL	0x40090204
SCB2_TX_FIFO_STATUS	0x40090208
SCB2_TX_FIFO_WR	0x40090240
SCB2_RX_CTRL	0x40090300
SCB2_RX_FIFO_CTRL	0x40090304
SCB2_RX_FIFO_STATUS	0x40090308
SCB2_RX_MATCH	0x40090310
SCB2_RX_FIFO_RD	0x40090340
SCB2_RX_FIFO_RD_SILENT	0x40090344
SCB2_EZ_DATA0	0x40090400
SCB2_EZ_DATA1	0x40090404
SCB2_EZ_DATA2	0x40090408
SCB2_EZ_DATA3	0x4009040C
SCB2_EZ_DATA4	0x40090410
SCB2_EZ_DATA5	0x40090414
SCB2_EZ_DATA6	0x40090418
SCB2_EZ_DATA7	0x4009041C
SCB2_EZ_DATA8	0x40090420
SCB2_EZ_DATA9	0x40090424
SCB2_EZ_DATA10	0x40090428
SCB2_EZ_DATA11	0x4009042C
SCB2_EZ_DATA12	0x40090430

Register Name	Address
SCB2_EZ_DATA13	0x40090434
SCB2_EZ_DATA14	0x40090438
SCB2_EZ_DATA15	0x4009043C
SCB2_EZ_DATA16	0x40090440
SCB2_EZ_DATA17	0x40090444
SCB2_EZ_DATA18	0x40090448
SCB2_EZ_DATA19	0x4009044C
SCB2_EZ_DATA20	0x40090450
SCB2_EZ_DATA21	0x40090454
SCB2_EZ_DATA22	0x40090458
SCB2_EZ_DATA23	0x4009045C
SCB2_EZ_DATA24	0x40090460
SCB2_EZ_DATA25	0x40090464
SCB2_EZ_DATA26	0x40090468
SCB2_EZ_DATA27	0x4009046C
SCB2_EZ_DATA28	0x40090470
SCB2_EZ_DATA29	0x40090474
SCB2_EZ_DATA30	0x40090478
SCB2_EZ_DATA31	0x4009047C
SCB2_INTR_CAUSE	0x40090E00
SCB2_INTR_I2C_EC	0x40090E80
SCB2_INTR_I2C_EC_MASK	0x40090E88
SCB2_INTR_I2C_EC_MASKED	0x40090E8C
SCB2_INTR_SPI_EC	0x40090EC0
SCB2_INTR_SPI_EC_MASK	0x40090EC8
SCB2_INTR_SPI_EC_MASKED	0x40090ECC
SCB2_INTR_M	0x40090F00
SCB2_INTR_M_SET	0x40090F04
SCB2_INTR_M_MASK	0x40090F08
SCB2_INTR_M_MASKED	0x40090F0C
SCB2_INTR_S	0x40090F40
SCB2_INTR_S_SET	0x40090F44
SCB2_INTR_S_MASK	0x40090F48
SCB2_INTR_S_MASKED	0x40090F4C
SCB2_INTR_TX	0x40090F80
SCB2_INTR_TX_SET	0x40090F84
SCB2_INTR_TX_MASK	0x40090F88
SCB2_INTR_TX_MASKED	0x40090F8C
SCB2_INTR_RX	0x40090FC0
SCB2_INTR_RX_SET	0x40090FC4
SCB2_INTR_RX_MASK	0x40090FC8
SCB2_INTR_RX_MASKED	0x40090FCC

21.1.1 SCB0_CTRL

Generic control register.

Address: 0x40070000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

21.1.1 SCB0_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is 0 and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

21.1.1 SCB0_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0
3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

21.1.2 SCB0_STATUS (continued)

21.1.2 SCB0_STATUS

Generic status register.

Address: 0x40070004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

21.1.3 SCB0_SPI_CTRL

SPI control register.

Address: 0x40070020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0
4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0

21.1.3 SCB0_SPI_CTRL (continued)

3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is 0: SCLK is 0 when not transmitting data. - CPOL is 1: SCLK is 1 when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is 0, CPHA is 0: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is 0, CPHA is 1: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is 1, CPHA is 0: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is 1, CPHA is 1: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data+G65 frames are send out with slave deselection. Default Value: 0

21.1.4 SCB0_SPI_STATUS (continued)

21.1.4 SCB0_SPI_STATUS

SPI status register.

Address: 0x40070024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined

0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

21.1.5 SCB0_UART_CTRL

UART control register.

Address: 0x40070040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

21.1.6 SCB0_UART_TX_CTRL

UART transmitter control register.

Address: 0x40070044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

21.1.7 SCB0_UART_RX_CTRL

UART receiver control register.

Address: 0x40070048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

21.1.7 SCB0_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

21.1.7 SCB0_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

21.1.8 SCB0_UART_RX_STATUS

UART receiver status register.

Address: 0x4007004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

21.1.9 SCB0_UART_FLOW_CTRL

UART flow control register

Address: 0x40070050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes are indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

21.1.9 SCB0_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

21.1.10 SCB0_I2C_CTRL

I2C control register.

Address: 0x40070060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

21.1.10 SCB0_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

21.1.10 SCB0_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

21.1.11 SCB0_I2C_STATUS

I2C status register.

Address: 0x40070064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

21.1.11 SCB0_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

21.1.12 SCB0_I2C_M_CMD

I2C master command register.

Address: 0x40070068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. This command has a higher priority than I2C_M_CMD.M_START: in situations where both a STOP and a REPEATED START could be transmitted, M_STOP takes precedence over M_START. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0

21.1.12 SCB0_I2C_M_CMD (continued)

0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

21.1.13 SCB0_I2C_S_CMD

I2C slave command register.

Address: 0x4007006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

21.1.14 SCB0_I2C_CFG

I2C configuration register.

Address: 0x40070070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

21.1.14 SCB0_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

21.1.15 SCB0_TX_CTRL

Transmitter control register.

Address: 0x40070200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

21.1.16 SCB0_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40070204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event is generated. Default Value: 0

21.1.17 SCB0_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40070208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

21.1.18 SCB0_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40070240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

21.1.19 SCB0_RX_CTRL

Receiver control register.

Address: 0x40070300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

21.1.20 SCB0_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40070304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event is generated. Default Value: 0

21.1.21 SCB0_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40070308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

21.1.22 SCB0_RX_MATCH

Slave address and mask register.

Address: 0x40070310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

21.1.23 SCB0_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40070340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

21.1.24 SCB0_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40070344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

21.1.25 SCB0_EZ_DATA0

Memory buffer registers.

Address: 0x40070400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.26 SCB0_EZ_DATA1

Memory buffer registers.

Address: 0x40070404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.27 SCB0_EZ_DATA2

Memory buffer registers.

Address: 0x40070408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.28 SCB0_EZ_DATA3

Memory buffer registers.

Address: 0x4007040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.29 SCB0_EZ_DATA4

Memory buffer registers.

Address: 0x40070410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.30 SCB0_EZ_DATA5

Memory buffer registers.

Address: 0x40070414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.31 SCB0_EZ_DATA6

Memory buffer registers.

Address: 0x40070418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.32 SCB0_EZ_DATA7

Memory buffer registers.

Address: 0x4007041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.33 SCB0_EZ_DATA8

Memory buffer registers.

Address: 0x40070420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.34 SCB0_EZ_DATA9

Memory buffer registers.

Address: 0x40070424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.35 SCB0_EZ_DATA10

Memory buffer registers.

Address: 0x40070428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.36 SCB0_EZ_DATA11

Memory buffer registers.

Address: 0x4007042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.37 SCB0_EZ_DATA12

Memory buffer registers.

Address: 0x40070430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.38 SCB0_EZ_DATA13

Memory buffer registers.

Address: 0x40070434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.39 SCB0_EZ_DATA14

Memory buffer registers.

Address: 0x40070438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.40 SCB0_EZ_DATA15

Memory buffer registers.

Address: 0x4007043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.41 SCB0_EZ_DATA16

Memory buffer registers.

Address: 0x40070440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.42 SCB0_EZ_DATA17

Memory buffer registers.

Address: 0x40070444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.43 SCB0_EZ_DATA18

Memory buffer registers.

Address: 0x40070448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.44 SCB0_EZ_DATA19

Memory buffer registers.

Address: 0x4007044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.45 SCB0_EZ_DATA20

Memory buffer registers.

Address: 0x40070450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.46 SCB0_EZ_DATA21

Memory buffer registers.

Address: 0x40070454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.47 SCB0_EZ_DATA22

Memory buffer registers.

Address: 0x40070458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.48 SCB0_EZ_DATA23

Memory buffer registers.

Address: 0x4007045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.49 SCB0_EZ_DATA24

Memory buffer registers.

Address: 0x40070460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.50 SCB0_EZ_DATA25

Memory buffer registers.

Address: 0x40070464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.51 SCB0_EZ_DATA26

Memory buffer registers.

Address: 0x40070468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.52 SCB0_EZ_DATA27

Memory buffer registers.

Address: 0x4007046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.53 SCB0_EZ_DATA28

Memory buffer registers.

Address: 0x40070470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.54 SCB0_EZ_DATA29

Memory buffer registers.

Address: 0x40070474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.55 SCB0_EZ_DATA30

Memory buffer registers.

Address: 0x40070478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.56 SCB0_EZ_DATA31

Memory buffer registers.

Address: 0x4007047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.57 SCB0_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40070E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

21.1.58 SCB0_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40070E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

21.1.58 SCB0_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

21.1.59 SCB0_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40070E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.60 SCB0_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40070E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

21.1.61 SCB0_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40070EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

21.1.61 SCB0_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

21.1.62 SCB0_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40070EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.63 SCB0_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40070ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

21.1.64 SCB0_INTR_M

Master interrupt request register.

Address: 0x40070F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO is empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0

21.1.64 SCB0_INTR_M (continued)

0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

21.1.65 SCB0_INTR_M_SET

Master interrupt set request register

Address: 0x40070F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.66 SCB0_INTR_M_MASK

Master interrupt mask register.

Address: 0x40070F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.67 SCB0_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40070F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

21.1.68 SCB0_INTR_S

Slave interrupt request register.

Address: 0x40070F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

21.1.68 SCB0_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

21.1.69 SCB0_INTR_S_SET

Slave interrupt set request register.

Address: 0x40070F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.69 SCB0_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.70 SCB0_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40070F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.70 SCB0_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.71 SCB0_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40070F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

21.1.71 SCB0_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

21.1.72 SCB0_INTR_TX

Transmitter interrupt request register.

Address: 0x40070F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

21.1.72 SCB0_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

21.1.73 SCB0_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40070F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.73 SCB0_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.74 SCB0_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40070F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.74 SCB0_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.75 SCB0_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40070F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

21.1.75 SCB0_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

21.1.76 SCB0_INTR_RX

Receiver interrupt request register.

Address: 0x40070FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is ecpected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

21.1.76 SCB0_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODET: BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

21.1.77 SCB0_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40070FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

21.1.77 SCB0_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.78 SCB0_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40070FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.78 SCB0_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.79 SCB0_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40070FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

21.1.79 SCB0_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

21.1.80 SCB1_CTRL

Generic control register.

Address: 0x40080000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

21.1.80 SCB1_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is 0 and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0
8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

21.1.80 SCB1_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode.

21.1.80 SCB1_CTRL (continued)

In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency):
- 0: 16 times oversampling.
    IP clock frequency of 16*115.2 KHz for 115.2 Kbps.
    IP clock frequency of 16*57.6 KHz for 57.6 Kbps.
    IP clock frequency of 16*38.4 KHz for 38.4 Kbps.
    IP clock frequency of 16*19.2 KHz for 19.2 Kbps.
    IP clock frequency of 16*9.6 KHz for 9.6 Kbps.
    IP clock frequency of 16*2.4 KHz for 2.4 Kbps.
    IP clock frequency of 16*1.2 KHz for 1.2 Kbps.
- all other values are not used in normal mode.

Low power mode, OVS field values (with the required IP clock frequency):
- 0: 16 times oversampling.
    IP clock frequency of 16*115.2 KHz for 115.2 Kbps.
- 1: 32 times oversampling.
    IP clock frequency of 32*57.6 KHz for 57.6 Kbps.
- 2: 48 times oversampling.
    IP clock frequency of 48*38.4 KHz for 38.4 Kbps.
- 3: 96 times oversampling.
    IP clock frequency of 96*19.2 KHz for 19.2 Kbps.
- 4: 192 times oversampling.
    IP clock frequency of 192*9.6 KHz for 9.6 Kbps.
- 5: 768 times oversampling.
    IP clock frequency of 768*2.4 KHz for 2.4 Kbps.
- 6: 1536 times oversampling.
    IP clock frequency of 1536*1.2 KHz for 1.2 Kbps.
- all other values are not used in low power mode.

Default Value: 15

21.1.81 SCB1_STATUS

Generic status register.

Address: 0x40080004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

21.1.82 SCB1_SPI_CTRL

SPI control register.

Address: 0x40080020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

21.1.82 SCB1_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

21.1.82 SCB1_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is 0: SCLK is 0 when not transmitting data. - CPOL is 1: SCLK is 1 when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is 0, CPHA is 0: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is 0, CPHA is 1: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is 1, CPHA is 0: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is 1, CPHA is 1: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data+G65 frames are send out with slave deselection. Default Value: 0

21.1.83 SCB1_SPI_STATUS

SPI status register.

Address: 0x40080024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

21.1.84 SCB1_UART_CTRL

UART control register.

Address: 0x40080040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

21.1.85 SCB1_UART_TX_CTRL

UART transmitter control register.

Address: 0x40080044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

21.1.86 SCB1_UART_RX_CTRL

UART receiver control register.

Address: 0x40080048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

21.1.86 SCB1_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

21.1.86 SCB1_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

21.1.87 SCB1_UART_RX_STATUS

UART receiver status register.

Address: 0x4008004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

21.1.88 SCB1_UART_FLOW_CTRL

UART flow control register

Address: 0x40080050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes are indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

21.1.88 SCB1_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

21.1.89 SCB1_I2C_CTRL

I2C control register.

Address: 0x40080060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

21.1.89 SCB1_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

21.1.89 SCB1_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

21.1.90 SCB1_I2C_STATUS

I2C status register.

Address: 0x40080064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

21.1.90 SCB1_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

21.1.91 SCB1_I2C_M_CMD

I2C master command register.

Address: 0x40080068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. This command has a higher priority than I2C_M_CMD.M_START: in situations where both a STOP and a REPEATED START could be transmitted, M_STOP takes precedence over M_START. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0

21.1.91 SCB1_I2C_M_CMD (continued)

0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

21.1.92 SCB1_I2C_S_CMD

I2C slave command register.

Address: 0x4008006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

21.1.93 SCB1_I2C_CFG

I2C configuration register.

Address: 0x40080070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

21.1.93 SCB1_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

21.1.94 SCB1_TX_CTRL

Transmitter control register.

Address: 0x40080200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

21.1.95 SCB1_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40080204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event is generated. Default Value: 0

21.1.96 SCB1_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40080208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

21.1.97 SCB1_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40080240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

21.1.98 SCB1_RX_CTRL

Receiver control register.

Address: 0x40080300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

21.1.99 SCB1_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40080304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event is generated. Default Value: 0

21.1.100 SCB1_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40080308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

21.1.101 SCB1_RX_MATCH

Slave address and mask register.

Address: 0x40080310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

21.1.102 SCB1_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40080340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

21.1.103 SCB1_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40080344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

21.1.104 SCB1_EZ_DATA0

Memory buffer registers.

Address: 0x40080400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.105 SCB1_EZ_DATA1

Memory buffer registers.

Address: 0x40080404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.106 SCB1_EZ_DATA2

Memory buffer registers.

Address: 0x40080408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.107 SCB1_EZ_DATA3

Memory buffer registers.

Address: 0x4008040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.108 SCB1_EZ_DATA4

Memory buffer registers.

Address: 0x40080410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.109 SCB1_EZ_DATA5

Memory buffer registers.

Address: 0x40080414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.110 SCB1_EZ_DATA6

Memory buffer registers.

Address: 0x40080418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.111 SCB1_EZ_DATA7

Memory buffer registers.

Address: 0x4008041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.112 SCB1_EZ_DATA8

Memory buffer registers.

Address: 0x40080420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.113 SCB1_EZ_DATA9

Memory buffer registers.

Address: 0x40080424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.114 SCB1_EZ_DATA10

Memory buffer registers.

Address: 0x40080428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.115 SCB1_EZ_DATA11

Memory buffer registers.

Address: 0x4008042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.116 SCB1_EZ_DATA12

Memory buffer registers.

Address: 0x40080430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.117 SCB1_EZ_DATA13

Memory buffer registers.

Address: 0x40080434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.118 SCB1_EZ_DATA14

Memory buffer registers.

Address: 0x40080438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.119 SCB1_EZ_DATA15

Memory buffer registers.

Address: 0x4008043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.120 SCB1_EZ_DATA16

Memory buffer registers.

Address: 0x40080440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.121 SCB1_EZ_DATA17

Memory buffer registers.

Address: 0x40080444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.122 SCB1_EZ_DATA18

Memory buffer registers.

Address: 0x40080448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.123 SCB1_EZ_DATA19

Memory buffer registers.

Address: 0x4008044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.124 SCB1_EZ_DATA20

Memory buffer registers.

Address: 0x40080450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.125 SCB1_EZ_DATA21

Memory buffer registers.

Address: 0x40080454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.126 SCB1_EZ_DATA22

Memory buffer registers.

Address: 0x40080458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.127 SCB1_EZ_DATA23

Memory buffer registers.

Address: 0x4008045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.128 SCB1_EZ_DATA24

Memory buffer registers.

Address: 0x40080460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.129 SCB1_EZ_DATA25

Memory buffer registers.

Address: 0x40080464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.130 SCB1_EZ_DATA26

Memory buffer registers.

Address: 0x40080468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.131 SCB1_EZ_DATA27

Memory buffer registers.

Address: 0x4008046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.132 SCB1_EZ_DATA28

Memory buffer registers.

Address: 0x40080470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.133 SCB1_EZ_DATA29

Memory buffer registers.

Address: 0x40080474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.134 SCB1_EZ_DATA30

Memory buffer registers.

Address: 0x40080478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.135 SCB1_EZ_DATA31

Memory buffer registers.

Address: 0x4008047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.136 SCB1_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40080E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

21.1.137 SCB1_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40080E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

21.1.137 SCB1_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

21.1.138 SCB1_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40080E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.139 SCB1_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40080E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

21.1.140 SCB1_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40080EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

21.1.140 SCB1_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

21.1.141 SCB1_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40080EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.142 SCB1_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40080ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

21.1.143 SCB1_INTR_M

Master interrupt request register.

Address: 0x40080F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO is empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0

21.1.143 SCB1_INTR_M (continued)

0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

21.1.144 SCB1_INTR_M_SET

Master interrupt set request register

Address: 0x40080F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.145 SCB1_INTR_M_MASK

Master interrupt mask register.

Address: 0x40080F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.146 SCB1_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40080F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

21.1.147 SCB1_INTR_S

Slave interrupt request register.

Address: 0x40080F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

21.1.147 SCB1_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

21.1.148 SCB1_INTR_S_SET

Slave interrupt set request register.

Address: 0x40080F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.148 SCB1_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.149 SCB1_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40080F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.149 SCB1_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.150 SCB1_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40080F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

21.1.150 SCB1_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

21.1.151 SCB1_INTR_TX

Transmitter interrupt request register.

Address: 0x40080F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

21.1.151 SCB1_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

21.1.152 SCB1_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40080F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.152 SCB1_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.153 SCB1_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40080F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.153 SCB1_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.154 SCB1_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40080F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

21.1.154 SCB1_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

21.1.155 SCB1_INTR_RX

Receiver interrupt request register.

Address: 0x40080FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is ecpected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

21.1.155 SCB1_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODET: BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

21.1.156 SCB1_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40080FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

21.1.156 SCB1_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.157 SCB1_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40080FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.157 SCB1_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.158 SCB1_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40080FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

21.1.158 SCB1_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

21.1.159 SCB2_CTRL

Generic control register.

Address: 0x40090000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

21.1.159 SCB2_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is 0 and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

21.1.159 SCB2_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0
3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

21.1.160 SCB2_STATUS (continued)

21.1.160 SCB2_STATUS

Generic status register.

Address: 0x40090004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

21.1.161 SCB2_SPI_CTRL

SPI control register.

Address: 0x40090020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0
4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0

21.1.161 SCB2_SPI_CTRL (continued)

3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is 0: SCLK is 0 when not transmitting data. - CPOL is 1: SCLK is 1 when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is 0, CPHA is 0: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is 0, CPHA is 1: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is 1, CPHA is 0: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is 1, CPHA is 1: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data+G65 frames are send out with slave deselection. Default Value: 0

21.1.162 SCB2_SPI_STATUS (continued)

21.1.162 SCB2_SPI_STATUS

SPI status register.

Address: 0x40090024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined

0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

21.1.163 SCB2_UART_CTRL

UART control register.

Address: 0x40090040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

21.1.164 SCB2_UART_TX_CTRL

UART transmitter control register.

Address: 0x40090044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

21.1.165 SCB2_UART_RX_CTRL

UART receiver control register.

Address: 0x40090048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

21.1.165 SCB2_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

21.1.165 SCB2_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

21.1.166 SCB2_UART_RX_STATUS

UART receiver status register.

Address: 0x4009004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

21.1.167 SCB2_UART_FLOW_CTRL

UART flow control register

Address: 0x40090050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes are indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

21.1.167 SCB2_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

21.1.168 SCB2_I2C_CTRL

I2C control register.

Address: 0x40090060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

21.1.168 SCB2_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

21.1.168 SCB2_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

21.1.169 SCB2_I2C_STATUS

I2C status register.

Address: 0x40090064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

21.1.169 SCB2_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

21.1.170 SCB2_I2C_M_CMD

I2C master command register.

Address: 0x40090068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. This command has a higher priority than I2C_M_CMD.M_START: in situations where both a STOP and a REPEATED START could be transmitted, M_STOP takes precedence over M_START. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0

21.1.170 SCB2_I2C_M_CMD (continued)

0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

21.1.171 SCB2_I2C_S_CMD

I2C slave command register.

Address: 0x4009006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

21.1.172 SCB2_I2C_CFG

I2C configuration register.

Address: 0x40090070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

21.1.172 SCB2_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

21.1.173 SCB2_TX_CTRL

Transmitter control register.

Address: 0x40090200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

21.1.174 SCB2_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40090204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event is generated. Default Value: 0

21.1.175 SCB2_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40090208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

21.1.176 SCB2_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40090240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

21.1.177 SCB2_RX_CTRL

Receiver control register.

Address: 0x40090300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

21.1.178 SCB2_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40090304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event is generated. Default Value: 0

21.1.179 SCB2_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40090308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

21.1.180 SCB2_RX_MATCH

Slave address and mask register.

Address: 0x40090310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

21.1.181 SCB2_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40090340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

21.1.182 SCB2_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40090344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

21.1.183 SCB2_EZ_DATA0

Memory buffer registers.

Address: 0x40090400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.184 SCB2_EZ_DATA1

Memory buffer registers.

Address: 0x40090404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.185 SCB2_EZ_DATA2

Memory buffer registers.

Address: 0x40090408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.186 SCB2_EZ_DATA3

Memory buffer registers.

Address: 0x4009040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.187 SCB2_EZ_DATA4

Memory buffer registers.

Address: 0x40090410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.188 SCB2_EZ_DATA5

Memory buffer registers.

Address: 0x40090414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.189 SCB2_EZ_DATA6

Memory buffer registers.

Address: 0x40090418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.190 SCB2_EZ_DATA7

Memory buffer registers.

Address: 0x4009041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.191 SCB2_EZ_DATA8

Memory buffer registers.

Address: 0x40090420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.192 SCB2_EZ_DATA9

Memory buffer registers.

Address: 0x40090424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.193 SCB2_EZ_DATA10

Memory buffer registers.

Address: 0x40090428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.194 SCB2_EZ_DATA11

Memory buffer registers.

Address: 0x4009042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.195 SCB2_EZ_DATA12

Memory buffer registers.

Address: 0x40090430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.196 SCB2_EZ_DATA13

Memory buffer registers.

Address: 0x40090434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.197 SCB2_EZ_DATA14

Memory buffer registers.

Address: 0x40090438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.198 SCB2_EZ_DATA15

Memory buffer registers.

Address: 0x4009043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.199 SCB2_EZ_DATA16

Memory buffer registers.

Address: 0x40090440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.200 SCB2_EZ_DATA17

Memory buffer registers.

Address: 0x40090444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.201 SCB2_EZ_DATA18

Memory buffer registers.

Address: 0x40090448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.202 SCB2_EZ_DATA19

Memory buffer registers.

Address: 0x4009044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.203 SCB2_EZ_DATA20

Memory buffer registers.

Address: 0x40090450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.204 SCB2_EZ_DATA21

Memory buffer registers.

Address: 0x40090454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.205 SCB2_EZ_DATA22

Memory buffer registers.

Address: 0x40090458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.206 SCB2_EZ_DATA23

Memory buffer registers.

Address: 0x4009045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.207 SCB2_EZ_DATA24

Memory buffer registers.

Address: 0x40090460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.208 SCB2_EZ_DATA25

Memory buffer registers.

Address: 0x40090464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.209 SCB2_EZ_DATA26

Memory buffer registers.

Address: 0x40090468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.210 SCB2_EZ_DATA27

Memory buffer registers.

Address: 0x4009046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.211 SCB2_EZ_DATA28

Memory buffer registers.

Address: 0x40090470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.212 SCB2_EZ_DATA29

Memory buffer registers.

Address: 0x40090474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.213 SCB2_EZ_DATA30

Memory buffer registers.

Address: 0x40090478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.214 SCB2_EZ_DATA31

Memory buffer registers.

Address: 0x4009047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

21.1.215 SCB2_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40090E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

21.1.216 SCB2_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40090E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

21.1.216 SCB2_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

21.1.217 SCB2_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40090E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.218 SCB2_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40090E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

21.1.219 SCB2_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40090EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

21.1.219 SCB2_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

21.1.220 SCB2_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40090EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.221 SCB2_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40090ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

21.1.222 SCB2_INTR_M

Master interrupt request register.

Address: 0x40090F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO is empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0

21.1.222 SCB2_INTR_M (continued)

0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

21.1.223 SCB2_INTR_M_SET

Master interrupt set request register

Address: 0x40090F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.224 SCB2_INTR_M_MASK

Master interrupt mask register.

Address: 0x40090F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.225 SCB2_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40090F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

21.1.226 SCB2_INTR_S

Slave interrupt request register.

Address: 0x40090F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

21.1.226 SCB2_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

21.1.227 SCB2_INTR_S_SET

Slave interrupt set request register.

Address: 0x40090F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.227 SCB2_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.228 SCB2_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40090F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.228 SCB2_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.229 SCB2_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40090F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

21.1.229 SCB2_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

21.1.230 SCB2_INTR_TX

Transmitter interrupt request register.

Address: 0x40090F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

21.1.230 SCB2_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

21.1.231 SCB2_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40090F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.231 SCB2_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.232 SCB2_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40090F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.232 SCB2_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.233 SCB2_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40090F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

21.1.233 SCB2_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

21.1.234 SCB2_INTR_RX

Receiver interrupt request register.

Address: 0x40090FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is ecpected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

21.1.234 SCB2_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODET: BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

21.1.235 SCB2_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40090FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

21.1.235 SCB2_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

21.1.236 SCB2_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40090FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.236 SCB2_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

21.1.237 SCB2_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40090FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

21.1.237 SCB2_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

22 Supervisory Flash (SFLASH) Registers

This section discusses the SFLASH registers. It lists all the registers in mapping tables, in address order.

22.1 Register Details

Register Name	Address
SFLASH_PROT_ROW0	0x0FFFF000
SFLASH_PROT_ROW1	0x0FFFF001
SFLASH_PROT_ROW2	0x0FFFF002
SFLASH_PROT_ROW3	0x0FFFF003
SFLASH_PROT_ROW4	0x0FFFF004
SFLASH_PROT_ROW5	0x0FFFF005
SFLASH_PROT_ROW6	0x0FFFF006
SFLASH_PROT_ROW7	0x0FFFF007
SFLASH_PROT_ROW8	0x0FFFF008
SFLASH_PROT_ROW9	0x0FFFF009
SFLASH_PROT_ROW10	0x0FFFF00A
SFLASH_PROT_ROW11	0x0FFFF00B
SFLASH_PROT_ROW12	0x0FFFF00C
SFLASH_PROT_ROW13	0x0FFFF00D
SFLASH_PROT_ROW14	0x0FFFF00E
SFLASH_PROT_ROW15	0x0FFFF00F
SFLASH_PROT_ROW16	0x0FFFF010
SFLASH_PROT_ROW17	0x0FFFF011
SFLASH_PROT_ROW18	0x0FFFF012
SFLASH_PROT_ROW19	0x0FFFF013
SFLASH_PROT_ROW20	0x0FFFF014
SFLASH_PROT_ROW21	0x0FFFF015
SFLASH_PROT_ROW22	0x0FFFF016
SFLASH_PROT_ROW23	0x0FFFF017
SFLASH_PROT_ROW24	0x0FFFF018
SFLASH_PROT_ROW25	0x0FFFF019
SFLASH_PROT_ROW26	0x0FFFF01A

Register Name	Address
SFLASH_PROT_ROW27	0x0FFFF01B
SFLASH_PROT_ROW28	0x0FFFF01C
SFLASH_PROT_ROW29	0x0FFFF01D
SFLASH_PROT_ROW30	0x0FFFF01E
SFLASH_PROT_ROW31	0x0FFFF01F
SFLASH_PROT_ROW32	0x0FFFF020
SFLASH_PROT_ROW33	0x0FFFF021
SFLASH_PROT_ROW34	0x0FFFF022
SFLASH_PROT_ROW35	0x0FFFF023
SFLASH_PROT_ROW36	0x0FFFF024
SFLASH_PROT_ROW37	0x0FFFF025
SFLASH_PROT_ROW38	0x0FFFF026
SFLASH_PROT_ROW39	0x0FFFF027
SFLASH_PROT_ROW40	0x0FFFF028
SFLASH_PROT_ROW41	0x0FFFF029
SFLASH_PROT_ROW42	0x0FFFF02A
SFLASH_PROT_ROW43	0x0FFFF02B
SFLASH_PROT_ROW44	0x0FFFF02C
SFLASH_PROT_ROW45	0x0FFFF02D
SFLASH_PROT_ROW46	0x0FFFF02E
SFLASH_PROT_ROW47	0x0FFFF02F
SFLASH_PROT_ROW48	0x0FFFF030
SFLASH_PROT_ROW49	0x0FFFF031
SFLASH_PROT_ROW50	0x0FFFF032
SFLASH_PROT_ROW51	0x0FFFF033
SFLASH_PROT_ROW52	0x0FFFF034
SFLASH_PROT_ROW53	0x0FFFF035
SFLASH_PROT_ROW54	0x0FFFF036
SFLASH_PROT_ROW55	0x0FFFF037
SFLASH_PROT_ROW56	0x0FFFF038
SFLASH_PROT_ROW57	0x0FFFF039
SFLASH_PROT_ROW58	0x0FFFF03A
SFLASH_PROT_ROW59	0x0FFFF03B
SFLASH_PROT_ROW60	0x0FFFF03C
SFLASH_PROT_ROW61	0x0FFFF03D
SFLASH_PROT_ROW62	0x0FFFF03E
SFLASH_PROT_ROW63	0x0FFFF03F
SFLASH_PROT_PROTECTION	0x0FFFF07F
SFLASH_AV_PAIRS_8B0	0x0FFFF080
SFLASH_AV_PAIRS_8B1	0x0FFFF081
SFLASH_AV_PAIRS_8B2	0x0FFFF082
SFLASH_AV_PAIRS_8B3	0x0FFFF083

Register Name	Address
SFLASH_AV_PAIRS_8B4	0x0FFFF084
SFLASH_AV_PAIRS_8B5	0x0FFFF085
SFLASH_AV_PAIRS_8B6	0x0FFFF086
SFLASH_AV_PAIRS_8B7	0x0FFFF087
SFLASH_AV_PAIRS_8B8	0x0FFFF088
SFLASH_AV_PAIRS_8B9	0x0FFFF089
SFLASH_AV_PAIRS_8B10	0x0FFFF08A
SFLASH_AV_PAIRS_8B11	0x0FFFF08B
SFLASH_AV_PAIRS_8B12	0x0FFFF08C
SFLASH_AV_PAIRS_8B13	0x0FFFF08D
SFLASH_AV_PAIRS_8B14	0x0FFFF08E
SFLASH_AV_PAIRS_8B15	0x0FFFF08F
SFLASH_AV_PAIRS_8B16	0x0FFFF090
SFLASH_AV_PAIRS_8B17	0x0FFFF091
SFLASH_AV_PAIRS_8B18	0x0FFFF092
SFLASH_AV_PAIRS_8B19	0x0FFFF093
SFLASH_AV_PAIRS_8B20	0x0FFFF094
SFLASH_AV_PAIRS_8B21	0x0FFFF095
SFLASH_AV_PAIRS_8B22	0x0FFFF096
SFLASH_AV_PAIRS_8B23	0x0FFFF097
SFLASH_AV_PAIRS_8B24	0x0FFFF098
SFLASH_AV_PAIRS_8B25	0x0FFFF099
SFLASH_AV_PAIRS_8B26	0x0FFFF09A
SFLASH_AV_PAIRS_8B27	0x0FFFF09B
SFLASH_AV_PAIRS_8B28	0x0FFFF09C
SFLASH_AV_PAIRS_8B29	0x0FFFF09D
SFLASH_AV_PAIRS_8B30	0x0FFFF09E
SFLASH_AV_PAIRS_8B31	0x0FFFF09F
SFLASH_AV_PAIRS_8B32	0x0FFFF0A0
SFLASH_AV_PAIRS_8B33	0x0FFFF0A1
SFLASH_AV_PAIRS_8B34	0x0FFFF0A2
SFLASH_AV_PAIRS_8B35	0x0FFFF0A3
SFLASH_AV_PAIRS_8B36	0x0FFFF0A4
SFLASH_AV_PAIRS_8B37	0x0FFFF0A5
SFLASH_AV_PAIRS_8B38	0x0FFFF0A6
SFLASH_AV_PAIRS_8B39	0x0FFFF0A7
SFLASH_AV_PAIRS_8B40	0x0FFFF0A8
SFLASH_AV_PAIRS_8B41	0x0FFFF0A9
SFLASH_AV_PAIRS_8B42	0x0FFFF0AA
SFLASH_AV_PAIRS_8B43	0x0FFFF0AB
SFLASH_AV_PAIRS_8B44	0x0FFFF0AC
SFLASH_AV_PAIRS_8B45	0x0FFFF0AD

Register Name	Address
SFLASH_AV_PAIRS_8B46	0x0FFFF0AE
SFLASH_AV_PAIRS_8B47	0x0FFFF0AF
SFLASH_AV_PAIRS_8B48	0x0FFFF0B0
SFLASH_AV_PAIRS_8B49	0x0FFFF0B1
SFLASH_AV_PAIRS_8B50	0x0FFFF0B2
SFLASH_AV_PAIRS_8B51	0x0FFFF0B3
SFLASH_AV_PAIRS_8B52	0x0FFFF0B4
SFLASH_AV_PAIRS_8B53	0x0FFFF0B5
SFLASH_AV_PAIRS_8B54	0x0FFFF0B6
SFLASH_AV_PAIRS_8B55	0x0FFFF0B7
SFLASH_AV_PAIRS_8B56	0x0FFFF0B8
SFLASH_AV_PAIRS_8B57	0x0FFFF0B9
SFLASH_AV_PAIRS_8B58	0x0FFFF0BA
SFLASH_AV_PAIRS_8B59	0x0FFFF0BB
SFLASH_AV_PAIRS_8B60	0x0FFFF0BC
SFLASH_AV_PAIRS_8B61	0x0FFFF0BD
SFLASH_AV_PAIRS_8B62	0x0FFFF0BE
SFLASH_AV_PAIRS_8B63	0x0FFFF0BF
SFLASH_AV_PAIRS_8B64	0x0FFFF0C0
SFLASH_AV_PAIRS_8B65	0x0FFFF0C1
SFLASH_AV_PAIRS_8B66	0x0FFFF0C2
SFLASH_AV_PAIRS_8B67	0x0FFFF0C3
SFLASH_AV_PAIRS_8B68	0x0FFFF0C4
SFLASH_AV_PAIRS_8B69	0x0FFFF0C5
SFLASH_AV_PAIRS_8B70	0x0FFFF0C6
SFLASH_AV_PAIRS_8B71	0x0FFFF0C7
SFLASH_AV_PAIRS_8B72	0x0FFFF0C8
SFLASH_AV_PAIRS_8B73	0x0FFFF0C9
SFLASH_AV_PAIRS_8B74	0x0FFFF0CA
SFLASH_AV_PAIRS_8B75	0x0FFFF0CB
SFLASH_AV_PAIRS_8B76	0x0FFFF0CC
SFLASH_AV_PAIRS_8B77	0x0FFFF0CD
SFLASH_AV_PAIRS_8B78	0x0FFFF0CE
SFLASH_AV_PAIRS_8B79	0x0FFFF0CF
SFLASH_AV_PAIRS_8B80	0x0FFFF0D0
SFLASH_AV_PAIRS_8B81	0x0FFFF0D1
SFLASH_AV_PAIRS_8B82	0x0FFFF0D2
SFLASH_AV_PAIRS_8B83	0x0FFFF0D3
SFLASH_AV_PAIRS_8B84	0x0FFFF0D4
SFLASH_CSDV2_CSD1_ADC_TRIM1	0x0FFFF0D4
SFLASH_AV_PAIRS_8B85	0x0FFFF0D5
SFLASH_CSDV2_CSD1_ADC_TRIM2	0x0FFFF0D5

Register Name	Address
SFLASH_AV_PAIRS_8B86	0x0FFFF0D6
SFLASH_AV_PAIRS_8B87	0x0FFFF0D7
SFLASH_AV_PAIRS_8B88	0x0FFFF0D8
SFLASH_AV_PAIRS_8B89	0x0FFFF0D9
SFLASH_AV_PAIRS_8B90	0x0FFFF0DA
SFLASH_AV_PAIRS_8B91	0x0FFFF0DB
SFLASH_AV_PAIRS_8B92	0x0FFFF0DC
SFLASH_AV_PAIRS_8B93	0x0FFFF0DD
SFLASH_AV_PAIRS_8B94	0x0FFFF0DE
SFLASH_AV_PAIRS_8B95	0x0FFFF0DF
SFLASH_AV_PAIRS_8B96	0x0FFFF0E0
SFLASH_AV_PAIRS_8B97	0x0FFFF0E1
SFLASH_AV_PAIRS_8B98	0x0FFFF0E2
SFLASH_AV_PAIRS_8B99	0x0FFFF0E3
SFLASH_AV_PAIRS_8B100	0x0FFFF0E4
SFLASH_AV_PAIRS_8B101	0x0FFFF0E5
SFLASH_AV_PAIRS_8B102	0x0FFFF0E6
SFLASH_AV_PAIRS_8B103	0x0FFFF0E7
SFLASH_AV_PAIRS_8B104	0x0FFFF0E8
SFLASH_AV_PAIRS_8B105	0x0FFFF0E9
SFLASH_AV_PAIRS_8B106	0x0FFFF0EA
SFLASH_AV_PAIRS_8B107	0x0FFFF0EB
SFLASH_AV_PAIRS_8B108	0x0FFFF0EC
SFLASH_AV_PAIRS_8B109	0x0FFFF0ED
SFLASH_AV_PAIRS_8B110	0x0FFFF0EE
SFLASH_AV_PAIRS_8B111	0x0FFFF0EF
SFLASH_AV_PAIRS_8B112	0x0FFFF0F0
SFLASH_AV_PAIRS_8B113	0x0FFFF0F1
SFLASH_AV_PAIRS_8B114	0x0FFFF0F2
SFLASH_AV_PAIRS_8B115	0x0FFFF0F3
SFLASH_AV_PAIRS_8B116	0x0FFFF0F4
SFLASH_AV_PAIRS_8B117	0x0FFFF0F5
SFLASH_AV_PAIRS_8B118	0x0FFFF0F6
SFLASH_AV_PAIRS_8B119	0x0FFFF0F7
SFLASH_AV_PAIRS_8B120	0x0FFFF0F8
SFLASH_AV_PAIRS_8B121	0x0FFFF0F9
SFLASH_AV_PAIRS_8B122	0x0FFFF0FA
SFLASH_AV_PAIRS_8B123	0x0FFFF0FB
SFLASH_AV_PAIRS_8B124	0x0FFFF0FC
SFLASH_AV_PAIRS_8B125	0x0FFFF0FD
SFLASH_AV_PAIRS_8B126	0x0FFFF0FE
SFLASH_AV_PAIRS_8B127	0x0FFFF0FF

Register Name	Address
SFLASH_AV_PAIRS_32B0	0x0FFFF100
SFLASH_AV_PAIRS_32B1	0x0FFFF104
SFLASH_AV_PAIRS_32B2	0x0FFFF108
SFLASH_AV_PAIRS_32B3	0x0FFFF10C
SFLASH_AV_PAIRS_32B4	0x0FFFF110
SFLASH_AV_PAIRS_32B5	0x0FFFF114
SFLASH_AV_PAIRS_32B6	0x0FFFF118
SFLASH_AV_PAIRS_32B7	0x0FFFF11C
SFLASH_AV_PAIRS_32B8	0x0FFFF120
SFLASH_AV_PAIRS_32B9	0x0FFFF124
SFLASH_AV_PAIRS_32B10	0x0FFFF128
SFLASH_AV_PAIRS_32B11	0x0FFFF12C
SFLASH_AV_PAIRS_32B12	0x0FFFF130
SFLASH_AV_PAIRS_32B13	0x0FFFF134
SFLASH_AV_PAIRS_32B14	0x0FFFF138
SFLASH_AV_PAIRS_32B15	0x0FFFF13C
SFLASH_CPUSS_WOUNDING	0x0FFFF140
SFLASH_SILICON_ID	0x0FFFF144
SFLASH_CPUSS_PRIV_RAM	0x0FFFF148
SFLASH_CPUSS_PRIV_ROM_BROM	0x0FFFF14A
SFLASH_CPUSS_PRIV_FLASH	0x0FFFF14C
SFLASH_CPUSS_PRIV_ROM_SROM	0x0FFFF14E
SFLASH_HIB_KEY_DELAY	0x0FFFF150
SFLASH_DPSLP_KEY_DELAY	0x0FFFF152
SFLASH_SWD_CONFIG	0x0FFFF154
SFLASH_SWD_LISTEN	0x0FFFF158
SFLASH_FLASH_START	0x0FFFF15C
SFLASH_CSDV2_CSD0_ADC_TRIM1	0x0FFFF160
SFLASH_CSDV2_CSD0_ADC_TRIM2	0x0FFFF161
SFLASH_SAR_TEMP_MULTIPLIER	0x0FFFF164
SFLASH_SAR_TEMP_OFFSET	0x0FFFF166
SFLASH_SKIP_CHECKSUM	0x0FFFF169
SFLASH_INITIAL_PWR_BG_TRIM1	0x0FFFF16A
SFLASH_INITIAL_PWR_BG_TRIM1_INV	0x0FFFF16B
SFLASH_INITIAL_PWR_BG_TRIM2	0x0FFFF16C
SFLASH_INITIAL_PWR_BG_TRIM2_INV	0x0FFFF16D
SFLASH_INITIAL_SPCIF_TRIM_M0_DAC0	0x0FFFF16E
SFLASH_INITIAL_SPCIF_TRIM_M0_DAC0_INV	0x0FFFF16F
SFLASH_PROT_VIRGINKEY0	0x0FFFF170
SFLASH_PROT_VIRGINKEY1	0x0FFFF171
SFLASH_PROT_VIRGINKEY2	0x0FFFF172
SFLASH_PROT_VIRGINKEY3	0x0FFFF173

Register Name	Address
SFLASH_PROT_VIRGINKEY4	0x0FFFF174
SFLASH_PROT_VIRGINKEY5	0x0FFFF175
SFLASH_PROT_VIRGINKEY6	0x0FFFF176
SFLASH_PROT_VIRGINKEY7	0x0FFFF177
SFLASH_DIE_LOT0	0x0FFFF178
SFLASH_DIE_LOT1	0x0FFFF179
SFLASH_DIE_LOT2	0x0FFFF17A
SFLASH_DIE_WAFER	0x0FFFF17B
SFLASH_DIE_X	0x0FFFF17C
SFLASH_DIE_Y	0x0FFFF17D
SFLASH_DIE_SORT	0x0FFFF17E
SFLASH_DIE_MINOR	0x0FFFF17F
SFLASH_PE_TE_DATA0	0x0FFFF180
SFLASH_PE_TE_DATA1	0x0FFFF181
SFLASH_PE_TE_DATA2	0x0FFFF182
SFLASH_PE_TE_DATA3	0x0FFFF183
SFLASH_PE_TE_DATA4	0x0FFFF184
SFLASH_PE_TE_DATA5	0x0FFFF185
SFLASH_PE_TE_DATA6	0x0FFFF186
SFLASH_PE_TE_DATA7	0x0FFFF187
SFLASH_PE_TE_DATA8	0x0FFFF188
SFLASH_PE_TE_DATA9	0x0FFFF189
SFLASH_PE_TE_DATA10	0x0FFFF18A
SFLASH_PE_TE_DATA11	0x0FFFF18B
SFLASH_PE_TE_DATA12	0x0FFFF18C
SFLASH_PE_TE_DATA13	0x0FFFF18D
SFLASH_PE_TE_DATA14	0x0FFFF18E
SFLASH_PE_TE_DATA15	0x0FFFF18F
SFLASH_PE_TE_DATA16	0x0FFFF190
SFLASH_PE_TE_DATA17	0x0FFFF191
SFLASH_PE_TE_DATA18	0x0FFFF192
SFLASH_PE_TE_DATA19	0x0FFFF193
SFLASH_PE_TE_DATA20	0x0FFFF194
SFLASH_PE_TE_DATA21	0x0FFFF195
SFLASH_PE_TE_DATA22	0x0FFFF196
SFLASH_PE_TE_DATA23	0x0FFFF197
SFLASH_PE_TE_DATA24	0x0FFFF198
SFLASH_PE_TE_DATA25	0x0FFFF199
SFLASH_PE_TE_DATA26	0x0FFFF19A
SFLASH_PE_TE_DATA27	0x0FFFF19B
SFLASH_PE_TE_DATA28	0x0FFFF19C
SFLASH_PE_TE_DATA29	0x0FFFF19D

Register Name	Address
SFLASH_PE_TE_DATA30	0x0FFFF19E
SFLASH_PE_TE_DATA31	0x0FFFF19F
SFLASH_PP	0x0FFFF1A0
SFLASH_E	0x0FFFF1A4
SFLASH_P	0x0FFFF1A8
SFLASH_EA_E	0x0FFFF1AC
SFLASH_EA_P	0x0FFFF1B0
SFLASH_ES_E	0x0FFFF1B4
SFLASH_ES_P_EO	0x0FFFF1B8
SFLASH_IMO_TRIM_USBMODE_24	0x0FFFF1BE
SFLASH_IMO_TRIM_USBMODE_48	0x0FFFF1BF
SFLASH_IMO_TCTRIM_LT0	0x0FFFF1CC
SFLASH_IMO_TCTRIM_LT1	0x0FFFF1CD
SFLASH_IMO_TCTRIM_LT2	0x0FFFF1CE
SFLASH_IMO_TCTRIM_LT3	0x0FFFF1CF
SFLASH_IMO_TCTRIM_LT4	0x0FFFF1D0
SFLASH_IMO_TCTRIM_LT5	0x0FFFF1D1
SFLASH_IMO_TCTRIM_LT6	0x0FFFF1D2
SFLASH_IMO_TCTRIM_LT7	0x0FFFF1D3
SFLASH_IMO_TCTRIM_LT8	0x0FFFF1D4
SFLASH_IMO_TCTRIM_LT9	0x0FFFF1D5
SFLASH_IMO_TCTRIM_LT10	0x0FFFF1D6
SFLASH_IMO_TCTRIM_LT11	0x0FFFF1D7
SFLASH_IMO_TCTRIM_LT12	0x0FFFF1D8
SFLASH_IMO_TCTRIM_LT13	0x0FFFF1D9
SFLASH_IMO_TCTRIM_LT14	0x0FFFF1DA
SFLASH_IMO_TCTRIM_LT15	0x0FFFF1DB
SFLASH_IMO_TCTRIM_LT16	0x0FFFF1DC
SFLASH_IMO_TCTRIM_LT17	0x0FFFF1DD
SFLASH_IMO_TCTRIM_LT18	0x0FFFF1DE
SFLASH_IMO_TCTRIM_LT19	0x0FFFF1DF
SFLASH_IMO_TCTRIM_LT20	0x0FFFF1E0
SFLASH_IMO_TCTRIM_LT21	0x0FFFF1E1
SFLASH_IMO_TCTRIM_LT22	0x0FFFF1E2
SFLASH_IMO_TCTRIM_LT23	0x0FFFF1E3
SFLASH_IMO_TCTRIM_LT24	0x0FFFF1E4
SFLASH_IMO_TRIM_LT0	0x0FFFF1E5
SFLASH_IMO_TRIM_LT1	0x0FFFF1E6
SFLASH_IMO_TRIM_LT2	0x0FFFF1E7
SFLASH_IMO_TRIM_LT3	0x0FFFF1E8
SFLASH_IMO_TRIM_LT4	0x0FFFF1E9
SFLASH_IMO_TRIM_LT5	0x0FFFF1EA

Register Name	Address
SFLASH_IMO_TRIM_LT6	0x0FFFF1EB
SFLASH_IMO_TRIM_LT7	0x0FFFF1EC
SFLASH_IMO_TRIM_LT8	0x0FFFF1ED
SFLASH_IMO_TRIM_LT9	0x0FFFF1EE
SFLASH_IMO_TRIM_LT10	0x0FFFF1EF
SFLASH_IMO_TRIM_LT11	0x0FFFF1F0
SFLASH_IMO_TRIM_LT12	0x0FFFF1F1
SFLASH_IMO_TRIM_LT13	0x0FFFF1F2
SFLASH_IMO_TRIM_LT14	0x0FFFF1F3
SFLASH_IMO_TRIM_LT15	0x0FFFF1F4
SFLASH_IMO_TRIM_LT16	0x0FFFF1F5
SFLASH_IMO_TRIM_LT17	0x0FFFF1F6
SFLASH_IMO_TRIM_LT18	0x0FFFF1F7
SFLASH_IMO_TRIM_LT19	0x0FFFF1F8
SFLASH_IMO_TRIM_LT20	0x0FFFF1F9
SFLASH_IMO_TRIM_LT21	0x0FFFF1FA
SFLASH_IMO_TRIM_LT22	0x0FFFF1FB
SFLASH_IMO_TRIM_LT23	0x0FFFF1FC
SFLASH_IMO_TRIM_LT24	0x0FFFF1FD
SFLASH_CHECKSUM	0x0FFFF1FE

22.1.1 SFLASH_PROT_ROW0

Per Page Write Protection

Address: 0x0FFFF000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.2 SFLASH_PROT_ROW1

Per Page Write Protection

Address: 0x0FFFF001

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.3 SFLASH_PROT_ROW2

Per Page Write Protection

Address: 0x0FFFF002

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.4 SFLASH_PROT_ROW3

Per Page Write Protection

Address: 0x0FFFF003

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.5 SFLASH_PROT_ROW4

Per Page Write Protection

Address: 0x0FFFF004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.6 SFLASH_PROT_ROW5

Per Page Write Protection

Address: 0x0FFFF005

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.7 SFLASH_PROT_ROW6

Per Page Write Protection

Address: 0x0FFFF006

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.8 SFLASH_PROT_ROW7

Per Page Write Protection

Address: 0x0FFFF007

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.9 SFLASH_PROT_ROW8

Per Page Write Protection

Address: 0x0FFFF008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.10 SFLASH_PROT_ROW9

Per Page Write Protection

Address: 0x0FFFF009

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.11 SFLASH_PROT_ROW10

Per Page Write Protection

Address: 0x0FFFF00A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.12 SFLASH_PROT_ROW11

Per Page Write Protection

Address: 0x0FFFF00B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.13 SFLASH_PROT_ROW12

Per Page Write Protection

Address: 0x0FFFF00C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.14 SFLASH_PROT_ROW13

Per Page Write Protection

Address: 0x0FFFF00D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.15 SFLASH_PROT_ROW14

Per Page Write Protection

Address: 0x0FFFF00E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.16 SFLASH_PROT_ROW15

Per Page Write Protection

Address: 0x0FFFF00F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.17 SFLASH_PROT_ROW16

Per Page Write Protection

Address: 0x0FFFF010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.18 SFLASH_PROT_ROW17

Per Page Write Protection

Address: 0x0FFFF011

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.19 SFLASH_PROT_ROW18

Per Page Write Protection

Address: 0x0FFFF012

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.20 SFLASH_PROT_ROW19

Per Page Write Protection

Address: 0x0FFFF013

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.21 SFLASH_PROT_ROW20

Per Page Write Protection

Address: 0x0FFFF014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.22 SFLASH_PROT_ROW21

Per Page Write Protection

Address: 0x0FFFF015

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.23 SFLASH_PROT_ROW22

Per Page Write Protection

Address: 0x0FFFF016

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.24 SFLASH_PROT_ROW23

Per Page Write Protection

Address: 0x0FFFF017

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.25 SFLASH_PROT_ROW24

Per Page Write Protection

Address: 0x0FFFF018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.26 SFLASH_PROT_ROW25

Per Page Write Protection

Address: 0x0FFFF019

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.27 SFLASH_PROT_ROW26

Per Page Write Protection

Address: 0x0FFFF01A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.28 SFLASH_PROT_ROW27

Per Page Write Protection

Address: 0x0FFFF01B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.29 SFLASH_PROT_ROW28

Per Page Write Protection

Address: 0x0FFFF01C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.30 SFLASH_PROT_ROW29

Per Page Write Protection

Address: 0x0FFFF01D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.31 SFLASH_PROT_ROW30

Per Page Write Protection

Address: 0x0FFFF01E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.32 SFLASH_PROT_ROW31

Per Page Write Protection

Address: 0x0FFFF01F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.33 SFLASH_PROT_ROW32

Per Page Write Protection

Address: 0x0FFFF020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.34 SFLASH_PROT_ROW33

Per Page Write Protection

Address: 0x0FFFF021

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.35 SFLASH_PROT_ROW34

Per Page Write Protection

Address: 0x0FFFF022

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.36 SFLASH_PROT_ROW35

Per Page Write Protection

Address: 0x0FFFF023

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.37 SFLASH_PROT_ROW36

Per Page Write Protection

Address: 0x0FFFF024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.38 SFLASH_PROT_ROW37

Per Page Write Protection

Address: 0x0FFFF025

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.39 SFLASH_PROT_ROW38

Per Page Write Protection

Address: 0x0FFFF026

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.40 SFLASH_PROT_ROW39

Per Page Write Protection

Address: 0x0FFFF027

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.41 SFLASH_PROT_ROW40

Per Page Write Protection

Address: 0x0FFFF028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.42 SFLASH_PROT_ROW41

Per Page Write Protection

Address: 0x0FFFF029

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.43 SFLASH_PROT_ROW42

Per Page Write Protection

Address: 0x0FFFF02A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.44 SFLASH_PROT_ROW43

Per Page Write Protection

Address: 0x0FFFF02B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.45 SFLASH_PROT_ROW44

Per Page Write Protection

Address: 0x0FFFF02C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.46 SFLASH_PROT_ROW45

Per Page Write Protection

Address: 0x0FFFF02D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.47 SFLASH_PROT_ROW46

Per Page Write Protection

Address: 0x0FFFF02E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.48 SFLASH_PROT_ROW47

Per Page Write Protection

Address: 0x0FFFF02F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.49 SFLASH_PROT_ROW48

Per Page Write Protection

Address: 0x0FFFF030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.50 SFLASH_PROT_ROW49

Per Page Write Protection

Address: 0x0FFFF031

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.51 SFLASH_PROT_ROW50

Per Page Write Protection

Address: 0x0FFFF032

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.52 SFLASH_PROT_ROW51

Per Page Write Protection

Address: 0x0FFFF033

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.53 SFLASH_PROT_ROW52

Per Page Write Protection

Address: 0x0FFFF034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.54 SFLASH_PROT_ROW53

Per Page Write Protection

Address: 0x0FFFF035

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.55 SFLASH_PROT_ROW54

Per Page Write Protection

Address: 0x0FFFF036

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.56 SFLASH_PROT_ROW55

Per Page Write Protection

Address: 0x0FFFF037

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.57 SFLASH_PROT_ROW56

Per Page Write Protection

Address: 0x0FFFF038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.58 SFLASH_PROT_ROW57

Per Page Write Protection

Address: 0x0FFFF039

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.59 SFLASH_PROT_ROW58

Per Page Write Protection

Address: 0x0FFFF03A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.60 SFLASH_PROT_ROW59

Per Page Write Protection

Address: 0x0FFFF03B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.61 SFLASH_PROT_ROW60

Per Page Write Protection

Address: 0x0FFFF03C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.62 SFLASH_PROT_ROW61

Per Page Write Protection

Address: 0x0FFFF03D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.63 SFLASH_PROT_ROW62

Per Page Write Protection

Address: 0x0FFFF03E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.64 SFLASH_PROT_ROW63

Per Page Write Protection

Address: 0x0FFFF03F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Protection Data (1b per page) Default Value: X

22.1.65 SFLASH_PROT_PROTECTION

Protection Level

Address: 0x0FFFF07F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						None	
Name	None [7:2]						PROT_LEVEL [1:0]	

Bits	Name	Description
1 : 0	PROT_LEVEL	Current Protection Mode - note that encoding is different from CPUSS_PROTECTION !! Default Value: X **0x0: OPEN:** System is in OPEN mode **0x1: VIRGIN:** System is in VIRGIN mode **0x2: PROTECTED:** System is in PROTECTED mode **0x3: KILL:** System is in KILL mode

22.1.66 SFLASH_AV_PAIRS_8B0

8b Addr/Value pair Section

Address: 0x0FFFF080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.67 SFLASH_AV_PAIRS_8B1

8b Addr/Value pair Section

Address: 0x0FFFF081

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.68 SFLASH_AV_PAIRS_8B2

8b Addr/Value pair Section

Address: 0x0FFFF082

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.69 SFLASH_AV_PAIRS_8B3

8b Addr/Value pair Section

Address: 0x0FFFF083

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.70 SFLASH_AV_PAIRS_8B4

8b Addr/Value pair Section

Address: 0x0FFFF084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.71 SFLASH_AV_PAIRS_8B5

8b Addr/Value pair Section

Address: 0x0FFFF085

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.72 SFLASH_AV_PAIRS_8B6

8b Addr/Value pair Section

Address: 0x0FFFF086

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.73 SFLASH_AV_PAIRS_8B7

8b Addr/Value pair Section

Address: 0x0FFFF087

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.74 SFLASH_AV_PAIRS_8B8

8b Addr/Value pair Section

Address: 0x0FFFF088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.75 SFLASH_AV_PAIRS_8B9

8b Addr/Value pair Section

Address: 0x0FFFF089

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.76 SFLASH_AV_PAIRS_8B10

8b Addr/Value pair Section

Address: 0x0FFFF08A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.77 SFLASH_AV_PAIRS_8B11

8b Addr/Value pair Section

Address: 0x0FFFF08B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.78 SFLASH_AV_PAIRS_8B12

8b Addr/Value pair Section

Address: 0x0FFFF08C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.79 SFLASH_AV_PAIRS_8B13

8b Addr/Value pair Section

Address: 0x0FFFF08D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.80 SFLASH_AV_PAIRS_8B14

8b Addr/Value pair Section

Address: 0x0FFFF08E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.81 SFLASH_AV_PAIRS_8B15

8b Addr/Value pair Section

Address: 0x0FFFF08F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.82 SFLASH_AV_PAIRS_8B16

8b Addr/Value pair Section

Address: 0x0FFFF090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.83 SFLASH_AV_PAIRS_8B17

8b Addr/Value pair Section

Address: 0x0FFFF091

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.84 SFLASH_AV_PAIRS_8B18

8b Addr/Value pair Section

Address: 0x0FFFF092

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.85 SFLASH_AV_PAIRS_8B19

8b Addr/Value pair Section

Address: 0x0FFFF093

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.86 SFLASH_AV_PAIRS_8B20

8b Addr/Value pair Section

Address: 0x0FFFF094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.87 SFLASH_AV_PAIRS_8B21

8b Addr/Value pair Section

Address: 0x0FFFF095

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.88 SFLASH_AV_PAIRS_8B22

8b Addr/Value pair Section

Address: 0x0FFFF096

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.89 SFLASH_AV_PAIRS_8B23

8b Addr/Value pair Section

Address: 0x0FFFF097

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.90 SFLASH_AV_PAIRS_8B24

8b Addr/Value pair Section

Address: 0x0FFFF098

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.91 SFLASH_AV_PAIRS_8B25

8b Addr/Value pair Section

Address: 0x0FFFF099

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.92 SFLASH_AV_PAIRS_8B26

8b Addr/Value pair Section

Address: 0x0FFFF09A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.93 SFLASH_AV_PAIRS_8B27

8b Addr/Value pair Section

Address: 0x0FFFF09B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.94 SFLASH_AV_PAIRS_8B28

8b Addr/Value pair Section

Address: 0x0FFFF09C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.95 SFLASH_AV_PAIRS_8B29

8b Addr/Value pair Section

Address: 0x0FFFF09D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.96 SFLASH_AV_PAIRS_8B30

8b Addr/Value pair Section

Address: 0x0FFFF09E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.97 SFLASH_AV_PAIRS_8B31

8b Addr/Value pair Section

Address: 0x0FFFF09F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.98 SFLASH_AV_PAIRS_8B32

8b Addr/Value pair Section

Address: 0x0FFFF0A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.99 SFLASH_AV_PAIRS_8B33

8b Addr/Value pair Section

Address: 0x0FFFF0A1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.100 SFLASH_AV_PAIRS_8B34

8b Addr/Value pair Section

Address: 0x0FFFF0A2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.101 SFLASH_AV_PAIRS_8B35

8b Addr/Value pair Section

Address: 0x0FFFF0A3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.102 SFLASH_AV_PAIRS_8B36

8b Addr/Value pair Section

Address: 0x0FFFF0A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.103 SFLASH_AV_PAIRS_8B37

8b Addr/Value pair Section

Address: 0x0FFFF0A5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.104 SFLASH_AV_PAIRS_8B38

8b Addr/Value pair Section

Address: 0x0FFFF0A6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.105 SFLASH_AV_PAIRS_8B39

8b Addr/Value pair Section

Address: 0x0FFFF0A7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.106 SFLASH_AV_PAIRS_8B40

8b Addr/Value pair Section

Address: 0x0FFFF0A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.107 SFLASH_AV_PAIRS_8B41

8b Addr/Value pair Section

Address: 0x0FFFF0A9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.108 SFLASH_AV_PAIRS_8B42

8b Addr/Value pair Section

Address: 0x0FFFF0AA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.109 SFLASH_AV_PAIRS_8B43

8b Addr/Value pair Section

Address: 0x0FFFF0AB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.110 SFLASH_AV_PAIRS_8B44

8b Addr/Value pair Section

Address: 0x0FFFF0AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.111 SFLASH_AV_PAIRS_8B45

8b Addr/Value pair Section

Address: 0x0FFFF0AD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.112 SFLASH_AV_PAIRS_8B46

8b Addr/Value pair Section

Address: 0x0FFFF0AE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.113 SFLASH_AV_PAIRS_8B47

8b Addr/Value pair Section

Address: 0x0FFFF0AF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.114 SFLASH_AV_PAIRS_8B48

8b Addr/Value pair Section

Address: 0x0FFFF0B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.115 SFLASH_AV_PAIRS_8B49

8b Addr/Value pair Section

Address: 0x0FFFF0B1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.116 SFLASH_AV_PAIRS_8B50

8b Addr/Value pair Section

Address: 0x0FFFF0B2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.117 SFLASH_AV_PAIRS_8B51

8b Addr/Value pair Section

Address: 0x0FFFF0B3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.118 SFLASH_AV_PAIRS_8B52

8b Addr/Value pair Section

Address: 0x0FFFF0B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.119 SFLASH_AV_PAIRS_8B53

8b Addr/Value pair Section

Address: 0x0FFFF0B5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.120 SFLASH_AV_PAIRS_8B54

8b Addr/Value pair Section

Address: 0x0FFFF0B6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.121 SFLASH_AV_PAIRS_8B55

8b Addr/Value pair Section

Address: 0x0FFFF0B7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.122 SFLASH_AV_PAIRS_8B56

8b Addr/Value pair Section

Address: 0x0FFFF0B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.123 SFLASH_AV_PAIRS_8B57

8b Addr/Value pair Section

Address: 0x0FFFF0B9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.124 SFLASH_AV_PAIRS_8B58

8b Addr/Value pair Section

Address: 0x0FFFF0BA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.125 SFLASH_AV_PAIRS_8B59

8b Addr/Value pair Section

Address: 0x0FFFF0BB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.126 SFLASH_AV_PAIRS_8B60

8b Addr/Value pair Section

Address: 0x0FFFF0BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.127 SFLASH_AV_PAIRS_8B61

8b Addr/Value pair Section

Address: 0x0FFFF0BD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.128 SFLASH_AV_PAIRS_8B62

8b Addr/Value pair Section

Address: 0x0FFFF0BE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.129 SFLASH_AV_PAIRS_8B63

8b Addr/Value pair Section

Address: 0x0FFFF0BF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.130 SFLASH_AV_PAIRS_8B64

8b Addr/Value pair Section

Address: 0x0FFFF0C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.131 SFLASH_AV_PAIRS_8B65

8b Addr/Value pair Section

Address: 0x0FFFF0C1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.132 SFLASH_AV_PAIRS_8B66

8b Addr/Value pair Section

Address: 0x0FFFF0C2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.133 SFLASH_AV_PAIRS_8B67

8b Addr/Value pair Section

Address: 0x0FFFF0C3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.134 SFLASH_AV_PAIRS_8B68

8b Addr/Value pair Section

Address: 0x0FFFF0C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.135 SFLASH_AV_PAIRS_8B69

8b Addr/Value pair Section

Address: 0x0FFFF0C5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.136 SFLASH_AV_PAIRS_8B70

8b Addr/Value pair Section

Address: 0x0FFFF0C6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.137 SFLASH_AV_PAIRS_8B71

8b Addr/Value pair Section

Address: 0x0FFFF0C7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.138 SFLASH_AV_PAIRS_8B72

8b Addr/Value pair Section

Address: 0x0FFFF0C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.139 SFLASH_AV_PAIRS_8B73

8b Addr/Value pair Section

Address: 0x0FFFF0C9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.140 SFLASH_AV_PAIRS_8B74

8b Addr/Value pair Section

Address: 0x0FFFF0CA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.141 SFLASH_AV_PAIRS_8B75

8b Addr/Value pair Section

Address: 0x0FFFF0CB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.142 SFLASH_AV_PAIRS_8B76

8b Addr/Value pair Section

Address: 0x0FFFF0CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.143 SFLASH_AV_PAIRS_8B77

8b Addr/Value pair Section

Address: 0x0FFFF0CD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.144 SFLASH_AV_PAIRS_8B78

8b Addr/Value pair Section

Address: 0x0FFFF0CE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.145 SFLASH_AV_PAIRS_8B79

8b Addr/Value pair Section

Address: 0x0FFFF0CF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.146 SFLASH_AV_PAIRS_8B80

8b Addr/Value pair Section

Address: 0x0FFFF0D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.147 SFLASH_AV_PAIRS_8B81

8b Addr/Value pair Section

Address: 0x0FFFF0D1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.148 SFLASH_AV_PAIRS_8B82

8b Addr/Value pair Section

Address: 0x0FFFF0D2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.149 SFLASH_AV_PAIRS_8B83

8b Addr/Value pair Section

Address: 0x0FFFF0D3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.150 SFLASH_AV_PAIRS_8B84

8b Addr/Value pair Section

Address: 0x0FFFF0D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.151 SFLASH_CSDV2_CSD1_ADC_TRIM1

CSDV2 CSD1 ADC TRIM 1

Address: 0x0FFFF0D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW			RW				
HW Access	None			None				
Name	ADCTRIM_2p4V_2_0 [7:5]			ADCTRIM_1p2V [4:0]				

Bits	Name	Description
7 : 5	ADCTRIM_2p4V_2_0	1.2V trim data - low order 3 bits of 5 bit field Default Value: X
4 : 0	ADCTRIM_1p2V	1.2V trim data Default Value: X

22.1.152 SFLASH_AV_PAIRS_8B85

8b Addr/Value pair Section

Address: 0x0FFFF0D5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.153 SFLASH_CSDV2_CSD1_ADC_TRIM2

CSDV2 CSD1 ADC TRIM2

Address: 0x0FFFF0D5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	None		None				
Name	None	ADCTRIM_2p4V_5_4 [6:5]		ADCTRIM_3p84V_2_0 [4:0]				

Bits	Name	Description
6 : 5	ADCTRIM_2p4V_5_4	1.2V trim data - high order 2 bits of 5 bit field Default Value: X
4 : 0	ADCTRIM_3p84V_2_0	1.2V trim data Default Value: X

22.1.154 SFLASH_AV_PAIRS_8B86

8b Addr/Value pair Section

Address: 0x0FFFF0D6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.155 SFLASH_AV_PAIRS_8B87

8b Addr/Value pair Section

Address: 0x0FFFF0D7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.156 SFLASH_AV_PAIRS_8B88

8b Addr/Value pair Section

Address: 0x0FFFF0D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.157 SFLASH_AV_PAIRS_8B89

8b Addr/Value pair Section

Address: 0x0FFFF0D9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.158 SFLASH_AV_PAIRS_8B90

8b Addr/Value pair Section

Address: 0x0FFFF0DA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.159 SFLASH_AV_PAIRS_8B91

8b Addr/Value pair Section

Address: 0x0FFFF0DB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.160 SFLASH_AV_PAIRS_8B92

8b Addr/Value pair Section

Address: 0x0FFFF0DC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.161 SFLASH_AV_PAIRS_8B93

8b Addr/Value pair Section

Address: 0x0FFFF0DD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.162 SFLASH_AV_PAIRS_8B94

8b Addr/Value pair Section

Address: 0x0FFFF0DE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.163 SFLASH_AV_PAIRS_8B95

8b Addr/Value pair Section

Address: 0x0FFFF0DF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.164 SFLASH_AV_PAIRS_8B96

8b Addr/Value pair Section

Address: 0x0FFFF0E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.165 SFLASH_AV_PAIRS_8B97

8b Addr/Value pair Section

Address: 0x0FFFF0E1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.166 SFLASH_AV_PAIRS_8B98

8b Addr/Value pair Section

Address: 0x0FFFF0E2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.167 SFLASH_AV_PAIRS_8B99

8b Addr/Value pair Section

Address: 0x0FFFF0E3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.168 SFLASH_AV_PAIRS_8B100

8b Addr/Value pair Section

Address: 0x0FFFF0E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.169 SFLASH_AV_PAIRS_8B101

8b Addr/Value pair Section

Address: 0x0FFFF0E5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.170 SFLASH_AV_PAIRS_8B102

8b Addr/Value pair Section

Address: 0x0FFFF0E6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.171 SFLASH_AV_PAIRS_8B103

8b Addr/Value pair Section

Address: 0x0FFFF0E7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.172 SFLASH_AV_PAIRS_8B104

8b Addr/Value pair Section

Address: 0x0FFFF0E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.173 SFLASH_AV_PAIRS_8B105

8b Addr/Value pair Section

Address: 0x0FFFF0E9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.174 SFLASH_AV_PAIRS_8B106

8b Addr/Value pair Section

Address: 0x0FFFF0EA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.175 SFLASH_AV_PAIRS_8B107

8b Addr/Value pair Section

Address: 0x0FFFF0EB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.176 SFLASH_AV_PAIRS_8B108

8b Addr/Value pair Section

Address: 0x0FFFF0EC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.177 SFLASH_AV_PAIRS_8B109

8b Addr/Value pair Section

Address: 0x0FFFF0ED

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.178 SFLASH_AV_PAIRS_8B110

8b Addr/Value pair Section

Address: 0x0FFFF0EE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.179 SFLASH_AV_PAIRS_8B111

8b Addr/Value pair Section

Address: 0x0FFFF0EF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.180 SFLASH_AV_PAIRS_8B112

8b Addr/Value pair Section

Address: 0x0FFFF0F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.181 SFLASH_AV_PAIRS_8B113

8b Addr/Value pair Section

Address: 0x0FFFF0F1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.182 SFLASH_AV_PAIRS_8B114

8b Addr/Value pair Section

Address: 0x0FFFF0F2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.183 SFLASH_AV_PAIRS_8B115

8b Addr/Value pair Section

Address: 0x0FFFF0F3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.184 SFLASH_AV_PAIRS_8B116

8b Addr/Value pair Section

Address: 0x0FFFF0F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.185 SFLASH_AV_PAIRS_8B117

8b Addr/Value pair Section

Address: 0x0FFFF0F5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.186 SFLASH_AV_PAIRS_8B118

8b Addr/Value pair Section

Address: 0x0FFFF0F6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.187 SFLASH_AV_PAIRS_8B119

8b Addr/Value pair Section

Address: 0x0FFFF0F7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.188 SFLASH_AV_PAIRS_8B120

8b Addr/Value pair Section

Address: 0x0FFFF0F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.189 SFLASH_AV_PAIRS_8B121

8b Addr/Value pair Section

Address: 0x0FFFF0F9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.190 SFLASH_AV_PAIRS_8B122

8b Addr/Value pair Section

Address: 0x0FFFF0FA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.191 SFLASH_AV_PAIRS_8B123

8b Addr/Value pair Section

Address: 0x0FFFF0FB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.192 SFLASH_AV_PAIRS_8B124

8b Addr/Value pair Section

Address: 0x0FFFF0FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.193 SFLASH_AV_PAIRS_8B125

8b Addr/Value pair Section

Address: 0x0FFFF0FD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.194 SFLASH_AV_PAIRS_8B126

8b Addr/Value pair Section

Address: 0x0FFFF0FE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.195 SFLASH_AV_PAIRS_8B127

8b Addr/Value pair Section

Address: 0x0FFFF0FF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	Address or Value Byte Default Value: X

22.1.196 SFLASH_AV_PAIRS_32B0

32b Addr/Value pair Section

Address: 0x0FFFF100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.197 SFLASH_AV_PAIRS_32B1

32b Addr/Value pair Section

Address: 0x0FFFF104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.198 SFLASH_AV_PAIRS_32B2

32b Addr/Value pair Section

Address: 0x0FFFF108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.199 SFLASH_AV_PAIRS_32B3

32b Addr/Value pair Section

Address: 0x0FFFF10C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.200 SFLASH_AV_PAIRS_32B4

32b Addr/Value pair Section

Address: 0x0FFFF110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.201 SFLASH_AV_PAIRS_32B5

32b Addr/Value pair Section

Address: 0x0FFFF114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.202 SFLASH_AV_PAIRS_32B6

32b Addr/Value pair Section

Address: 0x0FFFF118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.203 SFLASH_AV_PAIRS_32B7

32b Addr/Value pair Section

Address: 0x0FFFF11C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.204 SFLASH_AV_PAIRS_32B8

32b Addr/Value pair Section

Address: 0x0FFFF120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.205 SFLASH_AV_PAIRS_32B9

32b Addr/Value pair Section

Address: 0x0FFFF124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.206 SFLASH_AV_PAIRS_32B10

32b Addr/Value pair Section

Address: 0x0FFFF128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.207 SFLASH_AV_PAIRS_32B11

32b Addr/Value pair Section

Address: 0x0FFFF12C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.208 SFLASH_AV_PAIRS_32B12

32b Addr/Value pair Section

Address: 0x0FFFF130

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.209 SFLASH_AV_PAIRS_32B13

32b Addr/Value pair Section

Address: 0x0FFFF134

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.210 SFLASH_AV_PAIRS_32B14

32b Addr/Value pair Section

Address: 0x0FFFF138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.211 SFLASH_AV_PAIRS_32B15

32b Addr/Value pair Section

Address: 0x0FFFF13C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Address or Value Word Default Value: X

22.1.212 SFLASH_CPUSS_WOUNDING

CPUSS Wounding Register

Address: 0x0FFFF140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA32 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	DATA32 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	DATA32 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	DATA32 [31:24]							

Bits	Name	Description
31 : 0	DATA32	Data to use for register Default Value: X

22.1.213 SFLASH_SILICON_ID

Silicon ID

Address: 0x0FFFF144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	ID	Silicon ID Default Value: X

22.1.214 SFLASH_CPUSS_PRIV_RAM

RAM Privileged Limit

Address: 0x0FFFF148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RAM_PROT_LIMIT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RAM_PROT_LIMIT

Bits	Name	Description
8 : 0	RAM_PROT_LIMIT	Indicates the limit where the privileged area of SRAM starts in increments of 256 Bytes. "0": Entire SRAM is Privileged. "1": First 256 Bytes are User accessable. Any number larger than the size of the SRAM indicates that the entire SRAM is user mode accessible. Default Value: 0

22.1.215 SFLASH_CPUSS_PRIV_ROM_BROM

Boot ROM Privileged Limit

Address: 0x0FFFF14A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	BROM_PROT_LIMIT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	Name	Description
7 : 0	BROM_PROT_LIMIT	Indicates the limit where the privileged area of the Boot ROM partition starts in increments of 256 Bytes. "0": Entire Boot ROM is Privileged. "1": First 256 Bytes are User accessable. ... BROM_PROT_LIMIT >= "Boot ROM partition capacity": Entire Boot ROM partition is user mode accessible. Default Value: 0

22.1.216 SFLASH_CPUSS_PRIV_FLASH

Flash Privileged Limit

Address: 0x0FFFF14C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	FLASH_PROT_LIMIT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:11]					FLASH_PROT_LIMIT [10:8]		

Bits	Name	Description
10 : 0	FLASH_PROT_LIMIT	Indicates the limit where the privileged area of flash starts in increments of 256 Bytes. "0": Entire flash is Privileged. "1": First 256 Bytes are User accessable. Any number larger than the size of the flash indicates that the entire flash is user mode accessible. Note that SuperVisory rows are always User accessable. If FLASH_PROT_LIMIT defines a non-empty privileged area, the boot ROM will assume that a system call table exists at the beginning of the Flash privileged area and use it for all SystemCalls made using SYSREQ. Default Value: 0

22.1.217 SFLASH_CPUSS_PRIV_ROM_SROM

System ROM Privileged Limit

Address: 0x0FFFF14E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SROM_PROT_LIMIT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						SROM_PROT_LIMIT [9:8]	

Bits	Name	Description
9 : 0	SROM_PROT_LIMIT	Indicates the limit where the privileged area of System ROM partition starts in increments of 256 Bytes. The limit is wrt. the start of the ROM memory (start of the Boot ROM partition). SROM_PROT_LIMIT * 256 Byte <= "Boot ROM partition capacity": Entire System ROM is Privileged. SROM_PROT_LIMIT * 256 Byte > "Boot ROM partition capacity": First SROM_PROT_LIMIT * 256 - "Boot ROM partition capacity" Bytes are User accessable. ... SROM_PROT_LIMIT >= "ROM capacity": Entire System ROM is user mode accessible. Default Value: 0

22.1.218 SFLASH_HIB_KEY_DELAY

Hibernate wakeup value for PWR_KEY_DELAY

Address: 0x0FFFF150

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay (in 12MHz IMO clock cycles) to wait for references to settle on wakeup from hibernate/ deepsleep. PBOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. Default Value: X

22.1.219 SFLASH_DPSLP_KEY_DELAY

DeepSleep wakeup value for PWR_KEY_DELAY

Address: 0x0FFFF152

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay (in 12MHz IMO clock cycles) to wait for references to settle on wakeup from hibernate/ deepsleep. PBOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. Default Value: X

22.1.220 SFLASH_SWD_CONFIG

SWD pinout selector (not present in TSG4/TSG5-M)

Address: 0x0FFFF154

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							None
Name	None [7:1]							SWD_SELECT

Bits	Name	Description
0	SWD_SELECT	0: Use Primary SWD location 1: Use Alternate SWD location Default Value: X

22.1.221 SFLASH_SWD_LISTEN

Listen Window Length

Address: 0x0FFFF158

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CYCLES [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	CYCLES [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	CYCLES [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	CYCLES [31:24]							

Bits	Name	Description
31 : 0	CYCLES	Number of clock cycles Default Value: X

22.1.222 SFLASH_FLASH_START

Flash Image Start Address

Address: 0x0FFFF15C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	ADDRESS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	ADDRESS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	ADDRESS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	ADDRESS [31:24]							

Bits	Name	Description
31 : 0	ADDRESS	Start Address Default Value: X

22.1.223 SFLASH_CSDV2_CSD0_ADC_TRIM1

CSDv2 CSD0 ADC Trim 2

Address: 0x0FFFF160

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW			RW				
HW Access	None			None				
Name	ADCTRIM_2p4V_2_0 [7:5]			ADCTRIM_1p2V [4:0]				

Bits	Name	Description
7 : 5	ADCTRIM_2p4V_2_0	1.2V trim data - low order 3 bits of 5 bit field Default Value: X
4 : 0	ADCTRIM_1p2V	1.2V trim data Default Value: X

22.1.224 SFLASH_CSDV2_CSD0_ADC_TRIM2

CSDv2 CSD0 ADC Trim 1

Address: 0x0FFFF161

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	None		None				
Name	None	ADCTRIM_2p4V_5_4 [6:5]		ADCTRIM_3p84V_2_0 [4:0]				

Bits	Name	Description
6 : 5	ADCTRIM_2p4V_5_4	1.2V trim data - high order 2 bits of 5 bit field Default Value: X
4 : 0	ADCTRIM_3p84V_2_0	1.2V trim data Default Value: X

22.1.225 SFLASH_SAR_TEMP_MULTIPLIER

SAR Temperature Sensor Multiplication Factor

Address: 0x0FFFF164

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TEMP_MULTIPLIER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	TEMP_MULTIPLIER [15:8]							

Bits	Name	Description
15 : 0	TEMP_MULTIPLIER	Multiplier value for SAR temperature sensor in fixed point 0.16 format. Note: this field exists in products that contain SAR (m0s8sar) only. Default Value: X

22.1.226 SFLASH_SAR_TEMP_OFFSET

SAR Temperature Sensor Offset

Address: 0x0FFFF166

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TEMP_OFFSET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	TEMP_OFFSET [15:8]							

Bits	Name	Description
15 : 0	TEMP_OFFSET	Offset value for SAR temperature sensor in fixed point 10.6 format. Note: this field exists in products that contain SAR (m0s8sar) only. Default Value: X

22.1.227 SFLASH_SKIP_CHECKSUM

Checksum Skip Option Register

Address: 0x0FFFF169

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	SKIP [7:0]							

Bits	Name	Description
7 : 0	SKIP	0: Perform checksum check (see CHECKSUM fueld below) 1: Skip checksum check >1: Undefined - do not use Default Value: X

22.1.228 SFLASH_INITIAL_PWR_BG_TRIM1

SRSSLT BG Vref trim used during boot

Address: 0x0FFFF16A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		REF_ITRIM [5:0]					

Bits	Name	Description
5 : 0	REF_ITRIM	See PWR_BG_TRIM2 in SRSSLT Default Value: 0

22.1.229 SFLASH_INITIAL_PWR_BG_TRIM1_INV

SRSSLT BG Vref trim used during boot

Address: 0x0FFFF16B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		REF_ITRIM [5:0]					

Bits	Name	Description
5 : 0	REF_ITRIM	See PWR_BG_TRIM2 in SRSSLT Default Value: 0

22.1.230 SFLASH_INITIAL_PWR_BG_TRIM2

SRSSLT BG Iref trim used during boot

Address: 0x0FFFF16C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		REF_ITRIM [5:0]					

Bits	Name	Description
5 : 0	REF_ITRIM	See PWR_BG_TRIM2 in SRSSLT Default Value: 0

22.1.231 SFLASH_INITIAL_PWR_BG_TRIM2_INV

SRSSLT BG Iref trim used during boot

Address: 0x0FFFF16D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		REF_ITRIM [5:0]					

Bits	Name	Description
5 : 0	REF_ITRIM	See PWR_BG_TRIM2 in SRSSLT Default Value: 0

22.1.232 SFLASH_INITIAL_SPCIF_TRIM_M0_DAC0

FLASH IDAC trim used during boot

Address: 0x0FFFF16E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW			RW				
HW Access	R			R				
Name	SLOPE [7:5]			IDAC [4:0]				

Bits	Name	Description
7 : 5	SLOPE	See SPCIF_TRIM1 Default Value: 0
4 : 0	IDAC	See SPCIF_TRIM1 Default Value: 0

22.1.233 SFLASH_INITIAL_SPCIF_TRIM_M0_DAC0_INV

FLASH IDAC trim used during boot

Address: 0x0FFFF16F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW			RW				
HW Access	R			R				
Name	SLOPE [7:5]			IDAC [4:0]				

Bits	Name	Description
7 : 5	SLOPE	See SPCIF_TRIM1 Default Value: 0
4 : 0	IDAC	See SPCIF_TRIM1 Default Value: 0

22.1.234 SFLASH_PROT_VIRGINKEY0

Virgin Protection Mode Key

Address: 0x0FFFF170

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.235 SFLASH_PROT_VIRGINKEY1

Virgin Protection Mode Key

Address: 0x0FFFF171

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.236 SFLASH_PROT_VIRGINKEY2

Virgin Protection Mode Key

Address: 0x0FFFF172

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.237 SFLASH_PROT_VIRGINKEY3

Virgin Protection Mode Key

Address: 0x0FFFF173

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.238 SFLASH_PROT_VIRGINKEY4

Virgin Protection Mode Key

Address: 0x0FFFF174

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.239 SFLASH_PROT_VIRGINKEY5

Virgin Protection Mode Key

Address: 0x0FFFF175

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.240 SFLASH_PROT_VIRGINKEY6

Virgin Protection Mode Key

Address: 0x0FFFF176

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.241 SFLASH_PROT_VIRGINKEY7

Virgin Protection Mode Key

Address: 0x0FFFF177

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	KEY8 [7:0]							

Bits	Name	Description
7 : 0	KEY8	Key Byte Default Value: X

22.1.242 SFLASH_DIE_LOT0

Lot Number (3 bytes)

Address: 0x0FFFF178

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	LOT [7:0]							

Bits	Name	Description
7 : 0	LOT	Lot Number Byte Default Value: X

22.1.243 SFLASH_DIE_LOT1

Lot Number (3 bytes)

Address: 0x0FFFF179

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	LOT [7:0]							

Bits	Name	Description
7 : 0	LOT	Lot Number Byte Default Value: X

22.1.244 SFLASH_DIE_LOT2

Lot Number (3 bytes)

Address: 0x0FFFF17A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	LOT [7:0]							

Bits	Name	Description
7 : 0	LOT	Lot Number Byte Default Value: X

22.1.245 SFLASH_DIE_WAFER

Wafer Number

Address: 0x0FFFF17B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	WAFER [7:0]							

Bits	Name	Description
7 : 0	WAFER	Wafer Number Default Value: X

22.1.246 SFLASH_DIE_X

X Position on Wafer, CRI Pass/Fail Bin

Address: 0x0FFFF17C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	X [7:0]							

Bits	Name	Description
7 : 0	X	X Position Default Value: X

22.1.247 SFLASH_DIE_Y

Y Position on Wafer, CHI Pass/Fail Bin

Address: 0x0FFFF17D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	Y [7:0]							

Bits	Name	Description
7 : 0	Y	Y Position Default Value: X

22.1.248 SFLASH_DIE_SORT

Sort1/2/3 Pass/Fail Bin

Address: 0x0FFFF17E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		None	None	None	None	None	None
Name	None [7:6]		ENG_PASS	CHI_PASS	CRI_PASS	S3_PASS	S2_PASS	S1_PASS

Bits	Name	Description
5	ENG_PASS	ENG Pass Bin Default Value: X
4	CHI_PASS	CHI Pass Bin (1) or 0 (Fail Bin) Default Value: X
3	CRI_PASS	CRI Pass Bin (1) or 0 (Fail Bin) Default Value: X
2	S3_PASS	SORT3 Pass Bin (1) or 0 (Fail Bin) Default Value: X
1	S2_PASS	SORT2 Pass Bin (1) or 0 (Fail Bin) Default Value: X
0	S1_PASS	SORT1 Pass Bin (1) or 0 (Fail Bin) Default Value: X

22.1.249 SFLASH_DIE_MINOR

Minor Revision Number

Address: 0x0FFFF17F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	MINOR [7:0]							

Bits	Name	Description
7 : 0	MINOR	Minor revision number Default Value: X

22.1.250 SFLASH_PE_TE_DATA0

PE/TE Data

Address: 0x0FFFF180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.251 SFLASH_PE_TE_DATA1

PE/TE Data

Address: 0x0FFFF181

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.252 SFLASH_PE_TE_DATA2

PE/TE Data

Address: 0x0FFFF182

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.253 SFLASH_PE_TE_DATA3

PE/TE Data

Address: 0x0FFFF183

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.254 SFLASH_PE_TE_DATA4

PE/TE Data

Address: 0x0FFFF184

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.255 SFLASH_PE_TE_DATA5

PE/TE Data

Address: 0x0FFFF185

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.256 SFLASH_PE_TE_DATA6

PE/TE Data

Address: 0x0FFFF186

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.257 SFLASH_PE_TE_DATA7

PE/TE Data

Address: 0x0FFFF187

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.258 SFLASH_PE_TE_DATA8

PE/TE Data

Address: 0x0FFFF188

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.259 SFLASH_PE_TE_DATA9

PE/TE Data

Address: 0x0FFFF189

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.260 SFLASH_PE_TE_DATA10

PE/TE Data

Address: 0x0FFFF18A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.261 SFLASH_PE_TE_DATA11

PE/TE Data

Address: 0x0FFFF18B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.262 SFLASH_PE_TE_DATA12

PE/TE Data

Address: 0x0FFFF18C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.263 SFLASH_PE_TE_DATA13

PE/TE Data

Address: 0x0FFFF18D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.264 SFLASH_PE_TE_DATA14

PE/TE Data

Address: 0x0FFFF18E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.265 SFLASH_PE_TE_DATA15

PE/TE Data

Address: 0x0FFFF18F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.266 SFLASH_PE_TE_DATA16

PE/TE Data

Address: 0x0FFFF190

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.267 SFLASH_PE_TE_DATA17

PE/TE Data

Address: 0x0FFFF191

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.268 SFLASH_PE_TE_DATA18

PE/TE Data

Address: 0x0FFFF192

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.269 SFLASH_PE_TE_DATA19

PE/TE Data

Address: 0x0FFFF193

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.270 SFLASH_PE_TE_DATA20

PE/TE Data

Address: 0x0FFFF194

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.271 SFLASH_PE_TE_DATA21

PE/TE Data

Address: 0x0FFFF195

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.272 SFLASH_PE_TE_DATA22

PE/TE Data

Address: 0x0FFFF196

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.273 SFLASH_PE_TE_DATA23

PE/TE Data

Address: 0x0FFFF197

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.274 SFLASH_PE_TE_DATA24

PE/TE Data

Address: 0x0FFFF198

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.275 SFLASH_PE_TE_DATA25

PE/TE Data

Address: 0x0FFFF199

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.276 SFLASH_PE_TE_DATA26

PE/TE Data

Address: 0x0FFFF19A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.277 SFLASH_PE_TE_DATA27

PE/TE Data

Address: 0x0FFFF19B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.278 SFLASH_PE_TE_DATA28

PE/TE Data

Address: 0x0FFFF19C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.279 SFLASH_PE_TE_DATA29

PE/TE Data

Address: 0x0FFFF19D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.280 SFLASH_PE_TE_DATA30

PE/TE Data

Address: 0x0FFFF19E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.281 SFLASH_PE_TE_DATA31

PE/TE Data

Address: 0x0FFFF19F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	DATA8 [7:0]							

Bits	Name	Description
7 : 0	DATA8	PE/TE Data Default Value: X

22.1.282 SFLASH_PP

Preprogram Settings

Address: 0x0FFFF1A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	PERIOD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	None				None			
Name	NDAC [31:28]				PDAC [27:24]			

Bits	Name	Description
31 : 28	NDAC	NDAC input. Each increment in NDAC causes an increase of ~0.10V in VNEG Default Value: X
27 : 24	PDAC	PDAC input. Each increment in PDAC causes an increase of ~0.10V in VPOS Default Value: X
23 : 0	PERIOD	Period of timer in clk_spcif_timer ticks. For regular FLASH, clock is 36MHz from dedicated oscillator. For FLASH-Lite, clock is same as clk_hf, which must be set to 48MHz for 48MHz devices and 12MHz for max 16MHz devices Default Value: X

22.1.283 SFLASH_E

Erase Settings

Address: 0x0FFFF1A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	PERIOD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	None				None			
Name	NDAC [31:28]				PDAC [27:24]			

Bits	Name	Description
31 : 28	NDAC	NDAC input. Each increment in NDAC causes an increase of ~0.10V in VNEG Default Value: X
27 : 24	PDAC	PDAC input. Each increment in PDAC causes an increase of ~0.10V in VPOS Default Value: X
23 : 0	PERIOD	Period of timer in clk_spcif_timer ticks. For regular FLASH, clock is 36MHz from dedicated oscillator. For FLASH-Lite, clock is same as clk_hf, which must be set to 48MHz for 48MHz devices and 12MHz for max 16MHz devices Default Value: X

22.1.284 SFLASH_P

Program Settings

Address: 0x0FFFF1A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	PERIOD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	None				None			
Name	NDAC [31:28]				PDAC [27:24]			

Bits	Name	Description
31 : 28	NDAC	NDAC input. Each increment in NDAC causes an increase of ~0.10V in VNEG Default Value: X
27 : 24	PDAC	PDAC input. Each increment in PDAC causes an increase of ~0.10V in VPOS Default Value: X
23 : 0	PERIOD	Period of timer in clk_spcif_timer ticks. For regular FLASH, clock is 36MHz from dedicated oscillator. For FLASH-Lite, clock is same as clk_hf, which must be set to 48MHz for 48MHz devices and 12MHz for max 16MHz devices Default Value: X

22.1.285 SFLASH_EA_E

Erase All - Erase Settings

Address: 0x0FFFF1AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	PERIOD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	None				None			
Name	NDAC [31:28]				PDAC [27:24]			

Bits	Name	Description
31 : 28	NDAC	NDAC input. Each increment in NDAC causes an increase of ~0.10V in VNEG Default Value: X
27 : 24	PDAC	PDAC input. Each increment in PDAC causes an increase of ~0.10V in VPOS Default Value: X
23 : 0	PERIOD	Period of timer in clk_spcif_timer ticks. For regular FLASH, clock is 36MHz from dedicated oscillator. For FLASH-Lite, clock is same as clk_hf, which must be set to 48MHz for 48MHz devices and 12MHz for max 16MHz devices Default Value: X

22.1.286 SFLASH_EA_P

Erase All - Program Settings

Address: 0x0FFFF1B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	PERIOD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	None				None			
Name	NDAC [31:28]				PDAC [27:24]			

Bits	Name	Description
31 : 28	NDAC	NDAC input. Each increment in NDAC causes an increase of ~0.10V in VNEG Default Value: X
27 : 24	PDAC	PDAC input. Each increment in PDAC causes an increase of ~0.10V in VPOS Default Value: X
23 : 0	PERIOD	Period of timer in clk_spcif_timer ticks. For regular FLASH, clock is 36MHz from dedicated oscillator. For FLASH-Lite, clock is same as clk_hf, which must be set to 48MHz for 48MHz devices and 12MHz for max 16MHz devices Default Value: X

22.1.287 SFLASH_ES_E

Erase Sector - Erase Settings

Address: 0x0FFFF1B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	PERIOD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	None				None			
Name	NDAC [31:28]				PDAC [27:24]			

Bits	Name	Description
31 : 28	NDAC	NDAC input. Each increment in NDAC causes an increase of ~0.10V in VNEG Default Value: X
27 : 24	PDAC	PDAC input. Each increment in PDAC causes an increase of ~0.10V in VPOS Default Value: X
23 : 0	PERIOD	Period of timer in clk_spcif_timer ticks. For regular FLASH, clock is 36MHz from dedicated oscillator. For FLASH-Lite, clock is same as clk_hf, which must be set to 48MHz for 48MHz devices and 12MHz for max 16MHz devices Default Value: X

22.1.288 SFLASH_ES_P_EO

Erase Sector - Program EO Settings

Address: 0x0FFFF1B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	PERIOD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	None				None			
Name	NDAC [31:28]				PDAC [27:24]			

Bits	Name	Description
31 : 28	NDAC	NDAC input. Each increment in NDAC causes an increase of ~0.10V in VNEG Default Value: X
27 : 24	PDAC	PDAC input. Each increment in PDAC causes an increase of ~0.10V in VPOS Default Value: X
23 : 0	PERIOD	Period of timer in clk_spcif_timer ticks. For regular FLASH, clock is 36MHz from dedicated oscillator. For FLASH-Lite, clock is same as clk_hf, which must be set to 48MHz for 48MHz devices and 12MHz for max 16MHz devices Default Value: X

22.1.289 SFLASH_IMO_TRIM_USBMODE_24

USB IMO TRIM 24MHz

Address: 0x0FFFF1BE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TRIM_24 [7:0]							

Bits	Name	Description
7 : 0	TRIM_24	TRIM value for IMO with USB at 24MHz Default Value: X

22.1.290 SFLASH_IMO_TRIM_USBMODE_48

USB IMO TRIM 48MHz

Address: 0x0FFFF1BF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TRIM_24 [7:0]							

Bits	Name	Description
7 : 0	TRIM_24	TRIM value for IMO with USB at 24MHz Default Value: X

22.1.291 SFLASH_IMO_TCTRIM_LT0

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.292 SFLASH_IMO_TCTRIM_LT1

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.293 SFLASH_IMO_TCTRIM_LT2

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.294 SFLASH_IMO_TCTRIM_LT3

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.295 SFLASH_IMO_TCTRIM_LT4

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.296 SFLASH_IMO_TCTRIM_LT5

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.297 SFLASH_IMO_TCTRIM_LT6

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.298 SFLASH_IMO_TCTRIM_LT7

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.299 SFLASH_IMO_TCTRIM_LT8

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.300 SFLASH_IMO_TCTRIM_LT9

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.301 SFLASH_IMO_TCTRIM_LT10

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.302 SFLASH_IMO_TCTRIM_LT11

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.303 SFLASH_IMO_TCTRIM_LT12

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.304 SFLASH_IMO_TCTRIM_LT13

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.305 SFLASH_IMO_TCTRIM_LT14

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.306 SFLASH_IMO_TCTRIM_LT15

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.307 SFLASH_IMO_TCTRIM_LT16

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.308 SFLASH_IMO_TCTRIM_LT17

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.309 SFLASH_IMO_TCTRIM_LT18

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.310 SFLASH_IMO_TCTRIM_LT19

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.311 SFLASH_IMO_TCTRIM_LT20

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.312 SFLASH_IMO_TCTRIM_LT21

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.313 SFLASH_IMO_TCTRIM_LT22

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.314 SFLASH_IMO_TCTRIM_LT23

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.315 SFLASH_IMO_TCTRIM_LT24

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22.1.316 SFLASH_IMO_TRIM_LT0

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.317 SFLASH_IMO_TRIM_LT1

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.318 SFLASH_IMO_TRIM_LT2

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.319 SFLASH_IMO_TRIM_LT3

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.320 SFLASH_IMO_TRIM_LT4

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.321 SFLASH_IMO_TRIM_LT5

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.322 SFLASH_IMO_TRIM_LT6

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.323 SFLASH_IMO_TRIM_LT7

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.324 SFLASH_IMO_TRIM_LT8

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1ED

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.325 SFLASH_IMO_TRIM_LT9

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.326 SFLASH_IMO_TRIM_LT10

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.327 SFLASH_IMO_TRIM_LT11

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.328 SFLASH_IMO_TRIM_LT12

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.329 SFLASH_IMO_TRIM_LT13

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.330 SFLASH_IMO_TRIM_LT14

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.331 SFLASH_IMO_TRIM_LT15

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.332 SFLASH_IMO_TRIM_LT16

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.333 SFLASH_IMO_TRIM_LT17

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.334 SFLASH_IMO_TRIM_LT18

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.335 SFLASH_IMO_TRIM_LT19

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.336 SFLASH_IMO_TRIM_LT20

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.337 SFLASH_IMO_TRIM_LT21

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.338 SFLASH_IMO_TRIM_LT22

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.339 SFLASH_IMO_TRIM_LT23

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.340 SFLASH_IMO_TRIM_LT24

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

22.1.341 SFLASH_CHECKSUM

Boot Checksum

Address: 0x0FFFF1FE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CHECKSUM [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	CHECKSUM [15:8]							

Bits	Name	Description
15 : 0	CHECKSUM	Checksum of fixed data checked during boot. This checksum covers all of rows 1,2,3 of macro 0 + row 3 of macro 1 (except this checksum, and row 3 of macro 1 only if it exists). Default Value: X

23 SPC Interface (SPCIF) Registers

This section discusses the System Performance Controller Interface (SPCIF) registers. It lists all the registers in mapping tables, in address order.

23.1 Register Details

Register Name	Address
SPCIF_GEOMETRY	0x40110000
SPCIF_INTR	0x401107F0
SPCIF_INTR_SET	0x401107F4
SPCIF_INTR_MASK	0x401107F8
SPCIF_INTR_MASKED	0x401107FC

23.1.1 SPCIF_GEOMETRY

Flash/NVL geometry information

Address: 0x40110000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	FLASH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R		R					
HW Access	W		W					
Name	SFLASH [15:14]		FLASH [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	R		R		R			
HW Access	W		W		W			
Name	FLASH_ROW [23:22]		NUM_FLASH [21:20]		SFLASH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	None	None						
Name	DE_CPD_LP	None [30:24]						

Bits	Name	Description
31	DE_CPD_LP	0': SRAM busy wait loop has not been copied. '1': Busy wait loop has been written into SRAM. Default Value: 0
23 : 22	FLASH_ROW	Page size in 64 Byte multiples. This field contains "1" indicating 128 Byte page size. Default Value: Undefined
21 : 20	NUM_FLASH	Number of flash macros. This field contains "0" which indicates 1 flash macro. Default Value: Undefined
19 : 14	SFLASH	Supervisory flash capacity in 256 Byte multiples. This field contains 0x3 for PSoC Analog Coprocessor which has 1KB of supervisory flash. Default Value: Undefined
13 : 0	FLASH	Regular flash capacity in 256 Byte multiples (device dependent). 0x3F: 16KB parts 0x7F: 32KB parts Default Value: Undefined

23.1.2 SPCIF_INTR

SPCIF interrupt request register

Address: 0x401107F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1C
HW Access	None							RW1S
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Timer counter value reaches "0". Set to '1', when event is detected. Write INTR field with '1', to clear bit. Write INTR_SET field with '1', to set bit. Default Value: 0

23.1.3 SPCIF_INTR_SET

SPCIF interrupt set request register

Address: 0x401107F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1S
HW Access	None							A
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Write INTR_SET field with '1' to set corresponding INTR field. Default Value: 0

23.1.4 SPCIF_INTR_MASK

SPCIF interrupt mask register

Address: 0x401107F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Mask for corresponding field in INTR register. Default Value: 0

23.1.5 SPCIF_INTR_MASKED

SPCIF interrupt masked request register

Address: 0x401107FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Logical and of corresponding request and mask fields. Default Value: 0

24 System Resources Sub System Registers

This section discusses the System Resources Sub System (SRSS) registers. It lists all the registers in mapping tables, in address order.

24.1 Register Details

Register Name	Address
PWR_CONTROL	0x40030000
PWR_KEY_DELAY	0x40030004
TST_MODE	0x40030014
CLK_SELECT	0x40030028
CLK_ILO_CONFIG	0x4003002C
CLK_IMO_CONFIG	0x40030030
WDT_DISABLE_KEY	0x40030038
WDT_COUNTER	0x4003003C
WDT_MATCH	0x40030040
SRSS_INTR	0x40030044
SRSS_INTR_SET	0x40030048
SRSS_INTR_MASK	0x4003004C
RES_CAUSE	0x40030054
CLK_IMO_SELECT	0x40030F08
CLK_IMO_TRIM1	0x40030F0C
CLK_IMO_TRIM2	0x40030F10
CLK_IMO_TRIM3	0x40030F18

24.1.1 PWR_CONTROL

Power Mode Control

Address: 0x40030000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R			
HW Access	None		RW	RW	RW			
Name	None [7:6]		LPM_READY	DEBUG_SESSION	POWER_MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	None			R		RW	RW
HW Access	A	None			RW		R	R
Name	EXT_VCCD	None [22:20]			SPARE [19:18]		OVER_TEMP_THRESH	OVER_TEMP_EN

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	EXT_VCCD	Always write 0 except as noted below. Setting this bit turns off the active regulator and will lead to system reset (BOD) unless both Vddd and Vccd pins are supplied externally. This register bit only resets for XRES, POR, or a detected BOD. Default Value: 0
19 : 18	SPARE	Reserved bits Default Value: 0
17	OVER_TEMP_THRESH	Over-temperature threshold. 0: TEMP_HIGH condition occurs between 120C and 125C. 1: TEMP_HIGH condition occurs between 60C and 75C (used for testing). Default Value: 0
16	OVER_TEMP_EN	Enables the die over temperature sensor. Must be enabled when using the TEMP_HIGH interrupt. Default Value: 0

24.1.1 PWR_CONTROL (continued)

5	LPM_READY	Indicates whether the low power mode regulator is ready to enter DEEPSLEEP mode. 0: If DEEPSLEEP mode is requested, device will enter SLEEP mode. When low power regulators are ready, device will automatically enter the originally requested mode. 1: Normal operation. Default Value: 0
4	DEBUG_SESSION	Indicates whether a debug session is active (CDBGPWRUPREQ signal is 1) Default Value: 0 **0x0: NO_SESSION:** No debug session active **0x1: SESSION_ACTIVE:** Debug session is active
3 : 0	POWER_MODE	Current power mode of the device. Note that this field cannot be read in all power modes. Default Value: 0 **0x0: RESET:** RESET state **0x1: ACTIVE:** ACTIVE state **0x2: SLEEP:** SLEEP state **0x3: DEEP_SLEEP:** DEEP_SLEEP state

24.1.2 PWR_KEY_DELAY

Power System Key Register

Address: 0x40030004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay to wait for references to settle on wakeup from deepsleep. BOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. The default assumes the output of the predivider is 48MHz + 3%. Firmware may scale this setting according to the fastest actual clock frequency that can occur when waking from DEEPSLEEP. Default Value: 248

24.1.3 TST_MODE

Test Mode Control Register

Address: 0x40030014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R	None	
HW Access	None					RW	None	
Name	None [7:3]					SWD_CONNECTED	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	R	None	RW	None			
HW Access	R	RW	None	A	None			
Name	TEST_MODE	TEST_KEY_DFT_EN	None	BLOCK_ALT_XRES	None [27:24]			

Bits	Name	Description
31	TEST_MODE	0: Normal operation mode 1: Test mode (any test mode) Setting this bit will prevent BootROM from yielding execution to Flash image. Default Value: 0
30	TEST_KEY_DFT_EN	Reserved bit Default Value: 0
28	BLOCK_ALT_XRES	Relevant only for parts that have the alternate XRES mechanism of overloading a GPIO pin temporarily as alternate XRES during test. When set, this bit blocks the alternate XRES function, such that the pin can be used for normal I/O. This register bit only resets for XRES, POR, or a detected BOD. Default Value: 0
2	SWD_CONNECTED	0: SWD not active 1: SWD activated (Line Reset & Connect sequence passed) Default Value: 0

24.1.4 CLK_SELECT

Clock Select Register

Address: 0x40030028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	SYSCLK_DIV [7:6]		PUMP_SEL [5:4]		HFCLK_DIV [3:2]		HFCLK_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SYSCLK_DIV	Select clk_sys prescaler value. Default Value: 0 **0x0: NO_DIV:** SYSCLK= HFCLK/1 **0x1: DIV_BY_2:** SYSCLK= HFCLK/2 **0x2: DIV_BY_4:** SYSCLK= HFCLK/4 **0x3: DIV_BY_8:** SYSCLK= HFCLK/8
5 : 4	PUMP_SEL	Selects clock source for charge pump clock (AMUX charge pump). This clock is not guaranteed to be glitch free when changing any of its sources or settings. Default Value: 0 **0x0: GND:** No clock, connect to gnd

24.1.4 CLK_SELECT (continued)

		0x1: IMO: Use main IMO output **0x2: HFCLK:** Use HFCLK (using selected source after predivider but before prescaler)
3 : 2	HFCLK_DIV	Selects HFCLK predivider value. Default Value: 2 **0x0: NO_DIV:** Transparent mode, feed through selected clock source w/o dividing. **0x1: DIV_BY_2:** Divide selected clock source by 2 **0x2: DIV_BY_4:** Divide selected clock source by 4 **0x3: DIV_BY_8:** Divide selected clock source by 8
1 : 0	HFCLK_SEL	Selects a source for HFCLK Default Value: 0 **0x0: IMO:** IMO **0x1: EXTCLK:** EXTCLK **0x2: ECO:** Reserved bit - do not use

24.1.5 CLK_ILO_CONFIG

ILO Configuration

Address: 0x4003002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	ENABLE	None [30:24]						

Bits	Name	Description
31	ENABLE	Master enable for ILO oscillator. This bit is hardware set whenever the WD_DISABLE_KEY is not set to the magic value (0xACED8865). Default Value: 1

24.1.6 CLK_IMO_CONFIG

IMO Configuration

Address: 0x40030030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLE	None [30:24]						

Bits	Name	Description
31	ENABLE	Master enable for IMO oscillator. Clearing this bit will disable the IMO. Don't do this if the system is running off it. Default Value: 1

24.1.7 WDT_DISABLE_KEY

Watchdog Disable Key Register

Address: 0x40030038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	KEY [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	KEY [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	KEY [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	KEY [31:24]							

Bits	Name	Description
31 : 0	KEY	Disables WDT reset when equal to 0xACED8865. The WDT reset functions normally for any other setting. Default Value: 0

24.1.8 WDT_COUNTER

Watchdog Counter Register

Address: 0x4003003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	Current value of WDT Counter Default Value: 0

24.1.9 WDT_MATCH

Watchdog Match Register

Address: 0x40030040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	MATCH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	MATCH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				IGNORE_BITS [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	IGNORE_BITS	The number of MSB bits of the watchdog timer that are NOT checked against MATCH. This value provides control over the time-to-reset of the watchdog (which happens after 3 successive matches). Default Value: 0
15 : 0	MATCH	Match value for Watchdog counter. Every time WDT_COUNTER reaches MATCH an interrupt is generated. Two unserviced interrupts will lead to a system reset (i.e. at the third match). Default Value: 4096

24.1.10 SRSS_INTR

SRSS Interrupt Register

Address: 0x40030044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [7:2]						TEMP_HIGH	WDT_MATCH

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Regulator over-temp interrupt. This interrupt can occur when a short circuit exists on the vccd pin or when extreme loads are applied on IO-cells causing the die to overheat. Firmware is encourage to shutdown all IO cells and then go to DeepSleep mode when this interrupt occurs if protection against such conditions is desired. Default Value: 0
0	WDT_MATCH	WDT Interrupt Request. This bit is set each time WDT_COUNTR==WDT_MATCH. Clearing this bit also feeds the watch dog. Missing 2 interrupts in a row will generate brown-out reset. It takes 2 SYSCLK cycles to update after a write 1 to clear. Default Value: 0

24.1.11 SRSS_INTR_SET

SRSS Interrupt Set Register

Address: 0x40030048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	None
HW Access	None						A	None
Name	None [7:2]						TEMP_HIGH	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Writing 1 to this bit internally sets the overtemp interrupt. This can be observed by reading SRSS_INTR.TEMP_HIGH. This bit always reads back as zero. Default Value: 0

24.1.12 SRSS_INTR_MASK

SRSS Interrupt Mask Register

Address: 0x4003004C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						TEMP_HIGH	WDT_MATCH

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Masks REG_OVERTEMP interrupt Default Value: 0
0	WDT_MATCH	Clearing this bit will not forward the interrupt to the CPU. It will not, however, disable the WDT reset generation on 2 missed interrupts. Default Value: 0

24.1.13 RES_CAUSE

Reset Cause Observation Register

Address: 0x40030054

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	None		RW1C
HW Access	None			A	A	None		A
Name	None [7:5]			RESET_SOFT	RESET_PROT_FAULT	None [2:1]		RESET_WDT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESET_SOFT	Cortex-M0 requested a system reset through it's SYSRESETREQ. This can be done via a debugger probe or in firmware. Default Value: 0
3	RESET_PROT_FAULT	A protection violation occurred that requires a RESET. This includes, but is not limited to, hitting a debug breakpoint while in Privileged Mode. Default Value: 0
0	RESET_WDT	A WatchDog Timer reset has occurred since last power cycle. Default Value: 0

24.1.14 CLK_IMO_SELECT

IMO Frequency Select Register

Address: 0x40030F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					FREQ [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	FREQ	Select operating frequency Default Value: 0 **0x0: 24_MHZ:** IMO runs at 24 MHz **0x1: 28_MHZ:** IMO runs at 28 MHz **0x2: 32_MHZ:** IMO runs at 32 MHz **0x3: 36_MHZ:** IMO runs at 36 MHz **0x4: 40_MHZ:** IMO runs at 40 MHz **0x5: 44_MHZ:** IMO runs at 44 MHz **0x6: 48_MHZ:** IMO runs at 48 MHz

24.1.15 CLK_IMO_TRIM1

IMO Trim Register

Address: 0x40030F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	OFFSET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. This field is mapped to the most significant bits of the IMO trim imo_clk_trim[10:3]. The step size of 1 LSB on this field is approximately 120 kHz. Default Value: 128

24.1.16 CLK_IMO_TRIM2

IMO Trim Register

Address: 0x40030F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					RW		
Name	None [7:3]					FSOFFSET [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	FSOFFSET	Frequency trim bits. These bits are not trimmed during manufacturing and kept at 0 under normal operation. This field is mapped to the least significant bits of the IMO trim imo_clk_trim[2:0]. The step size of 1 LSB on this field is approximately 15 kHz. Default Value: 0

24.1.17 CLK_IMO_TRIM3

IMO Trim Register

Address: 0x40030F18

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

25 Timer, Counter, PWM (TCPWM) Registers

This section discusses the Timer, Counter, PWM (TCPWM) registers. It lists all the registers in mapping tables, in address order.

25.1 Register Details

Register Name	Address
TCPWM_CTRL	0x40010000
TCPWM_CMD	0x40010008
TCPWM_INTR_CAUSE	0x4001000C

25.1.1 TCPWM_CTRL

TCPWM control register 0.

Address: 0x40010000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	COUNTER_ENABLED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	COUNTER_ENABLED	Counter enables for counters 0 up to CNT_NR-1. '0': counter disabled. '1': counter enabled. Counter static configuration information (e.g. CTRL.MODE, all TR_CTRL0, TR_CTRL1, and TR_CTRL2 register fields) should only be modified when the counter is disabled. When a counter is disabled, command and status information associated to the counter is cleared by HW, this includes: - the associated counter triggers in the CMD register are set to '0'. - the counter's interrupt cause fields in counter's INTR register. - the counter's status fields in counter's STATUS register.. - the counter's trigger outputs ("tr_overflow", "tr_underflow" and "tr_compare_match"). - the counter's line outputs ("line_out" and "line_compl_out"). Default Value: 0

25.1.2 TCPWM_CMD

TCPWM command register.

Address: 0x40010008

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_CAPTURE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_RELOAD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_STOP [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_START [31:24]							

Bits	Name	Description
31 : 24	COUNTER_START	Counters SW start trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
23 : 16	COUNTER_STOP	Counters SW stop trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
15 : 8	COUNTER_RELOAD	Counters SW reload trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
7 : 0	COUNTER_CAPTURE	Counters SW capture trigger. When written with '1', a capture trigger is generated and the HW sets the field to '0' when the SW trigger has taken effect. It should be noted that the HW operates on the counter frequency. If the counter is disabled through CTRL.COUNTER_ENABLED, the field is immediately set to '0'. Default Value: 0

25.1.3 TCPWM_INTR_CAUSE

TCPWM Counter interrupt cause register.

Address: 0x4001000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	COUNTER_INT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	COUNTER_INT	Counters interrupt signal active. If the counter is disabled through CTRL.COUNTER_ENABLED, the associated interrupt field is immediately set to '0'. Default Value: 0

26 PERI Trigger Group Control Registers

This section discusses the PERI Trigger Group Control (TR_GROUP) registers. It lists all the registers in mapping tables, in address order.

26.1 Register Details

Register Name	Address
PERI_TR_GROUP0_TR_OUT_CTL0	0x40002000
PERI_TR_GROUP0_TR_OUT_CTL1	0x40002004
PERI_TR_GROUP0_TR_OUT_CTL2	0x40002008
PERI_TR_GROUP0_TR_OUT_CTL3	0x4000200C
PERI_TR_GROUP0_TR_OUT_CTL4	0x40002010
PERI_TR_GROUP0_TR_OUT_CTL5	0x40002014
PERI_TR_GROUP0_TR_OUT_CTL6	0x40002018
PERI_TR_GROUP0_TR_OUT_CTL7	0x4000201C
PERI_TR_GROUP1_TR_OUT_CTL0	0x40002200
PERI_TR_GROUP1_TR_OUT_CTL1	0x40002204
PERI_TR_GROUP1_TR_OUT_CTL2	0x40002208
PERI_TR_GROUP1_TR_OUT_CTL3	0x4000220C
PERI_TR_GROUP1_TR_OUT_CTL4	0x40002210
PERI_TR_GROUP1_TR_OUT_CTL5	0x40002214
PERI_TR_GROUP1_TR_OUT_CTL6	0x40002218
PERI_TR_GROUP2_TR_OUT_CTL0	0x40002400
PERI_TR_GROUP2_TR_OUT_CTL1	0x40002404
PERI_TR_GROUP2_TR_OUT_CTL2	0x40002408
PERI_TR_GROUP2_TR_OUT_CTL3	0x4000240C
PERI_TR_GROUP3_TR_OUT_CTL0	0x40002600
PERI_TR_GROUP3_TR_OUT_CTL1	0x40002604
PERI_TR_GROUP3_TR_OUT_CTL2	0x40002608
PERI_TR_GROUP3_TR_OUT_CTL3	0x4000260C
PERI_TR_GROUP4_TR_OUT_CTL0	0x40002800
PERI_TR_GROUP4_TR_OUT_CTL1	0x40002804
PERI_TR_GROUP4_TR_OUT_CTL2	0x40002808
PERI_TR_GROUP4_TR_OUT_CTL3	0x4000280C

Register Name	Address
PERI_TR_GROUP4_TR_OUT_CTL4	0x40002810
PERI_TR_GROUP4_TR_OUT_CTL5	0x40002814
PERI_TR_GROUP4_TR_OUT_CTL6	0x40002818
PERI_TR_GROUP4_TR_OUT_CTL7	0x4000281C
PERI_TR_GROUP4_TR_OUT_CTL8	0x40002820
PERI_TR_GROUP4_TR_OUT_CTL9	0x40002824
PERI_TR_GROUP4_TR_OUT_CTL10	0x40002828
PERI_TR_GROUP4_TR_OUT_CTL11	0x4000282C
PERI_TR_GROUP4_TR_OUT_CTL12	0x40002830
PERI_TR_GROUP4_TR_OUT_CTL13	0x40002834
PERI_TR_GROUP4_TR_OUT_CTL14	0x40002838
PERI_TR_GROUP4_TR_OUT_CTL15	0x4000283C
PERI_TR_GROUP4_TR_OUT_CTL16	0x40002840
PERI_TR_GROUP4_TR_OUT_CTL17	0x40002844
PERI_TR_GROUP4_TR_OUT_CTL18	0x40002848
PERI_TR_GROUP4_TR_OUT_CTL19	0x4000284C
PERI_TR_GROUP4_TR_OUT_CTL20	0x40002850
PERI_TR_GROUP4_TR_OUT_CTL21	0x40002854
PERI_TR_GROUP4_TR_OUT_CTL22	0x40002858
PERI_TR_GROUP4_TR_OUT_CTL23	0x4000285C

26.1.1 PERI_TR_GROUP0_TR_OUT_CTL0

Trigger control register

Address: 0x40002000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.2 PERI_TR_GROUP0_TR_OUT_CTL1

Trigger control register

Address: 0x40002004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.3 PERI_TR_GROUP0_TR_OUT_CTL2

Trigger control register

Address: 0x40002008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.4 PERI_TR_GROUP0_TR_OUT_CTL3

Trigger control register

Address: 0x4000200C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.5 PERI_TR_GROUP0_TR_OUT_CTL4

Trigger control register

Address: 0x40002010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.6 PERI_TR_GROUP0_TR_OUT_CTL5

Trigger control register

Address: 0x40002014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.7 PERI_TR_GROUP0_TR_OUT_CTL6

Trigger control register

Address: 0x40002018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.8 PERI_TR_GROUP0_TR_OUT_CTL7

Trigger control register

Address: 0x4000201C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.9 PERI_TR_GROUP1_TR_OUT_CTL0

Trigger control register

Address: 0x40002200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.10 PERI_TR_GROUP1_TR_OUT_CTL1

Trigger control register

Address: 0x40002204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.11 PERI_TR_GROUP1_TR_OUT_CTL2

Trigger control register

Address: 0x40002208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.12 PERI_TR_GROUP1_TR_OUT_CTL3

Trigger control register

Address: 0x4000220C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.13 PERI_TR_GROUP1_TR_OUT_CTL4

Trigger control register

Address: 0x40002210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.14 PERI_TR_GROUP1_TR_OUT_CTL5

Trigger control register

Address: 0x40002214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.15 PERI_TR_GROUP1_TR_OUT_CTL6

Trigger control register

Address: 0x40002218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.16 PERI_TR_GROUP2_TR_OUT_CTL0

Trigger control register

Address: 0x40002400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.17 PERI_TR_GROUP2_TR_OUT_CTL1

Trigger control register

Address: 0x40002404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.18 PERI_TR_GROUP2_TR_OUT_CTL2

Trigger control register

Address: 0x40002408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.19 PERI_TR_GROUP2_TR_OUT_CTL3

Trigger control register

Address: 0x4000240C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.20 PERI_TR_GROUP3_TR_OUT_CTL0

Trigger control register

Address: 0x40002600

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					SEL [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.21 PERI_TR_GROUP3_TR_OUT_CTL1

Trigger control register

Address: 0x40002604

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					SEL [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.22 PERI_TR_GROUP3_TR_OUT_CTL2

Trigger control register

Address: 0x40002608

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					SEL [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.23 PERI_TR_GROUP3_TR_OUT_CTL3

Trigger control register

Address: 0x4000260C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					SEL [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.24 PERI_TR_GROUP4_TR_OUT_CTL0

Trigger control register

Address: 0x40002800

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.25 PERI_TR_GROUP4_TR_OUT_CTL1

Trigger control register

Address: 0x40002804

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.26 PERI_TR_GROUP4_TR_OUT_CTL2

Trigger control register

Address: 0x40002808

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.27 PERI_TR_GROUP4_TR_OUT_CTL3

Trigger control register

Address: 0x4000280C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.28 PERI_TR_GROUP4_TR_OUT_CTL4

Trigger control register

Address: 0x40002810

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.29 PERI_TR_GROUP4_TR_OUT_CTL5

Trigger control register

Address: 0x40002814

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.30 PERI_TR_GROUP4_TR_OUT_CTL6

Trigger control register

Address: 0x40002818

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.31 PERI_TR_GROUP4_TR_OUT_CTL7

Trigger control register

Address: 0x4000281C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.32 PERI_TR_GROUP4_TR_OUT_CTL8

Trigger control register

Address: 0x40002820

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.33 PERI_TR_GROUP4_TR_OUT_CTL9

Trigger control register

Address: 0x40002824

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.34 PERI_TR_GROUP4_TR_OUT_CTL10

Trigger control register

Address: 0x40002828

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.35 PERI_TR_GROUP4_TR_OUT_CTL11

Trigger control register

Address: 0x4000282C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.36 PERI_TR_GROUP4_TR_OUT_CTL12

Trigger control register

Address: 0x40002830

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.37 PERI_TR_GROUP4_TR_OUT_CTL13

Trigger control register

Address: 0x40002834

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.38 PERI_TR_GROUP4_TR_OUT_CTL14

Trigger control register

Address: 0x40002838

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.39 PERI_TR_GROUP4_TR_OUT_CTL15

Trigger control register

Address: 0x4000283C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.40 PERI_TR_GROUP4_TR_OUT_CTL16

Trigger control register

Address: 0x40002840

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.41 PERI_TR_GROUP4_TR_OUT_CTL17

Trigger control register

Address: 0x40002844

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.42 PERI_TR_GROUP4_TR_OUT_CTL18

Trigger control register

Address: 0x40002848

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.43 PERI_TR_GROUP4_TR_OUT_CTL19

Trigger control register

Address: 0x4000284C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.44 PERI_TR_GROUP4_TR_OUT_CTL20

Trigger control register

Address: 0x40002850

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.45 PERI_TR_GROUP4_TR_OUT_CTL21

Trigger control register

Address: 0x40002854

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.46 PERI_TR_GROUP4_TR_OUT_CTL22

Trigger control register

Address: 0x40002858

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

26.1.47 PERI_TR_GROUP4_TR_OUT_CTL23

Trigger control register

Address: 0x4000285C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typicallu connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

27 UAB Registers

This section discusses the UAB registers. It lists all the registers in mapping tables, in address order.

27.1 Register Details

Register Name	Address
UAB_UAB_CTRL	0x40340000
UAB_INTR	0x40340020
UAB_INTR_SET	0x40340024
UAB_INTR_MASK	0x40340028
UAB_INTR_MASKED	0x4034002C
UAB_OA0_CTRL	0x40340200
UAB_CAP_CTRL0	0x40340204
UAB_CAP_ABCF0_VAL	0x40340208
UAB_CAP_AB0_VAL_NXT	0x4034020C
UAB_CAP_CF0_VAL_NXT	0x40340210
UAB_STARTUP_DELAY0	0x40340220
UAB_SUBSAMPLE_CTRL0	0x40340224
UAB_SW_STATIC0	0x40340230
UAB_SW_MODBIT_SRC0	0x40340234
UAB_SW_CA0_IN0	0x40340240
UAB_SW_CA0_IN1	0x40340244
UAB_SW_CA0_TOP	0x40340248
UAB_SW_CB0_IN0	0x40340250
UAB_SW_CB0_IN1	0x40340254
UAB_SW_CB0_TOP	0x40340258
UAB_SW_CC0_IN0	0x40340260
UAB_SW_CC0_IN1	0x40340264
UAB_SW_CC0_TOP	0x40340268
UAB_SW_CF0_BOT	0x4034026C
UAB_SW_OTHER0	0x40340270
UAB_SW_BOOST_CTRL0	0x40340274
UAB_SRAM0_CTRL	0x40340278

Register Name	Address
UAB_STAT0	0x4034027C
UAB_SRAM00	0x40340280
UAB_SRAM01	0x40340284
UAB_SRAM02	0x40340288
UAB_SRAM03	0x4034028C
UAB_SRAM04	0x40340290
UAB_SRAM05	0x40340294
UAB_SRAM06	0x40340298
UAB_SRAM07	0x4034029C
UAB_SRAM08	0x403402A0
UAB_SRAM09	0x403402A4
UAB_SRAM010	0x403402A8
UAB_SRAM011	0x403402AC
UAB_SRAM012	0x403402B0
UAB_SRAM013	0x403402B4
UAB_SRAM014	0x403402B8
UAB_SRAM015	0x403402BC
UAB_OA1_CTRL	0x40340300
UAB_CAP_CTRL1	0x40340304
UAB_CAP_ABCF1_VAL	0x40340308
UAB_CAP_AB1_VAL_NXT	0x4034030C
UAB_CAP_CF1_VAL_NXT	0x40340310
UAB_STARTUP_DELAY1	0x40340320
UAB_SUBSAMPLE_CTRL1	0x40340324
UAB_SW_STATIC1	0x40340330
UAB_SW_MODBIT_SRC1	0x40340334
UAB_SW_CA1_IN0	0x40340340
UAB_SW_CA1_IN1	0x40340344
UAB_SW_CA1_TOP	0x40340348
UAB_SW_CB1_IN0	0x40340350
UAB_SW_CB1_IN1	0x40340354
UAB_SW_CB1_TOP	0x40340358
UAB_SW_CC1_IN0	0x40340360
UAB_SW_CC1_IN1	0x40340364
UAB_SW_CC1_TOP	0x40340368
UAB_SW_CF1_BOT	0x4034036C
UAB_SW_OTHER1	0x40340370
UAB_SW_BOOST_CTRL1	0x40340374
UAB_SRAM1_CTRL	0x40340378
UAB_STAT1	0x4034037C
UAB_SRAM10	0x40340380
UAB_SRAM11	0x40340384

Register Name	Address
UAB_SRAM12	0x40340388
UAB_SRAM13	0x4034038C
UAB_SRAM14	0x40340390
UAB_SRAM15	0x40340394
UAB_SRAM16	0x40340398
UAB_SRAM17	0x4034039C
UAB_SRAM18	0x403403A0
UAB_SRAM19	0x403403A4
UAB_SRAM110	0x403403A8
UAB_SRAM111	0x403403AC
UAB_SRAM112	0x403403B0
UAB_SRAM113	0x403403B4
UAB_SRAM114	0x403403B8
UAB_SRAM115	0x403403BC
UAB_DECM_CTRL	0x40340400
UAB_DC0_CTRL	0x40340404
UAB_DC0_TRIG	0x40340408
UAB_DC0_OVR	0x4034040C
UAB_DC0_A0	0x40340410
UAB_DC0_A1	0x40340414
UAB_DC0_DEC_CNT	0x40340418
UAB_DC0_TMP	0x4034041C
UAB_DC0_D0	0x40340420
UAB_DC0_D1	0x40340424
UAB_DC0_RES	0x40340428
UAB_DC1_CTRL	0x40340434
UAB_DC1_TRIG	0x40340438
UAB_DC1_OVR	0x4034043C
UAB_DC1_A0	0x40340440
UAB_DC1_A1	0x40340444
UAB_DC1_DEC_CNT	0x40340448
UAB_DC1_TMP	0x4034044C
UAB_DC1_D0	0x40340450
UAB_DC1_D1	0x40340454
UAB_DC1_RES	0x40340458
UAB_CAP_TRIM0	0x40340F00
UAB_CAP_TRIM1	0x40340F04
UAB_OA_TRIM0	0x40340F08
UAB_OA_TRIM1	0x40340F0C

27.1.1 UAB_UAB_CTRL

Global UAB control

Address: 0x40340000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLED	None [30:24]						

Bits	Name	Description
31	ENABLED	- 0: UAB disabled (put analog in power down, open all switches) - 1: UAB enabled Default Value: 0

27.1.2 UAB_INTR

Interrupt request register

Address: 0x40340020

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [7:3]					DC0_RES	VDAC0_EMPTY	COMP0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [23:19]					DC1_RES	VDAC1_EMPTY	COMP1

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	DC1_RES	Decimator 1 Result Interrupt: hardware sets this interrupt when Decimator 1 writes a new result value in DC1_RES register. Write with '1' to clear bit. Default Value: 0
17	VDAC1_EMPTY	VDAC 1 Interrupt: hardware sets this interrupt when VDAC 1 next value field is empty. Write with '1' to clear bit. Default Value: 0
16	COMP1	Comparator 1 Interrupt: hardware sets this interrupt when comparator 1 triggers. Write with '1' to clear bit. Default Value: 0
2	DC0_RES	Decimator 0 Result Interrupt: hardware sets this interrupt when Decimator 0 writes a new result value in DC0_RES register. Write with '1' to clear bit. Default Value: 0
1	VDAC0_EMPTY	VDAC 0 Interrupt: hardware sets this interrupt when VDAC 0 next value field is empty. Write with '1' to clear bit. Default Value: 0

27.1.2 UAB_INTR (continued)

0	COMP0	Comparator 0 Interrupt: hardware sets this interrupt when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

27.1.3 UAB_INTR_SET

Interrupt request set register

Address: 0x40340024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [7:3]					DC0_RES_SET	VDAC0_EMPTY_SET	COMP0_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [23:19]					DC1_RES_SET	VDAC1_EMPTY_SET	COMP1_SET

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	DC1_RES_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
17	VDAC1_EMPTY_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
16	COMP1_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	DC0_RES_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	VDAC0_EMPTY_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	COMP0_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

27.1.4 UAB_INTR_MASK

Interrupt request mask

Address: 0x40340028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [7:3]					DC0_RES_MASK	VDAC0_EMPTY_MASK	COMP0_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [23:19]					DC1_RES_MASK	VDAC1_EMPTY_MASK	COMP1_MASK

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	DC1_RES_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
17	VDAC1_EMPTY_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
16	COMP1_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	DC0_RES_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	VDAC0_EMPTY_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	COMP0_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

27.1.5 UAB_INTR_MASKED

Interrupt request masked

Address: 0x4034002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [7:3]					DC0_RES_MASKED	VDAC0_EMPTY_MASKED	COMP0_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [23:19]					DC1_RES_MASKED	VDAC1_EMPTY_MASKED	COMP1_MASKED

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18	DC1_RES_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
17	VDAC1_EMPTY_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
16	COMP1_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
2	DC0_RES_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
1	VDAC0_EMPTY_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	COMP0_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

27.1.6 UAB_OA0_CTRL

Opamp, comparator, buffer controls

Address: 0x40340200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					OA0_PWR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW		None	RW		
HW Access	R	R	R		None	R		
Name	CTRL0_SPARE	CMP0_DSI_LEVEL	CMP0_EDGE [13:12]		None	CMP0_PWR [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW			RW	RW		
HW Access	R	R			R	R		
Name	AGND0_PTS	AGND0_PWR [22:20]			REF0_PTS	REF0_PWR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	H0_PWR [31:30]		None [29:26]				SPARE0_EN	SW_GG

Bits	Name	Description
31 : 30	H0_PWR	UAB Half, power profile Default Value: 0 **0x0: NORMAL:** Normal, for normal analog clock speeds **0x1: ULTRA_LOW:** Ultra low power, only allowed for lower analog clock speeds **0x2: ULTRA_HIGH:** Ultra high performance, for higher analog clock speeds (also ultra high power) **0x3: Reserved:** Reserved, do not use
25	SPARE0_EN	1 - Enable spare reference Default Value: 0

27.1.6 UAB_OA0_CTRL (continued)

24	SW_GG	Connect outputs of Agnd0 and Agnd1 buffer, one buffer must be off. This is to drive both UAB halves with the same buffer, so both halves get the same offset noise. Default Value: 0
23	AGND0_PTS	1 - Pull Agnd0 buffer output to VDDA Default Value: 0
22 : 20	AGND0_PWR	Agnd0 buffer power level Default Value: 0
19	REF0_PTS	1- Pull the Reference0 buffer output to VDDA Default Value: 0
18 : 16	REF0_PWR	Reference0 buffer power level Default Value: 0
15	CTRL0_SPARE	Reserved, do not use Default Value: 0
14	CMP0_DSI_LEVEL	Comparator0 output: 0=pulse, 1=level Default Value: 0
13 : 12	CMP0_EDGE	Comparator0 edge detect for output and interrupt Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
10 : 8	CMP0_PWR	Comparator0 power level Default Value: 0
2 : 0	OA0_PWR	Opamp0 power level Default Value: 0

27.1.7 UAB_CAP_CTRL0

Capacitance controls

Address: 0x40340204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	None				
HW Access	None	R	R	None				
Name	None	CC0_GND	CB0_GND	None [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	None			
HW Access	R		R	R	None			
Name	DAC0_MODE [31:30]		DAC0_MODE_EN	FRC0_SIGN_BIT	None [27:24]			

Bits	Name	Description
31 : 30	DAC0_MODE	DAC mode, this determines the AB Cap Value decoding Default Value: 0 **0x0: UNSIGNED12:** Off or Unsigned 12-bit VDAC, i.e. no AB Cap value decoding. SIGN1_VAL can be used as Firmware controlled modbit (e.g. to invert the Voltage for a Sign + Magnitude VDAC) **0x1: VIRT_SIGNED12:** Virtual signed 12-bits' VDAC. AB Cap value decoding: add 0x800 to the 12-bit AB Cap Value (=invert MSB), to convert the lowest signed number 0x800 to the lowest unsigned number 0x000. This is the same as the SAR handles 12-bit 'virtual' signed numbers.

27.1.7 UAB_CAP_CTRL0 (continued)

		0x2: SIGNED13: Signed 13-bit twos complement. AB Cap value decoding: for negative values (SIGN0_VAL=1) the AB Cap values are inverted, the 64th B cap unit is enabled and the Voltage should be inverted. - Voltage inversion only works if the right clocking waveforms, switch settings and reference voltages are used. - Enabling the 64th B cap unit adds 1 so that only a AB Cap value inversion is needed to create a true twos complement. **0x3: RESERVED:**
29	DAC0_MODE_EN	0: SIGN0_VAL can be programmed to be a modbit source 1: SIGN0_VAL is a dedicated sign bit (FW modbit source tied to 0) Default Value: 0
28	FRC0_SIGN_BIT	Forces the sign bit to be 1 in DAC mode. This is used to achieve 0 - Vref range for unsigned numbers using DAC mode 2 Default Value: 0
6	CC0_GND	Ground unused caps of CC0 array 0: leave unused caps floating 1: ground unused caps (typical when attentuation Cap is used) Default Value: 0
5	CB0_GND	Ground unused caps of CB0 array 0: leave unused caps floating 1: ground unused caps (typical when attentuation Cap is used, e.g. for VDAC use-case) Default Value: 0

27.1.8 UAB_CAP_ABCF0_VAL

Capacitance values for CA0, CB0, CC0 and CF0

Address: 0x40340208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW					
HW Access	RW		RW					
Name	CA0_VAL [7:6]		CB0_VAL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	RW			
HW Access	None		R	RW	RW			
Name	None [15:14]		CB0_64	SIGN0_VAL	CA0_VAL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW					
HW Access	None		RW					
Name	None [23:22]		CC0_VAL [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW				
HW Access	None			RW				
Name	None [31:29]			CF0_VAL [28:24]				

Bits	Name	Description
28 : 24	CF0_VAL	Cap F0 Value [2..64 is the range in steps of 2] Default Value: 0
21 : 16	CC0_VAL	Cap C0 Value Default Value: 0
13	CB0_64	Enable 64th Cap of CB0 array. In DAC mode the FW setting is overridden by the hardware based on DAC_MODE setting. 1 - Enables the 64th cap. This will also set CB0_val[5:0] to be 6'h3F Default Value: 0
12	SIGN0_VAL	Sign bit Value, when used in DAC_MODE, otherwise Firmware modbit. The MODBIT0_SRC0/1_SEL needs to be set to 31 to select this bit as a firmware modbit. In DAC_MODE the modbit should be used to invert the voltage on the AB Caps for the negative DAC values. Default Value: 0
11 : 6	CA0_VAL	Cap A0 Value, in DAC_MODE 1 and 2 this value is decoded Default Value: 0
5 : 0	CB0_VAL	Cap B0 Value, in DAC_MODE 1 and 2 this value is decoded Default Value: 0

27.1.9 UAB_CAP_AB0_VAL_NXT

Next capacitance values for CA0 and CB0

Address: 0x4034020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW					
HW Access	R		R					
Name	CA0_VAL [7:6]		CB0_VAL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW			
HW Access	None			R	R			
Name	None [15:13]			SIGN0_VAL	CA0_VAL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
12	SIGN0_VAL	Sign bit Value Default Value: 0
11 : 6	CA0_VAL	Cap A0 Value Default Value: 0
5 : 0	CB0_VAL	Cap B0 Value Default Value: 0

27.1.10 UAB_CAP_CF0_VAL_NXT

Next capacitance values for CC0 and CF0

Address: 0x40340210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW					
HW Access	None		R					
Name	None [23:22]		CC0_VAL [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None	RW				
HW Access	R	R	None	R				
Name	CF0_VAL_UPDATE	CC0_VAL_UPDATE	None	CF0_VAL [28:24]				

Bits	Name	Description
31	CF0_VAL_UPDATE	1 - Update the CF0 cap value with CAP_CF0_VAL_NXT.CF0_VAL Default Value: 0
30	CC0_VAL_UPDATE	1 - Update the CC0 cap value with CAP_CC0_VAL_NXT.CC0_VAL Default Value: 0
28 : 24	CF0_VAL	Cap F0 Value Default Value: 0
21 : 16	CC0_VAL	Cap C0 Value Default Value: 0

27.1.11 UAB_STARTUP_DELAY0

Startup delay

Address: 0x40340220

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	STARTUP_DELAY [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	STARTUP_DELAY [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							ALIGN_MODE

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	ALIGN_MODE	0 STARTUP_DELAY is number of clk_hf clocks to delay the UAB clock after a SAR Trigger for UAB-SAR alignment in scheduled mode 1 - STARTUP_DELAY is number of clk_hf clocks to delay UAB trigger to SAR for UAB-SAR alignment in unscheduled mode Default Value: 0
15 : 0	STARTUP_DELAY	Startup delay to synchronize the UAB-SAR interface. The usage and meaning of this field depends on the value of the ALIGN_MODE bit (below). A value of 0 disables this function. Default Value: 0

27.1.12 UAB_SUBSAMPLE_CTRL0

Subsample control

Address: 0x40340224

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SUBSAMPLE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	SUBSAMPLE_INIT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	SUBSAMPLE_INIT	Initial value of the subsampling down counter. Before this UAB half is running the firmware can write to this field the initial value of the subsample down counter. It is recommend that the following is true for the initial value SUBSAMPLE_INIT<=SUBSAMPLE, however this is not a requirement. Writing a bigger value can be used to postpone the very first Valid output. Default Value: 0
7 : 0	SUBSAMPLE	Subsampling: suppress Valid output during the first SUBSAMPLE analog clock periods. Only allow Valid output in the last of the SUBSAMPLE+1 analog clock periods. A value of 0 will not suppress Valid output. Default Value: 0

27.1.13 UAB_SW_STATIC0

Static switches for half 0 of the UAB

Address: 0x40340230

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SW_G0G	SW_R0G	SW_G03	SW_G02	SW_G01	SW_G00

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		EARLY_P0O	EARLY_P0S	None	SW_Q0T	SW_G0T	SW_R0T

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				RMB0_BITS [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW	RW				
HW Access	None		R	R				
Name	None [31:30]		STRB_RST0_EN	STRB_RST0_SEL [28:24]				

Bits	Name	Description
29	STRB_RST0_EN	Enable VDAC strobe or UAB analog-reset: 0: Use selected source as VDAC strobe for next CA0 and CB0 values 1: Use selected source as Analog-reset (discharge all Caps) Default Value: 0
28 : 24	STRB_RST0_SEL	Select source either for VDAC strobe or analog-reset to discharge all Caps (Delsig Modulator use-case) 0 = Decimator0 half 0 analog-reset output 1 = Decimator0 half 1 analog-reset output 8-13 = generic trigger input 0-5 Default Value: 0
19 : 16	RMB0_BITS	Risk mitigation bits (To be defined if they are used) Default Value: 0
13	EARLY_P0O	OUT0 to VOUT0 switch timing: 0=Regular, 1=Early Default Value: 0

27.1.13 UAB_SW_STATIC0 (continued)

12	EARLY_P0S	OUT0 to Sum0 switch timing: 0=Regular, 1=Early Default Value: 0
10	SW_Q0T	OUT1 to cmp0.vminus (Threshold) Default Value: 0
9	SW_G0T	AGND0 to cmp0.vminus (Threshold) Default Value: 0
8	SW_R0T	REF0 to cmp0.vminus (Threshold) Default Value: 0
5	SW_G0G	AGND0 to OA0.vplus (AG0) Default Value: 0
4	SW_R0G	REF0 to OA0.vplus (AG0) Default Value: 0
3	SW_G03	VIN03 to OA0.vplus (AG0) Default Value: 0
2	SW_G02	VIN02 to OA0.vplus (AG0) Default Value: 0
1	SW_G01	VIN01 to OA0.vplus (AG0) Default Value: 0
0	SW_G00	VIN00 to OA0.vplus (AG0) Default Value: 0

27.1.14 UAB_SW_MODBIT_SRC0

Select source of Modbit for A,B and C branches of half 0

Address: 0x40340234

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			MODBIT0_SRC0_SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			MODBIT1_SRC0_SEL [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
12 : 8	MODBIT1_SRC0_SEL	Select source of modbit for C branch 0=UAB0 half 0 comparator output 1=UAB0 half 1 comparator output 8-13 = generic trigger inputs 0-5 31=SIGN0_VAL, also used as Firmware modbit. (In VDAC use-case this should invert the voltage on the AB Cap) Default Value: 0
4 : 0	MODBIT0_SRC0_SEL	Select source of modbit for A & B branches 0=UAB0 half 0 comparator output 1=UAB0 half 1 comparator output 8-13 = generic trigger inputs 0-5 31=SIGN0_VAL, also used as Firmware modbit. (In VDAC use-case this should invert the voltage on the AB Cap) Default Value: 0

27.1.15 UAB_SW_CA0_IN0

Cap A0 input switches set 0

Address: 0x40340240

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A01_CMP [7:4]				SW_A00_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A03_CMP [15:12]				SW_A02_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A0Q [23:20]				SW_A0P [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_A0Q	OUT1 to Cap A0 input Default Value: 0
19 : 16	SW_A0P	OUT0 to Cap A0 input Default Value: 0
15 : 12	SW_A03_CMP	VIN03 to Cap A0 input, allows for modbit control Default Value: 0
11 : 8	SW_A02_CMP	VIN02 to Cap A0 input, allows for modbit control Default Value: 0
7 : 4	SW_A01_CMP	VIN01 to Cap A0 input, allows for modbit control Default Value: 0
3 : 0	SW_A00_CMP	VIN00 to Cap A0 input, allows for modbit control Default Value: 0

27.1.16 UAB_SW_CA0_IN1

Cap A0 input switches set 1

Address: 0x40340244

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A0R_CMP [7:4]				SW_AA [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A0V_CMP [15:12]				SW_A0G_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_A0V_CMP	VSS to Cap A0 input, allows for modbit control Default Value: 0
11 : 8	SW_A0G_CMP	AGND0 to Cap A0 input, allows for modbit control Default Value: 0
7 : 4	SW_A0R_CMP	REF0 to Cap A0 input, allows for modbit control Default Value: 0
3 : 0	SW_AA	Cap A0 input to Cap A1 input Default Value: 0

27.1.17 UAB_SW_CA0_TOP

Cap A0 top plate switches

Address: 0x40340248

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_G0A_CMP [7:4]				SW_R0A_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SW_V0A_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				SW_S0A [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	SW_S0A	Cap A0 top plate to SUM0 Default Value: 0
11 : 8	SW_V0A_CMP	Cap A0 top plate to VSS, allows for modbit control Default Value: 0
7 : 4	SW_G0A_CMP	Cap A0 top plate to AGND0, allows for modbit control Default Value: 0
3 : 0	SW_R0A_CMP	Cap A0 top plate to REF0, allows for modbit control Default Value: 0

27.1.18 UAB_SW_CB0_IN0

Cap B0 input switches set 0

Address: 0x40340250

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B01_CMP [7:4]				SW_B00_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B03_CMP [15:12]				SW_B02_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B0Q [23:20]				SW_B0P [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_B0Q	OUT1 to Cap B0 input Default Value: 0
19 : 16	SW_B0P	OUT0 to Cap B0 input Default Value: 0
15 : 12	SW_B03_CMP	VIN03 to Cap B0 input, allows for modbit control Default Value: 0
11 : 8	SW_B02_CMP	VIN02 to Cap B0 input, allows for modbit control Default Value: 0
7 : 4	SW_B01_CMP	VIN01 to Cap B0 input, allows for modbit control Default Value: 0
3 : 0	SW_B00_CMP	VIN00 to Cap B0 input, allows for modbit control Default Value: 0

27.1.19 UAB_SW_CB0_IN1

Cap B0 input switches set 1

Address: 0x40340254

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B0R_CMP [7:4]				SW_BB [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B0V_CMP [15:12]				SW_B0G_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_B0V_CMP	VSS to Cap B0 input, allows for modbit control Default Value: 0
11 : 8	SW_B0G_CMP	AGND0 to Cap B0 input, allows for modbit control Default Value: 0
7 : 4	SW_B0R_CMP	REF0 to Cap B0 input, allows for modbit control Default Value: 0
3 : 0	SW_BB	Cap B0 input to Cap B1 input (Note: In the UAB design this is called the BM switch) Default Value: 0

27.1.20 UAB_SW_CB0_TOP

Cap A0 top plate switches

Address: 0x40340258

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_G0B_CMP [7:4]				SW_R0B_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_T0B [15:12]				SW_V0B_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				SW_S0B [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	SW_S0B	Cap B0 top plate to SUM0 Default Value: 0
15 : 12	SW_T0B	Cap B0 top plate Trim/Attenuation bypass Default Value: 0
11 : 8	SW_V0B_CMP	Cap B0 top plate to VSS, allows for modbit control Default Value: 0
7 : 4	SW_G0B_CMP	Cap B0 top plate to AGND0, allows for modbit control Default Value: 0
3 : 0	SW_R0B_CMP	Cap B0 top plate to REF0, allows for modbit control Default Value: 0

27.1.21 UAB_SW_CC0_IN0

Cap C0 input switches set 0

Address: 0x40340260

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C01_CMP [7:4]				SW_C00_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C03_CMP [15:12]				SW_C02_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C0Q [23:20]				SW_C0P [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_C0Q	OUT1 to Cap C0 input Default Value: 0
19 : 16	SW_C0P	OUT0 to Cap C0 input Default Value: 0
15 : 12	SW_C03_CMP	VIN03 to Cap C0 input, allows for modbit control Default Value: 0
11 : 8	SW_C02_CMP	VIN02 to Cap C0 input, allows for modbit control Default Value: 0
7 : 4	SW_C01_CMP	VIN01 to Cap C0 input, allows for modbit control Default Value: 0
3 : 0	SW_C00_CMP	VIN00 to Cap C0 input, allows for modbit control Default Value: 0

27.1.22 UAB_SW_CC0_IN1

Cap C0 input switches set 1

Address: 0x40340264

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C0R_CMP [7:4]				SW_CC [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C0V_CMP [15:12]				SW_C0G_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_C0V_CMP	VSS to Cap C0 input, allows for modbit control Default Value: 0
11 : 8	SW_C0G_CMP	AGND0 to Cap C0 input, allows for modbit control Default Value: 0
7 : 4	SW_C0R_CMP	REF0 to Cap C0 input, allows for modbit control Default Value: 0
3 : 0	SW_CC	Cap C0 input to Cap C1 input Default Value: 0

27.1.23 UAB_SW_CC0_TOP

Cap A0 top plate switches

Address: 0x40340268

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_G0C_CMP [7:4]				SW_R0C_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_T0C [15:12]				SW_V0C_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_S10 [23:20]				SW_S0C [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_S10	Cap C0 top plate to SUM1 Default Value: 0
19 : 16	SW_S0C	Cap C0 top plate to SUM0 Default Value: 0
15 : 12	SW_T0C	Cap C0 top plate Trim/Attenuation bypass Default Value: 0
11 : 8	SW_V0C_CMP	Cap C0 top plate to VSS, allows for modbit control Default Value: 0
7 : 4	SW_G0C_CMP	Cap C0 top plate to AGND0, allows for modbit control Default Value: 0
3 : 0	SW_R0C_CMP	Cap C0 top plate to REF0, allows for modbit control Default Value: 0

27.1.24 UAB_SW_CF0_BOT

Cap F0 bottom plate and output switches

Address: 0x4034026C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_P0F [7:4]				SW_G0F [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_P0O [15:12]				SW_P0S [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_P0O	OUT0 to VOUT0 Default Value: 0
11 : 8	SW_P0S	Cap F bypass, OUT0 to SUM0 Default Value: 0
7 : 4	SW_P0F	Cap F0 bottom plate to OUT0 Default Value: 0
3 : 0	SW_G0F	Cap F0 bottom plate to AGND0 Default Value: 0

27.1.25 UAB_SW_OTHER0

Other clocked controls

Address: 0x40340270

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	VALID0 [7:4]				CMP0_FF [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				TRIG0_OUT [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	R				R			
Name	STROBE_RST0 [31:28]				STROBE_SW0 [27:24]			

Bits	Name	Description
31 : 28	STROBE_RST0	Use the positive edge of the selected clocking waveform to synchronize: STRB_RST0_EN=0: Capacitor Value update (Capacitor Strobe) STRB_RST0_EN=1: UAB analog-reset update Set to 0 to disable both functions. Result undefined for value 15. Default Value: 0
27 : 24	STROBE_SW0	Strobe for dsi_sw_ctrl (modbit) update, dsi_sw_ctrl updates in sync with posedge of this wave. To disable set to 0. To enable update anytime use 15. Default Value: 0
11 : 8	TRIG0_OUT	Trigger output (for other UABs or SAR) Default Value: 0
7 : 4	VALID0	Valid0, output flag to indicated that VOUT0 is valid. The Valid output can be suppressed due to sub-sampling. Note that when sub-sampling is used this clocking waveform is used to decrement the counter (decrement is aligned with the positive edge of this clocking waveform). Default Value: 0
3 : 0	CMP0_FF	Clock for Flip-Flop after Comparator 0 Default Value: 0

27.1.26 UAB_SW_BOOST_CTRL0

Bootstrap clock control

Address: 0x40340274

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	CB0_BOOST [7:4]				CA0_BOOST [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	CF0_BOOST [15:12]				CC0_BOOST [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	PUMP0_WAVE [23:20]				SUM0_BOOST [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	PUMP0_WAVE	Clock for pump in half0 Default Value: 0
19 : 16	SUM0_BOOST	Clock for boot strap master in Summing node branch Default Value: 0
15 : 12	CF0_BOOST	Clock for boot strap master in F branch Default Value: 0
11 : 8	CC0_BOOST	Clock for boot strap master in C branch Default Value: 0
7 : 4	CB0_BOOST	Clock for boot strap master in B branch Default Value: 0
3 : 0	CA0_BOOST	Clock for boot strap master in A branch Default Value: 0

27.1.27 UAB_SRAM0_CTRL

SRAM programmed size

Address: 0x40340278

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LAST_STEP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW				
HW Access	R	None	R	R				
Name	RUN	None	TRIGGER_EN	TRIG_SEL0 [28:24]				

Bits	Name	Description
31	RUN	Set to start executing the waveform. Trigger is required if TRIGGER_EN is set to 1. Clear to stop this UAB half. When RUN=0 all dynamic switches are forced open. Default Value: 0
29	TRIGGER_EN	Enable input trigger: 0: Ignore triggers, start running immediately after setting RUN bit 1: After RUN bit is set wait for a positive edge on the selected trigger input Default Value: 0
28 : 24	TRIG_SEL0	input Trigger select 0=UAB0 half 0 trigger output 1=UAB0 half 1 trigger output 8-13 = generic trigger inputs 0-5 31=SAR trigger output Default Value: 0
3 : 0	LAST_STEP	Last step of wave programmed in the SRAM Default Value: 0

27.1.28 UAB_STAT0

Status Current SRAM counter and comparator

Address: 0x4034027C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	R			
HW Access	None			RW	RW			
Name	None [7:5]			COMP	CURR_STEP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	RW							
Name	CURR_SUBSAMPLE [31:24]							

Bits	Name	Description
31 : 24	CURR_SUBSAMPLE	Current value of the subsampling down counter. The Valid is suppressed when SUBSAMPLE_CUR!=0. Default Value: 0
4	COMP	Current comparator status Default Value: 0
3 : 0	CURR_STEP	Current step executed from the SRAM Default Value: 0

27.1.29 UAB_SRAM00

Waveform SRAM for half 0 of the UAB

Address: 0x40340280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.30 UAB_SRAM01

Waveform SRAM for half 0 of the UAB

Address: 0x40340284

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.31 UAB_SRAM02

Waveform SRAM for half 0 of the UAB

Address: 0x40340288

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.32 UAB_SRAM03

Waveform SRAM for half 0 of the UAB

Address: 0x4034028C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.33 UAB_SRAM04

Waveform SRAM for half 0 of the UAB

Address: 0x40340290

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.34 UAB_SRAM05

Waveform SRAM for half 0 of the UAB

Address: 0x40340294

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.35 UAB_SRAM06

Waveform SRAM for half 0 of the UAB

Address: 0x40340298

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.36 UAB_SRAM07

Waveform SRAM for half 0 of the UAB

Address: 0x4034029C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.37 UAB_SRAM08

Waveform SRAM for half 0 of the UAB

Address: 0x403402A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.38 UAB_SRAM09

Waveform SRAM for half 0 of the UAB

Address: 0x403402A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.39 UAB_SRAM010

Waveform SRAM for half 0 of the UAB

Address: 0x403402A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.40 UAB_SRAM011

Waveform SRAM for half 0 of the UAB

Address: 0x403402AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.41 UAB_SRAM012

Waveform SRAM for half 0 of the UAB

Address: 0x403402B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.42 UAB_SRAM013

Waveform SRAM for half 0 of the UAB

Address: 0x403402B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.43 UAB_SRAM014

Waveform SRAM for half 0 of the UAB

Address: 0x403402B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.44 UAB_SRAM015

Waveform SRAM for half 0 of the UAB

Address: 0x403402BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.45 UAB_OA1_CTRL

Opamp, comparator, buffer controls

Address: 0x40340300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					OA1_PWR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW		None	RW		
HW Access	R	R	R		None	R		
Name	CTRL1_SPARE	CMP1_DSI_LEVEL	CMP1_EDGE [13:12]		None	CMP1_PWR [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW			RW	RW		
HW Access	R	R			R	R		
Name	AGND1_PTS	AGND1_PWR [22:20]			REF1_PTS	REF1_PWR [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	H1_PWR [31:30]		None [29:26]				SPARE1_EN	SW_RR

Bits	Name	Description
31 : 30	H1_PWR	UAB Half, power profile Default Value: 0 **0x0: NORMAL:** Normal, for normal analog clock speeds **0x1: ULTRA_LOW:** Ultra low power, only allowed for lower analog clock speeds **0x2: ULTRA_HIGH:** Ultra high performance, for higher analog clock speeds (also ultra high power) **0x3: Reserved:** Reserved, do not use
25	SPARE1_EN	1 - Enable the spare reference Default Value: 0

27.1.45 UAB_OA1_CTRL (continued)

24	SW_RR	Connect outputs of Reference0 and Reference1 buffer, one buffer must be off. This is to drive both UAB halves with the same buffer, so both halves get the same offset noise. Default Value: 0
23	AGND1_PTS	1- Pull the Agnd1 buffer output to VDDA Default Value: 0
22 : 20	AGND1_PWR	Agnd1 buffer power Default Value: 0
19	REF1_PTS	1- Pull the Reference1 buffer output to VDDA Default Value: 0
18 : 16	REF1_PWR	Reference1 buffer power Default Value: 0
15	CTRL1_SPARE	Spare bit Default Value: 0
14	CMP1_DSI_LEVEL	Comparator trigger out level : 0=pulse, 1=level Default Value: 0
13 : 12	CMP1_EDGE	Comparator1 edge detect for interrupt and trigger Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
10 : 8	CMP1_PWR	Comparator1 power level Default Value: 0
2 : 0	OA1_PWR	Opamp1 power level Default Value: 0

27.1.46 UAB_CAP_CTRL1

Capacitance controls

Address: 0x40340304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	None				
HW Access	None	R	R	None				
Name	None	CC1_GND	CB1_GND	None [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	None			
HW Access	R		R	R	None			
Name	DAC1_MODE [31:30]		DAC1_MODE_EN	FRC1_SIGN_BIT	None [27:24]			

Bits	Name	Description
31 : 30	DAC1_MODE	DAC mode, this determines the AB Cap Value decoding Default Value: 0 **0x0: UNSIGNED12:** Off or Unsigned 12-bit VDAC, i.e. no AB Cap value decoding. SIGN1_VAL can be used as Firmware controlled modbit (e.g. to invert the Voltage for a Sign + Magnitude VDAC) **0x1: VIRT_SIGNED12:** Virtual signed 12-bits' VDAC. AB Cap value decoding: add 0x800 to the 12-bit AB Cap Value (=invert MSB), to convert the lowest signed number 0x800 to the lowest unsigned number 0x000. This is the same as the SAR handles 12-bit 'virtual' signed numbers.

27.1.46 UAB_CAP_CTRL1 (continued)

		0x2: SIGNED13: Signed 13-bit twos complement. AB Cap value decoding: for negative values (SIGN1_VAL=1) the AB Cap values are inverted, the 64th B cap unit is enabled and the Voltage should be inverted. - Voltage inversion only works if the right clocking waveforms, switch settings and reference voltages are used. - Enabling the 64th B cap unit adds 1 so that only a AB Cap value inversion is needed to create a true twos complement. . **0x3: RESERVED:**
29	DAC1_MODE_EN	1: SIGN1_VAL is dedicated sign bit (FW modbit source tied to 0) 0: SIGN1_VAL can be programmed to be a modbit source Default Value: 0
28	FRC1_SIGN_BIT	Forces the sign bit to be 1 in DAC mode. This is used to achieve 0 - Vref range for unsigned numbers using DAC mode 2 Default Value: 0
6	CC1_GND	Ground unused caps of CC1 array 0: leave unused caps floating 1: ground unused caps (typical when attentuation Cap is used) Default Value: 0
5	CB1_GND	Ground unused caps of CB1 array 0: leave unused caps floating 1: ground unused caps (typical when attentuation Cap is used, e.g. for VDAC use-case) Default Value: 0

27.1.47 UAB_CAP_ABCF1_VAL

Capacitance values for CA1, CB1, CC1 and CF1

Address: 0x40340308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW					
HW Access	RW		RW					
Name	CA1_VAL [7:6]		CB1_VAL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	RW			
HW Access	None		R	RW	RW			
Name	None [15:14]		CB1_64	SIGN1_VAL	CA1_VAL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW					
HW Access	None		RW					
Name	None [23:22]		CC1_VAL [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW				
HW Access	None			RW				
Name	None [31:29]			CF1_VAL [28:24]				

Bits	Name	Description
28 : 24	CF1_VAL	Cap F1 Value Default Value: 0
21 : 16	CC1_VAL	Cap C1 Value Default Value: 0
13	CB1_64	Enable 64th Cap of CB1 array. In DAC mode the FW setting is overridden by the hardware based on DAC_MODE setting. 1 - Enables the 64th cap. This will also set CB1_val[5:0] to be 6'h3F Default Value: 0
12	SIGN1_VAL	Sign bit Value, when used in DAC_MODE, otherwise Firmware modbit. The MODBIT0_SRC0/1_SEL needs to be set to 31 to select this bit as a firmware modbit. In DAC_MODE the modbit should be used to invert the voltage on the AB Caps for the negative DAC values. Default Value: 0
11 : 6	CA1_VAL	Cap A1 Value, in DAC_MODE 1 and 2 this value is decoded Default Value: 0
5 : 0	CB1_VAL	Cap B1 Value, in DAC_MODE 1 and 2 this value is decoded Default Value: 0

27.1.48 UAB_CAP_AB1_VAL_NXT

Next capacitance values for CA1 and CB1

Address: 0x4034030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW					
HW Access	R		R					
Name	CA1_VAL [7:6]		CB1_VAL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW			
HW Access	None			R	R			
Name	None [15:13]			SIGN1_VAL	CA1_VAL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
12	SIGN1_VAL	Sign bit Value Default Value: 0
11 : 6	CA1_VAL	Cap A1 Value Default Value: 0
5 : 0	CB1_VAL	Cap B1 Value Default Value: 0

27.1.49 UAB_CAP_CF1_VAL_NXT

Next capacitance values for CC1 and CF1

Address: 0x40340310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW					
HW Access	None		R					
Name	None [23:22]		CC1_VAL [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None	RW				
HW Access	R	R	None	R				
Name	CF1_VAL_UPDATE	CC1_VAL_UPDATE	None	CF1_VAL [28:24]				

Bits	Name	Description
31	CF1_VAL_UPDATE	1 - Update the CF1 cap value with CAP_CF1_VAL_NXT.CF1_VAL Default Value: 0
30	CC1_VAL_UPDATE	1 - Update the CC1 cap value with CAP_CC1_VAL_NXT.CC1_VAL Default Value: 0
28 : 24	CF1_VAL	Cap F1 Value Default Value: 0
21 : 16	CC1_VAL	Cap C1 Value Default Value: 0

27.1.50 UAB_STARTUP_DELAY1

Startup delay

Address: 0x40340320

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	STARTUP_DELAY [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	STARTUP_DELAY [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							ALIGN_MODE

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	ALIGN_MODE	0 STARTUP_DELAY is number of clk_hf clocks to delay the UAB clock after a SAR Trigger for UAB-SAR alignment in scheduled mode 1 - STARTUP_DELAY is number of clk_hf clocks to delay UAB trigger to SAR for UAB-SAR alignment in unscheduled mode Default Value: 0
15 : 0	STARTUP_DELAY	Startup delay to synchronize the UAB-SAR interface. The usage and meaning of this field depends on the value of the ALIGN_MODE bit (below). A value of 0 disables this function. Default Value: 0

27.1.51 UAB_SUBSAMPLE_CTRL1

Subsample control

Address: 0x40340324

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SUBSAMPLE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	SUBSAMPLE_INIT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	SUBSAMPLE_INIT	Initial value of the subsampling down counter. Before this UAB half is running the firmware can write to this field the initial value of the subsample down counter. It is recommend that the following is true for the initial value SUBSAMPLE_INIT<=SUBSAMPLE, however this is not a requirement. Writing a bigger value can be used to postpone the very first Valid output. Default Value: 0
7 : 0	SUBSAMPLE	Subsampling: suppress Valid output during the first SUBSAMPLE analog clock periods. Only allow Valid output in the last of the SUBSAMPLE+1 analog clock periods. A value of 0 will not suppress Valid output. Default Value: 0

27.1.52 UAB_SW_STATIC1

Static switches for half 1 of the UAB

Address: 0x40340330

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SW_G1G	SW_R1G	SW_G13	SW_G12	SW_G11	SW_G10

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		EARLY_Q1O	EARLY_Q1S	None	SW_P1T	SW_G1T	SW_R1T

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				RMB1_BITS [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW	RW				
HW Access	None		R	R				
Name	None [31:30]		STRB_RST1_EN	STRB_RST1_SEL [28:24]				

Bits	Name	Description
29	STRB_RST1_EN	Enable VDAC strobe or UAB analog-reset: 0: Use selected source as VDAC strobe for next CA1 and CB1 values 1: Use selected source as Analog-reset (discharge all Caps) Default Value: 0
28 : 24	STRB_RST1_SEL	Select source either for VDAC strobe or analog-reset to discharge all Caps (Delsig Modulator use-case) 0 = Decimator0 half 0 analog-reset output 1 = Decimator0 half 1 analog-reset output 8-13 = generic trigger input 0-5 Default Value: 0
19 : 16	RMB1_BITS	Reserved Default Value: 0
13	EARLY_Q1O	OUT1 to VOUT1 switch timing: 0=Regular, 1=Early Default Value: 0

27.1.52 UAB_SW_STATIC1 (continued)

12	EARLY_Q1S	OUT1 to Sum1 switch timing: 0=Regular, 1=Early Default Value: 0
10	SW_P1T	OUT0 to cmp1.vminus (Threshold) Default Value: 0
9	SW_G1T	AGND1 to cmp1.vminus (Threshold) Default Value: 0
8	SW_R1T	REF1 to cmp1.vminus (Threshold) Default Value: 0
5	SW_G1G	AGND1 to OA1.vplus (AG1) Default Value: 0
4	SW_R1G	REF1 to OA1.vplus (AG1) Default Value: 0
3	SW_G13	VIN13 to OA1.vplus (AG1) Default Value: 0
2	SW_G12	VIN12 to OA1.vplus (AG1) Default Value: 0
1	SW_G11	VIN11 to OA1.vplus (AG1) Default Value: 0
0	SW_G10	VIN10 to OA1.vplus (AG1) Default Value: 0

27.1.53 UAB_SW_MODBIT_SRC1

Select source of Modbit for A,B and C branches of half 1

Address: 0x40340334

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				MODBIT0_SRC1_SEL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:13]				MODBIT1_SRC1_SEL [12:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
12 : 8	MODBIT1_SRC1_SEL	Select source of modbit for C branch 0=UAB0 half 0 comparator output 1=UAB0 half 1 comparator output 8-11 = generic trigger inputs 0-3 31=SIGN1_VAL, also used as Firmware modbit. (In VDAC use-case this should invert the voltage on the AB Cap) Default Value: 0
4 : 0	MODBIT0_SRC1_SEL	Select source of modbit for A & B branches 0=UAB0 half 0 comparator output 1=UAB0 half 1 comparator output 8-13 = generic trigger inputs 0-5 31=SIGN1_VAL, also used as Firmware modbit. (In VDAC use-case this should invert the voltage on the AB Cap) Default Value: 0

27.1.54 UAB_SW_CA1_IN0

Cap A1 input switches set 0

Address: 0x40340340

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A11_CMP [7:4]				SW_A10_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A13_CMP [15:12]				SW_A12_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A1Q [23:20]				SW_A1P [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_A1Q	OUT0 to Cap A1 input Default Value: 0
19 : 16	SW_A1P	OUT1 to Cap A1 input Default Value: 0
15 : 12	SW_A13_CMP	VIN13 to Cap A1 input, allows for modbit control Default Value: 0
11 : 8	SW_A12_CMP	VIN12 to Cap A1 input, allows for modbit control Default Value: 0
7 : 4	SW_A11_CMP	VIN11 to Cap A1 input, allows for modbit control Default Value: 0
3 : 0	SW_A10_CMP	VIN10 to Cap A1 input, allows for modbit control Default Value: 0

27.1.55 UAB_SW_CA1_IN1

Cap A1 input switches set 1

Address: 0x40340344

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				None			
HW Access	R				None			
Name	SW_A1R_CMP [7:4]				None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_A1V_CMP [15:12]				SW_A1G_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_A1V_CMP	VSS to Cap A1 input, allows for modbit control Default Value: 0
11 : 8	SW_A1G_CMP	AGND1 to Cap A1 input, allows for modbit control Default Value: 0
7 : 4	SW_A1R_CMP	REF1 to Cap A1 input, allows for modbit control Default Value: 0

27.1.56 UAB_SW_CA1_TOP

Cap A1 top plate switches

Address: 0x40340348

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_G1A_CMP [7:4]				SW_R1A_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SW_V1A_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				SW_S1A [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	SW_S1A	Cap A1 top plate to SUM1 Default Value: 0
11 : 8	SW_V1A_CMP	Cap A1 top plate to VSS, allows for modbit control Default Value: 0
7 : 4	SW_G1A_CMP	Cap A1 top plate to AGND1, allows for modbit control Default Value: 0
3 : 0	SW_R1A_CMP	Cap A1 top plate to REF1, allows for modbit control Default Value: 0

27.1.57 UAB_SW_CB1_IN0

Cap B1 input switches set 0

Address: 0x40340350

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B11_CMP [7:4]				SW_B10_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B13_CMP [15:12]				SW_B12_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B1Q [23:20]				SW_B1P [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_B1Q	OUT0 to Cap B1 input Default Value: 0
19 : 16	SW_B1P	OUT1 to Cap B1 input Default Value: 0
15 : 12	SW_B13_CMP	VIN13 to Cap B1 input, allows for modbit control Default Value: 0
11 : 8	SW_B12_CMP	VIN12 to Cap B1 input, allows for modbit control Default Value: 0
7 : 4	SW_B11_CMP	VIN11 to Cap B1 input, allows for modbit control Default Value: 0
3 : 0	SW_B10_CMP	VIN10 to Cap B1 input, allows for modbit control Default Value: 0

27.1.58 UAB_SW_CB1_IN1

Cap B1 input switches set 1

Address: 0x40340354

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				None			
HW Access	R				None			
Name	SW_B1R_CMP [7:4]				None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_B1V_CMP [15:12]				SW_B1G_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_B1V_CMP	VSS to Cap B1 input, allows for modbit control Default Value: 0
11 : 8	SW_B1G_CMP	AGND1 to Cap B1 input, allows for modbit control Default Value: 0
7 : 4	SW_B1R_CMP	REF1 to Cap B1 input, allows for modbit control Default Value: 0

27.1.59 UAB_SW_CB1_TOP

Cap A1 top plate switches

Address: 0x40340358

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_G1B_CMP [7:4]				SW_R1B_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_T1B [15:12]				SW_V1B_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				SW_S1B [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	SW_S1B	Cap B1 top plate to SUM1 Default Value: 0
15 : 12	SW_T1B	Cap B1 top plate Trim/Attenuation bypass Default Value: 0
11 : 8	SW_V1B_CMP	Cap B1 top plate to VSS, allows for modbit control Default Value: 0
7 : 4	SW_G1B_CMP	Cap B1 top plate to AGND1, allows for modbit control Default Value: 0
3 : 0	SW_R1B_CMP	Cap B1 top plate to REF1, allows for modbit control Default Value: 0

27.1.60 UAB_SW_CC1_IN0

Cap C1 input switches set 0

Address: 0x40340360

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C11_CMP [7:4]				SW_C10_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C13_CMP [15:12]				SW_C12_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C1Q [23:20]				SW_C1P [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_C1Q	OUT0 to Cap C1 input Default Value: 0
19 : 16	SW_C1P	OUT1 to Cap C1 input Default Value: 0
15 : 12	SW_C13_CMP	VIN13 to Cap C1 input, allows for modbit control Default Value: 0
11 : 8	SW_C12_CMP	VIN12 to Cap C1 input, allows for modbit control Default Value: 0
7 : 4	SW_C11_CMP	VIN11 to Cap C1 input, allows for modbit control Default Value: 0
3 : 0	SW_C10_CMP	VIN10 to Cap C1 input, allows for modbit control Default Value: 0

27.1.61 UAB_SW_CC1_IN1

Cap C1 input switches set 1

Address: 0x40340364

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				None			
HW Access	R				None			
Name	SW_C1R_CMP [7:4]				None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_C1V_CMP [15:12]				SW_C1G_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_C1V_CMP	VSS to Cap C1 input, allows for modbit control Default Value: 0
11 : 8	SW_C1G_CMP	AGND1 to Cap C1 input, allows for modbit control Default Value: 0
7 : 4	SW_C1R_CMP	REF1 to Cap C1 input, allows for modbit control Default Value: 0

27.1.62 UAB_SW_CC1_TOP

Cap A1 top plate switches

Address: 0x40340368

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_G1C_CMP [7:4]				SW_R1C_CMP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_T1C [15:12]				SW_V1C_CMP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	SW_S01 [23:20]				SW_S1C [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	SW_S01	Cap C1 top plate to SUM0 Default Value: 0
19 : 16	SW_S1C	Cap C1 top plate to SUM1 Default Value: 0
15 : 12	SW_T1C	Cap C1 top plate Trim/Attenuation bypass Default Value: 0
11 : 8	SW_V1C_CMP	Cap C1 top plate to VSS, allows for modbit control Default Value: 0
7 : 4	SW_G1C_CMP	Cap C1 top plate to AGND1, allows for modbit control Default Value: 0
3 : 0	SW_R1C_CMP	Cap C1 top plate to REF1, allows for modbit control Default Value: 0

27.1.63 UAB_SW_CF1_BOT

Cap F1 bottom plate and output switches

Address: 0x4034036C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SW_Q1F [7:4]				SW_G1F [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	SW_Q1O [15:12]				SW_Q1S [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	SW_Q1O	OUT1 to VOUT1 Default Value: 0
11 : 8	SW_Q1S	Cap F bypass, OUT1 to SUM1 Default Value: 0
7 : 4	SW_Q1F	Cap F1 bottom plate to OUT1 Default Value: 0
3 : 0	SW_G1F	Cap F1 bottom plate to AGND1 Default Value: 0

27.1.64 UAB_SW_OTHER1

Other clocked controls

Address: 0x40340370

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	VALID1 [7:4]				CMP1_FF [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				TRIG1_OUT [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	R				R			
Name	STROBE_RST1 [31:28]				STROBE_SW1 [27:24]			

Bits	Name	Description
31 : 28	STROBE_RST1	Use the positive edge of the selected clocking waveform to synchronize: STRB_RST0_EN=0: Capacitor Value update (Capacitor Strobe) STRB_RST0_EN=1: UAB analog-reset update Set to 0 to disable both functions. Result undefined for value 15. Default Value: 0
27 : 24	STROBE_SW1	Strobe for dsi_sw_ctrl (modbit) update, dsi_sw_ctrl updates in sync with posedge of this wave. To disable set to 0. To enable update anytime use 15. Default Value: 0
11 : 8	TRIG1_OUT	Trigger output (for other UABs or SAR) Default Value: 0
7 : 4	VALID1	Valid1, output flag to indicated that VOUT1 is valid. The Valid output can be suppressed due to sub-sampling. Note that when sub-sampling is used this clocking waveform is used to decrement the counter (decrement is aligned with the positive edge of this clocking waveform). Default Value: 0
3 : 0	CMP1_FF	Clock for Flip-Flop after Comparator 1 Default Value: 0

27.1.65 UAB_SW_BOOST_CTRL1

Bootstrap clock control

Address: 0x40340374

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	CB1_BOOST [7:4]				CA1_BOOST [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	CF1_BOOST [15:12]				CC1_BOOST [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	R				R			
Name	PUMP1_WAVE [23:20]				SUM1_BOOST [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	PUMP1_WAVE	Clock for pump in half1 Default Value: 0
19 : 16	SUM1_BOOST	Clock for boot strap master in Summing node branch Default Value: 0
15 : 12	CF1_BOOST	Clock for boot strap master in F branch Default Value: 0
11 : 8	CC1_BOOST	Clock for boot strap master in C branch Default Value: 0
7 : 4	CB1_BOOST	Clock for boot strap master in B branch Default Value: 0
3 : 0	CA1_BOOST	Clock for boot strap master in A branch Default Value: 0

27.1.66 UAB_SRAM1_CTRL

SRAM programmed size

Address: 0x40340378

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LAST_STEP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW				
HW Access	R	None	R	R				
Name	RUN	None	TRIGGER_EN	TRIG_SEL1 [28:24]				

Bits	Name	Description
31	RUN	Set to start executing the waveform. Trigger is required if TRIGGER_EN is set to 1. Clear to stop this UAB half. When RUN=0 all dynamic switches are forced open. Default Value: 0
29	TRIGGER_EN	Enable input trigger: 0: Ignore triggers, start running immediately after setting RUN bit 1: After RUN bit is set wait for a positive edge on the selected trigger input Default Value: 0
28 : 24	TRIG_SEL1	Trigger select 0=UAB0 half 0 trigger output 1=UAB0 half 1 trigger output 8-13 = generic trigger inputs 0-5 31=SAR trigger output Default Value: 0
3 : 0	LAST_STEP	Last step of wave programmed in the SRAM Default Value: 0

27.1.67 UAB_STAT1

Status Current SRAM counter and comparator

Address: 0x4034037C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	R			
HW Access	None			RW	RW			
Name	None [7:5]			COMP	CURR_STEP [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	RW							
Name	CURR_SUBSAMPLE [31:24]							

Bits	Name	Description
31 : 24	CURR_SUBSAMPLE	Current value of the subsampling down counter. The Valid is suppressed when SUBSAMPLE_CUR!=0. Default Value: 0
4	COMP	Current comparator status Default Value: 0
3 : 0	CURR_STEP	Current step executed from the SRAM Default Value: 0

27.1.68 UAB_SRAM10

Waveform SRAM for half 1 of the UAB

Address: 0x40340380

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.69 UAB_SRAM11

Waveform SRAM for half 1 of the UAB

Address: 0x40340384

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.70 UAB_SRAM12

Waveform SRAM for half 1 of the UAB

Address: 0x40340388

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.71 UAB_SRAM13

Waveform SRAM for half 1 of the UAB

Address: 0x4034038C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.72 UAB_SRAM14

Waveform SRAM for half 1 of the UAB

Address: 0x40340390

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.73 UAB_SRAM15

Waveform SRAM for half 1 of the UAB

Address: 0x40340394

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.74 UAB_SRAM16

Waveform SRAM for half 1 of the UAB

Address: 0x40340398

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.75 UAB_SRAM17

Waveform SRAM for half 1 of the UAB

Address: 0x4034039C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.76 UAB_SRAM18

Waveform SRAM for half 1 of the UAB

Address: 0x403403A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.77 UAB_SRAM19

Waveform SRAM for half 1 of the UAB

Address: 0x403403A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.78 UAB_SRAM110

Waveform SRAM for half 1 of the UAB

Address: 0x403403A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.79 UAB_SRAM111

Waveform SRAM for half 1 of the UAB

Address: 0x403403AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.80 UAB_SRAM112

Waveform SRAM for half 1 of the UAB

Address: 0x403403B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.81 UAB_SRAM113

Waveform SRAM for half 1 of the UAB

Address: 0x403403B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.82 UAB_SRAM114

Waveform SRAM for half 1 of the UAB

Address: 0x403403B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.83 UAB_SRAM115

Waveform SRAM for half 1 of the UAB

Address: 0x403403BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	A							
Name	WAVE_STEP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	WAVE_STEP	one step of the clocking waveform sequence Default Value: 0

27.1.84 UAB_DECM_CTRL

Global decimator control

Address: 0x40340400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLED	None [30:24]						

Bits	Name	Description
31	ENABLED	- 0: Decimator disabled (independent of UAB) - 1: Decimator enabled (independent of UAB) Default Value: 0

27.1.85 UAB_DC0_CTRL

decimator0 control

Address: 0x40340404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		None		RW	RW
HW Access	R		R		None		R	RW1C
Name	DC0_TYPE [7:6]		DC0_SEL [5:4]		None [3:2]		DC0_MODE	DC0_START

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			DC0_SHIFT [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DC0_RATIO [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							RW
HW Access	None							R
Name	None [31:25]							DC0_RATIO

Bits	Name	Description
24 : 16	DC0_RATIO	decimation ratio = DC0_RATIO+1, range 1..512 Default Value: 0
12 : 8	DC0_SHIFT	shift the result right by specified amount, legal range 0..16 Default Value: 0
7 : 6	DC0_TYPE	decimator type (filter order) Default Value: 0 **0x0: SINC1:** first order **0x1: SINC2:** second order **0x2: SINC3:** third order, this uses half of decimator1, therefore cannot be combined with dc1_mode SINC2 **0x3: reserved:** reserved value, do not use

27.1.85 UAB_DC0_CTRL (continued)

5 : 4	DC0_SEL	Source select Default Value: 0 **0x0: UAB_H0:** Comparator output from Half0 of this UAB **0x1: UAB_H1:** Comparator output from Half1 of this UAB **0x2: DSI0:** **0x3: DSI1:**
1	DC0_MODE	Operation mode 0: Incremental (one-shot) operation 1: Continuous operation Default Value: 0
0	DC0_START	Start decimator, in incremental mode, this bit is cleared by HW when done. If DSI trigger enable is set then only start after a DSI trigger. Default Value: 0

27.1.86 UAB_DC0_TRIG

decimator0 trigger control

Address: 0x40340408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW	RW				
HW Access	None		R	R				
Name	None [31:30]		DC0_DSI_TRIG_EN	DC0_TRIG_SEL [28:24]				

Bits	Name	Description
29	DC0_DSI_TRIG_EN	Decimator DSI trigger input Enable 0: Ignore decimator DSI trigger input 1: Wait for positive edge on selected DSI trigger input Default Value: 0
28 : 24	DC0_TRIG_SEL	Trigger select 0=UAB0 half 0 trigger output 1=UAB0 half 1 trigger output 8-11 = generic trigger inputs 0-3 31=SAR trigger output Default Value: 0

27.1.87 UAB_DC0_OVR

decimator 0 overflow control

Address: 0x4034040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			DC0_OVR_CORR_LOC [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	DC0_OVR_CORR_LOC	Bit location for overflow correction. This should be set to FILTER_ORDER*log2(DC0_RATIO) Default Value: 0

27.1.88 UAB_DC0_A0

decimator0 accumulator 0

Address: 0x40340410

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	A0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	A0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	A0 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	A0 [31:24]							

Bits	Name	Description
31 : 0	A0	24-bit sign extended accumulator0 status Default Value: 0

27.1.89 UAB_DC0_A1

decimator0 accumulator 1

Address: 0x40340414

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	A1 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	A1 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	A1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	A1 [31:24]							

Bits	Name	Description
31 : 0	A1	24-bit sign extended accumulator1 status Default Value: 0

27.1.90 UAB_DC0_DEC_CNT

decimator0 decimation counter

Address: 0x40340418

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	INT_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							INT_CNT

Bits	23	22	21	20	19	18	17	16
SW Access	None						R	
HW Access	None						W	
Name	None [23:18]						DIFF_CNT [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	DIFF_CNT	differentiation down counter Default Value: undefined
8 : 0	INT_CNT	integration/decimation down counter Default Value: undefined

27.1.91 UAB_DC0_TMP

decimator0 temporary value for differentiator

Address: 0x4034041C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	TMP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	TMP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	TMP [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	TMP [31:24]							

Bits	Name	Description
31 : 0	TMP	24-bit sign extended differentiator temporary value status Default Value: 0

27.1.92 UAB_DC0_D0

decimator0 differentiator 0

Address: 0x40340420

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	D0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	D0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	D0 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	D0 [31:24]							

Bits	Name	Description
31 : 0	D0	24-bit sign extended differentiator 0 status Default Value: 0

27.1.93 UAB_DC0_D1

decimator0 differentiator 1

Address: 0x40340424

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	D1 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	D1 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	D1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	D1 [31:24]							

Bits	Name	Description
31 : 0	D1	24-bit sign extended differentiator 1 status Default Value: 0

27.1.94 UAB_DC0_RES

decimator0 result

Address: 0x40340428

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RES [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RES [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	RES [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	RES [31:24]							

Bits	Name	Description
31 : 0	RES	24-bit sign extended result Default Value: 0

27.1.95 UAB_DC1_CTRL

decimator1 control

Address: 0x40340434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW		None		RW	RW
HW Access	R	R	R		None		R	RW1C
Name	DC01_CHAIN	DC1_TYPE	DC1_SEL [5:4]		None [3:2]		DC1_MODE	DC1_START

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			DC1_SHIFT [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DC1_RATIO [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							RW
HW Access	None							R
Name	None [31:25]							DC1_RATIO

Bits	Name	Description
24 : 16	DC1_RATIO	decimation ratio = DC1_RATIO+1, range 1..512 Default Value: 0
12 : 8	DC1_SHIFT	shift the result right by specified amount, legal range 0..16 Default Value: 0
7	DC01_CHAIN	Chain decimator0 and decimator1 Default Value: 0
6	DC1_TYPE	decimator type (filter order) Default Value: 0 **0x0: SINC1:** first order **0x1: SINC2:** second order
5 : 4	DC1_SEL	Source select Default Value: 0

27.1.95 UAB_DC1_CTRL (continued)

		0x0: UAB_H0: Comparator output from Half0 of this UAB **0x1: UAB_H1:** Comparator output from Half1 of this UAB **0x2: DSI0:** **0x3: DSI1:**
1	DC1_MODE	Operation mode 0: Incremental (one-shot) operation 1: Continuous operation Default Value: 0
0	DC1_START	Start decimator, in incremental mode, this bit is cleared by HW when done. If DSI trigger enable is set then only start after a DSI trigger. Default Value: 0

27.1.96 UAB_DC1_TRIG

decimator1 trigger control

Address: 0x40340438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW	RW				
HW Access	None		R	R				
Name	None [31:30]		DC1_DSI_TRIG_EN	DC1_TRIG_SEL [28:24]				

Bits	Name	Description
29	DC1_DSI_TRIG_EN	Decimator DSI trigger input Enable 0: Ignore decimator DSI trigger input 1: Wait for positive edge on selected DSI trigger input Default Value: 0
28 : 24	DC1_TRIG_SEL	Trigger select 0=UAB0 half 0 trigger output 1=UAB0 half 1 trigger output 8-11 = generic trigger inputs 0-3 31=SAR trigger output Default Value: 0

27.1.97 UAB_DC1_OVR

decimator 1 overflow control

Address: 0x4034043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			DC1_OVR_CORR_LOC [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	DC1_OVR_CORR_LOC	Bit location for overflow correction. This should be set to FILTER_ORDER*log2(DC1_RATIO) Default Value: 0

27.1.98 UAB_DC1_A0

decimator1 accumulator 0

Address: 0x40340440

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	A0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	A0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	A0 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	A0 [31:24]							

Bits	Name	Description
31 : 0	A0	27-bit sign extended accumulator0 status Default Value: 0

27.1.99 UAB_DC1_A1

decimator1 accumulator 1

Address: 0x40340444

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	A1 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	A1 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	A1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	A1 [31:24]							

Bits	Name	Description
31 : 0	A1	27-bit sign extended accumulator1 status Default Value: 0

27.1.100 UAB_DC1_DEC_CNT

decimator1 decimation counter

Address: 0x40340448

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	INT_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							INT_CNT

Bits	23	22	21	20	19	18	17	16
SW Access	None						R	
HW Access	None						W	
Name	None [23:18]						DIFF_CNT [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	DIFF_CNT	differentiation down counter Default Value: undefined
8 : 0	INT_CNT	integration/decimation down counter Default Value: undefined

27.1.101 UAB_DC1_TMP

decimator1 temporary value for differentiator

Address: 0x4034044C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	TMP [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	TMP [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	TMP [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	TMP [31:24]							

Bits	Name	Description
31 : 0	TMP	27-bit sign extended differentiator temporary value status Default Value: 0

27.1.102 UAB_DC1_D0

decimator1 differentiator 0

Address: 0x40340450

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	D0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	D0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	D0 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	D0 [31:24]							

Bits	Name	Description
31 : 0	D0	27-bit sign extended differentiator 0 status Default Value: 0

27.1.103 UAB_DC1_D1

decimator1 differentiator 1

Address: 0x40340454

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	D1 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	D1 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	D1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	D1 [31:24]							

Bits	Name	Description
31 : 0	D1	27-bit sign extended differentiator 1 status Default Value: 0

27.1.104 UAB_DC1_RES

decimator1 result

Address: 0x40340458

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RES [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RES [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	RES [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	RES [31:24]							

Bits	Name	Description
31 : 0	RES	27-bit sign extended result Default Value: 0

27.1.105 UAB_CAP_TRIM0

Trim for attenuation cap half0

Address: 0x40340F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				CBTC0_VAL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:11]					CCTC0_VAL [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10 : 8	CCTC0_VAL	Cap C Trim 0 Value Do not measure value, instead use same value as for CBTC0_VAL Default Value: 0
4 : 0	CBTC0_VAL	Cap B Trim 0 Value Trim attenuation cap in branch B for DAC correctness Default Value: 0

27.1.106 UAB_CAP_TRIM1

Trim for attenuation cap half1

Address: 0x40340F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:5]				CBTC1_VAL [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:11]					CCTC1_VAL [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10 : 8	CCTC1_VAL	Cap C Trim 1 Value Do not measure value, instead use same value as for CBTC1_VAL Default Value: 0
4 : 0	CBTC1_VAL	Cap B Trim 1 Value Trim attenuation cap in branch B for DAC correctness Default Value: 0

27.1.107 UAB_OA_TRIM0

Trim for opamp and buffers half0

Address: 0x40340F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OA0_OFFSET [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			REF0_OFFSET [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			AGND0_OFFSET [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	AGND0_OFFSET	Agnd buffer offset trim Default Value: 0
12 : 8	REF0_OFFSET	Reference buffer offset trim Default Value: 0
3 : 0	OA0_OFFSET	Opamp offset trim Default Value: 0

27.1.108 UAB_OA_TRIM1

Trim for opamp and buffers half1

Address: 0x40340F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OA1_OFFSET [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			REF1_OFFSET [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			AGND1_OFFSET [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	AGND1_OFFSET	Agnd buffer offset trim Default Value: 0
12 : 8	REF1_OFFSET	Reference buffer offset trim Default Value: 0
3 : 0	OA1_OFFSET	Opamp offset trim Default Value: 0

28 Watch Crystal Oscillator (WCO) Registers

This section discusses the WRK8 registers. It lists all the registers in mapping tables, in address order.

28.1 Register Details

Register Name	Address
WCO_CONFIG	0x40060000
WCO_DPLL	0x40060008
WCO_WDT_CTRLOW	0x40060200
WCO_WDT_CTRHIGH	0x40060204
WCO_WDT_MATCH	0x40060208
WCO_WDT_CONFIG	0x4006020C
WCO_WDT_CONTROL	0x40060210
WCO_WDT_CLKEN	0x40060214
WCO_TRIM	0x40060F00

28.1.1 WCO_CONFIG

WCO Configuration Register

Address: 0x40060000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [7:3]					EXT_INPUT_EN	LPM_AUTO	LPM_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	ENBUS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	IP_ENABLE	DPLL_ENABLE	None [29:24]					

Bits	Name	Description
31	IP_ENABLE	Master enable for IP - disables both WCO and DPLL Default Value: 0
30	DPLL_ENABLE	Enable DPLL operation. The Oscillator is specified to be stable after 500 ms thus the DPLL should be asserted no sooner than that after IP_ENABLE is set. Default Value: 0
23 : 16	ENBUS	Test Mode Control bits enbus[7] - N/A enbus[6] - 1=enable both primary Beta Multipliers enbus[5] - N/A enbus[4] - N/A enbus[3] - Load Resistor Control enbus[2] - Load Resistor Control enbus[1] - Load Resistor Control enbus[0] - Load Resistor Control Default Value: 71
2	EXT_INPUT_EN	Disables the load resistor and allows external clock input for pad_xin Default Value: 0

28.1.1 WCO_CONFIG (continued)

1	LPM_AUTO	Automatically control low power mode (only relevant when LPM_EN=0): 0: Do not enter low power mode (LPM) in DeepSleep 1: Enter low power mode (LPM) in DeepSleep. The logic monitors !act_power_en to determine the device has entered DeepSleep. Default Value: 1
0	LPM_EN	Force block into Low Power Mode: 0: Do not force low power mode (LPM) on 1: Force low power mode (LPM) on Default Value: 0

28.1.2 WCO_DPLL

WCO DPLL Register

Address: 0x40060008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DPLL_MULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:11]					DPLL_MULT [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DPLL_LF_LIMIT [23:22]		DPLL_LF_PGAIN [21:19]			DPLL_LF_IGAIN [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW					
HW Access	None		R					
Name	None [31:30]		DPLL_LF_LIMIT [29:24]					

Bits	Name	Description
29 : 22	DPLL_LF_LIMIT	Maximum IMO offset allowed (used to prevent DPLL dynamics from selecting an IMO frequency that the logic cannot support) Default Value: 255
21 : 19	DPLL_LF_PGAIN	DPLL Loop Filter Proportionial Gain Setting 0x0 - 0.0625 0x1 - 0.125 0x2 - 0.25 0x3 - 0.5 0x4 - 1.0 0x5 - 2.0 0x6 - 4.0 0x7 - 8.0 Default Value: 0

28.1.2 WCO_DPLL (continued)

18 : 16	DPLL_LF_IGAIN	DPLL Loop Filter Integral Gain Setting 0x0 - 0.0625 0x1 - 0.125 0x2 - 0.25 0x3 - 0.5 0x4 - 1.0 0x5 - 2.0 0x6 - 4.0 0x7 - 8.0 Default Value: 0
10 : 0	DPLL_MULT	Multiplier to determine IMO frequency in multiples of the WCO frequency Fimo = (DPLL_MULT + 1) * Fwco Default Value: 0

28.1.3 WCO_WDT_CTRLOW

Watchdog Counters 0/1

Address: 0x40060200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WDT_CTR0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WDT_CTR0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	WDT_CTR1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	RW							
Name	WDT_CTR1 [31:24]							

Bits	Name	Description
31 : 16	WDT_CTR1	Current value of WDT Counter 1 Default Value: 0
15 : 0	WDT_CTR0	Current value of WDT Counter 0 Default Value: 0

28.1.4 WCO_WDT_CTRHIGH

Watchdog Counter 2

Address: 0x40060204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [31:24]							

Bits	Name	Description
31 : 0	WDT_CTR2	Current value of WDT Counter 2 Default Value: 0

28.1.5 WCO_WDT_MATCH

Watchdog counter match values

Address: 0x40060208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WDT_MATCH0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	WDT_MATCH0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	WDT_MATCH1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	WDT_MATCH1 [31:24]							

Bits	Name	Description
31 : 16	WDT_MATCH1	Match value for Watchdog Counter 1 Default Value: 0
15 : 0	WDT_MATCH0	Match value for Watchdog Counter 0 Default Value: 0

28.1.6 WCO_WDT_CONFIG

Watchdog Counters Configuration

Address: 0x4006020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	
HW Access	None				R	R	R	
Name	None [7:4]				WDT_CASCADE0_1	WDT_CLEAR0	WDT_MODE0 [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	
HW Access	None				R	R	R	
Name	None [15:12]				WDT_CASCADE1_2	WDT_CLEAR1	WDT_MODE1 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							WDT_MODE2

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None	RW				
HW Access	R		None	R				
Name	LFCLK_SEL [31:30]		None	WDT_BITS2 [28:24]				

Bits	Name	Description
31 : 30	LFCLK_SEL	Select source for LFCLK: 0: ILO - Internal R/C Oscillator 1: WCO - Internal Crystal Oscillator 2-3: Reserved - do not use Note that not all products support all clock sources. Selecting a clock source that is not supported will result in undefined behavior. To safely change LFCLK_SEL wait for WDT_CTRLOW/WDT_CTRHIGH to change then chaneg the setting immediately. Default Value: 0
28 : 24	WDT_BITS2	Bit to observe for WDT_INT2: 0: Assert when bit0 of WDT_CTR2 toggles (one int every tick) .. 31: Assert when bit31 of WDT_CTR2 toggles (one int every 2^31 ticks) Default Value: 0
16	WDT_MODE2	Watchdog Counter 2 Mode. Default Value: 0

28.1.6 WCO_WDT_CONFIG (continued)

		0x0: NOTHING: Free running counter with no interrupt requests **0x1: INT:** Free running counter with interrupt request when a specified bit in CTR2 toggles (see WDT_BITS2)
11	WDT_CASCADE1_2	Cascade Watchdog Counters 1,2. Counter 2 increments the cycle after WDT_CTR1=WDT_MATCH1. It is allowed to cascade all three WDT counters. 0: Independent counters 1: Cascaded counters Default Value: 0
10	WDT_CLEAR1	Clear Watchdog Counter when WDT_CTR1=WDT_MATCH1. In other words WDT_CTR1 divides LFCLK by (WDT_MATCH1+1). 0: Free running counter 1: Clear on match Default Value: 0
9 : 8	WDT_MODE1	Watchdog Counter Action on Match (WDT_CTR1=WDT_MATCH1). Default Value: 0 **0x0: NOTHING:** Do nothing **0x1: INT:** Assert WDT_INTx **0x2: RESET:** Assert WDT Reset - Not Supported - here for backwards compatibility **0x3: INT_THEN_RESET:** Assert WDT_INTx, assert WDT Reset after 3rd unhandled interrupt - Not supported - here for backwards compatibility.
3	WDT_CASCADE0_1	Cascade Watchdog Counters 0,1. Counter 1 increments the cycle after WDT_CTR0=WDT_MATCH0. 0: Independent counters 1: Cascaded counters Default Value: 0
2	WDT_CLEAR0	Clear Watchdog Counter when WDT_CTR0=WDT_MATCH0. In other words WDT_CTR0 divides LFCLK by (WDT_MATCH0+1). 0: Free running counter 1: Clear on match Default Value: 0
1 : 0	WDT_MODE0	Watchdog Counter Action on Match (WDT_CTR0=WDT_MATCH0). Default Value: 0 **0x0: NOTHING:** Do nothing **0x1: INT:** Assert WDT_INTx **0x2: RESET:** Assert WDT Reset - Not Supported - here for backwards compatibility **0x3: INT_THEN_RESET:** Assert WDT_INTx, assert WDT Reset after 3rd unhandled interrupt. Not supported - here for Backwards compatibility.

28.1.7 WCO_WDT_CONTROL

Watchdog Counters Control

Address: 0x40060210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1C	R	RW
HW Access	None				RW0C	A	RW	R
Name	None [7:4]				WDT_RESET0	WDT_INT0	WDT_ENABLED0	WDT_ENABLE0

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1C	R	RW
HW Access	None				RW0C	A	RW	R
Name	None [15:12]				WDT_RESET1	WDT_INT1	WDT_ENABLED1	WDT_ENABLE1

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1S	RW1C	R	RW
HW Access	None				RW0C	A	RW	R
Name	None [23:20]				WDT_RESET2	WDT_INT2	WDT_ENABLED2	WDT_ENABLE2

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	WDT_RESET2	Resets counter 2 back to 0000_0000. Hardware will reset this bit after counter was reset. This will take several LFCLK cycles to take effect. Wait until the reset completes before enabling the WDT. Default Value: 0
18	WDT_INT2	WDT Interrupt Request. This bit is set by hardware as configured by this registers. This bit must be cleared by firmware. After W1C, WDT_CONTROL must be read for the hardware to internally remove the clear flag. Failure to do this may result in missing the next interrupt. Default Value: 0
17	WDT_ENABLED2	Indicates actual state of counter. May lag WDT_ENABLE2 by up to 3 LFCLK cycles. After changing WDT_ENABLE2, do not enter DEEPSLEEP mode until this field acknowledges the change. Default Value: 0

28.1.7 WCO_WDT_CONTROL (continued)

16	WDT_ENABLE2	Enable Counter 2 0: Counter is disabled (not clocked) 1: Counter is enabled (counting up) Note: This field takes considerable time (up to 3 LFCLK cycles) to take effect. It must not be changed more than once in that period. Default Value: 0
11	WDT_RESET1	Resets counter 1 back to 0000. Hardware will reset this bit after counter was reset. This will take several LFCLK cycles to take effect. Wait until the reset completes before enabling the WDT. Default Value: 0
10	WDT_INT1	WDT Interrupt Request. This bit is set by hardware as configured by this registers. This bit must be cleared by firmware. After W1C, WDT_CONTROL must be read for the hardware to internally remove the clear flag. Failure to do this may result in missing the next interrupt. Default Value: 0
9	WDT_ENABLED1	Indicates actual state of counter. May lag WDT_ENABLE1 by up to 3 LFCLK cycles. After changing WDT_ENABLE1, do not enter DEEPSLEEP mode until this field acknowledges the change. Default Value: 0
8	WDT_ENABLE1	Enable Counter 1 0: Counter is disabled (not clocked) 1: Counter is enabled (counting up) Note: This field takes considerable time (up to 3 LFCLK cycles) to take effect. It must not be changed more than once in that period. Default Value: 0
3	WDT_RESET0	Resets counter 0 back to 0000. Hardware will reset this bit after counter was reset. This will take several LFCLK cycles to take effect. Wait until the reset completes before enabling the WDT. Default Value: 0
2	WDT_INT0	WDT Interrupt Request. This bit is set by hardware as configured by this registers. This bit must be cleared by firmware. Clearing this bit also prevents Reset from happening when WDT_MODEx=3. After W1C, WDT_CONTROL must be read for the hardware to internally remove the clear flag. Failure to do this may result in missing the next interrupt. Default Value: 0
1	WDT_ENABLED0	Indicates actual state of counter. May lag WDT_ENABLE0 by up to 3 LFCLK cycles. After changing WDT_ENABLE0, do not enter DEEPSLEEP mode until this field acknowledges the change. Default Value: 0
0	WDT_ENABLE0	Enable Counter 0 0: Counter is disabled (not clocked) 1: Counter is enabled (counting up) Note: This field takes considerable time (up to 3 LFCLK cycles) to take effect. It must not be changed more than once in that period. Default Value: 0

28.1.8 WCO_WDT_CLKEN

Watchdog Counters Clock Enable

Address: 0x40060214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CLK_ILO_EN_FOR_WDT	CLK_WCO_EN_FOR_WDT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CLK_ILO_EN_FOR_WDT	Enables the ILO clock for use by the WDT logic. Wait at least 2 ILO clock cycles for a change to take effect. Must be 0 when switching WDT_CONFIG.LFCLK_SEL. Should be 0 if CLK_WCO_EN_FOR_WDT=1. Default Value: 0
0	CLK_WCO_EN_FOR_WDT	Enables the WCO clock for use by the WDT logic. Wait at least 2 WCO clock cycles for a change to take effect. Must be 0 when switching WDT_CONFIG.LFCLK_SEL. Should be 0 if CLK_ILO_EN_FOR_WDT=1 Default Value: 0

28.1.9 WCO_TRIM

WCO Trim Register

Address: 0x40060F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		None	RW		
HW Access	None		R		None	R		
Name	None [7:6]		LPM_GM [5:4]		None	XGM [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW		
HW Access	None		R		None	R		
Name	None [15:14]		LPM_GM_FOR_LPM_AUTO [13:12]		None	XGM_FOR_LPM_AUTO [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
13 : 12	LPM_GM_FOR_LPM_AUTO	GM setting for LPM (bandwidth = DC/ms) - Used when WCO.LPM_AUTO=1 and in DeepSleep mode Default Value: 2
10 : 8	XGM_FOR_LPM_AUTO	Amplifier GM setting - Used when WCO.LPM_AUTO=1 and in DeepSleep mode 0x0 - 3370 nA 0x1 - 2620 nA 0x2 - 2250 nA 0x3 - 1500 nA 0x4 - 1870 nA 0x5 - 1120 nA 0x6 - 750 nA 0x7 - 0 nA Default Value: 2
5 : 4	LPM_GM	GM setting for LPM (bandwidth = DC/ms) - Used when WCO.LPM_AUTO=0 or when LPM_AUTO=1 and not in DeepSleep mode. Default Value: 1

28.1.9 WCO_TRIM (continued)

2 : 0	XGM	Amplifier GM setting - Used when WCO.LPM_AUTO=0 or when LPM_AUTO=1 and not in Deep-Sleep mode. 0x0 - 3370 nA 0x1 - 2620 nA 0x2 - 2250 nA 0x3 - 1500 nA 0x4 - 1870 nA 0x5 - 1120 nA 0x6 - 750 nA 0x7 - 0 nA Default Value: 1

Revision History

Revision History

Document Title: CY8C4Axx PSoC® Analog Coprocessor Registers Technical Reference Manual (TRM) Document Number: 002-10405				
Revision	**ECN#**	**Issue Date**	**Origin of Change**	**Description of Change**
**	5054816	12/18/2015	AESA	Specification for new silicon
*A	5761355	06/05/2017	SHEA	Updated logo and copyright information.
*B	6434140	01/08/2019	RJVB	Sunset review; no content update