Please note that Cypress is an Infineon Technologies Company.
The document following this cover page is marked as “Cypress” document as this is the company that originally developed the product. Please note that Infineon will continue to offer the product to new and existing customers as part of the Infineon product portfolio.

Continuity of document content
The fact that Infineon offers the following product as part of the Infineon product portfolio does not lead to any changes to this document. Future revisions will occur when appropriate, and any changes will be set out on the document history page.

Continuity of ordering part numbers
Infineon continues to support existing part numbers. Please continue to use the ordering part numbers listed in the datasheet for ordering.

PMG1 Family

PMG1-S3 Registers Technical Reference Manual (TRM)

Document Number: 002-33773 Rev. *A

September 14, 2025

Cypress Semiconductor
An Infineon Technologies Company
198 Champion Court
San Jose, CA 95134-1709
www.cypress.com
www.infineon.com

Copyrights

© Cypress Semiconductor Corporation, 2021-2025. This document is the property of Cypress Semiconductor Corporation, an Infineon Technologies company, and its affiliates (“Cypress”). This document, including any software or firmware included or referenced in this document (“Software”), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress’s patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. No computing device can be absolutely secure. Therefore, despite security measures implemented in Cypress hardware or software products, Cypress shall have no liability arising out of any security breach, such as unauthorized access to or use of a Cypress product. CYPRESS DOES NOT REPRESENT, WARRANT, OR GUARANTEE THAT CYPRESS PRODUCTS, OR SYSTEMS CREATED USING CYPRESS PRODUCTS, WILL BE FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION (collectively, “Security Breach”). Cypress disclaims any liability relating to any Security Breach, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from any Security Breach. In addition, the products described in these materials may contain design defects or errors known as errata which may cause the product to deviate from published specifications. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. “High-Risk Device” means any device or system whose failure could cause personal injury, death, or property damage. Examples of High-Risk Devices are weapons, nuclear installations, surgical implants, and other medical devices. “Critical Component” means any component of a High-Risk Device whose failure to perform can be reasonably expected to cause, directly or indirectly, the failure of the High-Risk Device, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from any use of a Cypress product as a Critical Component in a High-Risk Device. You shall indemnify and hold Cypress, including its affiliates, and its directors, officers, employees, agents, distributors, and assigns harmless from and against all claims, costs, damages, and expenses, arising out of any claim, including claims for product liability, personal injury or death, or property damage arising from any use of a Cypress product as a Critical Component in a High-Risk Device. Cypress products are not intended or authorized for use as a Critical Component in any High-Risk Device except to the limited extent that (i) Cypress’s published data sheet for the product explicitly states Cypress has qualified the product for use in a specific High-Risk Device, or (ii) Cypress has given you advance written authorization to use the product as a Critical Component in the specific High-Risk Device and you have signed a separate indemnification agreement.

Cypress, the Cypress logo, and combinations thereof, PSoC, CapSense, EZ-USB, F-RAM, Traveo, WICED, and ModusToolbox are trademarks or registered trademarks of Cypress or a subsidiary of Cypress in the United States or in other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.

Contents Overview

Register Mapping **47**
1. CM0P Registers 51
2. Timer, Counter, PWM Counter (CNT) Registers 121
3. CPU Sub System (CPUSS) Registers 277
4. CRYPTOLITE Registers 290
5. CSD Registers 319
6. CTBM Registers 374
7. DMAC Registers 398
8. DMAC_DESCR Registers 441
9. GPIO Registers 653
10. GPIO Port Registers 655
11. High Speed IO Matrix (HSIOM) Registers 776
12. HSIOM Port Registers 783
13. Low-Power Comparator Registers 802
14. PASS Registers 815
15. Peripheral Interconnect (PERI) Registers 820
16. ROM Table Registers 884
17. SAR Registers 899
18. SCB Registers 1019
19. Supervisory Flash (SFLASH) Registers 1907
20. SPC Interface (SPCIF) Registers 1972
21. SRSSLT Registers 1979
22. TCPWM Registers 2007
23. TR Group Registers 2011
24. USBDEV Registers 2044
25. USBDEV_BCD Registers 2753

Revision History **2815**

Contents

Register Mapping **47**

1. CM0P Registers **51**

1.1.1 CM0P_DWT_PID4 53
1.1.2 CM0P_DWT_PID0 54
1.1.3 CM0P_DWT_PID1 55
1.1.4 CM0P_DWT_PID2 56
1.1.5 CM0P_DWT_PID3 57
1.1.6 CM0P_DWT_CID0 58
1.1.7 CM0P_DWT_CID1 59
1.1.8 CM0P_DWT_CID2 60
1.1.9 CM0P_DWT_CID3 61
1.1.10 CM0P_BP_PID4 62
1.1.11 CM0P_BP_PID0 63
1.1.12 CM0P_BP_PID1 64
1.1.13 CM0P_BP_PID2 65
1.1.14 CM0P_BP_PID3 66
1.1.15 CM0P_BP_CID0 67
1.1.16 CM0P_BP_CID1 68
1.1.17 CM0P_BP_CID2 69
1.1.18 CM0P_BP_CID3 70
1.1.19 CM0P_SYST_CSR 71
1.1.20 CM0P_SYST_RVR 73
1.1.21 CM0P_SYST_CVR 74
1.1.22 CM0P_SYST_CALIB 75
1.1.23 CM0P_ISER 77
1.1.24 CM0P_ICER 78
1.1.25 CM0P_ISPR 79
1.1.26 CM0P_ICPR 80
1.1.27 CM0P_IPR0 81
1.1.28 CM0P_IPR1 82
1.1.29 CM0P_IPR2 83
1.1.30 CM0P_IPR3 84
1.1.31 CM0P_IPR4 85
1.1.32 CM0P_IPR5 86
1.1.33 CM0P_IPR6 87
1.1.34 CM0P_IPR7 88
1.1.35 CM0P_CPUID 89
1.1.36 CM0P_ICSR 90
1.1.37 CM0P_AIRCR 92
1.1.38 CM0P_SCR 93
1.1.39 CM0P_CCR 94
1.1.40 CM0P_SHPR2 95

1.1.41 CM0P_SHPR3 96
1.1.42 CM0P_SHCSR 97
1.1.43 CM0P_SCS_PID4 98
1.1.44 CM0P_SCS_PID0 99
1.1.45 CM0P_SCS_PID1 100
1.1.46 CM0P_SCS_PID2 101
1.1.47 CM0P_SCS_PID3 102
1.1.48 CM0P_SCS_CID0 103
1.1.49 CM0P_SCS_CID1 104
1.1.50 CM0P_SCS_CID2 105
1.1.51 CM0P_SCS_CID3 106
1.1.52 CM0P_ROM_SCS 107
1.1.53 CM0P_ROM_DWT 108
1.1.54 CM0P_ROM_BPU 109
1.1.55 CM0P_ROM_END 110
1.1.56 CM0P_ROM_CSMT 111
1.1.57 CM0P_ROM_PID4 112
1.1.58 CM0P_ROM_PID0 113
1.1.59 CM0P_ROM_PID1 114
1.1.60 CM0P_ROM_PID2 115
1.1.61 CM0P_ROM_PID3 116
1.1.62 CM0P_ROM_CID0 117
1.1.63 CM0P_ROM_CID1 118
1.1.64 CM0P_ROM_CID2 119
1.1.65 CM0P_ROM_CID3 120

2. Timer, Counter, PWM Counter (CNT) Registers 121

2.1.1 TCPWM_CNT0_CTRL 125
2.1.2 TCPWM_CNT0_STATUS 128
2.1.3 TCPWM_CNT0_COUNTER 129
2.1.4 TCPWM_CNT0_CC 130
2.1.5 TCPWM_CNT0_CC_BUFF 131
2.1.6 TCPWM_CNT0_PERIOD 132
2.1.7 TCPWM_CNT0_PERIOD_BUFF 133
2.1.8 TCPWM_CNT0_TR_CTRL0 134
2.1.9 TCPWM_CNT0_TR_CTRL1 136
2.1.10 TCPWM_CNT0_TR_CTRL2 138
2.1.11 TCPWM_CNT0_INTR 140
2.1.12 TCPWM_CNT0_INTR_SET 141
2.1.13 TCPWM_CNT0_INTR_MASK 142
2.1.14 TCPWM_CNT0_INTR_MASKED 143
2.1.15 TCPWM_CNT1_CTRL 144
2.1.16 TCPWM_CNT1_STATUS 147
2.1.17 TCPWM_CNT1_COUNTER 148
2.1.18 TCPWM_CNT1_CC 149
2.1.19 TCPWM_CNT1_CC_BUFF 150
2.1.20 TCPWM_CNT1_PERIOD 151
2.1.21 TCPWM_CNT1_PERIOD_BUFF 152
2.1.22 TCPWM_CNT1_TR_CTRL0 153
2.1.23 TCPWM_CNT1_TR_CTRL1 155
2.1.24 TCPWM_CNT1_TR_CTRL2 157
2.1.25 TCPWM_CNT1_INTR 159
2.1.26 TCPWM_CNT1_INTR_SET 160

2.1.27 TCPWM_CNT1_INTR_MASK 161
2.1.28 TCPWM_CNT1_INTR_MASKED 162
2.1.29 TCPWM_CNT2_CTRL 163
2.1.30 TCPWM_CNT2_STATUS 166
2.1.31 TCPWM_CNT2_COUNTER 167
2.1.32 TCPWM_CNT2_CC 168
2.1.33 TCPWM_CNT2_CC_BUFF 169
2.1.34 TCPWM_CNT2_PERIOD 170
2.1.35 TCPWM_CNT2_PERIOD_BUFF 171
2.1.36 TCPWM_CNT2_TR_CTRL0 172
2.1.37 TCPWM_CNT2_TR_CTRL1 174
2.1.38 TCPWM_CNT2_TR_CTRL2 176
2.1.39 TCPWM_CNT2_INTR 178
2.1.40 TCPWM_CNT2_INTR_SET 179
2.1.41 TCPWM_CNT2_INTR_MASK 180
2.1.42 TCPWM_CNT2_INTR_MASKED 181
2.1.43 TCPWM_CNT3_CTRL 182
2.1.44 TCPWM_CNT3_STATUS 185
2.1.45 TCPWM_CNT3_COUNTER 186
2.1.46 TCPWM_CNT3_CC 187
2.1.47 TCPWM_CNT3_CC_BUFF 188
2.1.48 TCPWM_CNT3_PERIOD 189
2.1.49 TCPWM_CNT3_PERIOD_BUFF 190
2.1.50 TCPWM_CNT3_TR_CTRL0 191
2.1.51 TCPWM_CNT3_TR_CTRL1 193
2.1.52 TCPWM_CNT3_TR_CTRL2 195
2.1.53 TCPWM_CNT3_INTR 197
2.1.54 TCPWM_CNT3_INTR_SET 198
2.1.55 TCPWM_CNT3_INTR_MASK 199
2.1.56 TCPWM_CNT3_INTR_MASKED 200
2.1.57 TCPWM_CNT4_CTRL 201
2.1.58 TCPWM_CNT4_STATUS 204
2.1.59 TCPWM_CNT4_COUNTER 205
2.1.60 TCPWM_CNT4_CC 206
2.1.61 TCPWM_CNT4_CC_BUFF 207
2.1.62 TCPWM_CNT4_PERIOD 208
2.1.63 TCPWM_CNT4_PERIOD_BUFF 209
2.1.64 TCPWM_CNT4_TR_CTRL0 210
2.1.65 TCPWM_CNT4_TR_CTRL1 212
2.1.66 TCPWM_CNT4_TR_CTRL2 214
2.1.67 TCPWM_CNT4_INTR 216
2.1.68 TCPWM_CNT4_INTR_SET 217
2.1.69 TCPWM_CNT4_INTR_MASK 218
2.1.70 TCPWM_CNT4_INTR_MASKED 219
2.1.71 TCPWM_CNT5_CTRL 220
2.1.72 TCPWM_CNT5_STATUS 223
2.1.73 TCPWM_CNT5_COUNTER 224
2.1.74 TCPWM_CNT5_CC 225
2.1.75 TCPWM_CNT5_CC_BUFF 226
2.1.76 TCPWM_CNT5_PERIOD 227
2.1.77 TCPWM_CNT5_PERIOD_BUFF 228
2.1.78 TCPWM_CNT5_TR_CTRL0 229
2.1.79 TCPWM_CNT5_TR_CTRL1 231

2.1.80 TCPWM_CNT5_TR_CTRL2 233
2.1.81 TCPWM_CNT5_INTR 235
2.1.82 TCPWM_CNT5_INTR_SET 236
2.1.83 TCPWM_CNT5_INTR_MASK 237
2.1.84 TCPWM_CNT5_INTR_MASKED 238
2.1.85 TCPWM_CNT6_CTRL 239
2.1.86 TCPWM_CNT6_STATUS 242
2.1.87 TCPWM_CNT6_COUNTER 243
2.1.88 TCPWM_CNT6_CC 244
2.1.89 TCPWM_CNT6_CC_BUFF 245
2.1.90 TCPWM_CNT6_PERIOD 246
2.1.91 TCPWM_CNT6_PERIOD_BUFF 247
2.1.92 TCPWM_CNT6_TR_CTRL0 248
2.1.93 TCPWM_CNT6_TR_CTRL1 250
2.1.94 TCPWM_CNT6_TR_CTRL2 252
2.1.95 TCPWM_CNT6_INTR 254
2.1.96 TCPWM_CNT6_INTR_SET 255
2.1.97 TCPWM_CNT6_INTR_MASK 256
2.1.98 TCPWM_CNT6_INTR_MASKED 257
2.1.99 TCPWM_CNT7_CTRL 258
2.1.100 TCPWM_CNT7_STATUS 261
2.1.101 TCPWM_CNT7_COUNTER 262
2.1.102 TCPWM_CNT7_CC 263
2.1.103 TCPWM_CNT7_CC_BUFF 264
2.1.104 TCPWM_CNT7_PERIOD 265
2.1.105 TCPWM_CNT7_PERIOD_BUFF 266
2.1.106 TCPWM_CNT7_TR_CTRL0 267
2.1.107 TCPWM_CNT7_TR_CTRL1 269
2.1.108 TCPWM_CNT7_TR_CTRL2 271
2.1.109 TCPWM_CNT7_INTR 273
2.1.110 TCPWM_CNT7_INTR_SET 274
2.1.111 TCPWM_CNT7_INTR_MASK 275
2.1.112 TCPWM_CNT7_INTR_MASKED 276

3. CPU Sub System (CPUSS) Registers 277

3.1.1 CPUSS_SYSREQ 278
3.1.2 CPUSS_SYSARG 280
3.1.3 CPUSS_FLASH_CTL 281
3.1.4 CPUSS_ROM_CTL 283
3.1.5 CPUSS_RAM_CTL 284
3.1.6 CPUSS_DMAC_CTL 285
3.1.7 CPUSS_SL_CTL0 286
3.1.8 CPUSS_SL_CTL1 287
3.1.9 CPUSS_SL_CTL2 288
3.1.10 CPUSS_EXT_MS_CTL 289

4. CRYPTOLITE Registers 290

4.1.1 CRYPTOLITE_CTL 291
4.1.2 CRYPTOLITE_STATUS 293
4.1.3 CRYPTOLITE_AES_DESCR 294
4.1.4 CRYPTOLITE_VU_DESCR 295
4.1.5 CRYPTOLITE_SHA_DESCR 296

4.1.6 CRYPTOLITE_INTR_ERROR 297
4.1.7 CRYPTOLITE_INTR_ERROR_SET 298
4.1.8 CRYPTOLITE_INTR_ERROR_MASK 299
4.1.9 CRYPTOLITE_INTR_ERROR_MASKED 300
4.1.10 CRYPTOLITE_TRNG_CTL0 301
4.1.11 CRYPTOLITE_TRNG_CTL1 303
4.1.12 CRYPTOLITE_TRNG_STATUS 304
4.1.13 CRYPTOLITE_TRNG_RESULT 305
4.1.14 CRYPTOLITE_TRNG_GARO_CTL 306
4.1.15 CRYPTOLITE_TRNG_FIRO_CTL 307
4.1.16 CRYPTOLITE_TRNG_MON_CTL 308
4.1.17 CRYPTOLITE_TRNG_MON_RC_CTL 309
4.1.18 CRYPTOLITE_TRNG_MON_RC_STATUS0 310
4.1.19 CRYPTOLITE_TRNG_MON_RC_STATUS1 311
4.1.20 CRYPTOLITE_TRNG_MON_AP_CTL 312
4.1.21 CRYPTOLITE_TRNG_MON_AP_STATUS0 313
4.1.22 CRYPTOLITE_TRNG_MON_AP_STATUS1 314
4.1.23 CRYPTOLITE_INTR_TRNG 315
4.1.24 CRYPTOLITE_INTR_TRNG_SET 316
4.1.25 CRYPTOLITE_INTR_TRNG_MASK 317
4.1.26 CRYPTOLITE_INTR_TRNG_MASKED 318

5. CSD Registers 319

5.1.1 CSD_CONFIG 321
5.1.2 CSD_SPARE 324
5.1.3 CSD_STATUS 325
5.1.4 CSD_STAT_SEQ 326
5.1.5 CSD_STAT_CNTS 327
5.1.6 CSD_STAT_HCNT 328
5.1.7 CSD_RESULT_VAL1 329
5.1.8 CSD_RESULT_VAL2 330
5.1.9 CSD_ADC_RES 331
5.1.10 CSD_INTR 332
5.1.11 CSD_INTR_SET 333
5.1.12 CSD_INTR_MASK 334
5.1.13 CSD_INTR_MASKED 335
5.1.14 CSD_HSCMP 336
5.1.15 CSD_AMBUF 337
5.1.16 CSD_REFGEN 338
5.1.17 CSD_CSDCMP 340
5.1.18 CSD_IDACA 342
5.1.19 CSD_IDACB 345
5.1.20 CSD_SW_RES 348
5.1.21 CSD_SENSE_PERIOD 350
5.1.22 CSD_SENSE_DUTY 352
5.1.23 CSD_SW_HS_P_SEL 354
5.1.24 CSD_SW_HS_N_SEL 356
5.1.25 CSD_SW_SHIELD_SEL 357
5.1.26 CSD_SW_HS_P_SEL1 359
5.1.27 CSD_SW_AMUXBUF_SEL 360
5.1.28 CSD_SW_BYP_SEL 361
5.1.29 CSD_SW_CMP_P_SEL 362
5.1.30 CSD_SW_CMP_N_SEL 363

5.1.31 CSD_SW_REFGEN_SEL 364
5.1.32 CSD_SW_FW_MOD_SEL 365
5.1.33 CSD_SW_FW_TANK_SEL 366
5.1.34 CSD_SW_DSI_SEL 367
5.1.35 CSD_SEQ_TIME 368
5.1.36 CSD_SEQ_INIT_CNT 369
5.1.37 CSD_SEQ_NORM_CNT 370
5.1.38 CSD_ADC_CTL 371
5.1.39 CSD_SEQ_START 372

6. CTBM Registers 374

6.1.1 CTBM0_CTB_CTRL 375
6.1.2 CTBM0_OA_RES0_CTRL 376
6.1.3 CTBM0_OA_RES1_CTRL 378
6.1.4 CTBM0_COMP_STAT 380
6.1.5 CTBM0_INTR 381
6.1.6 CTBM0_INTR_SET 382
6.1.7 CTBM0_INTR_MASK 383
6.1.8 CTBM0_INTR_MASKED 384
6.1.9 CTBM0_DFT_CTRL 385
6.1.10 CTBM0_OA0_SW 386
6.1.11 CTBM0_OA0_SW_CLEAR 387
6.1.12 CTBM0_OA1_SW 388
6.1.13 CTBM0_OA1_SW_CLEAR 389
6.1.14 CTBM0_CTB_SW_HW_CTRL 390
6.1.15 CTBM0_CTB_SW_STATUS 391
6.1.16 CTBM0_OA0_OFFSET_TRIM 392
6.1.17 CTBM0_OA0_SLOPE_OFFSET_TRIM 393
6.1.18 CTBM0_OA0_COMP_TRIM 394
6.1.19 CTBM0_OA1_OFFSET_TRIM 395
6.1.20 CTBM0_OA1_SLOPE_OFFSET_TRIM 396
6.1.21 CTBM0_OA1_COMP_TRIM 397

7. DMAC Registers 398

7.1.1 DMAC_CTL 399
7.1.2 DMAC_STATUS 400
7.1.3 DMAC_STATUS_SRC_ADDR 402
7.1.4 DMAC_STATUS_DST_ADDR 403
7.1.5 DMAC_STATUS_CH_ACT 404
7.1.6 DMAC_CH_CTL0 405
7.1.7 DMAC_CH_CTL1 407
7.1.8 DMAC_CH_CTL2 409
7.1.9 DMAC_CH_CTL3 411
7.1.10 DMAC_CH_CTL4 413
7.1.11 DMAC_CH_CTL5 415
7.1.12 DMAC_CH_CTL6 417
7.1.13 DMAC_CH_CTL7 419
7.1.14 DMAC_CH_CTL8 421
7.1.15 DMAC_CH_CTL9 423
7.1.16 DMAC_CH_CTL10 425
7.1.17 DMAC_CH_CTL11 427
7.1.18 DMAC_CH_CTL12 429

7.1.19 DMAC_CH_CTL13 431
7.1.20 DMAC_CH_CTL14 433
7.1.21 DMAC_CH_CTL15 435
7.1.22 DMAC_INTR 437
7.1.23 DMAC_INTR_SET 438
7.1.24 DMAC_INTR_MASK 439
7.1.25 DMAC_INTR_MASKED 440

8. DMAC_DESCR Registers 441

8.1.1 DMAC_DESCR0_PING_SRC 445
8.1.2 DMAC_DESCR0_PING_DST 446
8.1.3 DMAC_DESCR0_PING_CTL 447
8.1.4 DMAC_DESCR0_PING_STATUS 451
8.1.5 DMAC_DESCR0_PONG_SRC 453
8.1.6 DMAC_DESCR0_PONG_DST 454
8.1.7 DMAC_DESCR0_PONG_CTL 455
8.1.8 DMAC_DESCR0_PONG_STATUS 457
8.1.9 DMAC_DESCR1_PING_SRC 458
8.1.10 DMAC_DESCR1_PING_DST 459
8.1.11 DMAC_DESCR1_PING_CTL 460
8.1.12 DMAC_DESCR1_PING_STATUS 464
8.1.13 DMAC_DESCR1_PONG_SRC 466
8.1.14 DMAC_DESCR1_PONG_DST 467
8.1.15 DMAC_DESCR1_PONG_CTL 468
8.1.16 DMAC_DESCR1_PONG_STATUS 470
8.1.17 DMAC_DESCR2_PING_SRC 471
8.1.18 DMAC_DESCR2_PING_DST 472
8.1.19 DMAC_DESCR2_PING_CTL 473
8.1.20 DMAC_DESCR2_PING_STATUS 477
8.1.21 DMAC_DESCR2_PONG_SRC 479
8.1.22 DMAC_DESCR2_PONG_DST 480
8.1.23 DMAC_DESCR2_PONG_CTL 481
8.1.24 DMAC_DESCR2_PONG_STATUS 483
8.1.25 DMAC_DESCR3_PING_SRC 484
8.1.26 DMAC_DESCR3_PING_DST 485
8.1.27 DMAC_DESCR3_PING_CTL 486
8.1.28 DMAC_DESCR3_PING_STATUS 490
8.1.29 DMAC_DESCR3_PONG_SRC 492
8.1.30 DMAC_DESCR3_PONG_DST 493
8.1.31 DMAC_DESCR3_PONG_CTL 494
8.1.32 DMAC_DESCR3_PONG_STATUS 496
8.1.33 DMAC_DESCR4_PING_SRC 497
8.1.34 DMAC_DESCR4_PING_DST 498
8.1.35 DMAC_DESCR4_PING_CTL 499
8.1.36 DMAC_DESCR4_PING_STATUS 503
8.1.37 DMAC_DESCR4_PONG_SRC 505
8.1.38 DMAC_DESCR4_PONG_DST 506
8.1.39 DMAC_DESCR4_PONG_CTL 507
8.1.40 DMAC_DESCR4_PONG_STATUS 509
8.1.41 DMAC_DESCR5_PING_SRC 510
8.1.42 DMAC_DESCR5_PING_DST 511
8.1.43 DMAC_DESCR5_PING_CTL 512
8.1.44 DMAC_DESCR5_PING_STATUS 516

8.1.45 DMAC_DESCR5_PONG_SRC 518
8.1.46 DMAC_DESCR5_PONG_DST 519
8.1.47 DMAC_DESCR5_PONG_CTL 520
8.1.48 DMAC_DESCR5_PONG_STATUS 522
8.1.49 DMAC_DESCR6_PING_SRC 523
8.1.50 DMAC_DESCR6_PING_DST 524
8.1.51 DMAC_DESCR6_PING_CTL 525
8.1.52 DMAC_DESCR6_PING_STATUS 529
8.1.53 DMAC_DESCR6_PONG_SRC 531
8.1.54 DMAC_DESCR6_PONG_DST 532
8.1.55 DMAC_DESCR6_PONG_CTL 533
8.1.56 DMAC_DESCR6_PONG_STATUS 535
8.1.57 DMAC_DESCR7_PING_SRC 536
8.1.58 DMAC_DESCR7_PING_DST 537
8.1.59 DMAC_DESCR7_PING_CTL 538
8.1.60 DMAC_DESCR7_PING_STATUS 542
8.1.61 DMAC_DESCR7_PONG_SRC 544
8.1.62 DMAC_DESCR7_PONG_DST 545
8.1.63 DMAC_DESCR7_PONG_CTL 546
8.1.64 DMAC_DESCR7_PONG_STATUS 548
8.1.65 DMAC_DESCR8_PING_SRC 549
8.1.66 DMAC_DESCR8_PING_DST 550
8.1.67 DMAC_DESCR8_PING_CTL 551
8.1.68 DMAC_DESCR8_PING_STATUS 555
8.1.69 DMAC_DESCR8_PONG_SRC 557
8.1.70 DMAC_DESCR8_PONG_DST 558
8.1.71 DMAC_DESCR8_PONG_CTL 559
8.1.72 DMAC_DESCR8_PONG_STATUS 561
8.1.73 DMAC_DESCR9_PING_SRC 562
8.1.74 DMAC_DESCR9_PING_DST 563
8.1.75 DMAC_DESCR9_PING_CTL 564
8.1.76 DMAC_DESCR9_PING_STATUS 568
8.1.77 DMAC_DESCR9_PONG_SRC 570
8.1.78 DMAC_DESCR9_PONG_DST 571
8.1.79 DMAC_DESCR9_PONG_CTL 572
8.1.80 DMAC_DESCR9_PONG_STATUS 574
8.1.81 DMAC_DESCR10_PING_SRC 575
8.1.82 DMAC_DESCR10_PING_DST 576
8.1.83 DMAC_DESCR10_PING_CTL 577
8.1.84 DMAC_DESCR10_PING_STATUS 581
8.1.85 DMAC_DESCR10_PONG_SRC 583
8.1.86 DMAC_DESCR10_PONG_DST 584
8.1.87 DMAC_DESCR10_PONG_CTL 585
8.1.88 DMAC_DESCR10_PONG_STATUS 587
8.1.89 DMAC_DESCR11_PING_SRC 588
8.1.90 DMAC_DESCR11_PING_DST 589
8.1.91 DMAC_DESCR11_PING_CTL 590
8.1.92 DMAC_DESCR11_PING_STATUS 594
8.1.93 DMAC_DESCR11_PONG_SRC 596
8.1.94 DMAC_DESCR11_PONG_DST 597
8.1.95 DMAC_DESCR11_PONG_CTL 598
8.1.96 DMAC_DESCR11_PONG_STATUS 600
8.1.97 DMAC_DESCR12_PING_SRC 601

8.1.98 DMAC_DESCR12_PING_DST 602
8.1.99 DMAC_DESCR12_PING_CTL 603
8.1.100 DMAC_DESCR12_PING_STATUS 607
8.1.101 DMAC_DESCR12_PONG_SRC 609
8.1.102 DMAC_DESCR12_PONG_DST 610
8.1.103 DMAC_DESCR12_PONG_CTL 611
8.1.104 DMAC_DESCR12_PONG_STATUS 613
8.1.105 DMAC_DESCR13_PING_SRC 614
8.1.106 DMAC_DESCR13_PING_DST 615
8.1.107 DMAC_DESCR13_PING_CTL 616
8.1.108 DMAC_DESCR13_PING_STATUS 620
8.1.109 DMAC_DESCR13_PONG_SRC 622
8.1.110 DMAC_DESCR13_PONG_DST 623
8.1.111 DMAC_DESCR13_PONG_CTL 624
8.1.112 DMAC_DESCR13_PONG_STATUS 626
8.1.113 DMAC_DESCR14_PING_SRC 627
8.1.114 DMAC_DESCR14_PING_DST 628
8.1.115 DMAC_DESCR14_PING_CTL 629
8.1.116 DMAC_DESCR14_PING_STATUS 633
8.1.117 DMAC_DESCR14_PONG_SRC 635
8.1.118 DMAC_DESCR14_PONG_DST 636
8.1.119 DMAC_DESCR14_PONG_CTL 637
8.1.120 DMAC_DESCR14_PONG_STATUS 639
8.1.121 DMAC_DESCR15_PING_SRC 640
8.1.122 DMAC_DESCR15_PING_DST 641
8.1.123 DMAC_DESCR15_PING_CTL 642
8.1.124 DMAC_DESCR15_PING_STATUS 646
8.1.125 DMAC_DESCR15_PONG_SRC 648
8.1.126 DMAC_DESCR15_PONG_DST 649
8.1.127 DMAC_DESCR15_PONG_CTL 650
8.1.128 DMAC_DESCR15_PONG_STATUS 652

9. GPIO Registers 653

9.1.1 GPIO_INTR_CAUSE 654

10. GPIO Port Registers 655

10.1.1 GPIO_PRT0_DR 658
10.1.2 GPIO_PRT0_PS 659
10.1.3 GPIO_PRT0_PC 661
10.1.4 GPIO_PRT0_INTR_CFG 664
10.1.5 GPIO_PRT0_INTR 666
10.1.6 GPIO_PRT0_PC2 668
10.1.7 GPIO_PRT0_DR_SET 670
10.1.8 GPIO_PRT0_DR_CLR 671
10.1.9 GPIO_PRT0_DR_INV 672
10.1.10 GPIO_PRT1_DR 673
10.1.11 GPIO_PRT1_PS 674
10.1.12 GPIO_PRT1_PC 676
10.1.13 GPIO_PRT1_INTR_CFG 679
10.1.14 GPIO_PRT1_INTR 681
10.1.15 GPIO_PRT1_PC2 683
10.1.16 GPIO_PRT1_DR_SET 684

10.1.17 GPIO_PRT1_DR_CLR 685
10.1.18 GPIO_PRT1_DR_INV 686
10.1.19 GPIO_PRT2_DR 687
10.1.20 GPIO_PRT2_PS 688
10.1.21 GPIO_PRT2_PC 690
10.1.22 GPIO_PRT2_INTR_CFG 693
10.1.23 GPIO_PRT2_INTR 695
10.1.24 GPIO_PRT2_PC2 697
10.1.25 GPIO_PRT2_DR_SET 699
10.1.26 GPIO_PRT2_DR_CLR 700
10.1.27 GPIO_PRT2_DR_INV 701
10.1.28 GPIO_PRT3_DR 702
10.1.29 GPIO_PRT3_PS 703
10.1.30 GPIO_PRT3_PC 705
10.1.31 GPIO_PRT3_INTR_CFG 708
10.1.32 GPIO_PRT3_INTR 710
10.1.33 GPIO_PRT3_PC2 712
10.1.34 GPIO_PRT3_DR_SET 714
10.1.35 GPIO_PRT3_DR_CLR 715
10.1.36 GPIO_PRT3_DR_INV 716
10.1.37 GPIO_PRT4_DR 717
10.1.38 GPIO_PRT4_PS 718
10.1.39 GPIO_PRT4_PC 719
10.1.40 GPIO_PRT4_INTR_CFG 722
10.1.41 GPIO_PRT4_INTR 724
10.1.42 GPIO_PRT4_PC2 725
10.1.43 GPIO_PRT4_DR_SET 726
10.1.44 GPIO_PRT4_DR_CLR 727
10.1.45 GPIO_PRT4_DR_INV 728
10.1.46 GPIO_PRT5_DR 729
10.1.47 GPIO_PRT5_PS 730
10.1.48 GPIO_PRT5_PC 732
10.1.49 GPIO_PRT5_INTR_CFG 734
10.1.50 GPIO_PRT5_INTR 736
10.1.51 GPIO_PRT5_PC2 738
10.1.52 GPIO_PRT5_DR_SET 739
10.1.53 GPIO_PRT5_DR_CLR 740
10.1.54 GPIO_PRT5_DR_INV 741
10.1.55 GPIO_PRT6_DR 742
10.1.56 GPIO_PRT6_PS 743
10.1.57 GPIO_PRT6_PC 744
10.1.58 GPIO_PRT6_INTR_CFG 746
10.1.59 GPIO_PRT6_INTR 748
10.1.60 GPIO_PRT6_PC2 750
10.1.61 GPIO_PRT6_DR_SET 751
10.1.62 GPIO_PRT6_DR_CLR 752
10.1.63 GPIO_PRT6_DR_INV 753
10.1.64 GPIO_PRT7_DR 754
10.1.65 GPIO_PRT7_PS 755
10.1.66 GPIO_PRT7_PC 757
10.1.67 GPIO_PRT7_INTR_CFG 760
10.1.68 GPIO_PRT7_INTR 762
10.1.69 GPIO_PRT7_PC2 764

10.1.70 GPIO_PRT7_DR_SET 765
10.1.71 GPIO_PRT7_DR_CLR 766
10.1.72 GPIO_PRT7_DR_INV 767
10.1.73 GPIO_PRT8_DR 768
10.1.74 GPIO_PRT8_PS 769
10.1.75 GPIO_PRT8_INTR_CFG 770
10.1.76 GPIO_PRT8_INTR 772
10.1.77 GPIO_PRT8_DR_SET 773
10.1.78 GPIO_PRT8_DR_CLR 774
10.1.79 GPIO_PRT8_DR_INV 775

11. High Speed IO Matrix (HSIOM) Registers 776

11.1.1 HSIOM_AMUX_SPLIT_CTL0 777
11.1.2 HSIOM_AMUX_SPLIT_CTL1 779
11.1.3 HSIOM_AMUX_SPLIT_CTL2 781

12. HSIOM Port Registers 783

12.1.1 HSIOM_PORT_SEL0 784
12.1.2 HSIOM_PORT_SEL1 786
12.1.3 HSIOM_PORT_SEL2 788
12.1.4 HSIOM_PORT_SEL3 790
12.1.5 HSIOM_PORT_SEL4 792
12.1.6 HSIOM_PORT_SEL5 794
12.1.7 HSIOM_PORT_SEL6 796
12.1.8 HSIOM_PORT_SEL7 798
12.1.9 HSIOM_PORT_SEL8 800

13. Low-Power Comparator Registers 802

13.1.1 LPCOMP_ID 803
13.1.2 LPCOMP_CONFIG 804
13.1.3 LPCOMP_INTR 807
13.1.4 LPCOMP_INTR_SET 808
13.1.5 LPCOMP_INTR_MASK 809
13.1.6 LPCOMP_INTR_MASKED 810
13.1.7 LPCOMP_TRIM1 811
13.1.8 LPCOMP_TRIM2 812
13.1.9 LPCOMP_TRIM3 813
13.1.10 LPCOMP_TRIM4 814

14. PASS Registers 815

14.1.1 PASS0_INTR_CAUSE 816
14.1.2 PASS0_DFT_CTRL 817
14.1.3 PASS0_PASS_CTRL 818
14.1.4 PASS0_DSAB_TRIM 819

15. Peripheral Interconnect (PERI) Registers 820

15.1.1 PERI_DIV_CMD 822
15.1.2 PERI_PCLK_CTL0 824
15.1.3 PERI_PCLK_CTL1 825
15.1.4 PERI_PCLK_CTL2 826
15.1.5 PERI_PCLK_CTL3 827

15.1.6 PERI_PCLK_CTL4 828
15.1.7 PERI_PCLK_CTL5 829
15.1.8 PERI_PCLK_CTL6 830
15.1.9 PERI_PCLK_CTL7 831
15.1.10 PERI_PCLK_CTL8 832
15.1.11 PERI_PCLK_CTL9 833
15.1.12 PERI_PCLK_CTL10 834
15.1.13 PERI_PCLK_CTL11 835
15.1.14 PERI_PCLK_CTL12 836
15.1.15 PERI_PCLK_CTL13 837
15.1.16 PERI_PCLK_CTL14 838
15.1.17 PERI_PCLK_CTL15 839
15.1.18 PERI_PCLK_CTL16 840
15.1.19 PERI_PCLK_CTL17 841
15.1.20 PERI_PCLK_CTL18 842
15.1.21 PERI_PCLK_CTL19 843
15.1.22 PERI_PCLK_CTL20 844
15.1.23 PERI_PCLK_CTL21 845
15.1.24 PERI_PCLK_CTL22 846
15.1.25 PERI_PCLK_CTL23 847
15.1.26 PERI_PCLK_CTL24 848
15.1.27 PERI_PCLK_CTL25 849
15.1.28 PERI_PCLK_CTL26 850
15.1.29 PERI_PCLK_CTL27 851
15.1.30 PERI_PCLK_CTL28 852
15.1.31 PERI_PCLK_CTL29 853
15.1.32 PERI_PCLK_CTL30 854
15.1.33 PERI_PCLK_CTL31 855
15.1.34 PERI_DIV_8_CTL0 856
15.1.35 PERI_DIV_8_CTL1 857
15.1.36 PERI_DIV_8_CTL2 858
15.1.37 PERI_DIV_8_CTL3 859
15.1.38 PERI_DIV_8_CTL4 860
15.1.39 PERI_DIV_8_CTL5 861
15.1.40 PERI_DIV_8_CTL6 862
15.1.41 PERI_DIV_8_CTL7 863
15.1.42 PERI_DIV_8_CTL8 864
15.1.43 PERI_DIV_8_CTL9 865
15.1.44 PERI_DIV_8_CTL10 866
15.1.45 PERI_DIV_8_CTL11 867
15.1.46 PERI_DIV_16_CTL0 868
15.1.47 PERI_DIV_16_CTL1 869
15.1.48 PERI_DIV_16_CTL2 870
15.1.49 PERI_DIV_16_CTL3 871
15.1.50 PERI_DIV_16_5_CTL0 872
15.1.51 PERI_DIV_16_5_CTL1 874
15.1.52 PERI_DIV_16_5_CTL2 876
15.1.53 PERI_DIV_16_5_CTL3 878
15.1.54 PERI_DIV_16_5_CTL4 880
15.1.55 PERI_TR_CTL 882

16. ROM Table Registers 884

16.1.1 ROMTABLE_ADDR 885

16.1.2 ROMTABLE_DID 886
16.1.3 ROMTABLE_PID4 887
16.1.4 ROMTABLE_PID5 888
16.1.5 ROMTABLE_PID6 889
16.1.6 ROMTABLE_PID7 890
16.1.7 ROMTABLE_PID0 891
16.1.8 ROMTABLE_PID1 892
16.1.9 ROMTABLE_PID2 893
16.1.10 ROMTABLE_PID3 894
16.1.11 ROMTABLE_CID0 895
16.1.12 ROMTABLE_CID1 896
16.1.13 ROMTABLE_CID2 897
16.1.14 ROMTABLE_CID3 898

17. SAR Registers 899

17.1.1 SAR0_CTRL 902
17.1.2 SAR0_SAMPLE_CTRL 905
17.1.3 SAR0_SAMPLE_TIME01 907
17.1.4 SAR0_SAMPLE_TIME23 908
17.1.5 SAR0_RANGE_THRES 909
17.1.6 SAR0_RANGE_COND 910
17.1.7 SAR0_CHAN_EN 911
17.1.8 SAR0_START_CTRL 912
17.1.9 SAR0_DFT_CTRL 913
17.1.10 SAR0_CHAN_CONFIG0 915
17.1.11 SAR0_CHAN_CONFIG1 917
17.1.12 SAR0_CHAN_CONFIG2 919
17.1.13 SAR0_CHAN_CONFIG3 921
17.1.14 SAR0_CHAN_CONFIG4 923
17.1.15 SAR0_CHAN_CONFIG5 925
17.1.16 SAR0_CHAN_CONFIG6 927
17.1.17 SAR0_CHAN_CONFIG7 929
17.1.18 SAR0_CHAN_CONFIG8 931
17.1.19 SAR0_CHAN_CONFIG9 933
17.1.20 SAR0_CHAN_CONFIG10 935
17.1.21 SAR0_CHAN_CONFIG11 937
17.1.22 SAR0_CHAN_CONFIG12 939
17.1.23 SAR0_CHAN_CONFIG13 941
17.1.24 SAR0_CHAN_CONFIG14 943
17.1.25 SAR0_CHAN_CONFIG15 945
17.1.26 SAR0_CHAN_WORK0 947
17.1.27 SAR0_CHAN_WORK1 948
17.1.28 SAR0_CHAN_WORK2 949
17.1.29 SAR0_CHAN_WORK3 950
17.1.30 SAR0_CHAN_WORK4 951
17.1.31 SAR0_CHAN_WORK5 952
17.1.32 SAR0_CHAN_WORK6 953
17.1.33 SAR0_CHAN_WORK7 954
17.1.34 SAR0_CHAN_WORK8 955
17.1.35 SAR0_CHAN_WORK9 956
17.1.36 SAR0_CHAN_WORK10 957
17.1.37 SAR0_CHAN_WORK11 958
17.1.38 SAR0_CHAN_WORK12 959

17.1.39 SAR0_CHAN_WORK13 960
17.1.40 SAR0_CHAN_WORK14 961
17.1.41 SAR0_CHAN_WORK15 962
17.1.42 SAR0_CHAN_RESULT0 963
17.1.43 SAR0_CHAN_RESULT1 964
17.1.44 SAR0_CHAN_RESULT2 965
17.1.45 SAR0_CHAN_RESULT3 966
17.1.46 SAR0_CHAN_RESULT4 967
17.1.47 SAR0_CHAN_RESULT5 968
17.1.48 SAR0_CHAN_RESULT6 969
17.1.49 SAR0_CHAN_RESULT7 970
17.1.50 SAR0_CHAN_RESULT8 971
17.1.51 SAR0_CHAN_RESULT9 972
17.1.52 SAR0_CHAN_RESULT10 973
17.1.53 SAR0_CHAN_RESULT11 974
17.1.54 SAR0_CHAN_RESULT12 975
17.1.55 SAR0_CHAN_RESULT13 976
17.1.56 SAR0_CHAN_RESULT14 977
17.1.57 SAR0_CHAN_RESULT15 978
17.1.58 SAR0_CHAN_WORK_VALID 979
17.1.59 SAR0_CHAN_RESULT_VALID 980
17.1.60 SAR0_STATUS 981
17.1.61 SAR0_AVG_STAT 982
17.1.62 SAR0_INTR 983
17.1.63 SAR0_INTR_SET 985
17.1.64 SAR0_INTR_MASK 987
17.1.65 SAR0_INTR_MASKED 989
17.1.66 SAR0_SATURATE_INTR 991
17.1.67 SAR0_SATURATE_INTR_SET 992
17.1.68 SAR0_SATURATE_INTR_MASK 993
17.1.69 SAR0_SATURATE_INTR_MASKED 994
17.1.70 SAR0_RANGE_INTR 995
17.1.71 SAR0_RANGE_INTR_SET 996
17.1.72 SAR0_RANGE_INTR_MASK 997
17.1.73 SAR0_RANGE_INTR_MASKED 998
17.1.74 SAR0_INTR_CAUSE 999
17.1.75 SAR0_INJ_CHAN_CONFIG 1001
17.1.76 SAR0_INJ_RESULT 1003
17.1.77 SAR0_MUX_SWITCH0 1004
17.1.78 SAR0_MUX_SWITCH_CLEAR0 1007
17.1.79 SAR0_MUX_SWITCH1 1010
17.1.80 SAR0_MUX_SWITCH_CLEAR1 1011
17.1.81 SAR0_MUX_SWITCH_HW_CTRL 1012
17.1.82 SAR0_MUX_SWITCH_STATUS 1014
17.1.83 SAR0_PUMP_CTRL 1016
17.1.84 SAR0_ANA_TRIM 1017
17.1.85 SAR0_WOUNDING 1018

18. SCB Registers 1019

18.1.1 SCB0_CTRL 1035
18.1.2 SCB0_STATUS 1039
18.1.3 SCB0_CMD_RESP_CTRL 1040
18.1.4 SCB0_CMD_RESP_STATUS 1041

18.1.5 SCB0_SPI_CTRL 1043
18.1.6 SCB0_SPI_STATUS 1046
18.1.7 SCB0_UART_CTRL 1047
18.1.8 SCB0_UART_TX_CTRL 1048
18.1.9 SCB0_UART_RX_CTRL 1049
18.1.10 SCB0_UART_RX_STATUS 1052
18.1.11 SCB0_UART_FLOW_CTRL 1053
18.1.12 SCB0_I2C_CTRL 1055
18.1.13 SCB0_I2C_STATUS 1058
18.1.14 SCB0_I2C_M_CMD 1060
18.1.15 SCB0_I2C_S_CMD 1062
18.1.16 SCB0_I2C_CFG 1063
18.1.17 SCB0_TX_CTRL 1065
18.1.18 SCB0_TX_FIFO_CTRL 1066
18.1.19 SCB0_TX_FIFO_STATUS 1067
18.1.20 SCB0_TX_FIFO_WR 1068
18.1.21 SCB0_RX_CTRL 1069
18.1.22 SCB0_RX_FIFO_CTRL 1070
18.1.23 SCB0_RX_FIFO_STATUS 1071
18.1.24 SCB0_RX_MATCH 1072
18.1.25 SCB0_RX_FIFO_RD 1073
18.1.26 SCB0_RX_FIFO_RD_SILENT 1074
18.1.27 SCB0_EZ_DATA0 1075
18.1.28 SCB0_EZ_DATA1 1076
18.1.29 SCB0_EZ_DATA2 1077
18.1.30 SCB0_EZ_DATA3 1078
18.1.31 SCB0_EZ_DATA4 1079
18.1.32 SCB0_EZ_DATA5 1080
18.1.33 SCB0_EZ_DATA6 1081
18.1.34 SCB0_EZ_DATA7 1082
18.1.35 SCB0_EZ_DATA8 1083
18.1.36 SCB0_EZ_DATA9 1084
18.1.37 SCB0_EZ_DATA10 1085
18.1.38 SCB0_EZ_DATA11 1086
18.1.39 SCB0_EZ_DATA12 1087
18.1.40 SCB0_EZ_DATA13 1088
18.1.41 SCB0_EZ_DATA14 1089
18.1.42 SCB0_EZ_DATA15 1090
18.1.43 SCB0_EZ_DATA16 1091
18.1.44 SCB0_EZ_DATA17 1092
18.1.45 SCB0_EZ_DATA18 1093
18.1.46 SCB0_EZ_DATA19 1094
18.1.47 SCB0_EZ_DATA20 1095
18.1.48 SCB0_EZ_DATA21 1096
18.1.49 SCB0_EZ_DATA22 1097
18.1.50 SCB0_EZ_DATA23 1098
18.1.51 SCB0_EZ_DATA24 1099
18.1.52 SCB0_EZ_DATA25 1100
18.1.53 SCB0_EZ_DATA26 1101
18.1.54 SCB0_EZ_DATA27 1102
18.1.55 SCB0_EZ_DATA28 1103
18.1.56 SCB0_EZ_DATA29 1104
18.1.57 SCB0_EZ_DATA30 1105

18.1.58 SCB0_EZ_DATA31 1106
18.1.59 SCB0_INTR_CAUSE 1107
18.1.60 SCB0_INTR_I2C_EC 1108
18.1.61 SCB0_INTR_I2C_EC_MASK 1110
18.1.62 SCB0_INTR_I2C_EC_MASKED 1111
18.1.63 SCB0_INTR_SPI_EC 1112
18.1.64 SCB0_INTR_SPI_EC_MASK 1114
18.1.65 SCB0_INTR_SPI_EC_MASKED 1115
18.1.66 SCB0_INTR_M 1116
18.1.67 SCB0_INTR_M_SET 1117
18.1.68 SCB0_INTR_M_MASK 1118
18.1.69 SCB0_INTR_M_MASKED 1119
18.1.70 SCB0_INTR_S 1120
18.1.71 SCB0_INTR_S_SET 1122
18.1.72 SCB0_INTR_S_MASK 1124
18.1.73 SCB0_INTR_S_MASKED 1126
18.1.74 SCB0_INTR_TX 1128
18.1.75 SCB0_INTR_TX_SET 1130
18.1.76 SCB0_INTR_TX_MASK 1132
18.1.77 SCB0_INTR_TX_MASKED 1134
18.1.78 SCB0_INTR_RX 1136
18.1.79 SCB0_INTR_RX_SET 1138
18.1.80 SCB0_INTR_RX_MASK 1140
18.1.81 SCB0_INTR_RX_MASKED 1142
18.1.82 SCB1_CTRL 1144
18.1.83 SCB1_STATUS 1148
18.1.84 SCB1_CMD_RESP_CTRL 1149
18.1.85 SCB1_CMD_RESP_STATUS 1150
18.1.86 SCB1_SPI_CTRL 1152
18.1.87 SCB1_SPI_STATUS 1155
18.1.88 SCB1_UART_CTRL 1156
18.1.89 SCB1_UART_TX_CTRL 1157
18.1.90 SCB1_UART_RX_CTRL 1158
18.1.91 SCB1_UART_RX_STATUS 1161
18.1.92 SCB1_UART_FLOW_CTRL 1162
18.1.93 SCB1_I2C_CTRL 1164
18.1.94 SCB1_I2C_STATUS 1167
18.1.95 SCB1_I2C_M_CMD 1169
18.1.96 SCB1_I2C_S_CMD 1171
18.1.97 SCB1_I2C_CFG 1172
18.1.98 SCB1_TX_CTRL 1174
18.1.99 SCB1_TX_FIFO_CTRL 1175
18.1.100 SCB1_TX_FIFO_STATUS 1176
18.1.101 SCB1_TX_FIFO_WR 1177
18.1.102 SCB1_RX_CTRL 1178
18.1.103 SCB1_RX_FIFO_CTRL 1179
18.1.104 SCB1_RX_FIFO_STATUS 1180
18.1.105 SCB1_RX_MATCH 1181
18.1.106 SCB1_RX_FIFO_RD 1182
18.1.107 SCB1_RX_FIFO_RD_SILENT 1183
18.1.108 SCB1_EZ_DATA0 1184
18.1.109 SCB1_EZ_DATA1 1185
18.1.110 SCB1_EZ_DATA2 1186

18.1.111 SCB1_EZ_DATA3 1187
18.1.112 SCB1_EZ_DATA4 1188
18.1.113 SCB1_EZ_DATA5 1189
18.1.114 SCB1_EZ_DATA6 1190
18.1.115 SCB1_EZ_DATA7 1191
18.1.116 SCB1_EZ_DATA8 1192
18.1.117 SCB1_EZ_DATA9 1193
18.1.118 SCB1_EZ_DATA10 1194
18.1.119 SCB1_EZ_DATA11 1195
18.1.120 SCB1_EZ_DATA12 1196
18.1.121 SCB1_EZ_DATA13 1197
18.1.122 SCB1_EZ_DATA14 1198
18.1.123 SCB1_EZ_DATA15 1199
18.1.124 SCB1_EZ_DATA16 1200
18.1.125 SCB1_EZ_DATA17 1201
18.1.126 SCB1_EZ_DATA18 1202
18.1.127 SCB1_EZ_DATA19 1203
18.1.128 SCB1_EZ_DATA20 1204
18.1.129 SCB1_EZ_DATA21 1205
18.1.130 SCB1_EZ_DATA22 1206
18.1.131 SCB1_EZ_DATA23 1207
18.1.132 SCB1_EZ_DATA24 1208
18.1.133 SCB1_EZ_DATA25 1209
18.1.134 SCB1_EZ_DATA26 1210
18.1.135 SCB1_EZ_DATA27 1211
18.1.136 SCB1_EZ_DATA28 1212
18.1.137 SCB1_EZ_DATA29 1213
18.1.138 SCB1_EZ_DATA30 1214
18.1.139 SCB1_EZ_DATA31 1215
18.1.140 SCB1_INTR_CAUSE 1216
18.1.141 SCB1_INTR_I2C_EC 1217
18.1.142 SCB1_INTR_I2C_EC_MASK 1219
18.1.143 SCB1_INTR_I2C_EC_MASKED 1220
18.1.144 SCB1_INTR_SPI_EC 1221
18.1.145 SCB1_INTR_SPI_EC_MASK 1223
18.1.146 SCB1_INTR_SPI_EC_MASKED 1224
18.1.147 SCB1_INTR_M 1225
18.1.148 SCB1_INTR_M_SET 1226
18.1.149 SCB1_INTR_M_MASK 1227
18.1.150 SCB1_INTR_M_MASKED 1228
18.1.151 SCB1_INTR_S 1229
18.1.152 SCB1_INTR_S_SET 1231
18.1.153 SCB1_INTR_S_MASK 1233
18.1.154 SCB1_INTR_S_MASKED 1235
18.1.155 SCB1_INTR_TX 1237
18.1.156 SCB1_INTR_TX_SET 1239
18.1.157 SCB1_INTR_TX_MASK 1241
18.1.158 SCB1_INTR_TX_MASKED 1243
18.1.159 SCB1_INTR_RX 1245
18.1.160 SCB1_INTR_RX_SET 1247
18.1.161 SCB1_INTR_RX_MASK 1249
18.1.162 SCB1_INTR_RX_MASKED 1251
18.1.163 SCB2_CTRL 1253

18.1.164 SCB2_STATUS 1257
18.1.165 SCB2_CMD_RESP_CTRL 1258
18.1.166 SCB2_CMD_RESP_STATUS 1259
18.1.167 SCB2_SPI_CTRL 1261
18.1.168 SCB2_SPI_STATUS 1264
18.1.169 SCB2_UART_CTRL 1265
18.1.170 SCB2_UART_TX_CTRL 1266
18.1.171 SCB2_UART_RX_CTRL 1267
18.1.172 SCB2_UART_RX_STATUS 1270
18.1.173 SCB2_UART_FLOW_CTRL 1271
18.1.174 SCB2_I2C_CTRL 1273
18.1.175 SCB2_I2C_STATUS 1276
18.1.176 SCB2_I2C_M_CMD 1278
18.1.177 SCB2_I2C_S_CMD 1280
18.1.178 SCB2_I2C_CFG 1281
18.1.179 SCB2_TX_CTRL 1283
18.1.180 SCB2_TX_FIFO_CTRL 1284
18.1.181 SCB2_TX_FIFO_STATUS 1285
18.1.182 SCB2_TX_FIFO_WR 1286
18.1.183 SCB2_RX_CTRL 1287
18.1.184 SCB2_RX_FIFO_CTRL 1288
18.1.185 SCB2_RX_FIFO_STATUS 1289
18.1.186 SCB2_RX_MATCH 1290
18.1.187 SCB2_RX_FIFO_RD 1291
18.1.188 SCB2_RX_FIFO_RD_SILENT 1292
18.1.189 SCB2_EZ_DATA0 1293
18.1.190 SCB2_EZ_DATA1 1294
18.1.191 SCB2_EZ_DATA2 1295
18.1.192 SCB2_EZ_DATA3 1296
18.1.193 SCB2_EZ_DATA4 1297
18.1.194 SCB2_EZ_DATA5 1298
18.1.195 SCB2_EZ_DATA6 1299
18.1.196 SCB2_EZ_DATA7 1300
18.1.197 SCB2_EZ_DATA8 1301
18.1.198 SCB2_EZ_DATA9 1302
18.1.199 SCB2_EZ_DATA10 1303
18.1.200 SCB2_EZ_DATA11 1304
18.1.201 SCB2_EZ_DATA12 1305
18.1.202 SCB2_EZ_DATA13 1306
18.1.203 SCB2_EZ_DATA14 1307
18.1.204 SCB2_EZ_DATA15 1308
18.1.205 SCB2_EZ_DATA16 1309
18.1.206 SCB2_EZ_DATA17 1310
18.1.207 SCB2_EZ_DATA18 1311
18.1.208 SCB2_EZ_DATA19 1312
18.1.209 SCB2_EZ_DATA20 1313
18.1.210 SCB2_EZ_DATA21 1314
18.1.211 SCB2_EZ_DATA22 1315
18.1.212 SCB2_EZ_DATA23 1316
18.1.213 SCB2_EZ_DATA24 1317
18.1.214 SCB2_EZ_DATA25 1318
18.1.215 SCB2_EZ_DATA26 1319
18.1.216 SCB2_EZ_DATA27 1320

18.1.217 SCB2_EZ_DATA28 1321
18.1.218 SCB2_EZ_DATA29 1322
18.1.219 SCB2_EZ_DATA30 1323
18.1.220 SCB2_EZ_DATA31 1324
18.1.221 SCB2_INTR_CAUSE 1325
18.1.222 SCB2_INTR_I2C_EC 1326
18.1.223 SCB2_INTR_I2C_EC_MASK 1328
18.1.224 SCB2_INTR_I2C_EC_MASKED 1329
18.1.225 SCB2_INTR_SPI_EC 1330
18.1.226 SCB2_INTR_SPI_EC_MASK 1332
18.1.227 SCB2_INTR_SPI_EC_MASKED 1333
18.1.228 SCB2_INTR_M 1334
18.1.229 SCB2_INTR_M_SET 1335
18.1.230 SCB2_INTR_M_MASK 1336
18.1.231 SCB2_INTR_M_MASKED 1337
18.1.232 SCB2_INTR_S 1338
18.1.233 SCB2_INTR_S_SET 1340
18.1.234 SCB2_INTR_S_MASK 1342
18.1.235 SCB2_INTR_S_MASKED 1344
18.1.236 SCB2_INTR_TX 1346
18.1.237 SCB2_INTR_TX_SET 1348
18.1.238 SCB2_INTR_TX_MASK 1350
18.1.239 SCB2_INTR_TX_MASKED 1352
18.1.240 SCB2_INTR_RX 1354
18.1.241 SCB2_INTR_RX_SET 1356
18.1.242 SCB2_INTR_RX_MASK 1358
18.1.243 SCB2_INTR_RX_MASKED 1360
18.1.244 SCB3_CTRL 1362
18.1.245 SCB3_STATUS 1366
18.1.246 SCB3_CMD_RESP_CTRL 1367
18.1.247 SCB3_CMD_RESP_STATUS 1368
18.1.248 SCB3_SPI_CTRL 1370
18.1.249 SCB3_SPI_STATUS 1373
18.1.250 SCB3_UART_CTRL 1374
18.1.251 SCB3_UART_TX_CTRL 1375
18.1.252 SCB3_UART_RX_CTRL 1376
18.1.253 SCB3_UART_RX_STATUS 1379
18.1.254 SCB3_UART_FLOW_CTRL 1380
18.1.255 SCB3_I2C_CTRL 1382
18.1.256 SCB3_I2C_STATUS 1385
18.1.257 SCB3_I2C_M_CMD 1387
18.1.258 SCB3_I2C_S_CMD 1389
18.1.259 SCB3_I2C_CFG 1390
18.1.260 SCB3_TX_CTRL 1392
18.1.261 SCB3_TX_FIFO_CTRL 1393
18.1.262 SCB3_TX_FIFO_STATUS 1394
18.1.263 SCB3_TX_FIFO_WR 1395
18.1.264 SCB3_RX_CTRL 1396
18.1.265 SCB3_RX_FIFO_CTRL 1397
18.1.266 SCB3_RX_FIFO_STATUS 1398
18.1.267 SCB3_RX_MATCH 1399
18.1.268 SCB3_RX_FIFO_RD 1400
18.1.269 SCB3_RX_FIFO_RD_SILENT 1401

18.1.270 SCB3_EZ_DATA0 1402
18.1.271 SCB3_EZ_DATA1 1403
18.1.272 SCB3_EZ_DATA2 1404
18.1.273 SCB3_EZ_DATA3 1405
18.1.274 SCB3_EZ_DATA4 1406
18.1.275 SCB3_EZ_DATA5 1407
18.1.276 SCB3_EZ_DATA6 1408
18.1.277 SCB3_EZ_DATA7 1409
18.1.278 SCB3_EZ_DATA8 1410
18.1.279 SCB3_EZ_DATA9 1411
18.1.280 SCB3_EZ_DATA10 1412
18.1.281 SCB3_EZ_DATA11 1413
18.1.282 SCB3_EZ_DATA12 1414
18.1.283 SCB3_EZ_DATA13 1415
18.1.284 SCB3_EZ_DATA14 1416
18.1.285 SCB3_EZ_DATA15 1417
18.1.286 SCB3_EZ_DATA16 1418
18.1.287 SCB3_EZ_DATA17 1419
18.1.288 SCB3_EZ_DATA18 1420
18.1.289 SCB3_EZ_DATA19 1421
18.1.290 SCB3_EZ_DATA20 1422
18.1.291 SCB3_EZ_DATA21 1423
18.1.292 SCB3_EZ_DATA22 1424
18.1.293 SCB3_EZ_DATA23 1425
18.1.294 SCB3_EZ_DATA24 1426
18.1.295 SCB3_EZ_DATA25 1427
18.1.296 SCB3_EZ_DATA26 1428
18.1.297 SCB3_EZ_DATA27 1429
18.1.298 SCB3_EZ_DATA28 1430
18.1.299 SCB3_EZ_DATA29 1431
18.1.300 SCB3_EZ_DATA30 1432
18.1.301 SCB3_EZ_DATA31 1433
18.1.302 SCB3_INTR_CAUSE 1434
18.1.303 SCB3_INTR_I2C_EC 1435
18.1.304 SCB3_INTR_I2C_EC_MASK 1437
18.1.305 SCB3_INTR_I2C_EC_MASKED 1438
18.1.306 SCB3_INTR_SPI_EC 1439
18.1.307 SCB3_INTR_SPI_EC_MASK 1441
18.1.308 SCB3_INTR_SPI_EC_MASKED 1442
18.1.309 SCB3_INTR_M 1443
18.1.310 SCB3_INTR_M_SET 1444
18.1.311 SCB3_INTR_M_MASK 1445
18.1.312 SCB3_INTR_M_MASKED 1446
18.1.313 SCB3_INTR_S 1447
18.1.314 SCB3_INTR_S_SET 1449
18.1.315 SCB3_INTR_S_MASK 1451
18.1.316 SCB3_INTR_S_MASKED 1453
18.1.317 SCB3_INTR_TX 1455
18.1.318 SCB3_INTR_TX_SET 1457
18.1.319 SCB3_INTR_TX_MASK 1459
18.1.320 SCB3_INTR_TX_MASKED 1461
18.1.321 SCB3_INTR_RX 1463
18.1.322 SCB3_INTR_RX_SET 1465

18.1.323 SCB3_INTR_RX_MASK 1467
18.1.324 SCB3_INTR_RX_MASKED 1469
18.1.325 SCB4_CTRL 1471
18.1.326 SCB4_STATUS 1475
18.1.327 SCB4_CMD_RESP_CTRL 1476
18.1.328 SCB4_CMD_RESP_STATUS 1477
18.1.329 SCB4_SPI_CTRL 1479
18.1.330 SCB4_SPI_STATUS 1482
18.1.331 SCB4_UART_CTRL 1483
18.1.332 SCB4_UART_TX_CTRL 1484
18.1.333 SCB4_UART_RX_CTRL 1485
18.1.334 SCB4_UART_RX_STATUS 1488
18.1.335 SCB4_UART_FLOW_CTRL 1489
18.1.336 SCB4_I2C_CTRL 1491
18.1.337 SCB4_I2C_STATUS 1494
18.1.338 SCB4_I2C_M_CMD 1496
18.1.339 SCB4_I2C_S_CMD 1498
18.1.340 SCB4_I2C_CFG 1499
18.1.341 SCB4_TX_CTRL 1501
18.1.342 SCB4_TX_FIFO_CTRL 1502
18.1.343 SCB4_TX_FIFO_STATUS 1503
18.1.344 SCB4_TX_FIFO_WR 1504
18.1.345 SCB4_RX_CTRL 1505
18.1.346 SCB4_RX_FIFO_CTRL 1506
18.1.347 SCB4_RX_FIFO_STATUS 1507
18.1.348 SCB4_RX_MATCH 1508
18.1.349 SCB4_RX_FIFO_RD 1509
18.1.350 SCB4_RX_FIFO_RD_SILENT 1510
18.1.351 SCB4_EZ_DATA0 1511
18.1.352 SCB4_EZ_DATA1 1512
18.1.353 SCB4_EZ_DATA2 1513
18.1.354 SCB4_EZ_DATA3 1514
18.1.355 SCB4_EZ_DATA4 1515
18.1.356 SCB4_EZ_DATA5 1516
18.1.357 SCB4_EZ_DATA6 1517
18.1.358 SCB4_EZ_DATA7 1518
18.1.359 SCB4_EZ_DATA8 1519
18.1.360 SCB4_EZ_DATA9 1520
18.1.361 SCB4_EZ_DATA10 1521
18.1.362 SCB4_EZ_DATA11 1522
18.1.363 SCB4_EZ_DATA12 1523
18.1.364 SCB4_EZ_DATA13 1524
18.1.365 SCB4_EZ_DATA14 1525
18.1.366 SCB4_EZ_DATA15 1526
18.1.367 SCB4_EZ_DATA16 1527
18.1.368 SCB4_EZ_DATA17 1528
18.1.369 SCB4_EZ_DATA18 1529
18.1.370 SCB4_EZ_DATA19 1530
18.1.371 SCB4_EZ_DATA20 1531
18.1.372 SCB4_EZ_DATA21 1532
18.1.373 SCB4_EZ_DATA22 1533
18.1.374 SCB4_EZ_DATA23 1534
18.1.375 SCB4_EZ_DATA24 1535

18.1.376 SCB4_EZ_DATA25 1536
18.1.377 SCB4_EZ_DATA26 1537
18.1.378 SCB4_EZ_DATA27 1538
18.1.379 SCB4_EZ_DATA28 1539
18.1.380 SCB4_EZ_DATA29 1540
18.1.381 SCB4_EZ_DATA30 1541
18.1.382 SCB4_EZ_DATA31 1542
18.1.383 SCB4_INTR_CAUSE 1543
18.1.384 SCB4_INTR_I2C_EC 1544
18.1.385 SCB4_INTR_I2C_EC_MASK 1546
18.1.386 SCB4_INTR_I2C_EC_MASKED 1547
18.1.387 SCB4_INTR_SPI_EC 1548
18.1.388 SCB4_INTR_SPI_EC_MASK 1550
18.1.389 SCB4_INTR_SPI_EC_MASKED 1551
18.1.390 SCB4_INTR_M 1552
18.1.391 SCB4_INTR_M_SET 1553
18.1.392 SCB4_INTR_M_MASK 1554
18.1.393 SCB4_INTR_M_MASKED 1555
18.1.394 SCB4_INTR_S 1556
18.1.395 SCB4_INTR_S_SET 1558
18.1.396 SCB4_INTR_S_MASK 1560
18.1.397 SCB4_INTR_S_MASKED 1562
18.1.398 SCB4_INTR_TX 1564
18.1.399 SCB4_INTR_TX_SET 1566
18.1.400 SCB4_INTR_TX_MASK 1568
18.1.401 SCB4_INTR_TX_MASKED 1570
18.1.402 SCB4_INTR_RX 1572
18.1.403 SCB4_INTR_RX_SET 1574
18.1.404 SCB4_INTR_RX_MASK 1576
18.1.405 SCB4_INTR_RX_MASKED 1578
18.1.406 SCB5_CTRL 1580
18.1.407 SCB5_STATUS 1584
18.1.408 SCB5_CMD_RESP_CTRL 1585
18.1.409 SCB5_CMD_RESP_STATUS 1586
18.1.410 SCB5_SPI_CTRL 1588
18.1.411 SCB5_SPI_STATUS 1591
18.1.412 SCB5_UART_CTRL 1592
18.1.413 SCB5_UART_TX_CTRL 1593
18.1.414 SCB5_UART_RX_CTRL 1594
18.1.415 SCB5_UART_RX_STATUS 1597
18.1.416 SCB5_UART_FLOW_CTRL 1598
18.1.417 SCB5_I2C_CTRL 1600
18.1.418 SCB5_I2C_STATUS 1603
18.1.419 SCB5_I2C_M_CMD 1605
18.1.420 SCB5_I2C_S_CMD 1607
18.1.421 SCB5_I2C_CFG 1608
18.1.422 SCB5_TX_CTRL 1610
18.1.423 SCB5_TX_FIFO_CTRL 1611
18.1.424 SCB5_TX_FIFO_STATUS 1612
18.1.425 SCB5_TX_FIFO_WR 1613
18.1.426 SCB5_RX_CTRL 1614
18.1.427 SCB5_RX_FIFO_CTRL 1615
18.1.428 SCB5_RX_FIFO_STATUS 1616

18.1.429 SCB5_RX_MATCH 1617
18.1.430 SCB5_RX_FIFO_RD 1618
18.1.431 SCB5_RX_FIFO_RD_SILENT 1619
18.1.432 SCB5_EZ_DATA0 1620
18.1.433 SCB5_EZ_DATA1 1621
18.1.434 SCB5_EZ_DATA2 1622
18.1.435 SCB5_EZ_DATA3 1623
18.1.436 SCB5_EZ_DATA4 1624
18.1.437 SCB5_EZ_DATA5 1625
18.1.438 SCB5_EZ_DATA6 1626
18.1.439 SCB5_EZ_DATA7 1627
18.1.440 SCB5_EZ_DATA8 1628
18.1.441 SCB5_EZ_DATA9 1629
18.1.442 SCB5_EZ_DATA10 1630
18.1.443 SCB5_EZ_DATA11 1631
18.1.444 SCB5_EZ_DATA12 1632
18.1.445 SCB5_EZ_DATA13 1633
18.1.446 SCB5_EZ_DATA14 1634
18.1.447 SCB5_EZ_DATA15 1635
18.1.448 SCB5_EZ_DATA16 1636
18.1.449 SCB5_EZ_DATA17 1637
18.1.450 SCB5_EZ_DATA18 1638
18.1.451 SCB5_EZ_DATA19 1639
18.1.452 SCB5_EZ_DATA20 1640
18.1.453 SCB5_EZ_DATA21 1641
18.1.454 SCB5_EZ_DATA22 1642
18.1.455 SCB5_EZ_DATA23 1643
18.1.456 SCB5_EZ_DATA24 1644
18.1.457 SCB5_EZ_DATA25 1645
18.1.458 SCB5_EZ_DATA26 1646
18.1.459 SCB5_EZ_DATA27 1647
18.1.460 SCB5_EZ_DATA28 1648
18.1.461 SCB5_EZ_DATA29 1649
18.1.462 SCB5_EZ_DATA30 1650
18.1.463 SCB5_EZ_DATA31 1651
18.1.464 SCB5_INTR_CAUSE 1652
18.1.465 SCB5_INTR_I2C_EC 1653
18.1.466 SCB5_INTR_I2C_EC_MASK 1655
18.1.467 SCB5_INTR_I2C_EC_MASKED 1656
18.1.468 SCB5_INTR_SPI_EC 1657
18.1.469 SCB5_INTR_SPI_EC_MASK 1659
18.1.470 SCB5_INTR_SPI_EC_MASKED 1660
18.1.471 SCB5_INTR_M 1661
18.1.472 SCB5_INTR_M_SET 1662
18.1.473 SCB5_INTR_M_MASK 1663
18.1.474 SCB5_INTR_M_MASKED 1664
18.1.475 SCB5_INTR_S 1665
18.1.476 SCB5_INTR_S_SET 1667
18.1.477 SCB5_INTR_S_MASK 1669
18.1.478 SCB5_INTR_S_MASKED 1671
18.1.479 SCB5_INTR_TX 1673
18.1.480 SCB5_INTR_TX_SET 1675
18.1.481 SCB5_INTR_TX_MASK 1677

18.1.482 SCB5_INTR_TX_MASKED 1679
18.1.483 SCB5_INTR_RX 1681
18.1.484 SCB5_INTR_RX_SET 1683
18.1.485 SCB5_INTR_RX_MASK 1685
18.1.486 SCB5_INTR_RX_MASKED 1687
18.1.487 SCB6_CTRL 1689
18.1.488 SCB6_STATUS 1693
18.1.489 SCB6_CMD_RESP_CTRL 1694
18.1.490 SCB6_CMD_RESP_STATUS 1695
18.1.491 SCB6_SPI_CTRL 1697
18.1.492 SCB6_SPI_STATUS 1700
18.1.493 SCB6_UART_CTRL 1701
18.1.494 SCB6_UART_TX_CTRL 1702
18.1.495 SCB6_UART_RX_CTRL 1703
18.1.496 SCB6_UART_RX_STATUS 1706
18.1.497 SCB6_UART_FLOW_CTRL 1707
18.1.498 SCB6_I2C_CTRL 1709
18.1.499 SCB6_I2C_STATUS 1712
18.1.500 SCB6_I2C_M_CMD 1714
18.1.501 SCB6_I2C_S_CMD 1716
18.1.502 SCB6_I2C_CFG 1717
18.1.503 SCB6_TX_CTRL 1719
18.1.504 SCB6_TX_FIFO_CTRL 1720
18.1.505 SCB6_TX_FIFO_STATUS 1721
18.1.506 SCB6_TX_FIFO_WR 1722
18.1.507 SCB6_RX_CTRL 1723
18.1.508 SCB6_RX_FIFO_CTRL 1724
18.1.509 SCB6_RX_FIFO_STATUS 1725
18.1.510 SCB6_RX_MATCH 1726
18.1.511 SCB6_RX_FIFO_RD 1727
18.1.512 SCB6_RX_FIFO_RD_SILENT 1728
18.1.513 SCB6_EZ_DATA0 1729
18.1.514 SCB6_EZ_DATA1 1730
18.1.515 SCB6_EZ_DATA2 1731
18.1.516 SCB6_EZ_DATA3 1732
18.1.517 SCB6_EZ_DATA4 1733
18.1.518 SCB6_EZ_DATA5 1734
18.1.519 SCB6_EZ_DATA6 1735
18.1.520 SCB6_EZ_DATA7 1736
18.1.521 SCB6_EZ_DATA8 1737
18.1.522 SCB6_EZ_DATA9 1738
18.1.523 SCB6_EZ_DATA10 1739
18.1.524 SCB6_EZ_DATA11 1740
18.1.525 SCB6_EZ_DATA12 1741
18.1.526 SCB6_EZ_DATA13 1742
18.1.527 SCB6_EZ_DATA14 1743
18.1.528 SCB6_EZ_DATA15 1744
18.1.529 SCB6_EZ_DATA16 1745
18.1.530 SCB6_EZ_DATA17 1746
18.1.531 SCB6_EZ_DATA18 1747
18.1.532 SCB6_EZ_DATA19 1748
18.1.533 SCB6_EZ_DATA20 1749
18.1.534 SCB6_EZ_DATA21 1750

18.1.535 SCB6_EZ_DATA22 1751
18.1.536 SCB6_EZ_DATA23 1752
18.1.537 SCB6_EZ_DATA24 1753
18.1.538 SCB6_EZ_DATA25 1754
18.1.539 SCB6_EZ_DATA26 1755
18.1.540 SCB6_EZ_DATA27 1756
18.1.541 SCB6_EZ_DATA28 1757
18.1.542 SCB6_EZ_DATA29 1758
18.1.543 SCB6_EZ_DATA30 1759
18.1.544 SCB6_EZ_DATA31 1760
18.1.545 SCB6_INTR_CAUSE 1761
18.1.546 SCB6_INTR_I2C_EC 1762
18.1.547 SCB6_INTR_I2C_EC_MASK 1764
18.1.548 SCB6_INTR_I2C_EC_MASKED 1765
18.1.549 SCB6_INTR_SPI_EC 1766
18.1.550 SCB6_INTR_SPI_EC_MASK 1768
18.1.551 SCB6_INTR_SPI_EC_MASKED 1769
18.1.552 SCB6_INTR_M 1770
18.1.553 SCB6_INTR_M_SET 1771
18.1.554 SCB6_INTR_M_MASK 1772
18.1.555 SCB6_INTR_M_MASKED 1773
18.1.556 SCB6_INTR_S 1774
18.1.557 SCB6_INTR_S_SET 1776
18.1.558 SCB6_INTR_S_MASK 1778
18.1.559 SCB6_INTR_S_MASKED 1780
18.1.560 SCB6_INTR_TX 1782
18.1.561 SCB6_INTR_TX_SET 1784
18.1.562 SCB6_INTR_TX_MASK 1786
18.1.563 SCB6_INTR_TX_MASKED 1788
18.1.564 SCB6_INTR_RX 1790
18.1.565 SCB6_INTR_RX_SET 1792
18.1.566 SCB6_INTR_RX_MASK 1794
18.1.567 SCB6_INTR_RX_MASKED 1796
18.1.568 SCB7_CTRL 1798
18.1.569 SCB7_STATUS 1802
18.1.570 SCB7_CMD_RESP_CTRL 1803
18.1.571 SCB7_CMD_RESP_STATUS 1804
18.1.572 SCB7_SPI_CTRL 1806
18.1.573 SCB7_SPI_STATUS 1809
18.1.574 SCB7_UART_CTRL 1810
18.1.575 SCB7_UART_TX_CTRL 1811
18.1.576 SCB7_UART_RX_CTRL 1812
18.1.577 SCB7_UART_RX_STATUS 1815
18.1.578 SCB7_UART_FLOW_CTRL 1816
18.1.579 SCB7_I2C_CTRL 1818
18.1.580 SCB7_I2C_STATUS 1821
18.1.581 SCB7_I2C_M_CMD 1823
18.1.582 SCB7_I2C_S_CMD 1825
18.1.583 SCB7_I2C_CFG 1826
18.1.584 SCB7_TX_CTRL 1828
18.1.585 SCB7_TX_FIFO_CTRL 1829
18.1.586 SCB7_TX_FIFO_STATUS 1830
18.1.587 SCB7_TX_FIFO_WR 1831

18.1.588 SCB7_RX_CTRL 1832
18.1.589 SCB7_RX_FIFO_CTRL 1833
18.1.590 SCB7_RX_FIFO_STATUS 1834
18.1.591 SCB7_RX_MATCH 1835
18.1.592 SCB7_RX_FIFO_RD 1836
18.1.593 SCB7_RX_FIFO_RD_SILENT 1837
18.1.594 SCB7_EZ_DATA0 1838
18.1.595 SCB7_EZ_DATA1 1839
18.1.596 SCB7_EZ_DATA2 1840
18.1.597 SCB7_EZ_DATA3 1841
18.1.598 SCB7_EZ_DATA4 1842
18.1.599 SCB7_EZ_DATA5 1843
18.1.600 SCB7_EZ_DATA6 1844
18.1.601 SCB7_EZ_DATA7 1845
18.1.602 SCB7_EZ_DATA8 1846
18.1.603 SCB7_EZ_DATA9 1847
18.1.604 SCB7_EZ_DATA10 1848
18.1.605 SCB7_EZ_DATA11 1849
18.1.606 SCB7_EZ_DATA12 1850
18.1.607 SCB7_EZ_DATA13 1851
18.1.608 SCB7_EZ_DATA14 1852
18.1.609 SCB7_EZ_DATA15 1853
18.1.610 SCB7_EZ_DATA16 1854
18.1.611 SCB7_EZ_DATA17 1855
18.1.612 SCB7_EZ_DATA18 1856
18.1.613 SCB7_EZ_DATA19 1857
18.1.614 SCB7_EZ_DATA20 1858
18.1.615 SCB7_EZ_DATA21 1859
18.1.616 SCB7_EZ_DATA22 1860
18.1.617 SCB7_EZ_DATA23 1861
18.1.618 SCB7_EZ_DATA24 1862
18.1.619 SCB7_EZ_DATA25 1863
18.1.620 SCB7_EZ_DATA26 1864
18.1.621 SCB7_EZ_DATA27 1865
18.1.622 SCB7_EZ_DATA28 1866
18.1.623 SCB7_EZ_DATA29 1867
18.1.624 SCB7_EZ_DATA30 1868
18.1.625 SCB7_EZ_DATA31 1869
18.1.626 SCB7_INTR_CAUSE 1870
18.1.627 SCB7_INTR_I2C_EC 1871
18.1.628 SCB7_INTR_I2C_EC_MASK 1873
18.1.629 SCB7_INTR_I2C_EC_MASKED 1874
18.1.630 SCB7_INTR_SPI_EC 1875
18.1.631 SCB7_INTR_SPI_EC_MASK 1877
18.1.632 SCB7_INTR_SPI_EC_MASKED 1878
18.1.633 SCB7_INTR_M 1879
18.1.634 SCB7_INTR_M_SET 1880
18.1.635 SCB7_INTR_M_MASK 1881
18.1.636 SCB7_INTR_M_MASKED 1882
18.1.637 SCB7_INTR_S 1883
18.1.638 SCB7_INTR_S_SET 1885
18.1.639 SCB7_INTR_S_MASK 1887
18.1.640 SCB7_INTR_S_MASKED 1889

18.1.641 SCB7_INTR_TX 1891
18.1.642 SCB7_INTR_TX_SET 1893
18.1.643 SCB7_INTR_TX_MASK 1895
18.1.644 SCB7_INTR_TX_MASKED 1897
18.1.645 SCB7_INTR_RX 1899
18.1.646 SCB7_INTR_RX_SET 1901
18.1.647 SCB7_INTR_RX_MASK 1903
18.1.648 SCB7_INTR_RX_MASKED 1905

19. Supervisory Flash (SFLASH) Registers 1907

19.1.1 SFLASH_SILICON_ID 1909
19.1.2 SFLASH_HIB_KEY_DELAY 1910
19.1.3 SFLASH_DPSLP_KEY_DELAY 1911
19.1.4 SFLASH_SWD_CONFIG 1912
19.1.5 SFLASH_INITIAL_SPCIF_TRIM_M1_DAC0 1913
19.1.6 SFLASH_SWD_LISTEN 1914
19.1.7 SFLASH_FLASH_START 1915
19.1.8 SFLASH_CSDV2_CSD0_ADC_TRIM1 1916
19.1.9 SFLASH_CSDV2_CSD0_ADC_TRIM2 1917
19.1.10 SFLASH_SAR_TEMP_MULTIPLIER 1918
19.1.11 SFLASH_SAR_TEMP_OFFSET 1919
19.1.12 SFLASH_IMO_TRIM_USBMODE_24 1920
19.1.13 SFLASH_IMO_TRIM_USBMODE_48 1921
19.1.14 SFLASH_IMO_TCTRIM_LT0 1922
19.1.15 SFLASH_IMO_TCTRIM_LT1 1923
19.1.16 SFLASH_IMO_TCTRIM_LT2 1924
19.1.17 SFLASH_IMO_TCTRIM_LT3 1925
19.1.18 SFLASH_IMO_TCTRIM_LT4 1926
19.1.19 SFLASH_IMO_TCTRIM_LT5 1927
19.1.20 SFLASH_IMO_TCTRIM_LT6 1928
19.1.21 SFLASH_IMO_TCTRIM_LT7 1929
19.1.22 SFLASH_IMO_TCTRIM_LT8 1930
19.1.23 SFLASH_IMO_TCTRIM_LT9 1931
19.1.24 SFLASH_IMO_TCTRIM_LT10 1932
19.1.25 SFLASH_IMO_TCTRIM_LT11 1933
19.1.26 SFLASH_IMO_TCTRIM_LT12 1934
19.1.27 SFLASH_IMO_TCTRIM_LT13 1935
19.1.28 SFLASH_IMO_TCTRIM_LT14 1936
19.1.29 SFLASH_IMO_TCTRIM_LT15 1937
19.1.30 SFLASH_IMO_TCTRIM_LT16 1938
19.1.31 SFLASH_IMO_TCTRIM_LT17 1939
19.1.32 SFLASH_IMO_TCTRIM_LT18 1940
19.1.33 SFLASH_IMO_TCTRIM_LT19 1941
19.1.34 SFLASH_IMO_TCTRIM_LT20 1942
19.1.35 SFLASH_IMO_TCTRIM_LT21 1943
19.1.36 SFLASH_IMO_TCTRIM_LT22 1944
19.1.37 SFLASH_IMO_TCTRIM_LT23 1945
19.1.38 SFLASH_IMO_TCTRIM_LT24 1946
19.1.39 SFLASH_IMO_TRIM_LT0 1947
19.1.40 SFLASH_IMO_TRIM_LT1 1948
19.1.41 SFLASH_IMO_TRIM_LT2 1949
19.1.42 SFLASH_IMO_TRIM_LT3 1950
19.1.43 SFLASH_IMO_TRIM_LT4 1951

19.1.44 SFLASH_IMO_TRIM_LT5 1952
19.1.45 SFLASH_IMO_TRIM_LT6 1953
19.1.46 SFLASH_IMO_TRIM_LT7 1954
19.1.47 SFLASH_IMO_TRIM_LT8 1955
19.1.48 SFLASH_IMO_TRIM_LT9 1956
19.1.49 SFLASH_IMO_TRIM_LT10 1957
19.1.50 SFLASH_IMO_TRIM_LT11 1958
19.1.51 SFLASH_IMO_TRIM_LT12 1959
19.1.52 SFLASH_IMO_TRIM_LT13 1960
19.1.53 SFLASH_IMO_TRIM_LT14 1961
19.1.54 SFLASH_IMO_TRIM_LT15 1962
19.1.55 SFLASH_IMO_TRIM_LT16 1963
19.1.56 SFLASH_IMO_TRIM_LT17 1964
19.1.57 SFLASH_IMO_TRIM_LT18 1965
19.1.58 SFLASH_IMO_TRIM_LT19 1966
19.1.59 SFLASH_IMO_TRIM_LT20 1967
19.1.60 SFLASH_IMO_TRIM_LT21 1968
19.1.61 SFLASH_IMO_TRIM_LT22 1969
19.1.62 SFLASH_IMO_TRIM_LT23 1970
19.1.63 SFLASH_IMO_TRIM_LT24 1971

20. SPC Interface (SPCIF) Registers 1972

20.1.1 SPCIF_GEOMETRY 1973
20.1.2 SPCIF_INTR 1975
20.1.3 SPCIF_INTR_SET 1976
20.1.4 SPCIF_INTR_MASK 1977
20.1.5 SPCIF_INTR_MASKED 1978

21. SRSSLT Registers 1979

21.1.1 PWR_CONTROL 1980
21.1.2 PWR_KEY_DELAY 1982
21.1.3 PWR_DDFT_SELECT 1983
21.1.4 TST_MODE 1986
21.1.5 CLK_SELECT 1988
21.1.6 CLK_ILO_CONFIG 1990
21.1.7 CLK_IMO_CONFIG 1991
21.1.8 CLK_DFT_SELECT 1992
21.1.9 WDT_DISABLE_KEY 1995
21.1.10 WDT_COUNTER 1996
21.1.11 WDT_MATCH 1997
21.1.12 SRSS_INTR 1998
21.1.13 SRSS_INTR_SET 1999
21.1.14 SRSS_INTR_MASK 2000
21.1.15 RES_CAUSE 2001
21.1.16 CLK_IMO_SELECT 2002
21.1.17 CLK_IMO_TRIM1 2003
21.1.18 CLK_IMO_TRIM2 2004
21.1.19 PWR_PWRSYS_TRIM1 2005
21.1.20 CLK_IMO_TRIM3 2006

22. TCPWM Registers 2007

22.1.1 TCPWM_CTRL 2008

22.1.2 TCPWM_CMD 2009
22.1.3 TCPWM_INTR_CAUSE 2010

23. TR Group Registers 2011

23.1.1 PERI_TR_GROUP0_TR_OUT_CTL0 2013
23.1.2 PERI_TR_GROUP0_TR_OUT_CTL1 2014
23.1.3 PERI_TR_GROUP0_TR_OUT_CTL2 2015
23.1.4 PERI_TR_GROUP0_TR_OUT_CTL3 2016
23.1.5 PERI_TR_GROUP0_TR_OUT_CTL4 2017
23.1.6 PERI_TR_GROUP0_TR_OUT_CTL5 2018
23.1.7 PERI_TR_GROUP0_TR_OUT_CTL6 2019
23.1.8 PERI_TR_GROUP0_TR_OUT_CTL7 2020
23.1.9 PERI_TR_GROUP1_TR_OUT_CTL0 2021
23.1.10 PERI_TR_GROUP1_TR_OUT_CTL1 2022
23.1.11 PERI_TR_GROUP1_TR_OUT_CTL2 2023
23.1.12 PERI_TR_GROUP1_TR_OUT_CTL3 2024
23.1.13 PERI_TR_GROUP1_TR_OUT_CTL4 2025
23.1.14 PERI_TR_GROUP1_TR_OUT_CTL5 2026
23.1.15 PERI_TR_GROUP1_TR_OUT_CTL6 2027
23.1.16 PERI_TR_GROUP1_TR_OUT_CTL7 2028
23.1.17 PERI_TR_GROUP2_TR_OUT_CTL0 2029
23.1.18 PERI_TR_GROUP2_TR_OUT_CTL1 2030
23.1.19 PERI_TR_GROUP2_TR_OUT_CTL2 2031
23.1.20 PERI_TR_GROUP2_TR_OUT_CTL3 2032
23.1.21 PERI_TR_GROUP2_TR_OUT_CTL4 2033
23.1.22 PERI_TR_GROUP2_TR_OUT_CTL5 2034
23.1.23 PERI_TR_GROUP2_TR_OUT_CTL6 2035
23.1.24 PERI_TR_GROUP2_TR_OUT_CTL7 2036
23.1.25 PERI_TR_GROUP3_TR_OUT_CTL0 2037
23.1.26 PERI_TR_GROUP3_TR_OUT_CTL1 2038
23.1.27 PERI_TR_GROUP3_TR_OUT_CTL2 2039
23.1.28 PERI_TR_GROUP3_TR_OUT_CTL3 2040
23.1.29 PERI_TR_GROUP3_TR_OUT_CTL4 2041
23.1.30 PERI_TR_GROUP3_TR_OUT_CTL5 2042
23.1.31 PERI_TR_GROUP4_TR_OUT_CTL 2043

24. USBDEV Registers 2044

24.1.1 USBDEVv2_EP0_DR0 2061
24.1.2 USBDEVv2_EP0_DR1 2062
24.1.3 USBDEVv2_EP0_DR2 2063
24.1.4 USBDEVv2_EP0_DR3 2064
24.1.5 USBDEVv2_EP0_DR4 2065
24.1.6 USBDEVv2_EP0_DR5 2066
24.1.7 USBDEVv2_EP0_DR6 2067
24.1.8 USBDEVv2_EP0_DR7 2068
24.1.9 USBDEVv2_CR0 2069
24.1.10 USBDEVv2_CR1 2070
24.1.11 USBDEVv2_SIE_EP_INT_EN 2071
24.1.12 USBDEVv2_SIE_EP_INT_SR 2073
24.1.13 USBDEVv2_SIE_EP1_CNT0 2074
24.1.14 USBDEVv2_SIE_EP1_CNT1 2075
24.1.15 USBDEVv2_SIE_EP1_CR0 2076

24.1.16 USBDEVv2_USBIO_CR0 2079
24.1.17 USBDEVv2_USBIO_CR2 2081
24.1.18 USBDEVv2_USBIO_CR1 2082
24.1.19 USBDEVv2_DYN_RECONFIG 2083
24.1.20 USBDEVv2_SOF0 2084
24.1.21 USBDEVv2_SOF1 2085
24.1.22 USBDEVv2_SIE_EP2_CNT0 2086
24.1.23 USBDEVv2_SIE_EP2_CNT1 2087
24.1.24 USBDEVv2_SIE_EP2_CR0 2088
24.1.25 USBDEVv2_OSCLK_DR0 2091
24.1.26 USBDEVv2_OSCLK_DR1 2092
24.1.27 USBDEVv2_EP0_CR 2093
24.1.28 USBDEVv2_EP0_CNT 2096
24.1.29 USBDEVv2_SIE_EP3_CNT0 2097
24.1.30 USBDEVv2_SIE_EP3_CNT1 2098
24.1.31 USBDEVv2_SIE_EP3_CR0 2099
24.1.32 USBDEVv2_SIE_EP4_CNT0 2102
24.1.33 USBDEVv2_SIE_EP4_CNT1 2103
24.1.34 USBDEVv2_SIE_EP4_CR0 2104
24.1.35 USBDEVv2_SIE_EP5_CNT0 2107
24.1.36 USBDEVv2_SIE_EP5_CNT1 2108
24.1.37 USBDEVv2_SIE_EP5_CR0 2109
24.1.38 USBDEVv2_SIE_EP6_CNT0 2112
24.1.39 USBDEVv2_SIE_EP6_CNT1 2113
24.1.40 USBDEVv2_SIE_EP6_CR0 2114
24.1.41 USBDEVv2_SIE_EP7_CNT0 2117
24.1.42 USBDEVv2_SIE_EP7_CNT1 2118
24.1.43 USBDEVv2_SIE_EP7_CR0 2119
24.1.44 USBDEVv2_SIE_EP8_CNT0 2122
24.1.45 USBDEVv2_SIE_EP8_CNT1 2123
24.1.46 USBDEVv2_SIE_EP8_CR0 2124
24.1.47 USBDEVv2_ARB_EP1_CFG 2127
24.1.48 USBDEVv2_ARB_EP1_INT_EN 2129
24.1.49 USBDEVv2_ARB_EP1_SR 2130
24.1.50 USBDEVv2_ARB_RW1_WA 2131
24.1.51 USBDEVv2_ARB_RW1_WA_MSB 2132
24.1.52 USBDEVv2_ARB_RW1_RA 2133
24.1.53 USBDEVv2_ARB_RW1_RA_MSB 2134
24.1.54 USBDEVv2_ARB_RW1_DR 2135
24.1.55 USBDEVv2_BUF_SIZE 2136
24.1.56 USBDEVv2_EP_ACTIVE 2137
24.1.57 USBDEVv2_EP_TYPE 2138
24.1.58 USBDEVv2_ARB_EP2_CFG 2140
24.1.59 USBDEVv2_ARB_EP2_INT_EN 2142
24.1.60 USBDEVv2_ARB_EP2_SR 2143
24.1.61 USBDEVv2_ARB_RW2_WA 2144
24.1.62 USBDEVv2_ARB_RW2_WA_MSB 2145
24.1.63 USBDEVv2_ARB_RW2_RA 2146
24.1.64 USBDEVv2_ARB_RW2_RA_MSB 2147
24.1.65 USBDEVv2_ARB_RW2_DR 2148
24.1.66 USBDEVv2_ARB_CFG 2149
24.1.67 USBDEVv2_USB_CLK_EN 2150
24.1.68 USBDEVv2_ARB_INT_EN 2151

24.1.69 USBDEVv2_ARB_INT_SR 2153
24.1.70 USBDEVv2_ARB_EP3_CFG 2154
24.1.71 USBDEVv2_ARB_EP3_INT_EN 2156
24.1.72 USBDEVv2_ARB_EP3_SR 2157
24.1.73 USBDEVv2_ARB_RW3_WA 2158
24.1.74 USBDEVv2_ARB_RW3_WA_MSB 2159
24.1.75 USBDEVv2_ARB_RW3_RA 2160
24.1.76 USBDEVv2_ARB_RW3_RA_MSB 2161
24.1.77 USBDEVv2_ARB_RW3_DR 2162
24.1.78 USBDEVv2_CWA 2163
24.1.79 USBDEVv2_CWA_MSB 2164
24.1.80 USBDEVv2_ARB_EP4_CFG 2165
24.1.81 USBDEVv2_ARB_EP4_INT_EN 2167
24.1.82 USBDEVv2_ARB_EP4_SR 2168
24.1.83 USBDEVv2_ARB_RW4_WA 2169
24.1.84 USBDEVv2_ARB_RW4_WA_MSB 2170
24.1.85 USBDEVv2_ARB_RW4_RA 2171
24.1.86 USBDEVv2_ARB_RW4_RA_MSB 2172
24.1.87 USBDEVv2_ARB_RW4_DR 2173
24.1.88 USBDEVv2_DMA_THRES 2174
24.1.89 USBDEVv2_DMA_THRES_MSB 2175
24.1.90 USBDEVv2_ARB_EP5_CFG 2176
24.1.91 USBDEVv2_ARB_EP5_INT_EN 2178
24.1.92 USBDEVv2_ARB_EP5_SR 2179
24.1.93 USBDEVv2_ARB_RW5_WA 2180
24.1.94 USBDEVv2_ARB_RW5_WA_MSB 2181
24.1.95 USBDEVv2_ARB_RW5_RA 2182
24.1.96 USBDEVv2_ARB_RW5_RA_MSB 2183
24.1.97 USBDEVv2_ARB_RW5_DR 2184
24.1.98 USBDEVv2_BUS_RST_CNT 2185
24.1.99 USBDEVv2_ARB_EP6_CFG 2186
24.1.100 USBDEVv2_ARB_EP6_INT_EN 2188
24.1.101 USBDEVv2_ARB_EP6_SR 2189
24.1.102 USBDEVv2_ARB_RW6_WA 2190
24.1.103 USBDEVv2_ARB_RW6_WA_MSB 2191
24.1.104 USBDEVv2_ARB_RW6_RA 2192
24.1.105 USBDEVv2_ARB_RW6_RA_MSB 2193
24.1.106 USBDEVv2_ARB_RW6_DR 2194
24.1.107 USBDEVv2_ARB_EP7_CFG 2195
24.1.108 USBDEVv2_ARB_EP7_INT_EN 2197
24.1.109 USBDEVv2_ARB_EP7_SR 2198
24.1.110 USBDEVv2_ARB_RW7_WA 2199
24.1.111 USBDEVv2_ARB_RW7_WA_MSB 2200
24.1.112 USBDEVv2_ARB_RW7_RA 2201
24.1.113 USBDEVv2_ARB_RW7_RA_MSB 2202
24.1.114 USBDEVv2_ARB_RW7_DR 2203
24.1.115 USBDEVv2_ARB_EP8_CFG 2204
24.1.116 USBDEVv2_ARB_EP8_INT_EN 2206
24.1.117 USBDEVv2_ARB_EP8_SR 2207
24.1.118 USBDEVv2_ARB_RW8_WA 2208
24.1.119 USBDEVv2_ARB_RW8_WA_MSB 2209
24.1.120 USBDEVv2_ARB_RW8_RA 2210
24.1.121 USBDEVv2_ARB_RW8_RA_MSB 2211

24.1.122 USBDEVv2_ARB_RW8_DR 2212
24.1.123 USBDEVv2_MEM_DATA0 2213
24.1.124 USBDEVv2_MEM_DATA1 2214
24.1.125 USBDEVv2_MEM_DATA2 2215
24.1.126 USBDEVv2_MEM_DATA3 2216
24.1.127 USBDEVv2_MEM_DATA4 2217
24.1.128 USBDEVv2_MEM_DATA5 2218
24.1.129 USBDEVv2_MEM_DATA6 2219
24.1.130 USBDEVv2_MEM_DATA7 2220
24.1.131 USBDEVv2_MEM_DATA8 2221
24.1.132 USBDEVv2_MEM_DATA9 2222
24.1.133 USBDEVv2_MEM_DATA10 2223
24.1.134 USBDEVv2_MEM_DATA11 2224
24.1.135 USBDEVv2_MEM_DATA12 2225
24.1.136 USBDEVv2_MEM_DATA13 2226
24.1.137 USBDEVv2_MEM_DATA14 2227
24.1.138 USBDEVv2_MEM_DATA15 2228
24.1.139 USBDEVv2_MEM_DATA16 2229
24.1.140 USBDEVv2_MEM_DATA17 2230
24.1.141 USBDEVv2_MEM_DATA18 2231
24.1.142 USBDEVv2_MEM_DATA19 2232
24.1.143 USBDEVv2_MEM_DATA20 2233
24.1.144 USBDEVv2_MEM_DATA21 2234
24.1.145 USBDEVv2_MEM_DATA22 2235
24.1.146 USBDEVv2_MEM_DATA23 2236
24.1.147 USBDEVv2_MEM_DATA24 2237
24.1.148 USBDEVv2_MEM_DATA25 2238
24.1.149 USBDEVv2_MEM_DATA26 2239
24.1.150 USBDEVv2_MEM_DATA27 2240
24.1.151 USBDEVv2_MEM_DATA28 2241
24.1.152 USBDEVv2_MEM_DATA29 2242
24.1.153 USBDEVv2_MEM_DATA30 2243
24.1.154 USBDEVv2_MEM_DATA31 2244
24.1.155 USBDEVv2_MEM_DATA32 2245
24.1.156 USBDEVv2_MEM_DATA33 2246
24.1.157 USBDEVv2_MEM_DATA34 2247
24.1.158 USBDEVv2_MEM_DATA35 2248
24.1.159 USBDEVv2_MEM_DATA36 2249
24.1.160 USBDEVv2_MEM_DATA37 2250
24.1.161 USBDEVv2_MEM_DATA38 2251
24.1.162 USBDEVv2_MEM_DATA39 2252
24.1.163 USBDEVv2_MEM_DATA40 2253
24.1.164 USBDEVv2_MEM_DATA41 2254
24.1.165 USBDEVv2_MEM_DATA42 2255
24.1.166 USBDEVv2_MEM_DATA43 2256
24.1.167 USBDEVv2_MEM_DATA44 2257
24.1.168 USBDEVv2_MEM_DATA45 2258
24.1.169 USBDEVv2_MEM_DATA46 2259
24.1.170 USBDEVv2_MEM_DATA47 2260
24.1.171 USBDEVv2_MEM_DATA48 2261
24.1.172 USBDEVv2_MEM_DATA49 2262
24.1.173 USBDEVv2_MEM_DATA50 2263
24.1.174 USBDEVv2_MEM_DATA51 2264

24.1.175 USBDEVv2_MEM_DATA52 2265
24.1.176 USBDEVv2_MEM_DATA53 2266
24.1.177 USBDEVv2_MEM_DATA54 2267
24.1.178 USBDEVv2_MEM_DATA55 2268
24.1.179 USBDEVv2_MEM_DATA56 2269
24.1.180 USBDEVv2_MEM_DATA57 2270
24.1.181 USBDEVv2_MEM_DATA58 2271
24.1.182 USBDEVv2_MEM_DATA59 2272
24.1.183 USBDEVv2_MEM_DATA60 2273
24.1.184 USBDEVv2_MEM_DATA61 2274
24.1.185 USBDEVv2_MEM_DATA62 2275
24.1.186 USBDEVv2_MEM_DATA63 2276
24.1.187 USBDEVv2_MEM_DATA64 2277
24.1.188 USBDEVv2_MEM_DATA65 2278
24.1.189 USBDEVv2_MEM_DATA66 2279
24.1.190 USBDEVv2_MEM_DATA67 2280
24.1.191 USBDEVv2_MEM_DATA68 2281
24.1.192 USBDEVv2_MEM_DATA69 2282
24.1.193 USBDEVv2_MEM_DATA70 2283
24.1.194 USBDEVv2_MEM_DATA71 2284
24.1.195 USBDEVv2_MEM_DATA72 2285
24.1.196 USBDEVv2_MEM_DATA73 2286
24.1.197 USBDEVv2_MEM_DATA74 2287
24.1.198 USBDEVv2_MEM_DATA75 2288
24.1.199 USBDEVv2_MEM_DATA76 2289
24.1.200 USBDEVv2_MEM_DATA77 2290
24.1.201 USBDEVv2_MEM_DATA78 2291
24.1.202 USBDEVv2_MEM_DATA79 2292
24.1.203 USBDEVv2_MEM_DATA80 2293
24.1.204 USBDEVv2_MEM_DATA81 2294
24.1.205 USBDEVv2_MEM_DATA82 2295
24.1.206 USBDEVv2_MEM_DATA83 2296
24.1.207 USBDEVv2_MEM_DATA84 2297
24.1.208 USBDEVv2_MEM_DATA85 2298
24.1.209 USBDEVv2_MEM_DATA86 2299
24.1.210 USBDEVv2_MEM_DATA87 2300
24.1.211 USBDEVv2_MEM_DATA88 2301
24.1.212 USBDEVv2_MEM_DATA89 2302
24.1.213 USBDEVv2_MEM_DATA90 2303
24.1.214 USBDEVv2_MEM_DATA91 2304
24.1.215 USBDEVv2_MEM_DATA92 2305
24.1.216 USBDEVv2_MEM_DATA93 2306
24.1.217 USBDEVv2_MEM_DATA94 2307
24.1.218 USBDEVv2_MEM_DATA95 2308
24.1.219 USBDEVv2_MEM_DATA96 2309
24.1.220 USBDEVv2_MEM_DATA97 2310
24.1.221 USBDEVv2_MEM_DATA98 2311
24.1.222 USBDEVv2_MEM_DATA99 2312
24.1.223 USBDEVv2_MEM_DATA100 2313
24.1.224 USBDEVv2_MEM_DATA101 2314
24.1.225 USBDEVv2_MEM_DATA102 2315
24.1.226 USBDEVv2_MEM_DATA103 2316
24.1.227 USBDEVv2_MEM_DATA104 2317

24.1.228 USBDEVv2_MEM_DATA105 2318
24.1.229 USBDEVv2_MEM_DATA106 2319
24.1.230 USBDEVv2_MEM_DATA107 2320
24.1.231 USBDEVv2_MEM_DATA108 2321
24.1.232 USBDEVv2_MEM_DATA109 2322
24.1.233 USBDEVv2_MEM_DATA110 2323
24.1.234 USBDEVv2_MEM_DATA111 2324
24.1.235 USBDEVv2_MEM_DATA112 2325
24.1.236 USBDEVv2_MEM_DATA113 2326
24.1.237 USBDEVv2_MEM_DATA114 2327
24.1.238 USBDEVv2_MEM_DATA115 2328
24.1.239 USBDEVv2_MEM_DATA116 2329
24.1.240 USBDEVv2_MEM_DATA117 2330
24.1.241 USBDEVv2_MEM_DATA118 2331
24.1.242 USBDEVv2_MEM_DATA119 2332
24.1.243 USBDEVv2_MEM_DATA120 2333
24.1.244 USBDEVv2_MEM_DATA121 2334
24.1.245 USBDEVv2_MEM_DATA122 2335
24.1.246 USBDEVv2_MEM_DATA123 2336
24.1.247 USBDEVv2_MEM_DATA124 2337
24.1.248 USBDEVv2_MEM_DATA125 2338
24.1.249 USBDEVv2_MEM_DATA126 2339
24.1.250 USBDEVv2_MEM_DATA127 2340
24.1.251 USBDEVv2_MEM_DATA128 2341
24.1.252 USBDEVv2_MEM_DATA129 2342
24.1.253 USBDEVv2_MEM_DATA130 2343
24.1.254 USBDEVv2_MEM_DATA131 2344
24.1.255 USBDEVv2_MEM_DATA132 2345
24.1.256 USBDEVv2_MEM_DATA133 2346
24.1.257 USBDEVv2_MEM_DATA134 2347
24.1.258 USBDEVv2_MEM_DATA135 2348
24.1.259 USBDEVv2_MEM_DATA136 2349
24.1.260 USBDEVv2_MEM_DATA137 2350
24.1.261 USBDEVv2_MEM_DATA138 2351
24.1.262 USBDEVv2_MEM_DATA139 2352
24.1.263 USBDEVv2_MEM_DATA140 2353
24.1.264 USBDEVv2_MEM_DATA141 2354
24.1.265 USBDEVv2_MEM_DATA142 2355
24.1.266 USBDEVv2_MEM_DATA143 2356
24.1.267 USBDEVv2_MEM_DATA144 2357
24.1.268 USBDEVv2_MEM_DATA145 2358
24.1.269 USBDEVv2_MEM_DATA146 2359
24.1.270 USBDEVv2_MEM_DATA147 2360
24.1.271 USBDEVv2_MEM_DATA148 2361
24.1.272 USBDEVv2_MEM_DATA149 2362
24.1.273 USBDEVv2_MEM_DATA150 2363
24.1.274 USBDEVv2_MEM_DATA151 2364
24.1.275 USBDEVv2_MEM_DATA152 2365
24.1.276 USBDEVv2_MEM_DATA153 2366
24.1.277 USBDEVv2_MEM_DATA154 2367
24.1.278 USBDEVv2_MEM_DATA155 2368
24.1.279 USBDEVv2_MEM_DATA156 2369
24.1.280 USBDEVv2_MEM_DATA157 2370

24.1.281 USBDEVv2_MEM_DATA158 2371
24.1.282 USBDEVv2_MEM_DATA159 2372
24.1.283 USBDEVv2_MEM_DATA160 2373
24.1.284 USBDEVv2_MEM_DATA161 2374
24.1.285 USBDEVv2_MEM_DATA162 2375
24.1.286 USBDEVv2_MEM_DATA163 2376
24.1.287 USBDEVv2_MEM_DATA164 2377
24.1.288 USBDEVv2_MEM_DATA165 2378
24.1.289 USBDEVv2_MEM_DATA166 2379
24.1.290 USBDEVv2_MEM_DATA167 2380
24.1.291 USBDEVv2_MEM_DATA168 2381
24.1.292 USBDEVv2_MEM_DATA169 2382
24.1.293 USBDEVv2_MEM_DATA170 2383
24.1.294 USBDEVv2_MEM_DATA171 2384
24.1.295 USBDEVv2_MEM_DATA172 2385
24.1.296 USBDEVv2_MEM_DATA173 2386
24.1.297 USBDEVv2_MEM_DATA174 2387
24.1.298 USBDEVv2_MEM_DATA175 2388
24.1.299 USBDEVv2_MEM_DATA176 2389
24.1.300 USBDEVv2_MEM_DATA177 2390
24.1.301 USBDEVv2_MEM_DATA178 2391
24.1.302 USBDEVv2_MEM_DATA179 2392
24.1.303 USBDEVv2_MEM_DATA180 2393
24.1.304 USBDEVv2_MEM_DATA181 2394
24.1.305 USBDEVv2_MEM_DATA182 2395
24.1.306 USBDEVv2_MEM_DATA183 2396
24.1.307 USBDEVv2_MEM_DATA184 2397
24.1.308 USBDEVv2_MEM_DATA185 2398
24.1.309 USBDEVv2_MEM_DATA186 2399
24.1.310 USBDEVv2_MEM_DATA187 2400
24.1.311 USBDEVv2_MEM_DATA188 2401
24.1.312 USBDEVv2_MEM_DATA189 2402
24.1.313 USBDEVv2_MEM_DATA190 2403
24.1.314 USBDEVv2_MEM_DATA191 2404
24.1.315 USBDEVv2_MEM_DATA192 2405
24.1.316 USBDEVv2_MEM_DATA193 2406
24.1.317 USBDEVv2_MEM_DATA194 2407
24.1.318 USBDEVv2_MEM_DATA195 2408
24.1.319 USBDEVv2_MEM_DATA196 2409
24.1.320 USBDEVv2_MEM_DATA197 2410
24.1.321 USBDEVv2_MEM_DATA198 2411
24.1.322 USBDEVv2_MEM_DATA199 2412
24.1.323 USBDEVv2_MEM_DATA200 2413
24.1.324 USBDEVv2_MEM_DATA201 2414
24.1.325 USBDEVv2_MEM_DATA202 2415
24.1.326 USBDEVv2_MEM_DATA203 2416
24.1.327 USBDEVv2_MEM_DATA204 2417
24.1.328 USBDEVv2_MEM_DATA205 2418
24.1.329 USBDEVv2_MEM_DATA206 2419
24.1.330 USBDEVv2_MEM_DATA207 2420
24.1.331 USBDEVv2_MEM_DATA208 2421
24.1.332 USBDEVv2_MEM_DATA209 2422
24.1.333 USBDEVv2_MEM_DATA210 2423

24.1.334 USBDEVv2_MEM_DATA211 2424
24.1.335 USBDEVv2_MEM_DATA212 2425
24.1.336 USBDEVv2_MEM_DATA213 2426
24.1.337 USBDEVv2_MEM_DATA214 2427
24.1.338 USBDEVv2_MEM_DATA215 2428
24.1.339 USBDEVv2_MEM_DATA216 2429
24.1.340 USBDEVv2_MEM_DATA217 2430
24.1.341 USBDEVv2_MEM_DATA218 2431
24.1.342 USBDEVv2_MEM_DATA219 2432
24.1.343 USBDEVv2_MEM_DATA220 2433
24.1.344 USBDEVv2_MEM_DATA221 2434
24.1.345 USBDEVv2_MEM_DATA222 2435
24.1.346 USBDEVv2_MEM_DATA223 2436
24.1.347 USBDEVv2_MEM_DATA224 2437
24.1.348 USBDEVv2_MEM_DATA225 2438
24.1.349 USBDEVv2_MEM_DATA226 2439
24.1.350 USBDEVv2_MEM_DATA227 2440
24.1.351 USBDEVv2_MEM_DATA228 2441
24.1.352 USBDEVv2_MEM_DATA229 2442
24.1.353 USBDEVv2_MEM_DATA230 2443
24.1.354 USBDEVv2_MEM_DATA231 2444
24.1.355 USBDEVv2_MEM_DATA232 2445
24.1.356 USBDEVv2_MEM_DATA233 2446
24.1.357 USBDEVv2_MEM_DATA234 2447
24.1.358 USBDEVv2_MEM_DATA235 2448
24.1.359 USBDEVv2_MEM_DATA236 2449
24.1.360 USBDEVv2_MEM_DATA237 2450
24.1.361 USBDEVv2_MEM_DATA238 2451
24.1.362 USBDEVv2_MEM_DATA239 2452
24.1.363 USBDEVv2_MEM_DATA240 2453
24.1.364 USBDEVv2_MEM_DATA241 2454
24.1.365 USBDEVv2_MEM_DATA242 2455
24.1.366 USBDEVv2_MEM_DATA243 2456
24.1.367 USBDEVv2_MEM_DATA244 2457
24.1.368 USBDEVv2_MEM_DATA245 2458
24.1.369 USBDEVv2_MEM_DATA246 2459
24.1.370 USBDEVv2_MEM_DATA247 2460
24.1.371 USBDEVv2_MEM_DATA248 2461
24.1.372 USBDEVv2_MEM_DATA249 2462
24.1.373 USBDEVv2_MEM_DATA250 2463
24.1.374 USBDEVv2_MEM_DATA251 2464
24.1.375 USBDEVv2_MEM_DATA252 2465
24.1.376 USBDEVv2_MEM_DATA253 2466
24.1.377 USBDEVv2_MEM_DATA254 2467
24.1.378 USBDEVv2_MEM_DATA255 2468
24.1.379 USBDEVv2_MEM_DATA256 2469
24.1.380 USBDEVv2_MEM_DATA257 2470
24.1.381 USBDEVv2_MEM_DATA258 2471
24.1.382 USBDEVv2_MEM_DATA259 2472
24.1.383 USBDEVv2_MEM_DATA260 2473
24.1.384 USBDEVv2_MEM_DATA261 2474
24.1.385 USBDEVv2_MEM_DATA262 2475
24.1.386 USBDEVv2_MEM_DATA263 2476

24.1.387 USBDEVv2_MEM_DATA264 2477
24.1.388 USBDEVv2_MEM_DATA265 2478
24.1.389 USBDEVv2_MEM_DATA266 2479
24.1.390 USBDEVv2_MEM_DATA267 2480
24.1.391 USBDEVv2_MEM_DATA268 2481
24.1.392 USBDEVv2_MEM_DATA269 2482
24.1.393 USBDEVv2_MEM_DATA270 2483
24.1.394 USBDEVv2_MEM_DATA271 2484
24.1.395 USBDEVv2_MEM_DATA272 2485
24.1.396 USBDEVv2_MEM_DATA273 2486
24.1.397 USBDEVv2_MEM_DATA274 2487
24.1.398 USBDEVv2_MEM_DATA275 2488
24.1.399 USBDEVv2_MEM_DATA276 2489
24.1.400 USBDEVv2_MEM_DATA277 2490
24.1.401 USBDEVv2_MEM_DATA278 2491
24.1.402 USBDEVv2_MEM_DATA279 2492
24.1.403 USBDEVv2_MEM_DATA280 2493
24.1.404 USBDEVv2_MEM_DATA281 2494
24.1.405 USBDEVv2_MEM_DATA282 2495
24.1.406 USBDEVv2_MEM_DATA283 2496
24.1.407 USBDEVv2_MEM_DATA284 2497
24.1.408 USBDEVv2_MEM_DATA285 2498
24.1.409 USBDEVv2_MEM_DATA286 2499
24.1.410 USBDEVv2_MEM_DATA287 2500
24.1.411 USBDEVv2_MEM_DATA288 2501
24.1.412 USBDEVv2_MEM_DATA289 2502
24.1.413 USBDEVv2_MEM_DATA290 2503
24.1.414 USBDEVv2_MEM_DATA291 2504
24.1.415 USBDEVv2_MEM_DATA292 2505
24.1.416 USBDEVv2_MEM_DATA293 2506
24.1.417 USBDEVv2_MEM_DATA294 2507
24.1.418 USBDEVv2_MEM_DATA295 2508
24.1.419 USBDEVv2_MEM_DATA296 2509
24.1.420 USBDEVv2_MEM_DATA297 2510
24.1.421 USBDEVv2_MEM_DATA298 2511
24.1.422 USBDEVv2_MEM_DATA299 2512
24.1.423 USBDEVv2_MEM_DATA300 2513
24.1.424 USBDEVv2_MEM_DATA301 2514
24.1.425 USBDEVv2_MEM_DATA302 2515
24.1.426 USBDEVv2_MEM_DATA303 2516
24.1.427 USBDEVv2_MEM_DATA304 2517
24.1.428 USBDEVv2_MEM_DATA305 2518
24.1.429 USBDEVv2_MEM_DATA306 2519
24.1.430 USBDEVv2_MEM_DATA307 2520
24.1.431 USBDEVv2_MEM_DATA308 2521
24.1.432 USBDEVv2_MEM_DATA309 2522
24.1.433 USBDEVv2_MEM_DATA310 2523
24.1.434 USBDEVv2_MEM_DATA311 2524
24.1.435 USBDEVv2_MEM_DATA312 2525
24.1.436 USBDEVv2_MEM_DATA313 2526
24.1.437 USBDEVv2_MEM_DATA314 2527
24.1.438 USBDEVv2_MEM_DATA315 2528
24.1.439 USBDEVv2_MEM_DATA316 2529

24.1.440 USBDEVv2_MEM_DATA317 2530
24.1.441 USBDEVv2_MEM_DATA318 2531
24.1.442 USBDEVv2_MEM_DATA319 2532
24.1.443 USBDEVv2_MEM_DATA320 2533
24.1.444 USBDEVv2_MEM_DATA321 2534
24.1.445 USBDEVv2_MEM_DATA322 2535
24.1.446 USBDEVv2_MEM_DATA323 2536
24.1.447 USBDEVv2_MEM_DATA324 2537
24.1.448 USBDEVv2_MEM_DATA325 2538
24.1.449 USBDEVv2_MEM_DATA326 2539
24.1.450 USBDEVv2_MEM_DATA327 2540
24.1.451 USBDEVv2_MEM_DATA328 2541
24.1.452 USBDEVv2_MEM_DATA329 2542
24.1.453 USBDEVv2_MEM_DATA330 2543
24.1.454 USBDEVv2_MEM_DATA331 2544
24.1.455 USBDEVv2_MEM_DATA332 2545
24.1.456 USBDEVv2_MEM_DATA333 2546
24.1.457 USBDEVv2_MEM_DATA334 2547
24.1.458 USBDEVv2_MEM_DATA335 2548
24.1.459 USBDEVv2_MEM_DATA336 2549
24.1.460 USBDEVv2_MEM_DATA337 2550
24.1.461 USBDEVv2_MEM_DATA338 2551
24.1.462 USBDEVv2_MEM_DATA339 2552
24.1.463 USBDEVv2_MEM_DATA340 2553
24.1.464 USBDEVv2_MEM_DATA341 2554
24.1.465 USBDEVv2_MEM_DATA342 2555
24.1.466 USBDEVv2_MEM_DATA343 2556
24.1.467 USBDEVv2_MEM_DATA344 2557
24.1.468 USBDEVv2_MEM_DATA345 2558
24.1.469 USBDEVv2_MEM_DATA346 2559
24.1.470 USBDEVv2_MEM_DATA347 2560
24.1.471 USBDEVv2_MEM_DATA348 2561
24.1.472 USBDEVv2_MEM_DATA349 2562
24.1.473 USBDEVv2_MEM_DATA350 2563
24.1.474 USBDEVv2_MEM_DATA351 2564
24.1.475 USBDEVv2_MEM_DATA352 2565
24.1.476 USBDEVv2_MEM_DATA353 2566
24.1.477 USBDEVv2_MEM_DATA354 2567
24.1.478 USBDEVv2_MEM_DATA355 2568
24.1.479 USBDEVv2_MEM_DATA356 2569
24.1.480 USBDEVv2_MEM_DATA357 2570
24.1.481 USBDEVv2_MEM_DATA358 2571
24.1.482 USBDEVv2_MEM_DATA359 2572
24.1.483 USBDEVv2_MEM_DATA360 2573
24.1.484 USBDEVv2_MEM_DATA361 2574
24.1.485 USBDEVv2_MEM_DATA362 2575
24.1.486 USBDEVv2_MEM_DATA363 2576
24.1.487 USBDEVv2_MEM_DATA364 2577
24.1.488 USBDEVv2_MEM_DATA365 2578
24.1.489 USBDEVv2_MEM_DATA366 2579
24.1.490 USBDEVv2_MEM_DATA367 2580
24.1.491 USBDEVv2_MEM_DATA368 2581
24.1.492 USBDEVv2_MEM_DATA369 2582

24.1.493 USBDEVv2_MEM_DATA370 2583
24.1.494 USBDEVv2_MEM_DATA371 2584
24.1.495 USBDEVv2_MEM_DATA372 2585
24.1.496 USBDEVv2_MEM_DATA373 2586
24.1.497 USBDEVv2_MEM_DATA374 2587
24.1.498 USBDEVv2_MEM_DATA375 2588
24.1.499 USBDEVv2_MEM_DATA376 2589
24.1.500 USBDEVv2_MEM_DATA377 2590
24.1.501 USBDEVv2_MEM_DATA378 2591
24.1.502 USBDEVv2_MEM_DATA379 2592
24.1.503 USBDEVv2_MEM_DATA380 2593
24.1.504 USBDEVv2_MEM_DATA381 2594
24.1.505 USBDEVv2_MEM_DATA382 2595
24.1.506 USBDEVv2_MEM_DATA383 2596
24.1.507 USBDEVv2_MEM_DATA384 2597
24.1.508 USBDEVv2_MEM_DATA385 2598
24.1.509 USBDEVv2_MEM_DATA386 2599
24.1.510 USBDEVv2_MEM_DATA387 2600
24.1.511 USBDEVv2_MEM_DATA388 2601
24.1.512 USBDEVv2_MEM_DATA389 2602
24.1.513 USBDEVv2_MEM_DATA390 2603
24.1.514 USBDEVv2_MEM_DATA391 2604
24.1.515 USBDEVv2_MEM_DATA392 2605
24.1.516 USBDEVv2_MEM_DATA393 2606
24.1.517 USBDEVv2_MEM_DATA394 2607
24.1.518 USBDEVv2_MEM_DATA395 2608
24.1.519 USBDEVv2_MEM_DATA396 2609
24.1.520 USBDEVv2_MEM_DATA397 2610
24.1.521 USBDEVv2_MEM_DATA398 2611
24.1.522 USBDEVv2_MEM_DATA399 2612
24.1.523 USBDEVv2_MEM_DATA400 2613
24.1.524 USBDEVv2_MEM_DATA401 2614
24.1.525 USBDEVv2_MEM_DATA402 2615
24.1.526 USBDEVv2_MEM_DATA403 2616
24.1.527 USBDEVv2_MEM_DATA404 2617
24.1.528 USBDEVv2_MEM_DATA405 2618
24.1.529 USBDEVv2_MEM_DATA406 2619
24.1.530 USBDEVv2_MEM_DATA407 2620
24.1.531 USBDEVv2_MEM_DATA408 2621
24.1.532 USBDEVv2_MEM_DATA409 2622
24.1.533 USBDEVv2_MEM_DATA410 2623
24.1.534 USBDEVv2_MEM_DATA411 2624
24.1.535 USBDEVv2_MEM_DATA412 2625
24.1.536 USBDEVv2_MEM_DATA413 2626
24.1.537 USBDEVv2_MEM_DATA414 2627
24.1.538 USBDEVv2_MEM_DATA415 2628
24.1.539 USBDEVv2_MEM_DATA416 2629
24.1.540 USBDEVv2_MEM_DATA417 2630
24.1.541 USBDEVv2_MEM_DATA418 2631
24.1.542 USBDEVv2_MEM_DATA419 2632
24.1.543 USBDEVv2_MEM_DATA420 2633
24.1.544 USBDEVv2_MEM_DATA421 2634
24.1.545 USBDEVv2_MEM_DATA422 2635

24.1.546 USBDEVv2_MEM_DATA423 2636
24.1.547 USBDEVv2_MEM_DATA424 2637
24.1.548 USBDEVv2_MEM_DATA425 2638
24.1.549 USBDEVv2_MEM_DATA426 2639
24.1.550 USBDEVv2_MEM_DATA427 2640
24.1.551 USBDEVv2_MEM_DATA428 2641
24.1.552 USBDEVv2_MEM_DATA429 2642
24.1.553 USBDEVv2_MEM_DATA430 2643
24.1.554 USBDEVv2_MEM_DATA431 2644
24.1.555 USBDEVv2_MEM_DATA432 2645
24.1.556 USBDEVv2_MEM_DATA433 2646
24.1.557 USBDEVv2_MEM_DATA434 2647
24.1.558 USBDEVv2_MEM_DATA435 2648
24.1.559 USBDEVv2_MEM_DATA436 2649
24.1.560 USBDEVv2_MEM_DATA437 2650
24.1.561 USBDEVv2_MEM_DATA438 2651
24.1.562 USBDEVv2_MEM_DATA439 2652
24.1.563 USBDEVv2_MEM_DATA440 2653
24.1.564 USBDEVv2_MEM_DATA441 2654
24.1.565 USBDEVv2_MEM_DATA442 2655
24.1.566 USBDEVv2_MEM_DATA443 2656
24.1.567 USBDEVv2_MEM_DATA444 2657
24.1.568 USBDEVv2_MEM_DATA445 2658
24.1.569 USBDEVv2_MEM_DATA446 2659
24.1.570 USBDEVv2_MEM_DATA447 2660
24.1.571 USBDEVv2_MEM_DATA448 2661
24.1.572 USBDEVv2_MEM_DATA449 2662
24.1.573 USBDEVv2_MEM_DATA450 2663
24.1.574 USBDEVv2_MEM_DATA451 2664
24.1.575 USBDEVv2_MEM_DATA452 2665
24.1.576 USBDEVv2_MEM_DATA453 2666
24.1.577 USBDEVv2_MEM_DATA454 2667
24.1.578 USBDEVv2_MEM_DATA455 2668
24.1.579 USBDEVv2_MEM_DATA456 2669
24.1.580 USBDEVv2_MEM_DATA457 2670
24.1.581 USBDEVv2_MEM_DATA458 2671
24.1.582 USBDEVv2_MEM_DATA459 2672
24.1.583 USBDEVv2_MEM_DATA460 2673
24.1.584 USBDEVv2_MEM_DATA461 2674
24.1.585 USBDEVv2_MEM_DATA462 2675
24.1.586 USBDEVv2_MEM_DATA463 2676
24.1.587 USBDEVv2_MEM_DATA464 2677
24.1.588 USBDEVv2_MEM_DATA465 2678
24.1.589 USBDEVv2_MEM_DATA466 2679
24.1.590 USBDEVv2_MEM_DATA467 2680
24.1.591 USBDEVv2_MEM_DATA468 2681
24.1.592 USBDEVv2_MEM_DATA469 2682
24.1.593 USBDEVv2_MEM_DATA470 2683
24.1.594 USBDEVv2_MEM_DATA471 2684
24.1.595 USBDEVv2_MEM_DATA472 2685
24.1.596 USBDEVv2_MEM_DATA473 2686
24.1.597 USBDEVv2_MEM_DATA474 2687
24.1.598 USBDEVv2_MEM_DATA475 2688

24.1.599 USBDEVv2_MEM_DATA476 2689
24.1.600 USBDEVv2_MEM_DATA477 2690
24.1.601 USBDEVv2_MEM_DATA478 2691
24.1.602 USBDEVv2_MEM_DATA479 2692
24.1.603 USBDEVv2_MEM_DATA480 2693
24.1.604 USBDEVv2_MEM_DATA481 2694
24.1.605 USBDEVv2_MEM_DATA482 2695
24.1.606 USBDEVv2_MEM_DATA483 2696
24.1.607 USBDEVv2_MEM_DATA484 2697
24.1.608 USBDEVv2_MEM_DATA485 2698
24.1.609 USBDEVv2_MEM_DATA486 2699
24.1.610 USBDEVv2_MEM_DATA487 2700
24.1.611 USBDEVv2_MEM_DATA488 2701
24.1.612 USBDEVv2_MEM_DATA489 2702
24.1.613 USBDEVv2_MEM_DATA490 2703
24.1.614 USBDEVv2_MEM_DATA491 2704
24.1.615 USBDEVv2_MEM_DATA492 2705
24.1.616 USBDEVv2_MEM_DATA493 2706
24.1.617 USBDEVv2_MEM_DATA494 2707
24.1.618 USBDEVv2_MEM_DATA495 2708
24.1.619 USBDEVv2_MEM_DATA496 2709
24.1.620 USBDEVv2_MEM_DATA497 2710
24.1.621 USBDEVv2_MEM_DATA498 2711
24.1.622 USBDEVv2_MEM_DATA499 2712
24.1.623 USBDEVv2_MEM_DATA500 2713
24.1.624 USBDEVv2_MEM_DATA501 2714
24.1.625 USBDEVv2_MEM_DATA502 2715
24.1.626 USBDEVv2_MEM_DATA503 2716
24.1.627 USBDEVv2_MEM_DATA504 2717
24.1.628 USBDEVv2_MEM_DATA505 2718
24.1.629 USBDEVv2_MEM_DATA506 2719
24.1.630 USBDEVv2_MEM_DATA507 2720
24.1.631 USBDEVv2_MEM_DATA508 2721
24.1.632 USBDEVv2_MEM_DATA509 2722
24.1.633 USBDEVv2_MEM_DATA510 2723
24.1.634 USBDEVv2_MEM_DATA511 2724
24.1.635 USBDEVv2_SOF16 2725
24.1.636 USBDEVv2_OSCLK_DR16 2726
24.1.637 USBDEVv2_ARB_RW1_WA16 2727
24.1.638 USBDEVv2_ARB_RW1_RA16 2728
24.1.639 USBDEVv2_ARB_RW1_DR16 2729
24.1.640 USBDEVv2_ARB_RW2_WA16 2730
24.1.641 USBDEVv2_ARB_RW2_RA16 2731
24.1.642 USBDEVv2_ARB_RW2_DR16 2732
24.1.643 USBDEVv2_ARB_RW3_WA16 2733
24.1.644 USBDEVv2_ARB_RW3_RA16 2734
24.1.645 USBDEVv2_ARB_RW3_DR16 2735
24.1.646 USBDEVv2_CWA16 2736
24.1.647 USBDEVv2_ARB_RW4_WA16 2737
24.1.648 USBDEVv2_ARB_RW4_RA16 2738
24.1.649 USBDEVv2_ARB_RW4_DR16 2739
24.1.650 USBDEVv2_DMA_THRES16 2740
24.1.651 USBDEVv2_ARB_RW5_WA16 2741

24.1.652 USBDEVv2_ARB_RW5_RA16 2742
24.1.653 USBDEVv2_ARB_RW5_DR16 2743
24.1.654 USBDEVv2_ARB_RW6_WA16 2744
24.1.655 USBDEVv2_ARB_RW6_RA16 2745
24.1.656 USBDEVv2_ARB_RW6_DR16 2746
24.1.657 USBDEVv2_ARB_RW7_WA16 2747
24.1.658 USBDEVv2_ARB_RW7_RA16 2748
24.1.659 USBDEVv2_ARB_RW7_DR16 2749
24.1.660 USBDEVv2_ARB_RW8_WA16 2750
24.1.661 USBDEVv2_ARB_RW8_RA16 2751
24.1.662 USBDEVv2_ARB_RW8_DR16 2752

25. USBDEV_BCD Registers 2753

25.1.1 USBDEVv2_USB_POWER_CTRL 2755
25.1.2 USBDEVv2_USB_USBIO_CTRL 2757
25.1.3 USBDEVv2_USB_FLOW_CTRL 2758
25.1.4 USBDEVv2_USB_LPM_CTRL 2760
25.1.5 USBDEVv2_USB_LPM_STAT 2762
25.1.6 USBDEVv2_USB_INTR_SIE 2763
25.1.7 USBDEVv2_USB_INTR_SIE_SET 2764
25.1.8 USBDEVv2_USB_INTR_SIE_MASK 2765
25.1.9 USBDEVv2_USB_INTR_SIE_MASKED 2766
25.1.10 USBDEVv2_USB_INTR_LVL_SEL 2767
25.1.11 USBDEVv2_USB_INTR_CAUSE_HI 2769
25.1.12 USBDEVv2_USB_INTR_CAUSE_MED 2771
25.1.13 USBDEVv2_USB_INTR_CAUSE_LO 2773
25.1.14 USBDEVv2_USB_DFT_CTRL 2775
25.1.15 USBDEVv2_USB_PHY_TRIM0 2777
25.1.16 USBDEVv2_USB_PHY_TRIM1 2778
25.1.17 USBDEVv2_USB_PHY_TRIM2 2779
25.1.18 USBDEVv2_USB_PHY_TRIM3 2780
25.1.19 USBDEVv2_USB_CHGDET_TRIM 2781
25.1.20 USBDEVv2_USB_TRIM 2782
25.1.21 USBDEVv2_USB_USBIO_TRIM 2783
25.1.22 USBDEVv2_USB_POWER_CTRL 2785
25.1.23 USBDEVv2_USB_USBIO_CTRL 2787
25.1.24 USBDEVv2_USB_FLOW_CTRL 2788
25.1.25 USBDEVv2_USB_LPM_CTRL 2790
25.1.26 USBDEVv2_USB_LPM_STAT 2792
25.1.27 USBDEVv2_USB_INTR_SIE 2793
25.1.28 USBDEVv2_USB_INTR_SIE_SET 2794
25.1.29 USBDEVv2_USB_INTR_SIE_MASK 2795
25.1.30 USBDEVv2_USB_INTR_SIE_MASKED 2796
25.1.31 USBDEVv2_USB_INTR_LVL_SEL 2797
25.1.32 USBDEVv2_USB_INTR_CAUSE_HI 2799
25.1.33 USBDEVv2_USB_INTR_CAUSE_MED 2801
25.1.34 USBDEVv2_USB_INTR_CAUSE_LO 2803
25.1.35 USBDEVv2_USB_DFT_CTRL 2805
25.1.36 USBDEVv2_USB_PHY_TRIM0 2807
25.1.37 USBDEVv2_USB_PHY_TRIM1 2808
25.1.38 USBDEVv2_USB_PHY_TRIM2 2809
25.1.39 USBDEVv2_USB_PHY_TRIM3 2810
25.1.40 USBDEVv2_USB_CHGDET_TRIM 2811

25.1.41 USBDEVv2_USB_TRIM 2812
25.1.42 USBDEVv2_USB_USBIO_TRIM 2813

Revision History 2815

Register Mapping

The Register Mapping section discusses the registers of the PMG1-S3 device. This document should be used in conjunction with PMG1 Family PMG1-S3 Architecture Technical Reference Manual (TRM). Register Mapping section lists all the registers in mapping tables, in address order.

Register General Conventions

The register conventions specific to this section and the Register Reference chapter are listed in this table.

Convention	Example	Description
'x' in a register name	ACBxxCR1	Multiple instances/address ranges of the same register
R	R : 00	Read register or bit(s)
W	W : 00	Write register or bit(s)
WOC	WOC:0	Write one to clear
WZC	WZC:0	Write zero to clear
RC	RC:0	Read to clear
WC	WC:0	Write to clear
NA	NA:000	Reserved
None	None: 0	Reserved
U	R:U	Undefined
00	RW : 00	Reset value is 0x00
XX	RW : XX	Register is not reset

Acronyms

This table lists the acronyms used in this document

Acronyms

Symbol	Unit of Measure
ABUS	analog output bus
AC	alternating current
ADC	analog-to-digital converter
ADV	advertising
AES	Advanced Encryption Standard
AHB	AMBA (advanced microcontroller bus architecture) high-performance bus, an ARM data transfer bus
API	application programming interface
APOR	analog power-on reset
BC	broadcast clock
BLE	Bluetooth Low Energy (Bluetooth SmartS)
BLESS	BLE subsystem
BOM	bill of materials
BR	bit rate

Acronyms (continued)

Symbol	Unit of Measure
BRA	bus request acknowledge
BRQ	bus request
CAN	controller area network
CI	carry in
CMP	compare
CO	carry out
CPU	central processing unit
CRC	cyclic redundancy check
CSD	CapSense sigma delta
CT	continuous time
DAC	digital-to-analog converter
DC	direct current
DI	digital or data input
DMA	direct memory access
DNL	differential nonlinearity
DO	digital or data output
DSI	digital signal interface
DSM	deep-sleep mode
ECO	external crystal oscillator
EEPROM	electrically erasable programmable read only memory
EMIF	external memory interface
FB	feedback
FIFO	first in first out
FSR	full scale range
GAP	generic access profile
GATT	generic attribute profile
GFSK	Gaussian frequency-shift keying
GPIO	general purpose I/O
HCI	host-controller interface (BLE stack)
HFCLK	high-frequency clock
I^2C	inter-integrated circuit
IDE	integrated development environment
ILO	internal low-speed oscillator
IMO	internal main oscillator
INL	integral nonlinearity
I/O	input/output
IOR	I/O read
IOW	I/O write
IRES	initial power on reset
IRA	interrupt request acknowledge
IRQ	interrupt request
ISR	interrupt service routine
IVR	interrupt vector read
L2CAP	logical link control and adaptation protocol

Acronyms (continued)

Symbol	Unit of Measure
LRb	last received bit
LRB	last received byte
LSb	least significant bit
LSB	least significant byte
LUT	lookup table
MISO	master-in-slave-out
MMIO	memory mapped input/output
MOSI	master-out-slave-in
MSb	most significant bit
MSB	most significant byte
PC	program counter
PCH	program counter high
PCL	program counter low
PD	power down
PDU	protocol data unit
PGA	programmable gain amplifier
PHY	physical layer
PM	power management
PMA	PSoC memory arbiter
POR	power-on reset
PPOR	precision power-on reset
PRS	pseudo random sequence
PSoC®	Programmable System-on-Chip
PSRR	power supply rejection ratio
PSSDC	power system sleep duty cycle
PWM	pulse width modulator
RAM	random-access memory
RETI	return from interrupt
RF	radio frequency
ROM	read only memory
RW	read/write
SAR	successive approximation register
SC	switched capacitor
SCB	serial communication block
SIE	serial interface engine
SIO	special I/O
SE0	single-ended zero
SNR	signal-to-noise ratio
SOF	start of frame
SOI	start of instruction
SP	stack pointer
SPD	sequential phase detector
SPI	serial peripheral interconnect
SPIM	serial peripheral interconnect master

Acronyms (continued)

Symbol	Unit of Measure
SPIS	serial peripheral interconnect slave
SRAM	static random-access memory
SROM	supervisory read only memory
SSADC	single slope ADC
SSC	supervisory system call
SYSCLK	system clock
SWD	single wire debug
TC	terminal count
TD	transaction descriptors
UART	universal asynchronous receiver/transmitter
UDB	universal digital block
USB	universal serial bus
USBIO	USB I/O
WCO	watch crystal oscillator
WDT	watchdog timer
WDR	watchdog reset
XRES	external reset
XRES_N	external reset, active low

1 CM0P Registers

This section discusses the CM0P registers. It lists all the registers in mapping tables, in address order.

1.1 Register Details

Register Name	Address
CM0P_DWT_PID4	0xE0001FD0
CM0P_DWT_PID0	0xE0001FE0
CM0P_DWT_PID1	0xE0001FE4
CM0P_DWT_PID2	0xE0001FE8
CM0P_DWT_PID3	0xE0001FEC
CM0P_DWT_CID0	0xE0001FF0
CM0P_DWT_CID1	0xE0001FF4
CM0P_DWT_CID2	0xE0001FF8
CM0P_DWT_CID3	0xE0001FFC
CM0P_BP_PID4	0xE0002FD0
CM0P_BP_PID0	0xE0002FE0
CM0P_BP_PID1	0xE0002FE4
CM0P_BP_PID2	0xE0002FE8
CM0P_BP_PID3	0xE0002FEC
CM0P_BP_CID0	0xE0002FF0
CM0P_BP_CID1	0xE0002FF4
CM0P_BP_CID2	0xE0002FF8
CM0P_BP_CID3	0xE0002FFC
CM0P_SYST_CSR	0xE000E010
CM0P_SYST_RVR	0xE000E014
CM0P_SYST_CVR	0xE000E018
CM0P_SYST_CALIB	0xE000E01C
CM0P_ISER	0xE000E100
CM0P_ICER	0xE000E180
CM0P_ISPR	0xE000E200
CM0P_ICPR	0xE000E280
CM0P_IPR0	0xE000E400

Register Name	Address
CM0P_IPR1	0xE000E404
CM0P_IPR2	0xE000E408
CM0P_IPR3	0xE000E40C
CM0P_IPR4	0xE000E410
CM0P_IPR5	0xE000E414
CM0P_IPR6	0xE000E418
CM0P_IPR7	0xE000E41C
CM0P_CPUID	0xE000ED00
CM0P_ICSR	0xE000ED04
CM0P_AIRCR	0xE000ED0C
CM0P_SCR	0xE000ED10
CM0P_CCR	0xE000ED14
CM0P_SHPR2	0xE000ED1C
CM0P_SHPR3	0xE000ED20
CM0P_SHCSR	0xE000ED24
CM0P_SCS_PID4	0xE000EFD0
CM0P_SCS_PID0	0xE000EFE0
CM0P_SCS_PID1	0xE000EFE4
CM0P_SCS_PID2	0xE000EFE8
CM0P_SCS_PID3	0xE000EFEC
CM0P_SCS_CID0	0xE000EFF0
CM0P_SCS_CID1	0xE000EFF4
CM0P_SCS_CID2	0xE000EFF8
CM0P_SCS_CID3	0xE000EFFC
CM0P_ROM_SCS	0xE00FF000
CM0P_ROM_DWT	0xE00FF004
CM0P_ROM_BPU	0xE00FF008
CM0P_ROM_END	0xE00FF00C
CM0P_ROM_CSMT	0xE00FFFCC
CM0P_ROM_PID4	0xE00FFFD0
CM0P_ROM_PID0	0xE00FFFE0
CM0P_ROM_PID1	0xE00FFFE4
CM0P_ROM_PID2	0xE00FFFE8
CM0P_ROM_PID3	0xE00FFFEC
CM0P_ROM_CID0	0xE00FFFF0
CM0P_ROM_CID1	0xE00FFFF4
CM0P_ROM_CID2	0xE00FFFF8
CM0P_ROM_CID3	0xE00FFFFC

1.1.1 CM0P_DWT_PID4

Watchpoint Unit CoreSight ROM Table Peripheral ID #4

Address: 0xE0001FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.2 CM0P_DWT_PID0

Watchpoint Unit CoreSight ROM Table Peripheral ID #0

Address: 0xE0001FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 10

1.1.3 CM0P_DWT_PID1

Watchpoint Unit CoreSight ROM Table Peripheral ID #1

Address: 0xE0001FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

1.1.4 CM0P_DWT_PID2

Watchpoint Unit CoreSight ROM Table Peripheral ID #2

Address: 0xE0001FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.5 CM0P_DWT_PID3

Watchpoint Unit CoreSight ROM Table Peripheral ID #3

Address: 0xE0001FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.6 CM0P_DWT_CID0

Watchpoint Unit CoreSight ROM Table Component ID #0

Address: 0xE0001FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.7 CM0P_DWT_CID1

Watchpoint Unit CoreSight ROM Table Component ID #1

Address: 0xE0001FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

1.1.8 CM0P_DWT_CID2

Watchpoint Unit CoreSight ROM Table Component ID #2

Address: 0xE0001FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.9 CM0P_DWT_CID3

Watchpoint Unit CoreSight ROM Table Component ID #3

Address: 0xE0001FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

1.1.10 CM0P_BP_PID4

Breakpoint Unit CoreSight ROM Table Peripheral ID #4

Address: 0xE0002FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.11 CM0P_BP_PID0

Breakpoint Unit CoreSight ROM Table Peripheral ID #0

Address: 0xE0002FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 11

1.1.12 CM0P_BP_PID1

Breakpoint Unit CoreSight ROM Table Peripheral ID #1

Address: 0xE0002FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

1.1.13 CM0P_BP_PID2

Breakpoint Unit CoreSight ROM Table Peripheral ID #2

Address: 0xE0002FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.14 CM0P_BP_PID3

Breakpoint Unit CoreSight ROM Table Peripheral ID #3

Address: 0xE0002FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.15 CM0P_BP_CID0

Breakpoint Unit CoreSight ROM Table Component ID #0

Address: 0xE0002FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.16 CM0P_BP_CID1

Breakpoint Unit CoreSight ROM Table Component ID #1

Address: 0xE0002FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

1.1.17 CM0P_BP_CID2

Breakpoint Unit CoreSight ROM Table Component ID #2

Address: 0xE0002FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.18 CM0P_BP_CID3

Breakpoint Unit CoreSight ROM Table Component ID #3

Address: 0xE0002FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

1.1.19 CM0P_SYST_CSR

SysTick Control & Status

Address: 0xE000E010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [7:3]					CLK-SOURCE	TICKINT	ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							RW
Name	None [23:17]							COUNT-FLAG

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	COUNTFLAG	Indicates whether the counter has counted to "0" since the last read of this register: '0': counter has not counted to "0". '1': counter has counted to "0". COUNTFLAG is set to '1' by a count transition from "1" to "0". COUNTFLAG is cleared to '0' by a read of this register, and by any write to the SYST_CVR register. Default Value: 0

1.1.19 CM0P_SYST_CSR (continued)

2	CLKSOURCE	Indicates the SysTick counter clock source: '0': SysTick uses the low frequency clock "clk_lf". For this mode to function, "clk_lf" should be less than half the frequency of "clk_sys". Note that "clk_lf" is generated by a low accuracy ILO (Internal Low power Oscillator), with a target frequency of 32.768 kHz (frequency can be as low as 15 KHz and as high as 60 kHz). '1': SysTick uses the system/processor clock "clk_sys". In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided. in SF, TSG6M products, this functionality is not provided. For these products, this field should be set to '1', such that SysTick uses the system clock "clk_sys". Default Value: 0
1	TICKINT	Indicates whether counting to "0" causes the status of the SysTick exception to change to pending: '0': count to "0" does not affect the SysTick exception status. '1': count to "0" changes the SysTick exception status to pending. Changing the value of the counter to "0" by writing zero to the SYST_CVR register to "0" never changes the status of the SysTick exception. Default Value: 0
0	ENABLE	Indicates the enabled status of the SysTick counter: '0': counter is disabled. '1': counter is operating. Default Value: 0

1.1.20 CM0P_SYST_RVR

SysTick Reload Value

Address: 0xE000E014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RELOAD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RELOAD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	RELOAD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 0	RELOAD	The value to load into the SYST_CVR register when the counter reaches 0. Default Value: X

1.1.21 CM0P_SYST_CVR

SysTick Current Value

Address: 0xE000E018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CURRENT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CURRENT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	CURRENT [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 0	CURRENT	Current counter value. This is the value of the counter at the time it is sampled. Default Value: X

1.1.22 CM0P_SYST_CALIB

SysTick Calibration Value

Address: 0xE000E01C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	TENMS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	TENMS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	TENMS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	None	RW	None					
Name	NOREF	SKEW	None [29:24]					

Bits	Name	Description
31	NOREF	Indicates whether a implementation defined reference clock is provided: '0': the reference clock is provided. '1': the reference clock is not provided. When this bit is '1', the SYST_CSR.CLKSOURCEis forced to '1' and cannot be cleared to '0'. In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided and this field is '0'. In earlier products, SysTick counter functionality on the low frequency clock is NOT provided and this field is '1'. Default Value: 0
30	SKEW	Indicates whether the 10ms calibration value is exact: '0': 10ms calibration value is exact. '1': 10ms calibration value is inexact, because of the clock frequency. In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided and this field is '1' (due to the low accuracy ILO). In earlier products, SysTick counter functionality on the low frequency clock is NOT provided and this field is '0'. Default Value: X

1.1.22 CM0P_SYST_CALIB (continued)

23 : 0	TENMS	Optionally, holds a reload value to be used for 10ms (100Hz) timing, subject to system clock skew errors. If this field is "0", the calibration value is not known. In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided and this field is 0x00:00147. In earlier products, SysTick counter functionality on the low frequency clock is NOT provided and this field is 0x00:0000. Default Value: X

1.1.23 CM0P_ISER

Interrupt Set-Enable Register

Address: 0xE000E100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	R							
Name	SETENA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	R							
Name	SETENA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	R							
Name	SETENA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	R							
Name	SETENA [31:24]							

Bits	Name	Description
31 : 0	SETENA	Enables, or reads the enabled state of one or more interrupts. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.24 CM0P_ICER

Interrupt Clear Enable Register

Address: 0xE000E180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	R							
Name	CLRENA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	R							
Name	CLRENA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C							
HW Access	R							
Name	CLRENA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C							
HW Access	R							
Name	CLRENA [31:24]							

Bits	Name	Description
31 : 0	CLRENA	Disables, or reads the enabled state of one or more interrupts. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.25 CM0P_ISPR

Interrupt Set-Pending Register

Address: 0xE000E200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	R							
Name	SETPEND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	R							
Name	SETPEND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	R							
Name	SETPEND [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	R							
Name	SETPEND [31:24]							

Bits	Name	Description
31 : 0	SETPEND	Changes the state of one or more interrupts to pending. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.26 CM0P_ICPR

Interrupt Clear-Pending Register

Address: 0xE000E280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [31:24]							

Bits	Name	Description
31 : 0	CLRPEND	Changes the state of one or more interrupts to not pending. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.27 CM0P_IPR0

Interrupt Priority Registers

Address: 0xE000E400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.28 CM0P_IPR1

Interrupt Priority Registers

Address: 0xE000E404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.29 CM0P_IPR2

Interrupt Priority Registers

Address: 0xE000E408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.30 CM0P_IPR3

Interrupt Priority Registers

Address: 0xE000E40C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.31 CM0P_IPR4

Interrupt Priority Registers

Address: 0xE000E410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.32 CM0P_IPR5

Interrupt Priority Registers

Address: 0xE000E414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.33 CM0P_IPR6

Interrupt Priority Registers

Address: 0xE000E418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.34 CM0P_IPR7

Interrupt Priority Registers

Address: 0xE000E41C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.35 CM0P_CPUID

CPUID Register

Address: 0xE000ED00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	None				None			
Name	PARTNO [7:4]				REVISION [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	PARTNO [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R				R			
HW Access	None				None			
Name	VARIANT [23:20]				CONSTANT [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	IMPLEMENTER [31:24]							

Bits	Name	Description
31 : 24	IMPLEMENTER	Implementer code for ARM. Default Value: 65
23 : 20	VARIANT	Implementation defined. In ARM implementations this is the major revision number n in the rn part of the rnpn revision status, Product revision status on page xii. Default Value: 0
19 : 16	CONSTANT	Indicates the architecture, ARMv6-M Default Value: 12
15 : 4	PARTNO	Indicates part number, Cortex-M0+ Default Value: 3168
3 : 0	REVISION	Indicates revision. In ARM implementations this is the minor revision number n in the pn part of the rnpn revision status, see Product revision status on page xii. For release r0p1. Default Value: 1

1.1.36 CM0P_ICSR

Interrupt Control State Register

Address: 0xE000ED04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VECTACTIVE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R				None			R
HW Access	RW				None			RW
Name	VECTPENDING [15:12]				None [11:9]			VECTAC-TIVE

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	None	R				
HW Access	RW	RW	None	RW				
Name	ISRPRE-EMPT	ISRPEND-ING	None	VECTPENDING [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None		RW1S	RW1C	RW1S	RW1C	None
HW Access	RW	None		RW	R	RW	R	None
Name	NMIPEND-SET	None [30:29]		PENDSV-SET	PENDSV-CLR	PENDST-SETb	PENDST-CLR	None

Bits	Name	Description
31	NMIPENDSET	Activates an NMI exception or reads back the current state. Because NMI is the highest priority exception, it activates as soon as it is registered. Default Value: 0
28	PENDSVSET	Sets a pending PendSV interrupt or reads back the current state. Use this normally to request a context switch. Writing PENDSVSET and PENDSVCLR to '1' concurrently is UNPREDICT-ABLE. Default Value: 0
27	PENDSVCLR	Clears a pending PendSV interrupt. Default Value: 0
26	PENDSTSETb	Sets a pending SysTick or reads back the current state. Writing PENDSTSET and PENDSTCLR to '1' concurrently is UNPREDICTABLE. Default Value: 0
25	PENDSTCLR	Clears a pending SysTick, whether set here or by the timer hardware. Default Value: 0

1.1.36 CM0P_ICSR (continued)

23	ISRPREEMPT	Indicates whether a pending exception will be serviced on exit from debug halt state. Default Value: 0
22	ISRPENDING	Indicates if an external configurable, NVIC generated, interrupt is pending. Default Value: 0
20 : 12	VECTPENDING	The exception number for the highest priority pending exception. 0= No pending exceptions. The pending state includes the effect of memory-mapped enable and mask registers. It does not include the PRIMASK special-purpose register qualifier. Default Value: 0
8 : 0	VECTACTIVE	The exception number for the current executing exception. 0= Thread mode. This is the same value as IPSR[8:0] Default Value: 0

1.1.37 CM0P_AIRCR

Application Interrupt and Reset Control Register

Address: 0xE000ED0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1S	RW1C	None
HW Access	None					R	R	None
Name	None [7:3]					SYSRESE-TREQ	VECTCL-RACTIVE	None

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	None	None						
Name	ENDIAN-NESS	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	VECTKEY [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	VECTKEY [31:24]							

Bits	Name	Description
31 : 16	VECTKEY	Vector Key. The value 0x05FA must be written to this register, otherwise the register write is UN-PREDICTABLE. Readback value is UNKNOWN. Default Value: X
15	ENDIANNESS	Indicates the memory system data endianness: 0 little endian 1 big endian. See Endian support on page A3-44 for more information. Default Value: 0
2	SYSRESETREQ	System Reset Request. Writing 1 to this bit asserts a signal to request a reset by the external system. This will cause a full system reset of the CPU and all other components in the device. See Reset management on page B1-240 for more information. Default Value: 0
1	VECTCLRACTIVE	Clears all active state information for fixed and configurable exceptions. The effect of writing a 1 to this bit if the processor is not halted in Debug state is UNPREDICTABLE. Default Value: 0

1.1.38 CM0P_SCR

System Control Register

Address: 0xE000ED10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	None
HW Access	None			R	None	R	R	None
Name	None [7:5]			SEVON-PEND	None	SLEEP-DEEP	SLEEPON-EXIT	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	SEVONPEND	Determines whether an interrupt transition from inactive state to pending state is a wakeup event: 0: transitions from inactive to pending are not wakeup events. 1: transitions from inactive to pending are wakeup events. See WFE on page A6-197 for more information. Default Value: 0
2	SLEEPDEEP	An implementation can use this bit to select DeepSleep/Hibernate power modes upon execution of WFI/WFE: 0: Select Sleep mode 1: Select DeepSleep/Hibernate (depends on PWR_CONTROL.HIBERNATE) Default Value: 0
1	SLEEPONEXIT	Determines whether, on an exit from an ISR that returns to the base level of execution priority, the processor enters a sleep state: 0 do not enter sleep state. 1 enter sleep state. See Power management on page B1-240 for more information. Default Value: 0

1.1.39 CM0P_CCR

Configuration and Control Register

Address: 0xE000ED14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	None		
HW Access	None				None	None		
Name	None [7:4]				UNALIGN_ TRP	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	None
HW Access	None						None	None
Name	None [15:10]						STKALIGN	None

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	STKALIGN	1: On exception entry, the SP used prior to the exception is adjusted to be 8-byte aligned and the context to restore it is saved. The SP is restored on the associated exception return. Default Value: 1
3	UNALIGN_TRP	1: unaligned word and halfword accesses generate a HardFault exception. Default Value: 1

1.1.40 CM0P_SHPR2

System Handler Priority Register 2

Address: 0xE000ED1C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_11 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_11	Priority of system handler 11, SVCall Default Value: 0

1.1.41 CM0P_SHPR3

System Handler Priority Register 3

Address: 0xE000ED20

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_14 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_15 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_15	Priority of system handler 15, SysTick Default Value: 0
23 : 22	PRI_14	Priority of system handler 14, PendSV Default Value: 0

1.1.42 CM0P_SHCSR

System Handler Control and State Register

Address: 0xE000ED24

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW	None						
HW Access	RW	None						
Name	SVCALL-PENDED	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	SVCALLPENDED	0 SVCall is not pending. 1 SVCall is pending. This bit reflects the pending state on a read, and updates the pending state, to the value written, on a write. (Pending state bits are set to 1 when an exception occurs, and are cleared to 0 when an exception becomes active.) Default Value: 0

1.1.43 CM0P_SCS_PID4

System Control Space ROM Table Peripheral ID #4

Address: 0xE000EFD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.44 CM0P_SCS_PID0

System Control Space ROM Table Peripheral ID #0

Address: 0xE000EFE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 8

1.1.45 CM0P_SCS_PID1

System Control Space ROM Table Peripheral ID #1

Address: 0xE000EFE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

1.1.46 CM0P_SCS_PID2

System Control Space ROM Table Peripheral ID #2

Address: 0xE000EFE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.47 CM0P_SCS_PID3

System Control Space ROM Table Peripheral ID #3

Address: 0xE000EFEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.48 CM0P_SCS_CID0

System Control Space ROM Table Component ID #0

Address: 0xE000EFF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.49 CM0P_SCS_CID1

System Control Space ROM Table Component ID #1

Address: 0xE000EFF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

1.1.50 CM0P_SCS_CID2

System Control Space ROM Table Component ID #2

Address: 0xE000EFF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.51 CM0P_SCS_CID3

System Control Space ROM Table Component ID #3

Address: 0xE000EFFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

1.1.52 CM0P_ROM_SCS

CM0+ CoreSight ROM Table Peripheral #0

Address: 0xE00FF000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to SCS ROM Table Default Value: 4293980163

1.1.53 CM0P_ROM_DWT

CM0+ CoreSight ROM Table Peripheral #1

Address: 0xE00FF004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to DWT ROM Table Default Value: 4293926915

1.1.54 CM0P_ROM_BPU

CM0+ CoreSight ROM Table Peripheral #2

Address: 0xE00FF008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to BPU ROM Table Default Value: 4293931011

1.1.55 CM0P_ROM_END

CM0+ CoreSight ROM Table End Marker

Address: 0xE00FF00C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	End marker in peripheral list Default Value: 0

1.1.56 CM0P_ROM_CSMT

CM0+ CoreSight ROM Table Memory Type

Address: 0xE00FFFCC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Memory Type Default Value: 1

1.1.57 CM0P_ROM_PID4

CM0+ CoreSight ROM Table Peripheral ID #4

Address: 0xE00FFFD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.58 CM0P_ROM_PID0

CM0+ CoreSight ROM Table Peripheral ID #0

Address: 0xE00FFFE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 192

1.1.59 CM0P_ROM_PID1

CM0+ CoreSight ROM Table Peripheral ID #1

Address: 0xE00FFFE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 180

1.1.60 CM0P_ROM_PID2

CM0+ CoreSight ROM Table Peripheral ID #2

Address: 0xE00FFFE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.61 CM0P_ROM_PID3

CM0+ CoreSight ROM Table Peripheral ID #3

Address: 0xE00FFFEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.62 CM0P_ROM_CID0

CM0+ CoreSight ROM Table Component ID #0

Address: 0xE00FFFF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.63 CM0P_ROM_CID1

CM0+ CoreSight ROM Table Component ID #1

Address: 0xE00FFFF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 16

1.1.64 CM0P_ROM_CID2

CM0+ CoreSight ROM Table Component ID #2

Address: 0xE00FFFF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.65 CM0P_ROM_CID3

CM0+ CoreSight ROM Table Component ID #3

Address: 0xE00FFFFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

2 Timer, Counter, PWM Counter (CNT) Registers

This section discusses the CNT registers. It lists all the registers in mapping tables, in address order.

2.1 Register Details

Register Name	Address
TCPWM_CNT0_CTRL	0x40200100
TCPWM_CNT0_STATUS	0x40200104
TCPWM_CNT0_COUNTER	0x40200108
TCPWM_CNT0_CC	0x4020010C
TCPWM_CNT0_CC_BUFF	0x40200110
TCPWM_CNT0_PERIOD	0x40200114
TCPWM_CNT0_PERIOD_BUFF	0x40200118
TCPWM_CNT0_TR_CTRL0	0x40200120
TCPWM_CNT0_TR_CTRL1	0x40200124
TCPWM_CNT0_TR_CTRL2	0x40200128
TCPWM_CNT0_INTR	0x40200130
TCPWM_CNT0_INTR_SET	0x40200134
TCPWM_CNT0_INTR_MASK	0x40200138
TCPWM_CNT0_INTR_MASKED	0x4020013C
TCPWM_CNT1_CTRL	0x40200140
TCPWM_CNT1_STATUS	0x40200144
TCPWM_CNT1_COUNTER	0x40200148
TCPWM_CNT1_CC	0x4020014C
TCPWM_CNT1_CC_BUFF	0x40200150
TCPWM_CNT1_PERIOD	0x40200154
TCPWM_CNT1_PERIOD_BUFF	0x40200158
TCPWM_CNT1_TR_CTRL0	0x40200160
TCPWM_CNT1_TR_CTRL1	0x40200164
TCPWM_CNT1_TR_CTRL2	0x40200168
TCPWM_CNT1_INTR	0x40200170
TCPWM_CNT1_INTR_SET	0x40200174
TCPWM_CNT1_INTR_MASK	0x40200178

Register Name	Address
TCPWM_CNT1_INTR_MASKED	0x4020017C
TCPWM_CNT2_CTRL	0x40200180
TCPWM_CNT2_STATUS	0x40200184
TCPWM_CNT2_COUNTER	0x40200188
TCPWM_CNT2_CC	0x4020018C
TCPWM_CNT2_CC_BUFF	0x40200190
TCPWM_CNT2_PERIOD	0x40200194
TCPWM_CNT2_PERIOD_BUFF	0x40200198
TCPWM_CNT2_TR_CTRL0	0x402001A0
TCPWM_CNT2_TR_CTRL1	0x402001A4
TCPWM_CNT2_TR_CTRL2	0x402001A8
TCPWM_CNT2_INTR	0x402001B0
TCPWM_CNT2_INTR_SET	0x402001B4
TCPWM_CNT2_INTR_MASK	0x402001B8
TCPWM_CNT2_INTR_MASKED	0x402001BC
TCPWM_CNT3_CTRL	0x402001C0
TCPWM_CNT3_STATUS	0x402001C4
TCPWM_CNT3_COUNTER	0x402001C8
TCPWM_CNT3_CC	0x402001CC
TCPWM_CNT3_CC_BUFF	0x402001D0
TCPWM_CNT3_PERIOD	0x402001D4
TCPWM_CNT3_PERIOD_BUFF	0x402001D8
TCPWM_CNT3_TR_CTRL0	0x402001E0
TCPWM_CNT3_TR_CTRL1	0x402001E4
TCPWM_CNT3_TR_CTRL2	0x402001E8
TCPWM_CNT3_INTR	0x402001F0
TCPWM_CNT3_INTR_SET	0x402001F4
TCPWM_CNT3_INTR_MASK	0x402001F8
TCPWM_CNT3_INTR_MASKED	0x402001FC
TCPWM_CNT4_CTRL	0x40200200
TCPWM_CNT4_STATUS	0x40200204
TCPWM_CNT4_COUNTER	0x40200208
TCPWM_CNT4_CC	0x4020020C
TCPWM_CNT4_CC_BUFF	0x40200210
TCPWM_CNT4_PERIOD	0x40200214
TCPWM_CNT4_PERIOD_BUFF	0x40200218
TCPWM_CNT4_TR_CTRL0	0x40200220
TCPWM_CNT4_TR_CTRL1	0x40200224
TCPWM_CNT4_TR_CTRL2	0x40200228
TCPWM_CNT4_INTR	0x40200230
TCPWM_CNT4_INTR_SET	0x40200234
TCPWM_CNT4_INTR_MASK	0x40200238

Register Name	Address
TCPWM_CNT4_INTR_MASKED	0x4020023C
TCPWM_CNT5_CTRL	0x40200240
TCPWM_CNT5_STATUS	0x40200244
TCPWM_CNT5_COUNTER	0x40200248
TCPWM_CNT5_CC	0x4020024C
TCPWM_CNT5_CC_BUFF	0x40200250
TCPWM_CNT5_PERIOD	0x40200254
TCPWM_CNT5_PERIOD_BUFF	0x40200258
TCPWM_CNT5_TR_CTRL0	0x40200260
TCPWM_CNT5_TR_CTRL1	0x40200264
TCPWM_CNT5_TR_CTRL2	0x40200268
TCPWM_CNT5_INTR	0x40200270
TCPWM_CNT5_INTR_SET	0x40200274
TCPWM_CNT5_INTR_MASK	0x40200278
TCPWM_CNT5_INTR_MASKED	0x4020027C
TCPWM_CNT6_CTRL	0x40200280
TCPWM_CNT6_STATUS	0x40200284
TCPWM_CNT6_COUNTER	0x40200288
TCPWM_CNT6_CC	0x4020028C
TCPWM_CNT6_CC_BUFF	0x40200290
TCPWM_CNT6_PERIOD	0x40200294
TCPWM_CNT6_PERIOD_BUFF	0x40200298
TCPWM_CNT6_TR_CTRL0	0x402002A0
TCPWM_CNT6_TR_CTRL1	0x402002A4
TCPWM_CNT6_TR_CTRL2	0x402002A8
TCPWM_CNT6_INTR	0x402002B0
TCPWM_CNT6_INTR_SET	0x402002B4
TCPWM_CNT6_INTR_MASK	0x402002B8
TCPWM_CNT6_INTR_MASKED	0x402002BC
TCPWM_CNT7_CTRL	0x402002C0
TCPWM_CNT7_STATUS	0x402002C4
TCPWM_CNT7_COUNTER	0x402002C8
TCPWM_CNT7_CC	0x402002CC
TCPWM_CNT7_CC_BUFF	0x402002D0
TCPWM_CNT7_PERIOD	0x402002D4
TCPWM_CNT7_PERIOD_BUFF	0x402002D8
TCPWM_CNT7_TR_CTRL0	0x402002E0
TCPWM_CNT7_TR_CTRL1	0x402002E4
TCPWM_CNT7_TR_CTRL2	0x402002E8
TCPWM_CNT7_INTR	0x402002F0
TCPWM_CNT7_INTR_SET	0x402002F4
TCPWM_CNT7_INTR_MASK	0x402002F8

Register Name	Address
TCPWM_CNT7_INTR_MASKED	0x402002FC

2.1.1 TCPWM_CNT0_CTRL

Counter control register

Address: 0x40200100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.1 TCPWM_CNT0_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.1 TCPWM_CNT0_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.2 TCPWM_CNT0_STATUS

Counter status register

Address: 0x40200104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.3 TCPWM_CNT0_COUNTER

Counter count register

Address: 0x40200108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.4 TCPWM_CNT0_CC

Counter compare/capture register

Address: 0x4020010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.5 TCPWM_CNT0_CC_BUFF

Counter buffered compare/capture register

Address: 0x40200110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.6 TCPWM_CNT0_PERIOD

Counter period register

Address: 0x40200114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.7 TCPWM_CNT0_PERIOD_BUFF

Counter buffered period register

Address: 0x40200118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.8 TCPWM_CNT0_TR_CTRL0

Counter trigger control register 0

Address: 0x40200120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.8 TCPWM_CNT0_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.9 TCPWM_CNT0_TR_CTRL1

Counter trigger control register 1

Address: 0x40200124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.9 TCPWM_CNT0_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.10 TCPWM_CNT0_TR_CTRL2

Counter trigger control register 2

Address: 0x40200128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.10 TCPWM_CNT0_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.11 TCPWM_CNT0_INTR

Interrupt request register.

Address: 0x40200130

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.12 TCPWM_CNT0_INTR_SET

Interrupt set request register.

Address: 0x40200134

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.13 TCPWM_CNT0_INTR_MASK

Interrupt mask register.

Address: 0x40200138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.14 TCPWM_CNT0_INTR_MASKED

Interrupt masked request register

Address: 0x4020013C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.15 TCPWM_CNT1_CTRL

Counter control register

Address: 0x40200140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.15 TCPWM_CNT1_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.15 TCPWM_CNT1_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.16 TCPWM_CNT1_STATUS

Counter status register

Address: 0x40200144

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.17 TCPWM_CNT1_COUNTER

Counter count register

Address: 0x40200148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.18 TCPWM_CNT1_CC

Counter compare/capture register

Address: 0x4020014C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.19 TCPWM_CNT1_CC_BUFF

Counter buffered compare/capture register

Address: 0x40200150

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.20 TCPWM_CNT1_PERIOD

Counter period register

Address: 0x40200154

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.21 TCPWM_CNT1_PERIOD_BUFF

Counter buffered period register

Address: 0x40200158

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.22 TCPWM_CNT1_TR_CTRL0

Counter trigger control register 0

Address: 0x40200160

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.22 TCPWM_CNT1_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.23 TCPWM_CNT1_TR_CTRL1

Counter trigger control register 1

Address: 0x40200164

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.23 TCPWM_CNT1_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.24 TCPWM_CNT1_TR_CTRL2

Counter trigger control register 2

Address: 0x40200168

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.24 TCPWM_CNT1_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.25 TCPWM_CNT1_INTR

Interrupt request register.

Address: 0x40200170

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.26 TCPWM_CNT1_INTR_SET

Interrupt set request register.

Address: 0x40200174

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.27 TCPWM_CNT1_INTR_MASK

Interrupt mask register.

Address: 0x40200178

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.28 TCPWM_CNT1_INTR_MASKED

Interrupt masked request register

Address: 0x4020017C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.29 TCPWM_CNT2_CTRL

Counter control register

Address: 0x40200180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.29 TCPWM_CNT2_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.29 TCPWM_CNT2_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.30 TCPWM_CNT2_STATUS

Counter status register

Address: 0x40200184

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.31 TCPWM_CNT2_COUNTER

Counter count register

Address: 0x40200188

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.32 TCPWM_CNT2_CC

Counter compare/capture register

Address: 0x4020018C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.33 TCPWM_CNT2_CC_BUFF

Counter buffered compare/capture register

Address: 0x40200190

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.34 TCPWM_CNT2_PERIOD

Counter period register

Address: 0x40200194

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.35 TCPWM_CNT2_PERIOD_BUFF

Counter buffered period register

Address: 0x40200198

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.36 TCPWM_CNT2_TR_CTRL0

Counter trigger control register 0

Address: 0x402001A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.36 TCPWM_CNT2_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.37 TCPWM_CNT2_TR_CTRL1

Counter trigger control register 1

Address: 0x402001A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.37 TCPWM_CNT2_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.38 TCPWM_CNT2_TR_CTRL2

Counter trigger control register 2

Address: 0x402001A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.38 TCPWM_CNT2_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.39 TCPWM_CNT2_INTR

Interrupt request register.

Address: 0x402001B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.40 TCPWM_CNT2_INTR_SET

Interrupt set request register.

Address: 0x402001B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.41 TCPWM_CNT2_INTR_MASK

Interrupt mask register.

Address: 0x402001B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.42 TCPWM_CNT2_INTR_MASKED

Interrupt masked request register

Address: 0x402001BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.43 TCPWM_CNT3_CTRL

Counter control register

Address: 0x402001C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.43 TCPWM_CNT3_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.43 TCPWM_CNT3_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.44 TCPWM_CNT3_STATUS

Counter status register

Address: 0x402001C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.45 TCPWM_CNT3_COUNTER

Counter count register

Address: 0x402001C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.46 TCPWM_CNT3_CC

Counter compare/capture register

Address: 0x402001CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.47 TCPWM_CNT3_CC_BUFF

Counter buffered compare/capture register

Address: 0x402001D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.48 TCPWM_CNT3_PERIOD

Counter period register

Address: 0x402001D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.49 TCPWM_CNT3_PERIOD_BUFF

Counter buffered period register

Address: 0x402001D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.50 TCPWM_CNT3_TR_CTRL0

Counter trigger control register 0

Address: 0x402001E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.50 TCPWM_CNT3_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.51 TCPWM_CNT3_TR_CTRL1

Counter trigger control register 1

Address: 0x402001E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.51 TCPWM_CNT3_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.52 TCPWM_CNT3_TR_CTRL2

Counter trigger control register 2

Address: 0x402001E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.52 TCPWM_CNT3_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.53 TCPWM_CNT3_INTR

Interrupt request register.

Address: 0x402001F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.54 TCPWM_CNT3_INTR_SET

Interrupt set request register.

Address: 0x402001F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.55 TCPWM_CNT3_INTR_MASK

Interrupt mask register.

Address: 0x402001F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.56 TCPWM_CNT3_INTR_MASKED

Interrupt masked request register

Address: 0x402001FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.57 TCPWM_CNT4_CTRL

Counter control register

Address: 0x40200200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.57 TCPWM_CNT4_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.57 TCPWM_CNT4_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.58 TCPWM_CNT4_STATUS

Counter status register

Address: 0x40200204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.59 TCPWM_CNT4_COUNTER

Counter count register

Address: 0x40200208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.60 TCPWM_CNT4_CC

Counter compare/capture register

Address: 0x4020020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.61 TCPWM_CNT4_CC_BUFF

Counter buffered compare/capture register

Address: 0x40200210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.62 TCPWM_CNT4_PERIOD

Counter period register

Address: 0x40200214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.63 TCPWM_CNT4_PERIOD_BUFF

Counter buffered period register

Address: 0x40200218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.64 TCPWM_CNT4_TR_CTRL0

Counter trigger control register 0

Address: 0x40200220

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.64 TCPWM_CNT4_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.65 TCPWM_CNT4_TR_CTRL1

Counter trigger control register 1

Address: 0x40200224

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.65 TCPWM_CNT4_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.66 TCPWM_CNT4_TR_CTRL2

Counter trigger control register 2

Address: 0x40200228

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.66 TCPWM_CNT4_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.67 TCPWM_CNT4_INTR

Interrupt request register.

Address: 0x40200230

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.68 TCPWM_CNT4_INTR_SET

Interrupt set request register.

Address: 0x40200234

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.69 TCPWM_CNT4_INTR_MASK

Interrupt mask register.

Address: 0x40200238

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.70 TCPWM_CNT4_INTR_MASKED

Interrupt masked request register

Address: 0x4020023C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.71 TCPWM_CNT5_CTRL

Counter control register

Address: 0x40200240

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.71 TCPWM_CNT5_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.71 TCPWM_CNT5_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.72 TCPWM_CNT5_STATUS

Counter status register

Address: 0x40200244

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.73 TCPWM_CNT5_COUNTER

Counter count register

Address: 0x40200248

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.74 TCPWM_CNT5_CC

Counter compare/capture register

Address: 0x4020024C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.75 TCPWM_CNT5_CC_BUFF

Counter buffered compare/capture register

Address: 0x40200250

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.76 TCPWM_CNT5_PERIOD

Counter period register

Address: 0x40200254

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.77 TCPWM_CNT5_PERIOD_BUFF

Counter buffered period register

Address: 0x40200258

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.78 TCPWM_CNT5_TR_CTRL0

Counter trigger control register 0

Address: 0x40200260

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.78 TCPWM_CNT5_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.79 TCPWM_CNT5_TR_CTRL1

Counter trigger control register 1

Address: 0x40200264

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.79 TCPWM_CNT5_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.80 TCPWM_CNT5_TR_CTRL2

Counter trigger control register 2

Address: 0x40200268

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.80 TCPWM_CNT5_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.81 TCPWM_CNT5_INTR

Interrupt request register.

Address: 0x40200270

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.82 TCPWM_CNT5_INTR_SET

Interrupt set request register.

Address: 0x40200274

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.83 TCPWM_CNT5_INTR_MASK

Interrupt mask register.

Address: 0x40200278

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.84 TCPWM_CNT5_INTR_MASKED

Interrupt masked request register

Address: 0x4020027C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.85 TCPWM_CNT6_CTRL

Counter control register

Address: 0x40200280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.85 TCPWM_CNT6_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.85 TCPWM_CNT6_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.86 TCPWM_CNT6_STATUS

Counter status register

Address: 0x40200284

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.87 TCPWM_CNT6_COUNTER

Counter count register

Address: 0x40200288

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.88 TCPWM_CNT6_CC

Counter compare/capture register

Address: 0x4020028C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.89 TCPWM_CNT6_CC_BUFF

Counter buffered compare/capture register

Address: 0x40200290

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.90 TCPWM_CNT6_PERIOD

Counter period register

Address: 0x40200294

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.91 TCPWM_CNT6_PERIOD_BUFF

Counter buffered period register

Address: 0x40200298

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.92 TCPWM_CNT6_TR_CTRL0

Counter trigger control register 0

Address: 0x402002A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.92 TCPWM_CNT6_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.93 TCPWM_CNT6_TR_CTRL1

Counter trigger control register 1

Address: 0x402002A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.93 TCPWM_CNT6_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.94 TCPWM_CNT6_TR_CTRL2

Counter trigger control register 2

Address: 0x402002A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.94 TCPWM_CNT6_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.95 TCPWM_CNT6_INTR

Interrupt request register.

Address: 0x402002B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.96 TCPWM_CNT6_INTR_SET

Interrupt set request register.

Address: 0x402002B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.97 TCPWM_CNT6_INTR_MASK

Interrupt mask register.

Address: 0x402002B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.98 TCPWM_CNT6_INTR_MASKED

Interrupt masked request register

Address: 0x402002BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.99 TCPWM_CNT7_CTRL

Counter control register

Address: 0x402002C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PWM_STOP_ON_KILL	PWM_SYNC_KILL	AUTO_RELOAD_PERIOD	AUTO_RELOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 **0x0: TIMER:** Timer mode **0x2: CAPTURE:** Capture mode **0x3: QUAD:** Quadrature encoding mode **0x4: PWM:** Pulse width modulation (PWM) mode **0x5: PWM_DT:** PWM with deadtime insertion mode **0x6: PWM_PR:** Pseudo random pulse width modulation

2.1.99 TCPWM_CNT7_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 **0x0: X1:** X1 encoding (QUAD mode) **0x1: X2:** X2 encoding (QUAD mode) **0x1: INV_OUT:** When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) **0x2: X4:** X4 encoding (QUAD mode) **0x2: INV_COMPL_OUT:** When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 **0x0: COUNT_UP:** Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. **0x1: COUNT_DOWN:** Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x2: COUNT_UPDN1:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". **0x3: COUNT_UPDN2:** Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 **0x0: DIVBY1:** Divide by 1 (other-than-PWM_DT mode) **0x1: DIVBY2:** Divide by 2 (other-than-PWM_DT mode) **0x2: DIVBY4:** Divide by 4 (other-than-PWM_DT mode)

2.1.99 TCPWM_CNT7_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode) **0x4: DIVBY16:** Divide by 16 (other-than-PWM_DT mode) **0x5: DIVBY32:** Divide by 32 (other-than-PWM_DT mode) **0x6: DIVBY64:** Divide by 64 (other-than-PWM_DT mode) **0x7: DIVBY128:** Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0: never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.100 TCPWM_CNT7_STATUS

Counter status register

Address: 0x402002C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.101 TCPWM_CNT7_COUNTER

Counter count register

Address: 0x402002C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.102 TCPWM_CNT7_CC

Counter compare/capture register

Address: 0x402002CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.103 TCPWM_CNT7_CC_BUFF

Counter buffered compare/capture register

Address: 0x402002D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.104 TCPWM_CNT7_PERIOD

Counter period register

Address: 0x402002D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.105 TCPWM_CNT7_PERIOD_BUFF

Counter buffered period register

Address: 0x402002D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.106 TCPWM_CNT7_TR_CTRL0

Counter trigger control register 0

Address: 0x402002E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.106 TCPWM_CNT7_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger 1 is always '1'. Input trigger 2 is the first external trigger line (tcpwm.tr_in[0]). In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.107 TCPWM_CNT7_TR_CTRL1

Counter trigger control register 1

Address: 0x402002E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event.

2.1.107 TCPWM_CNT7_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3 **0x0: RISING_EDGE:** Rising edge. Any rising edge generates an event. **0x1: FALLING_EDGE:** Falling edge. Any falling edge generates an event. **0x2: BOTH_EDGES:** Rising AND falling edge. Any odd amount of edges generates an event. **0x3: NO_EDGE_DET:** No edge detection, use trigger as is.

2.1.108 TCPWM_CNT7_TR_CTRL2

Counter trigger control register 2

Address: 0x402002E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 **0x0: SET:** Set to '1'

2.1.108 TCPWM_CNT7_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 **0x0: SET:** Set to '1' **0x1: CLEAR:** Set to '0' **0x2: INVERT:** Invert **0x3: NO_CHANGE:** No Change

2.1.109 TCPWM_CNT7_INTR

Interrupt request register.

Address: 0x402002F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.110 TCPWM_CNT7_INTR_SET

Interrupt set request register.

Address: 0x402002F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.111 TCPWM_CNT7_INTR_MASK

Interrupt mask register.

Address: 0x402002F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.112 TCPWM_CNT7_INTR_MASKED

Interrupt masked request register

Address: 0x402002FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3 CPU Sub System (CPUSS) Registers

This section discusses the CPUSS registers. It lists all the registers in mapping tables, in address order.

3.1 Register Details

Register Name	Address
CPUSS_SYSREQ	0x40100004
CPUSS_SYSARG	0x40100008
CPUSS_FLASH_CTL	0x40100030
CPUSS_ROM_CTL	0x40100034
CPUSS_RAM_CTL	0x40100038
CPUSS_DMAC_CTL	0x4010003C
CPUSS_SL_CTL0	0x40100100
CPUSS_SL_CTL1	0x40100104
CPUSS_SL_CTL2	0x40100108
CPUSS_EXT_MS_CTL	0x40100400

3.1.1 CPUSS_SYSREQ

SYSCALL control register

Address: 0x40100004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	SYSCALL_COMMAND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	SYSCALL_COMMAND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	R	R	RW	RW	None		
HW Access	R	W	RW	A	R	None		
Name	SYSCALL_REQ	HMASTER_0	ROM_ACCESS_EN	PRIVILEGED	DIS_RESET_VECT_REL	None [26:24]		

Bits	Name	Description
31	SYSCALL_REQ	CPU/DAP writes a '1' to this field to request a SystemCall. The HMASTER_0 field indicates the source of the write access. Setting this field to '1' immediate results in a NMI. The SystemCall NMI interrupt handler sets this field to '0' after servicing the request. Default Value: 0
30	HMASTER_0	Indicates the source of the write access to the SYSREQ register. '0': CPU write access. '1': DAP write access. HW sets this field when the SYSREQ register is written to and SYSCALL_REQ is '0' (the last time it is set is when SW sets SYSCALL_REQ from '0' to '1'). Default Value: 0
29	ROM_ACCESS_EN	Indicates that executing from Boot ROM is enabled. HW sets this field to '1', on reset or when the SystemCall NMI vector is fetched from Boot ROM. HW sets this field to '0', when the CPU is NOT executing from either Boot or System ROM. This bit is used for debug purposes only. Default Value: 1

3.1.1 CPUSS_SYSREQ (continued)

28	PRIVILEGED	Indicates whether the system is in privileged ('1') or user mode ('0'). Only CPU SW executing from ROM can set this field to '1' when ROM_ACCESS_EN is '1' (the CPU is executing a SystemCall NMI interrupt handler). Any other write to this field sets is to '0'. This field is used as the AHB-Lite hprot[1] signal to implement Cypress proprietary user/privileged modes. These modes are used to enable/disable access to specific MMIO registers and memory regions. Default Value: 1
27	DIS_RESET_VECT_REL	Disable Reset Vector fetch relocation: '0': CPU accesses to locations 0x0000:0000 - 0x0000:0007 are redirected to ROM. '1': CPU accesses to locations 0x0000:0000 - 0x0000:0007 are made to flash. Note that this field defaults to '0' on reset, ensuring actual reset vector fetches are always made to ROM. Note that this field does not affect DAP accesses. Flash DfT routines may set this bit to '1' to enable uninhibited read-back of programmed data in the first flash page. Default Value: 0
15 : 0	SYSCALL_COMMAND	Opcode of the system call being requested. Default Value: 0

3.1.2 CPUSS_SYSARG

SYSARG control register

Address: 0x40100008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [31:24]							

Bits	Name	Description
31 : 0	SYSCALL_ARG	Argument to System Call specified in SYSREQ. Semantics of argument depends on system call made. Typically a pointer to a parameter block. Default Value: 0

3.1.3 CPUSS_FLASH_CTL

FLASH control register

Address: 0x40100030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			PREF_EN	None [3:2]		FLASH_WS [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW1C
Name	None [15:9]							FLASH_INVALIDATE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU has priority "1": DW/DMA has priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0
8	FLASH_INVALIDATE	1': Invalidates the content of the flash controller's buffers. Default Value: 0
4	PREF_EN	Prefetch enable: '0': disabled. This is a desirable seeting when FLASH_WS is "0" or when predictable execution behavior is required. '1': enabled. Default Value: 0

3.1.3 CPUSS_FLASH_CTL (continued)

1 : 0	FLASH_WS	Amount of ROM wait states: "0": 0 wait states (fast flash: [0, 24] MHz system frequency, slow flash: [0, 16] MHz system frequency) "1": 1 wait state (fast flash: [24, 48] MHz system frequency, slow flash: [16, 32] MHz system frequency) "2": 2 wait states (slow flash: [32, 48] MHz system frequency) "3": 3 wait states (can be used to give more time for flash access if 2 wait states are not sufficient) Default Value: 0

3.1.4 CPUSS_ROM_CTL

ROM control register

Address: 0x40100034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							ROM_WS

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	ROM_WS	Amount of ROM wait states: '0': 0 wait states. Use this setting for newer, faster ROM design. Use this setting for older, slower ROM design and frequencies in the range [0, 24] MHz. '1': 1 wait state. Use this setting for older, slower ROM design and frequencies in the range <24, 48] MHz. CPUSSv2 supports two types of ROM memory: an older, slower design (operating at up to 24 MHz) and a newer, faster design (operating at up to 48 MHz). The older design requires 1 wait state for frequencies above 24 MHz. The newer design never requires wait states. All chips after Street Fighter will use the newer design. As a result, all chips after Street Fighter can always use 0 wait states. Default Value: 0

3.1.5 CPUSS_RAM_CTL

RAM control register

Address: 0x40100038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU has priority "1": DW/DMA has priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

3.1.6 CPUSS_DMAC_CTL

DMA controller register

Address: 0x4010003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU has priority "1": DW/DMA has priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

3.1.7 CPUSS_SL_CTL0

Slave control register

Address: 0x40100100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU priority "1": DMA priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

3.1.8 CPUSS_SL_CTL1

Slave control register

Address: 0x40100104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU priority "1": DMA priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

3.1.9 CPUSS_SL_CTL2

Slave control register

Address: 0x40100108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: "0": CPU priority "1": DMA priority "2": Roundrobin "3": Roundrobin - sticky Default Value: 0

3.1.10 CPUSS_EXT_MS_CTL

External master control register

Address: 0x40100400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ARB [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ARB	Arbitration policy: 0: EXTM0/DMAC has priority 1: EXTM1 has priority 2: Roundrobin 3: Roundrobin - sticky Default Value: 0

4 CRYPTOLITE Registers

This section discusses the CRYPTOLITE registers. It lists all the registers in mapping tables, in address order.

4.1 Register Details

Register Name	Address
CRYPTOLITE_CTL	0x402D0000
CRYPTOLITE_STATUS	0x402D0004
CRYPTOLITE_AES_DESCR	0x402D0040
CRYPTOLITE_VU_DESCR	0x402D0080
CRYPTOLITE_SHA_DESCR	0x402D00C0
CRYPTOLITE_INTR_ERROR	0x402D00F0
CRYPTOLITE_INTR_ERROR_SET	0x402D00F4
CRYPTOLITE_INTR_ERROR_MASK	0x402D00F8
CRYPTOLITE_INTR_ERROR_MASKED	0x402D00FC
CRYPTOLITE_TRNG_CTL0	0x402D0100
CRYPTOLITE_TRNG_CTL1	0x402D0104
CRYPTOLITE_TRNG_STATUS	0x402D010C
CRYPTOLITE_TRNG_RESULT	0x402D0110
CRYPTOLITE_TRNG_GARO_CTL	0x402D0120
CRYPTOLITE_TRNG_FIRO_CTL	0x402D0124
CRYPTOLITE_TRNG_MON_CTL	0x402D0140
CRYPTOLITE_TRNG_MON_RC_CTL	0x402D0150
CRYPTOLITE_TRNG_MON_RC_STATUS0	0x402D0158
CRYPTOLITE_TRNG_MON_RC_STATUS1	0x402D015C
CRYPTOLITE_TRNG_MON_AP_CTL	0x402D0160
CRYPTOLITE_TRNG_MON_AP_STATUS0	0x402D0168
CRYPTOLITE_TRNG_MON_AP_STATUS1	0x402D016C
CRYPTOLITE_INTR_TRNG	0x402D01F0
CRYPTOLITE_INTR_TRNG_SET	0x402D01F4
CRYPTOLITE_INTR_TRNG_MASK	0x402D01F8
CRYPTOLITE_INTR_TRNG_MASKED	0x402D01FC

4.1.1 CRYPTOLITE_CTL

Control

Address: 0x402D0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				None		R	R
HW Access	W				None		W	W
Name	PC [7:4]				None [3:2]		NS	P

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				MS [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 8	MS	Master identifier of the cryptography IP. This is a design time configurable parameter. Default Value: 2
7 : 4	PC	Protection context. This field is set with the protection context of the transaction that writes any (including possible memory holes in the IP aperture) of the CRYPTO component registers; i.e. the context is inherited from the write transaction and not specified by the transaction write data. All CRYPTO component master transactions use the PC field for the protection context. Default Value: Undefined

4.1.1 CRYPTOLITE_CTL (continued)

1	NS	Secure/on-secure access control: '0': secure. '1': non-secure. This field is set with the secure/non-secure access control of the transaction that writes any (including possible memory holes in the IP aperture) of the CRYPTO component registers; i.e. the access control is inherited from the write transaction and not specified by the transaction write data. All CRYPTO component master transactions use the NS field for the secure/non-secure access control ("hprot[4]"). Default Value: Undefined
0	P	User/privileged access control: '0': user mode. '1': privileged mode. This field is set with the user/privileged access control of the transaction that writes any (including possible memory holes in the IP aperture) of the CRYPTO component registers; i.e. the access control is inherited from the write transaction and not specified by the transaction write data. All CRYPTO component master transactions use the P field for the user/privileged access control ("hprot[1]"). Default Value: Undefined

4.1.2 CRYPTOLITE_STATUS

Status

Address: 0x402D0004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	BUSY	Busy indication: '0': IP not busy. '1': IP busy (AES, SHA or VU functionality (TRNG functionality NOT included)). Default Value: 0

4.1.3 CRYPTOLITE_AES_DESCR

AES descriptor pointer

Address: 0x402D0040

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW						None	
HW Access	RW						None	
Name	PTR [7:2]						None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	PTR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	PTR [31:24]							

Bits	Name	Description
31 : 2	PTR	AES descriptor pointer. The descriptor points to a structure with 32-bit words: Word 0: Pointer to a 128-bit AES key. Word 1: Pointer to a 128-bit source/plaintext. Word 2: Pointer to a 128-bit destination/ciphertext. A write to this register automatically starts a 128-bit AES encryption in ECB mode. The write ONLY takes effect when the IP is NOT busy (STATUS.BUSY is '0'). The write will be made pending/blocked as long as the IP is busy. Note: the pointers must be 4B aligned. Note: HW updates this field when the AES engine is busy. Default Value: Undefined

4.1.4 CRYPTOLITE_VU_DESCR

VU descriptor pointer

Address: 0x402D0080

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW						None	
HW Access	RW						None	
Name	PTR [7:2]						None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	PTR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	PTR [31:24]							

Bits	Name	Description
31 : 2	PTR	VU descriptor pointer. The descriptor points to a structure with 32-bit words: Word 0: Control word. Specifies operand size in 32-bit word multiples. - WORD[7:0]: Source operand 0 32-bit words (minus 1). - WORD[15:8]: Source operand 1 32-bit words (minus 1). - WORD[24:16]: Destination operand 32-bit words (minus 1). - WORD[31:28]: Opcode. "0": multiplication (MUL), "1": addition (ADD), "2": subtraction (SUB), "3": exclusive or (XOR), "4": binary multiplication (XMUL), "5": logical shift right by 1 (LSR1), "6": logical shift left by 1 (LSL1), "7": logical shift right (LSR), "8": conditional syubtraction (COND_SUB). "9": move (MOV). Word 1: Pointer to source 0. Word 2: Pointer to source 1. Word 3: Pointer to destination. A write to this register automatically starts a VU operation. The write ONLY takes effect when the IP is NOT busy (STATUS.BUSY is '0'). The write will be made pending/blocked as long as the IP is busy. Note: the pointers must be 4B aligned. Note: HW updates this field when the VU engine is busy. Default Value: Undefined

4.1.5 CRYPTOLITE_SHA_DESCR

SHA descriptor pointer

Address: 0x402D00C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW						None	
HW Access	RW						None	
Name	PTR [7:2]						None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	PTR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	PTR [31:24]							

Bits	Name	Description
31 : 2	PTR	SHA-256 descriptor pointer. The descriptor points to a structure with 32-bit words: For message schedule function: Word 0: Control word. - WORD0[28]: '0' for message schedule function. Word 1: Pointer to 512 b message chunk (input). Word 2: Pointer to 64 * 32 b word message schedule array (output). For process function: Word 0: Control word. - WORD0[28]: '1' for process function. Word 1: Pointer to 8 * 32 b word current hash value (input) and new hash value (output). Word 2: Pointer to 64 * 32 b word message schedule array (input). A write to this register automatically starts a SHA-256 operation. The write ONLY takes effect when the IP is NOT busy (STATUS.BUSY is '0'). The write will be made pending/blocked as long as the IP is busy. Note: the pointers must be 32-bit word aligned. Note: HW updates this field when the SHA-256 engine is busy. Default Value: Undefined

4.1.6 CRYPTOLITE_INTR_ERROR

Error interrupt

Address: 0x402D00F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1C
HW Access	None							RW1S
Name	None [7:1]							BUS_ERROR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	BUS_ERROR	AHB-Lite master interface bus error or ECC error. Note that the IP terminates its AES, SHA or VU functionality when it detects an error. Note: The error is sticky. This allows SW to check for an error after a series of operations, rather than checking after every individual operation. Default Value: 0

4.1.7 CRYPTOLITE_INTR_ERROR_SET

Error interrupt set

Address: 0x402D00F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1S
HW Access	None							A
Name	None [7:1]							BUS_ERROR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	BUS_ERROR	Write this field with '1' to set corresponding INTR_ERROR field to '1' (a write of '0' has no effect). Default Value: 0

4.1.8 CRYPTOLITE_INTR_ERROR_MASK

Error interrupt mask

Address: 0x402D00F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							BUS_ERROR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	BUS_ERROR	Mask for corresponding field in INTR_ERROR register. Default Value: 0

4.1.9 CRYPTOLITE_INTR_ERROR_MASKED

Error interrupt masked

Address: 0x402D00FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							BUS_ERROR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	BUS_ERROR	Logical and of corresponding INTR_ERROR and INTR_ERROR_MASK fields. Default Value: 0

4.1.10 CRYPTOLITE_TRNG_CTL0

TRNG control 0

Address: 0x402D0100

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SAMPLE_CLOCK_DIV [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RED_CLOCK_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INIT_DELAY [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW	RW	None		RW	RW
HW Access	None		R	R	None		R	R
Name	None [31:30]		STOP_ON_RC_DETECT	STOP_ON_AP_DETECT	None [27:26]		FEEDBACK_EN	VON_NEUMANN_CORR

Bits	Name	Description
29	STOP_ON_RC_DETECT	Specifies if TRNG functionality is stopped on a repetition count test detection (when HW sets INTR_ERROR.TRNG_RC_DETECT to '1'): '0': Functionality is NOT stopped. '1': Functionality is stopped (TRNG_CTL1 fields are set to '0' by HW). The DAS bitstream is set to '0'. Default Value: 1
28	STOP_ON_AP_DETECT	Specifies if TRNG functionality is stopped on an adaptive proportion test detection (when HW sets INTR_ERROR.TRNG_AP_DETECT to '1'): '0': Functionality is NOT stopped. '1': Functionality is stopped (TRNG_CTL1 fields are set to '0' by HW). The DAS bitstream is set to '0'. Default Value: 1

4.1.10 CRYPTOLITE_TRNG_CTL0 (continued)

25	FEEDBACK_EN	Specifies if the feedback of the reducution state is enabled: '0': Disabled. '1': Enabled. Note: This field is added in the "mxcryptolite" IP to address CDT#337111, in which it was observed that the reduction state feedback reduces the effectiveness of the "von Neumann corrector". The default value is '1' to provide backward compatibility. Default Value: 1
24	VON_NEUMANN_CORR	Specifies if the "von Neumann corrector" is disabled or enabled: '0': disabled. '1': enabled. The "von Neumann corrector" post-processes the reduced bits to remove a '0' or '1' bias. The corrector operates on reduced bit pairs ("oldest bit, newest bit"): "00": no bit is produced. "01": '0' bit is produced (oldest bit). "10": '1' bit is produced (oldest bit). "11": no bit is produced. Note that the corrector produces bits at a random pace and at a frequency that is 1/4 of the reduced bit frequency (reduced bits are processed in pairs, and half of the pairs do NOT produce a bit). Default Value: 1
23 : 16	INIT_DELAY	Specifies an initialization delay: number of removed/dropped samples before reduced bits are generated. This field should be programmed in the range [1, 255]. After starting the oscillators, at least the first 2 samples should be removed/dropped to clear the state of internal synchronizers. In addition, it is advised to drop at least the second 2 samples from the oscillators (to circumvent the semi-predictable oscillator startup behavior). This result in the default field value of "3". Field encoding is as follows: "0": 1 sample is dropped. "1": 2 samples are dropped. ... "255": 256 samples are dropped. The INTR.INITIALIZED interrupt cause is set to '1', when the initialization delay is passed. Default Value: 3
15 : 8	RED_CLOCK_DIV	Specifies the clock divider that is used to produce reduced bits. "0": 1 reduced bit is produced for each sample. "1": 1 reduced bit is produced for each 2 samples. ... "255": 1 reduced bit is produced for each 256 samples. The reduced bits are considered random bits and shifted into TRNG_RESULT.DATA. Default Value: 0
7 : 0	SAMPLE_CLOCK_DIV	Specifies the clock divider that is used to sample oscillator data. This clock divider is wrt. The IP clock. "0": sample clock is the IP clock. "1": sample clock is the IP clock divided by 2. ... "255": sample clock is the IP clock divided by 256. Default Value: 0

4.1.11 CRYPTOLITE_TRNG_CTL1

TRNG control 1

Address: 0x402D0104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:6]		FIRO31_EN	FIRO15_EN	GARO31_EN	GARO15_EN	RO15_EN	RO11_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	FIRO31_EN	FW sets this field to '1' to enable the programmable Fibonacci ring oscillator with up to 31 inverters. The TRNG_FIRO_CTL register specifies the programmable polynomial. Default Value: 0
4	FIRO15_EN	FW sets this field to '1' to enable the fixed Fibonacci ring oscillator with 15 inverters. Default Value: 0
3	GARO31_EN	FW sets this field to '1' to enable the programmable Galois ring oscillator with up to 31 inverters. The TRNG_GARO_CTL register specifies the programmable polynomial. Default Value: 0
2	GARO15_EN	FW sets this field to '1' to enable the fixed Galois ring oscillator with 15 inverters. Default Value: 0
1	RO15_EN	FW sets this field to '1' to enable the ring oscillator with 15 inverters. Default Value: 0
0	RO11_EN	FW sets this field to '1' to enable the ring oscillator with 11 inverters. Default Value: 0

4.1.12 CRYPTOLITE_TRNG_STATUS

TRNG status

Address: 0x402D010C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							INITIAL-IZED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	INITIALIZED	Reflects the state of the true random number generator: '0': Not initialized (TRNG_CTL0.INIT_DELAY has NOT passed). '1': Initialized (TRNG_CTL0.INIT_DELAY has passed). Default Value: 0

4.1.13 CRYPTOLITE_TRNG_RESULT

TRNG result

Address: 0x402D0110

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Generated 32-bit true random number. The INTR.DATA_AVAILABLE interrupt cause is activated when the number is generated. Default Value: Undefined

4.1.14 CRYPTOLITE_TRNG_GARO_CTL

TRNG GARO control

Address: 0x402D0120

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	POLYNOMIAL [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	POLYNOMIAL [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	POLYNOMIAL [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW						
HW Access	None	R						
Name	None	POLYNOMIAL [30:24]						

Bits	Name	Description
30 : 0	POLYNOMIAL	Polynomial for programmable Galois ring oscillator. The polynomial is represented WITHOUT the high order bit (this bit is always assumed '1'). The polynomial should be aligned such that the more significant bits (bit 30 and down) contain the polynomial and the less significant bits (bit 0 and up) contain padding '0's. Note: Default value per GESC#113. Default Value: 569907472

4.1.15 CRYPTOLITE_TRNG_FIRO_CTL

TRNG FIRO control

Address: 0x402D0124

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	POLYNOMIAL [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	POLYNOMIAL [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	POLYNOMIAL [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW						
HW Access	None	R						
Name	None	POLYNOMIAL [30:24]						

Bits	Name	Description
30 : 0	POLYNOMIAL	Polynomial for programmable Fibonacci ring oscillator. The polynomial is represented WITHOUT the high order bit (this bit is always assumed '1'). The polynomial should be aligned such that the more significant bits (bit 30 and down) contain the polynomial and the less significant bits (bit 0 and up) contain padding '0's. Note: Default value per GESC#113. Default Value: 1768882721

4.1.16 CRYPTOLITE_TRNG_MON_CTL

TRNG monitor control

Address: 0x402D0140

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						BITSTREAM_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [15:10]						RC	AP

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	RC	Repetition count (RC) test enable: '0': Disabled. '1': Enabled. On a RC detection, HW sets this field to '0' and sets INTR_ERROR.TRNG_RC_DETECT to '1. Default Value: 0
8	AP	Adaptive proportion (AP) test enable: '0': Disabled. '1': Enabled. On a AP detection, HW sets this field to '0' and sets INTR_ERROR.TRNG_AP_DETECT to '1. Default Value: 0
1 : 0	BITSTREAM_SEL	Selection of the bitstream: "0": DAS bitstream. "1": RED bitstream. "2": TR bitstream. "3": Undefined. Default Value: 2

4.1.17 CRYPTOLITE_TRNG_MON_RC_CTL

TRNG monitor RC control

Address: 0x402D0150

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CUTOFF_COUNT8 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	CUTOFF_COUNT8	Cutoff count (legal range is [1, 255]): "0": Illegal. "1": 1 repetition. ... "255": 255 repetitions. Default Value: 255

4.1.18 CRYPTOLITE_TRNG_MON_RC_STATUS0

TRNG monitor RC status 0

Address: 0x402D0158

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							BIT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	BIT	Current active bit value: '0': '0'. '1': '1'. This field is only valid when TRNG_MON_RC_STATUS1.REP_COUNT is NOT equal to "0". Default Value: 0

4.1.19 CRYPTOLITE_TRNG_MON_RC_STATUS1

TRNG monitor RC status 1

Address: 0x402D015C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	REP_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	REP_COUNT	Number of repetitions of the current active bit counter: "0": 0 repetitions. ... "255": 255 repetitions. Default Value: 0

4.1.20 CRYPTOLITE_TRNG_MON_AP_CTL

TRNG monitor AP control

Address: 0x402D0160

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CUTOFF_COUNT16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CUTOFF_COUNT16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	WINDOW_SIZE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	WINDOW_SIZE [31:24]							

Bits	Name	Description
31 : 16	WINDOW_SIZE	Window size (minus 1) : "0": 1 bit. ... "65535": 65536 bits. Default Value: 65535
15 : 0	CUTOFF_COUNT16	Cutoff count (legal range is [1, 65535]). "0": Illegal. "1": 1 occurrence. ... "65535": 65535 occurrences. Default Value: 65535

4.1.21 CRYPTOLITE_TRNG_MON_AP_STATUS0

TRNG monitor AP status 0

Address: 0x402D0168

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							BIT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	BIT	Current active bit value: '0': '0'. '1': '1'. This field is only valid when TRNG_MON_AP_STATUS1.OCC_COUNT is NOT equal to "0". Default Value: 0

4.1.22 CRYPTOLITE_TRNG_MON_AP_STATUS1

TRNG monitor AP status 1

Address: 0x402D016C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	OCC_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	OCC_COUNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	WINDOW_INDEX [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	RW							
Name	WINDOW_INDEX [31:24]							

Bits	Name	Description
31 : 16	WINDOW_INDEX	Counter to keep track of the current index in the window (counts from "0" to TRNG_MON_AP_CTL.WINDOW_SIZE to "0"). Default Value: 0
15 : 0	OCC_COUNT	Number of occurrences of the current active bit counter: "0": 0 occurrences ... "65535": 65535 occurrences Default Value: 0

4.1.23 CRYPTOLITE_INTR_TRNG

TRNG interrupt

Address: 0x402D01F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [7:4]				RC_DETECT	AP_DETECT	DATA_AVAILABLE	INITIAL-IZED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RC_DETECT	This interrupt cause is activated (HW sets the field to '1') when the TRNG monitor detects an "repetition count" error. Default Value: 0
2	AP_DETECT	This interrupt cause is activated (HW sets the field to '1') when the TRNG monitor detects an "adaptive proportion" error. Default Value: 0
1	DATA_AVAILABLE	This interrupt cause is activated (HW sets the field to '1') when 32 bits of TRNG data becomes available in TRNG_RESULT. Default Value: 0
0	INITIALIZED	This interrupt cause is activated (HW sets the field to '1') when the TRNG is initialized. Default Value: 0

4.1.24 CRYPTOLITE_INTR_TRNG_SET

TRNG Interrupt set

Address: 0x402D01F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [7:4]				RC_DETECT	AP_DETECT	DATA_AVAILABLE	INITIAL-IZED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RC_DETECT	SW writes a '1' to this field to set the corresponding field in interrupt request register. Default Value: 0
2	AP_DETECT	SW writes a '1' to this field to set the corresponding field in interrupt request register. Default Value: 0
1	DATA_AVAILABLE	SW writes a '1' to this field to set the corresponding field in interrupt request register. Default Value: 0
0	INITIALIZED	SW writes a '1' to this field to set the corresponding field in interrupt request register. Default Value: 0

4.1.25 CRYPTOLITE_INTR_TRNG_MASK

TRNG Interrupt mask

Address: 0x402D01F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RC_DETECT	AP_DETECT	DATA_AVAILABLE	INITIAL-IZED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RC_DETECT	Mask bit for corresponding field in interrupt request register. Default Value: 0
2	AP_DETECT	Mask bit for corresponding field in interrupt request register. Default Value: 0
1	DATA_AVAILABLE	Mask bit for corresponding field in interrupt request register. Default Value: 0
0	INITIALIZED	Mask bit for corresponding field in interrupt request register. Default Value: 0

4.1.26 CRYPTOLITE_INTR_TRNG_MASKED

TRNG Interrupt masked

Address: 0x402D01FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				RC_DETECT	AP_DETECT	DATA_AVAILABLE	INITIAL-IZED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RC_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
2	AP_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
1	DATA_AVAILABLE	Logical and of corresponding request and mask bits. Default Value: 0
0	INITIALIZED	Logical and of corresponding request and mask bits. Default Value: 0

5 CSD Registers

This section discusses the CSD registers. It lists all the registers in mapping tables, in address order.

5.1 Register Details

Register Name	Address
CSD_CONFIG	0x402A0000
CSD_SPARE	0x402A0004
CSD_STATUS	0x402A0080
CSD_STAT_SEQ	0x402A0084
CSD_STAT_CNTS	0x402A0088
CSD_STAT_HCNT	0x402A008C
CSD_RESULT_VAL1	0x402A00D0
CSD_RESULT_VAL2	0x402A00D4
CSD_ADC_RES	0x402A00E0
CSD_INTR	0x402A00F0
CSD_INTR_SET	0x402A00F4
CSD_INTR_MASK	0x402A00F8
CSD_INTR_MASKED	0x402A00FC
CSD_HSCMP	0x402A0180
CSD_AMBUF	0x402A0184
CSD_REFGEN	0x402A0188
CSD_CSDCMP	0x402A018C
CSD_IDACA	0x402A01C0
CSD_IDACB	0x402A01C4
CSD_SW_RES	0x402A01F0
CSD_SENSE_PERIOD	0x402A0200
CSD_SENSE_DUTY	0x402A0204
CSD_SW_HS_P_SEL	0x402A0280
CSD_SW_HS_N_SEL	0x402A0284
CSD_SW_SHIELD_SEL	0x402A0288
CSD_SW_HS_P_SEL1	0x402A028C
CSD_SW_AMUXBUF_SEL	0x402A0290

Register Name	Address
CSD_SW_BYP_SEL	0x402A0294
CSD_SW_CMP_P_SEL	0x402A02A0
CSD_SW_CMP_N_SEL	0x402A02A4
CSD_SW_REFGEN_SEL	0x402A02A8
CSD_SW_FW_MOD_SEL	0x402A02B0
CSD_SW_FW_TANK_SEL	0x402A02B4
CSD_SW_DSI_SEL	0x402A02C0
CSD_SEQ_TIME	0x402A0300
CSD_SEQ_INIT_CNT	0x402A0310
CSD_SEQ_NORM_CNT	0x402A0314
CSD_ADC_CTL	0x402A0320
CSD_SEQ_START	0x402A0340

5.1.1 CSD_CONFIG

Configuration and Control

Address: 0x402A0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			RW	None		
HW Access	None	R			R	None		
Name	None	FILTER_DELAY [6:4]			LOW_VDDA	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW	None	RW	None		RW	
HW Access	None	R	None	R	None		R	
Name	None	CHARGE_MODE	None	SENSE_EN	None [11:10]		SHIELD_DELAY [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW	RW	RW	None
HW Access	None				R	R	R	None
Name	None [23:20]				CSX_DUAL_CNT	MUTUAL_CAP	FULL_WAVE	None

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None		RW	RW	RW	RW
HW Access	R	R	None		R	R	R	R
Name	ENABLE	LP_MODE	None [29:28]		DSI_SENSE_EN	SAMPLE_SYNC	DSI_SAMPLE_EN	DSI_COUNT_SEL

Bits	Name	Description
31	ENABLE	Master enable of the CSDv2 IP. Must be set to 1 for any CSDv2, ADC or IDAC operation to function. When 0 all analog components will be off and all switches will be open. Default Value: 0
30	LP_MODE	Select the power mode for the CSD components (REFGEN, AMBUF, CSDCMP, HSCMP): 0: High Power mode 1: Low Power mode Default Value: 0
27	DSI_SENSE_EN	Enables the use of the dsi_sense_in input instead of the internally generated modulation signal to drive csd_sense and csd_shield signals. Default Value: 0
26	SAMPLE_SYNC	Enables double synchronizing of sample input from DSI (only relevant when DSI_SAMPLE_EN=1). Default Value: 1

5.1.1 CSD_CONFIG (continued)

25	DSI_SAMPLE_EN	Enables the use of the dsi_sample_in input instead of the comparator output to strobe COUNTER. Default Value: 0
24	DSI_COUNT_SEL	Select what to output on the dsi_count bus. Default Value: 0 **0x0: CSD_RESULT:** depending on the dsi_count_val_sel input either output RESULT_VAL1.VALUE (0) or RESULT_VAL2.VALUE (1) on the dsi_count bus. Note that dsi_count_val_sel is not synchronized, i.e. it controls the mux combinatorially. **0x1: ADC_RESULT:** output ADC_RES.VIN_CNT on the dsi_count bus
19	CSX_DUAL_CNT	Enable the use of two counters for MUTUAL cap sensing mode (CSX), do not use when MUTUAL_CAP=0 Default Value: 0 **0x0: ONE:** Use one counter for both phases (source and sink). **0x1: TWO:** Use two counters, separate count for when csd_sense is high and when csd_sense is low.
18	MUTUAL_CAP	Enables mutual cap sensing mode Default Value: 0 **0x0: SELFCAP:** Self-cap mode (configure sense line as CSD_SENSE) **0x1: MUTUALCAP:** Mutual-cap mode (configure Tx line as CSD_SENSE, inverted Tx line as CSD_SHIELD and Rx Line as AMUXA). In this mode the polarity bit of the IDAC is controlled by csd_sense.
17	FULL_WAVE	Enables full wave cap sensing mode Default Value: 0 **0x0: HALFWAVE:** Half Wave mode (normal). In this mode the comparator always trips in the same direction (positive or negative edge) and the same Vref, i.e. no polarity change. **0x1: FULLWAVE:** Full Wave mode. In this mode the comparator trips in opposite direction and with different Vref in each phase, i.e. the polarity flips.
14	CHARGE_MODE	Enable charging of the Cmod/Csh_tank capacitor using the GPIO digital output buffer using the csd_charge signal. Note that using the GPIO requires proper configuraiton of the GPIO pin. Default Value: 0 **0x0: CHARGE_OFF:** Use this to keep csd_charge signal low. For charging Cmod/Csh_tank capacitor CSD internal switches (HCBV) can be used but that is a separate configuration. **0x1: CHARGE_IO:** Use csd_charge to enable the GPIO Driver to charge capacitor. The capacitor must be sensed with HSCMP using the appropriate switches (HMPM or HMPT).
12	SENSE_EN	Enables the sense modulator output. 0: all switches, static or dynamic, are open and IDAC in CSD mode is off 1: switches and IDAC can be closed/on as per MMIO setting and CSD sequencer. Default Value: 0

5.1.1 CSD_CONFIG (continued)

9 : 8	SHIELD_DELAY	Selects the delay by which csd_shield is delayed relative to csd_sense. Default Value: 0 **0x0: OFF:** Delay line is off, csd_shield=csd_sense **0x1: D5NS:** Introduces a 5ns delay (typ) **0x2: D10NS:** Introduces a 10ns delay (typ) **0x3: D20NS:** Introduces a 20ns delay (typ)
6 : 4	FILTER_DELAY	This value determines the number of cycles that the digital filter makes the CSDCMP output ignored while the counter counts and IDAC is on. When set to 0 the digital filter is off. When set to any other value the ignoring will last for FILTER_DELAY clk_csd cycles after the start of each measurement and from the first comparator trip to the end of each measurement. Default Value: 0
3	LOW_VDDA	Set this bit when VDDA is known to be below ~2V, this bit is used to improve IDACs performance at low voltages. Default Value: 0

5.1.2 CSD_SPARE

Spare MMIO

Address: 0x402A0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				RW			
Name	None [7:4]				SPARE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SPARE	Spare MMIO Default Value: 0

5.1.3 CSD_STATUS

Status Register

Address: 0x402A0080

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				RW	RW	RW	RW
Name	None [7:4]				CSDCMP_OUT	HSCMP_OUT	CSD_SENSE	CSD_CHARGE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	CSDCMP_OUT	Output of main sensing comparator (synchronized) Default Value: 0
2	HSCMP_OUT	Output of reference buffer comparator used to charge up Cmod and/or Csh_tank (synchronized) Default Value: 0 **0x0: C_LT_VREF:** Vin < Vref **0x1: C_GT_VREF:** Vin > Vref
1	CSD_SENSE	Signal used to drive the Cs switches. Default Value: 0
0	CSD_CHARGE	Qualified, and possible inverted value of COMP_OUT that is used to drive GPIO's charging Cmod or Csh_tank. Default Value: 0

5.1.4 CSD_STAT_SEQ

Current Sequencer status

Address: 0x402A0084

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R		
HW Access	None					RW		
Name	None [7:3]					SEQ_STATE [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					R		
HW Access	None					RW		
Name	None [23:19]					ADC_STATE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
18 : 16	ADC_STATE	ADC sequencer state (only relevant after SEQ_STATE has reached SAMPLE_NORM and ADC sequencer has started) Default Value: 0
2 : 0	SEQ_STATE	CSD sequencer state Default Value: 0

5.1.5 CSD_STAT_CNTS

Current status counts

Address: 0x402A0088

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	NUM_CONV [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	NUM_CONV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	NUM_CONV	Current number of conversions remaining when in Sample_* states (note that in AutoZero* states the same down counter is reused to count the cycles) Default Value: 0

5.1.6 CSD_STAT_HCNT

Current count of the HSCMP counter

Address: 0x402A008C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CNT	Current value of HSCMP counter Default Value: 0

5.1.7 CSD_RESULT_VAL1

Result CSD/CSX accumulation counter value 1

Address: 0x402A00D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	BAD_CONVS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BAD_CONVS	Number of 'bad' conversion for which the CSD comparator did not trigger within the normal time window, either because Vref was not crossed at all, or if the Vref was already crossed before the window started. This counter is reset when the sequencer is started and will saturate at 255 when more than 255 conversions are bad. Default Value: 0
15 : 0	VALUE	Accumulated counter value for this result. In case of Mutual cap with two counters (CSX = config.mutual_cap & config.csx_dual_cnt) this counter counts when csd_sense is high. Default Value: 0

5.1.8 CSD_RESULT_VAL2

Result CSX accumulation counter value 2

Address: 0x402A00D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	VALUE	Only used in case of Mutual cap with two counters (CSX = config.mutual_cap & config.csx_dual_cnt), this counter counts when csd_sense is low. Default Value: 0

5.1.9 CSD_ADC_RES

ADC measurement

Address: 0x402A00E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	VIN_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	VIN_CNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							RW
Name	None [23:17]							HSCMP_POL

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	RW	RW	None					
Name	ADC_ABORT	ADC_OVERFLOW	None [29:24]					

Bits	Name	Description
31	ADC_ABORT	This flag is set when the ADC sequencer was aborted before tripping HSCMP. Default Value: 0
30	ADC_OVERFLOW	This flag is set when the ADC counter overflows. This is an indication to the firmware that the IDACB current level is too low. Default Value: 0
16	HSCMP_POL	Polarity used for IDACB for this last ADC result, 0= source, 1= sink Default Value: 0
15 : 0	VIN_CNT	Count to source/sink Cref1 + Cref2 from Vin to Vrefhi or Vssa. Default Value: 0

5.1.10 CSD_INTR

CSD Interrupt Request Register

Address: 0x402A00F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1C	RW1C	None
HW Access	None					RW1S	RW1S	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							RW1S
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	ADC Result ready Default Value: 0
2	INIT	Coarse initialization complete or Sample initialization complete (the latter is typically ignored) Default Value: 0
1	SAMPLE	A normal sample is complete (CSDv1 compatible interrupt) Default Value: 0

5.1.11 CSD_INTR_SET

CSD Interrupt set register

Address: 0x402A00F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1S	RW1S	None
HW Access	None					A	A	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1S
HW Access	None							A
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	INIT	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	SAMPLE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

5.1.12 CSD_INTR_MASK

CSD Interrupt mask register

Address: 0x402A00F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	None
HW Access	None					R	R	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	INIT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	SAMPLE	Mask bit for corresponding bit in interrupt request register. Default Value: 0

5.1.13 CSD_INTR_MASKED

CSD Interrupt masked register

Address: 0x402A00FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R	R	None
HW Access	None					W	W	None
Name	None [7:3]					INIT	SAMPLE	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							ADC_RES

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	ADC_RES	Logical and of corresponding request and mask bits. Default Value: 0
2	INIT	Logical and of corresponding request and mask bits. Default Value: 0
1	SAMPLE	Logical and of corresponding request and mask bits. Default Value: 0

5.1.14 CSD_HSCMP

High Speed Comparator configuration

Address: 0x402A0180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [7:5]			HSCMP_INVERT	None [3:1]			HSCMP_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	AZ_EN	None [30:24]						

Bits	Name	Description
31	AZ_EN	Auto-Zero enable, allow the Sequencer to Auto-Zero this component Default Value: 0
4	HSCMP_INVERT	Invert the HSCMP output before it is used to control switches and the CSD sequencer. This bit does not affect the ADC sequencer or the STATUS.HSCMP_OUT Default Value: 0
0	HSCMP_EN	High Speed Comparator enable Default Value: 0 **0x0: OFF:** Disable comparator, output is zero **0x1: ON:** On, regular operation. Note that CONFIG.LP_MODE determines the power mode level

5.1.15 CSD_AMBUF

Reference Generator configuration

Address: 0x402A0184

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	PWR_MODE	Amux buffer power level Default Value: 0 **0x0: OFF:** Disable buffer **0x1: NORM:** On, normal or low power level depending on CONFIG.LP_MODE. **0x2: HI:** On, high or low power level depending on CONFIG.LP_MODE.

5.1.16 CSD_REFGEN

Reference Generator configuration

Address: 0x402A0188

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None			RW
HW Access	None	R	R	R	None			R
Name	None	RES_EN	VDDA_EN	BYPASS	None [3:1]			REFGEN_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			GAIN [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	RW	None		RW				
HW Access	R	None		R				
Name	VREFLO_INT	None [22:21]		VREFLO_SEL [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	VREFLO_INT	Ouput the resistor string tap either to Vreflo (0) or Vreflo_int (1). Default Value: 0
20 : 16	VREFLO_SEL	Select resistor string tap for Vreflo/Vreflo_int, 0= minimum vout, 31= maximum vout = vrefhi (only works if the resistor string is enabled; RES_EN=1) Default Value: 0
12 : 8	GAIN	Select resistor string tap for feedback, 0= minimum vout, 31= maximum vout = vrefhi -> gain=1 (only works if the resistor string is enabled; RES_EN=1) Default Value: 0
6	RES_EN	Resistor string enable; 0= open switch on top of the resistor string (Vreflo=Vssa) Default Value: 0
5	VDDA_EN	Close Vdda switch to top of resistor string (or Vrefhi?) Default Value: 0
4	BYPASS	Bypass selected input reference unbuffered to Vrefhi Default Value: 0

5.1.16 CSD_REFGEN (continued)

0	REFGEN_EN	Reference Generator Enable Default Value: 0 **0x0: OFF:** Disable Reference Generator **0x1: ON:** On, regular operation. Note that CONFIG.LP_MODE determines the power mode level

5.1.17 CSD_CSDCMP

CSD Comparator configuration

Address: 0x402A018C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		None			RW
HW Access	None		R		None			R
Name	None [7:6]		POLARITY_SEL [5:4]		None [3:1]			CSDCMP_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						CMP_PHASE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW	None			
HW Access	R	None	R	R	None			
Name	AZ_EN	None	FEEDBACK_MODE	CMP_MODE	None [27:24]			

Bits	Name	Description
31	AZ_EN	Auto-Zero enable, allow the Sequencer to Auto-Zero this component Default Value: 0
29	FEEDBACK_MODE	This bit controls whether the output directly from the comparator (csdcmp_out) or the flopped version (csdcmp_out_ff) is used. For CSD operation, the selected signal controls the IDAC(s), in GP mode the signal goes out on dsi_sample_out. Default Value: 0 **0x0: FLOP:** Use feedback from sampling flip-flop (used in most modes). **0x1: COMP:** Use feedback from comparator directly (used in single Cmod mutual cap sensing only)
28	CMP_MODE	Select which signal to output on dsi_sample_out. Default Value: 0 **0x0: CSD:** CSD mode: output the filtered sample signal on dsi_sample_out

5.1.17 CSD_CSDCMP (continued)

		0x1: GP: General Purpose mode: output the unfiltered sample unfiltered comparator output, either asynchronous or flopped.
9 : 8	CMP_PHASE	Select in what phase(s) the comparator is active. Note, this also determines when a bad conversion is detected, namely at the beginning and end of the comparator active phase (also taking into account FILTER_DELAY and non-overlap). Default Value: 0
		0x0: FULL: Comparator is active from start of Phi2 and kept active into Phi1. Intended usage: legacy CSD for balancing over a full csd_sense period (non-overlap should be turned off)
		0x1: PHI1: Comparator is active during Phi1 only. Currently no known use-case.
		0x2: PHI2: Comparator is active during Phi2 only. Intended usage: CSD Low EMI.
		0x3: PHI1_2: Comparator is activated at the start of both Phi1 and Phi2 (non-overlap should be enabled). Intended usage: CSX, or Full-Wave.
5 : 4	POLARITY_SEL	Select which IDAC polarity to use to detect CSDCMP triggering Default Value: 0
		0x0: IDACA_POL: Use idaca_pol (firmware setting with CSX and optionally DSI mixed in) to determine the direction, this is the most common use-case, used for normal CSD and normal CSX
		0x1: IDACB_POL: Use idacb_pol (firmware setting with optional DSI mixed in) to determine the direction, this is only used for normal CSD if IDACB is used i.s.o. IDACA (not common)
		0x2: DUAL_POL: Use the expression (csd_sense ? idaca_pol : idacb_pol) to determine the direction, this is only useful for the CSX with DUAL_IDAC use-case
0	CSDCMP_EN	CSD Comparator Enable Default Value: 0
		0x0: OFF: Disable comparator, output is zero
		0x1: ON: On, regular operation. Note that CONFIG.LP_MODE determines the power mode level

5.1.18 CSD_IDACA

IDACA Configuration

Address: 0x402A01C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW						
HW Access	R	R						
Name	POL_DYN	VAL [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [15:12]				BAL_MODE [11:10]		POLARITY [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW	None	RW		RW	
HW Access	R		R	None	R		R	
Name	RANGE [23:22]		DSI_CTRL_EN	None	LEG2_MODE [19:18]		LEG1_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						LEG2_EN	LEG1_EN

Bits	Name	Description
25	LEG2_EN	output enable for leg 2 to CSDBUSA Default Value: 0
24	LEG1_EN	output enable for leg 1 to CSDBUSA Default Value: 0
23 : 22	RANGE	IDAC multiplier Default Value: 0 **0x0: IDAC_LO:** 1 LSB = 37.5 nA **0x1: IDAC_MED:** 1 LSB = 300 nA **0x2: IDAC_HI:** 1 LSB = 2400 nA **0x3: IDAC_MED2:** 1 LSB = 1200 nA

5.1.18 CSD_IDACA (continued)

21	DSI_CTRL_EN	Mix DSI inputs with MMIO controls or not (before getting mixed with CSD controls if enabled). 0: no DSI control IDACA_POLARITY = IDACA.POLARITY IDACA_LEG1_EN = IDACA.LEG1_EN IDACA_LEG2_EN = IDACA.LEG2_EN 1: Mix MMIO with DSI control IDACA_POLARITY = IDACA.POLARITY EXOR dsi_idaca_pol IDACA_LEG1_EN = IDACA.LEG1_EN AND dsi_idaca_leg1_en IDACA_LEG2_EN = IDACA.LEG2_EN AND dsi_idaca_leg2_en Default Value: 0
19 : 18	LEG2_MODE	Controls the usage mode of LEG2 Default Value: 0 **0x0: GP_STATIC:** General Purpose static mode: LEG2 is controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer. **0x1: GP:** General Purpose dynamic mode: LEG2 is controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled. **0x2: CSD_STATIC:** CSD static mode: LEG2 can only be on when the CSD Sequencer is in the Sample_init or Sample_norm state. In those states LEG2 is controlled by LEG2_EN, csd_sense and the CSD configuration. Polarity is controlled by the CSD configuration and operation. In addition leg2 enable and polarity can optionally be mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer. **0x3: CSD:** CSD dynamic mode: LEG2 can only be on when the CSD Sequencer is in the Sample_init or Sample_norm state. In those states LEG2 is controlled by LEG2_EN, the CSD configuration, csd_sense and the flopped CSDCMP output (CSDCMP_OUT_FF). In addition leg2 enable can optionally be mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled.
17 : 16	LEG1_MODE	Controls the usage mode of LEG1 and the Polarity bit Default Value: 0 **0x0: GP_STATIC:** General Purpose static mode: LEG1 and POLARITY are controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer. **0x1: GP:** General Purpose dynamic mode: LEG1 and POLARITY are controlled by MMIO and optionally mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled. **0x2: CSD_STATIC:** CSD static mode: LEG1 can only be on when the CSD Sequencer is in the Sample_init or Sample_norm state. In those states LEG1 is controlled by LEG1_EN, csd_sense and the CSD configuration. Polarity is controlled by the CSD configuration and operation. In addition leg1 enable and polarity can optionally be mixed with DSI (see DSI_CTRL_EN). No shunting is used, this saves power when off but also any on/off switching will take longer.

5.1.18 CSD_IDACA (continued)

		0x3: CSD: CSD dynamic mode: LEG1 can only be on when the CSD Sequencer is in the Sample_init or Sample_norm state. In thoses states LEG1 is controlled by LEG1_EN, the CSD configuration, csd_sense and the flopped CSDCMP output (CSDCMP_OUT_FF). Polarity is controlled by the CSD configuration and operation. In addition leg1 enable and polarity can optionally be mixed with DSI (see DSI_CTRL_EN). Shunting is used, so on/off switching is faster, but power is wasted when the leg is disabled.
11 : 10	BAL_MODE	Balancing mode: only applies to legs configured as CSD. Default Value: 0 **0x0: FULL:** enabled from start of Phi2 until disabled by CSDCMP. Intended usage: legacy CSD for balancing over a full csd_sense period (non-overlap should be turned off) **0x1: PHI1:** enabled from start of Phi1 and disabled by CSDCMP or at end of Phi1. Enables dual IDAC CSX or Full-Wave, one for sourcing and the other for sinking. **0x2: PHI2:** enabled from start of Phi2 and disabled by CSDCMP or at end of Phi2. Intended usage: CSD Low EMI or dual IDAC CSX or Full-Wave. **0x3: PHI1_2:** enabled from start of both Phi1 and Phi2 and disabled by CSDCMP or at end of Phi1 or Phi2 (if non-overlap enabled). Intended usage: single IDAC CSX, or Full-Wave.
9 : 8	POLARITY	Selects the polarity of the IDAC (sensing operation). Normally the actual polarity depends on this bit, optionally mixed with DSI (see DSI_CTRL_EN) and if LEG1_MODE==CSD also mixed with the CSD configuration and operation. However in mutual cap mode with one IDAC (config.mutual_cap=1 & config.csx_dual_idac=0) the polarity of the IDAC is controlled by csd_sense. Default Value: 0 **0x0: VSSA_SRC:** Normal: switch between Vssa and Cmod. For non-CSD application, IDAC will source current. **0x1: VDDA_SNK:** Inverted: switch between Vdda and Cmod. For non-CSD application, IDAC will sink current. **0x2: SENSE:** The polarity of the IDAC will follow the csd_sense signal (POL_DYN bit should be set too). The intended usage is for CSX using a single IDAC. **0x3: SENSE_INV:** The polarity of the IDAC will follow the inverted csd_sense signal (POL_DYN bit should be set too). The intended usage is for CSX using a single IDAC.
7	POL_DYN	Polarity is dynamic, this bit does not influence the logic in the SoftIP, it only goes to the HardIP. Default Value: 0 **0x0: STATIC:** Static polarity. Polarity is expected to be stable, so to save power this avoids the shunting of the unused polarity, at the expense of response time. **0x1: DYNAMIC:** Dynamic polarity. Polarity is expected to change frequently (e.g. invert after every csd_sense phase), so to improve response time this keeps the shunt of the unused polarity on at the expense of power.
6 : 0	VAL	Current value setting for this IDAC (7 bits). Default Value: 0

5.1.19 CSD_IDACB

IDACB Configuration

Address: 0x402A01C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW						
HW Access	R	R						
Name	POL_DYN	VAL [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [15:12]				BAL_MODE [11:10]		POLARITY [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW	None	RW		RW	
HW Access	R		R	None	R		R	
Name	RANGE [23:22]		DSI_CTRL_EN	None	LEG2_MODE [19:18]		LEG1_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [31:27]					LEG3_EN	LEG2_EN	LEG1_EN

Bits	Name	Description
26	LEG3_EN	output enable for leg3 to CSDBUSC, only allowed when RANGE = IDAC_LO. When this bit is set both other legs should be off. Note that leg3 can only be used for ADC mode, not GP mode. Which means that leg3 can only be on when the ADC Sequencer is in the ADC_measure or Calib_measure state. In those states leg3 is controlled by the ADC configuration and the HSCMP output. In addition this leg3 enable bit can optionally be mixed with DSI (see DSI_CTRL_EN). When LEG3_EN=1 also the IDACB polarity is controlled by the ADC sequencer. Default Value: 0
25	LEG2_EN	output enable for leg 2 to CSDBUSB or CSDBUSA Default Value: 0
24	LEG1_EN	output enable for leg 1 to CSDBUSB or CSDBUSA Default Value: 0
23 : 22	RANGE	IDAC multiplier Default Value: 0 **0x0: IDAC_LO:** 1 LSB = 37.5 nA

5.1.19 CSD_IDACB (continued)

		0x1: IDAC_MED: 1 LSB = 300 nA **0x2: IDAC_HI:** 1 LSB = 2400 nA **0x3: IDAC_MED2:** 1 LSB = 1200 nA
21	DSI_CTRL_EN	Mix DSI inputs with MMIO controls or not (before getting mixed with CSD controls if enabled) 0: no DSI control IDACB_POLARITY = IDACB.POLARITY IDACB_LEG1_EN = IDACB.LEG1_EN IDACB_LEG2_EN = IDACB.LEG2_EN IDACB_LEG3_EN = IDACB.LEG3_EN 1: Mix MMIO with DSI control IDACB_POLARITY = IDACB.POLARITY EXOR dsi_idacb_pol IDACB_LEG1_EN = IDACB.LEG1_EN AND dsi_idacb_leg1_en IDACB_LEG2_EN = IDACB.LEG2_EN AND dsi_idacb_leg2_en IDACB_LEG3_EN = IDACB.LEG3_EN AND dsi_idacb_leg3_en Default Value: 0
19 : 18	LEG2_MODE	Controls the usage mode of LEG2 Default Value: 0 **0x0: GP_STATIC:** same as corresponding IDACA.LEG2_MODE **0x1: GP:** same as corresponding IDACA.LEG2_MODE **0x2: CSD_STATIC:** same as corresponding IDACA.LEG2_MODE **0x3: CSD:** same as corresponding IDACA.LEG2_MODE
17 : 16	LEG1_MODE	Controls the usage mode of LEG1 and the Polarity bit Default Value: 0 **0x0: GP_STATIC:** same as corresponding IDACA.LEG1_MODE **0x1: GP:** same as corresponding IDACA.LEG1_MODE **0x2: CSD_STATIC:** same as corresponding IDACA.LEG1_MODE **0x3: CSD:** same as corresponding IDACA.LEG1_MODE
11 : 10	BAL_MODE	same as corresponding IDACA Balancing mode Default Value: 0 **0x0: FULL:** same as corresponding IDACA Balancing mode **0x1: PHI1:** same as corresponding IDACA Balancing mode **0x2: PHI2:** same as corresponding IDACA Balancing mode

5.1.19 CSD_IDACB (continued)

		0x3: PHI1_2: same as corresponding IDACA Balancing mode
9 : 8	POLARITY	Selects the polarity of the IDAC (sensing operation). Normally the actual polarity depends on this bit, optionally mixed with DSI (see DSI_CTRL_EN) and if LEG1_EN==1 and LEG1_MODE==CSD also mixed with the CSD configuration and operation. In mutual cap mode however (see config.mutual_cap) the polarity of the IDAC is controlled by csd_sense. If LEG3_EN=1 (the other two legs must be off) then the ADC sequencer controls the IDACB polarity, optionally mixed with DSI. Default Value: 0 **0x0: VSSA_SRC:** Normal: switch between Vssa and Cmod. For non-CSD application, IDAC will source current. **0x1: VDDA_SNK:** Inverted: switch between Vdda and Cmod. For non-CSD application, IDAC will sink current. **0x2: SENSE:** The polarity of the IDAC will follow the csd_sense signal (POL_DYN bit should be set too). The intended usage is for CSX using a single IDAC. **0x3: SENSE_INV:** The polarity of the IDAC will follow the inverted csd_sense signal (POL_DYN bit should be set too). The intended usage is for CSX using a single IDAC.
7	POL_DYN	Polarity is dynamic, this bit does not influence the logic in the SoftIP, it only goes to the HardIP. Default Value: 0 **0x0: STATIC:** Static polarity. Polarity is expected to be stable, so to save power this avoids the shunting of the unused polarity, at the expense of response time. **0x1: DYNAMIC:** Dynamic polarity. Polarity is expected to change frequently (e.g. invert after every csd_sense phase), so to improve response time this keeps the shunt of the unused polarity on at the expense of power.
6 : 0	VAL	Current value setting for this IDAC (7 bits). Default Value: 0

5.1.20 CSD_SW_RES

Switch Resistance configuration

Address: 0x402A01F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	RES_HCBG [7:6]		RES_HCBV [5:4]		RES_HCAG [3:2]		RES_HCAV [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [23:20]				RES_F2PT [19:18]		RES_F1PM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 18	RES_F2PT	Select resistance for the corresponding switch Default Value: 0
17 : 16	RES_F1PM	Select resistance for the corresponding switch Default Value: 0 **0x0: LOW:** Low **0x1: MED:** Medium **0x2: HIGH:** High **0x3: RESERVED:** reserved
7 : 6	RES_HCBG	Select resistance or low EMI for the corresponding switch Default Value: 0
5 : 4	RES_HCBV	Select resistance or low EMI for the corresponding switch Default Value: 0

5.1.20 CSD_SW_RES (continued)

3 : 2	RES_HCAG	Select resistance or low EMI for the corresponding switch Default Value: 0
1 : 0	RES_HCAV	Select resistance or low EMI (slow ramp) for the HCAV switch Default Value: 0 **0x0: LOW:** Low **0x1: MED:** Medium **0x2: HIGH:** High **0x3: LOWEMI:** Low EMI (slow ramp: 3 switches closed by fixed delay line)

5.1.21 CSD_SENSE_PERIOD

Sense clock period

Address: 0x402A0200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SENSE_DIV [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SENSE_DIV [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				None	RW		
HW Access	R				None	R		
Name	LFSR_SCALE [23:20]				None	LFSR_SIZE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None				RW		RW	RW1S
HW Access	None				R		R	RW1C
Name	None [31:28]				LFSR_BITS [27:26]		SEL_LFSR_MSB	LFSR_CLEAR

Bits	Name	Description
27 : 26	LFSR_BITS	Selects the number of LSB bits to use from the LSFR to provide the clock dithering variation on the base period. Caveat make sure that SENSE_DIV > the maximum absolute range (e.g. for 4B SENSE_DIV > 8), otherwise results are undefined. Default Value: 3 **0x0: 2B:** use 2 bits: range = [-2,1] **0x1: 3B:** use 3 bits: range = [-4,3] **0x2: 4B:** use 4 bits: range = [-8,7] **0x3: 5B:** use 5 bits: range = [-16,15] (default)
25	SEL_LFSR_MSB	Use the MSB of configured LSFR size as csd_sense signal. Intended to be used only with bit 8 or 12-bit LFSR size for CSDv1 backward compatibility (PRS). When this bit is set then clock divider dithering is disabled. Default Value: 0

5.1.21 CSD_SENSE_PERIOD (continued)

24	LFSR_CLEAR	When set, forces the LFSR to it's initial state (all ones). This bit is automatically cleared by hardware after the LFSR is cleared, which is at the next clk_csd positive edge. This bit should be set whenever this register is written and the LFSR is used. Note that the LFSR will also get reset to all ones during the AutoZero_1/2 states. Default Value: 0
23 : 20	LFSR_SCALE	Shift the LFSR output left by LSFR_SCALE bits before adding to SENSE_DIV. This dithering is disabled when SEL_LSFR_MSB is set. The clock divider to be used = (SENSE_DIV+1) + (SEL_LSFR_MSB ? 0 : (LFSR_OUT<_SCALE)). Note that the clock divider including the dithering term must fit in 12 bits, otherwise the result is undefined. Default Value: 0
18 : 16	LFSR_SIZE	Selects the length of the LFSR which determines the LFSR repeat period. LFSR_BITS LSB of the LFSR are used for the clock dithering variation on the base period (was PRS in CSDv1). Whenever the LFSR is used (non zero value in this field) the LFSR_CLEAR bit should also be set. Default Value: 0 **0x0: OFF:** Don't use clock dithering (=spreadspectrum) (LFSR output value is zero) **0x1: 6B:** 6-bit LFSR (G(x)=X^6 +X^4+X^3+ X+1, period= 63) **0x2: 7B:** 7-bit LFSR (G(x)=X^7 +X^4+X^3+X^2+1, period= 127) **0x3: 9B:** 9-bit LFSR (G(x)=X^9 +X^4+X^3+ X+1, period= 511) **0x4: 10B:** 10-bit LFSR (G(x)=X^10+X^4+X^3+ X+1, period= 1023) **0x5: 8B:** 8-bit LFSR (G(x)=X^8+X^4+X^3+X^2+1, period= 255) **0x6: 12B:** 12-bit LFSR (G(x)=X^12+X^7+X^4+X^3+1, period= 4095)
11 : 0	SENSE_DIV	The length-1 of the Sense modulation 'clock' period in clk_csd cycles. For regular CSD one sense clock cycle = one conversion (=phi1+phi2) . Note this is the base divider, clock dithering may change the actual period length. Note that SENSE_DIV must be at least 1 and additionally also allow for one clk_hf of non overlap on both phases, i.e. if clk_csd=clk_hf then SENSE_DIV must be >=3. Default Value: 0

5.1.22 CSD_SENSE_DUTY

Sense clock duty cycle

Address: 0x402A0204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SENSE_WIDTH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SENSE_WIDTH [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW	RW	None	RW
HW Access	None				R	R	None	R
Name	None [23:20]				OVERLAP_PHI2	OVERLAP_PHI1	None	SENSE_POL

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	OVERLAP_PHI2	Same as OVERLAP_PHI1 but for Phi2 (csd_sense=1). Default Value: 0
18	OVERLAP_PHI1	NonOverlap or not for Phi1 (csd_sense=0). 0 = Non-overlap for Phi1, the Phi1 signal is csd_sense inverted except that the signal goes low 1 clk_sample before csd_sense goes high. Intended usage: new low EMI CSD/CSX with static GPIO. 1 = 'Overlap' (= not non-overlap) for Phi1, the Phi1 signal is csd_sense inverted. Intended usage: legacy CSD with GPIO switching, the GPIO internal circuit ensures that the switches are non-overlapping. Default Value: 0
16	SENSE_POL	Polarity of the sense clock 0 = start with low phase (typical for regular negative transfer CSD) 1 = start with high phase Default Value: 0

5.1.22 CSD_SENSE_DUTY (continued)

11 : 0	SENSE_WIDTH	Defines the length of the first phase of the sense clock in clk_csd cycles. A value of 0 disables this feature and the duty cycle of csd_sense will be 50%, which is equal to SENSE_WIDTH = (SENSE_DIV+1)/2, or when clock dithering is used that becomes [(SENSE_DIV+1) + (LFSR_OUT << LSFR_SCALE)]/2. At all times it must be assured that the phases are at least 2 clk_csd cycles (1 for non overlap), if this rule is violated the result is undefined. Default Value: 0

5.1.23 CSD_SW_HS_P_SEL

HSCMP Pos input switch Waveform selection

Address: 0x402A0280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [7:5]			SW_HMPT	None [3:1]			SW_HMPM

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [15:13]			SW_HMMA	None [11:9]			SW_HMPS

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_HMCA	None [19:17]			SW_HMMB

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_HMRH	None [27:25]			SW_HMCB

Bits	Name	Description
28	SW_HMRH	Set corresponding switch Default Value: 0
24	SW_HMCB	Set corresponding switch Default Value: 0
20	SW_HMCA	Set corresponding switch Default Value: 0
16	SW_HMMB	Set corresponding switch Default Value: 0
12	SW_HMMA	Set corresponding switch Default Value: 0
8	SW_HMPS	Set corresponding switch Default Value: 0
4	SW_HMPT	Set corresponding switch Default Value: 0

5.1.23 CSD_SW_HS_P_SEL (continued)

0	SW_HMPM	Set HMPM switch 0: static open 1: static closed Default Value: 0

5.1.24 CSD_SW_HS_N_SEL

HSCMP Neg input switch Waveform selection

Address: 0x402A0284

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_HCCD	None [19:17]			SW_HCCC

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_HCRL [30:28]			None	SW_HCRH [26:24]		

Bits	Name	Description
30 : 28	SW_HCRL	Select waveform for corresponding switch Default Value: 0
26 : 24	SW_HCRH	Select waveform for corresponding switch Default Value: 0
20	SW_HCCD	Set corresponding switch Default Value: 0
16	SW_HCCC	Set corresponding switch Default Value: 0

5.1.25 CSD_SW_SHIELD_SEL

Shielding switches Waveform selection

Address: 0x402A0288

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_HCAG [6:4]			None	SW_HCAV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_HCBG [14:12]			None	SW_HCBV [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_HCCG	None [19:17]			SW_HCCV

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20	SW_HCCG	Set corresponding switch If the ADC is enabled then this switch is directly controlled by the ADC sequencer. Default Value: 0
16	SW_HCCV	Set corresponding switch Default Value: 0
14 : 12	SW_HCBG	Select waveform for corresponding switch, using csd_shield as base Default Value: 0
10 : 8	SW_HCBV	Select waveform for HCBV switch. The waveform for this switch follows the csd_shield signal, i.e. phi1 and phi2 are delayed with SHIELD_DELAY w.r.t. the csd_sense phases. Only this switch and HCBG use csd_shield as base all other switches use csd_sense as base. 0: static open 1: static closed 2: phi1_delay 3: phi2_delay 4: phi1_delay & HSCMP 5: phi2_delay & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0

5.1.25 CSD_SW_SHIELD_SEL (continued)

6 : 4	SW_HCAG	Select waveform for corresponding switch Default Value: 0
2 : 0	SW_HCAV	Select waveform for HCAV switch using csd_sense as base 0: static open 1: static closed 2: phi1 3: phi2 4: phi1 & HSCMP 5: phi2 & HSCMP 6: HSCMP (ignores phi1/2) 7: Reserved Default Value: 0

5.1.26 CSD_SW_HS_P_SEL1

HSCMP Pos input switch Waveform selection 1

Address: 0x402A028C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							SW_HMRE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	SW_HMRE	Set HMRE switch 0: static open 1: static closed Default Value: 0

5.1.27 CSD_SW_AMUXBUF_SEL

Amuxbuffer switches Waveform selection

Address: 0x402A0290

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			
HW Access	None			R	None			
Name	None [7:5]			SW_IRBY	None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [15:13]			SW_ICA	None [11:9]			SW_IRLB

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [23:21]			SW_IRLI	None	SW_ICB [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_IRL	None [27:25]			SW_IRH

Bits	Name	Description
28	SW_IRL	Set corresponding switch Default Value: 0
24	SW_IRH	Set corresponding switch Default Value: 0
20	SW_IRLI	Set corresponding switch Default Value: 0
18 : 16	SW_ICB	Select waveform for corresponding switch Default Value: 0
12	SW_ICA	Set corresponding switch Default Value: 0
8	SW_IRLB	Set corresponding switch Default Value: 0
4	SW_IRBY	Set corresponding switch Default Value: 0

5.1.28 CSD_SW_BYP_SEL

AMUXBUS bypass switches Waveform selection

Address: 0x402A0294

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None			
HW Access	None			R	None			
Name	None [15:13]			SW_BYA	None [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_CBCC	None [19:17]			SW_BYB

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20	SW_CBCC	Set corresponding switch If the ADC is enabled then this switch is directly controlled by the ADC sequencer. Default Value: 0
16	SW_BYB	Set corresponding switch Default Value: 0
12	SW_BYA	Set corresponding switch Default Value: 0

5.1.29 CSD_SW_CMP_P_SEL

CSDCMP Pos Switch Waveform selection

Address: 0x402A02A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_SFPT [6:4]			None	SW_SFPM [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [15:13]			SW_SFMA	None	SW_SFPS [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [23:21]			SW_SFCA	None [19:17]			SW_SFMB

Bits	31	30	29	28	27	26	25	24
SW Access	None							RW
HW Access	None							R
Name	None [31:25]							SW_SFCB

Bits	Name	Description
24	SW_SFCB	Set corresponding switch Default Value: 0
20	SW_SFCA	Set corresponding switch Default Value: 0
16	SW_SFMB	Set corresponding switch Default Value: 0
12	SW_SFMA	Set corresponding switch Default Value: 0
10 : 8	SW_SFPS	Select waveform for corresponding switch Default Value: 0
6 : 4	SW_SFPT	Select waveform for corresponding switch Default Value: 0
2 : 0	SW_SFPM	Select waveform for corresponding switch Default Value: 0

5.1.30 CSD_SW_CMP_N_SEL

CSDCMP Neg Switch Waveform selection

Address: 0x402A02A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_SCRL [30:28]			None	SW_SCRH [26:24]		

Bits	Name	Description
30 : 28	SW_SCRL	Select waveform for corresponding switch Default Value: 0
26 : 24	SW_SCRH	Select waveform for corresponding switch Default Value: 0

5.1.31 CSD_SW_REFGEN_SEL

Reference Generator Switch Waveform selection

Address: 0x402A02A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [7:5]			SW_IBCB	None [3:1]			SW_IAIB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							SW_SGMB

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_SGR	None [27:25]			SW_SGRE

Bits	Name	Description
28	SW_SGR	Set corresponding switch Default Value: 0
24	SW_SGRE	Set corresponding switch Default Value: 0
16	SW_SGMB	Set corresponding switch Default Value: 0
4	SW_IBCB	Set corresponding switch Default Value: 0
0	SW_IAIB	Set corresponding switch Default Value: 0

5.1.32 CSD_SW_FW_MOD_SEL

Full Wave Cmod Switch Waveform selection

Address: 0x402A02B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							SW_F1PM

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:11]					SW_F1MA [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [23:21]			SW_C1CC	None	SW_F1CA [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_C1F1	None [27:25]			SW_C1CD

Bits	Name	Description
28	SW_C1F1	Set corresponding switch Default Value: 0
24	SW_C1CD	Set corresponding switch Default Value: 0
20	SW_C1CC	Set corresponding switch Default Value: 0
18 : 16	SW_F1CA	Select waveform for corresponding switch Default Value: 0
10 : 8	SW_F1MA	Select waveform for corresponding switch Default Value: 0
0	SW_F1PM	Set corresponding switch Default Value: 0

5.1.33 CSD_SW_FW_TANK_SEL

Full Wave Csh_tank Switch Waveform selection

Address: 0x402A02B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None			
HW Access	None			R	None			
Name	None [7:5]			SW_F2PT	None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	SW_F2CA [14:12]			None	SW_F2MA [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	None	RW		
HW Access	None			R	None	R		
Name	None [23:21]			SW_C2CC	None	SW_F2CB [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None			RW	None			RW
HW Access	None			R	None			R
Name	None [31:29]			SW_C2F2	None [27:25]			SW_C2CD

Bits	Name	Description
28	SW_C2F2	Set corresponding switch Default Value: 0
24	SW_C2CD	Set corresponding switch Default Value: 0
20	SW_C2CC	Set corresponding switch Default Value: 0
18 : 16	SW_F2CB	Select waveform for corresponding switch Default Value: 0
14 : 12	SW_F2CA	Select waveform for corresponding switch Default Value: 0
10 : 8	SW_F2MA	Select waveform for corresponding switch Default Value: 0
4	SW_F2PT	Set corresponding switch Default Value: 0

5.1.34 CSD_SW_DSI_SEL

DSI output switch control Waveform selection

Address: 0x402A02C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	DSI_CMOD [6:4]			None	DSI_CSH_TANK [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 4	DSI_CMOD	Select waveform for dsi_cmod signal (called dsi_cap_hi_en in CDSv1). For CSX when DUAL_CAP_EN is set this signal will have the special functionality to go low one clk_hf cycle ahead of the end of the corresponding csd_sense phase (just like for CSDv1), in all other use-cases the functionality is the same as for other switch controls. Default Value: 0
2 : 0	DSI_CSH_TANK	Select waveform for dsi_csh_tank signal (called dsi_cap_lo_en in CDSv1). For CSX when DUAL_CAP_EN is set this signal will have the special functionality to go low one clk_hf cycle ahead of the end of the corresponding csd_sense phase (just like for CSDv1), in all other use-cases the functionality is the same as for other switch controls. Default Value: 0

5.1.35 CSD_SEQ_TIME

Sequencer Timing

Address: 0x402A0300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	AZ_TIME [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	AZ_TIME	Define Auto-Zero time in csd_sense cycles -1. Default Value: 0

5.1.36 CSD_SEQ_INIT_CNT

Sequencer Initial conversion and sample counts

Address: 0x402A0310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CONV_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CONV_CNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CONV_CNT	Number of conversion per sample, if set to 0 the Sample_init state will be skipped. Default Value: 0

5.1.37 CSD_SEQ_NORM_CNT

Sequencer Normal conversion and sample counts

Address: 0x402A0314

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CONV_CNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CONV_CNT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CONV_CNT	Number of conversion per sample, if set to 0 the Sample_norm state will be skipped. Sample window size = SEQ_NORM_CNT.CONV_CNT * (SENSE_PERIOD.SENSE_DIV+1). Note for CSDv1 Sample window size = PERIOD Default Value: 0

5.1.38 CSD_ADC_CTL

ADC Control

Address: 0x402A0320

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADC_TIME [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						ADC_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17 : 16	ADC_MODE	Enable ADC measurement. When enabled the ADC sequencer will be started when the main sequencer goes to the SAMPLE_NORM state Default Value: 0 **0x0: OFF:** No ADC measurement **0x1: VREF_CNT:** Count time A to bring Cref1 + Cref2 up from Vssa to Vrefhi with IDACB **0x2: VREF_BY2_CNT:** Count time B to bring Cref1 + Cref2 back up to Vrefhi with IDACB (after bringing them down for time A/2 cycles with IDACB sinking) **0x3: VIN_CNT:** Determine HSCMP polarity and count time C to source/sink Cref1 + Cref2 from Vin to Vrefhi.
7 : 0	ADC_TIME	ADC timing -1 in csd_sense clock cycles (actual time is ADC_TIME+1 cycles), either used to discharge Cref1&2, or as the aperture to capture the input voltage on Cref1&2 Default Value: 0

5.1.39 CSD_SEQ_START

Sequencer start

Address: 0x402A0340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW1C	None	RW	RW1S
HW Access	None			R	A	None	R	RW1C
Name	None [7:5]			DSI_START_EN	ABORT	None	SEQ_MODE	START

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						AZ1_SKIP	AZ0_SKIP

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	AZ1_SKIP	When set the AutoZero_1 state will be skipped Default Value: 0
8	AZ0_SKIP	When set the AutoZero_0 state will be skipped Default Value: 0
4	DSI_START_EN	When this bit is set a positive edge on dsi_start will start the CSD sequencer and if enabled also the ADC sequencer. Default Value: 0
3	ABORT	When a 1 is written the CSD and ADC sequencers will be aborted (if they are running) and the START bit will be cleared. This bit always read as 0. Default Value: 0
1	SEQ_MODE	0 = regular CSD scan + optional ADC 1 = coarse initialization, the Sequencer will go to the INIT_COARSE state. Default Value: 0

5.1.39 CSD_SEQ_START (continued)

0	START	Start the CSD sequencer. The sequencer will clear this bit when it is done. Depending on the mode the sequencer is done when a sample has been accumulated, when the high speed comparator trips or if the sequencer is aborted. When the ADC is enabled the ADC sequencer will start when the CSD sequencer reaches the Sample_norm state (only with the regular CSD scan mode). Default Value: 0

6 CTBM Registers

This section discusses the CTBM registers. It lists all the registers in mapping tables, in address order.

6.1 Register Details

Register Name	Address
CTBM0_CTB_CTRL	0x40300000
CTBM0_OA_RES0_CTRL	0x40300004
CTBM0_OA_RES1_CTRL	0x40300008
CTBM0_COMP_STAT	0x4030000C
CTBM0_INTR	0x40300020
CTBM0_INTR_SET	0x40300024
CTBM0_INTR_MASK	0x40300028
CTBM0_INTR_MASKED	0x4030002C
CTBM0_DFT_CTRL	0x40300030
CTBM0_OA0_SW	0x40300080
CTBM0_OA0_SW_CLEAR	0x40300084
CTBM0_OA1_SW	0x40300088
CTBM0_OA1_SW_CLEAR	0x4030008C
CTBM0_CTB_SW_HW_CTRL	0x403000C0
CTBM0_CTB_SW_STATUS	0x403000C4
CTBM0_OA0_OFFSET_TRIM	0x40300F00
CTBM0_OA0_SLOPE_OFFSET_TRIM	0x40300F04
CTBM0_OA0_COMP_TRIM	0x40300F08
CTBM0_OA1_OFFSET_TRIM	0x40300F0C
CTBM0_OA1_SLOPE_OFFSET_TRIM	0x40300F10
CTBM0_OA1_COMP_TRIM	0x40300F14

6.1.1 CTBM0_CTB_CTRL

global CTB and power control

Address: 0x40300000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	ENABLED	DEEPSLEEP_ON	None [29:24]					

Bits	Name	Description
31	ENABLED	- 0: CTB IP disabled (put analog in power down, open all switches) - 1: CTB IP enabled Default Value: 0
30	DEEPSLEEP_ON	- 0: CTB IP disabled off during DeepSleep power mode - 1: CTB IP remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0

6.1.2 CTBM0_OA_RES0_CTRL

Opamp0 and resistor0 control

Address: 0x40300004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA0_DSI_LEVEL	OA0_BYPASS_DSI_SYNC	OA0_HYST_EN	OA0_COMP_EN	None	OA0_DRIVE_STR_SEL	OA0_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA0_PUMP_EN	None	OA0_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	OA0_PUMP_EN	Opamp0 pump enable Default Value: 0
9 : 8	OA0_COMPINT	Opamp0 comparator edge detect for interrupt and pulse mode of DSI (trigger) Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

6.1.2 CTBM0_OA_RES0_CTRL (continued)

7	OA0_DSI_LEVEL	Opamp0 comparator DSI (trigger) out level : 0=pulse, each time an edge is detected (see OA0_COMPINT) a pulse is sent out on DSI 1=level, DSI output is a synchronized version of the comparator output Default Value: 0
6	OA0_BYPASS_DSI_SYNC	Opamp0 bypass comparator output synchronization for DSI (trigger) output: 0=synchronize (level or pulse), 1=bypass (output async) Default Value: 0
5	OA0_HYST_EN	Opamp0 hysteresis enable (10mV) Default Value: 0
4	OA0_COMP_EN	Opamp0 comparator enable Default Value: 0
2	OA0_DRIVE_STR_SEL	Opamp0 output strenght select 0=1x, 1=10x Default Value: 0
1 : 0	OA0_PWR_MODE	Opamp0 power level Default Value: 0 **0x0: OFF:** Off **0x1: LOW:** Low compensation setting (smallest cap, highest GBW). For gain=10: PM=60deg @ Cload=50pF for the output to pin driver and 10pF for the internal only driver **0x2: MEDIUM:** Medium compensation setting. For gain=4: PM=60deg @ Cload=50pF for the output to pin driver and 10pF for the internal only driver. **0x3: HIGH:** Highest compensation (largest cap, lowest GBW). For gain=1: PM=60deg @ Cload=50pF for the output to pin driver and 10pF for the internal only driver

6.1.3 CTBM0_OA_RES1_CTRL

Opamp1 and resistor1 control

Address: 0x40300008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA1_DSI_LEVEL	OA1_BYPASS_DSI_SYNC	OA1_HYST_EN	OA1_COMP_EN	None	OA1_DRIVE_STR_SEL	OA1_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA1_PUMP_EN	None	OA1_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	OA1_PUMP_EN	Opamp1 pump enable Default Value: 0
9 : 8	OA1_COMPINT	Opamp1 comparator edge detect for interrupt and pulse mode of DSI (trigger) Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

6.1.3 CTBM0_OA_RES1_CTRL (continued)

7	OA1_DSI_LEVEL	Opamp1 comparator DSI (trigger) out level : 0=pulse, each time an edge is detected (see OA1_COMPINT) a pulse is sent out on DSI 1=level, DSI output is a synchronized version of the comparator output Default Value: 0
6	OA1_BYPASS_DSI_SYNC	Opamp1 bypass comparator output synchronization for DSI output: 0=synchronize, 1=bypass Default Value: 0
5	OA1_HYST_EN	Opamp1 hysteresis enable (10mV) Default Value: 0
4	OA1_COMP_EN	Opamp1 comparator enable Default Value: 0
2	OA1_DRIVE_STR_SEL	Opamp1 output strenght select 0=1x, 1=10x Default Value: 0
1 : 0	OA1_PWR_MODE	Opamp1 power level: see description of OA0_PWR_MODE Default Value: 0

6.1.4 CTBM0_COMP_STAT

Comparator status

Address: 0x4030000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							OA0_COMP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							W
Name	None [23:17]							OA1_COMP

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	OA1_COMP	Opamp1 current comparator status Default Value: 0
0	OA0_COMP	Opamp0 current comparator status Default Value: 0

6.1.5 CTBM0_INTR

Interrupt request register

Address: 0x40300020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						COMP1	COMP0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1	Comparator 1 Interrupt: hardware sets this interrupt when comparator 1 triggers. Write with '1' to clear bit. Default Value: 0
0	COMP0	Comparator 0 Interrupt: hardware sets this interrupt when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

6.1.6 CTBM0_INTR_SET

Interrupt request set register

Address: 0x40300024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						COMP1_SET	COMP0_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	COMP0_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

6.1.7 CTBM0_INTR_MASK

Interrupt request mask

Address: 0x40300028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						COMP1_MASK	COMP0_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	COMP0_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

6.1.8 CTBM0_INTR_MASKED

Interrupt request masked

Address: 0x4030002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						COMP1_MASKED	COMP0_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	COMP0_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

6.1.9 CTBM0_DFT_CTRL

Was 'Analog DfT controls', now used as Risk Mitigation bits (RMP)

Address: 0x40300030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					DFT_MODE [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DFT_EN	None [30:24]						

Bits	Name	Description
31	DFT_EN	this bit is combined with the 3 bits 2:0, to form RMP[3:0] Default Value: 0
2 : 0	DFT_MODE	this bit is combined with bit 31, to form RMP[3:0], it must always be written with '3' for correct operation. Default Value: 0

6.1.10 CTBM0_OA0_SW

Opamp0 switch control

Address: 0x40300080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	None	RW1S
HW Access	None				RW1C	RW1C	None	RW1C
Name	None [7:4]				OA0P_A30	OA0P_A20	None	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1S	None					RW1S
HW Access	None	RW1C	None					RW1C
Name	None	OA0M_A81	None [13:9]					OA0M_A11

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1S	None		RW1S	None	
HW Access	None		RW1C	None		RW1C	None	
Name	None [23:22]		OA0O_D81	None [20:19]		OA0O_D51	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA0O_D81	Opamp0 output switch to short 1x with 10x drive Default Value: 0
18	OA0O_D51	Opamp0 output sarbus0 (ctbbus2 in CTB) Default Value: 0
14	OA0M_A81	Opamp0 negative terminal Opamp0 output Default Value: 0
8	OA0M_A11	Opamp0 negative terminal P1 Default Value: 0
3	OA0P_A30	Opamp0 positive terminal ctbbus0 Default Value: 0
2	OA0P_A20	Opamp0 positive terminal P0 Default Value: 0
0	OA0P_A00	Opamp0 positive terminal amuxbusa Default Value: 0

6.1.11 CTBM0_OA0_SW_CLEAR

Opamp0 switch control clear

Address: 0x40300084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	None	RW1C
HW Access	None				A	A	None	A
Name	None [7:4]				OA0P_A30	OA0P_A20	None	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1C	None					RW1C
HW Access	None	A	None					A
Name	None	OA0M_A81	None [13:9]					OA0M_A11

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1C	None		RW1C	None	
HW Access	None		A	None		A	None	
Name	None [23:22]		OA0O_D81	None [20:19]		OA0O_D51	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA0O_D81	see corresponding bit in OA0_SW Default Value: 0
18	OA0O_D51	see corresponding bit in OA0_SW Default Value: 0
14	OA0M_A81	see corresponding bit in OA0_SW Default Value: 0
8	OA0M_A11	see corresponding bit in OA0_SW Default Value: 0
3	OA0P_A30	see corresponding bit in OA0_SW Default Value: 0
2	OA0P_A20	see corresponding bit in OA0_SW Default Value: 0
0	OA0P_A00	see corresponding bit in OA0_SW Default Value: 0

6.1.12 CTBM0_OA1_SW

Opamp1 switch control

Address: 0x40300088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None		RW1S	RW1S
HW Access	None			RW1C	None		RW1C	RW1C
Name	None [7:5]			OA1P_A43	None [3:2]		OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1S	None					RW1S
HW Access	None	RW1C	None					RW1C
Name	None	OA1M_A82	None [13:9]					OA1M_A22

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1S	None	RW1S	RW1S	None	
HW Access	None		RW1C	None	RW1C	RW1C	None	
Name	None [23:22]		OA1O_D82	None	OA1O_D62	OA1O_D52	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA1O_D82	Opamp1 output switch to short 1x with 10x drive Default Value: 0
19	OA1O_D62	Opamp1 output sarbus1 (ctbbus3 in CTB) Default Value: 0
18	OA1O_D52	Opamp1 output sarbus0 (ctbbus2 in CTB) Default Value: 0
14	OA1M_A82	Opamp1 negative terminal Opamp1 output Default Value: 0
8	OA1M_A22	Opamp1 negative terminal P4 Default Value: 0
4	OA1P_A43	Opamp1 positive terminal ctbbus1 Default Value: 0
1	OA1P_A13	Opamp1 positive terminal P5 Default Value: 0
0	OA1P_A03	Opamp1 positive terminal amuxbusb Default Value: 0

6.1.13 CTBM0_OA1_SW_CLEAR

Opamp1 switch control clear

Address: 0x4030008C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None		RW1C	RW1C
HW Access	None			A	None		A	A
Name	None [7:5]			OA1P_A43	None [3:2]		OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1C	None					RW1C
HW Access	None	A	None					A
Name	None	OA1M_A82	None [13:9]					OA1M_A22

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1C	None	RW1C	RW1C	None	
HW Access	None		A	None	A	A	None	
Name	None [23:22]		OA1O_D82	None	OA1O_D62	OA1O_D52	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA1O_D82	see corresponding bit in OA1_SW Default Value: 0
19	OA1O_D62	see corresponding bit in OA1_SW Default Value: 0
18	OA1O_D52	see corresponding bit in OA1_SW Default Value: 0
14	OA1M_A82	see corresponding bit in OA1_SW Default Value: 0
8	OA1M_A22	see corresponding bit in OA1_SW Default Value: 0
4	OA1P_A43	see corresponding bit in OA1_SW Default Value: 0
1	OA1P_A13	see corresponding bit in OA1_SW Default Value: 0
0	OA1P_A03	see corresponding bit in OA1_SW Default Value: 0

6.1.14 CTBM0_CTB_SW_HW_CTRL

CTB bus switch control

Address: 0x403000C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	None	
HW Access	None				R	R	None	
Name	None [7:4]				P3_HW_CTRL	P2_HW_CTRL	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	P3_HW_CTRL	for P33, D52, D62 (dsi_out[3]) Default Value: 0
2	P2_HW_CTRL	for P22, D51 (dsi_out[2]) Default Value: 0

6.1.15 CTBM0_CTB_SW_STATUS

CTB bus switch control status

Address: 0x403000C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None	R	R	R	None			
HW Access	None	W	W	W	None			
Name	None	OA1O_D62 _STAT	OA1O_D52 _STAT	OA0O_D51 _STAT	None [27:24]			

Bits	Name	Description
30	OA1O_D62_STAT	see OA1O_D62 bit in OA1_SW Default Value: 0
29	OA1O_D52_STAT	see OA1O_D52 bit in OA1_SW Default Value: 0
28	OA0O_D51_STAT	see OA0O_D51 bit in OA0_SW Default Value: 0

6.1.16 CTBM0_OA0_OFFSET_TRIM

Opamp0 trim control

Address: 0x40300F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_OFFSET_TRIM	Opamp0 offset trim Default Value: 0

6.1.17 CTBM0_OA0_SLOPE_OFFSET_TRIM

Opamp0 trim control

Address: 0x40300F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_SLOPE_OFFSET_TRIM	Opamp0 slope offset drift trim Default Value: 0

6.1.18 CTBM0_OA0_COMP_TRIM

Opamp0 trim control

Address: 0x40300F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA0_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA0_COMP_TRIM	Opamp 0 Compensation Capacitor Trim Default Value: 0

6.1.19 CTBM0_OA1_OFFSET_TRIM

Opamp1 trim control

Address: 0x40300F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_OFFSET_TRIM	Opamp1 offset trim Default Value: 0

6.1.20 CTBM0_OA1_SLOPE_OFFSET_TRIM

Opamp1 trim control

Address: 0x40300F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_SLOPE_OFFSET_TRIM	Opamp1 slope offset drift trim Default Value: 0

6.1.21 CTBM0_OA1_COMP_TRIM

Opamp1 trim control

Address: 0x40300F14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA1_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA1_COMP_TRIM	Opamp 1 Compensation Capacitor Trim Default Value: 0

7 DMAC Registers

This section discusses the DMAC registers. It lists all the registers in mapping tables, in address order.

7.1 Register Details

Register Name	Address
DMAC_CTL	0x40101000
DMAC_STATUS	0x40101010
DMAC_STATUS_SRC_ADDR	0x40101014
DMAC_STATUS_DST_ADDR	0x40101018
DMAC_STATUS_CH_ACT	0x4010101C
DMAC_CH_CTL0	0x40101080
DMAC_CH_CTL1	0x40101084
DMAC_CH_CTL2	0x40101088
DMAC_CH_CTL3	0x4010108C
DMAC_CH_CTL4	0x40101090
DMAC_CH_CTL5	0x40101094
DMAC_CH_CTL6	0x40101098
DMAC_CH_CTL7	0x4010109C
DMAC_CH_CTL8	0x401010A0
DMAC_CH_CTL9	0x401010A4
DMAC_CH_CTL10	0x401010A8
DMAC_CH_CTL11	0x401010AC
DMAC_CH_CTL12	0x401010B0
DMAC_CH_CTL13	0x401010B4
DMAC_CH_CTL14	0x401010B8
DMAC_CH_CTL15	0x401010BC
DMAC_INTR	0x401017F0
DMAC_INTR_SET	0x401017F4
DMAC_INTR_MASK	0x401017F8
DMAC_INTR_MASKED	0x401017FC

7.1.1 DMAC_CTL

Control register

Address: 0x40101000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLED	None [30:24]						

Bits	Name	Description
31	ENABLED	0': IP is disabled. Non-retainable MMIO registers and logic functionality are reset (retainable MMIO registers are NOT reset): - INTR register is set to "0". - DW/DMA functionality is aborted. - DW/DMA controller input/pending triggers are de-activated. - DW/DMA controller output triggers are de-activated. Disabling the IP has the same effect as an active "rst_sys_act_n" reset in DeepSleep power mode. To prevent a loss of active (pending) DW/DMA triggers when disabling the IP or when transitioning from Active to DeepSleep power mode, the STATUS.ACTIVE and STATUS_CH_ACT.CH fields can be used. Note that most MMIO registers are retainable, and a transition from DeepSleep to Active/Sleep power modes makes the DW/DMA controller operational, and ready to react to DW/DMA input triggers that are activated after the transition. Triggers are Active/Sleep functionality. '1': IP is enabled. Default Value: 0

7.1.2 DMAC_STATUS

Status register

Address: 0x40101010

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				CH_ADDR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R		None	R		
HW Access	W	W	W		None	W		
Name	ACTIVE	PING_PONG	PRIO [29:28]		None	STATE [26:24]		

Bits	Name	Description
31	ACTIVE	Specifies if there is a currently active (pending) channel in the data transfer engine: '0': no currently active channel. '1': currently active channel. Default Value: 0
30	PING_PONG	Specifies the descriptor of the channel is currently in use. "0" - PING descriptor "1" - PONG descriptor Default Value: Undefined
29 : 28	PRIO	Specifies the priority of the currently active channel. Default Value: Undefined

7.1.2 DMAC_STATUS (continued)

26 : 24	STATE	State of the data transfer engine. "0": DEFAULT state. "1": Loading descriptor (SRC, DST, CONTROL and STATUS words). "2": Loading data element from source location. "3": Storing data element to destination location. "4": Storing descriptor (STATUS word). "5": Wait for trigger de-activation. "6": Storing descriptor with error response (STATUS word). Default Value: 0
19 : 16	CH_ADDR	Specifies the channel number of the currently active channel. E.g. if we have 32 channels, the channel number address with CH_ADDR_WIDTH is LOG2 (32) = 5, and this field is a 5-bit field. If channel 7 is active, STATUS.ACTIVE is '1' and STATUS.CH_ADDR is "7". Default Value: Undefined
15 : 0	DATA_NR	Specifies the index of the currently active data transfer. This value increases from "0" to CONTROL.DATA_NR. Default Value: Undefined

7.1.3 DMAC_STATUS_SRC_ADDR

Source address status register

Address: 0x40101014

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address or current address of source location of currently active channel. The specific address information is cycle dependent. This field is provided for debug purposes. Functionally, no assumption should be made on whether the base or current address is provided. The specifics of the currently active channel are available through STATUS. Note while reading the STATUS, STATUS_SRC_ADDR and STATUS_DST_ADDR registers, the transfer engine may have moved from one active channel to another. Default Value: Undefined

7.1.4 DMAC_STATUS_DST_ADDR

Destination address register

Address: 0x40101018

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address or current address of destination location of currently active channel. The specific address information is cycle dependent. This field is provided for debug purposes. Functionally, no assumption should be made on whether the base or current address is provided. The specifics of the currently active channel are available through STATUS. Note while reading the STATUS, STATUS_SRC_ADDR and STATUS_DST_ADDR registers, the transfer engine may have moved from one active channel to another. Default Value: Undefined

7.1.5 DMAC_STATUS_CH_ACT

Channel activation status register

Address: 0x4010101C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CH	Channel activation status. Bit i is associated to channel i, with i = 0, ..., CH_NR-1. Software reads this field to get information on all actively pending channels (either in pending or in the data transfer engine). Default Value: 0

7.1.6 DMAC_CH_CTL0

Channel control register

Address: 0x40101080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.6 DMAC_CH_CTL0 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.7 DMAC_CH_CTL1

Channel control register

Address: 0x40101084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.7 DMAC_CH_CTL1 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.8 DMAC_CH_CTL2

Channel control register

Address: 0x40101088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.8 DMAC_CH_CTL2 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.9 DMAC_CH_CTL3

Channel control register

Address: 0x4010108C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.9 DMAC_CH_CTL3 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.10 DMAC_CH_CTL4

Channel control register

Address: 0x40101090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.10 DMAC_CH_CTL4 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.11 DMAC_CH_CTL5

Channel control register

Address: 0x40101094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.11 DMAC_CH_CTL5 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.12 DMAC_CH_CTL6

Channel control register

Address: 0x40101098

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.12 DMAC_CH_CTL6 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.13 DMAC_CH_CTL7

Channel control register

Address: 0x4010109C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.13 DMAC_CH_CTL7 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.14 DMAC_CH_CTL8

Channel control register

Address: 0x401010A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.14 DMAC_CH_CTL8 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.15 DMAC_CH_CTL9

Channel control register

Address: 0x401010A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.15 DMAC_CH_CTL9 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.16 DMAC_CH_CTL10

Channel control register

Address: 0x401010A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.16 DMAC_CH_CTL10 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.17 DMAC_CH_CTL11

Channel control register

Address: 0x401010AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.17 DMAC_CH_CTL11 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.18 DMAC_CH_CTL12

Channel control register

Address: 0x401010B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.18 DMAC_CH_CTL12 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.19 DMAC_CH_CTL13

Channel control register

Address: 0x401010B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.19 DMAC_CH_CTL13 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.20 DMAC_CH_CTL14

Channel control register

Address: 0x401010B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.20 DMAC_CH_CTL14 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.21 DMAC_CH_CTL15

Channel control register

Address: 0x401010BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW		None			
HW Access	RW1C	RW	R		None			
Name	ENABLED	PING_PONG	PRIO [29:28]		None [27:24]			

Bits	Name	Description
31	ENABLED	'0': channel disabled. The channel's trigger is ignored and the channel cannot be activated. If the activated channel is disabled, the data transfer(s) are aborted. '1': channel enabled. Software sets this field to '1' to enable a specific channel. Hardware sets this field to '0' on erroneous channel behavior (the specific error is specified by STATUS.RESP in the channel's descriptor structure). Default Value: 0
30	PING_PONG	Each channel has two descriptor structures for double buffering purposes. As the controller operates on one structure, the main CPU can operate on the other structure. The descriptor structures are identified as PING ('0') and PONG ('1'). This field identifies the descriptor structure that is currently in use by the controller. Software sets this field to the desired descriptor structure. Hardware inverts the field value on the completion of a descriptor structure when CONTROL.FLIPPING of the current descriptor structure is set to '1'. Default Value: 0

7.1.21 DMAC_CH_CTL15 (continued)

29 : 28	PRIO	Channel priority, with "0" representing the highest priority and "3" representing the lowest priority. Priority decoding uses the channel priority to determine the highest priority activated channel. If multiple activated channels have the same highest priority, the channel with the lowest index i, is considered the highest priority activated channel. Default Value: 0

7.1.22 DMAC_INTR

Interrupt register

Address: 0x401017F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	RW1S							
Name	CH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CH	Set to '1', when event is detected. Write INTR field with '1', to clear bit. Write INTR_SET field with '1', to set bit. Default Value: 0

7.1.23 DMAC_INTR_SET

Interrupt set register

Address: 0x401017F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	A							
Name	CH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CH	Write INTR_SET field with '1' to set corresponding INTR field (a write of '0' has no effect). Default Value: 0

7.1.24 DMAC_INTR_MASK

Interrupt mask register

Address: 0x401017F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CH	Mask for corresponding field in INTR register. Default Value: 0

7.1.25 DMAC_INTR_MASKED

Interrupt masked register

Address: 0x401017FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	CH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CH	Logical BITWISE AND of corresponding request and mask fields. Default Value: 0

8 DMAC_DESCR Registers

This section discusses the DMAC_DESCR registers. It lists all the registers in mapping tables, in address order.

8.1 Register Details

Register Name	Address
DMAC_DESCR0_PING_SRC	0x40101800
DMAC_DESCR0_PING_DST	0x40101804
DMAC_DESCR0_PING_CTL	0x40101808
DMAC_DESCR0_PING_STATUS	0x4010180C
DMAC_DESCR0_PONG_SRC	0x40101810
DMAC_DESCR0_PONG_DST	0x40101814
DMAC_DESCR0_PONG_CTL	0x40101818
DMAC_DESCR0_PONG_STATUS	0x4010181C
DMAC_DESCR1_PING_SRC	0x40101820
DMAC_DESCR1_PING_DST	0x40101824
DMAC_DESCR1_PING_CTL	0x40101828
DMAC_DESCR1_PING_STATUS	0x4010182C
DMAC_DESCR1_PONG_SRC	0x40101830
DMAC_DESCR1_PONG_DST	0x40101834
DMAC_DESCR1_PONG_CTL	0x40101838
DMAC_DESCR1_PONG_STATUS	0x4010183C
DMAC_DESCR2_PING_SRC	0x40101840
DMAC_DESCR2_PING_DST	0x40101844
DMAC_DESCR2_PING_CTL	0x40101848
DMAC_DESCR2_PING_STATUS	0x4010184C
DMAC_DESCR2_PONG_SRC	0x40101850
DMAC_DESCR2_PONG_DST	0x40101854
DMAC_DESCR2_PONG_CTL	0x40101858
DMAC_DESCR2_PONG_STATUS	0x4010185C
DMAC_DESCR3_PING_SRC	0x40101860
DMAC_DESCR3_PING_DST	0x40101864
DMAC_DESCR3_PING_CTL	0x40101868

Register Name	Address
DMAC_DESCR3_PING_STATUS	0x4010186C
DMAC_DESCR3_PONG_SRC	0x40101870
DMAC_DESCR3_PONG_DST	0x40101874
DMAC_DESCR3_PONG_CTL	0x40101878
DMAC_DESCR3_PONG_STATUS	0x4010187C
DMAC_DESCR4_PING_SRC	0x40101880
DMAC_DESCR4_PING_DST	0x40101884
DMAC_DESCR4_PING_CTL	0x40101888
DMAC_DESCR4_PING_STATUS	0x4010188C
DMAC_DESCR4_PONG_SRC	0x40101890
DMAC_DESCR4_PONG_DST	0x40101894
DMAC_DESCR4_PONG_CTL	0x40101898
DMAC_DESCR4_PONG_STATUS	0x4010189C
DMAC_DESCR5_PING_SRC	0x401018A0
DMAC_DESCR5_PING_DST	0x401018A4
DMAC_DESCR5_PING_CTL	0x401018A8
DMAC_DESCR5_PING_STATUS	0x401018AC
DMAC_DESCR5_PONG_SRC	0x401018B0
DMAC_DESCR5_PONG_DST	0x401018B4
DMAC_DESCR5_PONG_CTL	0x401018B8
DMAC_DESCR5_PONG_STATUS	0x401018BC
DMAC_DESCR6_PING_SRC	0x401018C0
DMAC_DESCR6_PING_DST	0x401018C4
DMAC_DESCR6_PING_CTL	0x401018C8
DMAC_DESCR6_PING_STATUS	0x401018CC
DMAC_DESCR6_PONG_SRC	0x401018D0
DMAC_DESCR6_PONG_DST	0x401018D4
DMAC_DESCR6_PONG_CTL	0x401018D8
DMAC_DESCR6_PONG_STATUS	0x401018DC
DMAC_DESCR7_PING_SRC	0x401018E0
DMAC_DESCR7_PING_DST	0x401018E4
DMAC_DESCR7_PING_CTL	0x401018E8
DMAC_DESCR7_PING_STATUS	0x401018EC
DMAC_DESCR7_PONG_SRC	0x401018F0
DMAC_DESCR7_PONG_DST	0x401018F4
DMAC_DESCR7_PONG_CTL	0x401018F8
DMAC_DESCR7_PONG_STATUS	0x401018FC
DMAC_DESCR8_PING_SRC	0x40101900
DMAC_DESCR8_PING_DST	0x40101904
DMAC_DESCR8_PING_CTL	0x40101908
DMAC_DESCR8_PING_STATUS	0x4010190C
DMAC_DESCR8_PONG_SRC	0x40101910

Register Name	Address
DMAC_DESCR8_PONG_DST	0x40101914
DMAC_DESCR8_PONG_CTL	0x40101918
DMAC_DESCR8_PONG_STATUS	0x4010191C
DMAC_DESCR9_PING_SRC	0x40101920
DMAC_DESCR9_PING_DST	0x40101924
DMAC_DESCR9_PING_CTL	0x40101928
DMAC_DESCR9_PING_STATUS	0x4010192C
DMAC_DESCR9_PONG_SRC	0x40101930
DMAC_DESCR9_PONG_DST	0x40101934
DMAC_DESCR9_PONG_CTL	0x40101938
DMAC_DESCR9_PONG_STATUS	0x4010193C
DMAC_DESCR10_PING_SRC	0x40101940
DMAC_DESCR10_PING_DST	0x40101944
DMAC_DESCR10_PING_CTL	0x40101948
DMAC_DESCR10_PING_STATUS	0x4010194C
DMAC_DESCR10_PONG_SRC	0x40101950
DMAC_DESCR10_PONG_DST	0x40101954
DMAC_DESCR10_PONG_CTL	0x40101958
DMAC_DESCR10_PONG_STATUS	0x4010195C
DMAC_DESCR11_PING_SRC	0x40101960
DMAC_DESCR11_PING_DST	0x40101964
DMAC_DESCR11_PING_CTL	0x40101968
DMAC_DESCR11_PING_STATUS	0x4010196C
DMAC_DESCR11_PONG_SRC	0x40101970
DMAC_DESCR11_PONG_DST	0x40101974
DMAC_DESCR11_PONG_CTL	0x40101978
DMAC_DESCR11_PONG_STATUS	0x4010197C
DMAC_DESCR12_PING_SRC	0x40101980
DMAC_DESCR12_PING_DST	0x40101984
DMAC_DESCR12_PING_CTL	0x40101988
DMAC_DESCR12_PING_STATUS	0x4010198C
DMAC_DESCR12_PONG_SRC	0x40101990
DMAC_DESCR12_PONG_DST	0x40101994
DMAC_DESCR12_PONG_CTL	0x40101998
DMAC_DESCR12_PONG_STATUS	0x4010199C
DMAC_DESCR13_PING_SRC	0x401019A0
DMAC_DESCR13_PING_DST	0x401019A4
DMAC_DESCR13_PING_CTL	0x401019A8
DMAC_DESCR13_PING_STATUS	0x401019AC
DMAC_DESCR13_PONG_SRC	0x401019B0
DMAC_DESCR13_PONG_DST	0x401019B4
DMAC_DESCR13_PONG_CTL	0x401019B8

Register Name	Address
DMAC_DESCR13_PONG_STATUS	0x401019BC
DMAC_DESCR14_PING_SRC	0x401019C0
DMAC_DESCR14_PING_DST	0x401019C4
DMAC_DESCR14_PING_CTL	0x401019C8
DMAC_DESCR14_PING_STATUS	0x401019CC
DMAC_DESCR14_PONG_SRC	0x401019D0
DMAC_DESCR14_PONG_DST	0x401019D4
DMAC_DESCR14_PONG_CTL	0x401019D8
DMAC_DESCR14_PONG_STATUS	0x401019DC
DMAC_DESCR15_PING_SRC	0x401019E0
DMAC_DESCR15_PING_DST	0x401019E4
DMAC_DESCR15_PING_CTL	0x401019E8
DMAC_DESCR15_PING_STATUS	0x401019EC
DMAC_DESCR15_PONG_SRC	0x401019F0
DMAC_DESCR15_PONG_DST	0x401019F4
DMAC_DESCR15_PONG_CTL	0x401019F8
DMAC_DESCR15_PONG_STATUS	0x401019FC

8.1.1 DMAC_DESCR0_PING_SRC

Ping source address

Address: 0x40101800

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.2 DMAC_DESCR0_PING_DST

Ping destination address

Address: 0x40101804

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.3 DMAC_DESCR0_PING_CTL

Ping control word

Address: 0x40101808

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.3 DMAC_DESCR0_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.3 DMAC_DESCR0_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.3 DMAC_DESCR0_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.4 DMAC_DESCR0_PING_STATUS

Ping status word

Address: 0x4010180C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.4 DMAC_DESCR0_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.5 DMAC_DESCR0_PONG_SRC

Pong source address

Address: 0x40101810

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.6 DMAC_DESCR0_PONG_DST

Pong destination address

Address: 0x40101814

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.7 DMAC_DESCR0_PONG_CTL

Pong control word

Address: 0x40101818

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.7 DMAC_DESCR0_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.8 DMAC_DESCR0_PONG_STATUS

Pong status word

Address: 0x4010181C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.9 DMAC_DESCR1_PING_SRC

Ping source address

Address: 0x40101820

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.10 DMAC_DESCR1_PING_DST

Ping destination address

Address: 0x40101824

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.11 DMAC_DESCR1_PING_CTL

Ping control word

Address: 0x40101828

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.11 DMAC_DESCR1_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.11 DMAC_DESCR1_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.11 DMAC_DESCR1_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.12 DMAC_DESCR1_PING_STATUS

Ping status word

Address: 0x4010182C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.12 DMAC_DESCR1_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.13 DMAC_DESCR1_PONG_SRC

Pong source address

Address: 0x40101830

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.14 DMAC_DESCR1_PONG_DST

Pong destination address

Address: 0x40101834

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.15 DMAC_DESCR1_PONG_CTL

Pong control word

Address: 0x40101838

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.15 DMAC_DESCR1_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.16 DMAC_DESCR1_PONG_STATUS

Pong status word

Address: 0x4010183C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.17 DMAC_DESCR2_PING_SRC

Ping source address

Address: 0x40101840

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.18 DMAC_DESCR2_PING_DST

Ping destination address

Address: 0x40101844

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.19 DMAC_DESCR2_PING_CTL

Ping control word

Address: 0x40101848

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.19 DMAC_DESCR2_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.19 DMAC_DESCR2_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.19 DMAC_DESCR2_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.20 DMAC_DESCR2_PING_STATUS

Ping status word

Address: 0x4010184C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.20 DMAC_DESCR2_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.21 DMAC_DESCR2_PONG_SRC

Pong source address

Address: 0x40101850

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.22 DMAC_DESCR2_PONG_DST

Pong destination address

Address: 0x40101854

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.23 DMAC_DESCR2_PONG_CTL

Pong control word

Address: 0x40101858

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.23 DMAC_DESCR2_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.24 DMAC_DESCR2_PONG_STATUS

Pong status word

Address: 0x4010185C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.25 DMAC_DESCR3_PING_SRC

Ping source address

Address: 0x40101860

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.26 DMAC_DESCR3_PING_DST

Ping destination address

Address: 0x40101864

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.27 DMAC_DESCR3_PING_CTL

Ping control word

Address: 0x40101868

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.27 DMAC_DESCR3_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.27 DMAC_DESCR3_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.27 DMAC_DESCR3_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.28 DMAC_DESCR3_PING_STATUS

Ping status word

Address: 0x4010186C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.28 DMAC_DESCR3_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.29 DMAC_DESCR3_PONG_SRC

Pong source address

Address: 0x40101870

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.30 DMAC_DESCR3_PONG_DST

Pong destination address

Address: 0x40101874

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.31 DMAC_DESCR3_PONG_CTL

Pong control word

Address: 0x40101878

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.31 DMAC_DESCR3_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.32 DMAC_DESCR3_PONG_STATUS

Pong status word

Address: 0x4010187C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.33 DMAC_DESCR4_PING_SRC

Ping source address

Address: 0x40101880

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.34 DMAC_DESCR4_PING_DST

Ping destination address

Address: 0x40101884

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.35 DMAC_DESCR4_PING_CTL

Ping control word

Address: 0x40101888

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.35 DMAC_DESCR4_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.35 DMAC_DESCR4_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.35 DMAC_DESCR4_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.36 DMAC_DESCR4_PING_STATUS

Ping status word

Address: 0x4010188C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.36 DMAC_DESCR4_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.37 DMAC_DESCR4_PONG_SRC

Pong source address

Address: 0x40101890

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.38 DMAC_DESCR4_PONG_DST

Pong destination address

Address: 0x40101894

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.39 DMAC_DESCR4_PONG_CTL

Pong control word

Address: 0x40101898

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.39 DMAC_DESCR4_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.40 DMAC_DESCR4_PONG_STATUS

Pong status word

Address: 0x4010189C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.41 DMAC_DESCR5_PING_SRC

Ping source address

Address: 0x401018A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.42 DMAC_DESCR5_PING_DST

Ping destination address

Address: 0x401018A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.43 DMAC_DESCR5_PING_CTL

Ping control word

Address: 0x401018A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.43 DMAC_DESCR5_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.43 DMAC_DESCR5_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.43 DMAC_DESCR5_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.44 DMAC_DESCR5_PING_STATUS

Ping status word

Address: 0x401018AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.44 DMAC_DESCR5_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.45 DMAC_DESCR5_PONG_SRC

Pong source address

Address: 0x401018B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.46 DMAC_DESCR5_PONG_DST

Pong destination address

Address: 0x401018B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.47 DMAC_DESCR5_PONG_CTL

Pong control word

Address: 0x401018B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.47 DMAC_DESCR5_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.48 DMAC_DESCR5_PONG_STATUS

Pong status word

Address: 0x401018BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.49 DMAC_DESCR6_PING_SRC

Ping source address

Address: 0x401018C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.50 DMAC_DESCR6_PING_DST

Ping destination address

Address: 0x401018C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.51 DMAC_DESCR6_PING_CTL

Ping control word

Address: 0x401018C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.51 DMAC_DESCR6_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.51 DMAC_DESCR6_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.51 DMAC_DESCR6_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.52 DMAC_DESCR6_PING_STATUS

Ping status word

Address: 0x401018CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.52 DMAC_DESCR6_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.53 DMAC_DESCR6_PONG_SRC

Pong source address

Address: 0x401018D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.54 DMAC_DESCR6_PONG_DST

Pong destination address

Address: 0x401018D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.55 DMAC_DESCR6_PONG_CTL

Pong control word

Address: 0x401018D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.55 DMAC_DESCR6_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.56 DMAC_DESCR6_PONG_STATUS

Pong status word

Address: 0x401018DC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.57 DMAC_DESCR7_PING_SRC

Ping source address

Address: 0x401018E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.58 DMAC_DESCR7_PING_DST

Ping destination address

Address: 0x401018E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.59 DMAC_DESCR7_PING_CTL

Ping control word

Address: 0x401018E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.59 DMAC_DESCR7_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.59 DMAC_DESCR7_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.59 DMAC_DESCR7_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.60 DMAC_DESCR7_PING_STATUS

Ping status word

Address: 0x401018EC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.60 DMAC_DESCR7_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.61 DMAC_DESCR7_PONG_SRC

Pong source address

Address: 0x401018F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.62 DMAC_DESCR7_PONG_DST

Pong destination address

Address: 0x401018F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.63 DMAC_DESCR7_PONG_CTL

Pong control word

Address: 0x401018F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.63 DMAC_DESCR7_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.64 DMAC_DESCR7_PONG_STATUS

Pong status word

Address: 0x401018FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.65 DMAC_DESCR8_PING_SRC

Ping source address

Address: 0x40101900

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.66 DMAC_DESCR8_PING_DST

Ping destination address

Address: 0x40101904

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.67 DMAC_DESCR8_PING_CTL

Ping control word

Address: 0x40101908

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.67 DMAC_DESCR8_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.67 DMAC_DESCR8_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.67 DMAC_DESCR8_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.68 DMAC_DESCR8_PING_STATUS

Ping status word

Address: 0x4010190C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.68 DMAC_DESCR8_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.69 DMAC_DESCR8_PONG_SRC

Pong source address

Address: 0x40101910

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.70 DMAC_DESCR8_PONG_DST

Pong destination address

Address: 0x40101914

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.71 DMAC_DESCR8_PONG_CTL

Pong control word

Address: 0x40101918

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.71 DMAC_DESCR8_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.72 DMAC_DESCR8_PONG_STATUS

Pong status word

Address: 0x4010191C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.73 DMAC_DESCR9_PING_SRC

Ping source address

Address: 0x40101920

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.74 DMAC_DESCR9_PING_DST

Ping destination address

Address: 0x40101924

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.75 DMAC_DESCR9_PING_CTL

Ping control word

Address: 0x40101928

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.75 DMAC_DESCR9_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.75 DMAC_DESCR9_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.75 DMAC_DESCR9_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.76 DMAC_DESCR9_PING_STATUS

Ping status word

Address: 0x4010192C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.76 DMAC_DESCR9_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.77 DMAC_DESCR9_PONG_SRC

Pong source address

Address: 0x40101930

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.78 DMAC_DESCR9_PONG_DST

Pong destination address

Address: 0x40101934

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.79 DMAC_DESCR9_PONG_CTL

Pong control word

Address: 0x40101938

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.79 DMAC_DESCR9_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.80 DMAC_DESCR9_PONG_STATUS

Pong status word

Address: 0x4010193C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.81 DMAC_DESCR10_PING_SRC

Ping source address

Address: 0x40101940

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.82 DMAC_DESCR10_PING_DST

Ping destination address

Address: 0x40101944

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.83 DMAC_DESCR10_PING_CTL

Ping control word

Address: 0x40101948

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.83 DMAC_DESCR10_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.83 DMAC_DESCR10_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.83 DMAC_DESCR10_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.84 DMAC_DESCR10_PING_STATUS

Ping status word

Address: 0x4010194C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.84 DMAC_DESCR10_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.85 DMAC_DESCR10_PONG_SRC

Pong source address

Address: 0x40101950

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.86 DMAC_DESCR10_PONG_DST

Pong destination address

Address: 0x40101954

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.87 DMAC_DESCR10_PONG_CTL

Pong control word

Address: 0x40101958

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.87 DMAC_DESCR10_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.88 DMAC_DESCR10_PONG_STATUS

Pong status word

Address: 0x4010195C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.89 DMAC_DESCR11_PING_SRC

Ping source address

Address: 0x40101960

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.90 DMAC_DESCR11_PING_DST

Ping destination address

Address: 0x40101964

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.91 DMAC_DESCR11_PING_CTL

Ping control word

Address: 0x40101968

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.91 DMAC_DESCR11_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.91 DMAC_DESCR11_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.91 DMAC_DESCR11_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.92 DMAC_DESCR11_PING_STATUS

Ping status word

Address: 0x4010196C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.92 DMAC_DESCR11_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.93 DMAC_DESCR11_PONG_SRC

Pong source address

Address: 0x40101970

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.94 DMAC_DESCR11_PONG_DST

Pong destination address

Address: 0x40101974

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.95 DMAC_DESCR11_PONG_CTL

Pong control word

Address: 0x40101978

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.95 DMAC_DESCR11_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.96 DMAC_DESCR11_PONG_STATUS

Pong status word

Address: 0x4010197C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.97 DMAC_DESCR12_PING_SRC

Ping source address

Address: 0x40101980

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.98 DMAC_DESCR12_PING_DST

Ping destination address

Address: 0x40101984

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.99 DMAC_DESCR12_PING_CTL

Ping control word

Address: 0x40101988

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.99 DMAC_DESCR12_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.99 DMAC_DESCR12_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.99 DMAC_DESCR12_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.100 DMAC_DESCR12_PING_STATUS

Ping status word

Address: 0x4010198C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.100 DMAC_DESCR12_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.101 DMAC_DESCR12_PONG_SRC

Pong source address

Address: 0x40101990

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.102 DMAC_DESCR12_PONG_DST

Pong destination address

Address: 0x40101994

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.103 DMAC_DESCR12_PONG_CTL

Pong control word

Address: 0x40101998

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.103 DMAC_DESCR12_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.104 DMAC_DESCR12_PONG_STATUS

Pong status word

Address: 0x4010199C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.105 DMAC_DESCR13_PING_SRC

Ping source address

Address: 0x401019A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.106 DMAC_DESCR13_PING_DST

Ping destination address

Address: 0x401019A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.107 DMAC_DESCR13_PING_CTL

Ping control word

Address: 0x401019A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.107 DMAC_DESCR13_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.107 DMAC_DESCR13_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.107 DMAC_DESCR13_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.108 DMAC_DESCR13_PING_STATUS

Ping status word

Address: 0x401019AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.108 DMAC_DESCR13_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.109 DMAC_DESCR13_PONG_SRC

Pong source address

Address: 0x401019B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.110 DMAC_DESCR13_PONG_DST

Pong destination address

Address: 0x401019B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.111 DMAC_DESCR13_PONG_CTL

Pong control word

Address: 0x401019B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.111 DMAC_DESCR13_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.112 DMAC_DESCR13_PONG_STATUS

Pong status word

Address: 0x401019BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.113 DMAC_DESCR14_PING_SRC

Ping source address

Address: 0x401019C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.114 DMAC_DESCR14_PING_DST

Ping destination address

Address: 0x401019C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.115 DMAC_DESCR14_PING_CTL

Ping control word

Address: 0x401019C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.115 DMAC_DESCR14_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.115 DMAC_DESCR14_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.115 DMAC_DESCR14_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.116 DMAC_DESCR14_PING_STATUS

Ping status word

Address: 0x401019CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.116 DMAC_DESCR14_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.117 DMAC_DESCR14_PONG_SRC

Pong source address

Address: 0x401019D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.118 DMAC_DESCR14_PONG_DST

Pong destination address

Address: 0x401019D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.119 DMAC_DESCR14_PONG_CTL

Pong control word

Address: 0x401019D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.119 DMAC_DESCR14_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.120 DMAC_DESCR14_PONG_STATUS

Pong status word

Address: 0x401019DC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

8.1.121 DMAC_DESCR15_PING_SRC

Ping source address

Address: 0x401019E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of source location. The effective source location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.122 DMAC_DESCR15_PING_DST

Ping destination address

Address: 0x401019E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	Base address of destination location. The effective destination location is calculated by adding on offset (derived from PING.STATUS.CURR_DATA_NR) to this base address. Default Value: Undefined

8.1.123 DMAC_DESCR15_PING_CTL

Ping control word

Address: 0x401019E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description

8.1.123 DMAC_DESCR15_PING_CTL (continued)

31 : 30	OPCODE	Specifies the specific data transfer (only when the VALID bit of the descriptor's STATUS word is '1'): "0": A single trigger initiates a single data element transfer (DW mode). This opcode specifies a transfer of a single data element. The current descriptor is completed when the amount of transferred single data elements equals the programmed buffer size (DATA_NR+1). "1": A single trigger initiates a single descriptor transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure. The current descriptor is completed when its data transfer is completed. "2": A single trigger initiates a descriptor list transfer (DMA mode). This opcode specifies a transfer of DATA_NR+1 data elements as specified by the current descriptor structure and by successive valid descriptors. The current descriptor is completed when its data transfer is completed. This OPCODE relies on FLIPPING to be set to '1', such that the CH_CTLi.PING_PONG field is flipped/inverted and the successive descriptor is used. This continues for as long as the successive descriptor is valid. Note that as the HW is using the PING/PONG descriptor, the SW can prepare the alternate PONG/PING descriptor. The interrupt mechanism is used by HW to convey to the SW that the current descriptor is completed (and can be prepared for a successive transfer). After completerion of the opcode (and waiting for de-activation, the channel's output trigger is activated). Default Value: Undefined
29	FLIPPING	'1': On completion of the current descriptor structure, the current descriptor identifier CH_CTLi.PING_PONG is flipped/inverted. In DMA mode, descriptor list transfer, flipping of the current descriptor identifier can be used to construct a linked list of descriptor structures. Default Value: Undefined
28	PREEMPTABLE	'1': Transfer is preemptable. In DMA mode (OPCODE is "1" or "2"), multi data element transfers are constructed out of multiple single data element load (from the source location) and store (to the destination location) sequences. This field allows higher priority activated channels to preempt the current transfer in between these atomic (load, store) sequences. Preemption will NOT deactivate the current channel. As a result, after completion of a higher priority activated channel, the current channel is rescheduled. Default Value: Undefined
27	SET_CAUSE	'1': On completion of the current descriptor structure, the interrupt cause field of the channel is set to '1' (INTR.CH[i]). Default Value: Undefined
26	INV_DESCR	'1': On completion of the current descriptor structure, the VALID bit of the descriptor's STATUS word is set to '0'. Default Value: Undefined

8.1.123 DMAC_DESCR15_PING_CTL (continued)

25 : 24	WAIT_FOR_DEACT	Specifies whether the data transfer engine should wait for the channel to be deactivated; i.e. the selected system trigger is not active. This field is used to synchronize the controller's data transfer(s) with the agent that generated the trigger. This field is ONLY used at the completion of an opcode. E.g., a FIFO indicates that it is empty and it needs a new data sample. The agent removes the trigger ONLY when the data sample has been written by the transfer engine AND received by the agent. Furthermore, the agent's trigger may be delayed by a few cycles before it reaches the DW/DMA controller. This field is used for level sensitive trigger, which reflect state (pulse sensitive triggers should have this field set to "0"). The wait cycles incurred by this field reduce DW/DMA controller performance. "0": Do not wait for de-activation (for pulse sensitive triggers). "1": Wait for up to 4 cycles. "2": Wait for up to 8 cycles. "3": Wait indefinitely. This option may result in DW/DMA controller lockup if the system trigger is not de-activated by the source agent. Default Value: Undefined
23	SRC_ADDR_INCR	Specifies whether the source location address is incremented by the SRC_TRANSFER_SIZE after each single data element transfer or not. '0': No increment, typically used for receive (RX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
22	SRC_TRANSFER_SIZE	Specifies the bus transfer size to the source location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for source components with data elements that are smaller than their 32-bit bus interface width. E.g., an ADC source has a 32-bit bus transfer size, but only provides a 16-bit data element. Default Value: Undefined
21	DST_ADDR_INCR	Specifies whether the destination location address is incremented by the DST_TRANSFER_SIZE after each single data element transfer or not. '0' : No increment, typically used for transmit (TX) FIFO structures. '1': Increment, typically used for memory structures. Default Value: Undefined
20	DST_TRANSFER_SIZE	Specifies the bus transfer size to the destination location: '0': As specified by DATA_SIZE. '1': Word (32 bits). Distinguishing bus transfer size from data element size allows for destination components with data elements that are smaller than their 32-bit bus interface width. E.g., a DAC destination has a 32-bit bus transfer size, but only requires a 16-bit data element. Default Value: Undefined

8.1.123 DMAC_DESCR15_PING_CTL (continued)

17 : 16	DATA_SIZE	Specifies the data element size: "0": Byte (8 bits). "1": Halfword (16 bits). "2": Word (32 bits). DATA_SIZE, SRC_TRANSFER_SIZE and DST_TRANSFER_SIZE together determine how data elements are transferred. The following are the 9 legal settings: - DATA is 8 bit, SRC is 8 bit, DST is 8 bit - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 8 bit - DATA is 8 bit, SRC is 8 bit, DST is 32 bit (higher 24 bits are made "0") - DATA is 8 bit, SRC is 32 bit (higher 24 bits are dropped), DST is 32 bit (higher 24 bits are made "0") - DATA is 16 bit, SRC is 16 bit, DST is 16 bit - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 16 bit - DATA is 16 bit, SRC is 16 bit, DST is 32 bit (higher 16 bits are made "0") - DATA is 16 bit, SRC is 32 bit (higher 16 bits are dropped), DST is 32 bit (higher 16 bits are made "0") - DATA is 32 bit, SRC is 32 bit, DST is 32 bit Default Value: Undefined
15 : 0	DATA_NR	Number of data elements that are transferred by a single descriptor. In DW mode (OPCODE is "0") each trigger initiates the transfer of a single data element. This field specifies the source and/or destination buffer size in data elements: buffer size = DATA_NR+1. The buffer is typically associated to a memory structure. In DMA mode (OPCODE is "1" or "2") each trigger initiates the transfer of DATA_NR+1 data elements. Default Value: Undefined

8.1.124 DMAC_DESCR15_PING_STATUS

Ping status word

Address: 0x401019EC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	'0': Invalid, cannot be used for a data transfer. An attempt to use this descriptor for a data transfer will result in an INVALID_DESCR response code (and the interrupt cause bit is set to '1'). '1': Valid. Hardware set this field to '0' when a descriptor is done, but only if CONTROL.INV_DESCR is '1'. Software sets this field to '1' when a descriptor is initialized. Default Value: Undefined

8.1.124 DMAC_DESCR15_PING_STATUS (continued)

18 : 16	RESPONSE	Response code (the first two codes NO_ERROR and DONE are the result of normal behavior, the other codes are the result of erroneous behavior). "0"/NO_ERROR: No error. Setting this response does NOT set the interrupt cause bit to '1'. STATUS.VALID is NOT affected. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is not updated. This response is used for an unused or not completed descriptor. Software should set the RESPONSE field to "0"/NO_ERROR during descriptor initialization. "1"/DONE: Descriptor is done (without errors). Setting this response sets the interrupt cause bit to '1' if CONTROL.SET_CAUSE is '1'. STATUS.VALID is set to '0' if CONTROL.INV_DESCR is '1'. CH_CTLi.ENABLED is NOT affected. CH_CTLi.PING_PONG is updated if CONTROL.FLIPPING is '1'. "2"/SRC_BUS_ERROR: Bus error while loading data from the source location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "3"/DST_BUS_ERROR: Bus error while storing data to the destination location. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "4"/SRC_MISAL: Misalignment of source address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "5"/DST_MISAL: Misalignment of destination address. This occurs on a 16-bit bus transfer that is not 2-byte aligned or on a 32-bit bus transfer that is not 4-byte aligned. Setting this response sets the interrupt cause bit to '1'. STATUS.VALID is set '0'. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). "6"/INVALID_DESCR: Invalid descriptor (STATUS.VALID is '0'). This occurs when an activated channel has an invalid descriptor. CH_CTLi.ENABLED is set to '0'. CH_CTLi.PING_PONG is not updated (it identifies the descriptor that caused the error). Default Value: Undefined
15 : 0	CURR_DATA_NR	Specifies the index of the current data transfer. This value increases from 0 to CONTROL.DATA_NR. HW sets this field: - When a descriptor is done (RESPONSE is DONE), the field is set to "0" when PING_CTL.INV_DESCR is '0' and the field is set to PING_CTL.DATA_NR when PING_CTL.INV_DESCR is '1'. - When a descriptor is not done (RESPONSE is NO_ERROR), the field reflects the progress of a data transfer. - In case of erroneous behavior (RESPONSE is neither DONE or NO_ERROR), the field is not updated, but keeps its value to ease debugging. HW only modifies this field for an active descriptor (STATUS.VALID to be '1'). At descriptor initialization, SW should set this field to "0". This field allows software to read the progress of the data transfer. Note that SRC.ADDR and DST.ADDR represent base addresses and are not modified during data transfer. However, STATUS.CURR_DATA_NR is modified during data transfer and provides an offset wrt. the base addresses. Default Value: Undefined

8.1.125 DMAC_DESCR15_PONG_SRC

Pong source address

Address: 0x401019F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_SRC. Default Value: Undefined

8.1.126 DMAC_DESCR15_PONG_DST

Pong destination address

Address: 0x401019F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	RW							
Name	ADDR [31:24]							

Bits	Name	Description
31 : 0	ADDR	See description of PING_DST. Default Value: Undefined

8.1.127 DMAC_DESCR15_PONG_CTL

Pong control word

Address: 0x401019F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	RW	RW	None		RW	
HW Access	RW	RW	RW	RW	None		RW	
Name	SRC_ADDR_INCR	SRC_TRANSFER_SIZE	DST_ADDR_INCR	DST_TRANSFER_SIZE	None [19:18]		DATA_SIZE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW	RW	RW	RW	RW	
HW Access	RW		RW	RW	RW	RW	RW	
Name	OPCODE [31:30]		FLIPPING	PREEMPT-ABLE	SET_CAUSE	INV_DESCR	WAIT_FOR_DEACT [25:24]	

Bits	Name	Description
31 : 30	OPCODE	See description of PING_CTL. Default Value: Undefined
29	FLIPPING	See description of PING_CTL. Default Value: Undefined
28	PREEMPTABLE	See description of PING_CTL. Default Value: Undefined
27	SET_CAUSE	See description of PING_CTL. Default Value: Undefined
26	INV_DESCR	See description of PING_CTL. Default Value: Undefined
25 : 24	WAIT_FOR_DEACT	See description of PING_CTL. Default Value: Undefined
23	SRC_ADDR_INCR	See description of PING_CTL. Default Value: Undefined

8.1.127 DMAC_DESCR15_PONG_CTL (continued)

22	SRC_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
21	DST_ADDR_INCR	See description of PING_CTL. Default Value: Undefined
20	DST_TRANSFER_SIZE	See description of PING_CTL. Default Value: Undefined
17 : 16	DATA_SIZE	See description of PING_CTL. Default Value: Undefined
15 : 0	DATA_NR	See description of PING_CTL. Default Value: Undefined

8.1.128 DMAC_DESCR15_PONG_STATUS

Pong status word

Address: 0x401019FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CURR_DATA_NR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None					RW		
HW Access	None					RW		
Name	None [23:19]					RESPONSE [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	VALID	None [30:24]						

Bits	Name	Description
31	VALID	See description of PING_STATUS. Default Value: Undefined
18 : 16	RESPONSE	See description of PING_STATUS. Default Value: Undefined
15 : 0	CURR_DATA_NR	See description of PING_STATUS. Default Value: Undefined

9 GPIO Registers

This section discusses the GPIO registers. It lists all the registers in mapping tables, in address order.

9.1 Register Details

Register Name	Address
GPIO_INTR_CAUSE	0x40041000

9.1.1 GPIO_INTR_CAUSE

Interrupt port cause register

Address: 0x40041000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	PORT_INT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							PORT_INT

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	PORT_INT	Each IO port has an associated bit field in this register. The bit field reflects the IO port's interrupt line (bit field i reflects "gpio_interrupts[i]" for IO port i). The register is used when the system uses a shared/combined interrupt line "gpio_interrupt". The SW ISR reads the register to determine which IO port(s) is responsible for the shared/combined interrupt line "gpio_interrupt". Once, the IO port(s) is determined, the IO port's INTR register is read to determine the IO pad(s) in the IO port that caused the interrupt. Default Value: 0

10 GPIO Port Registers

This section discusses the GPIO Port registers. It lists all the registers in mapping tables, in address order.

10.1 Register Details

Register Name	Address
GPIO_PRT0_DR	0x40040000
GPIO_PRT0_PS	0x40040004
GPIO_PRT0_PC	0x40040008
GPIO_PRT0_INTR_CFG	0x4004000C
GPIO_PRT0_INTR	0x40040010
GPIO_PRT0_PC2	0x40040018
GPIO_PRT0_DR_SET	0x40040040
GPIO_PRT0_DR_CLR	0x40040044
GPIO_PRT0_DR_INV	0x40040048
GPIO_PRT1_DR	0x40040100
GPIO_PRT1_PS	0x40040104
GPIO_PRT1_PC	0x40040108
GPIO_PRT1_INTR_CFG	0x4004010C
GPIO_PRT1_INTR	0x40040110
GPIO_PRT1_PC2	0x40040118
GPIO_PRT1_DR_SET	0x40040140
GPIO_PRT1_DR_CLR	0x40040144
GPIO_PRT1_DR_INV	0x40040148
GPIO_PRT2_DR	0x40040200
GPIO_PRT2_PS	0x40040204
GPIO_PRT2_PC	0x40040208
GPIO_PRT2_INTR_CFG	0x4004020C
GPIO_PRT2_INTR	0x40040210
GPIO_PRT2_PC2	0x40040218
GPIO_PRT2_DR_SET	0x40040240
GPIO_PRT2_DR_CLR	0x40040244
GPIO_PRT2_DR_INV	0x40040248

Register Name	Address
GPIO_PRT3_DR	0x40040300
GPIO_PRT3_PS	0x40040304
GPIO_PRT3_PC	0x40040308
GPIO_PRT3_INTR_CFG	0x4004030C
GPIO_PRT3_INTR	0x40040310
GPIO_PRT3_PC2	0x40040318
GPIO_PRT3_DR_SET	0x40040340
GPIO_PRT3_DR_CLR	0x40040344
GPIO_PRT3_DR_INV	0x40040348
GPIO_PRT4_DR	0x40040400
GPIO_PRT4_PS	0x40040404
GPIO_PRT4_PC	0x40040408
GPIO_PRT4_INTR_CFG	0x4004040C
GPIO_PRT4_INTR	0x40040410
GPIO_PRT4_PC2	0x40040418
GPIO_PRT4_DR_SET	0x40040440
GPIO_PRT4_DR_CLR	0x40040444
GPIO_PRT4_DR_INV	0x40040448
GPIO_PRT5_DR	0x40040500
GPIO_PRT5_PS	0x40040504
GPIO_PRT5_PC	0x40040508
GPIO_PRT5_INTR_CFG	0x4004050C
GPIO_PRT5_INTR	0x40040510
GPIO_PRT5_PC2	0x40040518
GPIO_PRT5_DR_SET	0x40040540
GPIO_PRT5_DR_CLR	0x40040544
GPIO_PRT5_DR_INV	0x40040548
GPIO_PRT6_DR	0x40040600
GPIO_PRT6_PS	0x40040604
GPIO_PRT6_PC	0x40040608
GPIO_PRT6_INTR_CFG	0x4004060C
GPIO_PRT6_INTR	0x40040610
GPIO_PRT6_PC2	0x40040618
GPIO_PRT6_DR_SET	0x40040640
GPIO_PRT6_DR_CLR	0x40040644
GPIO_PRT6_DR_INV	0x40040648
GPIO_PRT7_DR	0x40040700
GPIO_PRT7_PS	0x40040704
GPIO_PRT7_PC	0x40040708
GPIO_PRT7_INTR_CFG	0x4004070C
GPIO_PRT7_INTR	0x40040710
GPIO_PRT7_PC2	0x40040718

Register Name	Address
GPIO_PRT7_DR_SET	0x40040740
GPIO_PRT7_DR_CLR	0x40040744
GPIO_PRT7_DR_INV	0x40040748
GPIO_PRT8_DR	0x40040800
GPIO_PRT8_PS	0x40040804
GPIO_PRT8_INTR_CFG	0x4004080C
GPIO_PRT8_INTR	0x40040810
GPIO_PRT8_DR_SET	0x40040840
GPIO_PRT8_DR_CLR	0x40040844
GPIO_PRT8_DR_INV	0x40040848

10.1.1 GPIO_PRT0_DR

Port output data register

Address: 0x40040000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.2 GPIO_PRT0_PS

Port IO pad state register

Address: 0x40040004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

10.1.2 GPIO_PRT0_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.3 GPIO_PRT0_PC

Port configuration register

Address: 0x40040008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.3 GPIO_PRT0_PC (continued)

25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. Illegal for GPIOV1P2_I2C

10.1.3 GPIO_PRT0_PC (continued)

0x6: 0_1:
Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on.
For GPIOV1P2_I2C, Strong pull down only.

0x7: PD_PU:
Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.
For GPIOV1P2_I2C: Weak pull down only.

10.1.4 GPIO_PRT0_INTR_CFG

Port interrupt configuration register

Address: 0x4004000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

10.1.4 GPIO_PRT0_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.5 GPIO_PRT0_INTR

Port interrupt status register

Address: 0x40040010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

10.1.5 GPIO_PRT0_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.6 GPIO_PRT0_PC2

Port configuration register 2

Address: 0x40040018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

10.1.6 GPIO_PRT0_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.7 GPIO_PRT0_DR_SET

Port output data set register

Address: 0x40040040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.8 GPIO_PRT0_DR_CLR

Port output data clear register

Address: 0x40040044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.9 GPIO_PRT0_DR_INV

Port output data invert register

Address: 0x40040048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.10 GPIO_PRT1_DR

Port output data register

Address: 0x40040100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	RW	RW	RW	RW
HW Access	None	RW	RW	RW	RW	RW	RW	RW
Name	None	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.11 GPIO_PRT1_PS

Port IO pad state register

Address: 0x40040104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	R	R	R	R	R	R	R
HW Access	None	W	W	W	W	W	W	W
Name	None	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

10.1.11 GPIO_PRT1_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.12 GPIO_PRT1_PC

Port configuration register

Address: 0x40040108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.12 GPIO_PRT1_PC (continued)

25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. Illegal for GPIOV1P2_I2C **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C, Strong pull down only.

10.1.12 GPIO_PRT1_PC (continued)

0x7: PD_PU:
Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.
For GPIOV1P2_I2C: Weak pull down only.

10.1.13 GPIO_PRT1_INTR_CFG

Port interrupt configuration register

Address: 0x4004010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0
11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0

10.1.13 GPIO_PRT1_INTR_CFG (continued)

9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.14 GPIO_PRT1_INTR

Port interrupt status register

Address: 0x40040110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None	A	A	A	A	A	A	A
Name	None	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None	R	R	R	R	R	R	R
HW Access	None	W	W	W	W	W	W	W
Name	None	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

10.1.14 GPIO_PRT1_INTR (continued)

6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.15 GPIO_PRT1_PC2

Port configuration register 2

Address: 0x40040118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	RW	RW	RW	RW
HW Access	None	R	R	R	R	R	R	R
Name	None	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.16 GPIO_PRT1_DR_SET

Port output data set register

Address: 0x40040140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.17 GPIO_PRT1_DR_CLR

Port output data clear register

Address: 0x40040144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.18 GPIO_PRT1_DR_INV

Port output data invert register

Address: 0x40040148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.19 GPIO_PRT2_DR

Port output data register

Address: 0x40040200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.20 GPIO_PRT2_PS

Port IO pad state register

Address: 0x40040204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

10.1.20 GPIO_PRT2_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.21 GPIO_PRT2_PC

Port configuration register

Address: 0x40040208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.21 GPIO_PRT2_PC (continued)

25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. Illegal for GPIOV1P2_I2C

10.1.21 GPIO_PRT2_PC (continued)

0x6: 0_1:
Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on.
For GPIOV1P2_I2C, Strong pull down only.

0x7: PD_PU:
Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.
For GPIOV1P2_I2C: Weak pull down only.

10.1.22 GPIO_PRT2_INTR_CFG

Port interrupt configuration register

Address: 0x4004020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

10.1.22 GPIO_PRT2_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.23 GPIO_PRT2_INTR

Port interrupt status register

Address: 0x40040210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

10.1.23 GPIO_PRT2_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.24 GPIO_PRT2_PC2

Port configuration register 2

Address: 0x40040218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

10.1.24 GPIO_PRT2_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.25 GPIO_PRT2_DR_SET

Port output data set register

Address: 0x40040240

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.26 GPIO_PRT2_DR_CLR

Port output data clear register

Address: 0x40040244

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.27 GPIO_PRT2_DR_INV

Port output data invert register

Address: 0x40040248

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.28 GPIO_PRT3_DR

Port output data register

Address: 0x40040300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.29 GPIO_PRT3_PS

Port IO pad state register

Address: 0x40040304

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

10.1.29 GPIO_PRT3_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.30 GPIO_PRT3_PC

Port configuration register

Address: 0x40040308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.30 GPIO_PRT3_PC (continued)

25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. Illegal for GPIOV1P2_I2C

10.1.30 GPIO_PRT3_PC (continued)

0x6: 0_1:
Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on.
For GPIOV1P2_I2C, Strong pull down only.

0x7: PD_PU:
Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.
For GPIOV1P2_I2C: Weak pull down only.

10.1.31 GPIO_PRT3_INTR_CFG

Port interrupt configuration register

Address: 0x4004030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

10.1.31 GPIO_PRT3_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.32 GPIO_PRT3_INTR

Port interrupt status register

Address: 0x40040310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

10.1.32 GPIO_PRT3_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.33 GPIO_PRT3_PC2

Port configuration register 2

Address: 0x40040318

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

10.1.33 GPIO_PRT3_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.34 GPIO_PRT3_DR_SET

Port output data set register

Address: 0x40040340

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.35 GPIO_PRT3_DR_CLR

Port output data clear register

Address: 0x40040344

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.36 GPIO_PRT3_DR_INV

Port output data invert register

Address: 0x40040348

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.37 GPIO_PRT4_DR

Port output data register

Address: 0x40040400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW	RW
Name	None [7:2]						DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.38 GPIO_PRT4_PS

Port IO pad state register

Address: 0x40040404

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0
0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.39 GPIO_PRT4_PC

Port configuration register

Address: 0x40040408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW			RW		
HW Access	None		R			R		
Name	None [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW		RW	None	RW	RW
HW Access	R		R		R	None	R	R
Name	PORT_IB_MODE_SEL [31:30]		PORT_SLEW_CTL [29:28]		PORT_HYST_TRIM	None	PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.39 GPIO_PRT4_PC (continued)

29 : 28	PORT_SLEW_CTL	Slew control. Only used in the O_Z drive mode (mode 4: strong pull down, open drain): This field is intended for I2C functionality. See BROS 001-70428 for more details. Default Value: 0 **0x0: PORT_SLEW_CTL_0:** HS mode (100pf < Cb < 400pF, 1.71<5.5, Vext>3.0) FS mode (10pf<400pf,1.71<5.5) (20-160ns) **0x1: PORT_SLEW_CTL_1:** HS mode (Cb<100pf,1.71<5.5,Vext>2.8,F=1.7MHz) (10-80ns) FS+ Mode (Vext>2.8,1.71<5.5) (20-120ns) **0x2: PORT_SLEW_CTL_2:** HS mode (100pf<400pf, 1.71<5.5,Vext<3.3) (20-160ns) **0x3: PORT_SLEW_CTL_3:** HS mode (Cb<100pf,1.71<5.5,Vext<=2.8,F=1.7MHz) (10-80ns) FS+ mode (Vext<=2.8,1.71<5.5) (20-120ns)
27	PORT_HYST_TRIM	This field is used to improve the hysteresis (to 10% of vddio) of the selectable trip point input buffer. The voltage reference comes from the VREFGEN block and is only available when using the VREFGEN block: '0': <= 2.2 V input signaling Voltage. '1': > 2.2 V input signaling Voltage. Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only.

10.1.39 GPIO_PRT4_PC (continued)

0x4: 0_Z:
Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on.
For GPIOV1P2_I2C, Strong pull down only.

0x5: Z_1:
Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on.
Illegal for GPIOV1P2_I2C

0x6: 0_1:
Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on.
For GPIOV1P2_I2C, Strong pull down only.

0x7: PD_PU:
Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.
For GPIOV1P2_I2C: Weak pull down only.

10.1.40 GPIO_PRT4_INTR_CFG

Port interrupt configuration register

Address: 0x4004040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [7:4]				EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0

10.1.40 GPIO_PRT4_INTR_CFG (continued)

0x0: DISABLE:
Disabled

0x1: RISING:
Rising edge

0x2: FALLING:
Falling edge

0x3: BOTH:
Both rising and falling edges

10.1.41 GPIO_PRT4_INTR

Port interrupt status register

Address: 0x40040410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [7:2]						DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None						R	R
HW Access	None						W	W
Name	None [23:18]						PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.42 GPIO_PRT4_PC2

Port configuration register 2

Address: 0x40040418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.43 GPIO_PRT4_DR_SET

Port output data set register

Address: 0x40040440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.44 GPIO_PRT4_DR_CLR

Port output data clear register

Address: 0x40040444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.45 GPIO_PRT4_DR_INV

Port output data invert register

Address: 0x40040448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.46 GPIO_PRT5_DR

Port output data register

Address: 0x40040500

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		RW	RW	RW	RW	RW	RW
Name	None [7:6]		DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.47 GPIO_PRT5_PS

Port IO pad state register

Address: 0x40040504

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

10.1.47 GPIO_PRT5_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.48 GPIO_PRT5_PC

Port configuration register

Address: 0x40040508

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	
HW Access	None						R	
Name	None [23:18]						DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.48 GPIO_PRT5_PC (continued)

25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. Illegal for GPIOV1P2_I2C **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x7: PD_PU:** Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C: Weak pull down only.

10.1.49 GPIO_PRT5_INTR_CFG

Port interrupt configuration register

Address: 0x4004050C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [15:12]				EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0

10.1.49 GPIO_PRT5_INTR_CFG (continued)

7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.50 GPIO_PRT5_INTR

Port interrupt status register

Address: 0x40040510

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None		A	A	A	A	A	A
Name	None [7:6]		DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [23:22]		PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.50 GPIO_PRT5_INTR (continued)

4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.51 GPIO_PRT5_PC2

Port configuration register 2

Address: 0x40040518

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.52 GPIO_PRT5_DR_SET

Port output data set register

Address: 0x40040540

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.53 GPIO_PRT5_DR_CLR

Port output data clear register

Address: 0x40040544

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.54 GPIO_PRT5_DR_INV

Port output data invert register

Address: 0x40040548

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.55 GPIO_PRT6_DR

Port output data register

Address: 0x40040600

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				RW	RW	RW	RW
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.56 GPIO_PRT6_PS

Port IO pad state register

Address: 0x40040604

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0
0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.57 GPIO_PRT6_PC

Port configuration register

Address: 0x40040608

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			RW
HW Access	None				R			R
Name	None [15:12]				DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.57 GPIO_PRT6_PC (continued)

25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. Illegal for GPIOV1P2_I2C **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x7: PD_PU:** Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C: Weak pull down only.

10.1.58 GPIO_PRT6_INTR_CFG

Port interrupt configuration register

Address: 0x4004060C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0

10.1.58 GPIO_PRT6_INTR_CFG (continued)

3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.59 GPIO_PRT6_INTR

Port interrupt status register

Address: 0x40040610

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [23:20]				PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.59 GPIO_PRT6_INTR (continued)

1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.60 GPIO_PRT6_PC2

Port configuration register 2

Address: 0x40040618

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.61 GPIO_PRT6_DR_SET

Port output data set register

Address: 0x40040640

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.62 GPIO_PRT6_DR_CLR

Port output data clear register

Address: 0x40040644

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.63 GPIO_PRT6_DR_INV

Port output data invert register

Address: 0x40040648

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.64 GPIO_PRT7_DR

Port output data register

Address: 0x40040700

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	RW	RW	RW	RW
HW Access	None	RW	RW	RW	RW	RW	RW	RW
Name	None	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.65 GPIO_PRT7_PS

Port IO pad state register

Address: 0x40040704

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	R	R	R	R	R	R	R
HW Access	None	W	W	W	W	W	W	W
Name	None	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

10.1.65 GPIO_PRT7_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.66 GPIO_PRT7_PC

Port configuration register

Address: 0x40040708

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTv2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). For GPIOV1P2 and GPIOV1P2_I2C cells, PC.PORT_IB_MODE_SEL unused. Refer to DS register. Default Value: 0

10.1.66 GPIO_PRT7_PC (continued)

25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0
24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. For GPIOV1P2 and GPIOV1P_I2C cells, PC.PORT_VTRIP_SEL is unused. Refer to DS register Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 **0x0: OFF:** Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x3: PD_1:** Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C: Weak pull down only. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. For GPIOV1P2_I2C, Strong pull down only. **0x5: Z_1:** Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. Illegal for GPIOV1P2_I2C **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. For GPIOV1P2_I2C, Strong pull down only.

10.1.66 GPIO_PRT7_PC (continued)

0x7: PD_PU:
Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.
For GPIOV1P2_I2C: Weak pull down only.

10.1.67 GPIO_PRT7_INTR_CFG

Port interrupt configuration register

Address: 0x4004070C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0
11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0

10.1.67 GPIO_PRT7_INTR_CFG (continued)

9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.68 GPIO_PRT7_INTR

Port interrupt status register

Address: 0x40040710

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None	A	A	A	A	A	A	A
Name	None	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None	R	R	R	R	R	R	R
HW Access	None	W	W	W	W	W	W	W
Name	None	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

10.1.68 GPIO_PRT7_INTR (continued)

6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.69 GPIO_PRT7_PC2

Port configuration register 2

Address: 0x40040718

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	RW	RW	RW	RW
HW Access	None	R	R	R	R	R	R	R
Name	None	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

10.1.70 GPIO_PRT7_DR_SET

Port output data set register

Address: 0x40040740

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.71 GPIO_PRT7_DR_CLR

Port output data clear register

Address: 0x40040744

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.72 GPIO_PRT7_DR_INV

Port output data invert register

Address: 0x40040748

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

10.1.73 GPIO_PRT8_DR

Port output data register

Address: 0x40040800

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	RW
HW Access	None					RW	RW	RW
Name	None [7:3]					DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

10.1.74 GPIO_PRT8_PS

Port IO pad state register

Address: 0x40040804

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [7:3]					DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0
0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

10.1.75 GPIO_PRT8_INTR_CFG

Port interrupt configuration register

Address: 0x4004080C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0

10.1.75 GPIO_PRT8_INTR_CFG (continued)

1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0 **0x0: DISABLE:** Disabled **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges

10.1.76 GPIO_PRT8_INTR

Port interrupt status register

Address: 0x40040810

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					A	A	A
Name	None [7:3]					DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [23:19]					PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	` Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

10.1.77 GPIO_PRT8_DR_SET

Port output data set register

Address: 0x40040840

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

10.1.78 GPIO_PRT8_DR_CLR

Port output data clear register

Address: 0x40040844

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

10.1.79 GPIO_PRT8_DR_INV

Port output data invert register

Address: 0x40040848

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

11 High Speed IO Matrix (HSIOM) Registers

This section discusses the HSIOM registers. It lists all the registers in mapping tables, in address order.

11.1 Register Details

Register Name	Address
HSIOM_AMUX_SPLIT_CTL0	0x40022100
HSIOM_AMUX_SPLIT_CTL1	0x40022104
HSIOM_AMUX_SPLIT_CTL2	0x40022108

11.1.1 HSIOM_AMUX_SPLIT_CTL0

AMUX splitter cell control

Address: 0x40022100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_BB_S0	SWITCH_BB_SR	SWITCH_BB_SL	None	SWITCH_AA_S0	SWITCH_AA_SR	SWITCH_AA_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

11.1.1 HSIOM_AMUX_SPLIT_CTL0 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

11.1.2 HSIOM_AMUX_SPLIT_CTL1

AMUX splitter cell control

Address: 0x40022104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_BB_S0	SWITCH_BB_SR	SWITCH_BB_SL	None	SWITCH_AA_S0	SWITCH_AA_SR	SWITCH_AA_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

11.1.2 HSIOM_AMUX_SPLIT_CTL1 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

11.1.3 HSIOM_AMUX_SPLIT_CTL2

AMUX splitter cell control

Address: 0x40022108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_BB_S0	SWITCH_BB_SR	SWITCH_BB_SL	None	SWITCH_AA_S0	SWITCH_AA_SR	SWITCH_AA_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

11.1.3 HSIOM_AMUX_SPLIT_CTL2 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

12 HSIOM Port Registers

This section discusses the HSIOM Port registers. It lists all the registers in mapping tables, in address order.

12.1 Register Details

Register Name	Address
HSIOM_PORT_SEL0	0x40020000
HSIOM_PORT_SEL1	0x40020100
HSIOM_PORT_SEL2	0x40020200
HSIOM_PORT_SEL3	0x40020300
HSIOM_PORT_SEL4	0x40020400
HSIOM_PORT_SEL5	0x40020500
HSIOM_PORT_SEL6	0x40020600
HSIOM_PORT_SEL7	0x40020700
HSIOM_PORT_SEL8	0x40020800

12.1.1 HSIOM_PORT_SEL0

Port selection register

Address: 0x40020000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

12.1.1 HSIOM_PORT_SEL0 (continued)

0x0: GPIO:
SW controlled GPIO.

0x1: GPIO_DSI:
SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:
DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:
DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.2 HSIOM_PORT_SEL1

Port selection register

Address: 0x40020100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				RW			
HW Access	None				RW			
Name	None [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO.

12.1.2 HSIOM_PORT_SEL1 (continued)

0x1: GPIO_DSI:
SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:
DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:
DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.3 HSIOM_PORT_SEL2

Port selection register

Address: 0x40020200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

12.1.3 HSIOM_PORT_SEL2 (continued)

0x0: GPIO:
SW controlled GPIO.

0x1: GPIO_DSI:
SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:
DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:
DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.4 HSIOM_PORT_SEL3

Port selection register

Address: 0x40020300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

12.1.4 HSIOM_PORT_SEL3 (continued)

0x0: GPIO:
SW controlled GPIO.

0x1: GPIO_DSI:
SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:
DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:
DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.5 HSIOM_PORT_SEL4

Port selection register

Address: 0x40020400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO. **0x1: GPIO_DSI:** SW controlled "out", DSI controlled "oe_n". **0x2: DSI_DSI:** DSI controlled "out" and "oe_n". **0x3: DSI_GPIO:** DSI controlled "out", SW controlled "oe_n". **0x4: CSD_SENSE:** CSD sense connection (analog mode) **0x5: CSD_SHIELD:** CSD shield connection (analog mode)

12.1.5 HSIOM_PORT_SEL4 (continued)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.6 HSIOM_PORT_SEL5

Port selection register

Address: 0x40020500

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO. **0x1: GPIO_DSI:** SW controlled "out", DSI controlled "oe_n".

12.1.6 HSIOM_PORT_SEL5 (continued)

0x2: DSI_DSI:
DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:
DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.7 HSIOM_PORT_SEL6

Port selection register

Address: 0x40020600

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO. **0x1: GPIO_DSI:** SW controlled "out", DSI controlled "oe_n". **0x2: DSI_DSI:** DSI controlled "out" and "oe_n". **0x3: DSI_GPIO:** DSI controlled "out", SW controlled "oe_n".

12.1.7 HSIOM_PORT_SEL6 (continued)

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.8 HSIOM_PORT_SEL7

Port selection register

Address: 0x40020700

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				RW			
HW Access	None				RW			
Name	None [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO.

12.1.8 HSIOM_PORT_SEL7 (continued)

0x1: GPIO_DSI:
SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:
DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:
DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:
CSD sense connection (analog mode)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

12.1.9 HSIOM_PORT_SEL8

Port selection register

Address: 0x40020800

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				RW			
Name	None [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0 **0x0: GPIO:** SW controlled GPIO. **0x1: GPIO_DSI:** SW controlled "out", DSI controlled "oe_n". **0x2: DSI_DSI:** DSI controlled "out" and "oe_n". **0x3: DSI_GPIO:** DSI controlled "out", SW controlled "oe_n". **0x4: CSD_SENSE:** CSD sense connection (analog mode)

12.1.9 HSIOM_PORT_SEL8 (continued)

0x5: CSD_SHIELD:
CSD shield connection (analog mode)

0x6: AMUXA:
AMUXBUS A connection.

0x7: AMUXB:
AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:
Chip specific Active source 0 connection.

0x9: ACT_1:
Chip specific Active source 1 connection.

0xa: ACT_2:
Chip specific Active source 2 connection.

0xb: ACT_3:
Chip specific Active source 3 connection.

0xc: LCD_COM:
LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:
Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:
LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:
Chip specific DeepSleep source 1 connection.

0xe: DS_2:
Chip specific DeepSleep source 2 connection.

0xf: DS_3:
Chip specific DeepSleep source 3 connection.

13 Low-Power Comparator Registers

This section discusses the Low-Power Comparator) registers. It lists all the registers in mapping tables, in address order.

13.1 Register Details

Register Name	Address
LPCOMP_ID	0x402B0000
LPCOMP_CONFIG	0x402B0004
LPCOMP_INTR	0x402B0010
LPCOMP_INTR_SET	0x402B0014
LPCOMP_INTR_MASK	0x402B0018
LPCOMP_INTR_MASKED	0x402B001C
LPCOMP_TRIM1	0x402BFF00
LPCOMP_TRIM2	0x402BFF04
LPCOMP_TRIM3	0x402BFF08
LPCOMP_TRIM4	0x402BFF0C

13.1.1 LPCOMP_ID

ID & Revision

Address: 0x402B0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	REVISION [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	REVISION [31:24]							

Bits	Name	Description
31 : 16	REVISION	the version number is 0x0001 Default Value: 1
15 : 0	ID	the ID of LPCOMP peripheral is 0xE0E0 Default Value: 57568

13.1.2 LPCOMP_CONFIG

LPCOMP Configuration Register

Address: 0x402B0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	R	RW		RW	RW	RW	
HW Access	R	RW	R		R	R	R	
Name	ENABLE1	OUT1	INTTYPE1 [5:4]		FILTER1	HYST1	MODE1 [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW	R	RW		RW	RW	RW	
HW Access	R	RW	R		R	R	R	
Name	ENABLE2	OUT2	INTTYPE2 [13:12]		FILTER2	HYST2	MODE2 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	None		RW	RW
HW Access	None		R	R	None		R	R
Name	None [23:22]		DSI_LEVEL2	DSI_BYPASS2	None [19:18]		DSI_LEVEL1	DSI_BYPASS1

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	DSI_LEVEL2	Opamp2 comparator DSI (trigger) out level : 0=pulse, 1=level Default Value: 0
20	DSI_BYPASS2	Opamp2 bypass comparator output synchronization for DSI output: 0=synchronize (level or pulse), 1=bypass (output async) Note that in DeepSleep mode this bit needs to be set to observe the DSI output on the dedicated pin. Default Value: 0
17	DSI_LEVEL1	Opamp1 comparator DSI (trigger) out level : 0=pulse, 1=level Default Value: 0
16	DSI_BYPASS1	Opamp1 bypass comparator output synchronization for DSI output: 0=synchronize (level or pulse), 1=bypass (output async) Note that in DeepSleep mode this bit needs to be set to observe the DSI output on the dedicated pin. Default Value: 0
15	ENABLE2	Enable comparator #2 Default Value: 0

13.1.2 LPCOMP_CONFIG (continued)

14	OUT2	Current output value of the comparator. Default Value: 0
13 : 12	INTTYPE2	Sets which edge will trigger an IRQ Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
11	FILTER2	Deprecated, Reserved, must be written 0 Default Value: 0
10	HYST2	Add 10mV hysteresis to the comparator - 0: Enable Hysteresis - 1: Disable Hysteresis Default Value: 0
9 : 8	MODE2	Operating mode for the comparator Default Value: 0 **0x0: SLOW:** Slow operating mode (uses less power, <50uA) **0x1: FAST:** Fast operating mode (uses more power, <400uA) **0x2: ULP:** Ultra low power operting mode (uses ~2-4uA)
7	ENABLE1	Enable comparator #1 Default Value: 0
6	OUT1	Current output value of the comparator. Default Value: 0
5 : 4	INTTYPE1	Sets which edge will trigger an IRQ Default Value: 0 **0x0: DISABLE:** Disabled, no interrupts will be detected **0x1: RISING:** Rising edge **0x2: FALLING:** Falling edge **0x3: BOTH:** Both rising and falling edges
3	FILTER1	Deprecated, Reserved, must be written 0 Default Value: 0
2	HYST1	Add 10mV hysteresis to the comparator - 0: Enable Hysteresis - 1: Disable Hysteresis Default Value: 0

13.1.2 LPCOMP_CONFIG (continued)

1 : 0	MODE1	Operating mode for the comparator Default Value: 0 **0x0: SLOW:** Slow operating mode (uses less power, <50uA) **0x1: FAST:** Fast operating mode (uses more power, <400uA) **0x2: ULP:** Ultra low power operting mode (uses ~2-4uA)

13.1.3 LPCOMP_INTR

LPCOMP Interrupt request register

Address: 0x402B0010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						COMP2	COMP1

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2	Comparator 2 Interrupt: hardware sets this interrupt when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0
0	COMP1	Comparator 1 Interrupt: hardware sets this interrupt when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

13.1.4 LPCOMP_INTR_SET

LPCOMP Interrupt set register

Address: 0x402B0014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						COMP2	COMP1

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	COMP1	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

13.1.5 LPCOMP_INTR_MASK

LPCOMP Interrupt request mask

Address: 0x402B0018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						COMP2_MASK	COMP1_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	COMP1_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

13.1.6 LPCOMP_INTR_MASKED

LPCOMP Interrupt request masked

Address: 0x402B001C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						COMP2_MASKED	COMP1_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	COMP1_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

13.1.7 LPCOMP_TRIM1

LPCOMP Trim Register

Address: 0x402BFF00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP1_TRIMA [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP1_TRIMA	Trim A for Comparator #1 Default Value: 0

13.1.8 LPCOMP_TRIM2

LPCOMP Trim Register

Address: 0x402BFF04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP1_TRIMB [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP1_TRIMB	Trim B for Comparator #1 Default Value: 0

13.1.9 LPCOMP_TRIM3

LPCOMP Trim Register

Address: 0x402BFF08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP2_TRIMA [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP2_TRIMA	Trim A for Comparator #2 Default Value: 0

13.1.10 LPCOMP_TRIM4

LPCOMP Trim Register

Address: 0x402BFF0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP2_TRIMB [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP2_TRIMB	Trim B for Comparator #2 Default Value: 0

14 PASS Registers

This section discusses the PASS registers. It lists all the registers in mapping tables, in address order.

14.1 Register Details

Register Name	Address
PASS0_INTR_CAUSE	0x403F0000
PASS0_DFT_CTRL	0x403F0030
PASS0_PASS_CTRL	0x403F0108
PASS0_DSAB_TRIM	0x403F0F00

14.1.1 PASS0_INTR_CAUSE

Interrupt cause register

Address: 0x403F0000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							CTB0_INT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	CTB0_INT	CTB0 interrupt pending Default Value: 0

14.1.2 PASS0_DFT_CTRL

DFT control register

Address: 0x403F0030

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							DSAB_ADFT_RES_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	DSAB_ADFT_RES_EN	Close the switch to connect the DSAB ADFT resistor to the AMUXBUS Default Value: 0

14.1.3 PASS0_PASS_CTRL

PASS Control

Address: 0x403F0108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						PMPCLK_SRC	PMPCLK_BYP

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RMB_BITS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	RMB_BITS	Risk mitigation bits Default Value: 0
1	PMPCLK_SRC	- 0: Pump clk is clk_hf - 1: Pump clk is direct from SRSS Default Value: 0
0	PMPCLK_BYP	- 0: Pump clk is clk_hf/2 - 1: Pump clk is selected from PMPCLK_SRC Default Value: 0

14.1.4 PASS0_DSAB_TRIM

DSAB Trim bits

Address: 0x403F0F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW			
HW Access	None		R		R			
Name	None [7:6]		DSAB_RMB_BITS [5:4]		IBIAS_TRIM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	DSAB_RMB_BITS	Risk mitigation bits Default Value: 0
3 : 0	IBIAS_TRIM	1111=lowest, 0000=highest Default Value: 0

15 Peripheral Interconnect (PERI) Registers

This section discusses the PERI registers. It lists all the registers in mapping tables, in address order.

15.1 Register Details

Register Name	Address
PERI_DIV_CMD	0x40010000
PERI_PCLK_CTL0	0x40010100
PERI_PCLK_CTL1	0x40010104
PERI_PCLK_CTL2	0x40010108
PERI_PCLK_CTL3	0x4001010C
PERI_PCLK_CTL4	0x40010110
PERI_PCLK_CTL5	0x40010114
PERI_PCLK_CTL6	0x40010118
PERI_PCLK_CTL7	0x4001011C
PERI_PCLK_CTL8	0x40010120
PERI_PCLK_CTL9	0x40010124
PERI_PCLK_CTL10	0x40010128
PERI_PCLK_CTL11	0x4001012C
PERI_PCLK_CTL12	0x40010130
PERI_PCLK_CTL13	0x40010134
PERI_PCLK_CTL14	0x40010138
PERI_PCLK_CTL15	0x4001013C
PERI_PCLK_CTL16	0x40010140
PERI_PCLK_CTL17	0x40010144
PERI_PCLK_CTL18	0x40010148
PERI_PCLK_CTL19	0x4001014C
PERI_PCLK_CTL20	0x40010150
PERI_PCLK_CTL21	0x40010154
PERI_PCLK_CTL22	0x40010158
PERI_PCLK_CTL23	0x4001015C
PERI_PCLK_CTL24	0x40010160
PERI_PCLK_CTL25	0x40010164

Register Name	Address
PERI_PCLK_CTL26	0x40010168
PERI_PCLK_CTL27	0x4001016C
PERI_PCLK_CTL28	0x40010170
PERI_PCLK_CTL29	0x40010174
PERI_PCLK_CTL30	0x40010178
PERI_PCLK_CTL31	0x4001017C
PERI_DIV_8_CTL0	0x40010200
PERI_DIV_8_CTL1	0x40010204
PERI_DIV_8_CTL2	0x40010208
PERI_DIV_8_CTL3	0x4001020C
PERI_DIV_8_CTL4	0x40010210
PERI_DIV_8_CTL5	0x40010214
PERI_DIV_8_CTL6	0x40010218
PERI_DIV_8_CTL7	0x4001021C
PERI_DIV_8_CTL8	0x40010220
PERI_DIV_8_CTL9	0x40010224
PERI_DIV_8_CTL10	0x40010228
PERI_DIV_8_CTL11	0x4001022C
PERI_DIV_16_CTL0	0x40010300
PERI_DIV_16_CTL1	0x40010304
PERI_DIV_16_CTL2	0x40010308
PERI_DIV_16_CTL3	0x4001030C
PERI_DIV_16_5_CTL0	0x40010400
PERI_DIV_16_5_CTL1	0x40010404
PERI_DIV_16_5_CTL2	0x40010408
PERI_DIV_16_5_CTL3	0x4001040C
PERI_DIV_16_5_CTL4	0x40010410
PERI_TR_CTL	0x40010600

15.1.1 PERI_DIV_CMD

Divider command register

Address: 0x40010000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW					
HW Access	R		R					
Name	SEL_TYPE [7:6]		SEL_DIV [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW					
HW Access	R		R					
Name	PA_SEL_TYPE [15:14]		PA_SEL_DIV [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	RW1C	RW1C	None					
Name	ENABLE	DISABLE	None [29:24]					

Bits	Name	Description
31	ENABLE	Clock divider enable command (mutually exclusive with DISABLE). Typically, SW sets this field to '1' to enable a divider and HW sets this field to '0' to indicate that divider enabling has completed. When a divider is enabled, its integer and fractional (if present) counters are initialized to "0". If a divider is to be re-enabled using different integer and fractional divider values, the SW should follow these steps: 0: Disable the divider using the DIV_CMD.DISABLE field. 1: Configure the divider's DIV_XXX_CTL register. 2: Enable the divider using the DIV_CMD_ENABLE field. The SEL_DIV and SEL_TYPE fields specify which divider is to be enabled. The enabled divider may be phase aligned to either "clk_hf" (typical usage) or to ANY enabled divider. The PA_SEL_DIV and P_SEL_TYPE fields specify the reference divider. The HW sets the ENABLE field to '0' when the enabling is performed and the HW set the DIV_XXX_CTL.EN field of the divider to '1' when the enabling is performed. Note that enabling with phase alignment to a low frequency divider takes time. E.g. To align to a divider that generates a clock of "clk_hf"/n (with n being the integer divider value INT_DIV+1), up to n cycles may be required to perform alignment. Phase alignment to "clk_hf" takes affect immediately. SW can set this field to '0' during phase alignment to abort the enabling process. Default Value: 0

15.1.1 PERI_DIV_CMD (continued)

30	DISABLE	Clock divider disable command (mutually exlusive with ENABLE). SW sets this field to '1' and HW sets this field to '0'. The SEL_DIV and SEL_TYPE fields specify which divider is to be disabled. The HW sets the DISABLE field to '0' immediately and the HW sets the DIV_XXX_CTL.EN field of the divider to '0' immediately. Default Value: 0
15 : 14	PA_SEL_TYPE	Specifies the divider type of the divider to which phase alignment is performed for the clock enable command: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
13 : 8	PA_SEL_DIV	(PA_SEL_TYPE, PA_SEL_DIV) pecifies the divider to which phase alignment is performed for the clock enable command. Any enabled divider can be used as reference. This allows all dividers to be aligned with each other, even when they are enabled at different times. If PA_SEL_DIV is "63" and "PA_SEL_TYPE" is "3", "clk_hf" is used as reference. Default Value: 63
7 : 6	SEL_TYPE	Specifies the divider type of the divider on which the command is performed: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
5 : 0	SEL_DIV	(SEL_TYPE, SEL_DIV) specifies the divider on which the command (DISABLE/ENABLE) is performed. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock signal(s) are generated. Default Value: 63

15.1.2 PERI_PCLK_CTL0

Programmable clock control register

Address: 0x40010100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.3 PERI_PCLK_CTL1

Programmable clock control register

Address: 0x40010104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.4 PERI_PCLK_CTL2

Programmable clock control register

Address: 0x40010108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.5 PERI_PCLK_CTL3

Programmable clock control register

Address: 0x4001010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.6 PERI_PCLK_CTL4

Programmable clock control register

Address: 0x40010110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.7 PERI_PCLK_CTL5

Programmable clock control register

Address: 0x40010114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.8 PERI_PCLK_CTL6

Programmable clock control register

Address: 0x40010118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.9 PERI_PCLK_CTL7

Programmable clock control register

Address: 0x4001011C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.10 PERI_PCLK_CTL8

Programmable clock control register

Address: 0x40010120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.11 PERI_PCLK_CTL9

Programmable clock control register

Address: 0x40010124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.12 PERI_PCLK_CTL10

Programmable clock control register

Address: 0x40010128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.13 PERI_PCLK_CTL11

Programmable clock control register

Address: 0x4001012C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.14 PERI_PCLK_CTL12

Programmable clock control register

Address: 0x40010130

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.15 PERI_PCLK_CTL13

Programmable clock control register

Address: 0x40010134

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.16 PERI_PCLK_CTL14

Programmable clock control register

Address: 0x40010138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.17 PERI_PCLK_CTL15

Programmable clock control register

Address: 0x4001013C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.18 PERI_PCLK_CTL16

Programmable clock control register

Address: 0x40010140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.19 PERI_PCLK_CTL17

Programmable clock control register

Address: 0x40010144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.20 PERI_PCLK_CTL18

Programmable clock control register

Address: 0x40010148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.21 PERI_PCLK_CTL19

Programmable clock control register

Address: 0x4001014C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.22 PERI_PCLK_CTL20

Programmable clock control register

Address: 0x40010150

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.23 PERI_PCLK_CTL21

Programmable clock control register

Address: 0x40010154

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.24 PERI_PCLK_CTL22

Programmable clock control register

Address: 0x40010158

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.25 PERI_PCLK_CTL23

Programmable clock control register

Address: 0x4001015C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.26 PERI_PCLK_CTL24

Programmable clock control register

Address: 0x40010160

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.27 PERI_PCLK_CTL25

Programmable clock control register

Address: 0x40010164

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.28 PERI_PCLK_CTL26

Programmable clock control register

Address: 0x40010168

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.29 PERI_PCLK_CTL27

Programmable clock control register

Address: 0x4001016C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.30 PERI_PCLK_CTL28

Programmable clock control register

Address: 0x40010170

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.31 PERI_PCLK_CTL29

Programmable clock control register

Address: 0x40010174

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.32 PERI_PCLK_CTL30

Programmable clock control register

Address: 0x40010178

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.33 PERI_PCLK_CTL31

Programmable clock control register

Address: 0x4001017C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None		RW			
HW Access	R		None		R			
Name	SEL_TYPE [7:6]		None [5:4]		SEL_DIV [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
3 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one "clk_hf" cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 15

15.1.34 PERI_DIV_8_CTL0

Divider control register (for 8.0 divider)

Address: 0x40010200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.35 PERI_DIV_8_CTL1

Divider control register (for 8.0 divider)

Address: 0x40010204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.36 PERI_DIV_8_CTL2

Divider control register (for 8.0 divider)

Address: 0x40010208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.37 PERI_DIV_8_CTL3

Divider control register (for 8.0 divider)

Address: 0x4001020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.38 PERI_DIV_8_CTL4

Divider control register (for 8.0 divider)

Address: 0x40010210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.39 PERI_DIV_8_CTL5

Divider control register (for 8.0 divider)

Address: 0x40010214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.40 PERI_DIV_8_CTL6

Divider control register (for 8.0 divider)

Address: 0x40010218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.41 PERI_DIV_8_CTL7

Divider control register (for 8.0 divider)

Address: 0x4001021C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.42 PERI_DIV_8_CTL8

Divider control register (for 8.0 divider)

Address: 0x40010220

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.43 PERI_DIV_8_CTL9

Divider control register (for 8.0 divider)

Address: 0x40010224

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.44 PERI_DIV_8_CTL10

Divider control register (for 8.0 divider)

Address: 0x40010228

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.45 PERI_DIV_8_CTL11

Divider control register (for 8.0 divider)

Address: 0x4001022C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT8_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	INT8_DIV	Integer division by (1+INT8_DIV). Allows for integer divisions in the range [1, 256]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 256]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is resticited to even numbers in the range [2, 256]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.46 PERI_DIV_16_CTL0

Divider control register (for 16.0 divider)

Address: 0x40010300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.47 PERI_DIV_16_CTL1

Divider control register (for 16.0 divider)

Address: 0x40010304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.48 PERI_DIV_16_CTL2

Divider control register (for 16.0 divider)

Address: 0x40010308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.49 PERI_DIV_16_CTL3

Divider control register (for 16.0 divider)

Address: 0x4001030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.50 PERI_DIV_16_5_CTL0

Divider control register (for 16.5 divider)

Address: 0x40010400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.50 PERI_DIV_16_5_CTL0 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.51 PERI_DIV_16_5_CTL1

Divider control register (for 16.5 divider)

Address: 0x40010404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.51 PERI_DIV_16_5_CTL1 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.52 PERI_DIV_16_5_CTL2

Divider control register (for 16.5 divider)

Address: 0x40010408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.52 PERI_DIV_16_5_CTL2 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.53 PERI_DIV_16_5_CTL3

Divider control register (for 16.5 divider)

Address: 0x4001040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.53 PERI_DIV_16_5_CTL3 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.54 PERI_DIV_16_5_CTL4

Divider control register (for 16.5 divider)

Address: 0x40010410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.54 PERI_DIV_16_5_CTL4 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

15.1.55 PERI_TR_CTL

Trigger control register

Address: 0x40010600

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW						
HW Access	None	R						
Name	None	TR_SEL [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				TR_GROUP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	TR_COUNT [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	RW1C	R	None					
Name	TR_ACT	TR_OUT	None [29:24]					

Bits	Name	Description
31	TR_ACT	SW sets this field to '1' by to activate (set to '1') a trigger as identified by TR_SEL and TR_OUT for TR_COUNT cycles. HW sets this field to '0' when the cycle counter is decremented to "0". Note: a TR_COUNT value of 255 is a special case and trigger activation is under direct control of the TR_ACT field (the counter is not decremented). Default Value: 0
30	TR_OUT	Specifies whether trigger activation is for a specific input or ouput trigger of the trigger multiplexer. Activation of a specific input trigger, will result in activation of all output triggers that have the specific input trigger selected through their TR_OUT_CTL.SEL field. Activation of a specific output trigger, will result in activation of the specified TR_SEL output trigger only. '0': TR_SEL selection and trigger activation is for an input trigger to the trigger multiplexer. '1': TR_SEL selection and trigger activation is for an output trigger from the trigger multiplexer. Default Value: 0
23 : 16	TR_COUNT	Amount of cycles a specific trigger is activated. During activation (TR_ACT is '1'), HW decrements this field to "0" using a cycle counter. During activation, SW should not modify this register field. A value of 255 is a special case: HW does NOT decrement this field to "0" and trigger activation is under direct control of TR_ACT: when TR_ACT is '1' the trigger is activated and when TR_ACT is '0' the trigger is deactivated. Default Value: 0

15.1.55 PERI_TR_CTL (continued)

11 : 8	TR_GROUP	Specifies the trigger group. Default Value: 0
6 : 0	TR_SEL	Specifies the activated trigger when TR_ACT is '1'. TR_OUT specifies whether the activated trigger is an input trigger or output trigger to the trigger multiplexer. During activation (TR_ACT is '1'), SW should not modify this register field. If the specified trigger is not present, the trigger activation has no effect. Default Value: 0

16 ROM Table Registers

This section discusses the ROM Table registers. It lists all the registers in mapping tables, in address order.

16.1 Register Details

Register Name	Address
ROMTABLE_ADDR	0xF0000000
ROMTABLE_DID	0xF0000FCC
ROMTABLE_PID4	0xF0000FD0
ROMTABLE_PID5	0xF0000FD4
ROMTABLE_PID6	0xF0000FD8
ROMTABLE_PID7	0xF0000FDC
ROMTABLE_PID0	0xF0000FE0
ROMTABLE_PID1	0xF0000FE4
ROMTABLE_PID2	0xF0000FE8
ROMTABLE_PID3	0xF0000FEC
ROMTABLE_CID0	0xF0000FF0
ROMTABLE_CID1	0xF0000FF4
ROMTABLE_CID2	0xF0000FF8
ROMTABLE_CID3	0xF0000FFC

16.1.1 ROMTABLE_ADDR

Link to Cortex M0 ROM Table.

Address: 0xF0000000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						R	R
Name	None [7:2]						FORMAT_32BIT	PRESENT

Bits	15	14	13	12	11	10	9	8
SW Access	R				None			
HW Access	R				None			
Name	ADDR_OFFSET [15:12]				None [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	ADDR_OFFSET [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	ADDR_OFFSET [31:24]							

Bits	Name	Description
31 : 12	ADDR_OFFSET	Address offset of the Cortex-M0 ROM Table base address (0xe00f:f000) wrt. Cypress chip specific ROM Table base address (0xf000:0000). ADDR_OFFSET[19:0] = 0xe00f:f - 0xf000:0 = 0xf00f:f. Default Value: 983295
1	FORMAT_32BIT	ROM Table format: '0: 8-bit format. '1': 32-bit format. Default Value: 1
0	PRESENT	Entry present. Default Value: 1

16.1.2 ROMTABLE_DID

Device Type Identifier register.

Address: 0xF0000FCC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 1

16.1.3 ROMTABLE_PID4

Peripheral Identification Register 4.

Address: 0xF0000FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	COUNT [7:4]				JEP_CONTINUATION [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	COUNT	Size of ROM Table is 2^COUNT * 4 KByte. Default Value: 0
3 : 0	JEP_CONTINUATION	JEP106 continuation code. This value is product specific and specified as part of the product definition in the CPUSS.JEPCONTINUATION parameter. Default Value: Undefined

16.1.4 ROMTABLE_PID5

Peripheral Identification Register 5.

Address: 0xF0000FD4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

16.1.5 ROMTABLE_PID6

Peripheral Identification Register 6.

Address: 0xF0000FD8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

16.1.6 ROMTABLE_PID7

Peripheral Identification Register 7.

Address: 0xF0000FDC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

16.1.7 ROMTABLE_PID0

Peripheral Identification Register 0.

Address: 0xF0000FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	PN_MIN [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	PN_MIN	JEP106 part number. 4 lsbs of CPUSS.PARTNUMBER parameter. These part numbers are maintained in spec 40-9500. Default Value: Undefined

16.1.8 ROMTABLE_PID1

Peripheral Identification Register 1.

Address: 0xF0000FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	JEPID_MIN [7:4]				PN_MAJ [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	JEPID_MIN	JEP106 vendor id. 4 lsbs of CPUSS.JEPID parameter. This number is maintained in spec 40-9500. Default Value: Undefined
3 : 0	PN_MAJ	JEP106 part number. 4 msbs of CPUSS.PARTNUMBER parameter. These part numbers are maintained in spec 40-9500. Default Value: Undefined

16.1.9 ROMTABLE_PID2

Peripheral Identification Register 2.

Address: 0xF0000FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				None	R		
HW Access	R				None	R		
Name	REV [7:4]				None	JEPID_MAJ [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	REV	Major REVision number (chip specific). Identifies the design iteration of the component. For first tape out: 0x1. This field is implemented in RTL by an ECO-able tie-off structure and is incremented on subsequent tape outs. Default Value: Undefined
2 : 0	JEPID_MAJ	JEP106 vendor id. 4 msbs of CPUSS.JEPID parameter. This number is maintained in spec 40-9500. Default Value: Undefined

16.1.10 ROMTABLE_PID3

Peripheral Identification Register 3.

Address: 0xF0000FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	REV_AND [7:4]				CM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	REV_AND	Minor REVision number (chip specific). For first tape out: 0x1. This field is implemented in RTL by an ECO-able tie-off structure and is incremented on subsequent tape outs. Default Value: Undefined
3 : 0	CM	Customer modified field. This field is used to track modifications to the original component design as a result of componenet IP reuse. Default Value: 0

16.1.11 ROMTABLE_CID0

Component Identification Register 0.

Address: 0xF0000FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 0 of 4-byte component identification 0xB105:100D. Default Value: 13

16.1.12 ROMTABLE_CID1

Component Identification Register 1.

Address: 0xF0000FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 1 of 4-byte component identification 0xB105:100D. Component class: "ROM Table". Default Value: 16

16.1.13 ROMTABLE_CID2

Component Identification Register 2.

Address: 0xF0000FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 2 of 4-byte component identification 0xB105:100D. Default Value: 5

16.1.14 ROMTABLE_CID3

Component Identification Register 3.

Address: 0xF0000FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 3 of 4-byte component identification 0xB105:100D. Default Value: 177

17 SAR Registers

This section discusses the SAR registers. It lists all the registers in mapping tables, in address order.

17.1 Register Details

Register Name	Address
SAR0_CTRL	0x403A0000
SAR0_SAMPLE_CTRL	0x403A0004
SAR0_SAMPLE_TIME01	0x403A0010
SAR0_SAMPLE_TIME23	0x403A0014
SAR0_RANGE_THRES	0x403A0018
SAR0_RANGE_COND	0x403A001C
SAR0_CHAN_EN	0x403A0020
SAR0_START_CTRL	0x403A0024
SAR0_DFT_CTRL	0x403A0030
SAR0_CHAN_CONFIG0	0x403A0080
SAR0_CHAN_CONFIG1	0x403A0084
SAR0_CHAN_CONFIG2	0x403A0088
SAR0_CHAN_CONFIG3	0x403A008C
SAR0_CHAN_CONFIG4	0x403A0090
SAR0_CHAN_CONFIG5	0x403A0094
SAR0_CHAN_CONFIG6	0x403A0098
SAR0_CHAN_CONFIG7	0x403A009C
SAR0_CHAN_CONFIG8	0x403A00A0
SAR0_CHAN_CONFIG9	0x403A00A4
SAR0_CHAN_CONFIG10	0x403A00A8
SAR0_CHAN_CONFIG11	0x403A00AC
SAR0_CHAN_CONFIG12	0x403A00B0
SAR0_CHAN_CONFIG13	0x403A00B4
SAR0_CHAN_CONFIG14	0x403A00B8
SAR0_CHAN_CONFIG15	0x403A00BC
SAR0_CHAN_WORK0	0x403A0100
SAR0_CHAN_WORK1	0x403A0104

Register Name	Address
SAR0_CHAN_WORK2	0x403A0108
SAR0_CHAN_WORK3	0x403A010C
SAR0_CHAN_WORK4	0x403A0110
SAR0_CHAN_WORK5	0x403A0114
SAR0_CHAN_WORK6	0x403A0118
SAR0_CHAN_WORK7	0x403A011C
SAR0_CHAN_WORK8	0x403A0120
SAR0_CHAN_WORK9	0x403A0124
SAR0_CHAN_WORK10	0x403A0128
SAR0_CHAN_WORK11	0x403A012C
SAR0_CHAN_WORK12	0x403A0130
SAR0_CHAN_WORK13	0x403A0134
SAR0_CHAN_WORK14	0x403A0138
SAR0_CHAN_WORK15	0x403A013C
SAR0_CHAN_RESULT0	0x403A0180
SAR0_CHAN_RESULT1	0x403A0184
SAR0_CHAN_RESULT2	0x403A0188
SAR0_CHAN_RESULT3	0x403A018C
SAR0_CHAN_RESULT4	0x403A0190
SAR0_CHAN_RESULT5	0x403A0194
SAR0_CHAN_RESULT6	0x403A0198
SAR0_CHAN_RESULT7	0x403A019C
SAR0_CHAN_RESULT8	0x403A01A0
SAR0_CHAN_RESULT9	0x403A01A4
SAR0_CHAN_RESULT10	0x403A01A8
SAR0_CHAN_RESULT11	0x403A01AC
SAR0_CHAN_RESULT12	0x403A01B0
SAR0_CHAN_RESULT13	0x403A01B4
SAR0_CHAN_RESULT14	0x403A01B8
SAR0_CHAN_RESULT15	0x403A01BC
SAR0_CHAN_WORK_VALID	0x403A0200
SAR0_CHAN_RESULT_VALID	0x403A0204
SAR0_STATUS	0x403A0208
SAR0_AVG_STAT	0x403A020C
SAR0_INTR	0x403A0210
SAR0_INTR_SET	0x403A0214
SAR0_INTR_MASK	0x403A0218
SAR0_INTR_MASKED	0x403A021C
SAR0_SATURATE_INTR	0x403A0220
SAR0_SATURATE_INTR_SET	0x403A0224
SAR0_SATURATE_INTR_MASK	0x403A0228
SAR0_SATURATE_INTR_MASKED	0x403A022C

Register Name	Address
SAR0_RANGE_INTR	0x403A0230
SAR0_RANGE_INTR_SET	0x403A0234
SAR0_RANGE_INTR_MASK	0x403A0238
SAR0_RANGE_INTR_MASKED	0x403A023C
SAR0_INTR_CAUSE	0x403A0240
SAR0_INJ_CHAN_CONFIG	0x403A0280
SAR0_INJ_RESULT	0x403A0290
SAR0_MUX_SWITCH0	0x403A0300
SAR0_MUX_SWITCH_CLEAR0	0x403A0304
SAR0_MUX_SWITCH1	0x403A0308
SAR0_MUX_SWITCH_CLEAR1	0x403A030C
SAR0_MUX_SWITCH_HW_CTRL	0x403A0340
SAR0_MUX_SWITCH_STATUS	0x403A0348
SAR0_PUMP_CTRL	0x403A0380
SAR0_ANA_TRIM	0x403A0F00
SAR0_WOUNDING	0x403A0F04

17.1.1 SAR0_CTRL

Analog control register.

Address: 0x403A0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW			None			
HW Access	R	R			None			
Name	VREF_BYP_CAP_EN	VREF_SEL [6:4]			None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW	None	RW			None
HW Access	R		R	None	R			None
Name	PWR_CTRL_VREF [15:14]		SAR_HW_CTRL_NEGVREF	None	NEG_SEL [11:9]			None

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	RW			
HW Access	None			R	R			
Name	None [23:21]			BOOSTPUMP_EN	SPARE [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW	RW	RW	None	RW	
HW Access	R	R	R	R	R	None	R	
Name	ENABLED	SWITCH_DISABLE	DSI_MODE	DSI_SYNC_CONFIG	DEEPSLEEP_ON	None	ICONT_LV [25:24]	

Bits	Name	Description
31	ENABLED	Before enabling always make sure the SAR is idle (STATUS.BUSY==0) - 0: SAR IP disabled (put analog in power down and stop clocks), also can clear FW_TRIGGER and INJ_START_EN (if not tailgaiting) on write. - 1: SAR IP enabled. Default Value: 0
30	SWITCH_DISABLE	Disable SAR sequencer from enabling routing switches (note DSI and firmware can always close switches independent of this control) - 0: Normal mode, SAR sequencer changes switches according to pin address in channel configurations - 1: Switches disabled, SAR sequencer does not enable any switches, it is the responsibility of the firmware or UDBs (through DSI) to set the switches to route the signal to be converted through the SARMUX Default Value: 0

17.1.1 SAR0_CTRL (continued)

29	DSI_MODE	SAR sequencer takes configuration from DSI signals (note this also has the same effect as SWITCH_DISABLE==1) - 0: Normal mode, SAR sequencer operates according to CHAN_EN enables and CHAN_CONFIG channel configurations - 1: CHAN_EN, INJ_START_EN and channel configurations in CHAN_CONFIG and INJ_CHAN_CONFIG are ignored Default Value: 0
28	DSI_SYNC_CONFIG	- 0: bypass clock domain synchronisation of the DSI config signals. - 1: synchronize the DSI config signals to peripheral clock domain. Default Value: 1
27	DEEPSLEEP_ON	- 0: SARMUX IP disabled off during DeepSleep power mode - 1: SARMUX IP remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0
25 : 24	ICONT_LV	SARADC low power mode. Default Value: 0 **0x0: NORMAL_PWR:** normal power (default), max clk_sar is 18MHz. **0x1: HALF_PWR:** 1/2 power mode, max clk_sar is 9MHz. **0x2: MORE_PWR:** 1.333 power mode, max clk_sar is 18MHz. **0x3: QUARTER_PWR:** 1/4 power mode, max clk_sar is 4.5MHz.
20	BOOSTPUMP_EN	SARADC internal pump: 0=disabled: pump output is VDDA, 1=enabled: pump output is boosted. Default Value: 0
19 : 16	SPARE	Spare controls, not yet designated, for late changes done with an ECO Default Value: 0
15 : 14	PWR_CTRL_VREF	VREF buffer low power mode. Default Value: 0 **0x0: NORMAL_PWR:** normal power (default), bypass cap, max clk_sar is 18MHz. **0x1: HALF_PWR:** deprecated **0x2: THIRD_PWR:** Invalid for PSoC4A, otherwise 2X power, no bypass cap, max clk_sar is 1.8MHz **0x3: QUARTER_PWR:** deprecated
13	SAR_HW_CTRL_NEGVREF	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for VREF to NEG switch. Default Value: 0
11 : 9	NEG_SEL	SARADC internal NEG selection for Single ended conversion Default Value: 0 **0x0: VSSA_KELVIN:** NEG input of SARADC is connected to "vssa_kelvin", gives more precision around zero. Note this opens both SARADC internal switches, therefore use this value to insert a break-before-make cycle on those switches when SWITCH_DISABLE is high.

17.1.1 SAR0_CTRL (continued)

		0x1: ART_VSSA: NEG input of SARADC is connected to VSSA in AROUTE close to the SARADC **0x2: P1:** NEG input of SARADC is connected to P1 pin of SARMUX **0x3: P3:** NEG input of SARADC is connected to P3 pin of SARMUX **0x4: P5:** NEG input of SARADC is connected to P5 pin of SARMUX **0x5: P7:** NEG input of SARADC is connected to P7 pin of SARMUX **0x6: ACORE:** NEG input of SARADC is connected to an ACORE in AROUTE **0x7: VREF:** NEG input of SARADC is shorted with VREF input of SARADC.
7	VREF_BYP_CAP_EN	VREF bypass cap enable for when VREF buffer is on Default Value: 0
6 : 4	VREF_SEL	SARADC internal VREF selection. Default Value: 0 **0x0: VREF0:** VREF0 from PRB (VREF buffer on) **0x1: VREF1:** VREF1 from PRB (VREF buffer on) **0x2: VREF2:** VREF2 from PRB (VREF buffer on) **0x3: VREF_AROUTE:** VREF from AROUTE (VREF buffer on) **0x4: VBGR:** 1.024V from BandGap (VREF buffer on) **0x5: VREF_EXT:** External precision Vref direct from a pin (low impedance path). **0x6: VDDA_DIV_2:** Vdda/2 (VREF buffer on) **0x7: VDDA:** Vdda.

17.1.2 SAR0_SAMPLE_CTRL

Sample control register.

Address: 0x403A0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW			RW	RW	RW	RW
HW Access	R	R			R	R	R	R
Name	AVG_SHIFT	AVG_CNT [6:4]			DIFFERENTIAL_SIGNED	SINGLE_ENDED_SIGNED	LEFT_ALIGN	SUB_RESOLUTION

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [23:20]				DSI_SYNC_TRIGGER	DSI_TRIGGER_LEVEL	DSI_TRIGGER_EN	CONTINU-OUS

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	EOS_DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	EOS_DSI_OUT_EN	Enable to output EOS_INTR to DSI. When enabled each time EOS_INTR is set by the hardware also a pulse is send on the dsi_eos signal. Default Value: 0
19	DSI_SYNC_TRIGGER	- 0: bypass clock domain synchronisation of the DSI trigger signal. - 1: synchronize the DSI trigger signal to the SAR clock domain, if needed an edge detect is done in the peripheral clock domain. Default Value: 1
18	DSI_TRIGGER_LEVEL	- 0: DSI trigger signal is a pulse input, a positive edge detected on the DSI trigger signal triggers a new scan. - 1: DSI trigger signal is a level input, as long as the DSI trigger signal remains high the SAR will do continuous scans. Default Value: 0
17	DSI_TRIGGER_EN	- 0: firmware trigger only: disable hardware (DSI) trigger. - 1: enable hardware (DSI) trigger (e.g. from TCPWM, GPIO or UDB). Default Value: 0

17.1.2 SAR0_SAMPLE_CTRL (continued)

16	CONTINUOUS	- 0: Wait for next FW_TRIGGER (one shot) or hardware (DSI) trigger (e.g. from TPWM for periodic triggering) before scanning enabled channels. - 1: Continuously scan enabled channels, ignore triggers. Default Value: 0
7	AVG_SHIFT	Averaging shifting: after averaging the result is shifted right to fit in the sample resolution. For averaging the sample resolution is the highest resolution allowed by wounding. Default Value: 0
6 : 4	AVG_CNT	Averaging Count for channels that have over sampling enabled (AVG_EN). A channel will be sampled back to back (1<<(AVG_CNT+1)) = [2..256] times before the result is stored and the next enabled channel is sampled (1st order accumulate and dump filter). If shifting is not enabled (AVG_SHIFT=0) then the result is forced to shift right so that is fits in 16 bits, so right shift is done by max(0,AVG_CNT-3). Default Value: 0
3	DIFFERENTIAL_SIGNED	Output data from a differential conversion as a signed value Default Value: 1 **0x0: UNSIGNED:** result data is unsigned (zero extended if needed) **0x1: SIGNED:** Default: result data is signed (sign extended if needed)
2	SINGLE_ENDED_SIGNED	Output data from a single ended conversion as a signed value Default Value: 0 **0x0: UNSIGNED:** Default: result data is unsigned (zero extended if needed) **0x1: SIGNED:** result data is signed (sign extended if needed)
1	LEFT_ALIGN	Left align data in data[15:0], default data is right aligned in data[11:0], with sign extension to 16 bits if the channel is differential. Default Value: 0
0	SUB_RESOLUTION	Conversion resolution for channels that have sub-resolution enabled (RESOLUTION=1) (otherwise resolution is 12-bit). Default Value: 0 **0x0: 8B:** 8-bit. **0x1: 10B:** 10-bit.

17.1.3 SAR0_SAMPLE_TIME01

Sample time specification ST0 and ST1

Address: 0x403A0010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						SAMPLE_TIME0 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						SAMPLE_TIME1 [25:24]	

Bits	Name	Description
25 : 16	SAMPLE_TIME1	Sample time1 Default Value: 4
9 : 0	SAMPLE_TIME0	Sample time0 (aperture) in ADC clock cycles. Note that actual sample time is half a clock less than specified here. The minimum sample time is 194ns, which is 3.5 cycles (4 in this field) with an 18MHz clock. Minimum legal value in this register is 2. Default Value: 4

17.1.4 SAR0_SAMPLE_TIME23

Sample time specification ST2 and ST3

Address: 0x403A0014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME2 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						SAMPLE_TIME2 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME3 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						SAMPLE_TIME3 [25:24]	

Bits	Name	Description
25 : 16	SAMPLE_TIME3	Sample time3 Default Value: 4
9 : 0	SAMPLE_TIME2	Sample time2 Default Value: 4

17.1.5 SAR0_RANGE_THRES

Global range detect threshold register.

Address: 0x403A0018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RANGE_LOW [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RANGE_LOW [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	RANGE_HIGH [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	RANGE_HIGH [31:24]							

Bits	Name	Description
31 : 16	RANGE_HIGH	High threshold for range detect. Default Value: 0
15 : 0	RANGE_LOW	Low threshold for range detect. Default Value: 0

17.1.6 SAR0_RANGE_COND

Global range detect mode register.

Address: 0x403A001C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	RANGE_COND [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	RANGE_COND	Range condition select. Default Value: 0 **0x0: BELOW:** result < RANGE_LOW **0x1: INSIDE:** RANGE_LOW <= result < RANGE_HIGH **0x2: ABOVE:** RANGE_HIGH <= result **0x3: OUTSIDE:** result < RANGE_LOW || RANGE_HIGH <= result

17.1.7 SAR0_CHAN_EN

Enable bits for the channels

Address: 0x403A0020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CHAN_EN [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CHAN_EN [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_EN	Channel enable. - 0: the corresponding channel is disabled. - 1: the corresponding channel is enabled, it will be included in the next scan. Default Value: 0

17.1.8 SAR0_START_CTRL

Start control register (firmware trigger).

Address: 0x403A0024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1S
HW Access	None							RW1C
Name	None [7:1]							FW_TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	FW_TRIGGER	When firmware writes a 1 here it will trigger the next scan of enabled channels, hardware clears this bit when the scan started with this trigger is completed. If scanning continuously the trigger is ignored and hardware clears this bit after the next scan is done. This bit is also cleared when the SAR is disabled. Default Value: 0

17.1.9 SAR0_DFT_CTRL

DFT control register.

Address: 0x403A0030

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						HIZ	DLY_INC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			RW			
HW Access	None	R			R			
Name	None	DFT_OUTC [22:20]			DFT_INC [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW	RW			
HW Access	R	None	R	R	R			
Name	ADFT_OVERRIDE	None	DCEN	EN_CSEL_DFT	SEL_CSEL_DFT [27:24]			

Bits	Name	Description
31	ADFT_OVERRIDE	During deepsleep/ hibernate mode keep SARMUX active, i.e. do not open all switches (disconnect), to be used for ADFT Default Value: 0
29	DCEN	Delay Control Enable for latch. - 0: doubles the latch enable time. - 1: normal latch enable time (default). Default Value: 0
28	EN_CSEL_DFT	Mux select signal for DAC control Default Value: 0
27 : 24	SEL_CSEL_DFT	Usage 1: DFT bits for DAC array Usage 2: For [0]=1 (when dcen=0): Delay timing for latch enable increased by 20% [1]=1: comparator preamp power level increased by 25% Default Value: 0
22 : 20	DFT_OUTC	DFT control for preamp outputs Default Value: 0
19 : 16	DFT_INC	DFT control for preamp inputs Default Value: 0

17.1.9 SAR0_DFT_CTRL (continued)

1	HIZ	DFT control for getting higher input impedance, must be 1 (0 is deprecated) Default Value: 1
0	DLY_INC	DFT control: Control for delay circuits on sampling phase, =1 doubes the non-overlap delay Default Value: 0

17.1.10 SAR0_CHAN_CONFIG0

Channel configuration register.

Address: 0x403A0080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.10 SAR0_CHAN_CONFIG0 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.11 SAR0_CHAN_CONFIG1

Channel configuration register.

Address: 0x403A0084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.11 SAR0_CHAN_CONFIG1 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.12 SAR0_CHAN_CONFIG2

Channel configuration register.

Address: 0x403A0088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.12 SAR0_CHAN_CONFIG2 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.13 SAR0_CHAN_CONFIG3

Channel configuration register.

Address: 0x403A008C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.13 SAR0_CHAN_CONFIG3 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.14 SAR0_CHAN_CONFIG4

Channel configuration register.

Address: 0x403A0090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.14 SAR0_CHAN_CONFIG4 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.15 SAR0_CHAN_CONFIG5

Channel configuration register.

Address: 0x403A0094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.15 SAR0_CHAN_CONFIG5 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.16 SAR0_CHAN_CONFIG6

Channel configuration register.

Address: 0x403A0098

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.16 SAR0_CHAN_CONFIG6 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.17 SAR0_CHAN_CONFIG7

Channel configuration register.

Address: 0x403A009C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.17 SAR0_CHAN_CONFIG7 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.18 SAR0_CHAN_CONFIG8

Channel configuration register.

Address: 0x403A00A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.18 SAR0_CHAN_CONFIG8 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.19 SAR0_CHAN_CONFIG9

Channel configuration register.

Address: 0x403A00A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.19 SAR0_CHAN_CONFIG9 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.20 SAR0_CHAN_CONFIG10

Channel configuration register.

Address: 0x403A00A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.20 SAR0_CHAN_CONFIG10 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.21 SAR0_CHAN_CONFIG11

Channel configuration register.

Address: 0x403A00AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.21 SAR0_CHAN_CONFIG11 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.22 SAR0_CHAN_CONFIG12

Channel configuration register.

Address: 0x403A00B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.22 SAR0_CHAN_CONFIG12 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.23 SAR0_CHAN_CONFIG13

Channel configuration register.

Address: 0x403A00B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.23 SAR0_CHAN_CONFIG13 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.24 SAR0_CHAN_CONFIG14

Channel configuration register.

Address: 0x403A00B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.24 SAR0_CHAN_CONFIG14 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.25 SAR0_CHAN_CONFIG15

Channel configuration register.

Address: 0x403A00BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLU-TION	DIFFEREN TIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_ EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formating), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by wounding) is used for this channel. Default Value: 0

17.1.25 SAR0_CHAN_CONFIG15 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding). **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x5: AROUTE_VIRT2:** AROUTE virtual port2 (VPORT2) **0x6: AROUTE_VIRT1:** AROUTE virtual port1 (VPORT1) **0x7: SARMUX_VIRT:** SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.26 SAR0_CHAN_WORK0

Channel working data register

Address: 0x403A0100

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.27 SAR0_CHAN_WORK1

Channel working data register

Address: 0x403A0104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.28 SAR0_CHAN_WORK2

Channel working data register

Address: 0x403A0108

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.29 SAR0_CHAN_WORK3

Channel working data register

Address: 0x403A010C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.30 SAR0_CHAN_WORK4

Channel working data register

Address: 0x403A0110

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.31 SAR0_CHAN_WORK5

Channel working data register

Address: 0x403A0114

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.32 SAR0_CHAN_WORK6

Channel working data register

Address: 0x403A0118

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.33 SAR0_CHAN_WORK7

Channel working data register

Address: 0x403A011C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.34 SAR0_CHAN_WORK8

Channel working data register

Address: 0x403A0120

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.35 SAR0_CHAN_WORK9

Channel working data register

Address: 0x403A0124

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.36 SAR0_CHAN_WORK10

Channel working data register

Address: 0x403A0128

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.37 SAR0_CHAN_WORK11

Channel working data register

Address: 0x403A012C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.38 SAR0_CHAN_WORK12

Channel working data register

Address: 0x403A0130

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.39 SAR0_CHAN_WORK13

Channel working data register

Address: 0x403A0134

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.40 SAR0_CHAN_WORK14

Channel working data register

Address: 0x403A0138

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.41 SAR0_CHAN_WORK15

Channel working data register

Address: 0x403A013C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.42 SAR0_CHAN_RESULT0

Channel result data register

Address: 0x403A0180

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.43 SAR0_CHAN_RESULT1

Channel result data register

Address: 0x403A0184

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.44 SAR0_CHAN_RESULT2

Channel result data register

Address: 0x403A0188

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.45 SAR0_CHAN_RESULT3

Channel result data register

Address: 0x403A018C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.46 SAR0_CHAN_RESULT4

Channel result data register

Address: 0x403A0190

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.47 SAR0_CHAN_RESULT5

Channel result data register

Address: 0x403A0194

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.48 SAR0_CHAN_RESULT6

Channel result data register

Address: 0x403A0198

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.49 SAR0_CHAN_RESULT7

Channel result data register

Address: 0x403A019C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.50 SAR0_CHAN_RESULT8

Channel result data register

Address: 0x403A01A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.51 SAR0_CHAN_RESULT9

Channel result data register

Address: 0x403A01A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.52 SAR0_CHAN_RESULT10

Channel result data register

Address: 0x403A01A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.53 SAR0_CHAN_RESULT11

Channel result data register

Address: 0x403A01AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.54 SAR0_CHAN_RESULT12

Channel result data register

Address: 0x403A01B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.55 SAR0_CHAN_RESULT13

Channel result data register

Address: 0x403A01B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.56 SAR0_CHAN_RESULT14

Channel result data register

Address: 0x403A01B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.57 SAR0_CHAN_RESULT15

Channel result data register

Address: 0x403A01BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RESULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RESULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.58 SAR0_CHAN_WORK_VALID

Channel working data register valid bits

Address: 0x403A0200

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_VALID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_VALID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_WORK_VALID	If set the corresponding WORK data is valid, i.e. was already sampled during the current scan. Default Value: 0

17.1.59 SAR0_CHAN_RESULT_VALID

Channel result data register valid bits

Address: 0x403A0204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_VALID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_VALID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_RESULT_VALID	If set the corresponding RESULT data is valid, i.e. was sampled during the last scan. Default Value: 0

17.1.60 SAR0_STATUS

Current status of internal SAR registers (mostly for debug)

Address: 0x403A0208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CUR_CHAN [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	BUSY	SW_VREF_NEG	None [29:24]					

Bits	Name	Description
31	BUSY	If high then the SAR is busy with a conversion. This bit is always high when CONTINUOUS is set. Firmware should wait for this bit to be low before putting the SAR in power down. Default Value: 0
30	SW_VREF_NEG	the current switch status, including DSI and sequencer controls, of the switch in the SARADC that shorts NEG with VREF input (see NEG_SEL). Default Value: 0
4 : 0	CUR_CHAN	current channel being sampled (channel 16 indicates the injection channel), only valid if BUSY. Default Value: 0

17.1.61 SAR0_AVG_STAT

Current averaging status (for debug)

Address: 0x403A020C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	CUR_AVG_ACCU [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CUR_AVG_ACCU [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				CUR_AVG_ACCU [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	CUR_AVG_CNT [31:24]							

Bits	Name	Description
31 : 24	CUR_AVG_CNT	the current value of the averaging counter. Note that the value shown is updated after the sampling time and therefore runs ahead of the accumulator update. Default Value: 0
19 : 0	CUR_AVG_ACCU	the current value of the averaging accumulator Default Value: 0

17.1.62 SAR0_INTR

Interrupt request register.

Address: 0x403A0210

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	INJ_COLLISION_INTR	INJ_RANGE_INTR	INJ_SATURATE_INTR	INJ_EOC_INTR	DSI_COLLISION_INTR	FW_COLLISION_INTR	OVERFLOW_INTR	EOS_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_INTR	Injection Collision Interrupt: hardware sets this interrupt when the injection trigger signal is asserted (INJ_START_EN==1 && INJ_TAILGATING==0) while the SAR is BUSY. Raising this interrupt is delayed to when the sampling of the injection channel has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the injection channel was sampled later than was intended. Write with '1' to clear bit. Default Value: 0
6	INJ_RANGE_INTR	Injection Range detect Interrupt: hardware sets this interrupt if the injection conversion result (after averaging) met the condition specified by the SAR_RANGE registers. Write with '1' to clear bit. Default Value: 0
5	INJ_SATURATE_INTR	Injection Saturation Interrupt: hardware sets this interrupt if an injection conversion result (before averaging) is either 0x000 or 0xFFF (for 12-bit resolution), this is an indication that the ADC likely saturated. Write with '1' to clear bit. Default Value: 0
4	INJ_EOC_INTR	Injection End of Conversion Interrupt: hardware sets this interrupt after completing the conversion for the injection channel (irrespective of if tailgating was used). Write with '1' to clear bit. Default Value: 0

17.1.62 SAR0_INTR (continued)

3	DSI_COLLISION_INTR	DSI Collision Interrupt: hardware sets this interrupt when the DSI trigger signal is asserted while the SAR is BUSY. Raising this interrupt is delayed to when the scan caused by the DSI trigger has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the channels were sampled later than was intended (jitter). Write with '1' to clear bit. Default Value: 0
2	FW_COLLISION_INTR	Firmware Collision Interrupt: hardware sets this interrupt when FW_TRIGGER is asserted while the SAR is BUSY. Raising this interrupt is delayed to when the scan caused by the FW_TRIGGER has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the channels were sampled later than was intended (jitter). Write with '1' to clear bit. Default Value: 0
1	OVERFLOW_INTR	Overflow Interrupt: hardware sets this interrupt when it sets a new EOS_INTR while that bit was not yet cleared by the firmware. Write with '1' to clear bit. Default Value: 0
0	EOS_INTR	End Of Scan Interrupt: hardware sets this interrupt after completing a scan of all the enabled channels. Write with '1' to clear bit. Default Value: 0

17.1.63 SAR0_INTR_SET

Interrupt set request register

Address: 0x403A0214

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	INJ_COLLISION_SET	INJ_RANGE_SET	INJ_SATURATE_SET	INJ_EOC_SET	DSI_COLLISION_SET	FW_COLLISION_SET	OVERFLOW_SET	EOS_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	INJ_RANGE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	INJ_SATURATE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	INJ_EOC_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	DSI_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	FW_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	OVERFLOW_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.63 SAR0_INTR_SET (continued)

0	EOS_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.64 SAR0_INTR_MASK

Interrupt mask register.

Address: 0x403A0218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INJ_COLLISION_MASK	INJ_RANGE_MASK	INJ_SATURATE_MASK	INJ_EOC_MASK	DSI_COLLISION_MASK	FW_COLLISION_MASK	OVERFLOW_MASK	EOS_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	INJ_RANGE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	INJ_SATURATE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	INJ_EOC_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	DSI_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	FW_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	OVERFLOW_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.64 SAR0_INTR_MASK (continued)

0	EOS_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.65 SAR0_INTR_MASKED

Interrupt masked request register

Address: 0x403A021C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	INJ_COLLISION_MASKED	INJ_RANGE_MASKED	INJ_SATURATE_MASKED	INJ_EOC_MASKED	DSI_COLLISION_MASKED	FW_COLLISION_MASKED	OVERFLOW_MASKED	EOS_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
6	INJ_RANGE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
5	INJ_SATURATE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
4	INJ_EOC_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
3	DSI_COLLISION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
2	FW_COLLISION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
1	OVERFLOW_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.65 SAR0_INTR_MASKED (continued)

0	EOS_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.66 SAR0_SATURATE_INTR

Saturate interrupt request register.

Address: 0x403A0220

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	SATURATE_INTR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	RW1S							
Name	SATURATE_INTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_INTR	Saturate Interrupt: hardware sets this interrupt for each channel if a conversion result (before averaging) of that channel is either 0x000 or 0xFFF (for 12-bit resolution), this is an indication that the ADC likely saturated. Write with '1' to clear bit. Default Value: 0

17.1.67 SAR0_SATURATE_INTR_SET

Saturate interrupt set request register

Address: 0x403A0224

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	SATURATE_SET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	A							
Name	SATURATE_SET [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.68 SAR0_SATURATE_INTR_MASK

Saturate interrupt mask register.

Address: 0x403A0228

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SATURATE_MASK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	SATURATE_MASK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.69 SAR0_SATURATE_INTR_MASKED

Saturate interrupt masked request register

Address: 0x403A022C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	SATURATE_MASKED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	SATURATE_MASKED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.70 SAR0_RANGE_INTR

Range detect interrupt request register.

Address: 0x403A0230

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	RANGE_INTR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	RW1S							
Name	RANGE_INTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_INTR	Range detect Interrupt: hardware sets this interrupt for each channel if the conversion result (after averaging) of that channel met the condition specified by the SAR_RANGE registers. Write with '1' to clear bit. Default Value: 0

17.1.71 SAR0_RANGE_INTR_SET

Range detect interrupt set request register

Address: 0x403A0234

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	RANGE_SET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	A							
Name	RANGE_SET [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.72 SAR0_RANGE_INTR_MASK

Range detect interrupt mask register.

Address: 0x403A0238

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RANGE_MASK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RANGE_MASK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.73 SAR0_RANGE_INTR_MASKED

Range interrupt masked request register

Address: 0x403A023C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RANGE_MASKED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RANGE_MASKED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.74 SAR0_INTR_CAUSE

Interrupt cause register

Address: 0x403A0240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	INJ_COLLISION_MASKED_MIR	INJ_RANGE_MASKED_MIR	INJ_SATURATE_MASKED_MIR	INJ_EOC_MASKED_MIR	DSI_COLLISION_MASKED_MIR	FW_COLLISION_MASKED_MIR	OVERFLOW_MASKED_MIR	EOS_MASKED_MIR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	RANGE_MASKED_RED	SATURATE_MASKED_RED	None [29:24]					

Bits	Name	Description
31	RANGE_MASKED_RED	Reduction OR of all SAR_RANGE_INTR_MASKED bits Default Value: 0
30	SATURATE_MASKED_RED	Reduction OR of all SAR_SATURATION_INTR_MASKED bits Default Value: 0
7	INJ_COLLISION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
6	INJ_RANGE_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
5	INJ_SATURATE_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
4	INJ_EOC_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0

17.1.74 SAR0_INTR_CAUSE (continued)

3	DSI_COLLISION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
2	FW_COLLISION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
1	OVERFLOW_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
0	EOS_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0

17.1.75 SAR0_INJ_CHAN_CONFIG

Injection channel configuration register.

Address: 0x403A0280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	INJ_PORT_ADDR [6:4]			None	INJ_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		INJ_SAMPLE_TIME_SEL [13:12]		None	INJ_AVG_EN	INJ_RESOLUTION	INJ_DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	RW	None					
HW Access	RW1C	R	None					
Name	INJ_START_EN	INJ_TAILGATING	None [29:24]					

Bits	Name	Description
31	INJ_START_EN	Set by firmware to enable the injection channel. If INJ_TAILGATING is not set this bit also functions as trigger for this channel. Cleared by hardware after this channel has been sampled (i.e. this channel is always one shot even if CONTINUOUS is set). Also cleared if the SAR is disabled. Default Value: 0
30	INJ_TAILGATING	Injection channel tailgating. - 0: no tailgating for this channel, SAR is immediately triggered when the INJ_START_EN bit is set if the SAR is not busy. If the SAR is busy, the INJ channel addressed pin is sampled at the end of the current scan. - 1: injection channel tailgating. The addressed pin is sampled after the next trigger and after all enabled channels have been scanned. Default Value: 0
13 : 12	INJ_SAMPLE_TIME_SEL	Injection sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	INJ_AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0

17.1.75 SAR0_INJ_CHAN_CONFIG (continued)

9	INJ_RESOLUTION	Resolution for this channel. Default Value: 0 **0x0: 12B:** 12-bit resolution is used for this channel. **0x1: SUBRES:** The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	INJ_DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (INJ_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	INJ_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 **0x0: SARMUX:** SARMUX pins. **0x1: CTB0:** CTB0 **0x2: CTB1:** CTB1 **0x3: CTB2:** CTB2 **0x4: CTB3:** CTB3 **0x6: AROUTE_VIRT:** AROUTE virtual port **0x7: SARMUX_VIRT:** SARMUX virtual port
2 : 0	INJ_PIN_ADDR	Address of the pin to be sampled by this injection channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. Default Value: 0

17.1.76 SAR0_INJ_RESULT

Injection channel result register

Address: 0x403A0290

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	INJ_RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	INJ_RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	R	None			
HW Access	W	W	W	W	None			
Name	INJ_EOC_INTR_MIR	INJ_RANGE_INTR_MIR	INJ_SATURATE_INTR_MIR	INJ_COLLISION_INTR_MIR	None [27:24]			

Bits	Name	Description
31	INJ_EOC_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
30	INJ_RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
29	INJ_SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
28	INJ_COLLISION_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
15 : 0	INJ_RESULT	SAR conversion result of the channel. Default Value: Undefined

17.1.77 SAR0_MUX_SWITCH0

SARMUX Firmware switch controls

Address: 0x403A0300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_FW_P7_VPLUS	MUX_FW_P6_VPLUS	MUX_FW_P5_VPLUS	MUX_FW_P4_VPLUS	MUX_FW_P3_VPLUS	MUX_FW_P2_VPLUS	MUX_FW_P1_VPLUS	MUX_FW_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_FW_P7_VMINUS	MUX_FW_P6_VMINUS	MUX_FW_P5_VMINUS	MUX_FW_P4_VMINUS	MUX_FW_P3_VMINUS	MUX_FW_P2_VMINUS	MUX_FW_P1_VMINUS	MUX_FW_P0_VMINUS

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_FW_SARBUS1_VPLUS	MUX_FW_SARBUS0_VPLUS	MUX_FW_AMUXBUSB_VMINUS	MUX_FW_AMUXBUSA_VMINUS	MUX_FW_AMUXBUSB_VPLUS	MUX_FW_AMUXBUSA_VPLUS	MUX_FW_TEMP_VPLUS	MUX_FW_VSSA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [31:30]		MUX_FW_P7_COREIO3	MUX_FW_P6_COREIO2	MUX_FW_P5_COREIO1	MUX_FW_P4_COREIO0	MUX_FW_SARBUS1_VMINUS	MUX_FW_SARBUS0_VMINUS

Bits	Name	Description
29	MUX_FW_P7_COREIO3	Firmware control: 0=open, 1=close switch between P7 and coreio3 signal. Write with '1' to set bit. Default Value: 0
28	MUX_FW_P6_COREIO2	Firmware control: 0=open, 1=close switch between P6 and coreio2 signal. Write with '1' to set bit. Default Value: 0
27	MUX_FW_P5_COREIO1	Firmware control: 0=open, 1=close switch between P5 and coreio1 signal. Write with '1' to set bit. Default Value: 0
26	MUX_FW_P4_COREIO0	Firmware control: 0=open, 1=close switch between P4 and coreio0 signal. Write with '1' to set bit. Default Value: 0
25	MUX_FW_SARBUS1_VMINUS	Firmware control: 0=open, 1=close switch between sarbus1 and vminus signal. Write with '1' to set bit. Default Value: 0

17.1.77 SAR0_MUX_SWITCH0 (continued)

24	MUX_FW_SARBUS0_VMINUS	Firmware control: 0=open, 1=close switch between sarbus0 and vminus signal. Write with '1' to set bit. Default Value: 0
23	MUX_FW_SARBUS1_VPLUS	Firmware control: 0=open, 1=close switch between sarbus1 and vplus signal. Write with '1' to set bit. Default Value: 0
22	MUX_FW_SARBUS0_VPLUS	Firmware control: 0=open, 1=close switch between sarbus0 and vplus signal. Write with '1' to set bit. Default Value: 0
21	MUX_FW_AMUXBUSB_VMINUS	Firmware control: 0=open, 1=close switch between amuxbusb and vminus signal. Write with '1' to set bit. Default Value: 0
20	MUX_FW_AMUXBUSA_VMINUS	Firmware control: 0=open, 1=close switch between amuxbusa and vminus signal. Write with '1' to set bit. Default Value: 0
19	MUX_FW_AMUXBUSB_VPLUS	Firmware control: 0=open, 1=close switch between amuxbusb and vplus signal. Write with '1' to set bit. Default Value: 0
18	MUX_FW_AMUXBUSA_VPLUS	Firmware control: 0=open, 1=close switch between amuxbusa and vplus signal. Write with '1' to set bit. Default Value: 0
17	MUX_FW_TEMP_VPLUS	Firmware control: 0=open, 1=close switch between temperature sensor and vplus signal, also powers on the temperature sensor. Write with '1' to set bit. Default Value: 0
16	MUX_FW_VSSA_VMINUS	Firmware control: 0=open, 1=close switch between vssa_kelvin and vminus signal. Write with '1' to set bit. Default Value: 0
15	MUX_FW_P7_VMINUS	Firmware control: 0=open, 1=close switch between pin P7 and vminus signal. Write with '1' to set bit. Default Value: 0
14	MUX_FW_P6_VMINUS	Firmware control: 0=open, 1=close switch between pin P6 and vminus signal. Write with '1' to set bit. Default Value: 0
13	MUX_FW_P5_VMINUS	Firmware control: 0=open, 1=close switch between pin P5 and vminus signal. Write with '1' to set bit. Default Value: 0
12	MUX_FW_P4_VMINUS	Firmware control: 0=open, 1=close switch between pin P4 and vminus signal. Write with '1' to set bit. Default Value: 0
11	MUX_FW_P3_VMINUS	Firmware control: 0=open, 1=close switch between pin P3 and vminus signal. Write with '1' to set bit. Default Value: 0
10	MUX_FW_P2_VMINUS	Firmware control: 0=open, 1=close switch between pin P2 and vminus signal. Write with '1' to set bit. Default Value: 0
9	MUX_FW_P1_VMINUS	Firmware control: 0=open, 1=close switch between pin P1 and vminus signal. Write with '1' to set bit. Default Value: 0

17.1.77 SAR0_MUX_SWITCH0 (continued)

8	MUX_FW_P0_VMINUS	Firmware control: 0=open, 1=close switch between pin P0 and vminus signal. Write with '1' to set bit. Default Value: 0
7	MUX_FW_P7_VPLUS	Firmware control: 0=open, 1=close switch between pin P7 and vplus signal. Write with '1' to set bit. Default Value: 0
6	MUX_FW_P6_VPLUS	Firmware control: 0=open, 1=close switch between pin P6 and vplus signal. Write with '1' to set bit. Default Value: 0
5	MUX_FW_P5_VPLUS	Firmware control: 0=open, 1=close switch between pin P5 and vplus signal. Write with '1' to set bit. Default Value: 0
4	MUX_FW_P4_VPLUS	Firmware control: 0=open, 1=close switch between pin P4 and vplus signal. Write with '1' to set bit. Default Value: 0
3	MUX_FW_P3_VPLUS	Firmware control: 0=open, 1=close switch between pin P3 and vplus signal. Write with '1' to set bit. Default Value: 0
2	MUX_FW_P2_VPLUS	Firmware control: 0=open, 1=close switch between pin P2 and vplus signal. Write with '1' to set bit. Default Value: 0
1	MUX_FW_P1_VPLUS	Firmware control: 0=open, 1=close switch between pin P1 and vplus signal. Write with '1' to set bit. Default Value: 0
0	MUX_FW_P0_VPLUS	Firmware control: 0=open, 1=close switch between pin P0 and vplus signal. Write with '1' to set bit. Default Value: 0

17.1.78 SAR0_MUX_SWITCH_CLEAR0

SARMUX Firmware switch control clear

Address: 0x403A0304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_FW_P7_VPLUS	MUX_FW_P6_VPLUS	MUX_FW_P5_VPLUS	MUX_FW_P4_VPLUS	MUX_FW_P3_VPLUS	MUX_FW_P2_VPLUS	MUX_FW_P1_VPLUS	MUX_FW_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_FW_P7_VMINUS	MUX_FW_P6_VMINUS	MUX_FW_P5_VMINUS	MUX_FW_P4_VMINUS	MUX_FW_P3_VMINUS	MUX_FW_P2_VMINUS	MUX_FW_P1_VMINUS	MUX_FW_P0_VMINUS

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_FW_SARBUS1_VPLUS	MUX_FW_SARBUS0_VPLUS	MUX_FW_AMUXBUSB_VMINUS	MUX_FW_AMUXBUSA_VMINUS	MUX_FW_AMUXBUSB_VPLUS	MUX_FW_AMUXBUSA_VPLUS	MUX_FW_TEMP_VPLUS	MUX_FW_VSSA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None		A	A	A	A	A	A
Name	None [31:30]		MUX_FW_P7_COREIO3	MUX_FW_P6_COREIO2	MUX_FW_P5_COREIO1	MUX_FW_P4_COREIO0	MUX_FW_SARBUS1_VMINUS	MUX_FW_SARBUS0_VMINUS

Bits	Name	Description
29	MUX_FW_P7_COREIO3	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
28	MUX_FW_P6_COREIO2	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
27	MUX_FW_P5_COREIO1	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
26	MUX_FW_P4_COREIO0	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
25	MUX_FW_SARBUS1_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.78 SAR0_MUX_SWITCH_CLEAR0 (continued)

24	MUX_FW_SARBUS0_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
23	MUX_FW_SARBUS1_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
22	MUX_FW_SARBUS0_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
21	MUX_FW_AMUXBUSB_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
20	MUX_FW_AMUXBUSA_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
19	MUX_FW_AMUXBUSB_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
18	MUX_FW_AMUXBUSA_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
17	MUX_FW_TEMP_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
16	MUX_FW_VSSA_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
15	MUX_FW_P7_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
14	MUX_FW_P6_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
13	MUX_FW_P5_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
12	MUX_FW_P4_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
11	MUX_FW_P3_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
10	MUX_FW_P2_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
9	MUX_FW_P1_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
8	MUX_FW_P0_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
7	MUX_FW_P7_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
6	MUX_FW_P6_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
5	MUX_FW_P5_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
4	MUX_FW_P4_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
3	MUX_FW_P3_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.78 SAR0_MUX_SWITCH_CLEAR0 (continued)

2	MUX_FW_P2_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
1	MUX_FW_P1_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
0	MUX_FW_P0_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.79 SAR0_MUX_SWITCH1

SARMUX Firmware switch controls

Address: 0x403A0308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [7:4]				MUX_FW_ADFT1_SARBUS1	MUX_FW_ADFT0_SARBUS0	MUX_FW_P5_DFT_INM	MUX_FW_P4_DFT_INP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	MUX_FW_ADFT1_SARBUS1	Firmware control: 0=open, 1=close switch between adft1 signal and sarbus1 signal. Write with '1' to set bit. Default Value: 0
2	MUX_FW_ADFT0_SARBUS0	Firmware control: 0=open, 1=close switch between adft0 signal and sarbus0 signal. Write with '1' to set bit. Default Value: 0
1	MUX_FW_P5_DFT_INM	Firmware control: 0=open, 1=close switch between P5 pin and dft_inm signal. Write with '1' to set bit. Default Value: 0
0	MUX_FW_P4_DFT_INP	Firmware control: 0=open, 1=close switch between P4 pin and dft_inp signal. Write with '1' to set bit. Default Value: 0

17.1.80 SAR0_MUX_SWITCH_CLEAR1

SARMUX Firmware switch control clear

Address: 0x403A030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				MUX_FW_ADFT1_SARBUS1	MUX_FW_ADFT0_SARBUS0	MUX_FW_P5_DFT_INM	MUX_FW_P4_DFT_INP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	MUX_FW_ADFT1_SARBUS1	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0
2	MUX_FW_ADFT0_SARBUS0	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0
1	MUX_FW_P5_DFT_INM	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0
0	MUX_FW_P4_DFT_INP	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0

17.1.81 SAR0_MUX_SWITCH_HW_CTRL

SARMUX switch hardware control

Address: 0x403A0340

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	MUX_HW_CTRL_P7	MUX_HW_CTRL_P6	MUX_HW_CTRL_P5	MUX_HW_CTRL_P4	MUX_HW_CTRL_P3	MUX_HW_CTRL_P2	MUX_HW_CTRL_P1	MUX_HW_CTRL_P0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	None		RW	RW	RW	RW
HW Access	R	R	None		R	R	R	R
Name	MUX_HW_CTRL_SARBUS1	MUX_HW_CTRL_SARBUS0	None [21:20]		MUX_HW_CTRL_AMUXBUSB	MUX_HW_CTRL_AMUXBUSA	MUX_HW_CTRL_TEMP	MUX_HW_CTRL_VSSA

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	MUX_HW_CTRL_SARBUS1	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for sarbus1 switches. Default Value: 0
22	MUX_HW_CTRL_SARBUS0	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for sarbus0 switches. Default Value: 0
19	MUX_HW_CTRL_AMUXBUSB	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for amuxbusb switches. Default Value: 0
18	MUX_HW_CTRL_AMUXBUSA	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for amuxbusa switches. Default Value: 0
17	MUX_HW_CTRL_TEMP	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for temp switch. Default Value: 0

17.1.81 SAR0_MUX_SWITCH_HW_CTRL (continued)

16	MUX_HW_CTRL_VSSA	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for vssa switch. Default Value: 0
7	MUX_HW_CTRL_P7	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P7 switches. Default Value: 0
6	MUX_HW_CTRL_P6	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P6 switches. Default Value: 0
5	MUX_HW_CTRL_P5	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P5 switches. Default Value: 0
4	MUX_HW_CTRL_P4	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P4 switches. Default Value: 0
3	MUX_HW_CTRL_P3	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P3 switches. Default Value: 0
2	MUX_HW_CTRL_P2	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P2 switches. Default Value: 0
1	MUX_HW_CTRL_P1	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P1 switches. Default Value: 0
0	MUX_HW_CTRL_P0	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P0 switches. Default Value: 0

17.1.82 SAR0_MUX_SWITCH_STATUS

SARMUX switch status

Address: 0x403A0348

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_FW_P7_VPLUS	MUX_FW_P6_VPLUS	MUX_FW_P5_VPLUS	MUX_FW_P4_VPLUS	MUX_FW_P3_VPLUS	MUX_FW_P2_VPLUS	MUX_FW_P1_VPLUS	MUX_FW_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_FW_P7_VMINUS	MUX_FW_P6_VMINUS	MUX_FW_P5_VMINUS	MUX_FW_P4_VMINUS	MUX_FW_P3_VMINUS	MUX_FW_P2_VMINUS	MUX_FW_P1_VMINUS	MUX_FW_P0_VMINUS

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_FW_SARBUS1_VPLUS	MUX_FW_SARBUS0_VPLUS	MUX_FW_AMUXBUSB_VMINUS	MUX_FW_AMUXBUSA_VMINUS	MUX_FW_AMUXBUSB_VPLUS	MUX_FW_AMUXBUSA_VPLUS	MUX_FW_TEMP_VPLUS	MUX_FW_VSSA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None						R	R
HW Access	None						W	W
Name	None [31:26]						MUX_FW_SARBUS1_VMINUS	MUX_FW_SARBUS0_VMINUS

Bits	Name	Description
25	MUX_FW_SARBUS1_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
24	MUX_FW_SARBUS0_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
23	MUX_FW_SARBUS1_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
22	MUX_FW_SARBUS0_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
21	MUX_FW_AMUXBUSB_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.82 SAR0_MUX_SWITCH_STATUS (continued)

20	MUX_FW_AMUXBUSA_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
19	MUX_FW_AMUXBUSB_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
18	MUX_FW_AMUXBUSA_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
17	MUX_FW_TEMP_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
16	MUX_FW_VSSA_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
15	MUX_FW_P7_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
14	MUX_FW_P6_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
13	MUX_FW_P5_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
12	MUX_FW_P4_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
11	MUX_FW_P3_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
10	MUX_FW_P2_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
9	MUX_FW_P1_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
8	MUX_FW_P0_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
7	MUX_FW_P7_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
6	MUX_FW_P6_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
5	MUX_FW_P5_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
4	MUX_FW_P4_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
3	MUX_FW_P3_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
2	MUX_FW_P2_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
1	MUX_FW_P1_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
0	MUX_FW_P0_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.83 SAR0_PUMP_CTRL

Switch pump control

Address: 0x403A0380

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							CLOCK_SEL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLED	None [30:24]						

Bits	Name	Description
31	ENABLED	0=disabled: pump output is VDDA_PUMP, 1=enabled: pump output is boosted. Default Value: 0
0	CLOCK_SEL	Clock select: 0=external clock, 1=internal clock (deprecated). Default Value: 0

17.1.84 SAR0_ANA_TRIM

Analog trim register.

Address: 0x403A0F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW		
HW Access	None				R	R		
Name	None [7:4]				TRIMUNIT	CAP_TRIM [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	TRIMUNIT	Attenuation cap trimming Default Value: 0
2 : 0	CAP_TRIM	Attenuation cap trimming Default Value: 0

17.1.85 SAR0_WOUNDING

SAR wounding register

Address: 0x403A0F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	
HW Access	None						R	
Name	None [7:2]						WOUND_RESOLUTION [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	WOUND_RESOLUTION	Maximum SAR resolution allowed Default Value: 0 **0x0: 12BIT:** unwounded: up to full 12-bit SAR resolution allowed **0x1: 10BIT:** wounded: max resolution upto 10-bit SAR resolution allowed **0x2: 8BIT:** wounded: only 8-bit SAR resolution allowed **0x3: 8BIT_TOO:** wounded: only 8-bit SAR resolution allowed

18 SCB Registers

This section discusses the SCB registers. It lists all the registers in mapping tables, in address order.

18.1 Register Details

Register Name	Address
SCB0_CTRL	0x40220000
SCB0_STATUS	0x40220004
SCB0_CMD_RESP_CTRL	0x40220008
SCB0_CMD_RESP_STATUS	0x4022000C
SCB0_SPI_CTRL	0x40220020
SCB0_SPI_STATUS	0x40220024
SCB0_UART_CTRL	0x40220040
SCB0_UART_TX_CTRL	0x40220044
SCB0_UART_RX_CTRL	0x40220048
SCB0_UART_RX_STATUS	0x4022004C
SCB0_UART_FLOW_CTRL	0x40220050
SCB0_I2C_CTRL	0x40220060
SCB0_I2C_STATUS	0x40220064
SCB0_I2C_M_CMD	0x40220068
SCB0_I2C_S_CMD	0x4022006C
SCB0_I2C_CFG	0x40220070
SCB0_TX_CTRL	0x40220200
SCB0_TX_FIFO_CTRL	0x40220204
SCB0_TX_FIFO_STATUS	0x40220208
SCB0_TX_FIFO_WR	0x40220240
SCB0_RX_CTRL	0x40220300
SCB0_RX_FIFO_CTRL	0x40220304
SCB0_RX_FIFO_STATUS	0x40220308
SCB0_RX_MATCH	0x40220310
SCB0_RX_FIFO_RD	0x40220340
SCB0_RX_FIFO_RD_SILENT	0x40220344
SCB0_EZ_DATA0	0x40220400

Register Name	Address
SCB0_EZ_DATA1	0x40220404
SCB0_EZ_DATA2	0x40220408
SCB0_EZ_DATA3	0x4022040C
SCB0_EZ_DATA4	0x40220410
SCB0_EZ_DATA5	0x40220414
SCB0_EZ_DATA6	0x40220418
SCB0_EZ_DATA7	0x4022041C
SCB0_EZ_DATA8	0x40220420
SCB0_EZ_DATA9	0x40220424
SCB0_EZ_DATA10	0x40220428
SCB0_EZ_DATA11	0x4022042C
SCB0_EZ_DATA12	0x40220430
SCB0_EZ_DATA13	0x40220434
SCB0_EZ_DATA14	0x40220438
SCB0_EZ_DATA15	0x4022043C
SCB0_EZ_DATA16	0x40220440
SCB0_EZ_DATA17	0x40220444
SCB0_EZ_DATA18	0x40220448
SCB0_EZ_DATA19	0x4022044C
SCB0_EZ_DATA20	0x40220450
SCB0_EZ_DATA21	0x40220454
SCB0_EZ_DATA22	0x40220458
SCB0_EZ_DATA23	0x4022045C
SCB0_EZ_DATA24	0x40220460
SCB0_EZ_DATA25	0x40220464
SCB0_EZ_DATA26	0x40220468
SCB0_EZ_DATA27	0x4022046C
SCB0_EZ_DATA28	0x40220470
SCB0_EZ_DATA29	0x40220474
SCB0_EZ_DATA30	0x40220478
SCB0_EZ_DATA31	0x4022047C
SCB0_INTR_CAUSE	0x40220E00
SCB0_INTR_I2C_EC	0x40220E80
SCB0_INTR_I2C_EC_MASK	0x40220E88
SCB0_INTR_I2C_EC_MASKED	0x40220E8C
SCB0_INTR_SPI_EC	0x40220EC0
SCB0_INTR_SPI_EC_MASK	0x40220EC8
SCB0_INTR_SPI_EC_MASKED	0x40220ECC
SCB0_INTR_M	0x40220F00
SCB0_INTR_M_SET	0x40220F04
SCB0_INTR_M_MASK	0x40220F08
SCB0_INTR_M_MASKED	0x40220F0C

Register Name	Address
SCB0_INTR_S	0x40220F40
SCB0_INTR_S_SET	0x40220F44
SCB0_INTR_S_MASK	0x40220F48
SCB0_INTR_S_MASKED	0x40220F4C
SCB0_INTR_TX	0x40220F80
SCB0_INTR_TX_SET	0x40220F84
SCB0_INTR_TX_MASK	0x40220F88
SCB0_INTR_TX_MASKED	0x40220F8C
SCB0_INTR_RX	0x40220FC0
SCB0_INTR_RX_SET	0x40220FC4
SCB0_INTR_RX_MASK	0x40220FC8
SCB0_INTR_RX_MASKED	0x40220FCC
SCB1_CTRL	0x40230000
SCB1_STATUS	0x40230004
SCB1_CMD_RESP_CTRL	0x40230008
SCB1_CMD_RESP_STATUS	0x4023000C
SCB1_SPI_CTRL	0x40230020
SCB1_SPI_STATUS	0x40230024
SCB1_UART_CTRL	0x40230040
SCB1_UART_TX_CTRL	0x40230044
SCB1_UART_RX_CTRL	0x40230048
SCB1_UART_RX_STATUS	0x4023004C
SCB1_UART_FLOW_CTRL	0x40230050
SCB1_I2C_CTRL	0x40230060
SCB1_I2C_STATUS	0x40230064
SCB1_I2C_M_CMD	0x40230068
SCB1_I2C_S_CMD	0x4023006C
SCB1_I2C_CFG	0x40230070
SCB1_TX_CTRL	0x40230200
SCB1_TX_FIFO_CTRL	0x40230204
SCB1_TX_FIFO_STATUS	0x40230208
SCB1_TX_FIFO_WR	0x40230240
SCB1_RX_CTRL	0x40230300
SCB1_RX_FIFO_CTRL	0x40230304
SCB1_RX_FIFO_STATUS	0x40230308
SCB1_RX_MATCH	0x40230310
SCB1_RX_FIFO_RD	0x40230340
SCB1_RX_FIFO_RD_SILENT	0x40230344
SCB1_EZ_DATA0	0x40230400
SCB1_EZ_DATA1	0x40230404
SCB1_EZ_DATA2	0x40230408
SCB1_EZ_DATA3	0x4023040C

Register Name	Address
SCB1_EZ_DATA4	0x40230410
SCB1_EZ_DATA5	0x40230414
SCB1_EZ_DATA6	0x40230418
SCB1_EZ_DATA7	0x4023041C
SCB1_EZ_DATA8	0x40230420
SCB1_EZ_DATA9	0x40230424
SCB1_EZ_DATA10	0x40230428
SCB1_EZ_DATA11	0x4023042C
SCB1_EZ_DATA12	0x40230430
SCB1_EZ_DATA13	0x40230434
SCB1_EZ_DATA14	0x40230438
SCB1_EZ_DATA15	0x4023043C
SCB1_EZ_DATA16	0x40230440
SCB1_EZ_DATA17	0x40230444
SCB1_EZ_DATA18	0x40230448
SCB1_EZ_DATA19	0x4023044C
SCB1_EZ_DATA20	0x40230450
SCB1_EZ_DATA21	0x40230454
SCB1_EZ_DATA22	0x40230458
SCB1_EZ_DATA23	0x4023045C
SCB1_EZ_DATA24	0x40230460
SCB1_EZ_DATA25	0x40230464
SCB1_EZ_DATA26	0x40230468
SCB1_EZ_DATA27	0x4023046C
SCB1_EZ_DATA28	0x40230470
SCB1_EZ_DATA29	0x40230474
SCB1_EZ_DATA30	0x40230478
SCB1_EZ_DATA31	0x4023047C
SCB1_INTR_CAUSE	0x40230E00
SCB1_INTR_I2C_EC	0x40230E80
SCB1_INTR_I2C_EC_MASK	0x40230E88
SCB1_INTR_I2C_EC_MASKED	0x40230E8C
SCB1_INTR_SPI_EC	0x40230EC0
SCB1_INTR_SPI_EC_MASK	0x40230EC8
SCB1_INTR_SPI_EC_MASKED	0x40230ECC
SCB1_INTR_M	0x40230F00
SCB1_INTR_M_SET	0x40230F04
SCB1_INTR_M_MASK	0x40230F08
SCB1_INTR_M_MASKED	0x40230F0C
SCB1_INTR_S	0x40230F40
SCB1_INTR_S_SET	0x40230F44
SCB1_INTR_S_MASK	0x40230F48

Register Name	Address
SCB1_INTR_S_MASKED	0x40230F4C
SCB1_INTR_TX	0x40230F80
SCB1_INTR_TX_SET	0x40230F84
SCB1_INTR_TX_MASK	0x40230F88
SCB1_INTR_TX_MASKED	0x40230F8C
SCB1_INTR_RX	0x40230FC0
SCB1_INTR_RX_SET	0x40230FC4
SCB1_INTR_RX_MASK	0x40230FC8
SCB1_INTR_RX_MASKED	0x40230FCC
SCB2_CTRL	0x40240000
SCB2_STATUS	0x40240004
SCB2_CMD_RESP_CTRL	0x40240008
SCB2_CMD_RESP_STATUS	0x4024000C
SCB2_SPI_CTRL	0x40240020
SCB2_SPI_STATUS	0x40240024
SCB2_UART_CTRL	0x40240040
SCB2_UART_TX_CTRL	0x40240044
SCB2_UART_RX_CTRL	0x40240048
SCB2_UART_RX_STATUS	0x4024004C
SCB2_UART_FLOW_CTRL	0x40240050
SCB2_I2C_CTRL	0x40240060
SCB2_I2C_STATUS	0x40240064
SCB2_I2C_M_CMD	0x40240068
SCB2_I2C_S_CMD	0x4024006C
SCB2_I2C_CFG	0x40240070
SCB2_TX_CTRL	0x40240200
SCB2_TX_FIFO_CTRL	0x40240204
SCB2_TX_FIFO_STATUS	0x40240208
SCB2_TX_FIFO_WR	0x40240240
SCB2_RX_CTRL	0x40240300
SCB2_RX_FIFO_CTRL	0x40240304
SCB2_RX_FIFO_STATUS	0x40240308
SCB2_RX_MATCH	0x40240310
SCB2_RX_FIFO_RD	0x40240340
SCB2_RX_FIFO_RD_SILENT	0x40240344
SCB2_EZ_DATA0	0x40240400
SCB2_EZ_DATA1	0x40240404
SCB2_EZ_DATA2	0x40240408
SCB2_EZ_DATA3	0x4024040C
SCB2_EZ_DATA4	0x40240410
SCB2_EZ_DATA5	0x40240414
SCB2_EZ_DATA6	0x40240418

Register Name	Address
SCB2_EZ_DATA7	0x4024041C
SCB2_EZ_DATA8	0x40240420
SCB2_EZ_DATA9	0x40240424
SCB2_EZ_DATA10	0x40240428
SCB2_EZ_DATA11	0x4024042C
SCB2_EZ_DATA12	0x40240430
SCB2_EZ_DATA13	0x40240434
SCB2_EZ_DATA14	0x40240438
SCB2_EZ_DATA15	0x4024043C
SCB2_EZ_DATA16	0x40240440
SCB2_EZ_DATA17	0x40240444
SCB2_EZ_DATA18	0x40240448
SCB2_EZ_DATA19	0x4024044C
SCB2_EZ_DATA20	0x40240450
SCB2_EZ_DATA21	0x40240454
SCB2_EZ_DATA22	0x40240458
SCB2_EZ_DATA23	0x4024045C
SCB2_EZ_DATA24	0x40240460
SCB2_EZ_DATA25	0x40240464
SCB2_EZ_DATA26	0x40240468
SCB2_EZ_DATA27	0x4024046C
SCB2_EZ_DATA28	0x40240470
SCB2_EZ_DATA29	0x40240474
SCB2_EZ_DATA30	0x40240478
SCB2_EZ_DATA31	0x4024047C
SCB2_INTR_CAUSE	0x40240E00
SCB2_INTR_I2C_EC	0x40240E80
SCB2_INTR_I2C_EC_MASK	0x40240E88
SCB2_INTR_I2C_EC_MASKED	0x40240E8C
SCB2_INTR_SPI_EC	0x40240EC0
SCB2_INTR_SPI_EC_MASK	0x40240EC8
SCB2_INTR_SPI_EC_MASKED	0x40240ECC
SCB2_INTR_M	0x40240F00
SCB2_INTR_M_SET	0x40240F04
SCB2_INTR_M_MASK	0x40240F08
SCB2_INTR_M_MASKED	0x40240F0C
SCB2_INTR_S	0x40240F40
SCB2_INTR_S_SET	0x40240F44
SCB2_INTR_S_MASK	0x40240F48
SCB2_INTR_S_MASKED	0x40240F4C
SCB2_INTR_TX	0x40240F80
SCB2_INTR_TX_SET	0x40240F84

Register Name	Address
SCB2_INTR_TX_MASK	0x40240F88
SCB2_INTR_TX_MASKED	0x40240F8C
SCB2_INTR_RX	0x40240FC0
SCB2_INTR_RX_SET	0x40240FC4
SCB2_INTR_RX_MASK	0x40240FC8
SCB2_INTR_RX_MASKED	0x40240FCC
SCB3_CTRL	0x40250000
SCB3_STATUS	0x40250004
SCB3_CMD_RESP_CTRL	0x40250008
SCB3_CMD_RESP_STATUS	0x4025000C
SCB3_SPI_CTRL	0x40250020
SCB3_SPI_STATUS	0x40250024
SCB3_UART_CTRL	0x40250040
SCB3_UART_TX_CTRL	0x40250044
SCB3_UART_RX_CTRL	0x40250048
SCB3_UART_RX_STATUS	0x4025004C
SCB3_UART_FLOW_CTRL	0x40250050
SCB3_I2C_CTRL	0x40250060
SCB3_I2C_STATUS	0x40250064
SCB3_I2C_M_CMD	0x40250068
SCB3_I2C_S_CMD	0x4025006C
SCB3_I2C_CFG	0x40250070
SCB3_TX_CTRL	0x40250200
SCB3_TX_FIFO_CTRL	0x40250204
SCB3_TX_FIFO_STATUS	0x40250208
SCB3_TX_FIFO_WR	0x40250240
SCB3_RX_CTRL	0x40250300
SCB3_RX_FIFO_CTRL	0x40250304
SCB3_RX_FIFO_STATUS	0x40250308
SCB3_RX_MATCH	0x40250310
SCB3_RX_FIFO_RD	0x40250340
SCB3_RX_FIFO_RD_SILENT	0x40250344
SCB3_EZ_DATA0	0x40250400
SCB3_EZ_DATA1	0x40250404
SCB3_EZ_DATA2	0x40250408
SCB3_EZ_DATA3	0x4025040C
SCB3_EZ_DATA4	0x40250410
SCB3_EZ_DATA5	0x40250414
SCB3_EZ_DATA6	0x40250418
SCB3_EZ_DATA7	0x4025041C
SCB3_EZ_DATA8	0x40250420
SCB3_EZ_DATA9	0x40250424

Register Name	Address
SCB3_EZ_DATA10	0x40250428
SCB3_EZ_DATA11	0x4025042C
SCB3_EZ_DATA12	0x40250430
SCB3_EZ_DATA13	0x40250434
SCB3_EZ_DATA14	0x40250438
SCB3_EZ_DATA15	0x4025043C
SCB3_EZ_DATA16	0x40250440
SCB3_EZ_DATA17	0x40250444
SCB3_EZ_DATA18	0x40250448
SCB3_EZ_DATA19	0x4025044C
SCB3_EZ_DATA20	0x40250450
SCB3_EZ_DATA21	0x40250454
SCB3_EZ_DATA22	0x40250458
SCB3_EZ_DATA23	0x4025045C
SCB3_EZ_DATA24	0x40250460
SCB3_EZ_DATA25	0x40250464
SCB3_EZ_DATA26	0x40250468
SCB3_EZ_DATA27	0x4025046C
SCB3_EZ_DATA28	0x40250470
SCB3_EZ_DATA29	0x40250474
SCB3_EZ_DATA30	0x40250478
SCB3_EZ_DATA31	0x4025047C
SCB3_INTR_CAUSE	0x40250E00
SCB3_INTR_I2C_EC	0x40250E80
SCB3_INTR_I2C_EC_MASK	0x40250E88
SCB3_INTR_I2C_EC_MASKED	0x40250E8C
SCB3_INTR_SPI_EC	0x40250EC0
SCB3_INTR_SPI_EC_MASK	0x40250EC8
SCB3_INTR_SPI_EC_MASKED	0x40250ECC
SCB3_INTR_M	0x40250F00
SCB3_INTR_M_SET	0x40250F04
SCB3_INTR_M_MASK	0x40250F08
SCB3_INTR_M_MASKED	0x40250F0C
SCB3_INTR_S	0x40250F40
SCB3_INTR_S_SET	0x40250F44
SCB3_INTR_S_MASK	0x40250F48
SCB3_INTR_S_MASKED	0x40250F4C
SCB3_INTR_TX	0x40250F80
SCB3_INTR_TX_SET	0x40250F84
SCB3_INTR_TX_MASK	0x40250F88
SCB3_INTR_TX_MASKED	0x40250F8C
SCB3_INTR_RX	0x40250FC0

Register Name	Address
SCB3_INTR_RX_SET	0x40250FC4
SCB3_INTR_RX_MASK	0x40250FC8
SCB3_INTR_RX_MASKED	0x40250FCC
SCB4_CTRL	0x40260000
SCB4_STATUS	0x40260004
SCB4_CMD_RESP_CTRL	0x40260008
SCB4_CMD_RESP_STATUS	0x4026000C
SCB4_SPI_CTRL	0x40260020
SCB4_SPI_STATUS	0x40260024
SCB4_UART_CTRL	0x40260040
SCB4_UART_TX_CTRL	0x40260044
SCB4_UART_RX_CTRL	0x40260048
SCB4_UART_RX_STATUS	0x4026004C
SCB4_UART_FLOW_CTRL	0x40260050
SCB4_I2C_CTRL	0x40260060
SCB4_I2C_STATUS	0x40260064
SCB4_I2C_M_CMD	0x40260068
SCB4_I2C_S_CMD	0x4026006C
SCB4_I2C_CFG	0x40260070
SCB4_TX_CTRL	0x40260200
SCB4_TX_FIFO_CTRL	0x40260204
SCB4_TX_FIFO_STATUS	0x40260208
SCB4_TX_FIFO_WR	0x40260240
SCB4_RX_CTRL	0x40260300
SCB4_RX_FIFO_CTRL	0x40260304
SCB4_RX_FIFO_STATUS	0x40260308
SCB4_RX_MATCH	0x40260310
SCB4_RX_FIFO_RD	0x40260340
SCB4_RX_FIFO_RD_SILENT	0x40260344
SCB4_EZ_DATA0	0x40260400
SCB4_EZ_DATA1	0x40260404
SCB4_EZ_DATA2	0x40260408
SCB4_EZ_DATA3	0x4026040C
SCB4_EZ_DATA4	0x40260410
SCB4_EZ_DATA5	0x40260414
SCB4_EZ_DATA6	0x40260418
SCB4_EZ_DATA7	0x4026041C
SCB4_EZ_DATA8	0x40260420
SCB4_EZ_DATA9	0x40260424
SCB4_EZ_DATA10	0x40260428
SCB4_EZ_DATA11	0x4026042C
SCB4_EZ_DATA12	0x40260430

Register Name	Address
SCB4_EZ_DATA13	0x40260434
SCB4_EZ_DATA14	0x40260438
SCB4_EZ_DATA15	0x4026043C
SCB4_EZ_DATA16	0x40260440
SCB4_EZ_DATA17	0x40260444
SCB4_EZ_DATA18	0x40260448
SCB4_EZ_DATA19	0x4026044C
SCB4_EZ_DATA20	0x40260450
SCB4_EZ_DATA21	0x40260454
SCB4_EZ_DATA22	0x40260458
SCB4_EZ_DATA23	0x4026045C
SCB4_EZ_DATA24	0x40260460
SCB4_EZ_DATA25	0x40260464
SCB4_EZ_DATA26	0x40260468
SCB4_EZ_DATA27	0x4026046C
SCB4_EZ_DATA28	0x40260470
SCB4_EZ_DATA29	0x40260474
SCB4_EZ_DATA30	0x40260478
SCB4_EZ_DATA31	0x4026047C
SCB4_INTR_CAUSE	0x40260E00
SCB4_INTR_I2C_EC	0x40260E80
SCB4_INTR_I2C_EC_MASK	0x40260E88
SCB4_INTR_I2C_EC_MASKED	0x40260E8C
SCB4_INTR_SPI_EC	0x40260EC0
SCB4_INTR_SPI_EC_MASK	0x40260EC8
SCB4_INTR_SPI_EC_MASKED	0x40260ECC
SCB4_INTR_M	0x40260F00
SCB4_INTR_M_SET	0x40260F04
SCB4_INTR_M_MASK	0x40260F08
SCB4_INTR_M_MASKED	0x40260F0C
SCB4_INTR_S	0x40260F40
SCB4_INTR_S_SET	0x40260F44
SCB4_INTR_S_MASK	0x40260F48
SCB4_INTR_S_MASKED	0x40260F4C
SCB4_INTR_TX	0x40260F80
SCB4_INTR_TX_SET	0x40260F84
SCB4_INTR_TX_MASK	0x40260F88
SCB4_INTR_TX_MASKED	0x40260F8C
SCB4_INTR_RX	0x40260FC0
SCB4_INTR_RX_SET	0x40260FC4
SCB4_INTR_RX_MASK	0x40260FC8
SCB4_INTR_RX_MASKED	0x40260FCC

Register Name	Address
SCB5_CTRL	0x40270000
SCB5_STATUS	0x40270004
SCB5_CMD_RESP_CTRL	0x40270008
SCB5_CMD_RESP_STATUS	0x4027000C
SCB5_SPI_CTRL	0x40270020
SCB5_SPI_STATUS	0x40270024
SCB5_UART_CTRL	0x40270040
SCB5_UART_TX_CTRL	0x40270044
SCB5_UART_RX_CTRL	0x40270048
SCB5_UART_RX_STATUS	0x4027004C
SCB5_UART_FLOW_CTRL	0x40270050
SCB5_I2C_CTRL	0x40270060
SCB5_I2C_STATUS	0x40270064
SCB5_I2C_M_CMD	0x40270068
SCB5_I2C_S_CMD	0x4027006C
SCB5_I2C_CFG	0x40270070
SCB5_TX_CTRL	0x40270200
SCB5_TX_FIFO_CTRL	0x40270204
SCB5_TX_FIFO_STATUS	0x40270208
SCB5_TX_FIFO_WR	0x40270240
SCB5_RX_CTRL	0x40270300
SCB5_RX_FIFO_CTRL	0x40270304
SCB5_RX_FIFO_STATUS	0x40270308
SCB5_RX_MATCH	0x40270310
SCB5_RX_FIFO_RD	0x40270340
SCB5_RX_FIFO_RD_SILENT	0x40270344
SCB5_EZ_DATA0	0x40270400
SCB5_EZ_DATA1	0x40270404
SCB5_EZ_DATA2	0x40270408
SCB5_EZ_DATA3	0x4027040C
SCB5_EZ_DATA4	0x40270410
SCB5_EZ_DATA5	0x40270414
SCB5_EZ_DATA6	0x40270418
SCB5_EZ_DATA7	0x4027041C
SCB5_EZ_DATA8	0x40270420
SCB5_EZ_DATA9	0x40270424
SCB5_EZ_DATA10	0x40270428
SCB5_EZ_DATA11	0x4027042C
SCB5_EZ_DATA12	0x40270430
SCB5_EZ_DATA13	0x40270434
SCB5_EZ_DATA14	0x40270438
SCB5_EZ_DATA15	0x4027043C

Register Name	Address
SCB5_EZ_DATA16	0x40270440
SCB5_EZ_DATA17	0x40270444
SCB5_EZ_DATA18	0x40270448
SCB5_EZ_DATA19	0x4027044C
SCB5_EZ_DATA20	0x40270450
SCB5_EZ_DATA21	0x40270454
SCB5_EZ_DATA22	0x40270458
SCB5_EZ_DATA23	0x4027045C
SCB5_EZ_DATA24	0x40270460
SCB5_EZ_DATA25	0x40270464
SCB5_EZ_DATA26	0x40270468
SCB5_EZ_DATA27	0x4027046C
SCB5_EZ_DATA28	0x40270470
SCB5_EZ_DATA29	0x40270474
SCB5_EZ_DATA30	0x40270478
SCB5_EZ_DATA31	0x4027047C
SCB5_INTR_CAUSE	0x40270E00
SCB5_INTR_I2C_EC	0x40270E80
SCB5_INTR_I2C_EC_MASK	0x40270E88
SCB5_INTR_I2C_EC_MASKED	0x40270E8C
SCB5_INTR_SPI_EC	0x40270EC0
SCB5_INTR_SPI_EC_MASK	0x40270EC8
SCB5_INTR_SPI_EC_MASKED	0x40270ECC
SCB5_INTR_M	0x40270F00
SCB5_INTR_M_SET	0x40270F04
SCB5_INTR_M_MASK	0x40270F08
SCB5_INTR_M_MASKED	0x40270F0C
SCB5_INTR_S	0x40270F40
SCB5_INTR_S_SET	0x40270F44
SCB5_INTR_S_MASK	0x40270F48
SCB5_INTR_S_MASKED	0x40270F4C
SCB5_INTR_TX	0x40270F80
SCB5_INTR_TX_SET	0x40270F84
SCB5_INTR_TX_MASK	0x40270F88
SCB5_INTR_TX_MASKED	0x40270F8C
SCB5_INTR_RX	0x40270FC0
SCB5_INTR_RX_SET	0x40270FC4
SCB5_INTR_RX_MASK	0x40270FC8
SCB5_INTR_RX_MASKED	0x40270FCC
SCB6_CTRL	0x40280000
SCB6_STATUS	0x40280004
SCB6_CMD_RESP_CTRL	0x40280008

Register Name	Address
SCB6_CMD_RESP_STATUS	0x4028000C
SCB6_SPI_CTRL	0x40280020
SCB6_SPI_STATUS	0x40280024
SCB6_UART_CTRL	0x40280040
SCB6_UART_TX_CTRL	0x40280044
SCB6_UART_RX_CTRL	0x40280048
SCB6_UART_RX_STATUS	0x4028004C
SCB6_UART_FLOW_CTRL	0x40280050
SCB6_I2C_CTRL	0x40280060
SCB6_I2C_STATUS	0x40280064
SCB6_I2C_M_CMD	0x40280068
SCB6_I2C_S_CMD	0x4028006C
SCB6_I2C_CFG	0x40280070
SCB6_TX_CTRL	0x40280200
SCB6_TX_FIFO_CTRL	0x40280204
SCB6_TX_FIFO_STATUS	0x40280208
SCB6_TX_FIFO_WR	0x40280240
SCB6_RX_CTRL	0x40280300
SCB6_RX_FIFO_CTRL	0x40280304
SCB6_RX_FIFO_STATUS	0x40280308
SCB6_RX_MATCH	0x40280310
SCB6_RX_FIFO_RD	0x40280340
SCB6_RX_FIFO_RD_SILENT	0x40280344
SCB6_EZ_DATA0	0x40280400
SCB6_EZ_DATA1	0x40280404
SCB6_EZ_DATA2	0x40280408
SCB6_EZ_DATA3	0x4028040C
SCB6_EZ_DATA4	0x40280410
SCB6_EZ_DATA5	0x40280414
SCB6_EZ_DATA6	0x40280418
SCB6_EZ_DATA7	0x4028041C
SCB6_EZ_DATA8	0x40280420
SCB6_EZ_DATA9	0x40280424
SCB6_EZ_DATA10	0x40280428
SCB6_EZ_DATA11	0x4028042C
SCB6_EZ_DATA12	0x40280430
SCB6_EZ_DATA13	0x40280434
SCB6_EZ_DATA14	0x40280438
SCB6_EZ_DATA15	0x4028043C
SCB6_EZ_DATA16	0x40280440
SCB6_EZ_DATA17	0x40280444
SCB6_EZ_DATA18	0x40280448

Register Name	Address
SCB6_EZ_DATA19	0x4028044C
SCB6_EZ_DATA20	0x40280450
SCB6_EZ_DATA21	0x40280454
SCB6_EZ_DATA22	0x40280458
SCB6_EZ_DATA23	0x4028045C
SCB6_EZ_DATA24	0x40280460
SCB6_EZ_DATA25	0x40280464
SCB6_EZ_DATA26	0x40280468
SCB6_EZ_DATA27	0x4028046C
SCB6_EZ_DATA28	0x40280470
SCB6_EZ_DATA29	0x40280474
SCB6_EZ_DATA30	0x40280478
SCB6_EZ_DATA31	0x4028047C
SCB6_INTR_CAUSE	0x40280E00
SCB6_INTR_I2C_EC	0x40280E80
SCB6_INTR_I2C_EC_MASK	0x40280E88
SCB6_INTR_I2C_EC_MASKED	0x40280E8C
SCB6_INTR_SPI_EC	0x40280EC0
SCB6_INTR_SPI_EC_MASK	0x40280EC8
SCB6_INTR_SPI_EC_MASKED	0x40280ECC
SCB6_INTR_M	0x40280F00
SCB6_INTR_M_SET	0x40280F04
SCB6_INTR_M_MASK	0x40280F08
SCB6_INTR_M_MASKED	0x40280F0C
SCB6_INTR_S	0x40280F40
SCB6_INTR_S_SET	0x40280F44
SCB6_INTR_S_MASK	0x40280F48
SCB6_INTR_S_MASKED	0x40280F4C
SCB6_INTR_TX	0x40280F80
SCB6_INTR_TX_SET	0x40280F84
SCB6_INTR_TX_MASK	0x40280F88
SCB6_INTR_TX_MASKED	0x40280F8C
SCB6_INTR_RX	0x40280FC0
SCB6_INTR_RX_SET	0x40280FC4
SCB6_INTR_RX_MASK	0x40280FC8
SCB6_INTR_RX_MASKED	0x40280FCC
SCB7_CTRL	0x40290000
SCB7_STATUS	0x40290004
SCB7_CMD_RESP_CTRL	0x40290008
SCB7_CMD_RESP_STATUS	0x4029000C
SCB7_SPI_CTRL	0x40290020
SCB7_SPI_STATUS	0x40290024

Register Name	Address
SCB7_UART_CTRL	0x40290040
SCB7_UART_TX_CTRL	0x40290044
SCB7_UART_RX_CTRL	0x40290048
SCB7_UART_RX_STATUS	0x4029004C
SCB7_UART_FLOW_CTRL	0x40290050
SCB7_I2C_CTRL	0x40290060
SCB7_I2C_STATUS	0x40290064
SCB7_I2C_M_CMD	0x40290068
SCB7_I2C_S_CMD	0x4029006C
SCB7_I2C_CFG	0x40290070
SCB7_TX_CTRL	0x40290200
SCB7_TX_FIFO_CTRL	0x40290204
SCB7_TX_FIFO_STATUS	0x40290208
SCB7_TX_FIFO_WR	0x40290240
SCB7_RX_CTRL	0x40290300
SCB7_RX_FIFO_CTRL	0x40290304
SCB7_RX_FIFO_STATUS	0x40290308
SCB7_RX_MATCH	0x40290310
SCB7_RX_FIFO_RD	0x40290340
SCB7_RX_FIFO_RD_SILENT	0x40290344
SCB7_EZ_DATA0	0x40290400
SCB7_EZ_DATA1	0x40290404
SCB7_EZ_DATA2	0x40290408
SCB7_EZ_DATA3	0x4029040C
SCB7_EZ_DATA4	0x40290410
SCB7_EZ_DATA5	0x40290414
SCB7_EZ_DATA6	0x40290418
SCB7_EZ_DATA7	0x4029041C
SCB7_EZ_DATA8	0x40290420
SCB7_EZ_DATA9	0x40290424
SCB7_EZ_DATA10	0x40290428
SCB7_EZ_DATA11	0x4029042C
SCB7_EZ_DATA12	0x40290430
SCB7_EZ_DATA13	0x40290434
SCB7_EZ_DATA14	0x40290438
SCB7_EZ_DATA15	0x4029043C
SCB7_EZ_DATA16	0x40290440
SCB7_EZ_DATA17	0x40290444
SCB7_EZ_DATA18	0x40290448
SCB7_EZ_DATA19	0x4029044C
SCB7_EZ_DATA20	0x40290450
SCB7_EZ_DATA21	0x40290454

Register Name	Address
SCB7_EZ_DATA22	0x40290458
SCB7_EZ_DATA23	0x4029045C
SCB7_EZ_DATA24	0x40290460
SCB7_EZ_DATA25	0x40290464
SCB7_EZ_DATA26	0x40290468
SCB7_EZ_DATA27	0x4029046C
SCB7_EZ_DATA28	0x40290470
SCB7_EZ_DATA29	0x40290474
SCB7_EZ_DATA30	0x40290478
SCB7_EZ_DATA31	0x4029047C
SCB7_INTR_CAUSE	0x40290E00
SCB7_INTR_I2C_EC	0x40290E80
SCB7_INTR_I2C_EC_MASK	0x40290E88
SCB7_INTR_I2C_EC_MASKED	0x40290E8C
SCB7_INTR_SPI_EC	0x40290EC0
SCB7_INTR_SPI_EC_MASK	0x40290EC8
SCB7_INTR_SPI_EC_MASKED	0x40290ECC
SCB7_INTR_M	0x40290F00
SCB7_INTR_M_SET	0x40290F04
SCB7_INTR_M_MASK	0x40290F08
SCB7_INTR_M_MASKED	0x40290F0C
SCB7_INTR_S	0x40290F40
SCB7_INTR_S_SET	0x40290F44
SCB7_INTR_S_MASK	0x40290F48
SCB7_INTR_S_MASKED	0x40290F4C
SCB7_INTR_TX	0x40290F80
SCB7_INTR_TX_SET	0x40290F84
SCB7_INTR_TX_MASK	0x40290F88
SCB7_INTR_TX_MASKED	0x40290F8C
SCB7_INTR_RX	0x40290FC0
SCB7_INTR_RX_SET	0x40290FC4
SCB7_INTR_RX_MASK	0x40290FC8
SCB7_INTR_RX_MASKED	0x40290FCC

18.1.1 SCB0_CTRL

Generic control register.

Address: 0x40220000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.1 SCB0_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.1 SCB0_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.1 SCB0_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.2 SCB0_STATUS

Generic status register.

Address: 0x40220004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.3 SCB0_CMD_RESP_CTRL

Command/response control register.

Address: 0x40220008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.4 SCB0_CMD_RESP_STATUS

Command/response status register.

Address: 0x4022000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.4 SCB0_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.5 SCB0_SPI_CTRL

SPI control register.

Address: 0x40220020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.5 SCB0_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.5 SCB0_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.6 SCB0_SPI_STATUS

SPI status register.

Address: 0x40220024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.7 SCB0_UART_CTRL

UART control register.

Address: 0x40220040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.8 SCB0_UART_TX_CTRL

UART transmitter control register.

Address: 0x40220044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.9 SCB0_UART_RX_CTRL

UART receiver control register.

Address: 0x40220048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.9 SCB0_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.9 SCB0_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.10 SCB0_UART_RX_STATUS

UART receiver status register.

Address: 0x4022004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.11 SCB0_UART_FLOW_CTRL

UART flow control register

Address: 0x40220050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.11 SCB0_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.12 SCB0_I2C_CTRL

I2C control register.

Address: 0x40220060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.12 SCB0_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.12 SCB0_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.13 SCB0_I2C_STATUS

I2C status register.

Address: 0x40220064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.13 SCB0_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.14 SCB0_I2C_M_CMD

I2C master command register.

Address: 0x40220068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.14 SCB0_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.15 SCB0_I2C_S_CMD

I2C slave command register.

Address: 0x4022006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.16 SCB0_I2C_CFG

I2C configuration register.

Address: 0x40220070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.16 SCB0_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.17 SCB0_TX_CTRL

Transmitter control register.

Address: 0x40220200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.18 SCB0_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40220204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.19 SCB0_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40220208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.20 SCB0_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40220240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.21 SCB0_RX_CTRL

Receiver control register.

Address: 0x40220300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.22 SCB0_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40220304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.23 SCB0_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40220308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.24 SCB0_RX_MATCH

Slave address and mask register.

Address: 0x40220310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.25 SCB0_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40220340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.26 SCB0_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40220344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.27 SCB0_EZ_DATA0

Memory buffer registers.

Address: 0x40220400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.28 SCB0_EZ_DATA1

Memory buffer registers.

Address: 0x40220404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.29 SCB0_EZ_DATA2

Memory buffer registers.

Address: 0x40220408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.30 SCB0_EZ_DATA3

Memory buffer registers.

Address: 0x4022040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.31 SCB0_EZ_DATA4

Memory buffer registers.

Address: 0x40220410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.32 SCB0_EZ_DATA5

Memory buffer registers.

Address: 0x40220414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.33 SCB0_EZ_DATA6

Memory buffer registers.

Address: 0x40220418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.34 SCB0_EZ_DATA7

Memory buffer registers.

Address: 0x4022041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.35 SCB0_EZ_DATA8

Memory buffer registers.

Address: 0x40220420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.36 SCB0_EZ_DATA9

Memory buffer registers.

Address: 0x40220424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.37 SCB0_EZ_DATA10

Memory buffer registers.

Address: 0x40220428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.38 SCB0_EZ_DATA11

Memory buffer registers.

Address: 0x4022042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.39 SCB0_EZ_DATA12

Memory buffer registers.

Address: 0x40220430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.40 SCB0_EZ_DATA13

Memory buffer registers.

Address: 0x40220434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.41 SCB0_EZ_DATA14

Memory buffer registers.

Address: 0x40220438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.42 SCB0_EZ_DATA15

Memory buffer registers.

Address: 0x4022043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.43 SCB0_EZ_DATA16

Memory buffer registers.

Address: 0x40220440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.44 SCB0_EZ_DATA17

Memory buffer registers.

Address: 0x40220444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.45 SCB0_EZ_DATA18

Memory buffer registers.

Address: 0x40220448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.46 SCB0_EZ_DATA19

Memory buffer registers.

Address: 0x4022044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.47 SCB0_EZ_DATA20

Memory buffer registers.

Address: 0x40220450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.48 SCB0_EZ_DATA21

Memory buffer registers.

Address: 0x40220454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.49 SCB0_EZ_DATA22

Memory buffer registers.

Address: 0x40220458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.50 SCB0_EZ_DATA23

Memory buffer registers.

Address: 0x4022045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.51 SCB0_EZ_DATA24

Memory buffer registers.

Address: 0x40220460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.52 SCB0_EZ_DATA25

Memory buffer registers.

Address: 0x40220464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.53 SCB0_EZ_DATA26

Memory buffer registers.

Address: 0x40220468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.54 SCB0_EZ_DATA27

Memory buffer registers.

Address: 0x4022046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.55 SCB0_EZ_DATA28

Memory buffer registers.

Address: 0x40220470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.56 SCB0_EZ_DATA29

Memory buffer registers.

Address: 0x40220474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.57 SCB0_EZ_DATA30

Memory buffer registers.

Address: 0x40220478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.58 SCB0_EZ_DATA31

Memory buffer registers.

Address: 0x4022047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.59 SCB0_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40220E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.60 SCB0_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40220E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.60 SCB0_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.61 SCB0_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40220E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.62 SCB0_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40220E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.63 SCB0_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40220EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.63 SCB0_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.64 SCB0_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40220EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.65 SCB0_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40220ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.66 SCB0_INTR_M

Master interrupt request register.

Address: 0x40220F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.67 SCB0_INTR_M_SET

Master interrupt set request register

Address: 0x40220F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.68 SCB0_INTR_M_MASK

Master interrupt mask register.

Address: 0x40220F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.69 SCB0_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40220F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.70 SCB0_INTR_S

Slave interrupt request register.

Address: 0x40220F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.70 SCB0_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.71 SCB0_INTR_S_SET

Slave interrupt set request register.

Address: 0x40220F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.71 SCB0_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.72 SCB0_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40220F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.72 SCB0_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.73 SCB0_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40220F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.73 SCB0_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.74 SCB0_INTR_TX

Transmitter interrupt request register.

Address: 0x40220F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.74 SCB0_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.75 SCB0_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40220F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.75 SCB0_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.76 SCB0_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40220F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.76 SCB0_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.77 SCB0_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40220F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.77 SCB0_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.78 SCB0_INTR_RX

Receiver interrupt request register.

Address: 0x40220FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.78 SCB0_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.79 SCB0_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40220FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.79 SCB0_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.80 SCB0_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40220FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.80 SCB0_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.81 SCB0_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40220FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.81 SCB0_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.82 SCB1_CTRL

Generic control register.

Address: 0x40230000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.82 SCB1_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.82 SCB1_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.82 SCB1_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.83 SCB1_STATUS

Generic status register.

Address: 0x40230004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.84 SCB1_CMD_RESP_CTRL

Command/response control register.

Address: 0x40230008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.85 SCB1_CMD_RESP_STATUS

Command/response status register.

Address: 0x4023000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.85 SCB1_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.86 SCB1_SPI_CTRL

SPI control register.

Address: 0x40230020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.86 SCB1_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.86 SCB1_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.87 SCB1_SPI_STATUS

SPI status register.

Address: 0x40230024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.88 SCB1_UART_CTRL

UART control register.

Address: 0x40230040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.89 SCB1_UART_TX_CTRL

UART transmitter control register.

Address: 0x40230044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.90 SCB1_UART_RX_CTRL

UART receiver control register.

Address: 0x40230048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.90 SCB1_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.90 SCB1_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.91 SCB1_UART_RX_STATUS

UART receiver status register.

Address: 0x4023004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.92 SCB1_UART_FLOW_CTRL

UART flow control register

Address: 0x40230050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.92 SCB1_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.93 SCB1_I2C_CTRL

I2C control register.

Address: 0x40230060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.93 SCB1_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.93 SCB1_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.94 SCB1_I2C_STATUS

I2C status register.

Address: 0x40230064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.94 SCB1_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.95 SCB1_I2C_M_CMD

I2C master command register.

Address: 0x40230068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.95 SCB1_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.96 SCB1_I2C_S_CMD

I2C slave command register.

Address: 0x4023006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.97 SCB1_I2C_CFG

I2C configuration register.

Address: 0x40230070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.97 SCB1_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.98 SCB1_TX_CTRL

Transmitter control register.

Address: 0x40230200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.99 SCB1_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40230204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.100 SCB1_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40230208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.101 SCB1_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40230240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.102 SCB1_RX_CTRL

Receiver control register.

Address: 0x40230300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.103 SCB1_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40230304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.104 SCB1_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40230308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.105 SCB1_RX_MATCH

Slave address and mask register.

Address: 0x40230310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.106 SCB1_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40230340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.107 SCB1_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40230344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.108 SCB1_EZ_DATA0

Memory buffer registers.

Address: 0x40230400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.109 SCB1_EZ_DATA1

Memory buffer registers.

Address: 0x40230404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.110 SCB1_EZ_DATA2

Memory buffer registers.

Address: 0x40230408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.111 SCB1_EZ_DATA3

Memory buffer registers.

Address: 0x4023040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.112 SCB1_EZ_DATA4

Memory buffer registers.

Address: 0x40230410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.113 SCB1_EZ_DATA5

Memory buffer registers.

Address: 0x40230414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.114 SCB1_EZ_DATA6

Memory buffer registers.

Address: 0x40230418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.115 SCB1_EZ_DATA7

Memory buffer registers.

Address: 0x4023041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.116 SCB1_EZ_DATA8

Memory buffer registers.

Address: 0x40230420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.117 SCB1_EZ_DATA9

Memory buffer registers.

Address: 0x40230424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.118 SCB1_EZ_DATA10

Memory buffer registers.

Address: 0x40230428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.119 SCB1_EZ_DATA11

Memory buffer registers.

Address: 0x4023042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.120 SCB1_EZ_DATA12

Memory buffer registers.

Address: 0x40230430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.121 SCB1_EZ_DATA13

Memory buffer registers.

Address: 0x40230434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.122 SCB1_EZ_DATA14

Memory buffer registers.

Address: 0x40230438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.123 SCB1_EZ_DATA15

Memory buffer registers.

Address: 0x4023043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.124 SCB1_EZ_DATA16

Memory buffer registers.

Address: 0x40230440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.125 SCB1_EZ_DATA17

Memory buffer registers.

Address: 0x40230444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.126 SCB1_EZ_DATA18

Memory buffer registers.

Address: 0x40230448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.127 SCB1_EZ_DATA19

Memory buffer registers.

Address: 0x4023044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.128 SCB1_EZ_DATA20

Memory buffer registers.

Address: 0x40230450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.129 SCB1_EZ_DATA21

Memory buffer registers.

Address: 0x40230454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.130 SCB1_EZ_DATA22

Memory buffer registers.

Address: 0x40230458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.131 SCB1_EZ_DATA23

Memory buffer registers.

Address: 0x4023045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.132 SCB1_EZ_DATA24

Memory buffer registers.

Address: 0x40230460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.133 SCB1_EZ_DATA25

Memory buffer registers.

Address: 0x40230464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.134 SCB1_EZ_DATA26

Memory buffer registers.

Address: 0x40230468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.135 SCB1_EZ_DATA27

Memory buffer registers.

Address: 0x4023046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.136 SCB1_EZ_DATA28

Memory buffer registers.

Address: 0x40230470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.137 SCB1_EZ_DATA29

Memory buffer registers.

Address: 0x40230474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.138 SCB1_EZ_DATA30

Memory buffer registers.

Address: 0x40230478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.139 SCB1_EZ_DATA31

Memory buffer registers.

Address: 0x4023047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.140 SCB1_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40230E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.141 SCB1_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40230E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.141 SCB1_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.142 SCB1_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40230E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.143 SCB1_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40230E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.144 SCB1_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40230EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.144 SCB1_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.145 SCB1_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40230EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.146 SCB1_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40230ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.147 SCB1_INTR_M

Master interrupt request register.

Address: 0x40230F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.148 SCB1_INTR_M_SET

Master interrupt set request register

Address: 0x40230F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.149 SCB1_INTR_M_MASK

Master interrupt mask register.

Address: 0x40230F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.150 SCB1_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40230F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.151 SCB1_INTR_S

Slave interrupt request register.

Address: 0x40230F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.151 SCB1_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.152 SCB1_INTR_S_SET

Slave interrupt set request register.

Address: 0x40230F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.152 SCB1_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.153 SCB1_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40230F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.153 SCB1_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.154 SCB1_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40230F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.154 SCB1_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.155 SCB1_INTR_TX

Transmitter interrupt request register.

Address: 0x40230F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.155 SCB1_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.156 SCB1_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40230F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.156 SCB1_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.157 SCB1_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40230F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.157 SCB1_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.158 SCB1_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40230F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.158 SCB1_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.159 SCB1_INTR_RX

Receiver interrupt request register.

Address: 0x40230FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.159 SCB1_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.160 SCB1_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40230FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.160 SCB1_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.161 SCB1_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40230FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.161 SCB1_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.162 SCB1_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40230FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.162 SCB1_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.163 SCB2_CTRL

Generic control register.

Address: 0x40240000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.163 SCB2_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.163 SCB2_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.163 SCB2_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.164 SCB2_STATUS

Generic status register.

Address: 0x40240004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.165 SCB2_CMD_RESP_CTRL

Command/response control register.

Address: 0x40240008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.166 SCB2_CMD_RESP_STATUS

Command/response status register.

Address: 0x4024000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.166 SCB2_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.167 SCB2_SPI_CTRL

SPI control register.

Address: 0x40240020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.167 SCB2_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.167 SCB2_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.168 SCB2_SPI_STATUS

SPI status register.

Address: 0x40240024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.169 SCB2_UART_CTRL

UART control register.

Address: 0x40240040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.170 SCB2_UART_TX_CTRL

UART transmitter control register.

Address: 0x40240044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.171 SCB2_UART_RX_CTRL

UART receiver control register.

Address: 0x40240048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.171 SCB2_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.171 SCB2_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.172 SCB2_UART_RX_STATUS

UART receiver status register.

Address: 0x4024004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.173 SCB2_UART_FLOW_CTRL

UART flow control register

Address: 0x40240050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.173 SCB2_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.174 SCB2_I2C_CTRL

I2C control register.

Address: 0x40240060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.174 SCB2_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.174 SCB2_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.175 SCB2_I2C_STATUS

I2C status register.

Address: 0x40240064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.175 SCB2_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.176 SCB2_I2C_M_CMD

I2C master command register.

Address: 0x40240068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.176 SCB2_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.177 SCB2_I2C_S_CMD

I2C slave command register.

Address: 0x4024006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.178 SCB2_I2C_CFG

I2C configuration register.

Address: 0x40240070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.178 SCB2_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.179 SCB2_TX_CTRL

Transmitter control register.

Address: 0x40240200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.180 SCB2_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40240204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.181 SCB2_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40240208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.182 SCB2_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40240240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.183 SCB2_RX_CTRL

Receiver control register.

Address: 0x40240300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.184 SCB2_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40240304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.185 SCB2_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40240308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.186 SCB2_RX_MATCH

Slave address and mask register.

Address: 0x40240310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.187 SCB2_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40240340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.188 SCB2_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40240344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.189 SCB2_EZ_DATA0

Memory buffer registers.

Address: 0x40240400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.190 SCB2_EZ_DATA1

Memory buffer registers.

Address: 0x40240404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.191 SCB2_EZ_DATA2

Memory buffer registers.

Address: 0x40240408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.192 SCB2_EZ_DATA3

Memory buffer registers.

Address: 0x4024040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.193 SCB2_EZ_DATA4

Memory buffer registers.

Address: 0x40240410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.194 SCB2_EZ_DATA5

Memory buffer registers.

Address: 0x40240414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.195 SCB2_EZ_DATA6

Memory buffer registers.

Address: 0x40240418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.196 SCB2_EZ_DATA7

Memory buffer registers.

Address: 0x4024041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.197 SCB2_EZ_DATA8

Memory buffer registers.

Address: 0x40240420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.198 SCB2_EZ_DATA9

Memory buffer registers.

Address: 0x40240424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.199 SCB2_EZ_DATA10

Memory buffer registers.

Address: 0x40240428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.200 SCB2_EZ_DATA11

Memory buffer registers.

Address: 0x4024042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.201 SCB2_EZ_DATA12

Memory buffer registers.

Address: 0x40240430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.202 SCB2_EZ_DATA13

Memory buffer registers.

Address: 0x40240434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.203 SCB2_EZ_DATA14

Memory buffer registers.

Address: 0x40240438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.204 SCB2_EZ_DATA15

Memory buffer registers.

Address: 0x4024043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.205 SCB2_EZ_DATA16

Memory buffer registers.

Address: 0x40240440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.206 SCB2_EZ_DATA17

Memory buffer registers.

Address: 0x40240444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.207 SCB2_EZ_DATA18

Memory buffer registers.

Address: 0x40240448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.208 SCB2_EZ_DATA19

Memory buffer registers.

Address: 0x4024044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.209 SCB2_EZ_DATA20

Memory buffer registers.

Address: 0x40240450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.210 SCB2_EZ_DATA21

Memory buffer registers.

Address: 0x40240454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.211 SCB2_EZ_DATA22

Memory buffer registers.

Address: 0x40240458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.212 SCB2_EZ_DATA23

Memory buffer registers.

Address: 0x4024045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.213 SCB2_EZ_DATA24

Memory buffer registers.

Address: 0x40240460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.214 SCB2_EZ_DATA25

Memory buffer registers.

Address: 0x40240464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.215 SCB2_EZ_DATA26

Memory buffer registers.

Address: 0x40240468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.216 SCB2_EZ_DATA27

Memory buffer registers.

Address: 0x4024046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.217 SCB2_EZ_DATA28

Memory buffer registers.

Address: 0x40240470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.218 SCB2_EZ_DATA29

Memory buffer registers.

Address: 0x40240474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.219 SCB2_EZ_DATA30

Memory buffer registers.

Address: 0x40240478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.220 SCB2_EZ_DATA31

Memory buffer registers.

Address: 0x4024047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.221 SCB2_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40240E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.222 SCB2_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40240E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.222 SCB2_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.223 SCB2_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40240E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.224 SCB2_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40240E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.225 SCB2_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40240EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.225 SCB2_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.226 SCB2_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40240EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.227 SCB2_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40240ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.228 SCB2_INTR_M

Master interrupt request register.

Address: 0x40240F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.229 SCB2_INTR_M_SET

Master interrupt set request register

Address: 0x40240F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.230 SCB2_INTR_M_MASK

Master interrupt mask register.

Address: 0x40240F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.231 SCB2_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40240F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.232 SCB2_INTR_S

Slave interrupt request register.

Address: 0x40240F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.232 SCB2_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.233 SCB2_INTR_S_SET

Slave interrupt set request register.

Address: 0x40240F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.233 SCB2_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.234 SCB2_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40240F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.234 SCB2_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.235 SCB2_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40240F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.235 SCB2_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.236 SCB2_INTR_TX

Transmitter interrupt request register.

Address: 0x40240F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.236 SCB2_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.237 SCB2_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40240F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.237 SCB2_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.238 SCB2_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40240F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.238 SCB2_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.239 SCB2_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40240F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.239 SCB2_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.240 SCB2_INTR_RX

Receiver interrupt request register.

Address: 0x40240FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.240 SCB2_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.241 SCB2_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40240FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.241 SCB2_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.242 SCB2_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40240FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.242 SCB2_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.243 SCB2_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40240FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.243 SCB2_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.244 SCB3_CTRL

Generic control register.

Address: 0x40250000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.244 SCB3_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.244 SCB3_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.244 SCB3_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.245 SCB3_STATUS

Generic status register.

Address: 0x40250004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.246 SCB3_CMD_RESP_CTRL

Command/response control register.

Address: 0x40250008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.247 SCB3_CMD_RESP_STATUS

Command/response status register.

Address: 0x4025000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.247 SCB3_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.248 SCB3_SPI_CTRL

SPI control register.

Address: 0x40250020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.248 SCB3_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.248 SCB3_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.249 SCB3_SPI_STATUS

SPI status register.

Address: 0x40250024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.250 SCB3_UART_CTRL

UART control register.

Address: 0x40250040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.251 SCB3_UART_TX_CTRL

UART transmitter control register.

Address: 0x40250044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.252 SCB3_UART_RX_CTRL

UART receiver control register.

Address: 0x40250048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.252 SCB3_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.252 SCB3_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.253 SCB3_UART_RX_STATUS

UART receiver status register.

Address: 0x4025004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.254 SCB3_UART_FLOW_CTRL

UART flow control register

Address: 0x40250050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.254 SCB3_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.255 SCB3_I2C_CTRL

I2C control register.

Address: 0x40250060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.255 SCB3_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.255 SCB3_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.256 SCB3_I2C_STATUS

I2C status register.

Address: 0x40250064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.256 SCB3_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.257 SCB3_I2C_M_CMD

I2C master command register.

Address: 0x40250068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.257 SCB3_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.258 SCB3_I2C_S_CMD

I2C slave command register.

Address: 0x4025006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.259 SCB3_I2C_CFG

I2C configuration register.

Address: 0x40250070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.259 SCB3_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.260 SCB3_TX_CTRL

Transmitter control register.

Address: 0x40250200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.261 SCB3_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40250204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.262 SCB3_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40250208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.263 SCB3_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40250240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.264 SCB3_RX_CTRL

Receiver control register.

Address: 0x40250300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.265 SCB3_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40250304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.266 SCB3_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40250308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.267 SCB3_RX_MATCH

Slave address and mask register.

Address: 0x40250310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.268 SCB3_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40250340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.269 SCB3_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40250344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.270 SCB3_EZ_DATA0

Memory buffer registers.

Address: 0x40250400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.271 SCB3_EZ_DATA1

Memory buffer registers.

Address: 0x40250404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.272 SCB3_EZ_DATA2

Memory buffer registers.

Address: 0x40250408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.273 SCB3_EZ_DATA3

Memory buffer registers.

Address: 0x4025040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.274 SCB3_EZ_DATA4

Memory buffer registers.

Address: 0x40250410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.275 SCB3_EZ_DATA5

Memory buffer registers.

Address: 0x40250414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.276 SCB3_EZ_DATA6

Memory buffer registers.

Address: 0x40250418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.277 SCB3_EZ_DATA7

Memory buffer registers.

Address: 0x4025041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.278 SCB3_EZ_DATA8

Memory buffer registers.

Address: 0x40250420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.279 SCB3_EZ_DATA9

Memory buffer registers.

Address: 0x40250424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.280 SCB3_EZ_DATA10

Memory buffer registers.

Address: 0x40250428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.281 SCB3_EZ_DATA11

Memory buffer registers.

Address: 0x4025042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.282 SCB3_EZ_DATA12

Memory buffer registers.

Address: 0x40250430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.283 SCB3_EZ_DATA13

Memory buffer registers.

Address: 0x40250434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.284 SCB3_EZ_DATA14

Memory buffer registers.

Address: 0x40250438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.285 SCB3_EZ_DATA15

Memory buffer registers.

Address: 0x4025043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.286 SCB3_EZ_DATA16

Memory buffer registers.

Address: 0x40250440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.287 SCB3_EZ_DATA17

Memory buffer registers.

Address: 0x40250444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.288 SCB3_EZ_DATA18

Memory buffer registers.

Address: 0x40250448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.289 SCB3_EZ_DATA19

Memory buffer registers.

Address: 0x4025044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.290 SCB3_EZ_DATA20

Memory buffer registers.

Address: 0x40250450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.291 SCB3_EZ_DATA21

Memory buffer registers.

Address: 0x40250454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.292 SCB3_EZ_DATA22

Memory buffer registers.

Address: 0x40250458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.293 SCB3_EZ_DATA23

Memory buffer registers.

Address: 0x4025045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.294 SCB3_EZ_DATA24

Memory buffer registers.

Address: 0x40250460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.295 SCB3_EZ_DATA25

Memory buffer registers.

Address: 0x40250464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.296 SCB3_EZ_DATA26

Memory buffer registers.

Address: 0x40250468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.297 SCB3_EZ_DATA27

Memory buffer registers.

Address: 0x4025046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.298 SCB3_EZ_DATA28

Memory buffer registers.

Address: 0x40250470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.299 SCB3_EZ_DATA29

Memory buffer registers.

Address: 0x40250474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.300 SCB3_EZ_DATA30

Memory buffer registers.

Address: 0x40250478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.301 SCB3_EZ_DATA31

Memory buffer registers.

Address: 0x4025047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.302 SCB3_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40250E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.303 SCB3_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40250E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.303 SCB3_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.304 SCB3_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40250E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.305 SCB3_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40250E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.306 SCB3_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40250EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.306 SCB3_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.307 SCB3_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40250EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.308 SCB3_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40250ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.309 SCB3_INTR_M

Master interrupt request register.

Address: 0x40250F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.310 SCB3_INTR_M_SET

Master interrupt set request register

Address: 0x40250F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.311 SCB3_INTR_M_MASK

Master interrupt mask register.

Address: 0x40250F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.312 SCB3_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40250F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.313 SCB3_INTR_S

Slave interrupt request register.

Address: 0x40250F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.313 SCB3_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.314 SCB3_INTR_S_SET

Slave interrupt set request register.

Address: 0x40250F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.314 SCB3_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.315 SCB3_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40250F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.315 SCB3_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.316 SCB3_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40250F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.316 SCB3_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.317 SCB3_INTR_TX

Transmitter interrupt request register.

Address: 0x40250F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.317 SCB3_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.318 SCB3_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40250F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.318 SCB3_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.319 SCB3_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40250F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.319 SCB3_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.320 SCB3_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40250F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.320 SCB3_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.321 SCB3_INTR_RX

Receiver interrupt request register.

Address: 0x40250FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.321 SCB3_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.322 SCB3_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40250FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.322 SCB3_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.323 SCB3_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40250FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.323 SCB3_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.324 SCB3_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40250FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.324 SCB3_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.325 SCB4_CTRL

Generic control register.

Address: 0x40260000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.325 SCB4_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.325 SCB4_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.325 SCB4_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.326 SCB4_STATUS

Generic status register.

Address: 0x40260004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.327 SCB4_CMD_RESP_CTRL

Command/response control register.

Address: 0x40260008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.328 SCB4_CMD_RESP_STATUS

Command/response status register.

Address: 0x4026000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.328 SCB4_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.329 SCB4_SPI_CTRL

SPI control register.

Address: 0x40260020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.329 SCB4_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.329 SCB4_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.330 SCB4_SPI_STATUS

SPI status register.

Address: 0x40260024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.331 SCB4_UART_CTRL

UART control register.

Address: 0x40260040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.332 SCB4_UART_TX_CTRL

UART transmitter control register.

Address: 0x40260044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.333 SCB4_UART_RX_CTRL

UART receiver control register.

Address: 0x40260048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.333 SCB4_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.333 SCB4_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.334 SCB4_UART_RX_STATUS

UART receiver status register.

Address: 0x4026004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.335 SCB4_UART_FLOW_CTRL

UART flow control register

Address: 0x40260050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.335 SCB4_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.336 SCB4_I2C_CTRL

I2C control register.

Address: 0x40260060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.336 SCB4_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.336 SCB4_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.337 SCB4_I2C_STATUS

I2C status register.

Address: 0x40260064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.337 SCB4_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.338 SCB4_I2C_M_CMD

I2C master command register.

Address: 0x40260068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.338 SCB4_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.339 SCB4_I2C_S_CMD

I2C slave command register.

Address: 0x4026006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.340 SCB4_I2C_CFG

I2C configuration register.

Address: 0x40260070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.340 SCB4_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.341 SCB4_TX_CTRL

Transmitter control register.

Address: 0x40260200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.342 SCB4_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40260204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.343 SCB4_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40260208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.344 SCB4_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40260240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.345 SCB4_RX_CTRL

Receiver control register.

Address: 0x40260300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.346 SCB4_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40260304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.347 SCB4_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40260308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.348 SCB4_RX_MATCH

Slave address and mask register.

Address: 0x40260310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.349 SCB4_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40260340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.350 SCB4_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40260344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.351 SCB4_EZ_DATA0

Memory buffer registers.

Address: 0x40260400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.352 SCB4_EZ_DATA1

Memory buffer registers.

Address: 0x40260404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.353 SCB4_EZ_DATA2

Memory buffer registers.

Address: 0x40260408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.354 SCB4_EZ_DATA3

Memory buffer registers.

Address: 0x4026040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.355 SCB4_EZ_DATA4

Memory buffer registers.

Address: 0x40260410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.356 SCB4_EZ_DATA5

Memory buffer registers.

Address: 0x40260414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.357 SCB4_EZ_DATA6

Memory buffer registers.

Address: 0x40260418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.358 SCB4_EZ_DATA7

Memory buffer registers.

Address: 0x4026041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.359 SCB4_EZ_DATA8

Memory buffer registers.

Address: 0x40260420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.360 SCB4_EZ_DATA9

Memory buffer registers.

Address: 0x40260424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.361 SCB4_EZ_DATA10

Memory buffer registers.

Address: 0x40260428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.362 SCB4_EZ_DATA11

Memory buffer registers.

Address: 0x4026042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.363 SCB4_EZ_DATA12

Memory buffer registers.

Address: 0x40260430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.364 SCB4_EZ_DATA13

Memory buffer registers.

Address: 0x40260434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.365 SCB4_EZ_DATA14

Memory buffer registers.

Address: 0x40260438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.366 SCB4_EZ_DATA15

Memory buffer registers.

Address: 0x4026043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.367 SCB4_EZ_DATA16

Memory buffer registers.

Address: 0x40260440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.368 SCB4_EZ_DATA17

Memory buffer registers.

Address: 0x40260444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.369 SCB4_EZ_DATA18

Memory buffer registers.

Address: 0x40260448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.370 SCB4_EZ_DATA19

Memory buffer registers.

Address: 0x4026044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.371 SCB4_EZ_DATA20

Memory buffer registers.

Address: 0x40260450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.372 SCB4_EZ_DATA21

Memory buffer registers.

Address: 0x40260454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.373 SCB4_EZ_DATA22

Memory buffer registers.

Address: 0x40260458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.374 SCB4_EZ_DATA23

Memory buffer registers.

Address: 0x4026045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.375 SCB4_EZ_DATA24

Memory buffer registers.

Address: 0x40260460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.376 SCB4_EZ_DATA25

Memory buffer registers.

Address: 0x40260464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.377 SCB4_EZ_DATA26

Memory buffer registers.

Address: 0x40260468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.378 SCB4_EZ_DATA27

Memory buffer registers.

Address: 0x4026046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.379 SCB4_EZ_DATA28

Memory buffer registers.

Address: 0x40260470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.380 SCB4_EZ_DATA29

Memory buffer registers.

Address: 0x40260474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.381 SCB4_EZ_DATA30

Memory buffer registers.

Address: 0x40260478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.382 SCB4_EZ_DATA31

Memory buffer registers.

Address: 0x4026047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.383 SCB4_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40260E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.384 SCB4_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40260E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.384 SCB4_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.385 SCB4_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40260E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.386 SCB4_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40260E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.387 SCB4_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40260EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.387 SCB4_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.388 SCB4_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40260EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.389 SCB4_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40260ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.390 SCB4_INTR_M

Master interrupt request register.

Address: 0x40260F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.391 SCB4_INTR_M_SET

Master interrupt set request register

Address: 0x40260F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.392 SCB4_INTR_M_MASK

Master interrupt mask register.

Address: 0x40260F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.393 SCB4_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40260F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.394 SCB4_INTR_S

Slave interrupt request register.

Address: 0x40260F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.394 SCB4_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.395 SCB4_INTR_S_SET

Slave interrupt set request register.

Address: 0x40260F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.395 SCB4_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.396 SCB4_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40260F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.396 SCB4_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.397 SCB4_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40260F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.397 SCB4_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.398 SCB4_INTR_TX

Transmitter interrupt request register.

Address: 0x40260F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.398 SCB4_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.399 SCB4_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40260F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.399 SCB4_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.400 SCB4_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40260F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.400 SCB4_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.401 SCB4_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40260F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.401 SCB4_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.402 SCB4_INTR_RX

Receiver interrupt request register.

Address: 0x40260FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.402 SCB4_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.403 SCB4_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40260FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.403 SCB4_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.404 SCB4_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40260FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.404 SCB4_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.405 SCB4_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40260FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.405 SCB4_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.406 SCB5_CTRL

Generic control register.

Address: 0x40270000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.406 SCB5_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.406 SCB5_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.406 SCB5_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.407 SCB5_STATUS

Generic status register.

Address: 0x40270004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.408 SCB5_CMD_RESP_CTRL

Command/response control register.

Address: 0x40270008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.409 SCB5_CMD_RESP_STATUS

Command/response status register.

Address: 0x4027000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.409 SCB5_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.410 SCB5_SPI_CTRL

SPI control register.

Address: 0x40270020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.410 SCB5_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.410 SCB5_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.411 SCB5_SPI_STATUS

SPI status register.

Address: 0x40270024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.412 SCB5_UART_CTRL

UART control register.

Address: 0x40270040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.413 SCB5_UART_TX_CTRL

UART transmitter control register.

Address: 0x40270044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.414 SCB5_UART_RX_CTRL

UART receiver control register.

Address: 0x40270048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.414 SCB5_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.414 SCB5_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.415 SCB5_UART_RX_STATUS

UART receiver status register.

Address: 0x4027004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.416 SCB5_UART_FLOW_CTRL

UART flow control register

Address: 0x40270050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.416 SCB5_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.417 SCB5_I2C_CTRL

I2C control register.

Address: 0x40270060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.417 SCB5_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.417 SCB5_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.418 SCB5_I2C_STATUS

I2C status register.

Address: 0x40270064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.418 SCB5_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.419 SCB5_I2C_M_CMD

I2C master command register.

Address: 0x40270068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.419 SCB5_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.420 SCB5_I2C_S_CMD

I2C slave command register.

Address: 0x4027006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.421 SCB5_I2C_CFG

I2C configuration register.

Address: 0x40270070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.421 SCB5_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.422 SCB5_TX_CTRL

Transmitter control register.

Address: 0x40270200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.423 SCB5_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40270204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.424 SCB5_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40270208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.425 SCB5_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40270240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.426 SCB5_RX_CTRL

Receiver control register.

Address: 0x40270300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.427 SCB5_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40270304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.428 SCB5_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40270308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.429 SCB5_RX_MATCH

Slave address and mask register.

Address: 0x40270310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.430 SCB5_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40270340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.431 SCB5_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40270344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.432 SCB5_EZ_DATA0

Memory buffer registers.

Address: 0x40270400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.433 SCB5_EZ_DATA1

Memory buffer registers.

Address: 0x40270404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.434 SCB5_EZ_DATA2

Memory buffer registers.

Address: 0x40270408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.435 SCB5_EZ_DATA3

Memory buffer registers.

Address: 0x4027040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.436 SCB5_EZ_DATA4

Memory buffer registers.

Address: 0x40270410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.437 SCB5_EZ_DATA5

Memory buffer registers.

Address: 0x40270414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.438 SCB5_EZ_DATA6

Memory buffer registers.

Address: 0x40270418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.439 SCB5_EZ_DATA7

Memory buffer registers.

Address: 0x4027041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.440 SCB5_EZ_DATA8

Memory buffer registers.

Address: 0x40270420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.441 SCB5_EZ_DATA9

Memory buffer registers.

Address: 0x40270424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.442 SCB5_EZ_DATA10

Memory buffer registers.

Address: 0x40270428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.443 SCB5_EZ_DATA11

Memory buffer registers.

Address: 0x4027042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.444 SCB5_EZ_DATA12

Memory buffer registers.

Address: 0x40270430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.445 SCB5_EZ_DATA13

Memory buffer registers.

Address: 0x40270434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.446 SCB5_EZ_DATA14

Memory buffer registers.

Address: 0x40270438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.447 SCB5_EZ_DATA15

Memory buffer registers.

Address: 0x4027043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.448 SCB5_EZ_DATA16

Memory buffer registers.

Address: 0x40270440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.449 SCB5_EZ_DATA17

Memory buffer registers.

Address: 0x40270444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.450 SCB5_EZ_DATA18

Memory buffer registers.

Address: 0x40270448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.451 SCB5_EZ_DATA19

Memory buffer registers.

Address: 0x4027044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.452 SCB5_EZ_DATA20

Memory buffer registers.

Address: 0x40270450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.453 SCB5_EZ_DATA21

Memory buffer registers.

Address: 0x40270454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.454 SCB5_EZ_DATA22

Memory buffer registers.

Address: 0x40270458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.455 SCB5_EZ_DATA23

Memory buffer registers.

Address: 0x4027045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.456 SCB5_EZ_DATA24

Memory buffer registers.

Address: 0x40270460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.457 SCB5_EZ_DATA25

Memory buffer registers.

Address: 0x40270464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.458 SCB5_EZ_DATA26

Memory buffer registers.

Address: 0x40270468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.459 SCB5_EZ_DATA27

Memory buffer registers.

Address: 0x4027046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.460 SCB5_EZ_DATA28

Memory buffer registers.

Address: 0x40270470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.461 SCB5_EZ_DATA29

Memory buffer registers.

Address: 0x40270474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.462 SCB5_EZ_DATA30

Memory buffer registers.

Address: 0x40270478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.463 SCB5_EZ_DATA31

Memory buffer registers.

Address: 0x4027047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.464 SCB5_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40270E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.465 SCB5_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40270E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.465 SCB5_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.466 SCB5_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40270E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.467 SCB5_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40270E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.468 SCB5_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40270EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.468 SCB5_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.469 SCB5_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40270EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.470 SCB5_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40270ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.471 SCB5_INTR_M

Master interrupt request register.

Address: 0x40270F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.472 SCB5_INTR_M_SET

Master interrupt set request register

Address: 0x40270F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.473 SCB5_INTR_M_MASK

Master interrupt mask register.

Address: 0x40270F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.474 SCB5_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40270F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.475 SCB5_INTR_S

Slave interrupt request register.

Address: 0x40270F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.475 SCB5_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.476 SCB5_INTR_S_SET

Slave interrupt set request register.

Address: 0x40270F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.476 SCB5_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.477 SCB5_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40270F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.477 SCB5_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.478 SCB5_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40270F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.478 SCB5_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.479 SCB5_INTR_TX

Transmitter interrupt request register.

Address: 0x40270F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.479 SCB5_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.480 SCB5_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40270F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.480 SCB5_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.481 SCB5_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40270F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.481 SCB5_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.482 SCB5_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40270F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.482 SCB5_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.483 SCB5_INTR_RX

Receiver interrupt request register.

Address: 0x40270FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.483 SCB5_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.484 SCB5_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40270FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.484 SCB5_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.485 SCB5_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40270FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.485 SCB5_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.486 SCB5_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40270FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.486 SCB5_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.487 SCB6_CTRL

Generic control register.

Address: 0x40280000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.487 SCB6_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.487 SCB6_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.487 SCB6_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.488 SCB6_STATUS

Generic status register.

Address: 0x40280004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.489 SCB6_CMD_RESP_CTRL

Command/response control register.

Address: 0x40280008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.490 SCB6_CMD_RESP_STATUS

Command/response status register.

Address: 0x4028000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.490 SCB6_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.491 SCB6_SPI_CTRL

SPI control register.

Address: 0x40280020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.491 SCB6_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.491 SCB6_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.492 SCB6_SPI_STATUS

SPI status register.

Address: 0x40280024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.493 SCB6_UART_CTRL

UART control register.

Address: 0x40280040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.494 SCB6_UART_TX_CTRL

UART transmitter control register.

Address: 0x40280044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.495 SCB6_UART_RX_CTRL

UART receiver control register.

Address: 0x40280048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.495 SCB6_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.495 SCB6_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.496 SCB6_UART_RX_STATUS

UART receiver status register.

Address: 0x4028004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.497 SCB6_UART_FLOW_CTRL

UART flow control register

Address: 0x40280050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.497 SCB6_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.498 SCB6_I2C_CTRL

I2C control register.

Address: 0x40280060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.498 SCB6_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.498 SCB6_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.499 SCB6_I2C_STATUS

I2C status register.

Address: 0x40280064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.499 SCB6_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.500 SCB6_I2C_M_CMD

I2C master command register.

Address: 0x40280068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.500 SCB6_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.501 SCB6_I2C_S_CMD

I2C slave command register.

Address: 0x4028006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.502 SCB6_I2C_CFG

I2C configuration register.

Address: 0x40280070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.502 SCB6_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.503 SCB6_TX_CTRL

Transmitter control register.

Address: 0x40280200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.504 SCB6_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40280204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.505 SCB6_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40280208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.506 SCB6_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40280240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.507 SCB6_RX_CTRL

Receiver control register.

Address: 0x40280300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.508 SCB6_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40280304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.509 SCB6_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40280308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.510 SCB6_RX_MATCH

Slave address and mask register.

Address: 0x40280310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.511 SCB6_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40280340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.512 SCB6_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40280344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.513 SCB6_EZ_DATA0

Memory buffer registers.

Address: 0x40280400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.514 SCB6_EZ_DATA1

Memory buffer registers.

Address: 0x40280404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.515 SCB6_EZ_DATA2

Memory buffer registers.

Address: 0x40280408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.516 SCB6_EZ_DATA3

Memory buffer registers.

Address: 0x4028040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.517 SCB6_EZ_DATA4

Memory buffer registers.

Address: 0x40280410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.518 SCB6_EZ_DATA5

Memory buffer registers.

Address: 0x40280414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.519 SCB6_EZ_DATA6

Memory buffer registers.

Address: 0x40280418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.520 SCB6_EZ_DATA7

Memory buffer registers.

Address: 0x4028041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.521 SCB6_EZ_DATA8

Memory buffer registers.

Address: 0x40280420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.522 SCB6_EZ_DATA9

Memory buffer registers.

Address: 0x40280424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.523 SCB6_EZ_DATA10

Memory buffer registers.

Address: 0x40280428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.524 SCB6_EZ_DATA11

Memory buffer registers.

Address: 0x4028042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.525 SCB6_EZ_DATA12

Memory buffer registers.

Address: 0x40280430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.526 SCB6_EZ_DATA13

Memory buffer registers.

Address: 0x40280434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.527 SCB6_EZ_DATA14

Memory buffer registers.

Address: 0x40280438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.528 SCB6_EZ_DATA15

Memory buffer registers.

Address: 0x4028043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.529 SCB6_EZ_DATA16

Memory buffer registers.

Address: 0x40280440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.530 SCB6_EZ_DATA17

Memory buffer registers.

Address: 0x40280444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.531 SCB6_EZ_DATA18

Memory buffer registers.

Address: 0x40280448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.532 SCB6_EZ_DATA19

Memory buffer registers.

Address: 0x4028044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.533 SCB6_EZ_DATA20

Memory buffer registers.

Address: 0x40280450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.534 SCB6_EZ_DATA21

Memory buffer registers.

Address: 0x40280454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.535 SCB6_EZ_DATA22

Memory buffer registers.

Address: 0x40280458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.536 SCB6_EZ_DATA23

Memory buffer registers.

Address: 0x4028045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.537 SCB6_EZ_DATA24

Memory buffer registers.

Address: 0x40280460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.538 SCB6_EZ_DATA25

Memory buffer registers.

Address: 0x40280464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.539 SCB6_EZ_DATA26

Memory buffer registers.

Address: 0x40280468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.540 SCB6_EZ_DATA27

Memory buffer registers.

Address: 0x4028046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.541 SCB6_EZ_DATA28

Memory buffer registers.

Address: 0x40280470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.542 SCB6_EZ_DATA29

Memory buffer registers.

Address: 0x40280474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.543 SCB6_EZ_DATA30

Memory buffer registers.

Address: 0x40280478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.544 SCB6_EZ_DATA31

Memory buffer registers.

Address: 0x4028047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.545 SCB6_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40280E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.546 SCB6_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40280E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.546 SCB6_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.547 SCB6_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40280E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.548 SCB6_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40280E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.549 SCB6_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40280EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.549 SCB6_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.550 SCB6_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40280EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.551 SCB6_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40280ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.552 SCB6_INTR_M

Master interrupt request register.

Address: 0x40280F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.553 SCB6_INTR_M_SET

Master interrupt set request register

Address: 0x40280F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.554 SCB6_INTR_M_MASK

Master interrupt mask register.

Address: 0x40280F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.555 SCB6_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40280F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.556 SCB6_INTR_S

Slave interrupt request register.

Address: 0x40280F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.556 SCB6_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.557 SCB6_INTR_S_SET

Slave interrupt set request register.

Address: 0x40280F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.557 SCB6_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.558 SCB6_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40280F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.558 SCB6_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.559 SCB6_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40280F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.559 SCB6_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.560 SCB6_INTR_TX

Transmitter interrupt request register.

Address: 0x40280F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.560 SCB6_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.561 SCB6_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40280F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.561 SCB6_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.562 SCB6_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40280F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.562 SCB6_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.563 SCB6_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40280F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.563 SCB6_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.564 SCB6_INTR_RX

Receiver interrupt request register.

Address: 0x40280FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.564 SCB6_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.565 SCB6_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40280FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.565 SCB6_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.566 SCB6_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40280FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.566 SCB6_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.567 SCB6_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40280FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.567 SCB6_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.568 SCB7_CTRL

Generic control register.

Address: 0x40290000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [15:13]			CMD_RESP_MODE	BYTE_MODE	EZ_MODE	EC_OP_MODE	EC_AM_MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_ACCEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	IP enabled ('1') or not ('0'). The proper order in which to initialize the IP is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL to enable IP, select the specific operation mode and oversampling factor. When the IP is enabled, no control information should be changed. Changes should be made AFTER disabling the IP, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the IP is re-enabled. Note that disabling the IP will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Mode of operation (3: Reserved) Default Value: 3 **0x0: I2C:** Inter-Integrated Circuits (I2C) mode.

18.1.568 SCB7_CTRL (continued)

		0x1: SPI: Serial Peripheral Interface (SPI) mode. **0x2: UART:** Universal Asynchronous Receiver/Transmitter (UART) mode.
17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the MMIO SW accesses to EZ memory coincide/collide, this bit determines whether a SW access should block and result in bus wait states ('BLOCK is 1') or not (BLOCK is '0'). IF BLOCK is '0' and the accesses collide, MMIO read operations return 0xffff:ffff and MMIO write operations are ignored. Colliding accesses are registered as interrupt causes: field BLOCKED of MMIO registers INTR_TX and INTR_RX. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when ADDR_ACCEPT is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
12	CMD_RESP_MODE	Determines CMD_RESP mode of operation: '0': CMD_RESP mode disabled. '1': CMD_RESP mode enabled (also requires EC_AM_MODE and EC_OP_MODE to be set to '1'). Default Value: 0
11	BYTE_MODE	Determines the number of bits per FIFO data element: '0': 16-bit FIFO data elements. '1': 8-bit FIFO data elements. This mode doubles the amount of FIFO entries, but TX_CTRL.DATA_WIDTH and RX_CTRL.DATA_WIDTH are restricted to [0, 7]. Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames mot seperated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	Internally clocked mode ('0') or externally clocked mode ('1') operation. In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.568 SCB7_CTRL (continued)

8	EC_AM_MODE	Internally clocked mode ('0') or externally clocked mode ('1') address matching (I2C) or selection (SPI). In internally clocked mode, the serial interface protocols run off the peripheral clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.568 SCB7_CTRL (continued)

3 : 0	OVS	Serial interface bit period oversampling factor expressed in IP clock cycles. Used for SPI and UART functionality. OVS + 1 IP clock cycles constitute a single serial interface clock/bit cycle. The IP clock is provided by the programmable clock IP. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the first and second phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the first phase of the interface clock period is 1 peripheral clock cycle longer than the second phase of the interface clock period. In SPI master mode, the valid range is [3, 15]. At an IP frequency of 48 MHz, the maximum IP bit rate is 12 Mbps. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock "spi_clk_out" to SPI MISO input "spi_miso_in" round trip delay is introducing significant delays (multiple "spi_clk_out" cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate. The maximum IP bit rate of 12 Mbps provides an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the IP clock wrt. the interface (IF) clock to guarantee functional correct behavior. This requirement is expressed as a ratio: IP clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE): - MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 6. At a IP frequency of 48 MHz, the maximum bit rate is 8 Mbps. - MEDIAN is '0' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 3. At a IP frequency of 48 MHz, the maximum bit rate is 16 Mbps. - MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": IP clock/IF clock >= 8. At a IP frequency of 48 MHz, the maximum bit rate is 6 Mbps. - MEDIAN is '1' and external SPI master has "late MISO sample functionality": IP clock/IF clock >= 4. At a IP frequency of 48 MHz, the maximum bit rate is 12 Mbps. The maximum bit rates provide an IP centric perspective, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The required IP clock/IF clock ratio increases and the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15]. In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value: - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two IP clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two IP clock cycles and greater or equal than one IP clock cycle may be detected by the receiver. Pulse widths less than one IP clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The IP clock (as provided by the programmable clock IP) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. IP clock frequency of 16*57.6 KHz for 57.6 Kbps. IP clock frequency of 16*38.4 KHz for 38.4 Kbps. IP clock frequency of 16*19.2 KHz for 19.2 Kbps. IP clock frequency of 16*9.6 KHz for 9.6 Kbps. IP clock frequency of 16*2.4 KHz for 2.4 Kbps. IP clock frequency of 16*1.2 KHz for 1.2 Kbps. - all other values are not used in normal mode. Low power mode, OVS field values (with the required IP clock frequency): - 0: 16 times oversampling. IP clock frequency of 16*115.2 KHz for 115.2 Kbps. - 1: 32 times oversampling. IP clock frequency of 32*57.6 KHz for 57.6 Kbps. - 2: 48 times oversampling. IP clock frequency of 48*38.4 KHz for 38.4 Kbps. - 3: 96 times oversampling. IP clock frequency of 96*19.2 KHz for 19.2 Kbps. - 4: 192 times oversampling. IP clock frequency of 192*9.6 KHz for 9.6 Kbps. - 5: 768 times oversampling. IP clock frequency of 768*2.4 KHz for 2.4 Kbps. - 6: 1536 times oversampling. IP clock frequency of 1536*1.2 KHz for 1.2 Kbps. - all other values are not used in low power mode. Default Value: 15

18.1.569 SCB7_STATUS

Generic status register.

Address: 0x40290004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.570 SCB7_CMD_RESP_CTRL

Command/response control register.

Address: 0x40290008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			BASE_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW				
HW Access	None			R				
Name	None [23:21]			BASE_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 16	BASE_WR_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode write transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode write transfer (CTRL.MODE is SPI): at the start of a write transfer BASE_WE_ADDR is copied to CMD_RESP_STATUS.CURR_WR_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0
4 : 0	BASE_RD_ADDR	I2C/SPI read base address for CMD_RESP mode. Address is used by a I2C CMD_RESP mode read transfer (CTRL.MODE is I2C) or a SPI CMD_RESP mode read transfer (CTRL.MODE is SPI): at the start of a read transfer BASE_RD_ADDR is copied to CMD_RESP_STATUS.CURR_RD_ADDR. This field should not be modified during ongoing bus transfers. Default Value: 0

18.1.571 SCB7_CMD_RESP_STATUS

Command/response status register.

Address: 0x4029000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CURR_RD_ADDR [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			R				
HW Access	None			W				
Name	None [23:21]			CURR_WR_ADDR [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	CMD_RESP_EC_BUSY	CMD_RESP_EC_BUS_BUSY	None [29:24]					

Bits	Name	Description
31	CMD_RESP_EC_BUSY	Indicates whether the CURR_RD_ADDR and CURR_WR_ADDR fields in this register are reliable (when CMD_RESP_EC_BUSY is '0') or not reliable (when CMD_RESP_EC_BUSY is '1'). Note: - When there is no ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable). - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '0' (reliable), when the CURR_RD_ADDR and CURR_WR_ADDR are not being updated by the HW. - When there is a ongoing bus transfer, CMD_RESP_EC_BUSY is '1' (not reliable), when the CURR_RD_ADDR or CURR_WR_ADDR are being updated by the HW. Note that this update lasts one I2C clock cycle, or two SPI clock cycles. Default Value: Undefined

18.1.571 SCB7_CMD_RESP_STATUS (continued)

30	CMD_RESP_EC_BUS_BUSY	Indicates whether there is an ongoing bus transfer to the IP. '0': no ongoing bus transfer. '1': ongoing bus transferr. For SPI, the field is '1' when the slave is selected. For I2C, the field is set to '1' at a I2C START/RESTART. In case of an address match, the field is set to '0' on a I2C STOP. In case of NO address match, the field is set to '0' after the failing address match. Default Value: Undefined
20 : 16	CURR_WR_ADDR	I2C/SPI write current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been written (# bytes = CURR_WR_ADDR - CMD_RESP_CTRL.BASE_WR_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined
4 : 0	CURR_RD_ADDR	I2C/SPI read current address for CMD_RESP mode. HW increments the field after a read access to the memory buffer. However, when the last memory buffer address is reached, the address is NOT incremented (but remains at the maximim memory buffer address). The field is used to determine how many bytes have been read (# bytes = CURR_RD_ADDR - CMD_RESP_CTRL.BASE_RD_ADDR). This field is reliable during when there is no bus transfer. This field is potentially unreliable when there is a bus transfer bus transfer: when CMD_RESP_EC_BUSY is '0', the field is reliable. Default Value: Undefined

18.1.572 SCB7_SPI_CTRL

SPI control register.

Address: 0x40290020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_CONTINUOUS	LATE_MISO_SAMPLE	CPOL	CPHA	SELECT_PRECEDE	CONTINU-OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_POLARITY3	SSEL_POLARITY2	SSEL_POLARITY1	SSEL_POLARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. The IP should be disabled when changes are made to this field. only SPI_SELECT[0] is used in slave mode. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.572 SCB7_SPI_CTRL (continued)

		0x0: SPI_MOTOROLA: SPI Motorola submode. In master mode, when not transmitting data (SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive. **0x1: SPI_TI:** SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive; i.e. no pulse is generated. **0x2: SPI_NS:** SPI National Semiconducturs submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), SELECT is inactive.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': the SPI master MISO line "spi_miso_in" is connected to the SPI MISO pin. '1': the SPI master MISO line "spi_miso_in" is connected to the SPI master MOSI line "spi_mosi_out". In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). only SPI_SELECT[0] is used in slave mode. For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Istruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.572 SCB7_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is '0': SCLK is '0' when not transmitting data. - CPOL is '1': SCLK is '1' when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is '0', CPHA is '0': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is '0', CPHA is '1': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is '1', CPHA is '0': MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is '1', CPHA is '1': MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily seperated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are send out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always seperated by slave deselection: independent of the availability of TX FIFO data frames, data frames are send out with slave deselection. Default Value: 0

18.1.573 SCB7_SPI_STATUS

SPI status register.

Address: 0x40290024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.574 SCB7_UART_CTRL

UART control register.

Address: 0x40290040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 **0x0: UART_STD:** Standard UART submode. **0x1: UART_SMARTCARD:** SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. **0x2: UART_IRDA:** Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS is 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). When '0', the transmitter TX line "uart_tx_out" is connected to the TX pin and the receiver RX line "uart_rx_in" is connected to the RX pin. When '1', the transmitter TX line "uart_tx_out" is connected to the receiver RX line "uart_rx_in". A similar connections scheme is followed for "uart_rts_out" and "uart_cts_in". This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.575 SCB7_UART_TX_CTRL

UART transmitter control register.

Address: 0x40290044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.576 SCB7_UART_RX_CTRL

UART receiver control register.

Address: 0x40290048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.576 SCB7_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame seperates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is send to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal "uart_rx_in". Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.576 SCB7_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.577 SCB7_UART_RX_STATUS

UART receiver status register.

Address: 0x4029004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least signficant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when INTR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.578 SCB7_UART_FLOW_CTRL

UART flow control register

Address: 0x40290050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal "uart_cts_in" by the UART transmitter: '0': Disabled. The UART transmitter ignores "uart_cts_in", and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses "uart_cts_in" to qualify the transmission of data. It transmits when "uart_cts_in" is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', "uart_cts_in" is connected to "uart_rts_out" in the IP (both signals are subjected to signal polarity changes as indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal "uart_cts_in": '0': CTS is low/'0' active; "uart_cts_in" is '0' when active and "uart_cts_in" is '1' when inactive. '1': CTS is high/'1' active; "uart_cts_in" is '1' when active and "uart_cts_in" is '0' when inactive. Default Value: 0

18.1.578 SCB7_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal "uart_rts_out": '0': RTS is low/'0' active; "uart_rts_out" is '0' when active and "uart_rts_out" is '1' when inactive. '1': RTS is high/'1' active; "uart_rts_out" is '1' when active and "uart_rts_out" is '0' when inactive. During IP reset (Hibernate system power mode), "uart_rts_out" is '1'. This represents an inactive state assuming a low/'0' active polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal "uart_rts_out" is activated. By setting this field to "0", flow control is effectively SW disabled (may be useful for debug purposes). Default Value: 0

18.1.579 SCB7_I2C_CTRL

I2C control register.

Address: 0x40290060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', the I2C SCL and SDA lines are connected to the I2C SCL and SDA pins. When '1', I2C SCL and SDA lines are routed internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0
15	S_NOT_READY_DATA_NACK	For internally clocked logic only. Only used when: - non EZ mode. Functionality is as follows: - 1: a received data element byte the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1

18.1.579 SCB7_I2C_CTRL (continued)

14	S_NOT_READY_ADDR_NACK	For internally clocked logic (EC_AM is '0' and EC_OP is '0') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when: - EC_AM is '0', EC_OP is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the internally clocked logic is enabled (we are in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). the internally clocked logic is not enabled (we are in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the internally clocked logic takes over). The internally clocked logic will handle the ongoing transfer as soon as it is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1
7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 peripheral clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular (no stretching) interface (IF) low time to guarantee functional correct behavior. With input signal median filtering, the IF low time should be >= 8 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF low time should be >= 7 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.579 SCB7_I2C_CTRL (continued)

3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 peripheral clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the IP clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be >= 6 IP clock cycles and <= 16 IP clock cycles. Without input signal median filtering, the IF high time should be >= 5 IP clock cycles and <= 16 IP clock cycles. Default Value: 8

18.1.580 SCB7_I2C_STATUS

I2C status register.

Address: 0x40290064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/idle or transmitting START, REPEATED START, STOP or an address, this field is '0". Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0". Default Value: 0

18.1.580 SCB7_I2C_STATUS (continued)

1	I2C_EC_BUSY	Inidicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_EZ_ADDR or CURR_EZ_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_EZ_ADDR and CURR_EZ_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If the IP is disabled, BUS_BUSY is '0'. After enabling the IP, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.581 SCB7_I2C_M_CMD

I2C master command register.

Address: 0x40290068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. I2C_M_CMD.M_START has a higher priority than this command: in situations where both a STOP and a REPEATED START could be transmitted, M_START takes precedence over M_STOP. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.581 SCB7_I2C_M_CMD (continued)

1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0') . A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0
0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.582 SCB7_I2C_S_CMD

I2C slave command register.

Address: 0x4029006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.583 SCB7_I2C_CFG

I2C configuration register.

Address: 0x40290070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative "i2c_sda_out" filter delay: "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 2. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 1. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim bits for "i2c_sda_out" 50 ns filter 0. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 2

18.1.583 SCB7_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Selection of "i2c_scl_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim bits for "i2c_scl_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. With s8iom0s8v1p2 I/Os, trim bits should be programmed to 3 to suppress glitches below 50ns. Default Value: 0
4	SDA_IN_FILT_SEL	Selection of "i2c_sda_in" filter delay: '0': 0 ns. '1: 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim bits for "i2c_sda_in" 50 ns filter. See s8i2cs BROS (001-59539) for more details on the trim bit values. Default Value: 3

18.1.584 SCB7_TX_CTRL

Transmitter control register.

Address: 0x40290200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.585 SCB7_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40290204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event INTR_TX.TRIGGER is generated. Default Value: 0

18.1.586 SCB7_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40290208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is tranmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.587 SCB7_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40290240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.588 SCB7_RX_CTRL

Receiver control register.

Address: 0x40290300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptability to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.589 SCB7_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40290304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event INTR_RX.TRIGGER is generated. Default Value: 0

18.1.590 SCB7_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40290308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R			
HW Access	None				W			
Name	None [7:5]				USED [4:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of entries in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR (EZ_DATA_NR/2). Default Value: 0

18.1.591 SCB7_RX_MATCH

Slave address and mask register.

Address: 0x40290310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the ADDR field bits in the ADDR field take part in the matching of the slave address: MATCH = ((ADDR & MASK) == ("slave address" & MASK)). Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.592 SCB7_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40290340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. This register has a side effect when read by software: a data frame is removed from the FIFO. This may be undesirable during debug; i.e. a read during debug should NOT have a side effect. To this end, the IP uses the AHB-Lite "hmaster[0]" input signal. When this signal is '1' in the address cycle of a bus transfer, a read transfer will not have a side effect. As a result, a read from this register will not remove a data frame from the FIFO. As a result, a read from this register behaves as a read from the SCB_RX_FIFO_RD_SILENT register. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.593 SCB7_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40290344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.594 SCB7_EZ_DATA0

Memory buffer registers.

Address: 0x40290400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.595 SCB7_EZ_DATA1

Memory buffer registers.

Address: 0x40290404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.596 SCB7_EZ_DATA2

Memory buffer registers.

Address: 0x40290408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.597 SCB7_EZ_DATA3

Memory buffer registers.

Address: 0x4029040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.598 SCB7_EZ_DATA4

Memory buffer registers.

Address: 0x40290410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.599 SCB7_EZ_DATA5

Memory buffer registers.

Address: 0x40290414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.600 SCB7_EZ_DATA6

Memory buffer registers.

Address: 0x40290418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.601 SCB7_EZ_DATA7

Memory buffer registers.

Address: 0x4029041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.602 SCB7_EZ_DATA8

Memory buffer registers.

Address: 0x40290420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.603 SCB7_EZ_DATA9

Memory buffer registers.

Address: 0x40290424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.604 SCB7_EZ_DATA10

Memory buffer registers.

Address: 0x40290428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.605 SCB7_EZ_DATA11

Memory buffer registers.

Address: 0x4029042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.606 SCB7_EZ_DATA12

Memory buffer registers.

Address: 0x40290430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.607 SCB7_EZ_DATA13

Memory buffer registers.

Address: 0x40290434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.608 SCB7_EZ_DATA14

Memory buffer registers.

Address: 0x40290438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.609 SCB7_EZ_DATA15

Memory buffer registers.

Address: 0x4029043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.610 SCB7_EZ_DATA16

Memory buffer registers.

Address: 0x40290440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.611 SCB7_EZ_DATA17

Memory buffer registers.

Address: 0x40290444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.612 SCB7_EZ_DATA18

Memory buffer registers.

Address: 0x40290448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.613 SCB7_EZ_DATA19

Memory buffer registers.

Address: 0x4029044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.614 SCB7_EZ_DATA20

Memory buffer registers.

Address: 0x40290450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.615 SCB7_EZ_DATA21

Memory buffer registers.

Address: 0x40290454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.616 SCB7_EZ_DATA22

Memory buffer registers.

Address: 0x40290458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.617 SCB7_EZ_DATA23

Memory buffer registers.

Address: 0x4029045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.618 SCB7_EZ_DATA24

Memory buffer registers.

Address: 0x40290460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.619 SCB7_EZ_DATA25

Memory buffer registers.

Address: 0x40290464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.620 SCB7_EZ_DATA26

Memory buffer registers.

Address: 0x40290468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.621 SCB7_EZ_DATA27

Memory buffer registers.

Address: 0x4029046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.622 SCB7_EZ_DATA28

Memory buffer registers.

Address: 0x40290470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.623 SCB7_EZ_DATA29

Memory buffer registers.

Address: 0x40290474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.624 SCB7_EZ_DATA30

Memory buffer registers.

Address: 0x40290478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.625 SCB7_EZ_DATA31

Memory buffer registers.

Address: 0x4029047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.626 SCB7_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40290E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.627 SCB7_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40290E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when EC_OP is '1'. Default Value: 0

18.1.627 SCB7_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when EC_AM is '1'. Default Value: 0

18.1.628 SCB7_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40290E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.629 SCB7_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40290E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.630 SCB7_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40290EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI de-selection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI de-selection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when EC_OP is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when EC_OP is '1'. Default Value: 0

18.1.630 SCB7_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when EC_AM is '1'. Default Value: 0

18.1.631 SCB7_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40290EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.632 SCB7_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40290ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.633 SCB7_INTR_M

Master interrupt request register.

Address: 0x40290F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO and shift register are empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.634 SCB7_INTR_M_SET

Master interrupt set request register

Address: 0x40290F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.635 SCB7_INTR_M_MASK

Master interrupt mask register.

Address: 0x40290F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.636 SCB7_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40290F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.637 SCB7_INTR_S

Slave interrupt request register.

Address: 0x40290F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.637 SCB7_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (till the internally clocked logic takes over) (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.638 SCB7_INTR_S_SET

Slave interrupt set request register.

Address: 0x40290F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.638 SCB7_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.639 SCB7_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40290F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.639 SCB7_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.640 SCB7_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40290F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.640 SCB7_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.641 SCB7_INTR_TX

Transmitter interrupt request register.

Address: 0x40290F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	AHB-Lite write transfer can not get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.641 SCB7_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when the IP is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.642 SCB7_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40290F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.642 SCB7_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.643 SCB7_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40290F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.643 SCB7_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.644 SCB7_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40290F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.644 SCB7_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.645 SCB7_INTR_RX

Receiver interrupt request register.

Address: 0x40290FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.645 SCB7_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	AHB-Lite read transfer can not get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODE: (FF_DATA_NR = EZ_DATA_NR/2) BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.646 SCB7_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40290FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.646 SCB7_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.647 SCB7_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40290FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.647 SCB7_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.648 SCB7_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40290FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMPTY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK_DETECT	BAUD_DETECT	PARITY_ERROR	FRAME_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.648 SCB7_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

19 Supervisory Flash (SFLASH) Registers

This section discusses the SFLASH registers. It lists all the registers in mapping tables, in address order.

19.1 Register Details

Register Name	Address
SFLASH_SILICON_ID	0x0FFFF244
SFLASH_HIB_KEY_DELAY	0x0FFFF250
SFLASH_DPSLP_KEY_DELAY	0x0FFFF252
SFLASH_SWD_CONFIG	0x0FFFF254
SFLASH_INITIAL_SPCIF_TRIM_M1_DAC0	0x0FFFF255
SFLASH_SWD_LISTEN	0x0FFFF258
SFLASH_FLASH_START	0x0FFFF25C
SFLASH_CSDV2_CSD0_ADC_TRIM1	0x0FFFF260
SFLASH_CSDV2_CSD0_ADC_TRIM2	0x0FFFF261
SFLASH_SAR_TEMP_MULTIPLIER	0x0FFFF264
SFLASH_SAR_TEMP_OFFSET	0x0FFFF266
SFLASH_IMO_TRIM_USBMODE_24	0x0FFFF33E
SFLASH_IMO_TRIM_USBMODE_48	0x0FFFF33F
SFLASH_IMO_TCTRIM_LT0	0x0FFFF34C
SFLASH_IMO_TCTRIM_LT1	0x0FFFF34D
SFLASH_IMO_TCTRIM_LT2	0x0FFFF34E
SFLASH_IMO_TCTRIM_LT3	0x0FFFF34F
SFLASH_IMO_TCTRIM_LT4	0x0FFFF350
SFLASH_IMO_TCTRIM_LT5	0x0FFFF351
SFLASH_IMO_TCTRIM_LT6	0x0FFFF352
SFLASH_IMO_TCTRIM_LT7	0x0FFFF353
SFLASH_IMO_TCTRIM_LT8	0x0FFFF354
SFLASH_IMO_TCTRIM_LT9	0x0FFFF355
SFLASH_IMO_TCTRIM_LT10	0x0FFFF356
SFLASH_IMO_TCTRIM_LT11	0x0FFFF357
SFLASH_IMO_TCTRIM_LT12	0x0FFFF358
SFLASH_IMO_TCTRIM_LT13	0x0FFFF359

Register Name	Address
SFLASH_IMO_TCTRIM_LT14	0x0FFFF35A
SFLASH_IMO_TCTRIM_LT15	0x0FFFF35B
SFLASH_IMO_TCTRIM_LT16	0x0FFFF35C
SFLASH_IMO_TCTRIM_LT17	0x0FFFF35D
SFLASH_IMO_TCTRIM_LT18	0x0FFFF35E
SFLASH_IMO_TCTRIM_LT19	0x0FFFF35F
SFLASH_IMO_TCTRIM_LT20	0x0FFFF360
SFLASH_IMO_TCTRIM_LT21	0x0FFFF361
SFLASH_IMO_TCTRIM_LT22	0x0FFFF362
SFLASH_IMO_TCTRIM_LT23	0x0FFFF363
SFLASH_IMO_TCTRIM_LT24	0x0FFFF364
SFLASH_IMO_TRIM_LT0	0x0FFFF365
SFLASH_IMO_TRIM_LT1	0x0FFFF366
SFLASH_IMO_TRIM_LT2	0x0FFFF367
SFLASH_IMO_TRIM_LT3	0x0FFFF368
SFLASH_IMO_TRIM_LT4	0x0FFFF369
SFLASH_IMO_TRIM_LT5	0x0FFFF36A
SFLASH_IMO_TRIM_LT6	0x0FFFF36B
SFLASH_IMO_TRIM_LT7	0x0FFFF36C
SFLASH_IMO_TRIM_LT8	0x0FFFF36D
SFLASH_IMO_TRIM_LT9	0x0FFFF36E
SFLASH_IMO_TRIM_LT10	0x0FFFF36F
SFLASH_IMO_TRIM_LT11	0x0FFFF370
SFLASH_IMO_TRIM_LT12	0x0FFFF371
SFLASH_IMO_TRIM_LT13	0x0FFFF372
SFLASH_IMO_TRIM_LT14	0x0FFFF373
SFLASH_IMO_TRIM_LT15	0x0FFFF374
SFLASH_IMO_TRIM_LT16	0x0FFFF375
SFLASH_IMO_TRIM_LT17	0x0FFFF376
SFLASH_IMO_TRIM_LT18	0x0FFFF377
SFLASH_IMO_TRIM_LT19	0x0FFFF378
SFLASH_IMO_TRIM_LT20	0x0FFFF379
SFLASH_IMO_TRIM_LT21	0x0FFFF37A
SFLASH_IMO_TRIM_LT22	0x0FFFF37B
SFLASH_IMO_TRIM_LT23	0x0FFFF37C
SFLASH_IMO_TRIM_LT24	0x0FFFF37D

19.1.1 SFLASH_SILICON_ID

Silicon ID

Address: 0x0FFFF244

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	ID	Silicon ID Default Value: X

19.1.2 SFLASH_HIB_KEY_DELAY

Hibernate wakeup value for PWR_KEY_DELAY

Address: 0x0FFFF250

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay (in 12MHz IMO clock cycles) to wait for references to settle on wakeup from hibernate/ deepsleep. PBOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. Default Value: X

19.1.3 SFLASH_DPSLP_KEY_DELAY

DeepSleep wakeup value for PWR_KEY_DELAY

Address: 0x0FFFF252

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay (in 12MHz IMO clock cycles) to wait for references to settle on wakeup from hibernate/ deepsleep. PBOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. Default Value: X

19.1.4 SFLASH_SWD_CONFIG

SWD pinout selector (not present in TSG4/TSG5-M)

Address: 0x0FFFF254

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							None
Name	None [7:1]							SWD_SELECT

Bits	Name	Description
0	SWD_SELECT	0: Use Primary SWD location 1: Use Alternate SWD location Default Value: X

19.1.5 SFLASH_INITIAL_SPCIF_TRIM_M1_DAC0

FLASH IDAC trim used during boot

Address: 0x0FFFF255

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW			RW				
HW Access	R			R				
Name	SLOPE [7:5]			IDAC [4:0]				

Bits	Name	Description
7 : 5	SLOPE	See SPCIF_TRIM1 Default Value: 0
4 : 0	IDAC	See SPCIF_TRIM1 Default Value: 0

19.1.6 SFLASH_SWD_LISTEN

Listen Window Length

Address: 0x0FFFF258

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CYCLES [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	CYCLES [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	CYCLES [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	CYCLES [31:24]							

Bits	Name	Description
31 : 0	CYCLES	Number of clock cycles Default Value: X

19.1.7 SFLASH_FLASH_START

Flash Image Start Address

Address: 0x0FFFF25C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	ADDRESS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	ADDRESS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	ADDRESS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	ADDRESS [31:24]							

Bits	Name	Description
31 : 0	ADDRESS	Start Address Default Value: X

19.1.8 SFLASH_CSDV2_CSD0_ADC_TRIM1

CSDV2 CSD0 ADC TRIM 1

Address: 0x0FFFF260

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CSD_ADC_CAL_LSB [7:0]							

Bits	Name	Description
7 : 0	CSD_ADC_CAL_LSB	Low byte of CSDv2 Calibration Default Value: X

19.1.9 SFLASH_CSDV2_CSD0_ADC_TRIM2

CSDV2 CSD0 ADC TRIM2

Address: 0x0FFFF261

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CSD_ADC_CAL_MSB [7:0]							

Bits	Name	Description
7 : 0	CSD_ADC_CAL_MSB	High byte of CSDv2 Calibration Default Value: X

19.1.10 SFLASH_SAR_TEMP_MULTIPLIER

SAR Temperature Sensor Multiplication Factor

Address: 0x0FFFF264

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TEMP_MULTIPLIER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	TEMP_MULTIPLIER [15:8]							

Bits	Name	Description
15 : 0	TEMP_MULTIPLIER	Multiplier value for SAR temperature sensor in fixed point 0.16 format. Note: this field exists in products that contain SAR (m0s8sar) only. Default Value: X

19.1.11 SFLASH_SAR_TEMP_OFFSET

SAR Temperature Sensor Offset

Address: 0x0FFFF266

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TEMP_OFFSET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	TEMP_OFFSET [15:8]							

Bits	Name	Description
15 : 0	TEMP_OFFSET	Offset value for SAR temperature sensor in fixed point 10.6 format. Note: this field exists in products that contain SAR (m0s8sar) only. Default Value: X

19.1.12 SFLASH_IMO_TRIM_USBMODE_24

USB IMO TRIM 24MHz

Address: 0x0FFFF33E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TRIM_24 [7:0]							

Bits	Name	Description
7 : 0	TRIM_24	TRIM value for IMO with USB at 24MHz Default Value: X

19.1.13 SFLASH_IMO_TRIM_USBMODE_48

USB IMO TRIM 48MHz

Address: 0x0FFFF33F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TRIM_24 [7:0]							

Bits	Name	Description
7 : 0	TRIM_24	TRIM value for IMO with USB at 24MHz Default Value: X

19.1.14 SFLASH_IMO_TCTRIM_LT0

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF34C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.15 SFLASH_IMO_TCTRIM_LT1

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF34D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.16 SFLASH_IMO_TCTRIM_LT2

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF34E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.17 SFLASH_IMO_TCTRIM_LT3

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF34F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.18 SFLASH_IMO_TCTRIM_LT4

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF350

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.19 SFLASH_IMO_TCTRIM_LT5

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF351

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.20 SFLASH_IMO_TCTRIM_LT6

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF352

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.21 SFLASH_IMO_TCTRIM_LT7

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF353

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.22 SFLASH_IMO_TCTRIM_LT8

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF354

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.23 SFLASH_IMO_TCTRIM_LT9

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF355

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.24 SFLASH_IMO_TCTRIM_LT10

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF356

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.25 SFLASH_IMO_TCTRIM_LT11

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF357

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.26 SFLASH_IMO_TCTRIM_LT12

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF358

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.27 SFLASH_IMO_TCTRIM_LT13

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF359

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.28 SFLASH_IMO_TCTRIM_LT14

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF35A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.29 SFLASH_IMO_TCTRIM_LT15

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF35B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.30 SFLASH_IMO_TCTRIM_LT16

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF35C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.31 SFLASH_IMO_TCTRIM_LT17

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF35D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.32 SFLASH_IMO_TCTRIM_LT18

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF35E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.33 SFLASH_IMO_TCTRIM_LT19

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF35F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.34 SFLASH_IMO_TCTRIM_LT20

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF360

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.35 SFLASH_IMO_TCTRIM_LT21

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF361

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.36 SFLASH_IMO_TCTRIM_LT22

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF362

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.37 SFLASH_IMO_TCTRIM_LT23

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF363

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.38 SFLASH_IMO_TCTRIM_LT24

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF364

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compesation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.39 SFLASH_IMO_TRIM_LT0

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF365

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.40 SFLASH_IMO_TRIM_LT1

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF366

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.41 SFLASH_IMO_TRIM_LT2

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF367

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.42 SFLASH_IMO_TRIM_LT3

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF368

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.43 SFLASH_IMO_TRIM_LT4

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF369

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.44 SFLASH_IMO_TRIM_LT5

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF36A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.45 SFLASH_IMO_TRIM_LT6

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF36B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.46 SFLASH_IMO_TRIM_LT7

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF36C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.47 SFLASH_IMO_TRIM_LT8

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF36D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.48 SFLASH_IMO_TRIM_LT9

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF36E

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.49 SFLASH_IMO_TRIM_LT10

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF36F

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.50 SFLASH_IMO_TRIM_LT11

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF370

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.51 SFLASH_IMO_TRIM_LT12

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF371

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.52 SFLASH_IMO_TRIM_LT13

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF372

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.53 SFLASH_IMO_TRIM_LT14

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF373

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.54 SFLASH_IMO_TRIM_LT15

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF374

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.55 SFLASH_IMO_TRIM_LT16

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF375

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.56 SFLASH_IMO_TRIM_LT17

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF376

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.57 SFLASH_IMO_TRIM_LT18

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF377

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.58 SFLASH_IMO_TRIM_LT19

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF378

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.59 SFLASH_IMO_TRIM_LT20

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF379

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.60 SFLASH_IMO_TRIM_LT21

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF37A

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.61 SFLASH_IMO_TRIM_LT22

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF37B

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.62 SFLASH_IMO_TRIM_LT23

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF37C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.63 SFLASH_IMO_TRIM_LT24

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF37D

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

20 SPC Interface (SPCIF) Registers

This section discusses the SPCIF registers. It lists all the registers in mapping tables, in address order.

20.1 Register Details

Register Name	Address
SPCIF_GEOMETRY	0x40110000
SPCIF_INTR	0x401107F0
SPCIF_INTR_SET	0x401107F4
SPCIF_INTR_MASK	0x401107F8
SPCIF_INTR_MASKED	0x401107FC

20.1.1 SPCIF_GEOMETRY

Flash/NVL geometry information

Address: 0x40110000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	FLASH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R		R					
HW Access	W		W					
Name	SFLASH [15:14]		FLASH [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	R		R		R			
HW Access	W		W		W			
Name	FLASH_ROW [23:22]		NUM_FLASH [21:20]		SFLASH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	None	None						
Name	DE_CPD_LP	None [30:24]						

Bits	Name	Description
31	DE_CPD_LP	0': SRAM busy wait loop has not been copied. '1': Busy wait loop has been written into SRAM. Default Value: 0
23 : 22	FLASH_ROW	Page size in 64 Byte multiples (chip dependent): "0": 64 byte "1": 128 byte "2": 192 byte "3": 256 byte The page size is used to detemine the number of Bytes in a page for Flash page based operations (e.g. PGM_PAGE). Note: the field name FLASH_ROW is misleading, as this field specifies the number of Bytes in a page, rather than the number of Bytes in a row. In a single plane flash macro architecture, a page consists of a single row. However, in a multi plane flash macro architecture, a page consists of multiple rows from different planes. Default Value: Undefined

20.1.1 SPCIF_GEOMETRY (continued)

21 : 20	NUM_FLASH	Number of flash macros (chip dependent): "0": 1 flash macro "1": 2 flash macros "2": 3 flash macros "3": 4 flash macros Default Value: Undefined
19 : 14	SFLASH	Supervisory flash capacity in 256 Byte multiples (chip dependent). If multiple flash macros are present, this field provides the supervisory flash capacity of all flash macros together: "0": 256 Bytes. "1": 2*256 Bytes. ... "63": 64*256 Bytes. Default Value: Undefined
13 : 0	FLASH	Regular flash capacity in 256 Byte multiples (chip dependent). If multiple flash macros are present, this field provides the flash capacity of all flash macros together: "0": 256 Bytes. "1": 2*256 Bytes. ... "16383": 16384*256 Bytes. Default Value: Undefined

20.1.2 SPCIF_INTR

SPCIF interrupt request register

Address: 0x401107F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1C
HW Access	None							RW1S
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Timer counter value reaches "0". Set to '1', when event is detected. Write INTR field with '1', to clear bit. Write INTR_SET field with '1', to set bit. Default Value: 0

20.1.3 SPCIF_INTR_SET

SPCIF interrupt set request register

Address: 0x401107F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1S
HW Access	None							A
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Write INTR_SET field with '1' to set corresponding INTR field. Default Value: 0

20.1.4 SPCIF_INTR_MASK

SPCIF interrupt mask register

Address: 0x401107F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Mask for corresponding field in INTR register. Default Value: 0

20.1.5 SPCIF_INTR_MASKED

SPCIF interrupt masked request register

Address: 0x401107FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Logical and of corresponding request and mask fields. Default Value: 0

21 SRSSLT Registers

This section discusses the SRSSLT registers. It lists all the registers in mapping tables, in address order.

21.1 Register Details

Register Name	Address
PWR_CONTROL	0x40030000
PWR_KEY_DELAY	0x40030004
PWR_DDFT_SELECT	0x4003000C
TST_MODE	0x40030014
CLK_SELECT	0x40030028
CLK_ILO_CONFIG	0x4003002C
CLK_IMO_CONFIG	0x40030030
CLK_DFT_SELECT	0x40030034
WDT_DISABLE_KEY	0x40030038
WDT_COUNTER	0x4003003C
WDT_MATCH	0x40030040
SRSS_INTR	0x40030044
SRSS_INTR_SET	0x40030048
SRSS_INTR_MASK	0x4003004C
RES_CAUSE	0x40030054
CLK_IMO_SELECT	0x40030F08
CLK_IMO_TRIM1	0x40030F0C
CLK_IMO_TRIM2	0x40030F10
PWR_PWRSYS_TRIM1	0x40030F14
CLK_IMO_TRIM3	0x40030F18

21.1.1 PWR_CONTROL

Power Mode Control

Address: 0x40030000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R			
HW Access	None		RW	RW	RW			
Name	None [7:6]		LPM_READY	DEBUG_SESSION	POWER_MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	None			R		RW	RW
HW Access	A	None			RW		R	R
Name	EXT_VCCD	None [22:20]			SPARE [19:18]		OVER_TEMP_THRESH	OVER_TEMP_EN

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	EXT_VCCD	Always write 0 except as noted below. PSoC4-S0 and Streetfighter CapSense products may set this bit if Vccd is provided externally (on Vccd pin). Setting this bit turns off the active regulator and will lead to system reset (BOD) unless both Vddd and Vccd pins are supplied externally. This register bit only resets for XRES, POR, or a detected BOD. Default Value: 0
19 : 18	SPARE	Spare AHB readback bits that are hooked to PWR_PWRSYS_TRIM1.SPARE_TRIM[1:0] through spare logic equivalent to bitwise inversion. Engineering only. Default Value: 0
17	OVER_TEMP_THRESH	Over-temperature threshold. 0: TEMP_HIGH condition occurs between 120C and 125C. 1: TEMP_HIGH condition occurs between 60C and 75C (used for testing). Default Value: 0
16	OVER_TEMP_EN	Enables the die over temperature sensor. Must be enabled when using the TEMP_HIGH interrupt. Default Value: 0

21.1.1 PWR_CONTROL (continued)

5	LPM_READY	Indicates whether the low power mode regulator is ready to enter DEEPSLEEP mode. 0: If DEEPSLEEP mode is requested, device will enter SLEEP mode. When low power regulators are ready, device will automatically enter the originally requested mode. 1: Normal operation. DEEPSLEEP works as described. Default Value: 0
4	DEBUG_SESSION	Indicates whether a debug session is active (CDBGPWRUPREQ signal is 1) Default Value: 0 **0x0: NO_SESSION:** No debug session active **0x1: SESSION_ACTIVE:** Debug session is active
3 : 0	POWER_MODE	Current power mode of the device. Note that this field cannot be read in all power modes on actual silicon. Default Value: 0 **0x0: RESET:** RESET state **0x1: ACTIVE:** ACTIVE state **0x2: SLEEP:** SLEEP state **0x3: DEEP_SLEEP:** DEEP_SLEEP state

21.1.2 PWR_KEY_DELAY

Power System Key Register

Address: 0x40030004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay to wait for references to settle on wakeup from deepsleep. BOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. The default assumes the output of the predivider is 48MHz + 3%. Firmware may scale this setting according to the fastest actual clock frequency that can occur when waking from DEEPSLEEP. Default Value: 248

21.1.3 PWR_DDFT_SELECT

Power DDFT Mode Selection Register

Address: 0x4003000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	DDFT1_SEL [7:4]				DDFT0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	DDFT1_SEL	Select signal for power DDFT output #1 Default Value: 0 **0x0: WAKEUP:** wakeup **0x1: AWAKE:** awake **0x2: ACT_POWER_EN:** act_power_en **0x3: ACT_POWER_UP:** act_power_up **0x4: ACT_POWER_GOOD:** act_power_good **0x5: ACT_REF_VALID:** act_ref_valid **0x6: ACT_REG_VALID:** act_reg_valid

21.1.3 PWR_DDFT_SELECT (continued)

		0x7: ACT_COMP_OUT: act_comp_out **0x8: ACT_TEMP_HIGH:** act_temp_high **0x9: DPSLP_COMP_OUT:** dpslp_comp_out **0xa: DPSLP_POWER_UP:** dpslp_power_up **0xb: AWAKE_DELAYED:** awake_delayed **0xc: LPM_READY:** lpm_ready **0xd: SLEEPHOLDACK_N:** sleepholdack_n **0xe: GND:** 1'b0 **0xf: PWR:** 1'b1
3 : 0	DDFT0_SEL	Select signal for power DDFT output #0 Default Value: 0 **0x0: WAKEUP:** wakeup **0x1: AWAKE:** awake **0x2: ACT_POWER_EN:** act_power_en **0x3: ACT_POWER_UP:** act_power_up **0x4: ACT_POWER_GOOD:** act_power_good **0x5: ACT_REF_EN:** srss_adft_control_act_ref_en **0x6: ACT_COMP_EN:** srss_adft_control_act_comp_en **0x7: DPSLP_REF_EN:** srss_adft_control_dpslp_ref_en **0x8: DPSLP_REG_EN:** srss_adft_control_dpslp_reg_en **0x9: DPSLP_COMP_EN:** srss_adft_control_dpslp_comp_en **0xa: OVER_TEMP_EN:** pwr_control_over_temp_en **0xb: SLEEPHOLDREQ_N:** sleepholdreq_n

21.1.3 PWR_DDFT_SELECT (continued)

0xc: ADFT_BUF_EN:
adft_buf_en

0xd: ATPG_OBSERVE:
ATPG observe point (no functional purpose)

0xe: GND:
1'b0

0xf: PWR:
1'b1

21.1.4 TST_MODE

Test Mode Control Register

Address: 0x40030014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R	None	
HW Access	None					RW	None	
Name	None [7:3]					SWD_CONNECTED	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	R	None	RW	None			
HW Access	R	RW	None	A	None			
Name	TEST_MODE	TEST_KEY_DFT_EN	None	BLOCK_ALT_XRES	None [27:24]			

Bits	Name	Description
31	TEST_MODE	Setting this bit will prevent BootROM from yielding execution to Flash image. 0: Normal operation mode 1: Test mode (any test mode) Default Value: 0
30	TEST_KEY_DFT_EN	This bit is set when a XRES test mode key is shifted in. It is the value of the test_key_dft_en signal. When this bit is set, the BootROM will not yield execution to the FLASH image (same function as setting TEST_MODE bit below). Default Value: 0
28	BLOCK_ALT_XRES	Relevant only for parts that have the alternate XRES mechanism of overloading a GPIO pin temporarily as alternate XRES during test. When set, this bit blocks the alternate XRES function, such that the pin can be used for normal I/O or for ddft/adft observation. See SAS Part-V and Part-IX for details. This register bit only resets for XRES, POR, or a detected BOD. Default Value: 0

21.1.4 TST_MODE (continued)

2	SWD_CONNECTED	0: SWD not active 1: SWD activated (Line Reset & Connect sequence passed) (Note: this bit replaces TST_CTRL.SWD_CONNECTED and is present in all M0S8 products except TSG4) Default Value: 0

21.1.5 CLK_SELECT

Clock Select Register

Address: 0x40030028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	SYSCLK_DIV [7:6]		PUMP_SEL [5:4]		HFCLK_DIV [3:2]		HFCLK_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SYSCLK_DIV	Select clk_sys prescaler value. Default Value: 0 **0x0: NO_DIV:** clk_sys= clk_hf/1 **0x1: DIV_BY_2:** clk_sys= clk_hf/2 **0x2: DIV_BY_4:** clk_sys= clk_hf/4 **0x3: DIV_BY_8:** clk_sys= clk_hf/8
5 : 4	PUMP_SEL	Selects clock source for charge pump clock. This clock is not guaranteed to be glitch free when changing any of its sources or settings. Default Value: 0 **0x0: GND:** No clock, connect to gnd

21.1.5 CLK_SELECT (continued)

		0x1: IMO: Use main IMO output **0x2: HFCLK:** Use clk_hf (using selected source after predivider but before prescaler)
3 : 2	HFCLK_DIV	Selects clk_hf predivider value. Default Value: 2 **0x0: NO_DIV:** Transparent mode, feed through selected clock source w/o dividing. **0x1: DIV_BY_2:** Divide selected clock source by 2 **0x2: DIV_BY_4:** Divide selected clock source by 4 **0x3: DIV_BY_8:** Divide selected clock source by 8
1 : 0	HFCLK_SEL	Selects a source for clk_hf and dsi_in[0]. Note that not all products support all clock sources. Selecting a clock source that is not supported will result in undefined behavior. Default Value: 0 **0x0: IMO:** IMO - Internal R/C Oscillator **0x1: EXTCLK:** EXTCLK - External Clock Pin **0x2: ECO:** ECO - External-Crystal Oscillator or PLL subsystem output

21.1.6 CLK_ILO_CONFIG

ILO Configuration

Address: 0x4003002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	ENABLE	None [30:24]						

Bits	Name	Description
31	ENABLE	Master enable for ILO oscillator. This bit is hardware set whenever the WDT_DISABLE_KEY is not set to the magic value. Default Value: 1

21.1.7 CLK_IMO_CONFIG

IMO Configuration

Address: 0x40030030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLE	None [30:24]						

Bits	Name	Description
31	ENABLE	Master enable for IMO oscillator. Clearing this bit will disable the IMO. Don't do this if the system is running off it. Default Value: 1

21.1.8 CLK_DFT_SELECT

Clock DFT Mode Selection Register

Address: 0x40030034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW		RW			
HW Access	None	R	R		R			
Name	None	DFT_EDGE0	DFT_DIV0 [5:4]		DFT_SEL0 [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW	RW		RW			
HW Access	None	R	R		R			
Name	None	DFT_EDGE1	DFT_DIV1 [13:12]		DFT_SEL1 [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
14	DFT_EDGE1	Edge sensitivity for in-line divider on output #1 (only relevant when DIV1>0). Default Value: 0 **0x0: POSEDGE:** Use posedge for divider **0x1: NEGEDGE:** Use negedge for divider
13 : 12	DFT_DIV1	DFT Output Divide Down. Default Value: 0 **0x0: NO_DIV:** Direct Output **0x1: DIV_BY_2:** Divide by 2 **0x2: DIV_BY_4:** Divide by 4

21.1.8 CLK_DFT_SELECT (continued)

		0x3: DIV_BY_8: Divide by 8
11 : 8	DFT_SEL1	Select signal for DFT output #1 Default Value: 0 **0x0: NC:** Disabled - output is 0 **0x1: ILO:** clk_ilo: ILO output **0x2: IMO:** clk_imo: IMO primary output **0x3: ECO:** clk_eco: ECO output **0x4: EXTCLK:** clk_ext: external clock input **0x5: HFCLK:** clk_hf: root of the high-speed clock tree **0x6: LFCLK:** clk_lf: root of the low-speed clock tree **0x7: SYSCLK:** clk_sys: root of the CPU/AHB clock tree (gated version of clk_hf) **0x8: PUMPCLK:** clk_pump: clock provided to charge pumps in FLASH and PA **0x9: SLPCTRLCLK:** clk_slpctrl: clock provided to SleepController
6	DFT_EDGE0	Edge sensitivity for in-line divider on output #0 (only relevant when DIV0>0). Default Value: 0 **0x0: POSEDGE:** Use posedge for divider **0x1: NEGEDGE:** Use negedge for divider
5 : 4	DFT_DIV0	DFT Output Divide Down. Default Value: 0 **0x0: NO_DIV:** Direct Output **0x1: DIV_BY_2:** Divide by 2 **0x2: DIV_BY_4:** Divide by 4 **0x3: DIV_BY_8:** Divide by 8
3 : 0	DFT_SEL0	Select signal for DFT output #0 Default Value: 0 **0x0: NC:** Disabled - output is 0

21.1.8 CLK_DFT_SELECT (continued)

0x1: ILO:
clk_ilo: ILO output

0x2: IMO:
clk_imo: IMO primary output

0x3: ECO:
clk_eco: ECO output

0x4: EXTCLK:
clk_ext: external clock input

0x5: HFCLK:
clk_hf: root of the high-speed clock tree

0x6: LFCLK:
clk_lf: root of the low-speed clock tree

0x7: SYSCLK:
clk_sys: root of the CPU/AHB clock tree (gated version of clk_hf)

0x8: PUMPCLK:
clk_pump: clock provided to charge pumps in FLASH and PA

0x9: SLPCTRLCLK:
clk_slpctrl: clock provided to SleepController

21.1.9 WDT_DISABLE_KEY

Watchdog Disable Key Register

Address: 0x40030038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	KEY [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	KEY [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	KEY [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	KEY [31:24]							

Bits	Name	Description
31 : 0	KEY	Disables WDT reset when equal to 0xACED8865. The WDT reset functions normally for any other setting. Default Value: 0

21.1.10 WDT_COUNTER

Watchdog Counter Register

Address: 0x4003003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	Current value of WDT Counter Default Value: 0

21.1.11 WDT_MATCH

Watchdog Match Register

Address: 0x40030040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	MATCH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	MATCH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				IGNORE_BITS [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	IGNORE_BITS	The number of MSB bits of the watchdog timer that are NOT checked against MATCH. This value provides control over the time-to-reset of the watchdog (which happens after 3 successive matches). Note that certain products may enforce a minimum value for this register through design time configuration. Default Value: 0
15 : 0	MATCH	Match value for Watchdog counter. Every time WDT_COUNTER reaches MATCH an interrupt is generated. Two unserviced interrupts will lead to a system reset (i.e. at the third match). Default Value: 4096

21.1.12 SRSS_INTR

SRSS Interrupt Register

Address: 0x40030044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [7:2]						TEMP_HIGH	WDT_MATCH

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Regulator over-temp interrupt. This interrupt can occur when a short circuit exists on the vccd pin or when extreme loads are applied on IO-cells causing the die to overheat. Firmware is encourage to shutdown all IO cells and then go to DeepSleep mode when this interrupt occurs if protection against such conditions is desired. Default Value: 0
0	WDT_MATCH	WDT Interrupt Request. This bit is set each time WDT_COUNTR==WDT_MATCH. Clearing this bit also feeds the watch dog. Missing 2 interrupts in a row will generate brown-out reset. Due to internal synchronization, it takes 2 SYSCLK cycles to update after a W1C. Default Value: 0

21.1.13 SRSS_INTR_SET

SRSS Interrupt Set Register

Address: 0x40030048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	None
HW Access	None						A	None
Name	None [7:2]						TEMP_HIGH	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Writing 1 to this bit internally sets the overtemp interrupt. This can be observed by reading SRSS_INTR.TEMP_HIGH. This bit always reads back as zero. Default Value: 0

21.1.14 SRSS_INTR_MASK

SRSS Interrupt Mask Register

Address: 0x4003004C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						TEMP_HIGH	WDT_MATCH

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Masks REG_OVERTEMP interrupt Default Value: 0
0	WDT_MATCH	Clearing this bit will not forward the interrupt to the CPU. It will not, however, disable the WDT reset generation on 2 missed interrupts. Default Value: 0

21.1.15 RES_CAUSE

Reset Cause Observation Register

Address: 0x40030054

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	None		RW1C
HW Access	None			A	A	None		A
Name	None [7:5]			RESET_SOFT	RESET_PROT_FAULT	None [2:1]		RESET_WDT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESET_SOFT	Cortex-M0 requested a system reset through it's SYSRESETREQ. This can be done via a debugger probe or in firmware. Default Value: 0
3	RESET_PROT_FAULT	A protection violation occurred that requires a RESET. This includes, but is not limited to, hitting a debug breakpoint while in Privileged Mode. Default Value: 0
0	RESET_WDT	A WatchDog Timer reset has occurred since last power cycle. Default Value: 0

21.1.16 CLK_IMO_SELECT

IMO Frequency Select Register

Address: 0x40030F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					FREQ [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	FREQ	Select operating frequency Default Value: 0 **0x0: 24_MHZ:** IMO runs at 24 MHz **0x1: 28_MHZ:** IMO runs at 28 MHz **0x2: 32_MHZ:** IMO runs at 32 MHz **0x3: 36_MHZ:** IMO runs at 36 MHz **0x4: 40_MHZ:** IMO runs at 40 MHz **0x5: 44_MHZ:** IMO runs at 44 MHz **0x6: 48_MHZ:** IMO runs at 48 MHz

21.1.17 CLK_IMO_TRIM1

IMO Trim Register

Address: 0x40030F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	OFFSET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. This field is hardware updated during USB osclock mode. This field is mapped to the most significant bits of the IMO trim imo_clk_trim[10:3]. The step size of 1 LSB on this field is approximately 120 kHz. Default Value: 128

21.1.18 CLK_IMO_TRIM2

IMO Trim Register

Address: 0x40030F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					RW		
Name	None [7:3]					FSOFFSET [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	FSOFFSET	Frequency trim bits. These bits are not trimmed during manufacturing and kept at 0 under normal operation. This field is hardware updated during USB osclock mode. This field is mapped to the least significant bits of the IMO trim imo_clk_trim[2:0]. The step size of 1 LSB on this field is approximately 15 kHz. Default Value: 0

21.1.19 PWR_PWRSYS_TRIM1

Power System Trim Register

Address: 0x40030F14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SPARE_TRIM [7:4]				DPSLP_REF_TRIM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	SPARE_TRIM	Active-Reference temperature compensation trim (repurposed from spare bits). Bits [7:6] - trim the Active-Reference IREF temperature coefficient (TC). 00: TC = 0 (unchanged) 01: TC = +80ppm/C 10: TC = -80ppm/C 11: TC = -150ppm/C Bits [5:4] - trim the Active-Reference VREF temperature coefficient (TC). 00: TC = 0 (unchanged) 01: TC = -50ppm/C 10: TC = -80ppm/C 11: TC = +150ppm/C Default Value: 0
3 : 0	DPSLP_REF_TRIM	Trims the DeepSleep reference that is used by the DeepSleep regulator and DeepSleep power comparator. Default Value: 0

21.1.20 CLK_IMO_TRIM3

IMO Trim Register

Address: 0x40030F18

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSIZE [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22 TCPWM Registers

This section discusses the TCPWM registers. It lists all the registers in mapping tables, in address order.

22.1 Register Details

Register Name	Address
TCPWM_CTRL	0x40200000
TCPWM_CMD	0x40200008
TCPWM_INTR_CAUSE	0x4020000C

22.1.1 TCPWM_CTRL

TCPWM control register 0.

Address: 0x40200000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	COUNTER_ENABLED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	COUNTER_ENABLED	Counter enables for counters 0 up to CNT_NR-1. '0': counter disabled. '1': counter enabled. Counter static configuration information (e.g. CTRL.MODE, all TR_CTRL0, TR_CTRL1, and TR_CTRL2 register fields) should only be modified when the counter is disabled. When a counter is disabled, command and status information associated to the counter is cleared by HW, this includes: - the associated counter triggers in the CMD register are set to '0'. - the counter's interrupt cause fields in counter's INTR register. - the counter's status fields in counter's STATUS register.. - the counter's trigger outputs ("tr_overflow", "tr_underflow" and "tr_compare_match"). - the counter's line outputs ("line_out" and "line_compl_out"). Default Value: 0

22.1.2 TCPWM_CMD

TCPWM command register.

Address: 0x40200008

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_CAPTURE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_RELOAD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_STOP [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	RW1C							
Name	COUNTER_START [31:24]							

Bits	Name	Description
31 : 24	COUNTER_START	Counters SW start trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
23 : 16	COUNTER_STOP	Counters SW stop trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
15 : 8	COUNTER_RELOAD	Counters SW reload trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
7 : 0	COUNTER_CAPTURE	Counters SW capture trigger. When written with '1', a capture trigger is generated and the HW sets the field to '0' when the SW trigger has taken effect. It should be noted that the HW operates on the counter frequency. If the counter is disabled through CTRL.COUNTER_ENABLED, the field is immediately set to '0'. Default Value: 0

22.1.3 TCPWM_INTR_CAUSE

TCPWM Counter interrupt cause register.

Address: 0x4020000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	COUNTER_INT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	COUNTER_INT	Counters interrupt signal active. If the counter is disabled through CTRL.COUNTER_ENABLED, the associated interrupt field is immediately set to '0'. Default Value: 0

23 TR Group Registers

This section discusses the TR Group registers. It lists all the registers in mapping tables, in address order.

23.1 Register Details

Register Name	Address
PERI_TR_GROUP0_TR_OUT_CTL0	0x40012000
PERI_TR_GROUP0_TR_OUT_CTL1	0x40012004
PERI_TR_GROUP0_TR_OUT_CTL2	0x40012008
PERI_TR_GROUP0_TR_OUT_CTL3	0x4001200C
PERI_TR_GROUP0_TR_OUT_CTL4	0x40012010
PERI_TR_GROUP0_TR_OUT_CTL5	0x40012014
PERI_TR_GROUP0_TR_OUT_CTL6	0x40012018
PERI_TR_GROUP0_TR_OUT_CTL7	0x4001201C
PERI_TR_GROUP1_TR_OUT_CTL0	0x40012200
PERI_TR_GROUP1_TR_OUT_CTL1	0x40012204
PERI_TR_GROUP1_TR_OUT_CTL2	0x40012208
PERI_TR_GROUP1_TR_OUT_CTL3	0x4001220C
PERI_TR_GROUP1_TR_OUT_CTL4	0x40012210
PERI_TR_GROUP1_TR_OUT_CTL5	0x40012214
PERI_TR_GROUP1_TR_OUT_CTL6	0x40012218
PERI_TR_GROUP1_TR_OUT_CTL7	0x4001221C
PERI_TR_GROUP2_TR_OUT_CTL0	0x40012400
PERI_TR_GROUP2_TR_OUT_CTL1	0x40012404
PERI_TR_GROUP2_TR_OUT_CTL2	0x40012408
PERI_TR_GROUP2_TR_OUT_CTL3	0x4001240C
PERI_TR_GROUP2_TR_OUT_CTL4	0x40012410
PERI_TR_GROUP2_TR_OUT_CTL5	0x40012414
PERI_TR_GROUP2_TR_OUT_CTL6	0x40012418
PERI_TR_GROUP2_TR_OUT_CTL7	0x4001241C
PERI_TR_GROUP3_TR_OUT_CTL0	0x40012600
PERI_TR_GROUP3_TR_OUT_CTL1	0x40012604
PERI_TR_GROUP3_TR_OUT_CTL2	0x40012608

Register Name	Address
PERI_TR_GROUP3_TR_OUT_CTL3	0x4001260C
PERI_TR_GROUP3_TR_OUT_CTL4	0x40012610
PERI_TR_GROUP3_TR_OUT_CTL5	0x40012614
PERI_TR_GROUP4_TR_OUT_CTL	0x40012800

23.1.1 PERI_TR_GROUP0_TR_OUT_CTL0

Trigger control register

Address: 0x40012000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.2 PERI_TR_GROUP0_TR_OUT_CTL1

Trigger control register

Address: 0x40012004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.3 PERI_TR_GROUP0_TR_OUT_CTL2

Trigger control register

Address: 0x40012008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.4 PERI_TR_GROUP0_TR_OUT_CTL3

Trigger control register

Address: 0x4001200C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.5 PERI_TR_GROUP0_TR_OUT_CTL4

Trigger control register

Address: 0x40012010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.6 PERI_TR_GROUP0_TR_OUT_CTL5

Trigger control register

Address: 0x40012014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.7 PERI_TR_GROUP0_TR_OUT_CTL6

Trigger control register

Address: 0x40012018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.8 PERI_TR_GROUP0_TR_OUT_CTL7

Trigger control register

Address: 0x4001201C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.9 PERI_TR_GROUP1_TR_OUT_CTL0

Trigger control register

Address: 0x40012200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.10 PERI_TR_GROUP1_TR_OUT_CTL1

Trigger control register

Address: 0x40012204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.11 PERI_TR_GROUP1_TR_OUT_CTL2

Trigger control register

Address: 0x40012208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.12 PERI_TR_GROUP1_TR_OUT_CTL3

Trigger control register

Address: 0x4001220C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.13 PERI_TR_GROUP1_TR_OUT_CTL4

Trigger control register

Address: 0x40012210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.14 PERI_TR_GROUP1_TR_OUT_CTL5

Trigger control register

Address: 0x40012214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.15 PERI_TR_GROUP1_TR_OUT_CTL6

Trigger control register

Address: 0x40012218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.16 PERI_TR_GROUP1_TR_OUT_CTL7

Trigger control register

Address: 0x4001221C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.17 PERI_TR_GROUP2_TR_OUT_CTL0

Trigger control register

Address: 0x40012400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.18 PERI_TR_GROUP2_TR_OUT_CTL1

Trigger control register

Address: 0x40012404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.19 PERI_TR_GROUP2_TR_OUT_CTL2

Trigger control register

Address: 0x40012408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.20 PERI_TR_GROUP2_TR_OUT_CTL3

Trigger control register

Address: 0x4001240C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.21 PERI_TR_GROUP2_TR_OUT_CTL4

Trigger control register

Address: 0x40012410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.22 PERI_TR_GROUP2_TR_OUT_CTL5

Trigger control register

Address: 0x40012414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.23 PERI_TR_GROUP2_TR_OUT_CTL6

Trigger control register

Address: 0x40012418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.24 PERI_TR_GROUP2_TR_OUT_CTL7

Trigger control register

Address: 0x4001241C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.25 PERI_TR_GROUP3_TR_OUT_CTL0

Trigger control register

Address: 0x40012600

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.26 PERI_TR_GROUP3_TR_OUT_CTL1

Trigger control register

Address: 0x40012604

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.27 PERI_TR_GROUP3_TR_OUT_CTL2

Trigger control register

Address: 0x40012608

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.28 PERI_TR_GROUP3_TR_OUT_CTL3

Trigger control register

Address: 0x4001260C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.29 PERI_TR_GROUP3_TR_OUT_CTL4

Trigger control register

Address: 0x40012610

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.30 PERI_TR_GROUP3_TR_OUT_CTL5

Trigger control register

Address: 0x40012614

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.31 PERI_TR_GROUP4_TR_OUT_CTL

Trigger control register

Address: 0x40012800

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

24 USBDEV Registers

This section discusses the USBDEV registers. It lists all the registers in mapping tables, in address order.

24.1 Register Details

Register Name	Address
USBDEVv2_EP0_DR0	0x402C0000
USBDEVv2_EP0_DR1	0x402C0004
USBDEVv2_EP0_DR2	0x402C0008
USBDEVv2_EP0_DR3	0x402C000C
USBDEVv2_EP0_DR4	0x402C0010
USBDEVv2_EP0_DR5	0x402C0014
USBDEVv2_EP0_DR6	0x402C0018
USBDEVv2_EP0_DR7	0x402C001C
USBDEVv2_CR0	0x402C0020
USBDEVv2_CR1	0x402C0024
USBDEVv2_SIE_EP_INT_EN	0x402C0028
USBDEVv2_SIE_EP_INT_SR	0x402C002C
USBDEVv2_SIE_EP1_CNT0	0x402C0030
USBDEVv2_SIE_EP1_CNT1	0x402C0034
USBDEVv2_SIE_EP1_CR0	0x402C0038
USBDEVv2_USBIO_CR0	0x402C0040
USBDEVv2_USBIO_CR2	0x402C0044
USBDEVv2_USBIO_CR1	0x402C0048
USBDEVv2_DYN_RECONFIG	0x402C0050
USBDEVv2_SOF0	0x402C0060
USBDEVv2_SOF1	0x402C0064
USBDEVv2_SIE_EP2_CNT0	0x402C0070
USBDEVv2_SIE_EP2_CNT1	0x402C0074
USBDEVv2_SIE_EP2_CR0	0x402C0078
USBDEVv2_OSCLK_DR0	0x402C0080
USBDEVv2_OSCLK_DR1	0x402C0084
USBDEVv2_EP0_CR	0x402C00A0

Register Name	Address
USBDEVv2_EP0_CNT	0x402C00A4
USBDEVv2_SIE_EP3_CNT0	0x402C00B0
USBDEVv2_SIE_EP3_CNT1	0x402C00B4
USBDEVv2_SIE_EP3_CR0	0x402C00B8
USBDEVv2_SIE_EP4_CNT0	0x402C00F0
USBDEVv2_SIE_EP4_CNT1	0x402C00F4
USBDEVv2_SIE_EP4_CR0	0x402C00F8
USBDEVv2_SIE_EP5_CNT0	0x402C0130
USBDEVv2_SIE_EP5_CNT1	0x402C0134
USBDEVv2_SIE_EP5_CR0	0x402C0138
USBDEVv2_SIE_EP6_CNT0	0x402C0170
USBDEVv2_SIE_EP6_CNT1	0x402C0174
USBDEVv2_SIE_EP6_CR0	0x402C0178
USBDEVv2_SIE_EP7_CNT0	0x402C01B0
USBDEVv2_SIE_EP7_CNT1	0x402C01B4
USBDEVv2_SIE_EP7_CR0	0x402C01B8
USBDEVv2_SIE_EP8_CNT0	0x402C01F0
USBDEVv2_SIE_EP8_CNT1	0x402C01F4
USBDEVv2_SIE_EP8_CR0	0x402C01F8
USBDEVv2_ARB_EP1_CFG	0x402C0200
USBDEVv2_ARB_EP1_INT_EN	0x402C0204
USBDEVv2_ARB_EP1_SR	0x402C0208
USBDEVv2_ARB_RW1_WA	0x402C0210
USBDEVv2_ARB_RW1_WA_MSB	0x402C0214
USBDEVv2_ARB_RW1_RA	0x402C0218
USBDEVv2_ARB_RW1_RA_MSB	0x402C021C
USBDEVv2_ARB_RW1_DR	0x402C0220
USBDEVv2_BUF_SIZE	0x402C0230
USBDEVv2_EP_ACTIVE	0x402C0238
USBDEVv2_EP_TYPE	0x402C023C
USBDEVv2_ARB_EP2_CFG	0x402C0240
USBDEVv2_ARB_EP2_INT_EN	0x402C0244
USBDEVv2_ARB_EP2_SR	0x402C0248
USBDEVv2_ARB_RW2_WA	0x402C0250
USBDEVv2_ARB_RW2_WA_MSB	0x402C0254
USBDEVv2_ARB_RW2_RA	0x402C0258
USBDEVv2_ARB_RW2_RA_MSB	0x402C025C
USBDEVv2_ARB_RW2_DR	0x402C0260
USBDEVv2_ARB_CFG	0x402C0270
USBDEVv2_USB_CLK_EN	0x402C0274
USBDEVv2_ARB_INT_EN	0x402C0278
USBDEVv2_ARB_INT_SR	0x402C027C

Register Name	Address
USBDEVv2_ARB_EP3_CFG	0x402C0280
USBDEVv2_ARB_EP3_INT_EN	0x402C0284
USBDEVv2_ARB_EP3_SR	0x402C0288
USBDEVv2_ARB_RW3_WA	0x402C0290
USBDEVv2_ARB_RW3_WA_MSB	0x402C0294
USBDEVv2_ARB_RW3_RA	0x402C0298
USBDEVv2_ARB_RW3_RA_MSB	0x402C029C
USBDEVv2_ARB_RW3_DR	0x402C02A0
USBDEVv2_CWA	0x402C02B0
USBDEVv2_CWA_MSB	0x402C02B4
USBDEVv2_ARB_EP4_CFG	0x402C02C0
USBDEVv2_ARB_EP4_INT_EN	0x402C02C4
USBDEVv2_ARB_EP4_SR	0x402C02C8
USBDEVv2_ARB_RW4_WA	0x402C02D0
USBDEVv2_ARB_RW4_WA_MSB	0x402C02D4
USBDEVv2_ARB_RW4_RA	0x402C02D8
USBDEVv2_ARB_RW4_RA_MSB	0x402C02DC
USBDEVv2_ARB_RW4_DR	0x402C02E0
USBDEVv2_DMA_THRES	0x402C02F0
USBDEVv2_DMA_THRES_MSB	0x402C02F4
USBDEVv2_ARB_EP5_CFG	0x402C0300
USBDEVv2_ARB_EP5_INT_EN	0x402C0304
USBDEVv2_ARB_EP5_SR	0x402C0308
USBDEVv2_ARB_RW5_WA	0x402C0310
USBDEVv2_ARB_RW5_WA_MSB	0x402C0314
USBDEVv2_ARB_RW5_RA	0x402C0318
USBDEVv2_ARB_RW5_RA_MSB	0x402C031C
USBDEVv2_ARB_RW5_DR	0x402C0320
USBDEVv2_BUS_RST_CNT	0x402C0330
USBDEVv2_ARB_EP6_CFG	0x402C0340
USBDEVv2_ARB_EP6_INT_EN	0x402C0344
USBDEVv2_ARB_EP6_SR	0x402C0348
USBDEVv2_ARB_RW6_WA	0x402C0350
USBDEVv2_ARB_RW6_WA_MSB	0x402C0354
USBDEVv2_ARB_RW6_RA	0x402C0358
USBDEVv2_ARB_RW6_RA_MSB	0x402C035C
USBDEVv2_ARB_RW6_DR	0x402C0360
USBDEVv2_ARB_EP7_CFG	0x402C0380
USBDEVv2_ARB_EP7_INT_EN	0x402C0384
USBDEVv2_ARB_EP7_SR	0x402C0388
USBDEVv2_ARB_RW7_WA	0x402C0390
USBDEVv2_ARB_RW7_WA_MSB	0x402C0394

Register Name	Address
USBDEVv2_ARB_RW7_RA	0x402C0398
USBDEVv2_ARB_RW7_RA_MSB	0x402C039C
USBDEVv2_ARB_RW7_DR	0x402C03A0
USBDEVv2_ARB_EP8_CFG	0x402C03C0
USBDEVv2_ARB_EP8_INT_EN	0x402C03C4
USBDEVv2_ARB_EP8_SR	0x402C03C8
USBDEVv2_ARB_RW8_WA	0x402C03D0
USBDEVv2_ARB_RW8_WA_MSB	0x402C03D4
USBDEVv2_ARB_RW8_RA	0x402C03D8
USBDEVv2_ARB_RW8_RA_MSB	0x402C03DC
USBDEVv2_ARB_RW8_DR	0x402C03E0
USBDEVv2_MEM_DATA0	0x402C0400
USBDEVv2_MEM_DATA1	0x402C0404
USBDEVv2_MEM_DATA2	0x402C0408
USBDEVv2_MEM_DATA3	0x402C040C
USBDEVv2_MEM_DATA4	0x402C0410
USBDEVv2_MEM_DATA5	0x402C0414
USBDEVv2_MEM_DATA6	0x402C0418
USBDEVv2_MEM_DATA7	0x402C041C
USBDEVv2_MEM_DATA8	0x402C0420
USBDEVv2_MEM_DATA9	0x402C0424
USBDEVv2_MEM_DATA10	0x402C0428
USBDEVv2_MEM_DATA11	0x402C042C
USBDEVv2_MEM_DATA12	0x402C0430
USBDEVv2_MEM_DATA13	0x402C0434
USBDEVv2_MEM_DATA14	0x402C0438
USBDEVv2_MEM_DATA15	0x402C043C
USBDEVv2_MEM_DATA16	0x402C0440
USBDEVv2_MEM_DATA17	0x402C0444
USBDEVv2_MEM_DATA18	0x402C0448
USBDEVv2_MEM_DATA19	0x402C044C
USBDEVv2_MEM_DATA20	0x402C0450
USBDEVv2_MEM_DATA21	0x402C0454
USBDEVv2_MEM_DATA22	0x402C0458
USBDEVv2_MEM_DATA23	0x402C045C
USBDEVv2_MEM_DATA24	0x402C0460
USBDEVv2_MEM_DATA25	0x402C0464
USBDEVv2_MEM_DATA26	0x402C0468
USBDEVv2_MEM_DATA27	0x402C046C
USBDEVv2_MEM_DATA28	0x402C0470
USBDEVv2_MEM_DATA29	0x402C0474
USBDEVv2_MEM_DATA30	0x402C0478

Register Name	Address
USBDEVv2_MEM_DATA31	0x402C047C
USBDEVv2_MEM_DATA32	0x402C0480
USBDEVv2_MEM_DATA33	0x402C0484
USBDEVv2_MEM_DATA34	0x402C0488
USBDEVv2_MEM_DATA35	0x402C048C
USBDEVv2_MEM_DATA36	0x402C0490
USBDEVv2_MEM_DATA37	0x402C0494
USBDEVv2_MEM_DATA38	0x402C0498
USBDEVv2_MEM_DATA39	0x402C049C
USBDEVv2_MEM_DATA40	0x402C04A0
USBDEVv2_MEM_DATA41	0x402C04A4
USBDEVv2_MEM_DATA42	0x402C04A8
USBDEVv2_MEM_DATA43	0x402C04AC
USBDEVv2_MEM_DATA44	0x402C04B0
USBDEVv2_MEM_DATA45	0x402C04B4
USBDEVv2_MEM_DATA46	0x402C04B8
USBDEVv2_MEM_DATA47	0x402C04BC
USBDEVv2_MEM_DATA48	0x402C04C0
USBDEVv2_MEM_DATA49	0x402C04C4
USBDEVv2_MEM_DATA50	0x402C04C8
USBDEVv2_MEM_DATA51	0x402C04CC
USBDEVv2_MEM_DATA52	0x402C04D0
USBDEVv2_MEM_DATA53	0x402C04D4
USBDEVv2_MEM_DATA54	0x402C04D8
USBDEVv2_MEM_DATA55	0x402C04DC
USBDEVv2_MEM_DATA56	0x402C04E0
USBDEVv2_MEM_DATA57	0x402C04E4
USBDEVv2_MEM_DATA58	0x402C04E8
USBDEVv2_MEM_DATA59	0x402C04EC
USBDEVv2_MEM_DATA60	0x402C04F0
USBDEVv2_MEM_DATA61	0x402C04F4
USBDEVv2_MEM_DATA62	0x402C04F8
USBDEVv2_MEM_DATA63	0x402C04FC
USBDEVv2_MEM_DATA64	0x402C0500
USBDEVv2_MEM_DATA65	0x402C0504
USBDEVv2_MEM_DATA66	0x402C0508
USBDEVv2_MEM_DATA67	0x402C050C
USBDEVv2_MEM_DATA68	0x402C0510
USBDEVv2_MEM_DATA69	0x402C0514
USBDEVv2_MEM_DATA70	0x402C0518
USBDEVv2_MEM_DATA71	0x402C051C
USBDEVv2_MEM_DATA72	0x402C0520

Register Name	Address
USBDEVv2_MEM_DATA73	0x402C0524
USBDEVv2_MEM_DATA74	0x402C0528
USBDEVv2_MEM_DATA75	0x402C052C
USBDEVv2_MEM_DATA76	0x402C0530
USBDEVv2_MEM_DATA77	0x402C0534
USBDEVv2_MEM_DATA78	0x402C0538
USBDEVv2_MEM_DATA79	0x402C053C
USBDEVv2_MEM_DATA80	0x402C0540
USBDEVv2_MEM_DATA81	0x402C0544
USBDEVv2_MEM_DATA82	0x402C0548
USBDEVv2_MEM_DATA83	0x402C054C
USBDEVv2_MEM_DATA84	0x402C0550
USBDEVv2_MEM_DATA85	0x402C0554
USBDEVv2_MEM_DATA86	0x402C0558
USBDEVv2_MEM_DATA87	0x402C055C
USBDEVv2_MEM_DATA88	0x402C0560
USBDEVv2_MEM_DATA89	0x402C0564
USBDEVv2_MEM_DATA90	0x402C0568
USBDEVv2_MEM_DATA91	0x402C056C
USBDEVv2_MEM_DATA92	0x402C0570
USBDEVv2_MEM_DATA93	0x402C0574
USBDEVv2_MEM_DATA94	0x402C0578
USBDEVv2_MEM_DATA95	0x402C057C
USBDEVv2_MEM_DATA96	0x402C0580
USBDEVv2_MEM_DATA97	0x402C0584
USBDEVv2_MEM_DATA98	0x402C0588
USBDEVv2_MEM_DATA99	0x402C058C
USBDEVv2_MEM_DATA100	0x402C0590
USBDEVv2_MEM_DATA101	0x402C0594
USBDEVv2_MEM_DATA102	0x402C0598
USBDEVv2_MEM_DATA103	0x402C059C
USBDEVv2_MEM_DATA104	0x402C05A0
USBDEVv2_MEM_DATA105	0x402C05A4
USBDEVv2_MEM_DATA106	0x402C05A8
USBDEVv2_MEM_DATA107	0x402C05AC
USBDEVv2_MEM_DATA108	0x402C05B0
USBDEVv2_MEM_DATA109	0x402C05B4
USBDEVv2_MEM_DATA110	0x402C05B8
USBDEVv2_MEM_DATA111	0x402C05BC
USBDEVv2_MEM_DATA112	0x402C05C0
USBDEVv2_MEM_DATA113	0x402C05C4
USBDEVv2_MEM_DATA114	0x402C05C8

Register Name	Address
USBDEVv2_MEM_DATA115	0x402C05CC
USBDEVv2_MEM_DATA116	0x402C05D0
USBDEVv2_MEM_DATA117	0x402C05D4
USBDEVv2_MEM_DATA118	0x402C05D8
USBDEVv2_MEM_DATA119	0x402C05DC
USBDEVv2_MEM_DATA120	0x402C05E0
USBDEVv2_MEM_DATA121	0x402C05E4
USBDEVv2_MEM_DATA122	0x402C05E8
USBDEVv2_MEM_DATA123	0x402C05EC
USBDEVv2_MEM_DATA124	0x402C05F0
USBDEVv2_MEM_DATA125	0x402C05F4
USBDEVv2_MEM_DATA126	0x402C05F8
USBDEVv2_MEM_DATA127	0x402C05FC
USBDEVv2_MEM_DATA128	0x402C0600
USBDEVv2_MEM_DATA129	0x402C0604
USBDEVv2_MEM_DATA130	0x402C0608
USBDEVv2_MEM_DATA131	0x402C060C
USBDEVv2_MEM_DATA132	0x402C0610
USBDEVv2_MEM_DATA133	0x402C0614
USBDEVv2_MEM_DATA134	0x402C0618
USBDEVv2_MEM_DATA135	0x402C061C
USBDEVv2_MEM_DATA136	0x402C0620
USBDEVv2_MEM_DATA137	0x402C0624
USBDEVv2_MEM_DATA138	0x402C0628
USBDEVv2_MEM_DATA139	0x402C062C
USBDEVv2_MEM_DATA140	0x402C0630
USBDEVv2_MEM_DATA141	0x402C0634
USBDEVv2_MEM_DATA142	0x402C0638
USBDEVv2_MEM_DATA143	0x402C063C
USBDEVv2_MEM_DATA144	0x402C0640
USBDEVv2_MEM_DATA145	0x402C0644
USBDEVv2_MEM_DATA146	0x402C0648
USBDEVv2_MEM_DATA147	0x402C064C
USBDEVv2_MEM_DATA148	0x402C0650
USBDEVv2_MEM_DATA149	0x402C0654
USBDEVv2_MEM_DATA150	0x402C0658
USBDEVv2_MEM_DATA151	0x402C065C
USBDEVv2_MEM_DATA152	0x402C0660
USBDEVv2_MEM_DATA153	0x402C0664
USBDEVv2_MEM_DATA154	0x402C0668
USBDEVv2_MEM_DATA155	0x402C066C
USBDEVv2_MEM_DATA156	0x402C0670

Register Name	Address
USBDEVv2_MEM_DATA157	0x402C0674
USBDEVv2_MEM_DATA158	0x402C0678
USBDEVv2_MEM_DATA159	0x402C067C
USBDEVv2_MEM_DATA160	0x402C0680
USBDEVv2_MEM_DATA161	0x402C0684
USBDEVv2_MEM_DATA162	0x402C0688
USBDEVv2_MEM_DATA163	0x402C068C
USBDEVv2_MEM_DATA164	0x402C0690
USBDEVv2_MEM_DATA165	0x402C0694
USBDEVv2_MEM_DATA166	0x402C0698
USBDEVv2_MEM_DATA167	0x402C069C
USBDEVv2_MEM_DATA168	0x402C06A0
USBDEVv2_MEM_DATA169	0x402C06A4
USBDEVv2_MEM_DATA170	0x402C06A8
USBDEVv2_MEM_DATA171	0x402C06AC
USBDEVv2_MEM_DATA172	0x402C06B0
USBDEVv2_MEM_DATA173	0x402C06B4
USBDEVv2_MEM_DATA174	0x402C06B8
USBDEVv2_MEM_DATA175	0x402C06BC
USBDEVv2_MEM_DATA176	0x402C06C0
USBDEVv2_MEM_DATA177	0x402C06C4
USBDEVv2_MEM_DATA178	0x402C06C8
USBDEVv2_MEM_DATA179	0x402C06CC
USBDEVv2_MEM_DATA180	0x402C06D0
USBDEVv2_MEM_DATA181	0x402C06D4
USBDEVv2_MEM_DATA182	0x402C06D8
USBDEVv2_MEM_DATA183	0x402C06DC
USBDEVv2_MEM_DATA184	0x402C06E0
USBDEVv2_MEM_DATA185	0x402C06E4
USBDEVv2_MEM_DATA186	0x402C06E8
USBDEVv2_MEM_DATA187	0x402C06EC
USBDEVv2_MEM_DATA188	0x402C06F0
USBDEVv2_MEM_DATA189	0x402C06F4
USBDEVv2_MEM_DATA190	0x402C06F8
USBDEVv2_MEM_DATA191	0x402C06FC
USBDEVv2_MEM_DATA192	0x402C0700
USBDEVv2_MEM_DATA193	0x402C0704
USBDEVv2_MEM_DATA194	0x402C0708
USBDEVv2_MEM_DATA195	0x402C070C
USBDEVv2_MEM_DATA196	0x402C0710
USBDEVv2_MEM_DATA197	0x402C0714
USBDEVv2_MEM_DATA198	0x402C0718

Register Name	Address
USBDEVv2_MEM_DATA199	0x402C071C
USBDEVv2_MEM_DATA200	0x402C0720
USBDEVv2_MEM_DATA201	0x402C0724
USBDEVv2_MEM_DATA202	0x402C0728
USBDEVv2_MEM_DATA203	0x402C072C
USBDEVv2_MEM_DATA204	0x402C0730
USBDEVv2_MEM_DATA205	0x402C0734
USBDEVv2_MEM_DATA206	0x402C0738
USBDEVv2_MEM_DATA207	0x402C073C
USBDEVv2_MEM_DATA208	0x402C0740
USBDEVv2_MEM_DATA209	0x402C0744
USBDEVv2_MEM_DATA210	0x402C0748
USBDEVv2_MEM_DATA211	0x402C074C
USBDEVv2_MEM_DATA212	0x402C0750
USBDEVv2_MEM_DATA213	0x402C0754
USBDEVv2_MEM_DATA214	0x402C0758
USBDEVv2_MEM_DATA215	0x402C075C
USBDEVv2_MEM_DATA216	0x402C0760
USBDEVv2_MEM_DATA217	0x402C0764
USBDEVv2_MEM_DATA218	0x402C0768
USBDEVv2_MEM_DATA219	0x402C076C
USBDEVv2_MEM_DATA220	0x402C0770
USBDEVv2_MEM_DATA221	0x402C0774
USBDEVv2_MEM_DATA222	0x402C0778
USBDEVv2_MEM_DATA223	0x402C077C
USBDEVv2_MEM_DATA224	0x402C0780
USBDEVv2_MEM_DATA225	0x402C0784
USBDEVv2_MEM_DATA226	0x402C0788
USBDEVv2_MEM_DATA227	0x402C078C
USBDEVv2_MEM_DATA228	0x402C0790
USBDEVv2_MEM_DATA229	0x402C0794
USBDEVv2_MEM_DATA230	0x402C0798
USBDEVv2_MEM_DATA231	0x402C079C
USBDEVv2_MEM_DATA232	0x402C07A0
USBDEVv2_MEM_DATA233	0x402C07A4
USBDEVv2_MEM_DATA234	0x402C07A8
USBDEVv2_MEM_DATA235	0x402C07AC
USBDEVv2_MEM_DATA236	0x402C07B0
USBDEVv2_MEM_DATA237	0x402C07B4
USBDEVv2_MEM_DATA238	0x402C07B8
USBDEVv2_MEM_DATA239	0x402C07BC
USBDEVv2_MEM_DATA240	0x402C07C0

Register Name	Address
USBDEVv2_MEM_DATA241	0x402C07C4
USBDEVv2_MEM_DATA242	0x402C07C8
USBDEVv2_MEM_DATA243	0x402C07CC
USBDEVv2_MEM_DATA244	0x402C07D0
USBDEVv2_MEM_DATA245	0x402C07D4
USBDEVv2_MEM_DATA246	0x402C07D8
USBDEVv2_MEM_DATA247	0x402C07DC
USBDEVv2_MEM_DATA248	0x402C07E0
USBDEVv2_MEM_DATA249	0x402C07E4
USBDEVv2_MEM_DATA250	0x402C07E8
USBDEVv2_MEM_DATA251	0x402C07EC
USBDEVv2_MEM_DATA252	0x402C07F0
USBDEVv2_MEM_DATA253	0x402C07F4
USBDEVv2_MEM_DATA254	0x402C07F8
USBDEVv2_MEM_DATA255	0x402C07FC
USBDEVv2_MEM_DATA256	0x402C0800
USBDEVv2_MEM_DATA257	0x402C0804
USBDEVv2_MEM_DATA258	0x402C0808
USBDEVv2_MEM_DATA259	0x402C080C
USBDEVv2_MEM_DATA260	0x402C0810
USBDEVv2_MEM_DATA261	0x402C0814
USBDEVv2_MEM_DATA262	0x402C0818
USBDEVv2_MEM_DATA263	0x402C081C
USBDEVv2_MEM_DATA264	0x402C0820
USBDEVv2_MEM_DATA265	0x402C0824
USBDEVv2_MEM_DATA266	0x402C0828
USBDEVv2_MEM_DATA267	0x402C082C
USBDEVv2_MEM_DATA268	0x402C0830
USBDEVv2_MEM_DATA269	0x402C0834
USBDEVv2_MEM_DATA270	0x402C0838
USBDEVv2_MEM_DATA271	0x402C083C
USBDEVv2_MEM_DATA272	0x402C0840
USBDEVv2_MEM_DATA273	0x402C0844
USBDEVv2_MEM_DATA274	0x402C0848
USBDEVv2_MEM_DATA275	0x402C084C
USBDEVv2_MEM_DATA276	0x402C0850
USBDEVv2_MEM_DATA277	0x402C0854
USBDEVv2_MEM_DATA278	0x402C0858
USBDEVv2_MEM_DATA279	0x402C085C
USBDEVv2_MEM_DATA280	0x402C0860
USBDEVv2_MEM_DATA281	0x402C0864
USBDEVv2_MEM_DATA282	0x402C0868

Register Name	Address
USBDEVv2_MEM_DATA283	0x402C086C
USBDEVv2_MEM_DATA284	0x402C0870
USBDEVv2_MEM_DATA285	0x402C0874
USBDEVv2_MEM_DATA286	0x402C0878
USBDEVv2_MEM_DATA287	0x402C087C
USBDEVv2_MEM_DATA288	0x402C0880
USBDEVv2_MEM_DATA289	0x402C0884
USBDEVv2_MEM_DATA290	0x402C0888
USBDEVv2_MEM_DATA291	0x402C088C
USBDEVv2_MEM_DATA292	0x402C0890
USBDEVv2_MEM_DATA293	0x402C0894
USBDEVv2_MEM_DATA294	0x402C0898
USBDEVv2_MEM_DATA295	0x402C089C
USBDEVv2_MEM_DATA296	0x402C08A0
USBDEVv2_MEM_DATA297	0x402C08A4
USBDEVv2_MEM_DATA298	0x402C08A8
USBDEVv2_MEM_DATA299	0x402C08AC
USBDEVv2_MEM_DATA300	0x402C08B0
USBDEVv2_MEM_DATA301	0x402C08B4
USBDEVv2_MEM_DATA302	0x402C08B8
USBDEVv2_MEM_DATA303	0x402C08BC
USBDEVv2_MEM_DATA304	0x402C08C0
USBDEVv2_MEM_DATA305	0x402C08C4
USBDEVv2_MEM_DATA306	0x402C08C8
USBDEVv2_MEM_DATA307	0x402C08CC
USBDEVv2_MEM_DATA308	0x402C08D0
USBDEVv2_MEM_DATA309	0x402C08D4
USBDEVv2_MEM_DATA310	0x402C08D8
USBDEVv2_MEM_DATA311	0x402C08DC
USBDEVv2_MEM_DATA312	0x402C08E0
USBDEVv2_MEM_DATA313	0x402C08E4
USBDEVv2_MEM_DATA314	0x402C08E8
USBDEVv2_MEM_DATA315	0x402C08EC
USBDEVv2_MEM_DATA316	0x402C08F0
USBDEVv2_MEM_DATA317	0x402C08F4
USBDEVv2_MEM_DATA318	0x402C08F8
USBDEVv2_MEM_DATA319	0x402C08FC
USBDEVv2_MEM_DATA320	0x402C0900
USBDEVv2_MEM_DATA321	0x402C0904
USBDEVv2_MEM_DATA322	0x402C0908
USBDEVv2_MEM_DATA323	0x402C090C
USBDEVv2_MEM_DATA324	0x402C0910

Register Name	Address
USBDEVv2_MEM_DATA325	0x402C0914
USBDEVv2_MEM_DATA326	0x402C0918
USBDEVv2_MEM_DATA327	0x402C091C
USBDEVv2_MEM_DATA328	0x402C0920
USBDEVv2_MEM_DATA329	0x402C0924
USBDEVv2_MEM_DATA330	0x402C0928
USBDEVv2_MEM_DATA331	0x402C092C
USBDEVv2_MEM_DATA332	0x402C0930
USBDEVv2_MEM_DATA333	0x402C0934
USBDEVv2_MEM_DATA334	0x402C0938
USBDEVv2_MEM_DATA335	0x402C093C
USBDEVv2_MEM_DATA336	0x402C0940
USBDEVv2_MEM_DATA337	0x402C0944
USBDEVv2_MEM_DATA338	0x402C0948
USBDEVv2_MEM_DATA339	0x402C094C
USBDEVv2_MEM_DATA340	0x402C0950
USBDEVv2_MEM_DATA341	0x402C0954
USBDEVv2_MEM_DATA342	0x402C0958
USBDEVv2_MEM_DATA343	0x402C095C
USBDEVv2_MEM_DATA344	0x402C0960
USBDEVv2_MEM_DATA345	0x402C0964
USBDEVv2_MEM_DATA346	0x402C0968
USBDEVv2_MEM_DATA347	0x402C096C
USBDEVv2_MEM_DATA348	0x402C0970
USBDEVv2_MEM_DATA349	0x402C0974
USBDEVv2_MEM_DATA350	0x402C0978
USBDEVv2_MEM_DATA351	0x402C097C
USBDEVv2_MEM_DATA352	0x402C0980
USBDEVv2_MEM_DATA353	0x402C0984
USBDEVv2_MEM_DATA354	0x402C0988
USBDEVv2_MEM_DATA355	0x402C098C
USBDEVv2_MEM_DATA356	0x402C0990
USBDEVv2_MEM_DATA357	0x402C0994
USBDEVv2_MEM_DATA358	0x402C0998
USBDEVv2_MEM_DATA359	0x402C099C
USBDEVv2_MEM_DATA360	0x402C09A0
USBDEVv2_MEM_DATA361	0x402C09A4
USBDEVv2_MEM_DATA362	0x402C09A8
USBDEVv2_MEM_DATA363	0x402C09AC
USBDEVv2_MEM_DATA364	0x402C09B0
USBDEVv2_MEM_DATA365	0x402C09B4
USBDEVv2_MEM_DATA366	0x402C09B8

Register Name	Address
USBDEVv2_MEM_DATA367	0x402C09BC
USBDEVv2_MEM_DATA368	0x402C09C0
USBDEVv2_MEM_DATA369	0x402C09C4
USBDEVv2_MEM_DATA370	0x402C09C8
USBDEVv2_MEM_DATA371	0x402C09CC
USBDEVv2_MEM_DATA372	0x402C09D0
USBDEVv2_MEM_DATA373	0x402C09D4
USBDEVv2_MEM_DATA374	0x402C09D8
USBDEVv2_MEM_DATA375	0x402C09DC
USBDEVv2_MEM_DATA376	0x402C09E0
USBDEVv2_MEM_DATA377	0x402C09E4
USBDEVv2_MEM_DATA378	0x402C09E8
USBDEVv2_MEM_DATA379	0x402C09EC
USBDEVv2_MEM_DATA380	0x402C09F0
USBDEVv2_MEM_DATA381	0x402C09F4
USBDEVv2_MEM_DATA382	0x402C09F8
USBDEVv2_MEM_DATA383	0x402C09FC
USBDEVv2_MEM_DATA384	0x402C0A00
USBDEVv2_MEM_DATA385	0x402C0A04
USBDEVv2_MEM_DATA386	0x402C0A08
USBDEVv2_MEM_DATA387	0x402C0A0C
USBDEVv2_MEM_DATA388	0x402C0A10
USBDEVv2_MEM_DATA389	0x402C0A14
USBDEVv2_MEM_DATA390	0x402C0A18
USBDEVv2_MEM_DATA391	0x402C0A1C
USBDEVv2_MEM_DATA392	0x402C0A20
USBDEVv2_MEM_DATA393	0x402C0A24
USBDEVv2_MEM_DATA394	0x402C0A28
USBDEVv2_MEM_DATA395	0x402C0A2C
USBDEVv2_MEM_DATA396	0x402C0A30
USBDEVv2_MEM_DATA397	0x402C0A34
USBDEVv2_MEM_DATA398	0x402C0A38
USBDEVv2_MEM_DATA399	0x402C0A3C
USBDEVv2_MEM_DATA400	0x402C0A40
USBDEVv2_MEM_DATA401	0x402C0A44
USBDEVv2_MEM_DATA402	0x402C0A48
USBDEVv2_MEM_DATA403	0x402C0A4C
USBDEVv2_MEM_DATA404	0x402C0A50
USBDEVv2_MEM_DATA405	0x402C0A54
USBDEVv2_MEM_DATA406	0x402C0A58
USBDEVv2_MEM_DATA407	0x402C0A5C
USBDEVv2_MEM_DATA408	0x402C0A60

Register Name	Address
USBDEVv2_MEM_DATA409	0x402C0A64
USBDEVv2_MEM_DATA410	0x402C0A68
USBDEVv2_MEM_DATA411	0x402C0A6C
USBDEVv2_MEM_DATA412	0x402C0A70
USBDEVv2_MEM_DATA413	0x402C0A74
USBDEVv2_MEM_DATA414	0x402C0A78
USBDEVv2_MEM_DATA415	0x402C0A7C
USBDEVv2_MEM_DATA416	0x402C0A80
USBDEVv2_MEM_DATA417	0x402C0A84
USBDEVv2_MEM_DATA418	0x402C0A88
USBDEVv2_MEM_DATA419	0x402C0A8C
USBDEVv2_MEM_DATA420	0x402C0A90
USBDEVv2_MEM_DATA421	0x402C0A94
USBDEVv2_MEM_DATA422	0x402C0A98
USBDEVv2_MEM_DATA423	0x402C0A9C
USBDEVv2_MEM_DATA424	0x402C0AA0
USBDEVv2_MEM_DATA425	0x402C0AA4
USBDEVv2_MEM_DATA426	0x402C0AA8
USBDEVv2_MEM_DATA427	0x402C0AAC
USBDEVv2_MEM_DATA428	0x402C0AB0
USBDEVv2_MEM_DATA429	0x402C0AB4
USBDEVv2_MEM_DATA430	0x402C0AB8
USBDEVv2_MEM_DATA431	0x402C0ABC
USBDEVv2_MEM_DATA432	0x402C0AC0
USBDEVv2_MEM_DATA433	0x402C0AC4
USBDEVv2_MEM_DATA434	0x402C0AC8
USBDEVv2_MEM_DATA435	0x402C0ACC
USBDEVv2_MEM_DATA436	0x402C0AD0
USBDEVv2_MEM_DATA437	0x402C0AD4
USBDEVv2_MEM_DATA438	0x402C0AD8
USBDEVv2_MEM_DATA439	0x402C0ADC
USBDEVv2_MEM_DATA440	0x402C0AE0
USBDEVv2_MEM_DATA441	0x402C0AE4
USBDEVv2_MEM_DATA442	0x402C0AE8
USBDEVv2_MEM_DATA443	0x402C0AEC
USBDEVv2_MEM_DATA444	0x402C0AF0
USBDEVv2_MEM_DATA445	0x402C0AF4
USBDEVv2_MEM_DATA446	0x402C0AF8
USBDEVv2_MEM_DATA447	0x402C0AFC
USBDEVv2_MEM_DATA448	0x402C0B00
USBDEVv2_MEM_DATA449	0x402C0B04
USBDEVv2_MEM_DATA450	0x402C0B08

Register Name	Address
USBDEVv2_MEM_DATA451	0x402C0B0C
USBDEVv2_MEM_DATA452	0x402C0B10
USBDEVv2_MEM_DATA453	0x402C0B14
USBDEVv2_MEM_DATA454	0x402C0B18
USBDEVv2_MEM_DATA455	0x402C0B1C
USBDEVv2_MEM_DATA456	0x402C0B20
USBDEVv2_MEM_DATA457	0x402C0B24
USBDEVv2_MEM_DATA458	0x402C0B28
USBDEVv2_MEM_DATA459	0x402C0B2C
USBDEVv2_MEM_DATA460	0x402C0B30
USBDEVv2_MEM_DATA461	0x402C0B34
USBDEVv2_MEM_DATA462	0x402C0B38
USBDEVv2_MEM_DATA463	0x402C0B3C
USBDEVv2_MEM_DATA464	0x402C0B40
USBDEVv2_MEM_DATA465	0x402C0B44
USBDEVv2_MEM_DATA466	0x402C0B48
USBDEVv2_MEM_DATA467	0x402C0B4C
USBDEVv2_MEM_DATA468	0x402C0B50
USBDEVv2_MEM_DATA469	0x402C0B54
USBDEVv2_MEM_DATA470	0x402C0B58
USBDEVv2_MEM_DATA471	0x402C0B5C
USBDEVv2_MEM_DATA472	0x402C0B60
USBDEVv2_MEM_DATA473	0x402C0B64
USBDEVv2_MEM_DATA474	0x402C0B68
USBDEVv2_MEM_DATA475	0x402C0B6C
USBDEVv2_MEM_DATA476	0x402C0B70
USBDEVv2_MEM_DATA477	0x402C0B74
USBDEVv2_MEM_DATA478	0x402C0B78
USBDEVv2_MEM_DATA479	0x402C0B7C
USBDEVv2_MEM_DATA480	0x402C0B80
USBDEVv2_MEM_DATA481	0x402C0B84
USBDEVv2_MEM_DATA482	0x402C0B88
USBDEVv2_MEM_DATA483	0x402C0B8C
USBDEVv2_MEM_DATA484	0x402C0B90
USBDEVv2_MEM_DATA485	0x402C0B94
USBDEVv2_MEM_DATA486	0x402C0B98
USBDEVv2_MEM_DATA487	0x402C0B9C
USBDEVv2_MEM_DATA488	0x402C0BA0
USBDEVv2_MEM_DATA489	0x402C0BA4
USBDEVv2_MEM_DATA490	0x402C0BA8
USBDEVv2_MEM_DATA491	0x402C0BAC
USBDEVv2_MEM_DATA492	0x402C0BB0

Register Name	Address
USBDEVv2_MEM_DATA493	0x402C0BB4
USBDEVv2_MEM_DATA494	0x402C0BB8
USBDEVv2_MEM_DATA495	0x402C0BBC
USBDEVv2_MEM_DATA496	0x402C0BC0
USBDEVv2_MEM_DATA497	0x402C0BC4
USBDEVv2_MEM_DATA498	0x402C0BC8
USBDEVv2_MEM_DATA499	0x402C0BCC
USBDEVv2_MEM_DATA500	0x402C0BD0
USBDEVv2_MEM_DATA501	0x402C0BD4
USBDEVv2_MEM_DATA502	0x402C0BD8
USBDEVv2_MEM_DATA503	0x402C0BDC
USBDEVv2_MEM_DATA504	0x402C0BE0
USBDEVv2_MEM_DATA505	0x402C0BE4
USBDEVv2_MEM_DATA506	0x402C0BE8
USBDEVv2_MEM_DATA507	0x402C0BEC
USBDEVv2_MEM_DATA508	0x402C0BF0
USBDEVv2_MEM_DATA509	0x402C0BF4
USBDEVv2_MEM_DATA510	0x402C0BF8
USBDEVv2_MEM_DATA511	0x402C0BFC
USBDEVv2_SOF16	0x402C1060
USBDEVv2_OSCLK_DR16	0x402C1080
USBDEVv2_ARB_RW1_WA16	0x402C1210
USBDEVv2_ARB_RW1_RA16	0x402C1218
USBDEVv2_ARB_RW1_DR16	0x402C1220
USBDEVv2_ARB_RW2_WA16	0x402C1250
USBDEVv2_ARB_RW2_RA16	0x402C1258
USBDEVv2_ARB_RW2_DR16	0x402C1260
USBDEVv2_ARB_RW3_WA16	0x402C1290
USBDEVv2_ARB_RW3_RA16	0x402C1298
USBDEVv2_ARB_RW3_DR16	0x402C12A0
USBDEVv2_CWA16	0x402C12B0
USBDEVv2_ARB_RW4_WA16	0x402C12D0
USBDEVv2_ARB_RW4_RA16	0x402C12D8
USBDEVv2_ARB_RW4_DR16	0x402C12E0
USBDEVv2_DMA_THRES16	0x402C12F0
USBDEVv2_ARB_RW5_WA16	0x402C1310
USBDEVv2_ARB_RW5_RA16	0x402C1318
USBDEVv2_ARB_RW5_DR16	0x402C1320
USBDEVv2_ARB_RW6_WA16	0x402C1350
USBDEVv2_ARB_RW6_RA16	0x402C1358
USBDEVv2_ARB_RW6_DR16	0x402C1360
USBDEVv2_ARB_RW7_WA16	0x402C1390

Register Name	Address
USBDEVv2_ARB_RW7_RA16	0x402C1398
USBDEVv2_ARB_RW7_DR16	0x402C13A0
USBDEVv2_ARB_RW8_WA16	0x402C13D0
USBDEVv2_ARB_RW8_RA16	0x402C13D8
USBDEVv2_ARB_RW8_DR16	0x402C13E0

24.1.1 USBDEVv2_EP0_DR0

Control End point EP0 Data Register

Address: 0x402C0000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.2 USBDEVv2_EP0_DR1

Control End point EP0 Data Register

Address: 0x402C0004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.3 USBDEVv2_EP0_DR2

Control End point EP0 Data Register

Address: 0x402C0008

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.4 USBDEVv2_EP0_DR3

Control End point EP0 Data Register

Address: 0x402C000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.5 USBDEVv2_EP0_DR4

Control End point EP0 Data Register

Address: 0x402C0010

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.6 USBDEVv2_EP0_DR5

Control End point EP0 Data Register

Address: 0x402C0014

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.7 USBDEVv2_EP0_DR6

Control End point EP0 Data Register

Address: 0x402C0018

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.8 USBDEVv2_EP0_DR7

Control End point EP0 Data Register

Address: 0x402C001C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_BYTE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_BYTE	This register is shared for both transmit and receive. The count in the EP0_CNT register determines the number of bytes received or to be transferred. Default Value: 0

24.1.9 USBDEVv2_CR0

USB control 0 Register

Address: 0x402C0020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW						
HW Access	R	R						
Name	USB_ENABLE	DEVICE_ADDRESS [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	USB_ENABLE	This bit enables the device to respond to USB traffic. Default Value: 0
6 : 0	DEVICE_ADDRESS	These bits specify the USB device address to which the SIE will respond. This address must be set by firmware and is specified by the USB Host with a SET ADDRESS command during USB enumeration. This value must be programmed by firmware when assigned during enumeration. It is not set automatically by the hardware. Default Value: 0

24.1.10 USBDEVv2_CR1

USB control 1 Register

Address: 0x402C0024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW0C	RW	RW
HW Access	None				R	RW1S	R	R
Name	None [7:4]				TRIM_OFFSET_MSB	BUS_ACTIVITY	ENABLE_LOCK	REG_ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	TRIM_OFFSET_MSB	This bit enables trim bit[7]. Default Value: 0
2	BUS_ACTIVITY	The Bus Activity bit is a stickybit that detects any non-idle USB event that has occurred on the USB bus. Once set to High by the SIE to indicate the bus activity this bit retains its logical High value until firmware clears it. Default Value: 0
1	ENABLE_LOCK	This bit is set to turn on the automatic frequency locking of the internal oscillator to USB traffic. Unless an external clock is being provided this bit should remain set for proper USB operation. Default Value: 0
0	REG_ENABLE	This bit controls the operation of the internal USB regulator. For applications with supply voltages in the 5V range this bit is set high to enable the internal regulator. For device supply voltage in the 3.3V range this bit is cleared to connect the transceiver directly to the supply. Default Value: 0

24.1.11 USBDEVv2_SIE_EP_INT_EN

USB SIE Data Endpoints Interrupt Enable Register

Address: 0x402C0028

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	EP8_INTR_EN	EP7_INTR_EN	EP6_INTR_EN	EP5_INTR_EN	EP4_INTR_EN	EP3_INTR_EN	EP2_INTR_EN	EP1_INTR_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_INTR_EN	Enables interrupt for EP8 Default Value: 0
6	EP7_INTR_EN	Enables interrupt for EP7 Default Value: 0
5	EP6_INTR_EN	Enables interrupt for EP6 Default Value: 0
4	EP5_INTR_EN	Enables interrupt for EP5 Default Value: 0
3	EP4_INTR_EN	Enables interrupt for EP4 Default Value: 0
2	EP3_INTR_EN	Enables interrupt for EP3 Default Value: 0
1	EP2_INTR_EN	Enables interrupt for EP2 Default Value: 0

24.1.11 USBDEVv2_SIE_EP_INT_EN (continued)

0	EP1_INTR_EN	Enables interrupt for EP1 Default Value: 0

24.1.12 USBDEVv2_SIE_EP_INT_SR

USB SIE Data Endpoint Interrupt Status

Address: 0x402C002C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_INTR	Interrupt status for EP8 Default Value: 0
6	EP7_INTR	Interrupt status for EP7 Default Value: 0
5	EP6_INTR	Interrupt status for EP6 Default Value: 0
4	EP5_INTR	Interrupt status for EP5 Default Value: 0
3	EP4_INTR	Interrupt status for EP4 Default Value: 0
2	EP3_INTR	Interrupt status for EP3 Default Value: 0
1	EP2_INTR	Interrupt status for EP2 Default Value: 0
0	EP1_INTR	Interrupt status for EP1 Default Value: 0

24.1.13 USBDEVv2_SIE_EP1_CNT0

Non-control endpoint count register

Address: 0x402C0030

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.14 USBDEVv2_SIE_EP1_CNT1

Non-control endpoint count register

Address: 0x402C0034

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.15 USBDEVv2_SIE_EP1_CR0

Non-control endpoint's control Register

Address: 0x402C0038

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.15 USBDEVv2_SIE_EP1_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.15 USBDEVv2_SIE_EP1_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.16 USBDEVv2_USBIO_CR0

USBIO Control 0 Register

Address: 0x402C0040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None				R
HW Access	R	R	R	None				W
Name	TEN	TSE0	TD	None [4:1]				RD

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	TEN	USB Transmit Enable. This is used to manually transmit on the D+ and D- pins. Normally this bit should be cleared to allow the internal SIE to drive the pins. The most common reason for manually transmitting is to force a resume state on the bus. Default Value: 0
6	TSE0	Transmit Single-Ended Zero. SE0: both D+ and D- low. No effect if TEN=0. Default Value: 0
5	TD	Transmit Data. Transmit a USB J or K state on the USB bus. No effect if TEN=0 or TSE0=1. Default Value: 0 **0x0: DIFF_K:** Force USB K state (D+ is low D- is high). **0x1: DIFF_J:** Force USB J state (D+ is high D- is low).
0	RD	Received Data. This read only bit gives the state of the USB differential receiver. Default Value: X **0x0: DIFF_LOW:** D+ < D- (K state), or D+=D-=0 (SE0)

24.1.16 USBDEVv2_USBIO_CR0 (continued)

0x1: DIFF_HIGH:
D+ > D- (J state)

24.1.17 USBDEVv2_USBIO_CR2

USBIO control 2 Register

Address: 0x402C0044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	R					
HW Access	R	R	R					
Name	TEST_RES	TEST_PKT	Reserved [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	TEST_RES	This bit is for testing the non-passthrough suspend mode pull up. When set, the resistor is applied to the D+ pin. Default Value: 0
6	TEST_PKT	This bit enables the device to transmit a packet in response to an internally generated IN packet. When set, one packet will be generated. Default Value: 0
5 : 0	Reserved	Reserved Default Value: 0

24.1.18 USBDEVv2_USBIO_CR1

USBIO control 1 Register

Address: 0x402C0048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	None		RW	R	R
HW Access	None		R	None		R	W	W
Name	None [7:6]		IOMODE	None [4:3]		USBPUEN	DPO	DMO

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	IOMODE	This bit allows the D+ and D- pins to be configured for either USB mode or bit-banged modes. If this bit is set the DMI and DPI bits are used to drive the D- and D+ pins. Default Value: 1
2	USBPUEN	This bit enables the connection of the internal 1.5 k pull up resistor on the D+ pin. Default Value: 0
1	DPO	This read only bit gives the state of the D+ pin. Default Value: X
0	DMO	This read only bit gives the state of the D- pin. Default Value: X

24.1.19 USBDEVv2_DYN_RECONFIG

USB Dynamic reconfiguration register

Address: 0x402C0050

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	RW			RW
HW Access	None			W	R			R
Name	None [7:5]			DYN_RECONFIG_RDY_STS	DYN_RECONFIG_EPNO [3:1]			DYN_CONFIG_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	DYN_RECONFIG_RDY_STS	This bit indicates the ready status for the dynamic reconfiguration, when set to 1, indicates the block is ready for reconfiguration. Default Value: 0
3 : 1	DYN_RECONFIG_EPNO	These bits indicates the EP number for which reconfiguration is required when dyn_config_en bit is set to 1. Default Value: 0
0	DYN_CONFIG_EN	This bit is used to enable the dynamic re-configuration for the selected EP. If set to 1, indicates the reconfiguration required for selected EP. Use 0 for EP1, 1 for EP2, etc. Default Value: 0

24.1.20 USBDEVv2_SOF0

Start Of Frame Register

Address: 0x402C0060

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	FRAME_NUMBER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	FRAME_NUMBER	It has the lower 8 bits [7:0] of the SOF frame number. Default Value: 0

24.1.21 USBDEVv2_SOF1

Start Of Frame Register

Address: 0x402C0064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R		
HW Access	None					RW		
Name	None [7:3]					FRAME_NUMBER_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	FRAME_NUMBER_MSB	It has the upper 3 bits [10:8] of the SOF frame number. Default Value: 0

24.1.22 USBDEVv2_SIE_EP2_CNT0

Non-control endpoint count register

Address: 0x402C0070

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.23 USBDEVv2_SIE_EP2_CNT1

Non-control endpoint count register

Address: 0x402C0074

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.24 USBDEVv2_SIE_EP2_CR0

Non-control endpoint's control Register

Address: 0x402C0078

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.24 USBDEVv2_SIE_EP2_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.24 USBDEVv2_SIE_EP2_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.25 USBDEVv2_OSCLK_DR0

Oscillator lock data register 0

Address: 0x402C0080

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	ADDER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	ADDER	These bits return the lower 8 bits of the oscillator locking circuits adder output. Default Value: X

24.1.26 USBDEVv2_OSCLK_DR1

Oscillator lock data register 1

Address: 0x402C0084

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	R						
HW Access	None	W						
Name	None	ADDER_MSB [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 0	ADDER_MSB	These bits return the upper 7 bits of the oscillator locking circuits adder output. Default Value: X

24.1.27 USBDEVv2_EP0_CR

Endpoint0 control Register

Address: 0x402C00A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RWC	RWC	RWC	RWC	RW			
HW Access	RW1S	RW1S	RW1S	RW1S	RW			
Name	SETUP_RCVD	IN_RCVD	OUT_RCVD	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	SETUP_RCVD	When set this bit indicates a valid SETUP packet was received and ACKed. This bit is forced HIGH from the start of the data packet phase of the SETUP transaction until the start of the ACK packet returned by the SIE. The CPU is prevented from clearing this bit during this interval. After this interval the bit will remain set until cleared by firmware. While this bit is set to '1' the CPU cannot write to the EP0_DRx registers. This prevents firmware from overwriting an incoming SETUP transaction before firmware has a chance to read the SETUP data. This bit is cleared by any non-locked writes to the register. Default Value: 0
6	IN_RCVD	When set this bit indicates a valid IN packet has been received. This bit is updated to '1' after the host acknowledges an IN data packet. When clear this bit indicates either no IN has been received or that the host did not acknowledge the IN data by sending ACK handshake. It is cleared by any writes to the register. Default Value: 0
5	OUT_RCVD	When set this bit indicates a valid OUT packet has been received and ACKed. This bit is updated to '1' after the last received packet in an OUT transaction. When clear this bit indicates no OUT received. It is cleared by any writes to the register. Default Value: 0

24.1.27 USBDEVv2_EP0_CR (continued)

4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's end-point that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.
3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data

24.1.27 USBDEVv2_EP0_CR (continued)

0xc: NAK_IN:
SETUP: Ignore
IN: NAK
OUT: Ignore

0xd: ACK_IN:
SETUP: Ignore
IN: Respond to IN with data if STALL=0, STALL otherwise
OUT: Ignore

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.28 USBDEVv2_EP0_CNT

Endpoint0 count Register

Address: 0x402C00A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None		RW			
HW Access	RW	RW1S	None		RW			
Name	DATA_TOGGLE	DATA_VALID	None [5:4]		BYTE_COUNT [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT/SETUP transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
3 : 0	BYTE_COUNT	These bits indicate the number of data bytes in a transaction. For IN transactions firmware loads the count with the number of bytes to be transmitted to the host from the endpoint FIFO. Valid values are 0 to 8. For OUT or SETUP transactions the count is updated by hardware to the number of data bytes received plus two for the CRC bytes. Valid values are 2 to 10. Default Value: 0

24.1.29 USBDEVv2_SIE_EP3_CNT0

Non-control endpoint count register

Address: 0x402C00B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.30 USBDEVv2_SIE_EP3_CNT1

Non-control endpoint count register

Address: 0x402C00B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.31 USBDEVv2_SIE_EP3_CR0

Non-control endpoint's control Register

Address: 0x402C00B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.31 USBDEVv2_SIE_EP3_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.31 USBDEVv2_SIE_EP3_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.32 USBDEVv2_SIE_EP4_CNT0

Non-control endpoint count register

Address: 0x402C00F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.33 USBDEVv2_SIE_EP4_CNT1

Non-control endpoint count register

Address: 0x402C00F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.34 USBDEVv2_SIE_EP4_CR0

Non-control endpoint's control Register

Address: 0x402C00F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.34 USBDEVv2_SIE_EP4_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.34 USBDEVv2_SIE_EP4_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.35 USBDEVv2_SIE_EP5_CNT0

Non-control endpoint count register

Address: 0x402C0130

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.36 USBDEVv2_SIE_EP5_CNT1

Non-control endpoint count register

Address: 0x402C0134

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.37 USBDEVv2_SIE_EP5_CR0

Non-control endpoint's control Register

Address: 0x402C0138

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.37 USBDEVv2_SIE_EP5_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.37 USBDEVv2_SIE_EP5_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.38 USBDEVv2_SIE_EP6_CNT0

Non-control endpoint count register

Address: 0x402C0170

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.39 USBDEVv2_SIE_EP6_CNT1

Non-control endpoint count register

Address: 0x402C0174

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.40 USBDEVv2_SIE_EP6_CR0

Non-control endpoint's control Register

Address: 0x402C0178

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.40 USBDEVv2_SIE_EP6_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.40 USBDEVv2_SIE_EP6_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.41 USBDEVv2_SIE_EP7_CNT0

Non-control endpoint count register

Address: 0x402C01B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.42 USBDEVv2_SIE_EP7_CNT1

Non-control endpoint count register

Address: 0x402C01B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.43 USBDEVv2_SIE_EP7_CR0

Non-control endpoint's control Register

Address: 0x402C01B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.43 USBDEVv2_SIE_EP7_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.43 USBDEVv2_SIE_EP7_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.44 USBDEVv2_SIE_EP8_CNT0

Non-control endpoint count register

Address: 0x402C01F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW0C	None			RW		
HW Access	RW	RW1S	None			RW		
Name	DATA_TOGGLE	DATA_VALID	None [5:3]			DATA_COUNT_MSB [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA_TOGGLE	This bit selects the DATA packet's toggle state. For IN transactions firmware must set this bit to the expected state. For OUT transactions the hardware sets this bit to the state of the received Data Toggle bit. Default Value: 0
6	DATA_VALID	This bit is used for OUT transactions only and is read only. It is cleared to '0' if CRC bit stuffing errors or PID errors occur. This bit does not update for some endpoint mode settings. Default Value: 0 **0x0: DATA_ERROR:** No ACK'd transactions since bit was last cleared. **0x1: DATA_VALID:** Indicates a transaction ended with an ACK.
2 : 0	DATA_COUNT_MSB	These bits are the 3 MSb bits of an 11-bit counter. The LSb are the Data Count[7:0] bits of the CNT1 register. Refer to the CNT1 register for more information. Default Value: 0

24.1.45 USBDEVv2_SIE_EP8_CNT1

Non-control endpoint count register

Address: 0x402C01F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DATA_COUNT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA_COUNT	These bits are the 8 LSb of a 11-bit counter. The 3 MSb bits are in the CNT0 register. The 11-bit count indicates the number of data bytes in a transaction. Default Value: 0

24.1.46 USBDEVv2_SIE_EP8_CR0

Non-control endpoint's control Register

Address: 0x402C01F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RWC	RW	RWC	RW			
HW Access	R	RW1S	R	RW1S	RW			
Name	STALL	ERR_IN_TXN	NAK_INT_EN	ACKED_TXN	MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	STALL	When this bit is set the SIE stalls an OUT packet if the Mode bits are set to ACK-OUT. The SIE stalls an IN packet if the mode bits are set to ACK-IN. This bit must be clear for all other modes. Default Value: 0
6	ERR_IN_TXN	The Error in transaction bit is set whenever an error is detected. For an IN transaction, this indicates a no response from HOST scenario. For an OUT transaction, this represents an RxErr (PID error/ CRC error/ bit-stuff error scenario). This bit is cleared by any writes to the register. Default Value: 0
5	NAK_INT_EN	When set this bit causes an endpoint interrupt to be generated even when a transfer completes with a NAK. Default Value: 0
4	ACKED_TXN	The ACK'd transaction bit is set whenever the SIE engages in a transaction to the register's endpoint that completes with an ACK packet. This bit is cleared by any writes to the register. Default Value: 0 **0x0: ACKED_NO:** No ACK'd transactions since bit was last cleared. **0x1: ACKED_YES:** Indicates a transaction ended with an ACK.

24.1.46 USBDEVv2_SIE_EP8_CR0 (continued)

3 : 0	MODE	The mode controls how the USB SIE responds to traffic and how the USB SIE changes the mode of that endpoint as a result of host packets to the endpoint. Default Value: 0 **0x0: DISABLE:** Ignore all USB traffic to this endpoint **0x1: NAK_INOUT:** SETUP: Accept IN: NAK OUT: NAK **0x2: STATUS_OUT_ONLY:** SETUP: Accept IN: STALL OUT: ACK 0B tokens, NAK others **0x3: STALL_INOUT:** SETUP: Accept IN: STALL OUT: STALL **0x5: ISO_OUT:** SETUP: Ignore IN: Ignore OUT: Accept Isochronous OUT token **0x6: STATUS_IN_ONLY:** SETUP: Accept IN: Respond with 0B data OUT: Stall **0x7: ISO_IN:** SETUP: Ignore IN: Accept Isochronous IN token OUT: Ignore **0x8: NAK_OUT:** SETUP: Ignore IN: Ignore OUT: NAK **0x9: ACK_OUT:** SETUP: Ignore IN: Ignore OUT: Accept data and ACK if STALL=0, STALL otherwise. Change to MODE=8 after one succesfull OUT token. **0xb: ACK_OUT_STATUS_IN:** SETUP: Accept IN: Respond with 0B data OUT: Accept data **0xc: NAK_IN:** SETUP: Ignore IN: NAK OUT: Ignore **0xd: ACK_IN:** SETUP: Ignore IN: Respond to IN with data if STALL=0, STALL otherwise OUT: Ignore

24.1.46 USBDEVv2_SIE_EP8_CR0 (continued)

0xf: ACK_IN STATUS OUT:
SETUP: Accept
IN: Respond to IN with data
OUT: ACK 0B tokens, NAK others

24.1.47 USBDEVv2_ARB_EP1_CFG

Endpoint Configuration Register

Address: 0x402C0200

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.47 USBDEVv2_ARB_EP1_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.48 USBDEVv2_ARB_EP1_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C0204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.49 USBDEVv2_ARB_EP1_SR

Endpoint Interrupt Enable Register

Address: 0x402C0208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.50 USBDEVv2_ARB_RW1_WA

Endpoint Write Address value

Address: 0x402C0210

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.51 USBDEVv2_ARB_RW1_WA_MSB

Endpoint Write Address value

Address: 0x402C0214

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.52 USBDEVv2_ARB_RW1_RA

Endpoint Read Address value

Address: 0x402C0218

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.53 USBDEVv2_ARB_RW1_RA_MSB

Endpoint Read Address value

Address: 0x402C021C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.54 USBDEVv2_ARB_RW1_DR

Endpoint Data Register

Address: 0x402C0220

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.55 USBDEVv2_BUF_SIZE

Dedicated Endpoint Buffer Size Register

Address: 0x402C0230

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	OUT_BUF [7:4]				IN_BUF [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	OUT_BUF	Buffer size for OUT Endpoints. Default Value: 0
3 : 0	IN_BUF	Buffer size for IN Endpoints. Default Value: 0

24.1.56 USBDEVv2_EP_ACTIVE

Endpoint Active Indication Register

Address: 0x402C0238

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	EP8_ACT	EP7_ACT	EP6_ACT	EP5_ACT	EP4_ACT	EP3_ACT	EP2_ACT	EP1_ACT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_ACT	Indicates that Endpoint is currently active. Default Value: 0
6	EP7_ACT	Indicates that Endpoint is currently active. Default Value: 0
5	EP6_ACT	Indicates that Endpoint is currently active. Default Value: 0
4	EP5_ACT	Indicates that Endpoint is currently active. Default Value: 0
3	EP4_ACT	Indicates that Endpoint is currently active. Default Value: 0
2	EP3_ACT	Indicates that Endpoint is currently active. Default Value: 0
1	EP2_ACT	Indicates that Endpoint is currently active. Default Value: 0
0	EP1_ACT	Indicates that Endpoint is currently active. Default Value: 0

24.1.57 USBDEVv2_EP_TYPE

Endpoint Type (IN/OUT) Indication

Address: 0x402C023C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	EP8_TYP	EP7_TYP	EP6_TYP	EP5_TYP	EP4_TYP	EP3_TYP	EP2_TYP	EP1_TYP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint **0x1: EP_OUT:** OUT outpoint
6	EP7_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint **0x1: EP_OUT:** OUT outpoint
5	EP6_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint

24.1.57 USBDEVv2_EP_TYPE (continued)

		0x1: EP_OUT: OUT outpoint
4	EP5_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint **0x1: EP_OUT:** OUT outpoint
3	EP4_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint **0x1: EP_OUT:** OUT outpoint
2	EP3_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint **0x1: EP_OUT:** OUT outpoint
1	EP2_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint **0x1: EP_OUT:** OUT outpoint
0	EP1_TYP	Endpoint Type Indication. Default Value: 0 **0x0: EP_IN:** IN outpoint **0x1: EP_OUT:** OUT outpoint

24.1.58 USBDEVv2_ARB_EP2_CFG

Endpoint Configuration Register

Address: 0x402C0240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.58 USBDEVv2_ARB_EP2_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.59 USBDEVv2_ARB_EP2_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C0244

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.60 USBDEVv2_ARB_EP2_SR

Endpoint Interrupt Enable Register

Address: 0x402C0248

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.61 USBDEVv2_ARB_RW2_WA

Endpoint Write Address value

Address: 0x402C0250

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.62 USBDEVv2_ARB_RW2_WA_MSB

Endpoint Write Address value

Address: 0x402C0254

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.63 USBDEVv2_ARB_RW2_RA

Endpoint Read Address value

Address: 0x402C0258

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.64 USBDEVv2_ARB_RW2_RA_MSB

Endpoint Read Address value

Address: 0x402C025C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.65 USBDEVv2_ARB_RW2_DR

Endpoint Data Register

Address: 0x402C0260

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.66 USBDEVv2_ARB_CFG

Arbiter Configuration Register

Address: 0x402C0270

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW		RW	None			
HW Access	R	R		R	None			
Name	CFG_CMP	DMA_CFG [6:5]		AUTO_MEM	None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	CFG_CMP	Register Configuration Complete Indication. Posedge is detected on this bit. Hence a 0 to 1 transition is required. Default Value: 0
6 : 5	DMA_CFG	DMA Access Configuration. Default Value: 0 **0x0: DMA_NONE:** No DMA **0x1: DMA_MANUAL:** Manual DMA **0x2: DMA_AUTO:** Auto DMA
4	AUTO_MEM	Enables Auto Memory Configuration. Manual memory configuration by default. Default Value: 0

24.1.67 USBDEVv2_USB_CLK_EN

USB Block Clock Enable Register

Address: 0x402C0274

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							CSR_CLK_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	CSR_CLK_EN	Clock Enable for Core Logic clocked by AHB bus clock Default Value: 0

24.1.68 USBDEVv2_ARB_INT_EN

Arbiter Interrupt Enable

Address: 0x402C0278

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	EP8_INTR_EN	EP7_INTR_EN	EP6_INTR_EN	EP5_INTR_EN	EP4_INTR_EN	EP3_INTR_EN	EP2_INTR_EN	EP1_INTR_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_INTR_EN	Enables interrupt for EP8 Default Value: 0
6	EP7_INTR_EN	Enables interrupt for EP7 Default Value: 0
5	EP6_INTR_EN	Enables interrupt for EP6 Default Value: 0
4	EP5_INTR_EN	Enables interrupt for EP5 Default Value: 0
3	EP4_INTR_EN	Enables interrupt for EP4 Default Value: 0
2	EP3_INTR_EN	Enables interrupt for EP3 Default Value: 0
1	EP2_INTR_EN	Enables interrupt for EP2 Default Value: 0

24.1.68 USBDEVv2_ARB_INT_EN (continued)

0	EP1_INTR_EN	Enables interrupt for EP1 Default Value: 0

24.1.69 USBDEVv2_ARB_INT_SR

Arbiter Interrupt Status

Address: 0x402C027C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_INTR	Interrupt status for EP8 Default Value: 0
6	EP7_INTR	Interrupt status for EP7 Default Value: 0
5	EP6_INTR	Interrupt status for EP6 Default Value: 0
4	EP5_INTR	Interrupt status for EP5 Default Value: 0
3	EP4_INTR	Interrupt status for EP4 Default Value: 0
2	EP3_INTR	Interrupt status for EP3 Default Value: 0
1	EP2_INTR	Interrupt status for EP2 Default Value: 0
0	EP1_INTR	Interrupt status for EP1 Default Value: 0

24.1.70 USBDEVv2_ARB_EP3_CFG

Endpoint Configuration Register

Address: 0x402C0280

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.70 USBDEVv2_ARB_EP3_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.71 USBDEVv2_ARB_EP3_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C0284

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.72 USBDEVv2_ARB_EP3_SR

Endpoint Interrupt Enable Register

Address: 0x402C0288

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.73 USBDEVv2_ARB_RW3_WA

Endpoint Write Address value

Address: 0x402C0290

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.74 USBDEVv2_ARB_RW3_WA_MSB

Endpoint Write Address value

Address: 0x402C0294

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.75 USBDEVv2_ARB_RW3_RA

Endpoint Read Address value

Address: 0x402C0298

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.76 USBDEVv2_ARB_RW3_RA_MSB

Endpoint Read Address value

Address: 0x402C029C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.77 USBDEVv2_ARB_RW3_DR

Endpoint Data Register

Address: 0x402C02A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.78 USBDEVv2_CWA

Common Area Write Address

Address: 0x402C02B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CWA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	CWA	Write Address for Common Area Default Value: 0

24.1.79 USBDEVv2_CWA_MSB

Endpoint Read Address value

Address: 0x402C02B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							CWA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	CWA_MSB	Write Address for Common Area Default Value: 0

24.1.80 USBDEVv2_ARB_EP4_CFG

Endpoint Configuration Register

Address: 0x402C02C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.80 USBDEVv2_ARB_EP4_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.81 USBDEVv2_ARB_EP4_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C02C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.82 USBDEVv2_ARB_EP4_SR

Endpoint Interrupt Enable Register

Address: 0x402C02C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.83 USBDEVv2_ARB_RW4_WA

Endpoint Write Address value

Address: 0x402C02D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.84 USBDEVv2_ARB_RW4_WA_MSB

Endpoint Write Address value

Address: 0x402C02D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.85 USBDEVv2_ARB_RW4_RA

Endpoint Read Address value

Address: 0x402C02D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.86 USBDEVv2_ARB_RW4_RA_MSB

Endpoint Read Address value

Address: 0x402C02DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.87 USBDEVv2_ARB_RW4_DR

Endpoint Data Register

Address: 0x402C02E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.88 USBDEVv2_DMA_THRES

DMA Burst / Threshold Configuration

Address: 0x402C02F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DMA_THS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DMA_THS	DMA Threshold count Default Value: 0

24.1.89 USBDEVv2_DMA_THRES_MSB

DMA Burst / Threshold Configuration

Address: 0x402C02F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							DMA_THS_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	DMA_THS_MSB	DMA Threshold count Default Value: 0

24.1.90 USBDEVv2_ARB_EP5_CFG

Endpoint Configuration Register

Address: 0x402C0300

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.90 USBDEVv2_ARB_EP5_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.91 USBDEVv2_ARB_EP5_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C0304

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.92 USBDEVv2_ARB_EP5_SR

Endpoint Interrupt Enable Register

Address: 0x402C0308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.93 USBDEVv2_ARB_RW5_WA

Endpoint Write Address value

Address: 0x402C0310

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.94 USBDEVv2_ARB_RW5_WA_MSB

Endpoint Write Address value

Address: 0x402C0314

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.95 USBDEVv2_ARB_RW5_RA

Endpoint Read Address value

Address: 0x402C0318

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.96 USBDEVv2_ARB_RW5_RA_MSB

Endpoint Read Address value

Address: 0x402C031C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.97 USBDEVv2_ARB_RW5_DR

Endpoint Data Register

Address: 0x402C0320

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.98 USBDEVv2_BUS_RST_CNT

Bus Reset Count Register

Address: 0x402C0330

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				bus_rst_cnt [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	bus_rst_cnt	Bus Reset Count Length Default Value: 10

24.1.99 USBDEVv2_ARB_EP6_CFG

Endpoint Configuration Register

Address: 0x402C0340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.99 USBDEVv2_ARB_EP6_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.100 USBDEVv2_ARB_EP6_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C0344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.101 USBDEVv2_ARB_EP6_SR

Endpoint Interrupt Enable Register

Address: 0x402C0348

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.102 USBDEVv2_ARB_RW6_WA

Endpoint Write Address value

Address: 0x402C0350

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.103 USBDEVv2_ARB_RW6_WA_MSB

Endpoint Write Address value

Address: 0x402C0354

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.104 USBDEVv2_ARB_RW6_RA

Endpoint Read Address value

Address: 0x402C0358

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.105 USBDEVv2_ARB_RW6_RA_MSB

Endpoint Read Address value

Address: 0x402C035C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.106 USBDEVv2_ARB_RW6_DR

Endpoint Data Register

Address: 0x402C0360

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.107 USBDEVv2_ARB_EP7_CFG

Endpoint Configuration Register

Address: 0x402C0380

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.107 USBDEVv2_ARB_EP7_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.108 USBDEVv2_ARB_EP7_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C0384

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.109 USBDEVv2_ARB_EP7_SR

Endpoint Interrupt Enable Register

Address: 0x402C0388

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.110 USBDEVv2_ARB_RW7_WA

Endpoint Write Address value

Address: 0x402C0390

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.111 USBDEVv2_ARB_RW7_WA_MSB

Endpoint Write Address value

Address: 0x402C0394

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.112 USBDEVv2_ARB_RW7_RA

Endpoint Read Address value

Address: 0x402C0398

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.113 USBDEVv2_ARB_RW7_RA_MSB

Endpoint Read Address value

Address: 0x402C039C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.114 USBDEVv2_ARB_RW7_DR

Endpoint Data Register

Address: 0x402C03A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.115 USBDEVv2_ARB_EP8_CFG

Endpoint Configuration Register

Address: 0x402C03C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				RESET_PTR	CRC_BYPASS	DMA_REQ	IN_DATA_RDY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	RESET_PTR	Configuration Setting to Reset the RA and WA Pointers to their start values at the End of Packet transaction. Default Value: 0 **0x0: RESET_KRYPTON:** Do not Reset Pointer; Krypton Backward compatibility mode **0x1: RESET_NORMAL:** Reset Pointer; recommended value for reduction of CPU Configuration Writes.
2	CRC_BYPASS	Configuration Setting to prevent CRC bytes from being written to memory and being read by firmware Default Value: 0 **0x0: CRC_NORMAL:** No CRC bypass; CRC bytes will be written to memory and Termin will be generated for the CRC byte/s **0x1: CRC_BYPASS:** CRC Bypass Set; CRC bytes will not be written into memory and Termin will be generated for the last data byte/s

24.1.115 USBDEVv2_ARB_EP8_CFG (continued)

1	DMA_REQ	Manual DMA Request for a particular (1 to 8) endpoint; changing this field from 0 to 1 causes a DMA request to be generated. Default Value: 0
0	IN_DATA_RDY	Indication that Endpoint Packet Data is Ready in Main memory Default Value: 0

24.1.116 USBDEVv2_ARB_EP8_INT_EN

Endpoint Interrupt Enable Register

Address: 0x402C03C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		DMA_TERMIN_EN	ERR_INT_EN	BUF_UNDER_EN	BUF_OVER_EN	DMA_GNT_EN	IN_BUF_FULL_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN_EN	Endpoint DMA Terminated Enable Default Value: 0
4	ERR_INT_EN	Endpoint Error in Transaction Interrupt Enable Default Value: 0
3	BUF_UNDER_EN	Endpoint Buffer Underflow Enable Default Value: 0
2	BUF_OVER_EN	Endpoint Buffer Overflow Enable Default Value: 0
1	DMA_GNT_EN	Endpoint DMA Grant Enable Default Value: 0
0	IN_BUF_FULL_EN	IN Endpoint Local Buffer Full Enable Default Value: 0

24.1.117 USBDEVv2_ARB_EP8_SR

Endpoint Interrupt Enable Register

Address: 0x402C03C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW1C	None	RW1C	RW1C	RW1C	RW1C
HW Access	None		RW1S	None	RW1S	RW1S	RW1S	RW1S
Name	None [7:6]		DMA_TERMIN	None	BUF_UNDER	BUF_OVER	DMA_GNT	IN_BUF_FULL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	DMA_TERMIN	Endpoint DMA Terminated Interrupt Default Value: 0
3	BUF_UNDER	Endpoint Buffer Underflow Interrupt Default Value: 0
2	BUF_OVER	Endpoint Buffer Overflow Interrupt Default Value: 0
1	DMA_GNT	Endpoint DMA Grant Interrupt Default Value: 0
0	IN_BUF_FULL	IN Endpoint Local Buffer Full Interrupt Default Value: 0

24.1.118 USBDEVv2_ARB_RW8_WA

Endpoint Write Address value

Address: 0x402C03D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	WA	Write Address for EP Default Value: 0

24.1.119 USBDEVv2_ARB_RW8_WA_MSB

Endpoint Write Address value

Address: 0x402C03D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							WA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	WA_MSB	Write Address for EP Default Value: 0

24.1.120 USBDEVv2_ARB_RW8_RA

Endpoint Read Address value

Address: 0x402C03D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	RA	Read Address for EP Default Value: 0

24.1.121 USBDEVv2_ARB_RW8_RA_MSB

Endpoint Read Address value

Address: 0x402C03DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							RW
Name	None [7:1]							RA_MSB

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	RA_MSB	Read Address for EP Default Value: 0

24.1.122 USBDEVv2_ARB_RW8_DR

Endpoint Data Register

Address: 0x402C03E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.123 USBDEVv2_MEM_DATA0

DATA

Address: 0x402C0400

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.124 USBDEVv2_MEM_DATA1

DATA

Address: 0x402C0404

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.125 USBDEVv2_MEM_DATA2

DATA

Address: 0x402C0408

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.126 USBDEVv2_MEM_DATA3

DATA

Address: 0x402C040C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.127 USBDEVv2_MEM_DATA4

DATA

Address: 0x402C0410

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.128 USBDEVv2_MEM_DATA5

DATA

Address: 0x402C0414

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.129 USBDEVv2_MEM_DATA6

DATA

Address: 0x402C0418

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.130 USBDEVv2_MEM_DATA7

DATA

Address: 0x402C041C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.131 USBDEVv2_MEM_DATA8

DATA

Address: 0x402C0420

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.132 USBDEVv2_MEM_DATA9

DATA

Address: 0x402C0424

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.133 USBDEVv2_MEM_DATA10

DATA

Address: 0x402C0428

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.134 USBDEVv2_MEM_DATA11

DATA

Address: 0x402C042C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.135 USBDEVv2_MEM_DATA12

DATA

Address: 0x402C0430

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.136 USBDEVv2_MEM_DATA13

DATA

Address: 0x402C0434

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.137 USBDEVv2_MEM_DATA14

DATA

Address: 0x402C0438

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.138 USBDEVv2_MEM_DATA15

DATA

Address: 0x402C043C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.139 USBDEVv2_MEM_DATA16

DATA

Address: 0x402C0440

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.140 USBDEVv2_MEM_DATA17

DATA

Address: 0x402C0444

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.141 USBDEVv2_MEM_DATA18

DATA

Address: 0x402C0448

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.142 USBDEVv2_MEM_DATA19

DATA

Address: 0x402C044C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.143 USBDEVv2_MEM_DATA20

DATA

Address: 0x402C0450

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.144 USBDEVv2_MEM_DATA21

DATA

Address: 0x402C0454

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.145 USBDEVv2_MEM_DATA22

DATA

Address: 0x402C0458

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.146 USBDEVv2_MEM_DATA23

DATA

Address: 0x402C045C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.147 USBDEVv2_MEM_DATA24

DATA

Address: 0x402C0460

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.148 USBDEVv2_MEM_DATA25

DATA

Address: 0x402C0464

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.149 USBDEVv2_MEM_DATA26

DATA

Address: 0x402C0468

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.150 USBDEVv2_MEM_DATA27

DATA

Address: 0x402C046C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.151 USBDEVv2_MEM_DATA28

DATA

Address: 0x402C0470

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.152 USBDEVv2_MEM_DATA29

DATA

Address: 0x402C0474

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.153 USBDEVv2_MEM_DATA30

DATA

Address: 0x402C0478

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.154 USBDEVv2_MEM_DATA31

DATA

Address: 0x402C047C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.155 USBDEVv2_MEM_DATA32

DATA

Address: 0x402C0480

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.156 USBDEVv2_MEM_DATA33

DATA

Address: 0x402C0484

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.157 USBDEVv2_MEM_DATA34

DATA

Address: 0x402C0488

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.158 USBDEVv2_MEM_DATA35

DATA

Address: 0x402C048C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.159 USBDEVv2_MEM_DATA36

DATA

Address: 0x402C0490

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.160 USBDEVv2_MEM_DATA37

DATA

Address: 0x402C0494

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.161 USBDEVv2_MEM_DATA38

DATA

Address: 0x402C0498

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.162 USBDEVv2_MEM_DATA39

DATA

Address: 0x402C049C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.163 USBDEVv2_MEM_DATA40

DATA

Address: 0x402C04A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.164 USBDEVv2_MEM_DATA41

DATA

Address: 0x402C04A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.165 USBDEVv2_MEM_DATA42

DATA

Address: 0x402C04A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.166 USBDEVv2_MEM_DATA43

DATA

Address: 0x402C04AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.167 USBDEVv2_MEM_DATA44

DATA

Address: 0x402C04B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.168 USBDEVv2_MEM_DATA45

DATA

Address: 0x402C04B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.169 USBDEVv2_MEM_DATA46

DATA

Address: 0x402C04B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.170 USBDEVv2_MEM_DATA47

DATA

Address: 0x402C04BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.171 USBDEVv2_MEM_DATA48

DATA

Address: 0x402C04C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.172 USBDEVv2_MEM_DATA49

DATA

Address: 0x402C04C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.173 USBDEVv2_MEM_DATA50

DATA

Address: 0x402C04C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.174 USBDEVv2_MEM_DATA51

DATA

Address: 0x402C04CC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.175 USBDEVv2_MEM_DATA52

DATA

Address: 0x402C04D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.176 USBDEVv2_MEM_DATA53

DATA

Address: 0x402C04D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.177 USBDEVv2_MEM_DATA54

DATA

Address: 0x402C04D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.178 USBDEVv2_MEM_DATA55

DATA

Address: 0x402C04DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.179 USBDEVv2_MEM_DATA56

DATA

Address: 0x402C04E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.180 USBDEVv2_MEM_DATA57

DATA

Address: 0x402C04E4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.181 USBDEVv2_MEM_DATA58

DATA

Address: 0x402C04E8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.182 USBDEVv2_MEM_DATA59

DATA

Address: 0x402C04EC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.183 USBDEVv2_MEM_DATA60

DATA

Address: 0x402C04F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.184 USBDEVv2_MEM_DATA61

DATA

Address: 0x402C04F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.185 USBDEVv2_MEM_DATA62

DATA

Address: 0x402C04F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.186 USBDEVv2_MEM_DATA63

DATA

Address: 0x402C04FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.187 USBDEVv2_MEM_DATA64

DATA

Address: 0x402C0500

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.188 USBDEVv2_MEM_DATA65

DATA

Address: 0x402C0504

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.189 USBDEVv2_MEM_DATA66

DATA

Address: 0x402C0508

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.190 USBDEVv2_MEM_DATA67

DATA

Address: 0x402C050C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.191 USBDEVv2_MEM_DATA68

DATA

Address: 0x402C0510

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.192 USBDEVv2_MEM_DATA69

DATA

Address: 0x402C0514

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.193 USBDEVv2_MEM_DATA70

DATA

Address: 0x402C0518

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.194 USBDEVv2_MEM_DATA71

DATA

Address: 0x402C051C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.195 USBDEVv2_MEM_DATA72

DATA

Address: 0x402C0520

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.196 USBDEVv2_MEM_DATA73

DATA

Address: 0x402C0524

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.197 USBDEVv2_MEM_DATA74

DATA

Address: 0x402C0528

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.198 USBDEVv2_MEM_DATA75

DATA

Address: 0x402C052C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.199 USBDEVv2_MEM_DATA76

DATA

Address: 0x402C0530

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.200 USBDEVv2_MEM_DATA77

DATA

Address: 0x402C0534

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.201 USBDEVv2_MEM_DATA78

DATA

Address: 0x402C0538

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.202 USBDEVv2_MEM_DATA79

DATA

Address: 0x402C053C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.203 USBDEVv2_MEM_DATA80

DATA

Address: 0x402C0540

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.204 USBDEVv2_MEM_DATA81

DATA

Address: 0x402C0544

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.205 USBDEVv2_MEM_DATA82

DATA

Address: 0x402C0548

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.206 USBDEVv2_MEM_DATA83

DATA

Address: 0x402C054C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.207 USBDEVv2_MEM_DATA84

DATA

Address: 0x402C0550

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.208 USBDEVv2_MEM_DATA85

DATA

Address: 0x402C0554

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.209 USBDEVv2_MEM_DATA86

DATA

Address: 0x402C0558

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.210 USBDEVv2_MEM_DATA87

DATA

Address: 0x402C055C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.211 USBDEVv2_MEM_DATA88

DATA

Address: 0x402C0560

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.212 USBDEVv2_MEM_DATA89

DATA

Address: 0x402C0564

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.213 USBDEVv2_MEM_DATA90

DATA

Address: 0x402C0568

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.214 USBDEVv2_MEM_DATA91

DATA

Address: 0x402C056C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.215 USBDEVv2_MEM_DATA92

DATA

Address: 0x402C0570

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.216 USBDEVv2_MEM_DATA93

DATA

Address: 0x402C0574

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.217 USBDEVv2_MEM_DATA94

DATA

Address: 0x402C0578

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.218 USBDEVv2_MEM_DATA95

DATA

Address: 0x402C057C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.219 USBDEVv2_MEM_DATA96

DATA

Address: 0x402C0580

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.220 USBDEVv2_MEM_DATA97

DATA

Address: 0x402C0584

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.221 USBDEVv2_MEM_DATA98

DATA

Address: 0x402C0588

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.222 USBDEVv2_MEM_DATA99

DATA

Address: 0x402C058C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.223 USBDEVv2_MEM_DATA100

DATA

Address: 0x402C0590

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.224 USBDEVv2_MEM_DATA101

DATA

Address: 0x402C0594

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.225 USBDEVv2_MEM_DATA102

DATA

Address: 0x402C0598

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.226 USBDEVv2_MEM_DATA103

DATA

Address: 0x402C059C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.227 USBDEVv2_MEM_DATA104

DATA

Address: 0x402C05A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.228 USBDEVv2_MEM_DATA105

DATA

Address: 0x402C05A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.229 USBDEVv2_MEM_DATA106

DATA

Address: 0x402C05A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.230 USBDEVv2_MEM_DATA107

DATA

Address: 0x402C05AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.231 USBDEVv2_MEM_DATA108

DATA

Address: 0x402C05B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.232 USBDEVv2_MEM_DATA109

DATA

Address: 0x402C05B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.233 USBDEVv2_MEM_DATA110

DATA

Address: 0x402C05B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.234 USBDEVv2_MEM_DATA111

DATA

Address: 0x402C05BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.235 USBDEVv2_MEM_DATA112

DATA

Address: 0x402C05C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.236 USBDEVv2_MEM_DATA113

DATA

Address: 0x402C05C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.237 USBDEVv2_MEM_DATA114

DATA

Address: 0x402C05C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.238 USBDEVv2_MEM_DATA115

DATA

Address: 0x402C05CC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.239 USBDEVv2_MEM_DATA116

DATA

Address: 0x402C05D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.240 USBDEVv2_MEM_DATA117

DATA

Address: 0x402C05D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.241 USBDEVv2_MEM_DATA118

DATA

Address: 0x402C05D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.242 USBDEVv2_MEM_DATA119

DATA

Address: 0x402C05DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.243 USBDEVv2_MEM_DATA120

DATA

Address: 0x402C05E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.244 USBDEVv2_MEM_DATA121

DATA

Address: 0x402C05E4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.245 USBDEVv2_MEM_DATA122

DATA

Address: 0x402C05E8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.246 USBDEVv2_MEM_DATA123

DATA

Address: 0x402C05EC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.247 USBDEVv2_MEM_DATA124

DATA

Address: 0x402C05F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.248 USBDEVv2_MEM_DATA125

DATA

Address: 0x402C05F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.249 USBDEVv2_MEM_DATA126

DATA

Address: 0x402C05F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.250 USBDEVv2_MEM_DATA127

DATA

Address: 0x402C05FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.251 USBDEVv2_MEM_DATA128

DATA

Address: 0x402C0600

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.252 USBDEVv2_MEM_DATA129

DATA

Address: 0x402C0604

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.253 USBDEVv2_MEM_DATA130

DATA

Address: 0x402C0608

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.254 USBDEVv2_MEM_DATA131

DATA

Address: 0x402C060C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.255 USBDEVv2_MEM_DATA132

DATA

Address: 0x402C0610

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.256 USBDEVv2_MEM_DATA133

DATA

Address: 0x402C0614

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.257 USBDEVv2_MEM_DATA134

DATA

Address: 0x402C0618

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.258 USBDEVv2_MEM_DATA135

DATA

Address: 0x402C061C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.259 USBDEVv2_MEM_DATA136

DATA

Address: 0x402C0620

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.260 USBDEVv2_MEM_DATA137

DATA

Address: 0x402C0624

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.261 USBDEVv2_MEM_DATA138

DATA

Address: 0x402C0628

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.262 USBDEVv2_MEM_DATA139

DATA

Address: 0x402C062C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.263 USBDEVv2_MEM_DATA140

DATA

Address: 0x402C0630

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.264 USBDEVv2_MEM_DATA141

DATA

Address: 0x402C0634

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.265 USBDEVv2_MEM_DATA142

DATA

Address: 0x402C0638

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.266 USBDEVv2_MEM_DATA143

DATA

Address: 0x402C063C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.267 USBDEVv2_MEM_DATA144

DATA

Address: 0x402C0640

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.268 USBDEVv2_MEM_DATA145

DATA

Address: 0x402C0644

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.269 USBDEVv2_MEM_DATA146

DATA

Address: 0x402C0648

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.270 USBDEVv2_MEM_DATA147

DATA

Address: 0x402C064C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.271 USBDEVv2_MEM_DATA148

DATA

Address: 0x402C0650

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.272 USBDEVv2_MEM_DATA149

DATA

Address: 0x402C0654

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.273 USBDEVv2_MEM_DATA150

DATA

Address: 0x402C0658

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.274 USBDEVv2_MEM_DATA151

DATA

Address: 0x402C065C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.275 USBDEVv2_MEM_DATA152

DATA

Address: 0x402C0660

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.276 USBDEVv2_MEM_DATA153

DATA

Address: 0x402C0664

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.277 USBDEVv2_MEM_DATA154

DATA

Address: 0x402C0668

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.278 USBDEVv2_MEM_DATA155

DATA

Address: 0x402C066C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.279 USBDEVv2_MEM_DATA156

DATA

Address: 0x402C0670

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.280 USBDEVv2_MEM_DATA157

DATA

Address: 0x402C0674

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.281 USBDEVv2_MEM_DATA158

DATA

Address: 0x402C0678

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.282 USBDEVv2_MEM_DATA159

DATA

Address: 0x402C067C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.283 USBDEVv2_MEM_DATA160

DATA

Address: 0x402C0680

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.284 USBDEVv2_MEM_DATA161

DATA

Address: 0x402C0684

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.285 USBDEVv2_MEM_DATA162

DATA

Address: 0x402C0688

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.286 USBDEVv2_MEM_DATA163

DATA

Address: 0x402C068C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.287 USBDEVv2_MEM_DATA164

DATA

Address: 0x402C0690

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.288 USBDEVv2_MEM_DATA165

DATA

Address: 0x402C0694

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.289 USBDEVv2_MEM_DATA166

DATA

Address: 0x402C0698

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.290 USBDEVv2_MEM_DATA167

DATA

Address: 0x402C069C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.291 USBDEVv2_MEM_DATA168

DATA

Address: 0x402C06A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.292 USBDEVv2_MEM_DATA169

DATA

Address: 0x402C06A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.293 USBDEVv2_MEM_DATA170

DATA

Address: 0x402C06A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.294 USBDEVv2_MEM_DATA171

DATA

Address: 0x402C06AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.295 USBDEVv2_MEM_DATA172

DATA

Address: 0x402C06B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.296 USBDEVv2_MEM_DATA173

DATA

Address: 0x402C06B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.297 USBDEVv2_MEM_DATA174

DATA

Address: 0x402C06B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.298 USBDEVv2_MEM_DATA175

DATA

Address: 0x402C06BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.299 USBDEVv2_MEM_DATA176

DATA

Address: 0x402C06C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.300 USBDEVv2_MEM_DATA177

DATA

Address: 0x402C06C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.301 USBDEVv2_MEM_DATA178

DATA

Address: 0x402C06C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.302 USBDEVv2_MEM_DATA179

DATA

Address: 0x402C06CC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.303 USBDEVv2_MEM_DATA180

DATA

Address: 0x402C06D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.304 USBDEVv2_MEM_DATA181

DATA

Address: 0x402C06D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.305 USBDEVv2_MEM_DATA182

DATA

Address: 0x402C06D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.306 USBDEVv2_MEM_DATA183

DATA

Address: 0x402C06DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.307 USBDEVv2_MEM_DATA184

DATA

Address: 0x402C06E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.308 USBDEVv2_MEM_DATA185

DATA

Address: 0x402C06E4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.309 USBDEVv2_MEM_DATA186

DATA

Address: 0x402C06E8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.310 USBDEVv2_MEM_DATA187

DATA

Address: 0x402C06EC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.311 USBDEVv2_MEM_DATA188

DATA

Address: 0x402C06F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.312 USBDEVv2_MEM_DATA189

DATA

Address: 0x402C06F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.313 USBDEVv2_MEM_DATA190

DATA

Address: 0x402C06F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.314 USBDEVv2_MEM_DATA191

DATA

Address: 0x402C06FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.315 USBDEVv2_MEM_DATA192

DATA

Address: 0x402C0700

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.316 USBDEVv2_MEM_DATA193

DATA

Address: 0x402C0704

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.317 USBDEVv2_MEM_DATA194

DATA

Address: 0x402C0708

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.318 USBDEVv2_MEM_DATA195

DATA

Address: 0x402C070C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.319 USBDEVv2_MEM_DATA196

DATA

Address: 0x402C0710

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.320 USBDEVv2_MEM_DATA197

DATA

Address: 0x402C0714

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.321 USBDEVv2_MEM_DATA198

DATA

Address: 0x402C0718

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.322 USBDEVv2_MEM_DATA199

DATA

Address: 0x402C071C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.323 USBDEVv2_MEM_DATA200

DATA

Address: 0x402C0720

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.324 USBDEVv2_MEM_DATA201

DATA

Address: 0x402C0724

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.325 USBDEVv2_MEM_DATA202

DATA

Address: 0x402C0728

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.326 USBDEVv2_MEM_DATA203

DATA

Address: 0x402C072C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.327 USBDEVv2_MEM_DATA204

DATA

Address: 0x402C0730

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.328 USBDEVv2_MEM_DATA205

DATA

Address: 0x402C0734

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.329 USBDEVv2_MEM_DATA206

DATA

Address: 0x402C0738

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.330 USBDEVv2_MEM_DATA207

DATA

Address: 0x402C073C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.331 USBDEVv2_MEM_DATA208

DATA

Address: 0x402C0740

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.332 USBDEVv2_MEM_DATA209

DATA

Address: 0x402C0744

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.333 USBDEVv2_MEM_DATA210

DATA

Address: 0x402C0748

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.334 USBDEVv2_MEM_DATA211

DATA

Address: 0x402C074C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.335 USBDEVv2_MEM_DATA212

DATA

Address: 0x402C0750

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.336 USBDEVv2_MEM_DATA213

DATA

Address: 0x402C0754

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.337 USBDEVv2_MEM_DATA214

DATA

Address: 0x402C0758

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.338 USBDEVv2_MEM_DATA215

DATA

Address: 0x402C075C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.339 USBDEVv2_MEM_DATA216

DATA

Address: 0x402C0760

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.340 USBDEVv2_MEM_DATA217

DATA

Address: 0x402C0764

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.341 USBDEVv2_MEM_DATA218

DATA

Address: 0x402C0768

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.342 USBDEVv2_MEM_DATA219

DATA

Address: 0x402C076C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.343 USBDEVv2_MEM_DATA220

DATA

Address: 0x402C0770

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.344 USBDEVv2_MEM_DATA221

DATA

Address: 0x402C0774

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.345 USBDEVv2_MEM_DATA222

DATA

Address: 0x402C0778

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.346 USBDEVv2_MEM_DATA223

DATA

Address: 0x402C077C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.347 USBDEVv2_MEM_DATA224

DATA

Address: 0x402C0780

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.348 USBDEVv2_MEM_DATA225

DATA

Address: 0x402C0784

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.349 USBDEVv2_MEM_DATA226

DATA

Address: 0x402C0788

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.350 USBDEVv2_MEM_DATA227

DATA

Address: 0x402C078C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.351 USBDEVv2_MEM_DATA228

DATA

Address: 0x402C0790

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.352 USBDEVv2_MEM_DATA229

DATA

Address: 0x402C0794

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.353 USBDEVv2_MEM_DATA230

DATA

Address: 0x402C0798

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.354 USBDEVv2_MEM_DATA231

DATA

Address: 0x402C079C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.355 USBDEVv2_MEM_DATA232

DATA

Address: 0x402C07A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.356 USBDEVv2_MEM_DATA233

DATA

Address: 0x402C07A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.357 USBDEVv2_MEM_DATA234

DATA

Address: 0x402C07A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.358 USBDEVv2_MEM_DATA235

DATA

Address: 0x402C07AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.359 USBDEVv2_MEM_DATA236

DATA

Address: 0x402C07B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.360 USBDEVv2_MEM_DATA237

DATA

Address: 0x402C07B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.361 USBDEVv2_MEM_DATA238

DATA

Address: 0x402C07B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.362 USBDEVv2_MEM_DATA239

DATA

Address: 0x402C07BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.363 USBDEVv2_MEM_DATA240

DATA

Address: 0x402C07C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.364 USBDEVv2_MEM_DATA241

DATA

Address: 0x402C07C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.365 USBDEVv2_MEM_DATA242

DATA

Address: 0x402C07C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.366 USBDEVv2_MEM_DATA243

DATA

Address: 0x402C07CC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.367 USBDEVv2_MEM_DATA244

DATA

Address: 0x402C07D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.368 USBDEVv2_MEM_DATA245

DATA

Address: 0x402C07D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.369 USBDEVv2_MEM_DATA246

DATA

Address: 0x402C07D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.370 USBDEVv2_MEM_DATA247

DATA

Address: 0x402C07DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.371 USBDEVv2_MEM_DATA248

DATA

Address: 0x402C07E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.372 USBDEVv2_MEM_DATA249

DATA

Address: 0x402C07E4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.373 USBDEVv2_MEM_DATA250

DATA

Address: 0x402C07E8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.374 USBDEVv2_MEM_DATA251

DATA

Address: 0x402C07EC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.375 USBDEVv2_MEM_DATA252

DATA

Address: 0x402C07F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.376 USBDEVv2_MEM_DATA253

DATA

Address: 0x402C07F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.377 USBDEVv2_MEM_DATA254

DATA

Address: 0x402C07F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.378 USBDEVv2_MEM_DATA255

DATA

Address: 0x402C07FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.379 USBDEVv2_MEM_DATA256

DATA

Address: 0x402C0800

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.380 USBDEVv2_MEM_DATA257

DATA

Address: 0x402C0804

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.381 USBDEVv2_MEM_DATA258

DATA

Address: 0x402C0808

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.382 USBDEVv2_MEM_DATA259

DATA

Address: 0x402C080C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.383 USBDEVv2_MEM_DATA260

DATA

Address: 0x402C0810

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.384 USBDEVv2_MEM_DATA261

DATA

Address: 0x402C0814

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.385 USBDEVv2_MEM_DATA262

DATA

Address: 0x402C0818

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.386 USBDEVv2_MEM_DATA263

DATA

Address: 0x402C081C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.387 USBDEVv2_MEM_DATA264

DATA

Address: 0x402C0820

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.388 USBDEVv2_MEM_DATA265

DATA

Address: 0x402C0824

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.389 USBDEVv2_MEM_DATA266

DATA

Address: 0x402C0828

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.390 USBDEVv2_MEM_DATA267

DATA

Address: 0x402C082C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.391 USBDEVv2_MEM_DATA268

DATA

Address: 0x402C0830

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.392 USBDEVv2_MEM_DATA269

DATA

Address: 0x402C0834

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.393 USBDEVv2_MEM_DATA270

DATA

Address: 0x402C0838

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.394 USBDEVv2_MEM_DATA271

DATA

Address: 0x402C083C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.395 USBDEVv2_MEM_DATA272

DATA

Address: 0x402C0840

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.396 USBDEVv2_MEM_DATA273

DATA

Address: 0x402C0844

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.397 USBDEVv2_MEM_DATA274

DATA

Address: 0x402C0848

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.398 USBDEVv2_MEM_DATA275

DATA

Address: 0x402C084C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.399 USBDEVv2_MEM_DATA276

DATA

Address: 0x402C0850

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.400 USBDEVv2_MEM_DATA277

DATA

Address: 0x402C0854

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.401 USBDEVv2_MEM_DATA278

DATA

Address: 0x402C0858

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.402 USBDEVv2_MEM_DATA279

DATA

Address: 0x402C085C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.403 USBDEVv2_MEM_DATA280

DATA

Address: 0x402C0860

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.404 USBDEVv2_MEM_DATA281

DATA

Address: 0x402C0864

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.405 USBDEVv2_MEM_DATA282

DATA

Address: 0x402C0868

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.406 USBDEVv2_MEM_DATA283

DATA

Address: 0x402C086C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.407 USBDEVv2_MEM_DATA284

DATA

Address: 0x402C0870

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.408 USBDEVv2_MEM_DATA285

DATA

Address: 0x402C0874

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.409 USBDEVv2_MEM_DATA286

DATA

Address: 0x402C0878

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.410 USBDEVv2_MEM_DATA287

DATA

Address: 0x402C087C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.411 USBDEVv2_MEM_DATA288

DATA

Address: 0x402C0880

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.412 USBDEVv2_MEM_DATA289

DATA

Address: 0x402C0884

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.413 USBDEVv2_MEM_DATA290

DATA

Address: 0x402C0888

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.414 USBDEVv2_MEM_DATA291

DATA

Address: 0x402C088C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.415 USBDEVv2_MEM_DATA292

DATA

Address: 0x402C0890

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.416 USBDEVv2_MEM_DATA293

DATA

Address: 0x402C0894

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.417 USBDEVv2_MEM_DATA294

DATA

Address: 0x402C0898

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.418 USBDEVv2_MEM_DATA295

DATA

Address: 0x402C089C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.419 USBDEVv2_MEM_DATA296

DATA

Address: 0x402C08A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.420 USBDEVv2_MEM_DATA297

DATA

Address: 0x402C08A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.421 USBDEVv2_MEM_DATA298

DATA

Address: 0x402C08A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.422 USBDEVv2_MEM_DATA299

DATA

Address: 0x402C08AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.423 USBDEVv2_MEM_DATA300

DATA

Address: 0x402C08B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.424 USBDEVv2_MEM_DATA301

DATA

Address: 0x402C08B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.425 USBDEVv2_MEM_DATA302

DATA

Address: 0x402C08B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.426 USBDEVv2_MEM_DATA303

DATA

Address: 0x402C08BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.427 USBDEVv2_MEM_DATA304

DATA

Address: 0x402C08C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.428 USBDEVv2_MEM_DATA305

DATA

Address: 0x402C08C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.429 USBDEVv2_MEM_DATA306

DATA

Address: 0x402C08C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.430 USBDEVv2_MEM_DATA307

DATA

Address: 0x402C08CC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.431 USBDEVv2_MEM_DATA308

DATA

Address: 0x402C08D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.432 USBDEVv2_MEM_DATA309

DATA

Address: 0x402C08D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.433 USBDEVv2_MEM_DATA310

DATA

Address: 0x402C08D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.434 USBDEVv2_MEM_DATA311

DATA

Address: 0x402C08DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.435 USBDEVv2_MEM_DATA312

DATA

Address: 0x402C08E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.436 USBDEVv2_MEM_DATA313

DATA

Address: 0x402C08E4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.437 USBDEVv2_MEM_DATA314

DATA

Address: 0x402C08E8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.438 USBDEVv2_MEM_DATA315

DATA

Address: 0x402C08EC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.439 USBDEVv2_MEM_DATA316

DATA

Address: 0x402C08F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.440 USBDEVv2_MEM_DATA317

DATA

Address: 0x402C08F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.441 USBDEVv2_MEM_DATA318

DATA

Address: 0x402C08F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.442 USBDEVv2_MEM_DATA319

DATA

Address: 0x402C08FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.443 USBDEVv2_MEM_DATA320

DATA

Address: 0x402C0900

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.444 USBDEVv2_MEM_DATA321

DATA

Address: 0x402C0904

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.445 USBDEVv2_MEM_DATA322

DATA

Address: 0x402C0908

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.446 USBDEVv2_MEM_DATA323

DATA

Address: 0x402C090C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.447 USBDEVv2_MEM_DATA324

DATA

Address: 0x402C0910

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.448 USBDEVv2_MEM_DATA325

DATA

Address: 0x402C0914

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.449 USBDEVv2_MEM_DATA326

DATA

Address: 0x402C0918

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.450 USBDEVv2_MEM_DATA327

DATA

Address: 0x402C091C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.451 USBDEVv2_MEM_DATA328

DATA

Address: 0x402C0920

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.452 USBDEVv2_MEM_DATA329

DATA

Address: 0x402C0924

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.453 USBDEVv2_MEM_DATA330

DATA

Address: 0x402C0928

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.454 USBDEVv2_MEM_DATA331

DATA

Address: 0x402C092C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.455 USBDEVv2_MEM_DATA332

DATA

Address: 0x402C0930

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.456 USBDEVv2_MEM_DATA333

DATA

Address: 0x402C0934

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.457 USBDEVv2_MEM_DATA334

DATA

Address: 0x402C0938

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.458 USBDEVv2_MEM_DATA335

DATA

Address: 0x402C093C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.459 USBDEVv2_MEM_DATA336

DATA

Address: 0x402C0940

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.460 USBDEVv2_MEM_DATA337

DATA

Address: 0x402C0944

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.461 USBDEVv2_MEM_DATA338

DATA

Address: 0x402C0948

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.462 USBDEVv2_MEM_DATA339

DATA

Address: 0x402C094C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.463 USBDEVv2_MEM_DATA340

DATA

Address: 0x402C0950

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.464 USBDEVv2_MEM_DATA341

DATA

Address: 0x402C0954

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.465 USBDEVv2_MEM_DATA342

DATA

Address: 0x402C0958

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.466 USBDEVv2_MEM_DATA343

DATA

Address: 0x402C095C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.467 USBDEVv2_MEM_DATA344

DATA

Address: 0x402C0960

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.468 USBDEVv2_MEM_DATA345

DATA

Address: 0x402C0964

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.469 USBDEVv2_MEM_DATA346

DATA

Address: 0x402C0968

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.470 USBDEVv2_MEM_DATA347

DATA

Address: 0x402C096C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.471 USBDEVv2_MEM_DATA348

DATA

Address: 0x402C0970

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.472 USBDEVv2_MEM_DATA349

DATA

Address: 0x402C0974

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.473 USBDEVv2_MEM_DATA350

DATA

Address: 0x402C0978

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.474 USBDEVv2_MEM_DATA351

DATA

Address: 0x402C097C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.475 USBDEVv2_MEM_DATA352

DATA

Address: 0x402C0980

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.476 USBDEVv2_MEM_DATA353

DATA

Address: 0x402C0984

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.477 USBDEVv2_MEM_DATA354

DATA

Address: 0x402C0988

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.478 USBDEVv2_MEM_DATA355

DATA

Address: 0x402C098C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.479 USBDEVv2_MEM_DATA356

DATA

Address: 0x402C0990

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.480 USBDEVv2_MEM_DATA357

DATA

Address: 0x402C0994

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.481 USBDEVv2_MEM_DATA358

DATA

Address: 0x402C0998

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.482 USBDEVv2_MEM_DATA359

DATA

Address: 0x402C099C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.483 USBDEVv2_MEM_DATA360

DATA

Address: 0x402C09A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.484 USBDEVv2_MEM_DATA361

DATA

Address: 0x402C09A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.485 USBDEVv2_MEM_DATA362

DATA

Address: 0x402C09A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.486 USBDEVv2_MEM_DATA363

DATA

Address: 0x402C09AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.487 USBDEVv2_MEM_DATA364

DATA

Address: 0x402C09B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.488 USBDEVv2_MEM_DATA365

DATA

Address: 0x402C09B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.489 USBDEVv2_MEM_DATA366

DATA

Address: 0x402C09B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.490 USBDEVv2_MEM_DATA367

DATA

Address: 0x402C09BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.491 USBDEVv2_MEM_DATA368

DATA

Address: 0x402C09C0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.492 USBDEVv2_MEM_DATA369

DATA

Address: 0x402C09C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.493 USBDEVv2_MEM_DATA370

DATA

Address: 0x402C09C8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.494 USBDEVv2_MEM_DATA371

DATA

Address: 0x402C09CC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.495 USBDEVv2_MEM_DATA372

DATA

Address: 0x402C09D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.496 USBDEVv2_MEM_DATA373

DATA

Address: 0x402C09D4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.497 USBDEVv2_MEM_DATA374

DATA

Address: 0x402C09D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.498 USBDEVv2_MEM_DATA375

DATA

Address: 0x402C09DC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.499 USBDEVv2_MEM_DATA376

DATA

Address: 0x402C09E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.500 USBDEVv2_MEM_DATA377

DATA

Address: 0x402C09E4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.501 USBDEVv2_MEM_DATA378

DATA

Address: 0x402C09E8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.502 USBDEVv2_MEM_DATA379

DATA

Address: 0x402C09EC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.503 USBDEVv2_MEM_DATA380

DATA

Address: 0x402C09F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.504 USBDEVv2_MEM_DATA381

DATA

Address: 0x402C09F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.505 USBDEVv2_MEM_DATA382

DATA

Address: 0x402C09F8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.506 USBDEVv2_MEM_DATA383

DATA

Address: 0x402C09FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.507 USBDEVv2_MEM_DATA384

DATA

Address: 0x402C0A00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.508 USBDEVv2_MEM_DATA385

DATA

Address: 0x402C0A04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.509 USBDEVv2_MEM_DATA386

DATA

Address: 0x402C0A08

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.510 USBDEVv2_MEM_DATA387

DATA

Address: 0x402C0A0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.511 USBDEVv2_MEM_DATA388

DATA

Address: 0x402C0A10

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.512 USBDEVv2_MEM_DATA389

DATA

Address: 0x402C0A14

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.513 USBDEVv2_MEM_DATA390

DATA

Address: 0x402C0A18

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.514 USBDEVv2_MEM_DATA391

DATA

Address: 0x402C0A1C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.515 USBDEVv2_MEM_DATA392

DATA

Address: 0x402C0A20

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.516 USBDEVv2_MEM_DATA393

DATA

Address: 0x402C0A24

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.517 USBDEVv2_MEM_DATA394

DATA

Address: 0x402C0A28

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.518 USBDEVv2_MEM_DATA395

DATA

Address: 0x402C0A2C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.519 USBDEVv2_MEM_DATA396

DATA

Address: 0x402C0A30

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.520 USBDEVv2_MEM_DATA397

DATA

Address: 0x402C0A34

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.521 USBDEVv2_MEM_DATA398

DATA

Address: 0x402C0A38

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.522 USBDEVv2_MEM_DATA399

DATA

Address: 0x402C0A3C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.523 USBDEVv2_MEM_DATA400

DATA

Address: 0x402C0A40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.524 USBDEVv2_MEM_DATA401

DATA

Address: 0x402C0A44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.525 USBDEVv2_MEM_DATA402

DATA

Address: 0x402C0A48

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.526 USBDEVv2_MEM_DATA403

DATA

Address: 0x402C0A4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.527 USBDEVv2_MEM_DATA404

DATA

Address: 0x402C0A50

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.528 USBDEVv2_MEM_DATA405

DATA

Address: 0x402C0A54

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.529 USBDEVv2_MEM_DATA406

DATA

Address: 0x402C0A58

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.530 USBDEVv2_MEM_DATA407

DATA

Address: 0x402C0A5C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.531 USBDEVv2_MEM_DATA408

DATA

Address: 0x402C0A60

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.532 USBDEVv2_MEM_DATA409

DATA

Address: 0x402C0A64

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.533 USBDEVv2_MEM_DATA410

DATA

Address: 0x402C0A68

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.534 USBDEVv2_MEM_DATA411

DATA

Address: 0x402C0A6C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.535 USBDEVv2_MEM_DATA412

DATA

Address: 0x402C0A70

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.536 USBDEVv2_MEM_DATA413

DATA

Address: 0x402C0A74

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.537 USBDEVv2_MEM_DATA414

DATA

Address: 0x402C0A78

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.538 USBDEVv2_MEM_DATA415

DATA

Address: 0x402C0A7C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.539 USBDEVv2_MEM_DATA416

DATA

Address: 0x402C0A80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.540 USBDEVv2_MEM_DATA417

DATA

Address: 0x402C0A84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.541 USBDEVv2_MEM_DATA418

DATA

Address: 0x402C0A88

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.542 USBDEVv2_MEM_DATA419

DATA

Address: 0x402C0A8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.543 USBDEVv2_MEM_DATA420

DATA

Address: 0x402C0A90

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.544 USBDEVv2_MEM_DATA421

DATA

Address: 0x402C0A94

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.545 USBDEVv2_MEM_DATA422

DATA

Address: 0x402C0A98

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.546 USBDEVv2_MEM_DATA423

DATA

Address: 0x402C0A9C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.547 USBDEVv2_MEM_DATA424

DATA

Address: 0x402C0AA0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.548 USBDEVv2_MEM_DATA425

DATA

Address: 0x402C0AA4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.549 USBDEVv2_MEM_DATA426

DATA

Address: 0x402C0AA8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.550 USBDEVv2_MEM_DATA427

DATA

Address: 0x402C0AAC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.551 USBDEVv2_MEM_DATA428

DATA

Address: 0x402C0AB0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.552 USBDEVv2_MEM_DATA429

DATA

Address: 0x402C0AB4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.553 USBDEVv2_MEM_DATA430

DATA

Address: 0x402C0AB8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.554 USBDEVv2_MEM_DATA431

DATA

Address: 0x402C0ABC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.555 USBDEVv2_MEM_DATA432

DATA

Address: 0x402C0AC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.556 USBDEVv2_MEM_DATA433

DATA

Address: 0x402C0AC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.557 USBDEVv2_MEM_DATA434

DATA

Address: 0x402C0AC8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.558 USBDEVv2_MEM_DATA435

DATA

Address: 0x402C0ACC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.559 USBDEVv2_MEM_DATA436

DATA

Address: 0x402C0AD0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.560 USBDEVv2_MEM_DATA437

DATA

Address: 0x402C0AD4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.561 USBDEVv2_MEM_DATA438

DATA

Address: 0x402C0AD8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.562 USBDEVv2_MEM_DATA439

DATA

Address: 0x402C0ADC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.563 USBDEVv2_MEM_DATA440

DATA

Address: 0x402C0AE0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.564 USBDEVv2_MEM_DATA441

DATA

Address: 0x402C0AE4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.565 USBDEVv2_MEM_DATA442

DATA

Address: 0x402C0AE8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.566 USBDEVv2_MEM_DATA443

DATA

Address: 0x402C0AEC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.567 USBDEVv2_MEM_DATA444

DATA

Address: 0x402C0AF0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.568 USBDEVv2_MEM_DATA445

DATA

Address: 0x402C0AF4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.569 USBDEVv2_MEM_DATA446

DATA

Address: 0x402C0AF8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.570 USBDEVv2_MEM_DATA447

DATA

Address: 0x402C0AFC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.571 USBDEVv2_MEM_DATA448

DATA

Address: 0x402C0B00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.572 USBDEVv2_MEM_DATA449

DATA

Address: 0x402C0B04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.573 USBDEVv2_MEM_DATA450

DATA

Address: 0x402C0B08

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.574 USBDEVv2_MEM_DATA451

DATA

Address: 0x402C0B0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.575 USBDEVv2_MEM_DATA452

DATA

Address: 0x402C0B10

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.576 USBDEVv2_MEM_DATA453

DATA

Address: 0x402C0B14

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.577 USBDEVv2_MEM_DATA454

DATA

Address: 0x402C0B18

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.578 USBDEVv2_MEM_DATA455

DATA

Address: 0x402C0B1C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.579 USBDEVv2_MEM_DATA456

DATA

Address: 0x402C0B20

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.580 USBDEVv2_MEM_DATA457

DATA

Address: 0x402C0B24

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.581 USBDEVv2_MEM_DATA458

DATA

Address: 0x402C0B28

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.582 USBDEVv2_MEM_DATA459

DATA

Address: 0x402C0B2C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.583 USBDEVv2_MEM_DATA460

DATA

Address: 0x402C0B30

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.584 USBDEVv2_MEM_DATA461

DATA

Address: 0x402C0B34

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.585 USBDEVv2_MEM_DATA462

DATA

Address: 0x402C0B38

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.586 USBDEVv2_MEM_DATA463

DATA

Address: 0x402C0B3C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.587 USBDEVv2_MEM_DATA464

DATA

Address: 0x402C0B40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.588 USBDEVv2_MEM_DATA465

DATA

Address: 0x402C0B44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.589 USBDEVv2_MEM_DATA466

DATA

Address: 0x402C0B48

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.590 USBDEVv2_MEM_DATA467

DATA

Address: 0x402C0B4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.591 USBDEVv2_MEM_DATA468

DATA

Address: 0x402C0B50

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.592 USBDEVv2_MEM_DATA469

DATA

Address: 0x402C0B54

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.593 USBDEVv2_MEM_DATA470

DATA

Address: 0x402C0B58

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.594 USBDEVv2_MEM_DATA471

DATA

Address: 0x402C0B5C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.595 USBDEVv2_MEM_DATA472

DATA

Address: 0x402C0B60

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.596 USBDEVv2_MEM_DATA473

DATA

Address: 0x402C0B64

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.597 USBDEVv2_MEM_DATA474

DATA

Address: 0x402C0B68

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.598 USBDEVv2_MEM_DATA475

DATA

Address: 0x402C0B6C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.599 USBDEVv2_MEM_DATA476

DATA

Address: 0x402C0B70

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.600 USBDEVv2_MEM_DATA477

DATA

Address: 0x402C0B74

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.601 USBDEVv2_MEM_DATA478

DATA

Address: 0x402C0B78

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.602 USBDEVv2_MEM_DATA479

DATA

Address: 0x402C0B7C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.603 USBDEVv2_MEM_DATA480

DATA

Address: 0x402C0B80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.604 USBDEVv2_MEM_DATA481

DATA

Address: 0x402C0B84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.605 USBDEVv2_MEM_DATA482

DATA

Address: 0x402C0B88

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.606 USBDEVv2_MEM_DATA483

DATA

Address: 0x402C0B8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.607 USBDEVv2_MEM_DATA484

DATA

Address: 0x402C0B90

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.608 USBDEVv2_MEM_DATA485

DATA

Address: 0x402C0B94

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.609 USBDEVv2_MEM_DATA486

DATA

Address: 0x402C0B98

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.610 USBDEVv2_MEM_DATA487

DATA

Address: 0x402C0B9C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.611 USBDEVv2_MEM_DATA488

DATA

Address: 0x402C0BA0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.612 USBDEVv2_MEM_DATA489

DATA

Address: 0x402C0BA4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.613 USBDEVv2_MEM_DATA490

DATA

Address: 0x402C0BA8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.614 USBDEVv2_MEM_DATA491

DATA

Address: 0x402C0BAC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.615 USBDEVv2_MEM_DATA492

DATA

Address: 0x402C0BB0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.616 USBDEVv2_MEM_DATA493

DATA

Address: 0x402C0BB4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.617 USBDEVv2_MEM_DATA494

DATA

Address: 0x402C0BB8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.618 USBDEVv2_MEM_DATA495

DATA

Address: 0x402C0BBC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.619 USBDEVv2_MEM_DATA496

DATA

Address: 0x402C0BC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.620 USBDEVv2_MEM_DATA497

DATA

Address: 0x402C0BC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.621 USBDEVv2_MEM_DATA498

DATA

Address: 0x402C0BC8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.622 USBDEVv2_MEM_DATA499

DATA

Address: 0x402C0BCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.623 USBDEVv2_MEM_DATA500

DATA

Address: 0x402C0BD0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.624 USBDEVv2_MEM_DATA501

DATA

Address: 0x402C0BD4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.625 USBDEVv2_MEM_DATA502

DATA

Address: 0x402C0BD8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.626 USBDEVv2_MEM_DATA503

DATA

Address: 0x402C0BDC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.627 USBDEVv2_MEM_DATA504

DATA

Address: 0x402C0BE0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.628 USBDEVv2_MEM_DATA505

DATA

Address: 0x402C0BE4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.629 USBDEVv2_MEM_DATA506

DATA

Address: 0x402C0BE8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.630 USBDEVv2_MEM_DATA507

DATA

Address: 0x402C0BEC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.631 USBDEVv2_MEM_DATA508

DATA

Address: 0x402C0BF0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.632 USBDEVv2_MEM_DATA509

DATA

Address: 0x402C0BF4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.633 USBDEVv2_MEM_DATA510

DATA

Address: 0x402C0BF8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.634 USBDEVv2_MEM_DATA511

DATA

Address: 0x402C0BFC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DR	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.635 USBDEVv2_SOF16

Start Of Frame Register

Address: 0x402C1060

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	FRAME_NUMBER16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None					R		
HW Access	None					RW		
Name	None [15:11]					FRAME_NUMBER16 [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10 : 0	FRAME_NUMBER16	The frame number (11b) Default Value: 0

24.1.636 USBDEVv2_OSCLK_DR16

Oscillator lock data register

Address: 0x402C1080

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	ADDER16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None	R						
HW Access	None	W						
Name	None	ADDER16 [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
14 : 0	ADDER16	These bits return the oscillator locking circuits adder output. Default Value: X

24.1.637 USBDEVv2_ARB_RW1_WA16

Endpoint Write Address value

Address: 0x402C1210

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.638 USBDEVv2_ARB_RW1_RA16

Endpoint Read Address value

Address: 0x402C1218

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.639 USBDEVv2_ARB_RW1_DR16

Endpoint Data Register

Address: 0x402C1220

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.640 USBDEVv2_ARB_RW2_WA16

Endpoint Write Address value

Address: 0x402C1250

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.641 USBDEVv2_ARB_RW2_RA16

Endpoint Read Address value

Address: 0x402C1258

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.642 USBDEVv2_ARB_RW2_DR16

Endpoint Data Register

Address: 0x402C1260

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.643 USBDEVv2_ARB_RW3_WA16

Endpoint Write Address value

Address: 0x402C1290

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.644 USBDEVv2_ARB_RW3_RA16

Endpoint Read Address value

Address: 0x402C1298

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.645 USBDEVv2_ARB_RW3_DR16

Endpoint Data Register

Address: 0x402C12A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.646 USBDEVv2_CWA16

Common Area Write Address

Address: 0x402C12B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CWA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							CWA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	CWA16	Write Address for Common Area Default Value: 0

24.1.647 USBDEVv2_ARB_RW4_WA16

Endpoint Write Address value

Address: 0x402C12D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.648 USBDEVv2_ARB_RW4_RA16

Endpoint Read Address value

Address: 0x402C12D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.649 USBDEVv2_ARB_RW4_DR16

Endpoint Data Register

Address: 0x402C12E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.650 USBDEVv2_DMA_THRES16

DMA Burst / Threshold Configuration

Address: 0x402C12F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DMA_THS16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							DMA_THS16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	DMA_THS16	DMA Threshold count Default Value: 0

24.1.651 USBDEVv2_ARB_RW5_WA16

Endpoint Write Address value

Address: 0x402C1310

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.652 USBDEVv2_ARB_RW5_RA16

Endpoint Read Address value

Address: 0x402C1318

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.653 USBDEVv2_ARB_RW5_DR16

Endpoint Data Register

Address: 0x402C1320

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.654 USBDEVv2_ARB_RW6_WA16

Endpoint Write Address value

Address: 0x402C1350

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.655 USBDEVv2_ARB_RW6_RA16

Endpoint Read Address value

Address: 0x402C1358

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.656 USBDEVv2_ARB_RW6_DR16

Endpoint Data Register

Address: 0x402C1360

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.657 USBDEVv2_ARB_RW7_WA16

Endpoint Write Address value

Address: 0x402C1390

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.658 USBDEVv2_ARB_RW7_RA16

Endpoint Read Address value

Address: 0x402C1398

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.659 USBDEVv2_ARB_RW7_DR16

Endpoint Data Register

Address: 0x402C13A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

24.1.660 USBDEVv2_ARB_RW8_WA16

Endpoint Write Address value

Address: 0x402C13D0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	WA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							WA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	WA16	Write Address for EP Default Value: 0

24.1.661 USBDEVv2_ARB_RW8_RA16

Endpoint Read Address value

Address: 0x402C13D8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	RA16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW
Name	None [15:9]							RA16

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8 : 0	RA16	Read Address for EP Default Value: 0

24.1.662 USBDEVv2_ARB_RW8_DR16

Endpoint Data Register

Address: 0x402C13E0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	DR16 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	DR16 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DR16	Data Register for EP ; This register is linked to the memory, hence reset value is undefined Default Value: X

25 USBDEV_BCD Registers

This section discusses the USBDEV_BCD registers. It lists all the registers in mapping tables, in address order.

25.1 Register Details

Register Name	Address
USBDEVv2_USB_POWER_CTRL	0x402C2000
USBDEVv2_USB_USBIO_CTRL	0x402C2008
USBDEVv2_USB_FLOW_CTRL	0x402C200C
USBDEVv2_USB_LPM_CTRL	0x402C2010
USBDEVv2_USB_LPM_STAT	0x402C2014
USBDEVv2_USB_INTR_SIE	0x402C2020
USBDEVv2_USB_INTR_SIE_SET	0x402C2024
USBDEVv2_USB_INTR_SIE_MASK	0x402C2028
USBDEVv2_USB_INTR_SIE_MASKED	0x402C202C
USBDEVv2_USB_INTR_LVL_SEL	0x402C2030
USBDEVv2_USB_INTR_CAUSE_HI	0x402C2034
USBDEVv2_USB_INTR_CAUSE_MED	0x402C2038
USBDEVv2_USB_INTR_CAUSE_LO	0x402C203C
USBDEVv2_USB_DFT_CTRL	0x402C2070
USBDEVv2_USB_PHY_TRIM0	0x402C2F00
USBDEVv2_USB_PHY_TRIM1	0x402C2F04
USBDEVv2_USB_PHY_TRIM2	0x402C2F08
USBDEVv2_USB_PHY_TRIM3	0x402C2F0C
USBDEVv2_USB_CHGDET_TRIM	0x402C2F10
USBDEVv2_USB_TRIM	0x402C2F14
USBDEVv2_USB_USBIO_TRIM	0x402C2F18
USBDEVv2_USB_POWER_CTRL	0x402CF000
USBDEVv2_USB_USBIO_CTRL	0x402CF008
USBDEVv2_USB_FLOW_CTRL	0x402CF00C
USBDEVv2_USB_LPM_CTRL	0x402CF010
USBDEVv2_USB_LPM_STAT	0x402CF014
USBDEVv2_USB_INTR_SIE	0x402CF020

Register Name	Address
USBDEVv2_USB_INTR_SIE_SET	0x402CF024
USBDEVv2_USB_INTR_SIE_MASK	0x402CF028
USBDEVv2_USB_INTR_SIE_MASKED	0x402CF02C
USBDEVv2_USB_INTR_LVL_SEL	0x402CF030
USBDEVv2_USB_INTR_CAUSE_HI	0x402CF034
USBDEVv2_USB_INTR_CAUSE_MED	0x402CF038
USBDEVv2_USB_INTR_CAUSE_LO	0x402CF03C
USBDEVv2_USB_DFT_CTRL	0x402CF070
USBDEVv2_USB_PHY_TRIM0	0x402CFF00
USBDEVv2_USB_PHY_TRIM1	0x402CFF04
USBDEVv2_USB_PHY_TRIM2	0x402CFF08
USBDEVv2_USB_PHY_TRIM3	0x402CFF0C
USBDEVv2_USB_CHGDET_TRIM	0x402CFF10
USBDEVv2_USB_TRIM	0x402CFF14
USBDEVv2_USB_USBIO_TRIM	0x402CFF18

25.1.1 USBDEVv2_USB_POWER_CTRL

Power Control Register

Address: 0x402C2000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	
HW Access	None			R	R	R	R	
Name	None [7:5]			ISOLATE	SUSPEND_DEL	SUSPEND	VBUS_VALID_OVR [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW	RW	None		
HW Access	R	None	R	R	R	None		
Name	ENABLE	None	ENABLE_DMO	ENABLE_DPO	ENABLE_RCVR	None [26:24]		

Bits	Name	Description
31	ENABLE	Mast enable of PHY and Charger Detector. Nothing will work until this bit is set. Default Value: 0
29	ENABLE_DMO	Enables the signle ended receiver on D-. Default Value: 0
28	ENABLE_DPO	Enables the single ended receiver on D+. Default Value: 0
27	ENABLE_RCVR	Enables the differential USB receiver. Default Value: 0
4	ISOLATE	Isolates the PHY outputs. Clear this bit at least 2us after vbus is known to be valid (vbus_valid=1). Isolation will be forced when vbus_valid goes low (see VBUS_VALID_OVR). Default Value: 1
3	SUSPEND_DEL	Delayed version of SUSPEND. Always set SUSPEND and SUSPEND_DEL together in a single register write. When taking PHY out of suspend mode, first clear SUSPEND, then clear SUSPEND_DEL at least 2us later. Default Value: 0

25.1.1 USBDEVv2_USB_POWER_CTRL (continued)

2	SUSPEND	Put PHY into Suspend mode. If the PHY is enabled, this bit MUST be set before entering a low power mode (DeepSleep/Hibernate). Default Value: 0
1 : 0	VBUS_VALID_OVR	Overrides the value received from the GPIO input buffer connected to VBUS: 0: Force vbus_valid=0 1: Force vbus_valid=1 2: Use vbus_valid signal from GPIO input 3: Use vbus_valid signal from PHY detector Default Value: 0

25.1.2 USBDEVv2_USB_USBIO_CTRL

USB IO Control Register

Address: 0x402C2008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW			RW		
HW Access	None		R			R		
Name	None [7:6]		DM_M [5:3]			DM_P [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 3	DM_M	The GPIO Drive Mode for DM IO pad. Default Value: 0
2 : 0	DM_P	The GPIO Drive Mode for DP IO pad. This field only applies if USBIO_CR1.IOMODE =1. Data comes from the corresponding GPIO.DR register. Default Value: 0 **0x0: OFF:** Mode 0: Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off) ('1'). Input buffer on. **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. Other values, not supported

25.1.3 USBDEVv2_USB_FLOW_CTRL

Flow Control Register

Address: 0x402C200C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	EP8_ERR_RESP	EP7_ERR_RESP	EP6_ERR_RESP	EP5_ERR_RESP	EP4_ERR_RESP	EP3_ERR_RESP	EP2_ERR_RESP	EP1_ERR_RESP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_ERR_RESP	End Point 8 error response Default Value: 0
6	EP7_ERR_RESP	End Point 7 error response Default Value: 0
5	EP6_ERR_RESP	End Point 6 error response Default Value: 0
4	EP5_ERR_RESP	End Point 5 error response Default Value: 0
3	EP4_ERR_RESP	End Point 4 error response Default Value: 0
2	EP3_ERR_RESP	End Point 3 error response Default Value: 0
1	EP2_ERR_RESP	End Point 2 error response Default Value: 0

25.1.3 USBDEVv2_USB_FLOW_CTRL (continued)

0	EP1_ERR_RESP	End Point 1 error response 0: do nothing (backward compatibility mode) 1: if this is an IN EP and an underflow occurs then cause a CRC error, if this is an OUT EP and an overflow occurs then send a NAK Default Value: 0

25.1.4 USBDEVv2_USB_LPM_CTRL

LPM Control Register

Address: 0x402C2010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			SUB_RESP	None	NYET_EN	LPM_ACK_RESP	LPM_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	SUB_RESP	Enable a STALL response for all undefined SubPIDs, i.e. other than LPM (0011b). If not enabled then there will be no response (Error) for the undefined SubPIDs. Default Value: 0
2	NYET_EN	Allow firmware to choose which response to use for an LPM token (LPM_EN=1) when the device is NOT ready to go to the requested low power mode (LPM_ACK_RESP=0). 0: a LPM token will get an NAK response (indicating a CRC error), the host is expected to repeat the LPM token. 1: a LPM token will get a NYET response Default Value: 0
1	LPM_ACK_RESP	LPM ACK response enable (if LPM_EN=1), to allow firmware to refuse a low power request 0: a LPM token will get a NYET or NAK (depending on NYET_EN bit below) response and the device will NOT go to a low power mode 1: a LPM token will get an ACK response and the device will go to the requested low power mode Default Value: 0

25.1.4 USBDEVv2_USB_LPM_CTRL (continued)

0	LPM_EN	LPM enable 0: Disabled, LPM token will not get a response (backward compatibility mode) 1: Enable, LPM token will get a handshake response (ACK, STALL, NYET or NAK) A STALL will be sent if the bLinkState is not 0001b A NYET, NAK or ACK response will be sent depending on the NYET_EN and LPM_ACK_RESP bits below Default Value: 0

25.1.5 USBDEVv2_USB_LPM_STAT

LPM Status register

Address: 0x402C2014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	R			
HW Access	None			RW	RW			
Name	None [7:5]			LPM_REMOTEWAKE	LPM_BESL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	LPM_REMOTEWAKE	0: Device is prohibited from initiating a remote wake 1: Device is allow to wake the host Default Value: 0
3 : 0	LPM_BESL	Best Effort Service Latency This value should match either the Baseline (DeepSleep) or Deep (Hibernate) BESL in the BOS descriptor. Default Value: 0

25.1.6 USBDEVv2_USB_INTR_SIE

USB SOF, BUS RESET and EP0 Interrupt Status

Address: 0x402C2020

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None			RW1S	RW1S	RW1S	RW1S	RW1S
Name	None [7:5]			RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR	Interrupt status for Resume Default Value: 0
3	LPM_INTR	Interrupt status for LPM (Link Power Management, L1 entry) Default Value: 0
2	EP0_INTR	Interrupt status for EP0 Default Value: 0
1	BUS_RESET_INTR	Interrupt status for BUS RESET Default Value: 0
0	SOF_INTR	Interrupt status for USB SOF Default Value: 0

25.1.7 USBDEVv2_USB_INTR_SIE_SET

USB SOF, BUS RESET and EP0 Interrupt Set

Address: 0x402C2024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None			A	A	A	A	A
Name	None [7:5]			RESUME_INTR_SET	LPM_INTR_SET	EP0_INTR_SET	BUS_RESET_INTR_SET	SOF_INTR_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	LPM_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	EP0_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	BUS_RESET_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	SOF_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

25.1.8 USBDEVv2_USB_INTR_SIE_MASK

USB SOF, BUS RESET and EP0 Interrupt Mask

Address: 0x402C2028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [7:5]			RESUME_INTR_MASK	LPM_INTR_MASK	EP0_INTR_MASK	BUS_RESET_INTR_MASK	SOF_INTR_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
3	LPM_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
2	EP0_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
1	BUS_RESET_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
0	SOF_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0

25.1.9 USBDEVv2_USB_INTR_SIE_MASKED

USB SOF, BUS RESET and EP0 Interrupt Masked

Address: 0x402C202C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	R	R	R	R
HW Access	None			W	W	W	W	W
Name	None [7:5]			RESUME_INTR_MASKED	LPM_INTR_MASKED	EP0_INTR_MASKED	BUS_RESET_INTR_MASKED	SOF_INTR_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
3	LPM_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
2	EP0_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
1	BUS_RESET_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	SOF_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

25.1.10 USBDEVv2_USB_INTR_LVL_SEL

Select interrupt level for each interrupt source

Address: 0x402C2030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	LPM_LVL_SEL [7:6]		EP0_LVL_SEL [5:4]		BUS_RESET_LVL_SEL [3:2]		SOF_LVL_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None				RW	
HW Access	R		None				R	
Name	ARB_EP_LVL_SEL [15:14]		None [13:10]				RESUME_LVL_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EP4_LVL_SEL [23:22]		EP3_LVL_SEL [21:20]		EP2_LVL_SEL [19:18]		EP1_LVL_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EP8_LVL_SEL [31:30]		EP7_LVL_SEL [29:28]		EP6_LVL_SEL [27:26]		EP5_LVL_SEL [25:24]	

Bits	Name	Description
31 : 30	EP8_LVL_SEL	EP8 Interrupt level select Default Value: 0
29 : 28	EP7_LVL_SEL	EP7 Interrupt level select Default Value: 0
27 : 26	EP6_LVL_SEL	EP6 Interrupt level select Default Value: 0
25 : 24	EP5_LVL_SEL	EP5 Interrupt level select Default Value: 0
23 : 22	EP4_LVL_SEL	EP4 Interrupt level select Default Value: 0
21 : 20	EP3_LVL_SEL	EP3 Interrupt level select Default Value: 0
19 : 18	EP2_LVL_SEL	EP2 Interrupt level select Default Value: 0

25.1.10 USBDEVv2_USB_INTR_LVL_SEL (continued)

17 : 16	EP1_LVL_SEL	EP1 Interrupt level select Default Value: 0
15 : 14	ARB_EP_LVL_SEL	Arbiter Endpoint Interrupt level select Default Value: 0
9 : 8	RESUME_LVL_SEL	Resume Interrupt level select Default Value: 0
7 : 6	LPM_LVL_SEL	LPM Interrupt level select Default Value: 0
5 : 4	EP0_LVL_SEL	EP0 Interrupt level select Default Value: 0
3 : 2	BUS_RESET_LVL_SEL	BUS RESET Interrupt level select Default Value: 0
1 : 0	SOF_LVL_SEL	USB SOF Interrupt level select Default Value: 0 **0x0: HI:** High priority interrupt **0x1: MED:** Medium priority interrupt **0x2: LO:** Low priority interrupt **0x3: RESERVED:** illegal

25.1.11 USBDEVv2_USB_INTR_CAUSE_HI

High priority interrupt Cause register

Address: 0x402C2034

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	None		R	R	R	R	R
HW Access	RW	None		RW	RW	RW	RW	RW
Name	ARB_EP_INTR	None [6:5]		RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	EP8_INTR	EP8 Interrupt Default Value: 0
14	EP7_INTR	EP7 Interrupt Default Value: 0
13	EP6_INTR	EP6 Interrupt Default Value: 0
12	EP5_INTR	EP5 Interrupt Default Value: 0
11	EP4_INTR	EP4 Interrupt Default Value: 0
10	EP3_INTR	EP3 Interrupt Default Value: 0
9	EP2_INTR	EP2 Interrupt Default Value: 0

25.1.11 USBDEVv2_USB_INTR_CAUSE_HI (continued)

8	EP1_INTR	EP1 Interrupt Default Value: 0
7	ARB_EP_INTR	Arbiter Endpoint Interrupt Default Value: 0
4	RESUME_INTR	Resume Interrupt Default Value: 0
3	LPM_INTR	LPM Interrupt Default Value: 0
2	EP0_INTR	EP0 Interrupt Default Value: 0
1	BUS_RESET_INTR	BUS RESET Interrupt Default Value: 0
0	SOF_INTR	USB SOF Interrupt Default Value: 0

25.1.12 USBDEVv2_USB_INTR_CAUSE_MED

Medium priority interrupt Cause register

Address: 0x402C2038

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	None		R	R	R	R	R
HW Access	RW	None		RW	RW	RW	RW	RW
Name	ARB_EP_INTR	None [6:5]		RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	EP8_INTR	EP8 Interrupt Default Value: 0
14	EP7_INTR	EP7 Interrupt Default Value: 0
13	EP6_INTR	EP6 Interrupt Default Value: 0
12	EP5_INTR	EP5 Interrupt Default Value: 0
11	EP4_INTR	EP4 Interrupt Default Value: 0
10	EP3_INTR	EP3 Interrupt Default Value: 0
9	EP2_INTR	EP2 Interrupt Default Value: 0

25.1.12 USBDEVv2_USB_INTR_CAUSE_MED (continued)

8	EP1_INTR	EP1 Interrupt Default Value: 0
7	ARB_EP_INTR	Arbiter Endpoint Interrupt Default Value: 0
4	RESUME_INTR	Resume Interrupt Default Value: 0
3	LPM_INTR	LPM Interrupt Default Value: 0
2	EP0_INTR	EP0 Interrupt Default Value: 0
1	BUS_RESET_INTR	BUS RESET Interrupt Default Value: 0
0	SOF_INTR	USB SOF Interrupt Default Value: 0

25.1.13 USBDEVv2_USB_INTR_CAUSE_LO

Low priority interrupt Cause register

Address: 0x402C203C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	None		R	R	R	R	R
HW Access	RW	None		RW	RW	RW	RW	RW
Name	ARB_EP_INTR	None [6:5]		RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	EP8_INTR	EP8 Interrupt Default Value: 0
14	EP7_INTR	EP7 Interrupt Default Value: 0
13	EP6_INTR	EP6 Interrupt Default Value: 0
12	EP5_INTR	EP5 Interrupt Default Value: 0
11	EP4_INTR	EP4 Interrupt Default Value: 0
10	EP3_INTR	EP3 Interrupt Default Value: 0
9	EP2_INTR	EP2 Interrupt Default Value: 0

25.1.13 USBDEVv2_USB_INTR_CAUSE_LO (continued)

8	EP1_INTR	EP1 Interrupt Default Value: 0
7	ARB_EP_INTR	Arbiter Endpoint Interrupt Default Value: 0
4	RESUME_INTR	Resume Interrupt Default Value: 0
3	LPM_INTR	LPM Interrupt Default Value: 0
2	EP0_INTR	EP0 Interrupt Default Value: 0
1	BUS_RESET_INTR	BUS RESET Interrupt Default Value: 0
0	SOF_INTR	USB SOF Interrupt Default Value: 0

25.1.14 USBDEVv2_USB_DFT_CTRL

DFT control

Address: 0x402C2070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					DDFT_SEL [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						ADFT_VREFOUT_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	ADFT_VREFOUT_SEL	Select ADFT connection for VREF_OUT Default Value: 0 **0x0: OPEN:** no connections **0x1: AMUXA:** Connect adft_vref_out output to amuxbusa (should not be used because adft_vref_in connects to this bus) **0x2: AMUXB:** Connect adft_vref_out output to amuxbusb **0x3: RSVD:** reserved
2 : 0	DDFT_SEL	DDFT select signal Default Value: 0 **0x0: OFF:** Nothing connected, output 0

25.1.14 USBDEVv2_USB_DFT_CTRL (continued)

0x1: DP_SE:
Single Ended output of DP

0x2: DM_SE:
Single Ended output of DM

0x3: RCV_DF:
Differential Receiver output

0x4: CHRG_DET:
Charger detect output

0x5: VBUS_DET:
Vbus detect output

25.1.15 USBDEVv2_USB_PHY_TRIM0

PHY trim control register.

Address: 0x402C2F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DP_R_REG [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DP_R_REG	Trim control for D+ pin poly termination resistors when PHY is in regulated mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.16 USBDEVv2_USB_PHY_TRIM1

PHY trim control register.

Address: 0x402C2F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DM_R_REG [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DM_R_REG	Trim control for D- pin poly termination resistors when PHY is in regulated mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.17 USBDEVv2_USB_PHY_TRIM2

PHY trim control register.

Address: 0x402C2F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DP_R_BYPASS [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DP_R_BYPASS	Trim control for D+ pin poly termination resistors when PHY is in bypass mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.18 USBDEVv2_USB_PHY_TRIM3

PHY trim control register.

Address: 0x402C2F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DM_R_BYPASS [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DM_R_BYPASS	Trim control for D- pin poly termination resistors when PHY is in bypass mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.19 USBDEVv2_USB_CHGDET_TRIM

Charger detect trim values

Address: 0x402C2F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None		RW	
HW Access	None	R			None		R	
Name	None	V600M_TRIM [6:4]			None [3:2]		V325M_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 4	V600M_TRIM	Trim bits for 600mV voltage reference. Used for charger detect voltage driver. Default Value: 4
1 : 0	V325M_TRIM	Trim bits for 325mV voltage reference. Used for charger detect comparator reference. Default Value: 2

25.1.20 USBDEVv2_USB_TRIM

trim values

Address: 0x402C2F14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						DM_PD_VAL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	DM_PD_VAL	Trim bit for DM Pull Down register, to get resistance value close enough to 15kohm Default Value: 0

25.1.21 USBDEVv2_USB_USBIO_TRIM

trim values for IOs

Address: 0x402C2F18

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	
HW Access	None		R	R	R	R	R	
Name	None [7:6]		X_DEC	X_INC	MINC	MDEC	TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	X_DEC	This bit enables a decrease of the USB crossover voltage. Default Value: 0
4	X_INC	This bit enables a increase of the USB crossover voltage. Default Value: 0
3	MINC	When set this bit increases the USB edge matching ratio Default Value: 0
2	MDEC	When set this bit decreases the USB edge matching ratio. Default Value: 0
1 : 0	TRIM	These two bits of trim are for the suspend mode resistor. Default Value: 0 **0x0: TRIM_NO:** No effect. **0x1: TRIM_LOWER:** Lower idle voltage **0x2: TRIM_HIGHER:** Higher idle voltage

25.1.21 USBDEVv2_USB_USBIO_TRIM (continued)

0x3: TRIM_DONT_USE:
Do not use

25.1.22 USBDEVv2_USB_POWER_CTRL

Power Control Register

Address: 0x402CF000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	
HW Access	None			R	R	R	R	
Name	None [7:5]			ISOLATE	SUSPEND_DEL	SUSPEND	VBUS_VALID_OVR [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW	RW	None		
HW Access	R	None	R	R	R	None		
Name	ENABLE	None	ENABLE_DMO	ENABLE_DPO	ENABLE_RCVR	None [26:24]		

Bits	Name	Description
31	ENABLE	Mast enable of PHY and Charger Detector. Nothing will work until this bit is set. Default Value: 0
29	ENABLE_DMO	Enables the signle ended receiver on D-. Default Value: 0
28	ENABLE_DPO	Enables the single ended receiver on D+. Default Value: 0
27	ENABLE_RCVR	Enables the differential USB receiver. Default Value: 0
4	ISOLATE	Isolates the PHY outputs. Clear this bit at least 2us after vbus is known to be valid (vbus_valid=1). Isolation will be forced when vbus_valid goes low (see VBUS_VALID_OVR). Default Value: 1
3	SUSPEND_DEL	Delayed version of SUSPEND. Always set SUSPEND and SUSPEND_DEL together in a single register write. When taking PHY out of suspend mode, first clear SUSPEND, then clear SUSPEND_DEL at least 2us later. Default Value: 0

25.1.22 USBDEVv2_USB_POWER_CTRL (continued)

2	SUSPEND	Put PHY into Suspend mode. If the PHY is enabled, this bit MUST be set before entering a low power mode (DeepSleep/Hibernate). Default Value: 0
1 : 0	VBUS_VALID_OVR	Overrides the value received from the GPIO input buffer connected to VBUS: 0: Force vbus_valid=0 1: Force vbus_valid=1 2: Use vbus_valid signal from GPIO input 3: Use vbus_valid signal from PHY detector Default Value: 0

25.1.23 USBDEVv2_USB_USBIO_CTRL

USB IO Control Register

Address: 0x402CF008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW			RW		
HW Access	None		R			R		
Name	None [7:6]		DM_M [5:3]			DM_P [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 3	DM_M	The GPIO Drive Mode for DM IO pad. Default Value: 0
2 : 0	DM_P	The GPIO Drive Mode for DP IO pad. This field only applies if USBIO_CR1.IOMODE =1. Data comes from the corresponding GPIO.DR register. Default Value: 0 **0x0: OFF:** Mode 0: Output buffer off (high Z). Input buffer off. **0x1: INPUT:** Mode 1: Output buffer off (high Z). Input buffer on. **0x2: 0_PU:** Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. **0x4: 0_Z:** Mode 4: Strong pull down ('0'), open drain (pull up off) ('1'). Input buffer on. **0x6: 0_1:** Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. Other values, not supported

25.1.24 USBDEVv2_USB_FLOW_CTRL

Flow Control Register

Address: 0x402CF00C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	EP8_ERR_RESP	EP7_ERR_RESP	EP6_ERR_RESP	EP5_ERR_RESP	EP4_ERR_RESP	EP3_ERR_RESP	EP2_ERR_RESP	EP1_ERR_RESP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	EP8_ERR_RESP	End Point 8 error response Default Value: 0
6	EP7_ERR_RESP	End Point 7 error response Default Value: 0
5	EP6_ERR_RESP	End Point 6 error response Default Value: 0
4	EP5_ERR_RESP	End Point 5 error response Default Value: 0
3	EP4_ERR_RESP	End Point 4 error response Default Value: 0
2	EP3_ERR_RESP	End Point 3 error response Default Value: 0
1	EP2_ERR_RESP	End Point 2 error response Default Value: 0

25.1.24 USBDEVv2_USB_FLOW_CTRL (continued)

0	EP1_ERR_RESP	End Point 1 error response 0: do nothing (backward compatibility mode) 1: if this is an IN EP and an underflow occurs then cause a CRC error, if this is an OUT EP and an overflow occurs then send a NAK Default Value: 0

25.1.25 USBDEVv2_USB_LPM_CTRL

LPM Control Register

Address: 0x402CF010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			SUB_RESP	None	NYET_EN	LPM_ACK_RESP	LPM_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	SUB_RESP	Enable a STALL response for all undefined SubPIDs, i.e. other than LPM (0011b). If not enabled then there will be no response (Error) for the undefined SubPIDs. Default Value: 0
2	NYET_EN	Allow firmware to choose which response to use for an LPM token (LPM_EN=1) when the device is NOT ready to go to the requested low power mode (LPM_ACK_RESP=0). 0: a LPM token will get an NAK response (indicating a CRC error), the host is expected to repeat the LPM token. 1: a LPM token will get a NYET response Default Value: 0
1	LPM_ACK_RESP	LPM ACK response enable (if LPM_EN=1), to allow firmware to refuse a low power request 0: a LPM token will get a NYET or NAK (depending on NYET_EN bit below) response and the device will NOT go to a low power mode 1: a LPM token will get an ACK response and the device will go to the requested low power mode Default Value: 0

25.1.25 USBDEVv2_USB_LPM_CTRL (continued)

0	LPM_EN	LPM enable 0: Disabled, LPM token will not get a response (backward compatibility mode) 1: Enable, LPM token will get a handshake response (ACK, STALL, NYET or NAK) A STALL will be sent if the bLinkState is not 0001b A NYET, NAK or ACK response will be sent depending on the NYET_EN and LPM_ACK_RESP bits below Default Value: 0

25.1.26 USBDEVv2_USB_LPM_STAT

LPM Status register

Address: 0x402CF014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	R			
HW Access	None			RW	RW			
Name	None [7:5]			LPM_REMOTEWAKE	LPM_BESL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	LPM_REMOTEWAKE	0: Device is prohibited from initiating a remote wake 1: Device is allow to wake the host Default Value: 0
3 : 0	LPM_BESL	Best Effort Service Latency This value should match either the Baseline (DeepSleep) or Deep (Hibernate) BESL in the BOS descriptor. Default Value: 0

25.1.27 USBDEVv2_USB_INTR_SIE

USB SOF, BUS RESET and EP0 Interrupt Status

Address: 0x402CF020

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None			RW1S	RW1S	RW1S	RW1S	RW1S
Name	None [7:5]			RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR	Interrupt status for Resume Default Value: 0
3	LPM_INTR	Interrupt status for LPM (Link Power Management, L1 entry) Default Value: 0
2	EP0_INTR	Interrupt status for EP0 Default Value: 0
1	BUS_RESET_INTR	Interrupt status for BUS RESET Default Value: 0
0	SOF_INTR	Interrupt status for USB SOF Default Value: 0

25.1.28 USBDEVv2_USB_INTR_SIE_SET

USB SOF, BUS RESET and EP0 Interrupt Set

Address: 0x402CF024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None			A	A	A	A	A
Name	None [7:5]			RESUME_INTR_SET	LPM_INTR_SET	EP0_INTR_SET	BUS_RESET_INTR_SET	SOF_INTR_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	LPM_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	EP0_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	BUS_RESET_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	SOF_INTR_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

25.1.29 USBDEVv2_USB_INTR_SIE_MASK

USB SOF, BUS RESET and EP0 Interrupt Mask

Address: 0x402CF028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			R	R	R	R	R
Name	None [7:5]			RESUME_INTR_MASK	LPM_INTR_MASK	EP0_INTR_MASK	BUS_RESET_INTR_MASK	SOF_INTR_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
3	LPM_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
2	EP0_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
1	BUS_RESET_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0
0	SOF_INTR_MASK	Set to 1 to enable interrupt corresponding to interrupt request register Default Value: 0

25.1.30 USBDEVv2_USB_INTR_SIE_MASKED

USB SOF, BUS RESET and EP0 Interrupt Masked

Address: 0x402CF02C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	R	R	R	R
HW Access	None			W	W	W	W	W
Name	None [7:5]			RESUME_INTR_MASKED	LPM_INTR_MASKED	EP0_INTR_MASKED	BUS_RESET_INTR_MASKED	SOF_INTR_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESUME_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
3	LPM_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
2	EP0_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
1	BUS_RESET_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	SOF_INTR_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

25.1.31 USBDEVv2_USB_INTR_LVL_SEL

Select interrupt level for each interrupt source

Address: 0x402CF030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	LPM_LVL_SEL [7:6]		EP0_LVL_SEL [5:4]		BUS_RESET_LVL_SEL [3:2]		SOF_LVL_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None				RW	
HW Access	R		None				R	
Name	ARB_EP_LVL_SEL [15:14]		None [13:10]				RESUME_LVL_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EP4_LVL_SEL [23:22]		EP3_LVL_SEL [21:20]		EP2_LVL_SEL [19:18]		EP1_LVL_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EP8_LVL_SEL [31:30]		EP7_LVL_SEL [29:28]		EP6_LVL_SEL [27:26]		EP5_LVL_SEL [25:24]	

Bits	Name	Description
31 : 30	EP8_LVL_SEL	EP8 Interrupt level select Default Value: 0
29 : 28	EP7_LVL_SEL	EP7 Interrupt level select Default Value: 0
27 : 26	EP6_LVL_SEL	EP6 Interrupt level select Default Value: 0
25 : 24	EP5_LVL_SEL	EP5 Interrupt level select Default Value: 0
23 : 22	EP4_LVL_SEL	EP4 Interrupt level select Default Value: 0
21 : 20	EP3_LVL_SEL	EP3 Interrupt level select Default Value: 0
19 : 18	EP2_LVL_SEL	EP2 Interrupt level select Default Value: 0

25.1.31 USBDEVv2_USB_INTR_LVL_SEL (continued)

17 : 16	EP1_LVL_SEL	EP1 Interrupt level select Default Value: 0
15 : 14	ARB_EP_LVL_SEL	Arbiter Endpoint Interrupt level select Default Value: 0
9 : 8	RESUME_LVL_SEL	Resume Interrupt level select Default Value: 0
7 : 6	LPM_LVL_SEL	LPM Interrupt level select Default Value: 0
5 : 4	EP0_LVL_SEL	EP0 Interrupt level select Default Value: 0
3 : 2	BUS_RESET_LVL_SEL	BUS RESET Interrupt level select Default Value: 0
1 : 0	SOF_LVL_SEL	USB SOF Interrupt level select Default Value: 0 **0x0: HI:** High priority interrupt **0x1: MED:** Medium priority interrupt **0x2: LO:** Low priority interrupt **0x3: RESERVED:** illegal

25.1.32 USBDEVv2_USB_INTR_CAUSE_HI

High priority interrupt Cause register

Address: 0x402CF034

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	None		R	R	R	R	R
HW Access	RW	None		RW	RW	RW	RW	RW
Name	ARB_EP_INTR	None [6:5]		RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	EP8_INTR	EP8 Interrupt Default Value: 0
14	EP7_INTR	EP7 Interrupt Default Value: 0
13	EP6_INTR	EP6 Interrupt Default Value: 0
12	EP5_INTR	EP5 Interrupt Default Value: 0
11	EP4_INTR	EP4 Interrupt Default Value: 0
10	EP3_INTR	EP3 Interrupt Default Value: 0
9	EP2_INTR	EP2 Interrupt Default Value: 0

25.1.32 USBDEVv2_USB_INTR_CAUSE_HI (continued)

8	EP1_INTR	EP1 Interrupt Default Value: 0
7	ARB_EP_INTR	Arbiter Endpoint Interrupt Default Value: 0
4	RESUME_INTR	Resume Interrupt Default Value: 0
3	LPM_INTR	LPM Interrupt Default Value: 0
2	EP0_INTR	EP0 Interrupt Default Value: 0
1	BUS_RESET_INTR	BUS RESET Interrupt Default Value: 0
0	SOF_INTR	USB SOF Interrupt Default Value: 0

25.1.33 USBDEVv2_USB_INTR_CAUSE_MED

Medium priority interrupt Cause register

Address: 0x402CF038

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	None		R	R	R	R	R
HW Access	RW	None		RW	RW	RW	RW	RW
Name	ARB_EP_INTR	None [6:5]		RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	EP8_INTR	EP8 Interrupt Default Value: 0
14	EP7_INTR	EP7 Interrupt Default Value: 0
13	EP6_INTR	EP6 Interrupt Default Value: 0
12	EP5_INTR	EP5 Interrupt Default Value: 0
11	EP4_INTR	EP4 Interrupt Default Value: 0
10	EP3_INTR	EP3 Interrupt Default Value: 0
9	EP2_INTR	EP2 Interrupt Default Value: 0

25.1.33 USBDEVv2_USB_INTR_CAUSE_MED (continued)

8	EP1_INTR	EP1 Interrupt Default Value: 0
7	ARB_EP_INTR	Arbiter Endpoint Interrupt Default Value: 0
4	RESUME_INTR	Resume Interrupt Default Value: 0
3	LPM_INTR	LPM Interrupt Default Value: 0
2	EP0_INTR	EP0 Interrupt Default Value: 0
1	BUS_RESET_INTR	BUS RESET Interrupt Default Value: 0
0	SOF_INTR	USB SOF Interrupt Default Value: 0

25.1.34 USBDEVv2_USB_INTR_CAUSE_LO

Low priority interrupt Cause register

Address: 0x402CF03C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	None		R	R	R	R	R
HW Access	RW	None		RW	RW	RW	RW	RW
Name	ARB_EP_INTR	None [6:5]		RESUME_INTR	LPM_INTR	EP0_INTR	BUS_RESET_INTR	SOF_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	EP8_INTR	EP7_INTR	EP6_INTR	EP5_INTR	EP4_INTR	EP3_INTR	EP2_INTR	EP1_INTR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	EP8_INTR	EP8 Interrupt Default Value: 0
14	EP7_INTR	EP7 Interrupt Default Value: 0
13	EP6_INTR	EP6 Interrupt Default Value: 0
12	EP5_INTR	EP5 Interrupt Default Value: 0
11	EP4_INTR	EP4 Interrupt Default Value: 0
10	EP3_INTR	EP3 Interrupt Default Value: 0
9	EP2_INTR	EP2 Interrupt Default Value: 0

25.1.34 USBDEVv2_USB_INTR_CAUSE_LO (continued)

8	EP1_INTR	EP1 Interrupt Default Value: 0
7	ARB_EP_INTR	Arbiter Endpoint Interrupt Default Value: 0
4	RESUME_INTR	Resume Interrupt Default Value: 0
3	LPM_INTR	LPM Interrupt Default Value: 0
2	EP0_INTR	EP0 Interrupt Default Value: 0
1	BUS_RESET_INTR	BUS RESET Interrupt Default Value: 0
0	SOF_INTR	USB SOF Interrupt Default Value: 0

25.1.35 USBDEVv2_USB_DFT_CTRL

DFT control

Address: 0x402CF070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					DDFT_SEL [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						ADFT_VREFOUT_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	ADFT_VREFOUT_SEL	Select ADFT connection for VREF_OUT Default Value: 0 **0x0: OPEN:** no connections **0x1: AMUXA:** Connect adft_vref_out output to amuxbusa (should not be used because adft_vref_in connects to this bus) **0x2: AMUXB:** Connect adft_vref_out output to amuxbusb **0x3: RSVD:** reserved
2 : 0	DDFT_SEL	DDFT select signal Default Value: 0 **0x0: OFF:** Nothing connected, output 0

25.1.35 USBDEVv2_USB_DFT_CTRL (continued)

0x1: DP_SE:
Single Ended output of DP

0x2: DM_SE:
Single Ended output of DM

0x3: RCV_DF:
Differential Receiver output

0x4: CHRG_DET:
Charger detect output

0x5: VBUS_DET:
Vbus detect output

25.1.36 USBDEVv2_USB_PHY_TRIM0

PHY trim control register.

Address: 0x402CFF00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DP_R_REG [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DP_R_REG	Trim control for D+ pin poly termination resistors when PHY is in regulated mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.37 USBDEVv2_USB_PHY_TRIM1

PHY trim control register.

Address: 0x402CFF04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DM_R_REG [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DM_R_REG	Trim control for D- pin poly termination resistors when PHY is in regulated mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.38 USBDEVv2_USB_PHY_TRIM2

PHY trim control register.

Address: 0x402CFF08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DP_R_BYPASS [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DP_R_BYPASS	Trim control for D+ pin poly termination resistors when PHY is in bypass mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.39 USBDEVv2_USB_PHY_TRIM3

PHY trim control register.

Address: 0x402CFF0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		TRIM_DM_R_BYPASS [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	TRIM_DM_R_BYPASS	Trim control for D- pin poly termination resistors when PHY is in bypass mode. Default value is ~22Ohm. Increasing from 0 to 31 decreases the resistance to minimum. 32 gives the maximum resistance. Increasing from 32 to 62 decreases the resistance from maximum to default. Default Value: 0

25.1.40 USBDEVv2_USB_CHGDET_TRIM

Charger detect trim values

Address: 0x402CFF10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None		RW	
HW Access	None	R			None		R	
Name	None	V600M_TRIM [6:4]			None [3:2]		V325M_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 4	V600M_TRIM	Trim bits for 600mV voltage reference. Used for charger detect voltage driver. Default Value: 4
1 : 0	V325M_TRIM	Trim bits for 325mV voltage reference. Used for charger detect comparator reference. Default Value: 2

25.1.41 USBDEVv2_USB_TRIM

trim values

Address: 0x402CFF14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						DM_PD_VAL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	DM_PD_VAL	Trim bit for DM Pull Down register, to get resistance value close enough to 15kohm Default Value: 0

25.1.42 USBDEVv2_USB_USBIO_TRIM

trim values for IOs

Address: 0x402CFF18

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	
HW Access	None		R	R	R	R	R	
Name	None [7:6]		X_DEC	X_INC	MINC	MDEC	TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	X_DEC	This bit enables a decrease of the USB crossover voltage. Default Value: 0
4	X_INC	This bit enables a increase of the USB crossover voltage. Default Value: 0
3	MINC	When set this bit increases the USB edge matching ratio Default Value: 0
2	MDEC	When set this bit decreases the USB edge matching ratio. Default Value: 0
1 : 0	TRIM	These two bits of trim are for the suspend mode resistor. Default Value: 0 **0x0: TRIM_NO:** No effect. **0x1: TRIM_LOWER:** Lower idle voltage **0x2: TRIM_HIGHER:** Higher idle voltage

25.1.42 USBDEVv2_USB_USBIO_TRIM (continued)

0x3: TRIM_DONT_USE:
Do not use

Revision History

Revision History

Document Title: PMG1 Family PMG1-S3 Registers Technical Reference Manual (TRM) Document Number: 002-33773			
Revision	**ECN#**	**Issue Date**	**Description of Change**
**	7244294	08/26/2021	Specification for new silicon.
*A	8142021	09/14/2025	Removed USB PD and PMG1S3_TRIMS chapters.