

Please note that Cypress is an Infineon Technologies Company.

The document following this cover page is marked as “Cypress” document as this is the company that originally developed the product. Please note that Infineon will continue to offer the product to new and existing customers as part of the Infineon product portfolio.

Continuity of document content

The fact that Infineon offers the following product as part of the Infineon product portfolio does not lead to any changes to this document. Future revisions will occur when appropriate, and any changes will be set out on the document history page.

Continuity of ordering part numbers

Infineon continues to support existing part numbers. Please continue to use the ordering part numbers listed in the datasheet for ordering.



PSoC 4100S Family

PSoC[®] 4 Registers Technical Reference Manual (TRM)

Document No. 002-10523 Rev. *D

July 1, 2024

Cypress Semiconductor
198 Champion Court
San Jose, CA 95134-1709
www.infineon.com

Copyrights

© Cypress Semiconductor Corporation, 2016-2024. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. No computing device can be absolutely secure. Therefore, despite security measures implemented in Cypress hardware or software products, Cypress shall have no liability arising out of any security breach, such as unauthorized access to or use of a Cypress product. CYPRESS DOES NOT REPRESENT, WARRANT, OR GUARANTEE THAT CYPRESS PRODUCTS, OR SYSTEMS CREATED USING CYPRESS PRODUCTS, WILL BE FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION (collectively, "Security Breach"). Cypress disclaims any liability relating to any Security Breach, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from any Security Breach. In addition, the products described in these materials may contain design defects or errors known as errata which may cause the product to deviate from published specifications. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. "High-Risk Device" means any device or system whose failure could cause personal injury, death, or property damage. Examples of High-Risk Devices are weapons, nuclear installations, surgical implants, and other medical devices. "Critical Component" means any component of a High-Risk Device whose failure to perform can be reasonably expected to cause, directly or indirectly, the failure of the High-Risk Device, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from any use of a Cypress product as a Critical Component in a High-Risk Device. You shall indemnify and hold Cypress, its directors, officers, employees, agents, affiliates, distributors, and assigns harmless from and against all claims, costs, damages, and expenses, arising out of any claim, including claims for product liability, personal injury or death, or property damage arising from any use of a Cypress product as a Critical Component in a High-Risk Device. Cypress products are not intended or authorized for use as a Critical Component in any High-Risk Device except to the limited extent that (i) Cypress's published data sheet for the product explicitly states Cypress has qualified the product for use in a specific High-Risk Device, or (ii) Cypress has given you advance written authorization to use the product as a Critical Component in the specific High-Risk Device and you have signed a separate indemnification agreement.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.

Contents



Register Mapping 19

1. Cortex M0+ (CM0+) Registers 23

1.1	Register Details	23
1.1.1	CM0P_DWT_PID4	25
1.1.2	CM0P_DWT_PID0	26
1.1.3	CM0P_DWT_PID1	27
1.1.4	CM0P_DWT_PID2	28
1.1.5	CM0P_DWT_PID3	29
1.1.6	CM0P_DWT_CID0	30
1.1.7	CM0P_DWT_CID1	31
1.1.8	CM0P_DWT_CID2	32
1.1.9	CM0P_DWT_CID3	33
1.1.10	CM0P_BP_PID4	34
1.1.11	CM0P_BP_PID0	35
1.1.12	CM0P_BP_PID1	36
1.1.13	CM0P_BP_PID2	37
1.1.14	CM0P_BP_PID3	38
1.1.15	CM0P_BP_CID0	39
1.1.16	CM0P_BP_CID1	40
1.1.17	CM0P_BP_CID2	41
1.1.18	CM0P_BP_CID3	42
1.1.19	CM0P_SYST_CSR	43
1.1.20	CM0P_SYST_RVR	45
1.1.21	CM0P_SYST_CVR	46
1.1.22	CM0P_SYST_CALIB	47
1.1.23	CM0P_ISER	49
1.1.24	CM0P_ICER	50
1.1.25	CM0P_ISPR	51
1.1.26	CM0P_ICPR	52
1.1.27	CM0P_IPR0	53
1.1.28	CM0P_IPR1	54
1.1.29	CM0P_IPR2	55
1.1.30	CM0P_IPR3	56
1.1.31	CM0P_IPR4	57
1.1.32	CM0P_IPR5	58
1.1.33	CM0P_IPR6	59
1.1.34	CM0P_IPR7	60
1.1.35	CM0P_CPUID	61
1.1.36	CM0P_ICSR	62
1.1.37	CM0P_AIRCR	64
1.1.38	CM0P_SCR	65
1.1.39	CM0P_CCR	66

1.1.40	CM0P_SHPR2	67
1.1.41	CM0P_SHPR3	68
1.1.42	CM0P_SHCSR	69
1.1.43	CM0P_SCS_PID4	70
1.1.44	CM0P_SCS_PID0	71
1.1.45	CM0P_SCS_PID1	72
1.1.46	CM0P_SCS_PID2	73
1.1.47	CM0P_SCS_PID3	74
1.1.48	CM0P_SCS_CID0	75
1.1.49	CM0P_SCS_CID1	76
1.1.50	CM0P_SCS_CID2	77
1.1.51	CM0P_SCS_CID3	78
1.1.52	CM0P_ROM_SCS	79
1.1.53	CM0P_ROM_DWT	80
1.1.54	CM0P_ROM_BPU	81
1.1.55	CM0P_ROM_END	82
1.1.56	CM0P_ROM_CSMT	83
1.1.57	CM0P_ROM_PID4	84
1.1.58	CM0P_ROM_PID0	85
1.1.59	CM0P_ROM_PID1	86
1.1.60	CM0P_ROM_PID2	87
1.1.61	CM0P_ROM_PID3	88
1.1.62	CM0P_ROM_CID0	89
1.1.63	CM0P_ROM_CID1	90
1.1.64	CM0P_ROM_CID2	91
1.1.65	CM0P_ROM_CID3	92

2. TCPWM - Individual Counter (CNT) Registers 93

2.1	Register Details	93
2.1.1	TCPWM_CNT0_CTRL	96
2.1.2	TCPWM_CNT0_STATUS	99
2.1.3	TCPWM_CNT0_COUNTER	100
2.1.4	TCPWM_CNT0_CC	101
2.1.5	TCPWM_CNT0_CC_BUFF	102
2.1.6	TCPWM_CNT0_PERIOD	103
2.1.7	TCPWM_CNT0_PERIOD_BUFF	104
2.1.8	TCPWM_CNT0_TR_CTRL0	105
2.1.9	TCPWM_CNT0_TR_CTRL1	107
2.1.10	TCPWM_CNT0_TR_CTRL2	109
2.1.11	TCPWM_CNT0_INTR	111
2.1.12	TCPWM_CNT0_INTR_SET	112
2.1.13	TCPWM_CNT0_INTR_MASK	113
2.1.14	TCPWM_CNT0_INTR_MASKED	114
2.1.15	TCPWM_CNT1_CTRL	115
2.1.16	TCPWM_CNT1_STATUS	118
2.1.17	TCPWM_CNT1_COUNTER	119
2.1.18	TCPWM_CNT1_CC	120
2.1.19	TCPWM_CNT1_CC_BUFF	121
2.1.20	TCPWM_CNT1_PERIOD	122
2.1.21	TCPWM_CNT1_PERIOD_BUFF	123
2.1.22	TCPWM_CNT1_TR_CTRL0	124
2.1.23	TCPWM_CNT1_TR_CTRL1	126
2.1.24	TCPWM_CNT1_TR_CTRL2	128
2.1.25	TCPWM_CNT1_INTR	130

2.1.26	TCPWM_CNT1_INTR_SET	131
2.1.27	TCPWM_CNT1_INTR_MASK	132
2.1.28	TCPWM_CNT1_INTR_MASKED	133
2.1.29	TCPWM_CNT2_CTRL	134
2.1.30	TCPWM_CNT2_STATUS	137
2.1.31	TCPWM_CNT2_COUNTER	138
2.1.32	TCPWM_CNT2_CC	139
2.1.33	TCPWM_CNT2_CC_BUFF	140
2.1.34	TCPWM_CNT2_PERIOD	141
2.1.35	TCPWM_CNT2_PERIOD_BUFF	142
2.1.36	TCPWM_CNT2_TR_CTRL0	143
2.1.37	TCPWM_CNT2_TR_CTRL1	145
2.1.38	TCPWM_CNT2_TR_CTRL2	147
2.1.39	TCPWM_CNT2_INTR	149
2.1.40	TCPWM_CNT2_INTR_SET	150
2.1.41	TCPWM_CNT2_INTR_MASK	151
2.1.42	TCPWM_CNT2_INTR_MASKED	152
2.1.43	TCPWM_CNT3_CTRL	153
2.1.44	TCPWM_CNT3_STATUS	156
2.1.45	TCPWM_CNT3_COUNTER	157
2.1.46	TCPWM_CNT3_CC	158
2.1.47	TCPWM_CNT3_CC_BUFF	159
2.1.48	TCPWM_CNT3_PERIOD	160
2.1.49	TCPWM_CNT3_PERIOD_BUFF	161
2.1.50	TCPWM_CNT3_TR_CTRL0	162
2.1.51	TCPWM_CNT3_TR_CTRL1	164
2.1.52	TCPWM_CNT3_TR_CTRL2	166
2.1.53	TCPWM_CNT3_INTR	168
2.1.54	TCPWM_CNT3_INTR_SET	169
2.1.55	TCPWM_CNT3_INTR_MASK	170
2.1.56	TCPWM_CNT3_INTR_MASKED	171
2.1.57	TCPWM_CNT4_CTRL	172
2.1.58	TCPWM_CNT4_STATUS	175
2.1.59	TCPWM_CNT4_COUNTER	176
2.1.60	TCPWM_CNT4_CC	177
2.1.61	TCPWM_CNT4_CC_BUFF	178
2.1.62	TCPWM_CNT4_PERIOD	179
2.1.63	TCPWM_CNT4_PERIOD_BUFF	180
2.1.64	TCPWM_CNT4_TR_CTRL0	181
2.1.65	TCPWM_CNT4_TR_CTRL1	183
2.1.66	TCPWM_CNT4_TR_CTRL2	185
2.1.67	TCPWM_CNT4_INTR	187
2.1.68	TCPWM_CNT4_INTR_SET	188
2.1.69	TCPWM_CNT4_INTR_MASK	189
2.1.70	TCPWM_CNT4_INTR_MASKED	190

3. CPU Sub System (CPUSS) Registers 191

3.1	Register Details	191
3.1.1	CPUSS_SYSREQ	192
3.1.2	CPUSS_SYSARG	194
3.1.3	CPUSS_FLASH_CTL	195
3.1.4	CPUSS_ROM_CTL	196

4. CapSense Registers	197
5. Continuous Time Block Mini Registers	198
5.1 Register Details	198
5.1.1 CTBM0_CTB_CTRL	199
5.1.2 CTBM0_OA_RES0_CTRL	200
5.1.3 CTBM0_OA_RES1_CTRL	202
5.1.4 CTBM0_COMP_STAT	204
5.1.5 CTBM0_INTR	205
5.1.6 CTBM0_INTR_SET	206
5.1.7 CTBM0_INTR_MASK	207
5.1.8 CTBM0_INTR_MASKED	208
5.1.9 CTBM0_DFT_CTRL	209
5.1.10 CTBM0_OA0_SW	210
5.1.11 CTBM0_OA0_SW_CLEAR	211
5.1.12 CTBM0_OA1_SW	212
5.1.13 CTBM0_OA1_SW_CLEAR	213
5.1.14 CTBM0_CTB_SW_HW_CTRL	214
5.1.15 CTBM0_CTB_SW_STATUS	215
5.1.16 CTBM0_OA0_OFFSET_TRIM	216
5.1.17 CTBM0_OA0_SLOPE_OFFSET_TRIM	217
5.1.18 CTBM0_OA0_COMP_TRIM	218
5.1.19 CTBM0_OA1_OFFSET_TRIM	219
5.1.20 CTBM0_OA1_SLOPE_OFFSET_TRIM	220
5.1.21 CTBM0_OA1_COMP_TRIM	221
6. Deep Sleep Amplifier Bias (DSAB) Registers	222
6.1 Register Details	222
6.1.1 PASS_DSAB_DSAB_CTRL	223
6.1.2 PASS_DSAB_DSAB_DFT	225
7. GPIO - Common Registers	226
7.1 Register Details	226
7.1.1 GPIO_INTR_CAUSE	227
8. GPIO - Port Specific Registers	228
8.1 Register Details	228
8.1.1 GPIO_PRT0_DR	230
8.1.2 GPIO_PRT0_PS	231
8.1.3 GPIO_PRT0_PC	233
8.1.4 GPIO_PRT0_INTR_CFG	235
8.1.5 GPIO_PRT0_INTR	237
8.1.6 GPIO_PRT0_PC2	239
8.1.7 GPIO_PRT0_DR_SET	241
8.1.8 GPIO_PRT0_DR_CLR	242
8.1.9 GPIO_PRT0_DR_INV	243
8.1.10 GPIO_PRT1_DR	244
8.1.11 GPIO_PRT1_PS	245
8.1.12 GPIO_PRT1_PC	247
8.1.13 GPIO_PRT1_INTR_CFG	249
8.1.14 GPIO_PRT1_INTR	251
8.1.15 GPIO_PRT1_PC2	253
8.1.16 GPIO_PRT1_DR_SET	255

8.1.17	GPIO_PRT1_DR_CLR	256
8.1.18	GPIO_PRT1_DR_INV	257
8.1.19	GPIO_PRT2_DR	258
8.1.20	GPIO_PRT2_PS	259
8.1.21	GPIO_PRT2_PC	261
8.1.22	GPIO_PRT2_INTR_CFG	263
8.1.23	GPIO_PRT2_INTR	265
8.1.24	GPIO_PRT2_PC2	267
8.1.25	GPIO_PRT2_DR_SET	269
8.1.26	GPIO_PRT2_DR_CLR	270
8.1.27	GPIO_PRT2_DR_INV	271
8.1.28	GPIO_PRT3_DR	272
8.1.29	GPIO_PRT3_PS	273
8.1.30	GPIO_PRT3_PC	275
8.1.31	GPIO_PRT3_INTR_CFG	277
8.1.32	GPIO_PRT3_INTR	279
8.1.33	GPIO_PRT3_PC2	281
8.1.34	GPIO_PRT3_DR_SET	283
8.1.35	GPIO_PRT3_DR_CLR	284
8.1.36	GPIO_PRT3_DR_INV	285
8.1.37	GPIO_PRT4_DR	286
8.1.38	GPIO_PRT4_PS	287
8.1.39	GPIO_PRT4_PC	288
8.1.40	GPIO_PRT4_INTR_CFG	290
8.1.41	GPIO_PRT4_INTR	292
8.1.42	GPIO_PRT4_PC2	294
8.1.43	GPIO_PRT4_DR_SET	295
8.1.44	GPIO_PRT4_DR_CLR	296
8.1.45	GPIO_PRT4_DR_INV	297
9. High Speed IO Matrix (HSIOM) Registers		298
9.1	Register Details	298
9.1.1	HSIOM_AMUX_SPLIT_CTL0	299
9.1.2	HSIOM_AMUX_SPLIT_CTL1	301
10. HSIOM - Port Specific Registers		303
10.1	Register Details	303
10.1.1	HSIOM_PORT_SEL0	304
10.1.2	HSIOM_PORT_SEL1	306
10.1.3	HSIOM_PORT_SEL2	308
10.1.4	HSIOM_PORT_SEL3	310
10.1.5	HSIOM_PORT_SEL4	312
11. LCD Registers		314
11.1	Register Details	314
11.1.1	LCD_ID	315
11.1.2	LCD_DIVIDER	316
11.1.3	LCD_CONTROL	317
11.1.4	LCD_DATA00	319
11.1.5	LCD_DATA01	320
11.1.6	LCD_DATA02	321
11.1.7	LCD_DATA03	322
11.1.8	LCD_DATA04	323

11.1.9	LCD_DATA10	324
11.1.10	LCD_DATA11	325
11.1.11	LCD_DATA12	326
11.1.12	LCD_DATA13	327
11.1.13	LCD_DATA14	328
12. Low Power Comparator (LPCOMP) Registers		329
12.1	Register Details	329
12.1.1	LPCOMP_ID	330
12.1.2	LPCOMP_CONFIG	331
12.1.3	LPCOMP_INTR	334
12.1.4	LPCOMP_INTR_SET	335
12.1.5	LPCOMP_INTR_MASK	336
12.1.6	LPCOMP_INTR_MASKED	337
12.1.7	LPCOMP_TRIM1	338
12.1.8	LPCOMP_TRIM2	339
12.1.9	LPCOMP_TRIM3	340
12.1.10	LPCOMP_TRIM4	341
13. PASS MMIO Registers		342
13.1	Register Details	342
13.1.1	PASS_INTR_CAUSE	343
13.1.2	PASS_DFT_CTRL	344
13.1.3	PASS_PASS_CTRL	345
13.1.4	PASS_DSAB_TRIM	346
14. Peripheral Interconnect (PERI) Registers		347
14.1	Register Details	347
14.1.1	PERI_DIV_CMD	348
14.1.2	PERI_PCLK_CTL0	350
14.1.3	PERI_PCLK_CTL1	351
14.1.4	PERI_PCLK_CTL2	352
14.1.5	PERI_PCLK_CTL3	353
14.1.6	PERI_PCLK_CTL4	354
14.1.7	PERI_PCLK_CTL5	355
14.1.8	PERI_PCLK_CTL6	356
14.1.9	PERI_PCLK_CTL7	357
14.1.10	PERI_PCLK_CTL8	358
14.1.11	PERI_PCLK_CTL9	359
14.1.12	PERI_PCLK_CTL10	360
14.1.13	PERI_PCLK_CTL11	361
14.1.14	PERI_PCLK_CTL12	362
14.1.15	PERI_DIV_16_CTL0	363
14.1.16	PERI_DIV_16_CTL1	364
14.1.17	PERI_DIV_16_CTL2	365
14.1.18	PERI_DIV_16_CTL3	366
14.1.19	PERI_DIV_16_CTL4	367
14.1.20	PERI_DIV_16_CTL5	368
14.1.21	PERI_DIV_16_5_CTL0	369
14.1.22	PERI_DIV_16_5_CTL1	371
14.1.23	PERI_DIV_16_5_CTL2	373
14.1.24	PERI_TR_CTL	375

15. Programmable IO (PRGIO) Registers 377

15.1	Register Details	377
15.1.1	PRGIO_PRT0_CTL	379
15.1.2	PRGIO_PRT0_SYNC_CTL	381
15.1.3	PRGIO_PRT0_LUT_SEL0	382
15.1.4	PRGIO_PRT0_LUT_SEL1	384
15.1.5	PRGIO_PRT0_LUT_SEL2	386
15.1.6	PRGIO_PRT0_LUT_SEL3	388
15.1.7	PRGIO_PRT0_LUT_SEL4	390
15.1.8	PRGIO_PRT0_LUT_SEL5	392
15.1.9	PRGIO_PRT0_LUT_SEL6	394
15.1.10	PRGIO_PRT0_LUT_SEL7	396
15.1.11	PRGIO_PRT0_LUT_CTL0	398
15.1.12	PRGIO_PRT0_LUT_CTL1	400
15.1.13	PRGIO_PRT0_LUT_CTL2	402
15.1.14	PRGIO_PRT0_LUT_CTL3	404
15.1.15	PRGIO_PRT0_LUT_CTL4	406
15.1.16	PRGIO_PRT0_LUT_CTL5	408
15.1.17	PRGIO_PRT0_LUT_CTL6	410
15.1.18	PRGIO_PRT0_LUT_CTL7	412
15.1.19	PRGIO_PRT0_DU_SEL	414
15.1.20	PRGIO_PRT0_DU_CTL	416
15.1.21	PRGIO_PRT0_DATA	417
15.1.22	PRGIO_PRT1_CTL	418
15.1.23	PRGIO_PRT1_SYNC_CTL	420
15.1.24	PRGIO_PRT1_LUT_SEL0	421
15.1.25	PRGIO_PRT1_LUT_SEL1	423
15.1.26	PRGIO_PRT1_LUT_SEL2	425
15.1.27	PRGIO_PRT1_LUT_SEL3	427
15.1.28	PRGIO_PRT1_LUT_SEL4	429
15.1.29	PRGIO_PRT1_LUT_SEL5	431
15.1.30	PRGIO_PRT1_LUT_SEL6	433
15.1.31	PRGIO_PRT1_LUT_SEL7	435
15.1.32	PRGIO_PRT1_LUT_CTL0	437
15.1.33	PRGIO_PRT1_LUT_CTL1	439
15.1.34	PRGIO_PRT1_LUT_CTL2	441
15.1.35	PRGIO_PRT1_LUT_CTL3	443
15.1.36	PRGIO_PRT1_LUT_CTL4	445
15.1.37	PRGIO_PRT1_LUT_CTL5	447
15.1.38	PRGIO_PRT1_LUT_CTL6	449
15.1.39	PRGIO_PRT1_LUT_CTL7	451
15.1.40	PRGIO_PRT1_DU_SEL	453
15.1.41	PRGIO_PRT1_DU_CTL	455
15.1.42	PRGIO_PRT1_DATA	456

16. CoreSight ROM Table Registers 457

16.1	Register Details	457
16.1.1	ROMTABLE_ADDR	458
16.1.2	ROMTABLE_DID	459
16.1.3	ROMTABLE_PID4	460
16.1.4	ROMTABLE_PID5	461
16.1.5	ROMTABLE_PID6	462
16.1.6	ROMTABLE_PID7	463
16.1.7	ROMTABLE_PID0	464

16.1.8	ROMTABLE_PID1	465
16.1.9	ROMTABLE_PID2	466
16.1.10	ROMTABLE_PID3	467
16.1.11	ROMTABLE_CID0	468
16.1.12	ROMTABLE_CID1	469
16.1.13	ROMTABLE_CID2	470
16.1.14	ROMTABLE_CID3	471

17. SAR Registers 472

17.1	Register Details	472
17.1.1	SAR_CTRL	475
17.1.2	SAR_SAMPLE_CTRL	478
17.1.3	SAR_SAMPLE_TIME01	480
17.1.4	SAR_SAMPLE_TIME23	481
17.1.5	SAR_RANGE_THRES	482
17.1.6	SAR_RANGE_COND	483
17.1.7	SAR_CHAN_EN	484
17.1.8	SAR_START_CTRL	485
17.1.9	SAR_DFT_CTRL	486
17.1.10	SAR_CHAN_CONFIG0	488
17.1.11	SAR_CHAN_CONFIG1	490
17.1.12	SAR_CHAN_CONFIG2	492
17.1.13	SAR_CHAN_CONFIG3	494
17.1.14	SAR_CHAN_CONFIG4	496
17.1.15	SAR_CHAN_CONFIG5	498
17.1.16	SAR_CHAN_CONFIG6	500
17.1.17	SAR_CHAN_CONFIG7	502
17.1.18	SAR_CHAN_CONFIG8	504
17.1.19	SAR_CHAN_CONFIG9	506
17.1.20	SAR_CHAN_CONFIG10	508
17.1.21	SAR_CHAN_CONFIG11	510
17.1.22	SAR_CHAN_CONFIG12	512
17.1.23	SAR_CHAN_CONFIG13	514
17.1.24	SAR_CHAN_CONFIG14	516
17.1.25	SAR_CHAN_CONFIG15	518
17.1.26	SAR_CHAN_WORK0	520
17.1.27	SAR_CHAN_WORK1	521
17.1.28	SAR_CHAN_WORK2	522
17.1.29	SAR_CHAN_WORK3	523
17.1.30	SAR_CHAN_WORK4	524
17.1.31	SAR_CHAN_WORK5	525
17.1.32	SAR_CHAN_WORK6	526
17.1.33	SAR_CHAN_WORK7	527
17.1.34	SAR_CHAN_WORK8	528
17.1.35	SAR_CHAN_WORK9	529
17.1.36	SAR_CHAN_WORK10	530
17.1.37	SAR_CHAN_WORK11	531
17.1.38	SAR_CHAN_WORK12	532
17.1.39	SAR_CHAN_WORK13	533
17.1.40	SAR_CHAN_WORK14	534
17.1.41	SAR_CHAN_WORK15	535
17.1.42	SAR_CHAN_RESULT0	536
17.1.43	SAR_CHAN_RESULT1	537
17.1.44	SAR_CHAN_RESULT2	538

17.1.45	SAR_CHAN_RESULT3	539
17.1.46	SAR_CHAN_RESULT4	540
17.1.47	SAR_CHAN_RESULT5	541
17.1.48	SAR_CHAN_RESULT6	542
17.1.49	SAR_CHAN_RESULT7	543
17.1.50	SAR_CHAN_RESULT8	544
17.1.51	SAR_CHAN_RESULT9	545
17.1.52	SAR_CHAN_RESULT10	546
17.1.53	SAR_CHAN_RESULT11	547
17.1.54	SAR_CHAN_RESULT12	548
17.1.55	SAR_CHAN_RESULT13	549
17.1.56	SAR_CHAN_RESULT14	550
17.1.57	SAR_CHAN_RESULT15	551
17.1.58	SAR_CHAN_WORK_VALID	552
17.1.59	SAR_CHAN_RESULT_VALID	553
17.1.60	SAR_STATUS	554
17.1.61	SAR_AVG_STAT	555
17.1.62	SAR_INTR	556
17.1.63	SAR_INTR_SET	558
17.1.64	SAR_INTR_MASK	560
17.1.65	SAR_INTR_MASKED	562
17.1.66	SAR_SATURATE_INTR	564
17.1.67	SAR_SATURATE_INTR_SET	565
17.1.68	SAR_SATURATE_INTR_MASK	566
17.1.69	SAR_SATURATE_INTR_MASKED	567
17.1.70	SAR_RANGE_INTR	568
17.1.71	SAR_RANGE_INTR_SET	569
17.1.72	SAR_RANGE_INTR_MASK	570
17.1.73	SAR_RANGE_INTR_MASKED	571
17.1.74	SAR_INTR_CAUSE	572
17.1.75	SAR_INJ_CHAN_CONFIG	574
17.1.76	SAR_INJ_RESULT	576
17.1.77	SAR_MUX_SWITCH0	577
17.1.78	SAR_MUX_SWITCH_CLEAR0	580
17.1.79	SAR_MUX_SWITCH1	583
17.1.80	SAR_MUX_SWITCH_CLEAR1	584
17.1.81	SAR_MUX_SWITCH_HW_CTRL	585
17.1.82	SAR_MUX_SWITCH_STATUS	587
17.1.83	SAR_PUMP_CTRL	589
17.1.84	SAR_ANA_TRIM	590
17.1.85	SAR_WOUNDING	591

18. Serial Communication Block (SCB) Registers 592

18.1	Register Details	592
18.1.1	SCB0_CTRL	598
18.1.2	SCB0_STATUS	602
18.1.3	SCB0_SPI_CTRL	603
18.1.4	SCB0_SPI_STATUS	606
18.1.5	SCB0_UART_CTRL	607
18.1.6	SCB0_UART_TX_CTRL	608
18.1.7	SCB0_UART_RX_CTRL	609
18.1.8	SCB0_UART_RX_STATUS	612
18.1.9	SCB0_UART_FLOW_CTRL	613
18.1.10	SCB0_I2C_CTRL	615

18.1.11	SCB0_I2C_STATUS	618
18.1.12	SCB0_I2C_M_CMD	620
18.1.13	SCB0_I2C_S_CMD	622
18.1.14	SCB0_I2C_CFG	623
18.1.15	SCB0_TX_CTRL	625
18.1.16	SCB0_TX_FIFO_CTRL	626
18.1.17	SCB0_TX_FIFO_STATUS	627
18.1.18	SCB0_TX_FIFO_WR	628
18.1.19	SCB0_RX_CTRL	629
18.1.20	SCB0_RX_FIFO_CTRL	630
18.1.21	SCB0_RX_FIFO_STATUS	631
18.1.22	SCB0_RX_MATCH	632
18.1.23	SCB0_RX_FIFO_RD	633
18.1.24	SCB0_RX_FIFO_RD_SILENT	634
18.1.25	SCB0_EZ_DATA0	635
18.1.26	SCB0_EZ_DATA1	636
18.1.27	SCB0_EZ_DATA2	637
18.1.28	SCB0_EZ_DATA3	638
18.1.29	SCB0_EZ_DATA4	639
18.1.30	SCB0_EZ_DATA5	640
18.1.31	SCB0_EZ_DATA6	641
18.1.32	SCB0_EZ_DATA7	642
18.1.33	SCB0_EZ_DATA8	643
18.1.34	SCB0_EZ_DATA9	644
18.1.35	SCB0_EZ_DATA10	645
18.1.36	SCB0_EZ_DATA11	646
18.1.37	SCB0_EZ_DATA12	647
18.1.38	SCB0_EZ_DATA13	648
18.1.39	SCB0_EZ_DATA14	649
18.1.40	SCB0_EZ_DATA15	650
18.1.41	SCB0_EZ_DATA16	651
18.1.42	SCB0_EZ_DATA17	652
18.1.43	SCB0_EZ_DATA18	653
18.1.44	SCB0_EZ_DATA19	654
18.1.45	SCB0_EZ_DATA20	655
18.1.46	SCB0_EZ_DATA21	656
18.1.47	SCB0_EZ_DATA22	657
18.1.48	SCB0_EZ_DATA23	658
18.1.49	SCB0_EZ_DATA24	659
18.1.50	SCB0_EZ_DATA25	660
18.1.51	SCB0_EZ_DATA26	661
18.1.52	SCB0_EZ_DATA27	662
18.1.53	SCB0_EZ_DATA28	663
18.1.54	SCB0_EZ_DATA29	664
18.1.55	SCB0_EZ_DATA30	665
18.1.56	SCB0_EZ_DATA31	666
18.1.57	SCB0_INTR_CAUSE	667
18.1.58	SCB0_INTR_I2C_EC	668
18.1.59	SCB0_INTR_I2C_EC_MASK	670
18.1.60	SCB0_INTR_I2C_EC_MASKED	671
18.1.61	SCB0_INTR_SPI_EC	672
18.1.62	SCB0_INTR_SPI_EC_MASK	674
18.1.63	SCB0_INTR_SPI_EC_MASKED	675
18.1.64	SCB0_INTR_M	676

18.1.65	SCB0_INTR_M_SET	677
18.1.66	SCB0_INTR_M_MASK	678
18.1.67	SCB0_INTR_M_MASKED	679
18.1.68	SCB0_INTR_S	680
18.1.69	SCB0_INTR_S_SET	682
18.1.70	SCB0_INTR_S_MASK	684
18.1.71	SCB0_INTR_S_MASKED	686
18.1.72	SCB0_INTR_TX	688
18.1.73	SCB0_INTR_TX_SET	690
18.1.74	SCB0_INTR_TX_MASK	692
18.1.75	SCB0_INTR_TX_MASKED	694
18.1.76	SCB0_INTR_RX	696
18.1.77	SCB0_INTR_RX_SET	698
18.1.78	SCB0_INTR_RX_MASK	700
18.1.79	SCB0_INTR_RX_MASKED	702
18.1.80	SCB1_CTRL	704
18.1.81	SCB1_STATUS	708
18.1.82	SCB1_SPI_CTRL	709
18.1.83	SCB1_SPI_STATUS	712
18.1.84	SCB1_UART_CTRL	713
18.1.85	SCB1_UART_TX_CTRL	714
18.1.86	SCB1_UART_RX_CTRL	715
18.1.87	SCB1_UART_RX_STATUS	718
18.1.88	SCB1_UART_FLOW_CTRL	719
18.1.89	SCB1_I2C_CTRL	721
18.1.90	SCB1_I2C_STATUS	724
18.1.91	SCB1_I2C_M_CMD	726
18.1.92	SCB1_I2C_S_CMD	728
18.1.93	SCB1_I2C_CFG	729
18.1.94	SCB1_TX_CTRL	731
18.1.95	SCB1_TX_FIFO_CTRL	732
18.1.96	SCB1_TX_FIFO_STATUS	733
18.1.97	SCB1_TX_FIFO_WR	734
18.1.98	SCB1_RX_CTRL	735
18.1.99	SCB1_RX_FIFO_CTRL	736
18.1.100	SCB1_RX_FIFO_STATUS	737
18.1.101	SCB1_RX_MATCH	738
18.1.102	SCB1_RX_FIFO_RD	739
18.1.103	SCB1_RX_FIFO_RD_SILENT	740
18.1.104	SCB1_EZ_DATA0	741
18.1.105	SCB1_EZ_DATA1	742
18.1.106	SCB1_EZ_DATA2	743
18.1.107	SCB1_EZ_DATA3	744
18.1.108	SCB1_EZ_DATA4	745
18.1.109	SCB1_EZ_DATA5	746
18.1.110	SCB1_EZ_DATA6	747
18.1.111	SCB1_EZ_DATA7	748
18.1.112	SCB1_EZ_DATA8	749
18.1.113	SCB1_EZ_DATA9	750
18.1.114	SCB1_EZ_DATA10	751
18.1.115	SCB1_EZ_DATA11	752
18.1.116	SCB1_EZ_DATA12	753
18.1.117	SCB1_EZ_DATA13	754
18.1.118	SCB1_EZ_DATA14	755

18.1.119	SCB1_EZ_DATA15	756
18.1.120	SCB1_EZ_DATA16	757
18.1.121	SCB1_EZ_DATA17	758
18.1.122	SCB1_EZ_DATA18	759
18.1.123	SCB1_EZ_DATA19	760
18.1.124	SCB1_EZ_DATA20	761
18.1.125	SCB1_EZ_DATA21	762
18.1.126	SCB1_EZ_DATA22	763
18.1.127	SCB1_EZ_DATA23	764
18.1.128	SCB1_EZ_DATA24	765
18.1.129	SCB1_EZ_DATA25	766
18.1.130	SCB1_EZ_DATA26	767
18.1.131	SCB1_EZ_DATA27	768
18.1.132	SCB1_EZ_DATA28	769
18.1.133	SCB1_EZ_DATA29	770
18.1.134	SCB1_EZ_DATA30	771
18.1.135	SCB1_EZ_DATA31	772
18.1.136	SCB1_INTR_CAUSE	773
18.1.137	SCB1_INTR_I2C_EC	774
18.1.138	SCB1_INTR_I2C_EC_MASK	776
18.1.139	SCB1_INTR_I2C_EC_MASKED	777
18.1.140	SCB1_INTR_SPI_EC	778
18.1.141	SCB1_INTR_SPI_EC_MASK	780
18.1.142	SCB1_INTR_SPI_EC_MASKED	781
18.1.143	SCB1_INTR_M	782
18.1.144	SCB1_INTR_M_SET	783
18.1.145	SCB1_INTR_M_MASK	784
18.1.146	SCB1_INTR_M_MASKED	785
18.1.147	SCB1_INTR_S	786
18.1.148	SCB1_INTR_S_SET	788
18.1.149	SCB1_INTR_S_MASK	790
18.1.150	SCB1_INTR_S_MASKED	792
18.1.151	SCB1_INTR_TX	794
18.1.152	SCB1_INTR_TX_SET	796
18.1.153	SCB1_INTR_TX_MASK	798
18.1.154	SCB1_INTR_TX_MASKED	800
18.1.155	SCB1_INTR_RX	802
18.1.156	SCB1_INTR_RX_SET	804
18.1.157	SCB1_INTR_RX_MASK	806
18.1.158	SCB1_INTR_RX_MASKED	808
18.1.159	SCB2_CTRL	810
18.1.160	SCB2_STATUS	814
18.1.161	SCB2_SPI_CTRL	815
18.1.162	SCB2_SPI_STATUS	818
18.1.163	SCB2_UART_CTRL	819
18.1.164	SCB2_UART_TX_CTRL	820
18.1.165	SCB2_UART_RX_CTRL	821
18.1.166	SCB2_UART_RX_STATUS	824
18.1.167	SCB2_UART_FLOW_CTRL	825
18.1.168	SCB2_I2C_CTRL	827
18.1.169	SCB2_I2C_STATUS	830
18.1.170	SCB2_I2C_M_CMD	832
18.1.171	SCB2_I2C_S_CMD	834
18.1.172	SCB2_I2C_CFG	835

18.1.173	SCB2_TX_CTRL	837
18.1.174	SCB2_TX_FIFO_CTRL	838
18.1.175	SCB2_TX_FIFO_STATUS	839
18.1.176	SCB2_TX_FIFO_WR	840
18.1.177	SCB2_RX_CTRL	841
18.1.178	SCB2_RX_FIFO_CTRL	842
18.1.179	SCB2_RX_FIFO_STATUS	843
18.1.180	SCB2_RX_MATCH	844
18.1.181	SCB2_RX_FIFO_RD	845
18.1.182	SCB2_RX_FIFO_RD_SILENT	846
18.1.183	SCB2_EZ_DATA0	847
18.1.184	SCB2_EZ_DATA1	848
18.1.185	SCB2_EZ_DATA2	849
18.1.186	SCB2_EZ_DATA3	850
18.1.187	SCB2_EZ_DATA4	851
18.1.188	SCB2_EZ_DATA5	852
18.1.189	SCB2_EZ_DATA6	853
18.1.190	SCB2_EZ_DATA7	854
18.1.191	SCB2_EZ_DATA8	855
18.1.192	SCB2_EZ_DATA9	856
18.1.193	SCB2_EZ_DATA10	857
18.1.194	SCB2_EZ_DATA11	858
18.1.195	SCB2_EZ_DATA12	859
18.1.196	SCB2_EZ_DATA13	860
18.1.197	SCB2_EZ_DATA14	861
18.1.198	SCB2_EZ_DATA15	862
18.1.199	SCB2_EZ_DATA16	863
18.1.200	SCB2_EZ_DATA17	864
18.1.201	SCB2_EZ_DATA18	865
18.1.202	SCB2_EZ_DATA19	866
18.1.203	SCB2_EZ_DATA20	867
18.1.204	SCB2_EZ_DATA21	868
18.1.205	SCB2_EZ_DATA22	869
18.1.206	SCB2_EZ_DATA23	870
18.1.207	SCB2_EZ_DATA24	871
18.1.208	SCB2_EZ_DATA25	872
18.1.209	SCB2_EZ_DATA26	873
18.1.210	SCB2_EZ_DATA27	874
18.1.211	SCB2_EZ_DATA28	875
18.1.212	SCB2_EZ_DATA29	876
18.1.213	SCB2_EZ_DATA30	877
18.1.214	SCB2_EZ_DATA31	878
18.1.215	SCB2_INTR_CAUSE	879
18.1.216	SCB2_INTR_I2C_EC	880
18.1.217	SCB2_INTR_I2C_EC_MASK	882
18.1.218	SCB2_INTR_I2C_EC_MASKED	883
18.1.219	SCB2_INTR_SPI_EC	884
18.1.220	SCB2_INTR_SPI_EC_MASK	886
18.1.221	SCB2_INTR_SPI_EC_MASKED	887
18.1.222	SCB2_INTR_M	888
18.1.223	SCB2_INTR_M_SET	889
18.1.224	SCB2_INTR_M_MASK	890
18.1.225	SCB2_INTR_M_MASKED	891
18.1.226	SCB2_INTR_S	892

18.1.227	SCB2_INTR_S_SET	894
18.1.228	SCB2_INTR_S_MASK	896
18.1.229	SCB2_INTR_S_MASKED	898
18.1.230	SCB2_INTR_TX	900
18.1.231	SCB2_INTR_TX_SET	902
18.1.232	SCB2_INTR_TX_MASK	904
18.1.233	SCB2_INTR_TX_MASKED	906
18.1.234	SCB2_INTR_RX	908
18.1.235	SCB2_INTR_RX_SET	910
18.1.236	SCB2_INTR_RX_MASK	912
18.1.237	SCB2_INTR_RX_MASKED	914

19. Supervisory Flash (SFLASH) Registers 916

19.1	Register Details	916
19.1.1	SFLASH_SILICON_ID	918
19.1.2	SFLASH_HIB_KEY_DELAY	919
19.1.3	SFLASH_DPSLP_KEY_DELAY	920
19.1.4	SFLASH_SWD_CONFIG	921
19.1.5	SFLASH_SWD_LISTEN	922
19.1.6	SFLASH_FLASH_START	923
19.1.7	SFLASH_CSDV2_CSD0_ADC_TRIM1	924
19.1.8	SFLASH_CSDV2_CSD0_ADC_TRIM2	925
19.1.9	SFLASH_SAR_TEMP_MULTIPLIER	926
19.1.10	SFLASH_SAR_TEMP_OFFSET	927
19.1.11	SFLASH_IMO_TCTRIM_LT0	928
19.1.12	SFLASH_IMO_TCTRIM_LT1	929
19.1.13	SFLASH_IMO_TCTRIM_LT2	930
19.1.14	SFLASH_IMO_TCTRIM_LT3	931
19.1.15	SFLASH_IMO_TCTRIM_LT4	932
19.1.16	SFLASH_IMO_TCTRIM_LT5	933
19.1.17	SFLASH_IMO_TCTRIM_LT6	934
19.1.18	SFLASH_IMO_TCTRIM_LT7	935
19.1.19	SFLASH_IMO_TCTRIM_LT8	936
19.1.20	SFLASH_IMO_TCTRIM_LT9	937
19.1.21	SFLASH_IMO_TCTRIM_LT10	938
19.1.22	SFLASH_IMO_TCTRIM_LT11	939
19.1.23	SFLASH_IMO_TCTRIM_LT12	940
19.1.24	SFLASH_IMO_TCTRIM_LT13	941
19.1.25	SFLASH_IMO_TCTRIM_LT14	942
19.1.26	SFLASH_IMO_TCTRIM_LT15	943
19.1.27	SFLASH_IMO_TCTRIM_LT16	944
19.1.28	SFLASH_IMO_TCTRIM_LT17	945
19.1.29	SFLASH_IMO_TCTRIM_LT18	946
19.1.30	SFLASH_IMO_TCTRIM_LT19	947
19.1.31	SFLASH_IMO_TCTRIM_LT20	948
19.1.32	SFLASH_IMO_TCTRIM_LT21	949
19.1.33	SFLASH_IMO_TCTRIM_LT22	950
19.1.34	SFLASH_IMO_TCTRIM_LT23	951
19.1.35	SFLASH_IMO_TCTRIM_LT24	952
19.1.36	SFLASH_IMO_TRIM_LT0	953
19.1.37	SFLASH_IMO_TRIM_LT1	954
19.1.38	SFLASH_IMO_TRIM_LT2	955
19.1.39	SFLASH_IMO_TRIM_LT3	956
19.1.40	SFLASH_IMO_TRIM_LT4	957

19.1.41	SFLASH_IMO_TRIM_LT5	958
19.1.42	SFLASH_IMO_TRIM_LT6	959
19.1.43	SFLASH_IMO_TRIM_LT7	960
19.1.44	SFLASH_IMO_TRIM_LT8	961
19.1.45	SFLASH_IMO_TRIM_LT9	962
19.1.46	SFLASH_IMO_TRIM_LT10	963
19.1.47	SFLASH_IMO_TRIM_LT11	964
19.1.48	SFLASH_IMO_TRIM_LT12	965
19.1.49	SFLASH_IMO_TRIM_LT13	966
19.1.50	SFLASH_IMO_TRIM_LT14	967
19.1.51	SFLASH_IMO_TRIM_LT15	968
19.1.52	SFLASH_IMO_TRIM_LT16	969
19.1.53	SFLASH_IMO_TRIM_LT17	970
19.1.54	SFLASH_IMO_TRIM_LT18	971
19.1.55	SFLASH_IMO_TRIM_LT19	972
19.1.56	SFLASH_IMO_TRIM_LT20	973
19.1.57	SFLASH_IMO_TRIM_LT21	974
19.1.58	SFLASH_IMO_TRIM_LT22	975
19.1.59	SFLASH_IMO_TRIM_LT23	976
19.1.60	SFLASH_IMO_TRIM_LT24	977
20. SPC Interface (SPCIF) Registers		978
20.1	Register Details	978
20.1.1	SPCIF_GEOMETRY	979
20.1.2	SPCIF_INTR	981
20.1.3	SPCIF_INTR_SET	982
20.1.4	SPCIF_INTR_MASK	983
20.1.5	SPCIF_INTR_MASKED	984
21. System Resources Sub System Registers		985
21.1	Register Details	985
21.1.1	PWR_CONTROL	986
21.1.2	PWR_KEY_DELAY	988
21.1.3	PWR_DDFT_SELECT	989
21.1.4	TST_MODE	992
21.1.5	CLK_SELECT	994
21.1.6	CLK_ILO_CONFIG	996
21.1.7	CLK_IMO_CONFIG	997
21.1.8	CLK_DFT_SELECT	998
21.1.9	WDT_DISABLE_KEY	1001
21.1.10	WDT_COUNTER	1002
21.1.11	WDT_MATCH	1003
21.1.12	SRSS_INTR	1004
21.1.13	SRSS_INTR_SET	1005
21.1.14	SRSS_INTR_MASK	1006
21.1.15	RES_CAUSE	1007
21.1.16	CLK_IMO_SELECT	1008
21.1.17	CLK_IMO_TRIM1	1009
21.1.18	CLK_IMO_TRIM2	1010
21.1.19	PWR_PWRSYS_TRIM1	1011
21.1.20	CLK_IMO_TRIM3	1012

22. Timer, Counter, PWM (TCPWM) Registers	1013
22.1 Register Details	1013
22.1.1 TCPWM_CTRL	1014
22.1.2 TCPWM_CMD	1015
22.1.3 TCPWM_INTR_CAUSE	1016
23. PERI Trigger Group Control Registers	1017
23.1 Register Details	1017
23.1.1 PERI_TR_GROUP0_TR_OUT_CTL0	1018
23.1.2 PERI_TR_GROUP0_TR_OUT_CTL1	1019
23.1.3 PERI_TR_GROUP0_TR_OUT_CTL2	1020
23.1.4 PERI_TR_GROUP0_TR_OUT_CTL3	1021
23.1.5 PERI_TR_GROUP0_TR_OUT_CTL4	1022
23.1.6 PERI_TR_GROUP0_TR_OUT_CTL5	1023
23.1.7 PERI_TR_GROUP0_TR_OUT_CTL6	1024
23.1.8 PERI_TR_GROUP1_TR_OUT_CTL	1025
24. Watch Crystal Oscillator (WCO) Registers	1026
24.1 Register Details	1026
24.1.1 WCO_CONFIG	1027
24.1.2 WCO_STATUS	1029
24.1.3 WCO_DPLL	1030
24.1.4 WCO_WDT_CTLLOW	1032
24.1.5 WCO_WDT_CTRHIGH	1033
24.1.6 WCO_WDT_MATCH	1034
24.1.7 WCO_WDT_CONFIG	1035
24.1.8 WCO_WDT_CONTROL	1037
24.1.9 WCO_WDT_CLKEN	1039
24.1.10 WCO_TRIM	1040
Revision History	1041

Register Mapping



The Register Mapping section discusses the registers and lists all the registers in mapping tables, in address order. For Architecture details, refer to [PSoC 4100S Family PSoC 4 Architecture Technical Reference Manual \(TRM\)](#).

Register General Conventions

The register conventions specific to this section and the Register Reference chapter are listed in this table.

Convention	Example	Description
'x' in a register name	ACBxxCR1	Multiple instances/address ranges of the same register
R	R : 00	Read register or bit(s)
W	W : 00	Write register or bit(s)
WOC	WOC:0	Write one to clear
WZC	WZC:0	Write zero to clear
RC	RC:0	Read to clear
WC	WC:0	Write to clear
NA	NA:000	Reserved
U	R:U	Undefined
00	RW : 00	Reset value is 0x00
XX	RW : XX	Register is not reset

Acronyms

This table lists the acronyms used in this document

Table 3-1. Acronyms

Symbol	Unit of Measure
ABUS	analog output bus
AC	alternating current
ADC	analog-to-digital converter
AHB	AMBA (advanced microcontroller bus architecture) high-performance bus, an ARM data transfer bus
API	application programming interface
APOR	analog power-on reset
BC	broadcast clock
BOM	bill of materials
BR	bit rate
BRA	bus request acknowledge
BRQ	bus request
CAN	controller area network
CI	carry in
CMP	compare
CO	carry out

Table 3-1. Acronyms

Symbol	Unit of Measure
CPU	central processing unit
CRC	cyclic redundancy check
CSD	CapSense sigma delta
CT	continuous time
DAC	digital-to-analog converter
DC	direct current
DI	digital or data input
DMA	direct memory access
DNL	differential nonlinearity
DO	digital or data output
DSI	digital signal interface
DSM	deep-sleep mode
ECO	external crystal oscillator
EEPROM	electrically erasable programmable read only memory
EMIF	external memory interface
FB	feedback
FIFO	first in first out
FSR	full scale range
GPIO	general purpose I/O
HCI	host-controller interface
HFCLK	high-frequency clock
I ² C	inter-integrated circuit
IDE	integrated development environment
ILO	internal low-speed oscillator
IMO	internal main oscillator
INL	integral nonlinearity
I/O	input/output
IOR	I/O read
IOW	I/O write
IRES	initial power on reset
IRA	interrupt request acknowledge
IRQ	interrupt request
ISR	interrupt service routine
IVR	interrupt vector read
L2CAP	logical link control and adaptation protocol
LRb	last received bit
LRB	last received byte
LSb	least significant bit
LSB	least significant byte
LUT	lookup table
MISO	master-in-slave-out
MMIO	memory mapped input/output
MOSI	master-out-slave-in
MSb	most significant bit

Table 3-1. Acronyms

Symbol	Unit of Measure
MSB	most significant byte
PC	program counter
PCH	program counter high
PCL	program counter low
PD	power down
PGA	programmable gain amplifier
PM	power management
PMA	PSoC memory arbiter
POR	power-on reset
PPOR	precision power-on reset
PRS	pseudo random sequence
PSoC®	Programmable System-on-Chip
PSRR	power supply rejection ratio
PSSDC	power system sleep duty cycle
PWM	pulse width modulator
RAM	random-access memory
RETI	return from interrupt
RF	radio frequency
ROM	read only memory
RW	read/write
SAR	successive approximation register
SC	switched capacitor
SCB	serial communication block
SIE	serial interface engine
SIO	special I/O
SE0	single-ended zero
SNR	signal-to-noise ratio
SOF	start of frame
SOI	start of instruction
SP	stack pointer
SPD	sequential phase detector
SPI	serial peripheral interconnect
SPIM	serial peripheral interconnect master
SPIS	serial peripheral interconnect slave
SRAM	static random-access memory
SROM	supervisory read only memory
SSADC	single slope ADC
SSC	supervisory system call
SYSCLK	system clock
SWD	single wire debug
TC	terminal count
TD	transaction descriptors
UART	universal asynchronous receiver/transmitter
UDB	universal digital block

Table 3-1. Acronyms

Symbol	Unit of Measure
USB	universal serial bus
USBIO	USB I/O
WCO	watch crystal oscillator
WDT	watchdog timer
WDR	watchdog reset
XRES	external reset
XRES_N	external reset, active low

1 Cortex M0+ (CM0+) Registers



This section discusses the CM0+ registers. It lists all the registers in mapping tables, in address order.

1.1 Register Details

Register Name	Address
CM0P_DWT_PID4	0xE0001FD0
CM0P_DWT_PID0	0xE0001FE0
CM0P_DWT_PID1	0xE0001FE4
CM0P_DWT_PID2	0xE0001FE8
CM0P_DWT_PID3	0xE0001FEC
CM0P_DWT_CID0	0xE0001FF0
CM0P_DWT_CID1	0xE0001FF4
CM0P_DWT_CID2	0xE0001FF8
CM0P_DWT_CID3	0xE0001FFC
CM0P_BP_PID4	0xE0002FD0
CM0P_BP_PID0	0xE0002FE0
CM0P_BP_PID1	0xE0002FE4
CM0P_BP_PID2	0xE0002FE8
CM0P_BP_PID3	0xE0002FEC
CM0P_BP_CID0	0xE0002FF0
CM0P_BP_CID1	0xE0002FF4
CM0P_BP_CID2	0xE0002FF8
CM0P_BP_CID3	0xE0002FFC
CM0P_SYST_CSR	0xE000E010
CM0P_SYST_RVR	0xE000E014
CM0P_SYST_CVR	0xE000E018
CM0P_SYST_CALIB	0xE000E01C
CM0P_ISER	0xE000E100
CM0P_ICER	0xE000E180
CM0P_ISPR	0xE000E200
CM0P_ICPR	0xE000E280
CM0P_IPR0	0xE000E400

Register Name	Address
CM0P_IPR1	0xE000E404
CM0P_IPR2	0xE000E408
CM0P_IPR3	0xE000E40C
CM0P_IPR4	0xE000E410
CM0P_IPR5	0xE000E414
CM0P_IPR6	0xE000E418
CM0P_IPR7	0xE000E41C
CM0P_CPUID	0xE000ED00
CM0P_ICSR	0xE000ED04
CM0P_AIRCR	0xE000ED0C
CM0P_SCR	0xE000ED10
CM0P_CCR	0xE000ED14
CM0P_SHPR2	0xE000ED1C
CM0P_SHPR3	0xE000ED20
CM0P_SHCSR	0xE000ED24
CM0P_SCS_PID4	0xE000EFD0
CM0P_SCS_PID0	0xE000EFE0
CM0P_SCS_PID1	0xE000EFE4
CM0P_SCS_PID2	0xE000EFE8
CM0P_SCS_PID3	0xE000EFEC
CM0P_SCS_CID0	0xE000EFF0
CM0P_SCS_CID1	0xE000EFF4
CM0P_SCS_CID2	0xE000EFF8
CM0P_SCS_CID3	0xE000EFFC
CM0P_ROM_SCS	0xE00FF000
CM0P_ROM_DWT	0xE00FF004
CM0P_ROM_BPU	0xE00FF008
CM0P_ROM_END	0xE00FF00C
CM0P_ROM_CSMT	0xE00FF0CC
CM0P_ROM_PID4	0xE00FFFD0
CM0P_ROM_PID0	0xE00FFFE0
CM0P_ROM_PID1	0xE00FFFE4
CM0P_ROM_PID2	0xE00FFFE8
CM0P_ROM_PID3	0xE00FF FEC
CM0P_ROM_CID0	0xE00FFFF0
CM0P_ROM_CID1	0xE00FFFF4
CM0P_ROM_CID2	0xE00FFFF8
CM0P_ROM_CID3	0xE00FFFFC

1.1.1 CM0P_DWT_PID4

Watchpoint Unit CoreSight ROM Table Peripheral ID #4

Address: 0xE0001FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.2 CM0P_DWT_PID0

Watchpoint Unit CoreSight ROM Table Peripheral ID #0

Address: 0xE0001FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 10

1.1.3 CM0P_DWT_PID1

Watchpoint Unit CoreSight ROM Table Peripheral ID #1

Address: 0xE0001FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

1.1.4 CM0P_DWT_PID2

Watchpoint Unit CoreSight ROM Table Peripheral ID #2

Address: 0xE0001FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.5 CM0P_DWT_PID3

Watchpoint Unit CoreSight ROM Table Peripheral ID #3

Address: 0xE0001FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.6 CM0P_DWT_CID0

Watchpoint Unit CoreSight ROM Table Component ID #0

Address: 0xE0001FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.7 CM0P_DWT_CID1

Watchpoint Unit CoreSight ROM Table Component ID #1

Address: 0xE0001FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

1.1.8 CM0P_DWT_CID2

Watchpoint Unit CoreSight ROM Table Component ID #2

Address: 0xE0001FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.9 CM0P_DWT_CID3

Watchpoint Unit CoreSight ROM Table Component ID #3

Address: 0xE0001FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

1.1.10 CM0P_BP_PID4

Breakpoint Unit CoreSight ROM Table Peripheral ID #4

Address: 0xE0002FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.11 CM0P_BP_PID0

Breakpoint Unit CoreSight ROM Table Peripheral ID #0

Address: 0xE0002FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 11

1.1.12 CM0P_BP_PID1

Breakpoint Unit CoreSight ROM Table Peripheral ID #1

Address: 0xE0002FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

1.1.13 CM0P_BP_PID2

Breakpoint Unit CoreSight ROM Table Peripheral ID #2

Address: 0xE0002FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.14 CM0P_BP_PID3

Breakpoint Unit CoreSight ROM Table Peripheral ID #3

Address: 0xE0002FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.15 CM0P_BP_CID0

Breakpoint Unit CoreSight ROM Table Component ID #0

Address: 0xE0002FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.16 CM0P_BP_CID1

Breakpoint Unit CoreSight ROM Table Component ID #1

Address: 0xE0002FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

1.1.17 CM0P_BP_CID2

Breakpoint Unit CoreSight ROM Table Component ID #2

Address: 0xE0002FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.18 CM0P_BP_CID3

Breakpoint Unit CoreSight ROM Table Component ID #3

Address: 0xE0002FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

1.1.19 CM0P_SYST_CSR

SysTick Control & Status

Address: 0xE000E010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [7:3]					CLK-SOURCE	TICKINT	ENABLE

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							RW
Name	None [23:17]							COUNT-FLAG

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	COUNTFLAG	Indicates whether the counter has counted to "0" since the last read of this register: '0': counter has not counted to "0". '1': counter has counted to "0". COUNTFLAG is set to '1' by a count transition from "1" to "0". COUNTFLAG is cleared to '0' by a read of this register, and by any write to the SYST_CVR register. Default Value: 0

1.1.19 CM0P_SYST_CSR (continued)

2	CLKSOURCE	Indicates the SysTick counter clock source: '0': SysTick uses the low frequency clock "clk_lf". For this mode to function, "clk_lf" should be less than half the frequency of "clk_sys". Note that "clk_lf" is generated by a low accuracy ILO (Internal Low power Oscillator), with a target frequency of 32.768 kHz (frequency can be as low as 15 KHz and as high as 60 kHz). '1': SysTick uses the system/processor clock "clk_sys". In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided. in SF, TSG6M products, this functionality is not provided. For these products, this field should be set to '1', such that SysTick uses the system clock "clk_sys". Default Value: 0
1	TICKINT	Indicates whether counting to "0" causes the status of the SysTick exception to change to pending: '0': count to "0" does not affect the SysTick exception status. '1': count to "0" changes the SysTick exception status to pending. Changing the value of the counter to "0" by writing zero to the SYST_CVR register to "0" never changes the status of the SysTick exception. Default Value: 0
0	ENABLE	Indicates the enabled status of the SysTick counter: '0': counter is disabled. '1': counter is operating. Default Value: 0

1.1.20 CM0P_SYST_RVR

SysTick Reload Value

Address: 0xE000E014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RELOAD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RELOAD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	RELOAD [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 0	RELOAD	The value to load into the SYST_CVR register when the counter reaches 0. Default Value: X

1.1.21 CM0P_SYST_CVR

SysTick Current Value

Address: 0xE000E018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CURRENT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CURRENT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	CURRENT [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 0	CURRENT	Current counter value. This is the value of the counter at the time it is sampled. Default Value: X

1.1.22 CM0P_SYST_CALIB

SysTick Calibration Value

Address: 0xE000E01C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	TENMS [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	TENMS [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	TENMS [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	None	RW	None					
Name	NOREF	SKEW	None [29:24]					

Bits	Name	Description
31	NOREF	Indicates whether a implementation defined reference clock is provided: '0': the reference clock is provided. '1': the reference clock is not provided. When this bit is '1', the SYST_CSR.CLKSOURCE is forced to '1' and cannot be cleared to '0'. In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided and this field is '0'. In earlier products, SysTick counter functionality on the low frequency clock is NOT provided and this field is '1'. Default Value: 0
30	SKEW	Indicates whether the 10ms calibration value is exact: '0': 10ms calibration value is exact. '1': 10ms calibration value is inexact, because of the clock frequency. In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided and this field is '1' (due to the low accuracy ILO). In earlier products, SysTick counter functionality on the low frequency clock is NOT provided and this field is '0'. Default Value: X

1.1.22 CM0P_SYST_CALIB (continued)

23 : 0 TENMS

Optionally, holds a reload value to be used for 10ms (100Hz) timing, subject to system clock skew errors. If this field is "0", the calibration value is not known.

In PSoC4A-BLE (and later products), SysTick counter functionality on the low frequency clock is provided and this field is 0x00:00147. In earlier products, SysTick counter functionality on the low frequency clock is NOT provided and this field is 0x00:0000.
Default Value: X

1.1.23 CM0P_ISER

Interrupt Set-Enable Register

Address: 0xE000E100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	R							
Name	SETENA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	R							
Name	SETENA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	R							
Name	SETENA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	R							
Name	SETENA [31:24]							

Bits	Name	Description
31 : 0	SETENA	Enables, or reads the enabled state of one or more interrupts. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.24 CM0P_ICER

Interrupt Clear Enable Register

Address: 0xE000E180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	R							
Name	CLRENA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	R							
Name	CLRENA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C							
HW Access	R							
Name	CLRENA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C							
HW Access	R							
Name	CLRENA [31:24]							

Bits	Name	Description
31 : 0	CLRENA	Disables, or reads the enabled state of one or more interrupts. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.25 CM0P_ISPR

Interrupt Set-Pending Register

Address: 0xE000E200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	R							
Name	SETPEND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	R							
Name	SETPEND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S							
HW Access	R							
Name	SETPEND [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S							
HW Access	R							
Name	SETPEND [31:24]							

Bits	Name	Description
31 : 0	SETPEND	Changes the state of one or more interrupts to pending. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.26 CM0P_ICPR

Interrupt Clear-Pending Register

Address: 0xE000E280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1C							
HW Access	R							
Name	CLRPEND [31:24]							

Bits	Name	Description
31 : 0	CLRPEND	Changes the state of one or more interrupts to not pending. Each bit corresponds to the same numbered interrupt. Default Value: 0

1.1.27 CM0P_IPR0

Interrupt Priority Registers

Address: 0xE000E400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.28 CM0P_IPR1

Interrupt Priority Registers

Address: 0xE000E404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.29 CM0P_IPR2

Interrupt Priority Registers

Address: 0xE000E408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.30 CM0P_IPR3

Interrupt Priority Registers

Address: 0xE000E40C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.31 CM0P_IPR4

Interrupt Priority Registers

Address: 0xE000E410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.32 CM0P_IPR5

Interrupt Priority Registers

Address: 0xE000E414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.33 CM0P_IPR6

Interrupt Priority Registers

Address: 0xE000E418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.34 CM0P_IPR7

Interrupt Priority Registers

Address: 0xE000E41C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N0 [7:6]		None [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N1 [15:14]		None [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N2 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_N3 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_N3	Priority of interrupt number N+3. Default Value: 0
23 : 22	PRI_N2	Priority of interrupt number N+2. Default Value: 0
15 : 14	PRI_N1	Priority of interrupt number N+1. Default Value: 0
7 : 6	PRI_N0	Priority of interrupt number N. Default Value: 0

1.1.35 CM0P_CPUID

CPUID Register

Address: 0xE00ED00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	None				None			
Name	PARTNO [7:4]				REVISION [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	PARTNO [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R				R			
HW Access	None				None			
Name	VARIANT [23:20]				CONSTANT [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	IMPLEMENTER [31:24]							

Bits	Name	Description
31 : 24	IMPLEMENTER	Implementer code for ARM. Default Value: 65
23 : 20	VARIANT	Implementation defined. In ARM implementations this is the major revision number n in the rn part of the rn timer revision status, Product revision status on page xii. Default Value: 0
19 : 16	CONSTANT	Indicates the architecture, ARMv6-M Default Value: 12
15 : 4	PARTNO	Indicates part number, Cortex-M0+ Default Value: 3168
3 : 0	REVISION	Indicates revision. In ARM implementations this is the minor revision number n in the pn part of the rn timer revision status, see Product revision status on page xii. For release r0p1. Default Value: 1

1.1.36 CM0P_ICSR

Interrupt Control State Register

Address: 0xE000ED04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	VECTACTIVE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R				None			R
HW Access	RW				None			RW
Name	VECTPENDING [15:12]				None [11:9]			VECTACTIVE

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	None	R				
HW Access	RW	RW	None	RW				
Name	ISRPRE-EMPT	ISRPEND-ING	None	VECTPENDING [20:16]				

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	None		RW1S	RW1C	RW1S	RW1C	None
HW Access	RW	None		RW	R	RW	R	None
Name	NMIPEND-SET	None [30:29]		PENDSVSET	PENDSVCLR	PENDSTSETb	PENDSTCLR	None

Bits	Name	Description
31	NMIPENDSET	Activates an NMI exception or reads back the current state. Because NMI is the highest priority exception, it activates as soon as it is registered. Default Value: 0
28	PENDSVSET	Sets a pending PendSV interrupt or reads back the current state. Use this normally to request a context switch. Writing PENDSVSET and PENDSVCLR to '1' concurrently is UNPREDICTABLE. Default Value: 0
27	PENDSVCLR	Clears a pending PendSV interrupt. Default Value: 0
26	PENDSTSETb	Sets a pending SysTick or reads back the current state. Writing PENDSTSET and PENDSTCLR to '1' concurrently is UNPREDICTABLE. Default Value: 0
25	PENDSTCLR	Clears a pending SysTick, whether set here or by the timer hardware. Default Value: 0

1.1.36 CM0P_ICSR (continued)

23	ISRPREEMPT	Indicates whether a pending exception will be serviced on exit from debug halt state. Default Value: 0
22	ISRPENDING	Indicates if an external configurable, NVIC generated, interrupt is pending. Default Value: 0
20 : 12	VECTPENDING	The exception number for the highest priority pending exception. 0= No pending exceptions. The pending state includes the effect of memory-mapped enable and mask registers. It does not include the PRIMASK special-purpose register qualifier. Default Value: 0
8 : 0	VECTACTIVE	The exception number for the current executing exception. 0= Thread mode. This is the same value as IPSR[8:0] Default Value: 0

1.1.37 CM0P_AIRCR

Application Interrupt and Reset Control Register

Address: 0xE000ED0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW1S	RW1C	None
HW Access	None					R	R	None
Name	None [7:3]					SYSRESE- TREQ	VECTCL- RACTIVE	None

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	None	None						
Name	ENDIAN- NESS	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	VECTKEY [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	VECTKEY [31:24]							

Bits	Name	Description
31 : 16	VECTKEY	Vector Key. The value 0x05FA must be written to this register, otherwise the register write is UNPREDICTABLE. Readback value is UNKNOWN. Default Value: X
15	ENDIANNESS	Indicates the memory system data endianness: 0 little endian 1 big endian. See Endian support on page A3-44 for more information. Default Value: 0
2	SYSRESETREQ	System Reset Request. Writing 1 to this bit asserts a signal to request a reset by the external system. This will cause a full system reset of the CPU and all other components in the device. See Reset management on page B1-240 for more information. Default Value: 0
1	VECTCLRACTIVE	Clears all active state information for fixed and configurable exceptions. The effect of writing a 1 to this bit if the processor is not halted in Debug state is UNPREDICTABLE. Default Value: 0

1.1.38 CM0P_SCR

System Control Register

Address: 0xE000ED10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	None
HW Access	None			R	None	R	R	None
Name	None [7:5]			SEVON- PEND	None	SLEEP- DEEP	SLEEPON- EXIT	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	SEVONPEND	Determines whether an interrupt transition from inactive state to pending state is a wakeup event: 0: transitions from inactive to pending are not wakeup events. 1: transitions from inactive to pending are wakeup events. See WFE on page A6-197 for more information. Default Value: 0
2	SLEEPDEEP	An implementation can use this bit to select DeepSleep/Hibernate power modes upon execution of WFI/WFE: 0: Select Sleep mode 1: Select DeepSleep/Hibernate (depends on PWR_CONTROL.HIBERNATE) Default Value: 0
1	SLEEPONEXIT	Determines whether, on an exit from an ISR that returns to the base level of execution priority, the processor enters a sleep state: 0 do not enter sleep state. 1 enter sleep state. See Power management on page B1-240 for more information. Default Value: 0

1.1.39 CM0P_CCR

Configuration and Control Register

Address: 0xE000ED14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	None		
HW Access	None				None	None		
Name	None [7:4]				UN- ALIGN_TR P	None [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	None
HW Access	None						None	None
Name	None [15:10]						STKALIGN	None

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	STKALIGN	1: On exception entry, the SP used prior to the exception is adjusted to be 8-byte aligned and the context to restore it is saved. The SP is restored on the associated exception return. Default Value: 1
3	UNALIGN_TRP	1: unaligned word and halfword accesses generate a HardFault exception. Default Value: 1

1.1.40 CM0P_SHPR2

System Handler Priority Register 2

Address: 0xE000ED1C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_11 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_11	Priority of system handler 11, SVCall Default Value: 0

1.1.41 CM0P_SHPR3

System Handler Priority Register 3

Address: 0xE000ED20

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW		None					
HW Access	R		None					
Name	PRI_14 [23:22]		None [21:16]					

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	PRI_15 [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	PRI_15	Priority of system handler 15, SysTick Default Value: 0
23 : 22	PRI_14	Priority of system handler 14, PendSV Default Value: 0

1.1.42 CM0P_SHCSR

System Handler Control and State Register

Address: 0xE000ED24

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW	None						
HW Access	RW	None						
Name	SVCALL- PENDED	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15	SVCALLPENDED	0 SVCAll is not pending. 1 SVCAll is pending. This bit reflects the pending state on a read, and updates the pending state, to the value written, on a write. (Pending state bits are set to 1 when an exception occurs, and are cleared to 0 when an exception becomes active.) Default Value: 0

1.1.43 CM0P_SCS_PID4

System Control Space ROM Table Peripheral ID #4

Address: 0xE000EFD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.44 CM0P_SCS_PID0

System Control Space ROM Table Peripheral ID #0

Address: 0xE000EFE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 8

1.1.45 CM0P_SCS_PID1

System Control Space ROM Table Peripheral ID #1

Address: 0xE000EFE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 176

1.1.46 CM0P_SCS_PID2

System Control Space ROM Table Peripheral ID #2

Address: 0xE000EFE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.47 CM0P_SCS_PID3

System Control Space ROM Table Peripheral ID #3

Address: 0xE000EFEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.48 CM0P_SCS_CID0

System Control Space ROM Table Component ID #0

Address: 0xE000EFF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.49 CM0P_SCS_CID1

System Control Space ROM Table Component ID #1

Address: 0xE000EFF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 224

1.1.50 CM0P_SCS_CID2

System Control Space ROM Table Component ID #2

Address: 0xE000EFF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.51 CM0P_SCS_CID3

System Control Space ROM Table Component ID #3

Address: 0xE000EFFF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

1.1.52 CM0P_ROM_SCS

CM0+ CoreSight ROM Table Peripheral #0

Address: 0xE00FF000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to SCS ROM Table Default Value: 4293980163

1.1.53 CM0P_ROM_DWT

CM0+ CoreSight ROM Table Peripheral #1

Address: 0xE00FF004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to DWT ROM Table Default Value: 4293926915

1.1.54 CM0P_ROM_BPU

CM0+ CoreSight ROM Table Peripheral #2

Address: 0xE00FF008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Offset to BPU ROM Table Default Value: 4293931011

1.1.55 CM0P_ROM_END

CM0+ CoreSight ROM Table End Marker

Address: 0xE00FF00C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	End marker in peripheral list Default Value: 0

1.1.56 CM0P_ROM_CSMT

CM0+ CoreSight ROM Table Memory Type

Address: 0xE00FFFCC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Memory Type Default Value: 1

1.1.57 CM0P_ROM_PID4

CM0+ CoreSight ROM Table Peripheral ID #4

Address: 0xE00FFFD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #4 Default Value: 4

1.1.58 CM0P_ROM_PID0

CM0+ CoreSight ROM Table Peripheral ID #0

Address: 0xE00FFE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #0 Default Value: 192

1.1.59 CM0P_ROM_PID1

CM0+ CoreSight ROM Table Peripheral ID #1

Address: 0xE00FFE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #1 Default Value: 180

1.1.60 CM0P_ROM_PID2

CM0+ CoreSight ROM Table Peripheral ID #2

Address: 0xE00FFE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #2 Default Value: 11

1.1.61 CM0P_ROM_PID3

CM0+ CoreSight ROM Table Peripheral ID #3

Address: 0xE00FFFE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Peripheral ID #3 Default Value: 0

1.1.62 CM0P_ROM_CID0

CM0+ CoreSight ROM Table Component ID #0

Address: 0xE00FFF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #0 Default Value: 13

1.1.63 CM0P_ROM_CID1

CM0+ CoreSight ROM Table Component ID #1

Address: 0xE00FFF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #1 Default Value: 16

1.1.64 CM0P_ROM_CID2

CM0+ CoreSight ROM Table Component ID #2

Address: 0xE00FFF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #2 Default Value: 5

1.1.65 CM0P_ROM_CID3

CM0+ CoreSight ROM Table Component ID #3

Address: 0xE00FFFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component ID #3 Default Value: 177

2 TCPWM - Individual Counter (CNT) Registers



This section discusses the CNT registers. It lists all the registers in mapping tables, in address order.

2.1 Register Details

Register Name	Address
TCPWM_CNT0_CTRL	0x40060100
TCPWM_CNT0_STATUS	0x40060104
TCPWM_CNT0_COUNTER	0x40060108
TCPWM_CNT0_CC	0x4006010C
TCPWM_CNT0_CC_BUFF	0x40060110
TCPWM_CNT0_PERIOD	0x40060114
TCPWM_CNT0_PERIOD_BUFF	0x40060118
TCPWM_CNT0_TR_CTRL0	0x40060120
TCPWM_CNT0_TR_CTRL1	0x40060124
TCPWM_CNT0_TR_CTRL2	0x40060128
TCPWM_CNT0_INTR	0x40060130
TCPWM_CNT0_INTR_SET	0x40060134
TCPWM_CNT0_INTR_MASK	0x40060138
TCPWM_CNT0_INTR_MASKED	0x4006013C
TCPWM_CNT1_CTRL	0x40060140
TCPWM_CNT1_STATUS	0x40060144
TCPWM_CNT1_COUNTER	0x40060148
TCPWM_CNT1_CC	0x4006014C
TCPWM_CNT1_CC_BUFF	0x40060150
TCPWM_CNT1_PERIOD	0x40060154
TCPWM_CNT1_PERIOD_BUFF	0x40060158
TCPWM_CNT1_TR_CTRL0	0x40060160
TCPWM_CNT1_TR_CTRL1	0x40060164
TCPWM_CNT1_TR_CTRL2	0x40060168
TCPWM_CNT1_INTR	0x40060170
TCPWM_CNT1_INTR_SET	0x40060174
TCPWM_CNT1_INTR_MASK	0x40060178

Register Name	Address
TCPWM_CNT1_INTR_MASKED	0x4006017C
TCPWM_CNT2_CTRL	0x40060180
TCPWM_CNT2_STATUS	0x40060184
TCPWM_CNT2_COUNTER	0x40060188
TCPWM_CNT2_CC	0x4006018C
TCPWM_CNT2_CC_BUFF	0x40060190
TCPWM_CNT2_PERIOD	0x40060194
TCPWM_CNT2_PERIOD_BUFF	0x40060198
TCPWM_CNT2_TR_CTRL0	0x400601A0
TCPWM_CNT2_TR_CTRL1	0x400601A4
TCPWM_CNT2_TR_CTRL2	0x400601A8
TCPWM_CNT2_INTR	0x400601B0
TCPWM_CNT2_INTR_SET	0x400601B4
TCPWM_CNT2_INTR_MASK	0x400601B8
TCPWM_CNT2_INTR_MASKED	0x400601BC
TCPWM_CNT3_CTRL	0x400601C0
TCPWM_CNT3_STATUS	0x400601C4
TCPWM_CNT3_COUNTER	0x400601C8
TCPWM_CNT3_CC	0x400601CC
TCPWM_CNT3_CC_BUFF	0x400601D0
TCPWM_CNT3_PERIOD	0x400601D4
TCPWM_CNT3_PERIOD_BUFF	0x400601D8
TCPWM_CNT3_TR_CTRL0	0x400601E0
TCPWM_CNT3_TR_CTRL1	0x400601E4
TCPWM_CNT3_TR_CTRL2	0x400601E8
TCPWM_CNT3_INTR	0x400601F0
TCPWM_CNT3_INTR_SET	0x400601F4
TCPWM_CNT3_INTR_MASK	0x400601F8
TCPWM_CNT3_INTR_MASKED	0x400601FC
TCPWM_CNT4_CTRL	0x40060200
TCPWM_CNT4_STATUS	0x40060204
TCPWM_CNT4_COUNTER	0x40060208
TCPWM_CNT4_CC	0x4006020C
TCPWM_CNT4_CC_BUFF	0x40060210
TCPWM_CNT4_PERIOD	0x40060214
TCPWM_CNT4_PERIOD_BUFF	0x40060218
TCPWM_CNT4_TR_CTRL0	0x40060220
TCPWM_CNT4_TR_CTRL1	0x40060224
TCPWM_CNT4_TR_CTRL2	0x40060228
TCPWM_CNT4_INTR	0x40060230
TCPWM_CNT4_INTR_SET	0x40060234
TCPWM_CNT4_INTR_MASK	0x40060238

Register Name	Address
TCPWM_CNT4_INTR_MASKED	0x4006023C

2.1.1 TCPWM_CNT0_CTRL

Counter control register

Address: 0x40060100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PW-M_STOP_ON_KILL	PWM_SYN-C_KILL	AUTO_RE-LOAD_PERIOD	AUTO_RE-LOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 0x0: TIMER: Timer mode 0x2: CAPTURE: Capture mode 0x3: QUAD: Quadrature encoding mode 0x4: PWM: Pulse width modulation (PWM) mode 0x5: PWM_DT: PWM with deadtime insertion mode 0x6: PWM_PR: Pseudo random pulse width modulation

2.1.1 TCPWM_CNT0_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 0x0: X1: X1 encoding (QUAD mode) 0x1: X2: X2 encoding (QUAD mode) 0x1: INV_OUT: When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) 0x2: X4: X4 encoding (QUAD mode) 0x2: INV_COMPL_OUT: When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 0x0: COUNT_UP: Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. 0x1: COUNT_DOWN: Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x2: COUNT_UPDN1: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x3: COUNT_UPDN2: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 0x0: DIVBY1: Divide by 1 (other-than-PWM_DT mode) 0x1: DIVBY2: Divide by 2 (other-than-PWM_DT mode) 0x2: DIVBY4: Divide by 4 (other-than-PWM_DT mode)

2.1.1 TCPWM_CNT0_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode)
		0x4: DIVBY16: Divide by 16 (other-than-PWM_DT mode)
		0x5: DIVBY32: Divide by 32 (other-than-PWM_DT mode)
		0x6: DIVBY64: Divide by 64 (other-than-PWM_DT mode)
		0x7: DIVBY128: Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0': never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.2 TCPWM_CNT0_STATUS

Counter status register

Address: 0x40060104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.3 TCPWM_CNT0_COUNTER

Counter count register

Address: 0x40060108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.4 TCPWM_CNT0_CC

Counter compare/capture register

Address: 0x4006010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.5 TCPWM_CNT0_CC_BUFF

Counter buffered compare/capture register

Address: 0x40060110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.6 TCPWM_CNT0_PERIOD

Counter period register

Address: 0x40060114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.7 TCPWM_CNT0_PERIOD_BUFF

Counter buffered period register

Address: 0x40060118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.8 TCPWM_CNT0_TR_CTRL0

Counter trigger control register 0

Address: 0x40060120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.8 TCPWM_CNT0_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.9 TCPWM_CNT0_TR_CTRL1

Counter trigger control register 1

Address: 0x40060124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event. 0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. 0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event. 0x3: NO_EDGE_DET: No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.

2.1.9 TCPWM_CNT0_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.

2.1.10 TCPWM_CNT0_TR_CTRL2

Counter trigger control register 2

Address: 0x40060128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1'

2.1.10 TCPWM_CNT0_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0'
		0x2: INVERT: Invert
		0x3: NO_CHANGE: No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3
		0x0: SET: Set to '1'
		0x1: CLEAR: Set to '0'
		0x2: INVERT: Invert
		0x3: NO_CHANGE: No Change

2.1.11 TCPWM_CNT0_INTR

Interrupt request register.

Address: 0x40060130

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.12 TCPWM_CNT0_INTR_SET

Interrupt set request register.

Address: 0x40060134

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.13 TCPWM_CNT0_INTR_MASK

Interrupt mask register.

Address: 0x40060138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.14 TCPWM_CNT0_INTR_MASKED

Interrupt masked request register

Address: 0x4006013C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.15 TCPWM_CNT1_CTRL

Counter control register

Address: 0x40060140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PW- M_STOP_O N_KILL	PWM_SYN- C_KILL	AUTO_RE- LOAD_PE- RIOD	AUTO_RE- LOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 0x0: TIMER: Timer mode 0x2: CAPTURE: Capture mode 0x3: QUAD: Quadrature encoding mode 0x4: PWM: Pulse width modulation (PWM) mode 0x5: PWM_DT: PWM with deadtime insertion mode 0x6: PWM_PR: Pseudo random pulse width modulation

2.1.15 TCPWM_CNT1_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 0x0: X1: X1 encoding (QUAD mode) 0x1: X2: X2 encoding (QUAD mode) 0x1: INV_OUT: When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) 0x2: X4: X4 encoding (QUAD mode) 0x2: INV_COMPL_OUT: When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 0x0: COUNT_UP: Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. 0x1: COUNT_DOWN: Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x2: COUNT_UPDN1: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x3: COUNT_UPDN2: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 0x0: DIVBY1: Divide by 1 (other-than-PWM_DT mode) 0x1: DIVBY2: Divide by 2 (other-than-PWM_DT mode) 0x2: DIVBY4: Divide by 4 (other-than-PWM_DT mode)

2.1.15 TCPWM_CNT1_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode)
		0x4: DIVBY16: Divide by 16 (other-than-PWM_DT mode)
		0x5: DIVBY32: Divide by 32 (other-than-PWM_DT mode)
		0x6: DIVBY64: Divide by 64 (other-than-PWM_DT mode)
		0x7: DIVBY128: Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0': never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.16 TCPWM_CNT1_STATUS

Counter status register

Address: 0x40060144

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.17 TCPWM_CNT1_COUNTER

Counter count register

Address: 0x40060148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.18 TCPWM_CNT1_CC

Counter compare/capture register

Address: 0x4006014C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.19 TCPWM_CNT1_CC_BUFF

Counter buffered compare/capture register

Address: 0x40060150

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.20 TCPWM_CNT1_PERIOD

Counter period register

Address: 0x40060154

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.21 TCPWM_CNT1_PERIOD_BUFF

Counter buffered period register

Address: 0x40060158

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.22 TCPWM_CNT1_TR_CTRL0

Counter trigger control register 0

Address: 0x40060160

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.22 TCPWM_CNT1_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.23 TCPWM_CNT1_TR_CTRL1

Counter trigger control register 1

Address: 0x40060164

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event. 0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. 0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event. 0x3: NO_EDGE_DET: No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.

2.1.23 TCPWM_CNT1_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.

2.1.24 TCPWM_CNT1_TR_CTRL2

Counter trigger control register 2

Address: 0x40060168

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1'

2.1.24 TCPWM_CNT1_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0'
		0x2: INVERT: Invert
		0x3: NO_CHANGE: No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change

2.1.25 TCPWM_CNT1_INTR

Interrupt request register.

Address: 0x40060170

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.26 TCPWM_CNT1_INTR_SET

Interrupt set request register.

Address: 0x40060174

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.27 TCPWM_CNT1_INTR_MASK

Interrupt mask register.

Address: 0x40060178

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.28 TCPWM_CNT1_INTR_MASKED

Interrupt masked request register

Address: 0x4006017C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.29 TCPWM_CNT2_CTRL

Counter control register

Address: 0x40060180

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PW- M_STOP_O N_KILL	PWM_SYN- C_KILL	AUTO_RE- LOAD_PE- RIOD	AUTO_RE- LOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 0x0: TIMER: Timer mode 0x2: CAPTURE: Capture mode 0x3: QUAD: Quadrature encoding mode 0x4: PWM: Pulse width modulation (PWM) mode 0x5: PWM_DT: PWM with deadtime insertion mode 0x6: PWM_PR: Pseudo random pulse width modulation

2.1.29 TCPWM_CNT2_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 0x0: X1: X1 encoding (QUAD mode) 0x1: X2: X2 encoding (QUAD mode) 0x1: INV_OUT: When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) 0x2: X4: X4 encoding (QUAD mode) 0x2: INV_COMPL_OUT: When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 0x0: COUNT_UP: Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. 0x1: COUNT_DOWN: Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x2: COUNT_UPDN1: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x3: COUNT_UPDN2: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 0x0: DIVBY1: Divide by 1 (other-than-PWM_DT mode) 0x1: DIVBY2: Divide by 2 (other-than-PWM_DT mode) 0x2: DIVBY4: Divide by 4 (other-than-PWM_DT mode)

2.1.29 TCPWM_CNT2_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode)
		0x4: DIVBY16: Divide by 16 (other-than-PWM_DT mode)
		0x5: DIVBY32: Divide by 32 (other-than-PWM_DT mode)
		0x6: DIVBY64: Divide by 64 (other-than-PWM_DT mode)
		0x7: DIVBY128: Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0': never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.30 TCPWM_CNT2_STATUS

Counter status register

Address: 0x40060184

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.31 TCPWM_CNT2_COUNTER

Counter count register

Address: 0x40060188

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.32 TCPWM_CNT2_CC

Counter compare/capture register

Address: 0x4006018C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.33 TCPWM_CNT2_CC_BUFF

Counter buffered compare/capture register

Address: 0x40060190

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.34 TCPWM_CNT2_PERIOD

Counter period register

Address: 0x40060194

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.35 TCPWM_CNT2_PERIOD_BUFF

Counter buffered period register

Address: 0x40060198

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.36 TCPWM_CNT2_TR_CTRL0

Counter trigger control register 0

Address: 0x400601A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			
Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			
Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.36 TCPWM_CNT2_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.37 TCPWM_CNT2_TR_CTRL1

Counter trigger control register 1

Address: 0x400601A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event. 0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. 0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event. 0x3: NO_EDGE_DET: No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.

2.1.37 TCPWM_CNT2_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.

2.1.38 TCPWM_CNT2_TR_CTRL2

Counter trigger control register 2

Address: 0x400601A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1'

2.1.38 TCPWM_CNT2_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0'
		0x2: INVERT: Invert
		0x3: NO_CHANGE: No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change

2.1.39 TCPWM_CNT2_INTR

Interrupt request register.

Address: 0x400601B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.40 TCPWM_CNT2_INTR_SET

Interrupt set request register.

Address: 0x400601B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.41 TCPWM_CNT2_INTR_MASK

Interrupt mask register.

Address: 0x400601B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.42 TCPWM_CNT2_INTR_MASKED

Interrupt masked request register

Address: 0x400601BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.43 TCPWM_CNT3_CTRL

Counter control register

Address: 0x400601C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PW-M_STOP_ON_KILL	PWM_SYN-C_KILL	AUTO_RE-LOAD_PERIOD	AUTO_RE-LOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 0x0: TIMER: Timer mode 0x2: CAPTURE: Capture mode 0x3: QUAD: Quadrature encoding mode 0x4: PWM: Pulse width modulation (PWM) mode 0x5: PWM_DT: PWM with deadtime insertion mode 0x6: PWM_PR: Pseudo random pulse width modulation

2.1.43 TCPWM_CNT3_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 0x0: X1: X1 encoding (QUAD mode) 0x1: X2: X2 encoding (QUAD mode) 0x1: INV_OUT: When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) 0x2: X4: X4 encoding (QUAD mode) 0x2: INV_COMPL_OUT: When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 0x0: COUNT_UP: Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. 0x1: COUNT_DOWN: Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x2: COUNT_UPDN1: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x3: COUNT_UPDN2: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 0x0: DIVBY1: Divide by 1 (other-than-PWM_DT mode) 0x1: DIVBY2: Divide by 2 (other-than-PWM_DT mode) 0x2: DIVBY4: Divide by 4 (other-than-PWM_DT mode)

2.1.43 TCPWM_CNT3_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode)
		0x4: DIVBY16: Divide by 16 (other-than-PWM_DT mode)
		0x5: DIVBY32: Divide by 32 (other-than-PWM_DT mode)
		0x6: DIVBY64: Divide by 64 (other-than-PWM_DT mode)
		0x7: DIVBY128: Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0': never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.44 TCPWM_CNT3_STATUS

Counter status register

Address: 0x400601C4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.45 TCPWM_CNT3_COUNTER

Counter count register

Address: 0x400601C8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.46 TCPWM_CNT3_CC

Counter compare/capture register

Address: 0x400601CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.47 TCPWM_CNT3_CC_BUFF

Counter buffered compare/capture register

Address: 0x400601D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.48 TCPWM_CNT3_PERIOD

Counter period register

Address: 0x400601D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.49 TCPWM_CNT3_PERIOD_BUFF

Counter buffered period register

Address: 0x400601D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.50 TCPWM_CNT3_TR_CTRL0

Counter trigger control register 0

Address: 0x400601E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			
Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			
Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.50 TCPWM_CNT3_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.51 TCPWM_CNT3_TR_CTRL1

Counter trigger control register 1

Address: 0x400601E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event. 0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. 0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event. 0x3: NO_EDGE_DET: No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.

2.1.51 TCPWM_CNT3_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.

2.1.52 TCPWM_CNT3_TR_CTRL2

Counter trigger control register 2

Address: 0x400601E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1'

2.1.52 TCPWM_CNT3_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0'
		0x2: INVERT: Invert
		0x3: NO_CHANGE: No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change

2.1.53 TCPWM_CNT3_INTR

Interrupt request register.

Address: 0x400601F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.54 TCPWM_CNT3_INTR_SET

Interrupt set request register.

Address: 0x400601F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.55 TCPWM_CNT3_INTR_MASK

Interrupt mask register.

Address: 0x400601F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.56 TCPWM_CNT3_INTR_MASKED

Interrupt masked request register

Address: 0x400601FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

2.1.57 TCPWM_CNT4_CTRL

Counter control register

Address: 0x40060200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				PW-M_STOP_ON_KILL	PWM_SYN-C_KILL	AUTO_RE-LOAD_PERIOD	AUTO_RE-LOAD_CC

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		None	RW	RW	
HW Access	None		R		None	R	R	
Name	None [23:22]		QUADRATURE_MODE [21:20]		None	ONE_SHOT	UP_DOWN_MODE [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None					RW		
HW Access	None					R		
Name	None [31:27]					MODE [26:24]		

Bits	Name	Description
26 : 24	MODE	Counter mode. Default Value: 0 0x0: TIMER: Timer mode 0x2: CAPTURE: Capture mode 0x3: QUAD: Quadrature encoding mode 0x4: PWM: Pulse width modulation (PWM) mode 0x5: PWM_DT: PWM with deadtime insertion mode 0x6: PWM_PR: Pseudo random pulse width modulation

2.1.57 TCPWM_CNT4_CTRL (continued)

21 : 20	QUADRATURE_MODE	In QUAD mode selects quadrature encoding mode (X1/X2/X4). In PWM, PWM_DT and PWM_PR modes, these two bits can be used to invert "dt_line_out" and "dt_line_compl_out". Inversion is the last step in generation of "dt_line_out" and "dt_line_compl_out"; i.e. a disabled output line "dt_line_out" has the value QUADRATURE_MODE[0] and a disabled output line "dt_line_compl_out" has the value QUADRATURE_MODE[1]. Default Value: 0 0x0: X1: X1 encoding (QUAD mode) 0x1: X2: X2 encoding (QUAD mode) 0x1: INV_OUT: When bit 0 is '1', QUADRATURE_MODE[0] inverts "dt_line_out" (PWM/PWM_DT modes) 0x2: X4: X4 encoding (QUAD mode) 0x2: INV_COMPL_OUT: When bit 1 is '1', QUADRATURE_MODE[1] inverts "dt_line_compl_out" (PWM/PWM_DT modes)
18	ONE_SHOT	When '0', counter runs continuous. When '1', counter is turned off by hardware when a terminal count event is generated. Default Value: 0
17 : 16	UP_DOWN_MODE	Determines counter direction. Default Value: 0 0x0: COUNT_UP: Count up (to PERIOD). An overflow event is generated when the counter reaches PERIOD. A terminal count event is generated when the counter reaches PERIOD. 0x1: COUNT_DOWN: Count down (to "0"). An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x2: COUNT_UPDN1: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0". 0x3: COUNT_UPDN2: Count up (to PERIOD), then count down (to "0"). An overflow event is generated when the counter reaches PERIOD. An underflow event is generated when the counter reaches "0". A terminal count event is generated when the counter reaches "0" AND when the counter reaches PERIOD (this counter direction can be used for PWM functionality with asymmetrical updates).
15 : 8	GENERIC	Generic 8-bit control field. In PWM_DT mode, this field is used to determine the dead time: amount of dead time cycles in the counter clock domain. In all other modes, the lower 3 bits of this field determine pre-scaling of the selected counter clock. Default Value: 0 0x0: DIVBY1: Divide by 1 (other-than-PWM_DT mode) 0x1: DIVBY2: Divide by 2 (other-than-PWM_DT mode) 0x2: DIVBY4: Divide by 4 (other-than-PWM_DT mode)

2.1.57 TCPWM_CNT4_CTRL (continued)

		0x3: DIVBY8: Divide by 8 (other-than-PWM_DT mode)
		0x4: DIVBY16: Divide by 16 (other-than-PWM_DT mode)
		0x5: DIVBY32: Divide by 32 (other-than-PWM_DT mode)
		0x6: DIVBY64: Divide by 64 (other-than-PWM_DT mode)
		0x7: DIVBY128: Divide by 128 (other-than-PWM_DT mode)
3	PWM_STOP_ON_KILL	Specifies whether the counter stops on a kill events: '0': kill event does NOT stop counter. '1': kill event stops counter. This field has a function in PWM, PWM_DT and PWM_PR modes only. Default Value: 0
2	PWM_SYNC_KILL	Specifies asynchronous/synchronous kill behavior: '1': synchronous kill mode: the kill event disables the "dt_line_out" and "dt_line_compl_out" signals till the next terminal count event (synchronous kill). In synchronous kill mode, STOP_EDGE should be RISING_EDGE. '0': asynchronous kill mode: the kill event only disables the "dt_line_out" and "dt_line_compl_out" signals when present. In asynchronous kill mode, STOP_EDGE should be NO_EDGE_DET. This field has a function in PWM and PWM_DT modes only. This field is only used when PWM_STOP_ON_KILL is '0'. Default Value: 0
1	AUTO_RELOAD_PERIOD	Specifies switching of the PERIOD and buffered PERIOD values. This field has a function in PWM, PWM_DT and PWM_PR modes. '0': never switch. '1': switch on a terminal count event with and actively pending siwtch event. Default Value: 0
0	AUTO_RELOAD_CC	Specifies switching of the CC and buffered CC values. This field has a function in TIMER, PWM, PWM_DT and PWM_PR modes. Timer mode: '0': never switch. '1': switch on a compare match event. PWM, PWM_DT, PWM_PR modes: '0': never switch. '1': switch on a terminal count event with an actively pending switch event. Default Value: 0

2.1.58 TCPWM_CNT4_STATUS

Counter status register

Address: 0x40060204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							DOWN

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	GENERIC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	RW	None						
Name	RUNNING	None [30:24]						

Bits	Name	Description
31	RUNNING	When '0', the counter is NOT running. When '1', the counter is running. Default Value: 0
15 : 8	GENERIC	Generic 8-bit counter field. In PWM_DT mode, this counter is used for dead time insertion. In all other modes, this counter is used for pre-scaling the selected counter clock. PWM_DT mode can NOT use prescaled clock functionality. Default Value: 0
0	DOWN	When '0', counter is counting up. When '1', counter is counting down. In QUAD mode, this field indicates the direction of the latest counter change: '0' when last incremented and '1' when last decremented. Default Value: 0

2.1.59 TCPWM_CNT4_COUNTER

Counter count register

Address: 0x40060208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	COUNTER [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	COUNTER [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	16-bit counter value. It is advised to not write to this field when the counter is running. Default Value: 0

2.1.60 TCPWM_CNT4_CC

Counter compare/capture register

Address: 0x4006020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	In CAPTURE mode, captures the counter value. In other modes, compared to counter value. Default Value: 65535

2.1.61 TCPWM_CNT4_CC_BUFF

Counter buffered compare/capture register

Address: 0x40060210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	CC [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	CC [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CC	Additional buffer for counter CC register. Default Value: 65535

2.1.62 TCPWM_CNT4_PERIOD

Counter period register

Address: 0x40060214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Period value: upper value of the counter. When the counter should count for n cycles, this field should be set to n-1. Default Value: 65535

2.1.63 TCPWM_CNT4_PERIOD_BUFF

Counter buffered period register

Address: 0x40060218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	PERIOD [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	RW							
Name	PERIOD [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	PERIOD	Additional buffer for counter PERIOD register. Default Value: 65535

2.1.64 TCPWM_CNT4_TR_CTRL0

Counter trigger control register 0

Address: 0x40060220

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	COUNT_SEL [7:4]				CAPTURE_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	R				R			
Name	STOP_SEL [15:12]				RELOAD_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				START_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	START_SEL	Selects one of the 16 input triggers as a start trigger. In QUAD mode, this is the second phase (phi B). Default Value: 0
15 : 12	STOP_SEL	Selects one of the 16 input triggers as a stop trigger. In PWM, PWM_DT and PWM_PR modes, this is the kill trigger. In these modes, the kill trigger is used to either temporarily block the PWM outputs (PWM_STOP_ON_KILL is '0') or stop the functionality (PWM_STOP_ON_KILL is '1'). For the PWM and PWM_DT modes, the blocking of the output signals can be asynchronous (STOP_EDGE should be NO_EDGE_DET) in which case the blocking is as long as the trigger is '1' or synchronous (STOP_EDGE should be RISING_EDGE) in which case it extends till the next terminal count event. Default Value: 0
11 : 8	RELOAD_SEL	Selects one of the 16 input triggers as a reload trigger. In QUAD mode, this is the index or revolution pulse. In this mode, it will update the counter with the value in the TCPWM_CNTn_PERIOD register. Default Value: 0
7 : 4	COUNT_SEL	Selects one of the 16 input triggers as a count trigger. In QUAD mode, this is the first phase (phi A). Default setting selects input trigger 1, which is always '1'. Default Value: 1

2.1.64 TCPWM_CNT4_TR_CTRL0 (continued)

3 : 0	CAPTURE_SEL	Selects one of the 16 input triggers as a capture trigger. Input trigger 0 is always '0' and input trigger is always '1'. In the PWM, PWM_DT and PWM_PR modes this trigger is used to switch the values if the compare and period registers with their buffer counterparts. Default Value: 0

2.1.65 TCPWM_CNT4_TR_CTRL1

Counter trigger control register 1

Address: 0x40060224

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	STOP_EDGE [7:6]		RELOAD_EDGE [5:4]		COUNT_EDGE [3:2]		CAPTURE_EDGE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						START_EDGE [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	START_EDGE	A start event will start the counter; i.e. the counter will become running. Starting does NOT enable the counter. A start event will not initialize the counter whereas the reload event does. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event. 0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event. 0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event. 0x3: NO_EDGE_DET: No edge detection, use trigger as is.
7 : 6	STOP_EDGE	A stop event, will stop the counter; i.e. it will no longer be running. Stopping will NOT disable the counter. Default Value: 3 0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.

2.1.65 TCPWM_CNT4_TR_CTRL1 (continued)

		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
5 : 4	RELOAD_EDGE	A reload event will initialize the counter. When counting up, the counter is initialized to "0". When counting down, the counter is initialized with PERIOD. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
3 : 2	COUNT_EDGE	A counter event will increase or decrease the counter by '1'. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.
1 : 0	CAPTURE_EDGE	A capture event will copy the counter value into the CC register. Default Value: 3
		0x0: RISING_EDGE: Rising edge. Any rising edge generates an event.
		0x1: FALLING_EDGE: Falling edge. Any falling edge generates an event.
		0x2: BOTH_EDGES: Rising AND falling edge. Any odd amount of edges generates an event.
		0x3: NO_EDGE_DET: No edge detection, use trigger as is.

2.1.66 TCPWM_CNT4_TR_CTRL2

Counter trigger control register 2

Address: 0x40060228

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [7:6]		UNDERFLOW_MODE [5:4]		OVERFLOW_MODE [3:2]		CC_MATCH_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	UNDERFLOW_MODE	Determines the effect of a counter underflow event (COUNTER reaches "0") on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change
3 : 2	OVERFLOW_MODE	Determines the effect of a counter overflow event (COUNTER reaches PERIOD) on the "line_out" output signals. Default Value: 3 0x0: SET: Set to '1'

2.1.66 TCPWM_CNT4_TR_CTRL2 (continued)

		0x1: CLEAR: Set to '0'
		0x2: INVERT: Invert
		0x3: NO_CHANGE: No Change
1 : 0	CC_MATCH_MODE	Determines the effect of a compare match event (COUNTER equals CC register) on the "line_out" output signals. Note that INVERT is especially useful for center aligned pulse width modulation. To generate a duty cycle of 0%, the counter CC register should be set to "0". For a 100% duty cycle, the counter CC register should be set to larger than the counter PERIOD register. Default Value: 3 0x0: SET: Set to '1' 0x1: CLEAR: Set to '0' 0x2: INVERT: Invert 0x3: NO_CHANGE: No Change

2.1.67 TCPWM_CNT4_INTR

Interrupt request register.

Address: 0x40060230

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Counter matches CC register event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
0	TC	Terminal count event. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

2.1.68 TCPWM_CNT4_INTR_SET

Interrupt set request register.

Address: 0x40060234

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TC	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

2.1.69 TCPWM_CNT4_INTR_MASK

Interrupt mask register.

Address: 0x40060238

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TC	Mask bit for corresponding bit in interrupt request register. Default Value: 0

2.1.70 TCPWM_CNT4_INTR_MASKED

Interrupt masked request register

Address: 0x4006023C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						CC_MATCH	TC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CC_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
0	TC	Logical and of corresponding request and mask bits. Default Value: 0

3 CPU Sub System (CPUSS) Registers



This section discusses the CPUSS registers. It lists all the registers in mapping tables, in address order.

3.1 Register Details

Register Name	Address
CPUSS_SYSREQ	0x40100004
CPUSS_SYSARG	0x40100008
CPUSS_FLASH_CTL	0x40100030
CPUSS_ROM_CTL	0x40100034

3.1.1 CPUSS_SYSREQ

SYSCALL control register

Address: 0x40100004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	SYSCALL_COMMAND [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	SYSCALL_COMMAND [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	R	R	RW	RW	None		
HW Access	R	A	RW	A	R	None		
Name	SY- SCALL_RE Q	HMAS- TER_0	ROM_AC- CESS_EN	PRIVI- LEGED	DIS_RE- SET_VECT _REL	None [26:24]		

Bits	Name	Description
31	SYSCALL_REQ	CPU/DAP writes a '1' to this field to request a SystemCall. The HMASTER_0 field indicates the source of the write access. Setting this field to '1' immediate results in a NMI. The SystemCall NMI interrupt handler sets this field to '0' after servicing the request. Default Value: 0
30	HMASTER_0	Indicates the source of the write access to the SYSREQ register. '0': CPU write access. '1': DAP write access. HW sets this field when the SYSREQ register is written to and SYSCALL_REQ is '0' (the last time it is set is when SW sets SYSCALL_REQ from '0' to '1'). Default Value: 0
29	ROM_ACCESS_EN	Indicates that executing from Boot ROM is enabled. HW sets this field to '1', on reset or when the SystemCall NMI vector is fetched from Boot ROM. HW sets this field to '0', when the CPU is NOT executing from either Boot or System ROM. This bit is used for debug purposes only. Default Value: 1

3.1.1 CPUSS_SYSREQ (continued)

28	PRIVILEGED	Indicates whether the system is in privileged ('1') or user mode ('0'). Only CPU SW executing from ROM can set this field to '1' when ROM_ACCESS_EN is '1' (the CPU is executing a SystemCall NMI interrupt handler). Any other write to this field sets is to '0'. This field is used as the AHB-Lite hprot[1] signal to implement Cypress proprietary user/privileged modes. These modes are used to enable/disable access to specific MMIO registers and memory regions. Default Value: 1
27	DIS_RESET_VECT_REL	Disable Reset Vector fetch relocation: '0': CPU accesses to locations 0x0000:0000 - 0x0000:0007 are redirected to ROM. '1': CPU accesses to locations 0x0000:0000 - 0x0000:0007 are made to flash. Note that this field defaults to '0' on reset, ensuring actual reset vector fetches are always made to ROM. Note that this field does not affect DAP accesses. Flash DfT routines may set this bit to '1' to enable uninhibited read-back of programmed data in the first flash page. Default Value: 0
15 : 0	SYSCALL_COMMAND	Opcode of the system call being requested. Default Value: 0

3.1.2 CPUSS_SYSARG

SYSARG control register

Address: 0x40100008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	SYSCALL_ARG [31:24]							

Bits	Name	Description
31 : 0	SYSCALL_ARG	Argument to System Call specified in SYSREQ. Semantics of argument depends on system call made. Typically a pointer to a parameter block. Default Value: 0

3.1.3 CPOUSS_FLASH_CTL

FLASH control register

Address: 0x40100030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			PREF_EN	None [3:2]		FLASH_WS [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							RW1C
Name	None [15:9]							FLASH_IN- VALIDATE

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLASH_INVALIDATE	1': Invalidates the content of the flash controller's buffers. Default Value: 0
4	PREF_EN	Prefetch enable: '0': disabled. This is a desirable setting when FLASH_WS is "0" or when predictable execution behavior is required. '1': enabled. Default Value: 0
1 : 0	FLASH_WS	Amount of ROM wait states: "0": 0 wait states (fast flash: [0, 24] MHz system frequency, slow flash: [0, 16] MHz system frequency) "1": 1 wait state (fast flash: [24, 48] MHz system frequency, slow flash: [16, 32] MHz system frequency) "2": 2 wait states (slow flash: [32, 48] MHz system frequency) "3": undefined Default Value: 0

3.1.4 CPUSS_ROM_CTL

ROM control register

Address: 0x40100034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							ROM_WS

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	ROM_WS	Amount of ROM wait states: '0': 0 wait states. Use this setting for newer, faster ROM design. Use this setting for older, slower ROM design and frequencies in the range [0, 24] MHz. '1': 1 wait state. Use this setting for older, slower ROM design and frequencies in the range <24, 48] MHz. CPUSSv2 supports two types of ROM memory: an older, slower design (operating at up to 24 MHz) and a newer, faster design (operating at up to 48 MHz). The older design requires 1 wait state for frequencies above 24 MHz. The newer design never requires wait states. Default Value: 0

4 CapSense Registers



Note: Cypress recommends to use the CapSense component provided by the PSoC Creator IDE to implement CapSense designs. See the [PSoC 4 and PSoC 6 MCU CapSense design guide](#) for more details.

It is not recommended to directly access or modify CapSense registers. If you want to create custom register settings, contact Cypress technical support.

5 Continuous Time Block Mini Registers



This section discusses the Continuous Time Block Mini registers. It lists all the registers in mapping tables, in address order.

5.1 Register Details

Register Name	Address
CTBM0_CTB_CTRL	0x40300000
CTBM0_OA_RES0_CTRL	0x40300004
CTBM0_OA_RES1_CTRL	0x40300008
CTBM0_COMP_STAT	0x4030000C
CTBM0_INTR	0x40300020
CTBM0_INTR_SET	0x40300024
CTBM0_INTR_MASK	0x40300028
CTBM0_INTR_MASKED	0x4030002C
CTBM0_DFT_CTRL	0x40300030
CTBM0_OA0_SW	0x40300080
CTBM0_OA0_SW_CLEAR	0x40300084
CTBM0_OA1_SW	0x40300088
CTBM0_OA1_SW_CLEAR	0x4030008C
CTBM0_CTB_SW_HW_CTRL	0x403000C0
CTBM0_CTB_SW_STATUS	0x403000C4
CTBM0_OA0_OFFSET_TRIM	0x40300F00
CTBM0_OA0_SLOPE_OFFSET_TRIM	0x40300F04
CTBM0_OA0_COMP_TRIM	0x40300F08
CTBM0_OA1_OFFSET_TRIM	0x40300F0C
CTBM0_OA1_SLOPE_OFFSET_TRIM	0x40300F10
CTBM0_OA1_COMP_TRIM	0x40300F14

5.1.1 CTBM0_CTLB_CTRL

global CTB and power control

Address: 0x40300000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	ENABLED	DEEPSLEEP_ON	None [29:24]					

Bits	Name	Description
31	ENABLED	- 0: CTB IP disabled (put analog in power down, open all switches) - 1: CTB IP enabled Default Value: 0
30	DEEPSLEEP_ON	- 0: CTB IP disabled off during DeepSleep power mode - 1: CTB IP remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0

5.1.2 CTBM0_OA_RES0_CTRL

Opamp0 and resistor0 control

Address: 0x40300004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA0_DSI_L EVEL	OA0_BY- PASS_DSI_ SYNC	OA0_HYST _EN	OA0_COM- P_EN	None	OA0_DRIV E_STR_- SEL	OA0_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA0_PUMP _EN	None	OA0_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	OA0_PUMP_EN	Opamp0 pump enable Default Value: 0
9 : 8	OA0_COMPINT	Opamp0 comparator edge detect Default Value: 0 0x0: DISABLE: Disabled, no interrupts will be detected 0x1: RISING: Rising edge 0x2: FALLING: Falling edge 0x3: BOTH: Both rising and falling edges
7	OA0_DSI_LEVEL	Opamp0 comparator DSI (trigger) out level : 0=pulse, 1=level Default Value: 0

5.1.2 CTBM0_OA_RES0_CTRL (continued)

6	OA0_BY-PASS_DSI_SYNC	Opamp0 bypass comparator output synchronization for DSI (trigger) output: 0=synchronize (level or pulse), 1=bypass (output async) Default Value: 0
5	OA0_HYST_EN	Opamp0 hysteresis enable (10mV) Default Value: 0
4	OA0_COMP_EN	Opamp0 comparator enable Default Value: 0
2	OA0_DRIVE_STR_SEL	Opamp0 output strenght select 0=1x, 1=10x Default Value: 0
1 : 0	OA0_PWR_MODE	Opamp0 power level Default Value: 0 0x0: OFF: Off 0x1: LOW: Low compensation setting (smallest cap, highest GBW). For gain=10: PM=60deg @ Cload=50pF for the output to pin driver and 10pF for the internal only driver 0x2: MEDIUM: Medium compensation setting. For gain=4: PM=60deg @ Cload=50pF for the output to pin driver and 10pF for the internal only driver. 0x3: HIGH: Highest compensation (largest cap, lowest GBW). For gain=1: PM=60deg @ Cload=50pF for the output to pin driver and 10pF for the internal only driver

5.1.3 CTBM0_OA_RES1_CTRL

Opamp1 and resistor1 control

Address: 0x40300008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None	RW	RW	
HW Access	R	R	R	R	None	R	R	
Name	OA1_DSI_L EVEL	OA1_BY- PASS_DSI_ SYNC	OA1_HYST _EN	OA1_COM- P_EN	None	OA1_DRIV E_STR_- SEL	OA1_PWR_MODE [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	None	RW	
HW Access	None				R	None	R	
Name	None [15:12]				OA1_PUMP _EN	None	OA1_COMPINT [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	OA1_PUMP_EN	Opamp1 pump enable Default Value: 0
9 : 8	OA1_COMPINT	Opamp0 comparator edge detect Default Value: 0 0x0: DISABLE: Disabled, no interrupts will be detected 0x1: RISING: Rising edge 0x2: FALLING: Falling edge 0x3: BOTH: Both rising and falling edges
7	OA1_DSI_LEVEL	Opamp0 comparator DSI (trigger) out level : 0=pulse, 1=level Default Value: 0

5.1.3 CTBM0_OA_RES1_CTRL (continued)

6	OA1_BY-PASS_DSI_SYNC	Opamp1 bypass comparator output synchronization for DSI output: 0=synchronize, 1=bypass Default Value: 0
5	OA1_HYST_EN	Opamp1 hysteresis enable (10mV) Default Value: 0
4	OA1_COMP_EN	Opamp1 comparator enable Default Value: 0
2	OA1_DRIVE_STR_SEL	Opamp1 output strenght select 0=1x, 1=10x Default Value: 0
1 : 0	OA1_PWR_MODE	Opamp1 power level: see description of OA0_PWR_MODE Default Value: 0

5.1.4 CTBM0_COMP_STAT

Comparator status

Address: 0x4030000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							OA0_- COMP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							R
HW Access	None							W
Name	None [23:17]							OA1_- COMP

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
16	OA1_COMP	Opamp1 current comparator status Default Value: 0
0	OA0_COMP	Opamp0 current comparator status Default Value: 0

5.1.5 CTBM0_INTR

Interrupt request register

Address: 0x40300020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						COMP1	COMP0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1	Comparator 1 Interrupt: hardware sets this interrupt when comparator 1 triggers. Write with '1' to clear bit. Default Value: 0
0	COMP0	Comparator 0 Interrupt: hardware sets this interrupt when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

5.1.6 CTBM0_INTR_SET

Interrupt request set register

Address: 0x40300024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						COMP1_SET	COMP0_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	COMP0_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

5.1.7 CTBM0_INTR_MASK

Interrupt request mask

Address: 0x40300028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						COMP1_M ASK	COMP0_M ASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	COMP0_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

5.1.8 CTBM0_INTR_MASKED

Interrupt request masked

Address: 0x4030002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						COMP1_M ASKED	COMP0_M ASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP1_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
0	COMP0_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

5.1.9 CTBM0_DFT_CTRL

Was 'Analog DfT controls', now used as Risk Mitigation bits (RMP)

Address: 0x40300030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					DFT_MODE [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DFT_EN	None [30:24]						

Bits	Name	Description
31	DFT_EN	this bit is combined with the 3 bits 2:0, to form RMP[3:0] Default Value: 0
2 : 0	DFT_MODE	this bit is combined with bit 31, to form RMP[3:0], it must always be written with '3' for correct operation. Default Value: 0

5.1.10 CTBM0_OA0_SW

Opamp0 switch control

Address: 0x40300080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	None	RW1S
HW Access	None				RW1C	RW1C	None	RW1C
Name	None [7:4]				OA0P_A30	OA0P_A20	None	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1S	None					RW1S
HW Access	None	RW1C	None					RW1C
Name	None	OA0M_A81	None [13:9]					OA0M_A11

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1S	None		RW1S	None	
HW Access	None		RW1C	None		RW1C	None	
Name	None [23:22]		OA0O_D81	None [20:19]		OA0O_D51	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA0O_D81	Opamp0 output switch to short 1x with 10x drive Default Value: 0
18	OA0O_D51	Opamp0 output sarbus0 (ctbbus2 in CTB) Default Value: 0
14	OA0M_A81	Opamp0 negative terminal Opamp0 output Default Value: 0
8	OA0M_A11	Opamp0 negative terminal P1 Default Value: 0
3	OA0P_A30	Opamp0 positive terminal ctbbus0 Default Value: 0
2	OA0P_A20	Opamp0 positive terminal P0 Default Value: 0
0	OA0P_A00	Opamp0 positive terminal amuxbusa Default Value: 0

5.1.11 CTBM0_OA0_SW_CLEAR

Opamp0 switch control clear

Address: 0x40300084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	None	RW1C
HW Access	None				A	A	None	A
Name	None [7:4]				OA0P_A30	OA0P_A20	None	OA0P_A00

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1C	None					RW1C
HW Access	None	A	None					A
Name	None	OA0M_A81	None [13:9]					OA0M_A11

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1C	None		RW1C	None	
HW Access	None		A	None		A	None	
Name	None [23:22]		OA0O_D81	None [20:19]		OA0O_D51	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA0O_D81	see corresponding bit in OA0_SW Default Value: 0
18	OA0O_D51	see corresponding bit in OA0_SW Default Value: 0
14	OA0M_A81	see corresponding bit in OA0_SW Default Value: 0
8	OA0M_A11	see corresponding bit in OA0_SW Default Value: 0
3	OA0P_A30	see corresponding bit in OA0_SW Default Value: 0
2	OA0P_A20	see corresponding bit in OA0_SW Default Value: 0
0	OA0P_A00	see corresponding bit in OA0_SW Default Value: 0

5.1.12 CTBM0_OA1_SW

Opamp1 switch control

Address: 0x40300088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None		RW1S	RW1S
HW Access	None			RW1C	None		RW1C	RW1C
Name	None [7:5]			OA1P_A43	None [3:2]		OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1S	None					RW1S
HW Access	None	RW1C	None					RW1C
Name	None	OA1M_A82	None [13:9]					OA1M_A22

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1S	None	RW1S	RW1S	None	
HW Access	None		RW1C	None	RW1C	RW1C	None	
Name	None [23:22]		OA1O_D82	None	OA1O_D62	OA1O_D52	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA1O_D82	Opamp1 output switch to short 1x with 10x drive Default Value: 0
19	OA1O_D62	Opamp1 output sarbus1 (ctbbus3 in CTB) Default Value: 0
18	OA1O_D52	Opamp1 output sarbus0 (ctbbus2 in CTB) Default Value: 0
14	OA1M_A82	Opamp1 negative terminal Opamp1 output Default Value: 0
8	OA1M_A22	Opamp1 negative terminal P4 Default Value: 0
4	OA1P_A43	Opamp1 positive terminal ctbbus1 Default Value: 0
1	OA1P_A13	Opamp1 positive terminal P5 Default Value: 0
0	OA1P_A03	Opamp1 positive terminal amuxbusb Default Value: 0

5.1.13 CTBM0_OA1_SW_CLEAR

Opamp1 switch control clear

Address: 0x4030008C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None		RW1C	RW1C
HW Access	None			A	None		A	A
Name	None [7:5]			OA1P_A43	None [3:2]		OA1P_A13	OA1P_A03

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW1C	None					RW1C
HW Access	None	A	None					A
Name	None	OA1M_A82	None [13:9]					OA1M_A22

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW1C	None	RW1C	RW1C	None	
HW Access	None		A	None	A	A	None	
Name	None [23:22]		OA1O_D82	None	OA1O_D62	OA1O_D52	None [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	OA1O_D82	see corresponding bit in OA1_SW Default Value: 0
19	OA1O_D62	see corresponding bit in OA1_SW Default Value: 0
18	OA1O_D52	see corresponding bit in OA1_SW Default Value: 0
14	OA1M_A82	see corresponding bit in OA1_SW Default Value: 0
8	OA1M_A22	see corresponding bit in OA1_SW Default Value: 0
4	OA1P_A43	see corresponding bit in OA1_SW Default Value: 0
1	OA1P_A13	see corresponding bit in OA1_SW Default Value: 0
0	OA1P_A03	see corresponding bit in OA1_SW Default Value: 0

5.1.14 CTBM0_CTB_SW_HW_CTRL

CTB bus switch control

Address: 0x403000C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	None	
HW Access	None				R	R	None	
Name	None [7:4]				P3_HW_C-TRL	P2_HW_C-TRL	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	P3_HW_CTRL	Pin P3 switches Default Value: 0
2	P2_HW_CTRL	Pin P2 switches Default Value: 0

5.1.15 CTBM0_CTB_SW_STATUS

CTB bus switch control status

Address: 0x403000C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None	R	R	R	None			
HW Access	None	W	W	W	None			
Name	None	OA1O_D62_STAT	OA1O_D52_STAT	OA0O_D51_STAT	None [27:24]			

Bits	Name	Description
30	OA1O_D62_STAT	see OA1O_D62 bit in OA1_SW Default Value: 0
29	OA1O_D52_STAT	see OA1O_D52 bit in OA1_SW Default Value: 0
28	OA0O_D51_STAT	see OA0O_D51 bit in OA0_SW Default Value: 0

5.1.16 CTBM0_OA0_OFFSET_TRIM

Opamp0 trim control

Address: 0x40300F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_OFFSET_TRIM	Opamp0 offset trim Default Value: 0

5.1.17 CTBM0_OA0_SLOPE_OFFSET_TRIM

Opamp0 trim control

Address: 0x40300F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA0_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA0_SLOPE_OFFSET_TRIM	Opamp0 slope offset drift trim Default Value: 0

5.1.18 CTBM0_OA0_COMP_TRIM

Opamp0 trim control

Address: 0x40300F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA0_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA0_COMP_TRIM	Opamp0 Compensation Capacitor Trim Default Value: 0

5.1.19 CTBM0_OA1_OFFSET_TRIM

Opamp1 trim control

Address: 0x40300F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_OFFSET_TRIM	Opamp1 offset trim Default Value: 0

5.1.20 CTBM0_OA1_SLOPE_OFFSET_TRIM

Opamp1 trim control

Address: 0x40300F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		OA1_SLOPE_OFFSET_TRIM [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 0	OA1_SLOPE_OFFSET_TRIM	Opamp1 slope offset drift trim Default Value: 0

5.1.21 CTBM0_OA1_COMP_TRIM

Opamp1 trim control

Address: 0x40300F14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	
HW Access	None						R	
Name	None [7:2]						OA1_COMP_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	OA1_COMP_TRIM	Opamp1 Compensation Capacitor Trim Default Value: 0

6 Deep Sleep Amplifier Bias (DSAB) Registers



This section discusses the DSAB registers. It lists all the registers in mapping tables, in address order.

6.1 Register Details

Register Name	Address
PASS_DSAB_DSAB_CTRL	0x403F0E00
PASS_DSAB_DSAB_DFT	0x403F0E04

6.1.1 PASS_DSAB_DSAB_CTRL

global DSAB control

Address: 0x403F0E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW					
HW Access	None		R					
Name	None [7:6]		CURRENT_SEL [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				SEL_OUT [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				REF_SWAP_EN [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None		RW	None			RW
HW Access	R	None		R	None			R
Name	ENABLED	None [30:29]		START-UP_RM	None [27:25]			BYPASS_MODE_EN

Bits	Name	Description
31	ENABLED	This field (along with SEL_OUT and REF_SWAP_EN) provides bitwise selection of the current sources that drive the DSAB ZTC and PTAT outputs. See SEL_OUT field for truth tables. In SRSSLT devices, in active mode, this bit is overridden to '1', that is - it is always enabled in active mode. Default Value: 0
28	STARTUP_RM	Risk mitigation control 1 - Force start the startup circuit Default Value: 0
24	BYPASS_MODE_EN	0 - DSAB PTAT generator is powered from DSAB regulator: VDDA must be at least 2.4V 1 - DSAB PTAT generator is powered directly from VDDA: VDDA cannot exceed 4.0V Default Value: 0
19 : 16	REF_SWAP_EN	This field (along with SEL_OUT and ENABLED) provides bitwise selection of the current sources that drive the DSAB ZTC and PTAT outputs. See SEL_OUT field for truth tables. Default Value: 0

6.1.1 PASS_DSAB_DSAB_CTRL (continued)

11 : 8 SEL_OUT

This field (along with REF_SWAP_EN and ENABLED) provides bitwise selection of the current sources that drive the DSAB ZTC and PTAT outputs. The available current sources are a function of the type of SRSS. The SRSS current sources are disabled in chip DeepSleep mode which is indicated by () entries in the truth table. CTB(m) factory trim has SRSS-ZTC and either SRSS-PTAT (SRSSv2) or DSAB_PTAT (SRSS-LITE) enabled. If different settings are used, then a periodic re-trim of CTB(m) offset should be performed.

Truth Table with SRSSv2 (backwards compatible with PSoC4A family)

ENABLED	SEL_OUT	REF_SWAP_EN	"Chip Power Mode"	ZTC Output	PTAT Output
0	X	X	Active	SRSS-ZTC	SRSS-PTAT
0	X	X	DeepSleep	(SRSS-ZTC)	(SRSS-PTAT)
1	0	0	Active	SRSS-ZTC	SRSS-PTAT
1	0	0	DeepSleep	(SRSS-ZTC)	(SRSS-PTAT)
1	0	1	Active	SRSS-PTAT	SRSS-ZTC
1	0	1	DeepSleep	(SRSS-PTAT)	(SRSS-ZTC)
1	1	0	Active	DSAB-PTAT	SRSS-PTAT
1	1	0	DeepSleep	DSAB-PTAT	(SRSS-PTAT)
1	1	1	Active	SRSS-PTAT	DSAB-PTAT
1	1	1	DeepSleep	(SRSS-PTAT)	DSAB-PTAT

Truth Table with SRSS-LITE

ENABLED	SEL_OUT	REF_SWAP_EN	"Chip Power Mode"	ZTC Output	PTAT Output
0	X	X	Active	SRSS-ZTC	DSAB-PTAT
0	X	X	DeepSleep	(SRSS-ZTC)	--
1	0	0	Active	SRSS-ZTC	DSAB-PTAT
1	0	0	DeepSleep	(SRSS-ZTC)	--
1	0	1	Active	DSAB-PTAT	SRSS-ZTC
1	0	1	DeepSleep	DSAB-PTAT	(SRSS-ZTC)
1	1	0	Active	DSAB-PTAT	--
1	1	0	DeepSleep	DSAB-PTAT	--
1	1	1	Active	--	DSAB-PTAT
1	1	1	DeepSleep	--	DSAB-PTAT

Default Value: 0

5 : 0 CURRENT_SEL

DSAB DAC control field

Nominal DSAB Output Current = CURRENT_SEL * 0.075 uA

In products with SRSS-LITE, this setting impacts the CTB(m) offset. A value of 0x20 is used during factory trim and is required to maintain low offsets across temperature variation. If a different setting is used then a periodic re-trim of CTB(m) offset should be performed.

Default Value: 0

6.1.2 PASS_DSAB_DSAB_DFT

DFT bits

Address: 0x403F0E04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				EN_DFT [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3 : 0	EN_DFT	- 0: DSAB DFT disabled - 1: DSAB DFT enabled (connect output to amuxbus)
		0001 - PTAT<0> 0010 - PTAT<1> 0011 - PTAT<1:0> 0100 - PTAT<2> 0111 - PTAT<2:0> 1000 - PTAT<3> 1111 - PTAT<3:0> 1001 - DSAB Reg Out Default Value: 0

7 GPIO - Common Registers



This section discusses the GPIO registers. It lists all the registers in mapping tables, in address order.

7.1 Register Details

Register Name	Address
GPIO_INTR_CAUSE	0x40041000

7.1.1 GPIO_INTR_CAUSE

Interrupt port cause register

Address: 0x40041000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			PORT_INT [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	PORT_INT	Each IO port has an associated bit field in this register. The bit field reflects the IO port's interrupt line (bit field i reflects "gpio_interrupts[i]" for IO port i). The register is used when the system uses a shared/combined interrupt line "gpio_interrupt". The SW ISR reads the register to determine which IO port(s) is responsible for the shared/combined interrupt line "gpio_interrupt". Once, the IO port(s) is determined, the IO port's INTR register is read to determine the IO pad(s) in the IO port that caused the interrupt. Default Value: 0

8 GPIO - Port Specific Registers



This section discusses the GPIO Port registers. It lists all the registers in mapping tables, in address order.

8.1 Register Details

Register Name	Address
GPIO_PRT0_DR	0x40040000
GPIO_PRT0_PS	0x40040004
GPIO_PRT0_PC	0x40040008
GPIO_PRT0_INTR_CFG	0x4004000C
GPIO_PRT0_INTR	0x40040010
GPIO_PRT0_PC2	0x40040018
GPIO_PRT0_DR_SET	0x40040040
GPIO_PRT0_DR_CLR	0x40040044
GPIO_PRT0_DR_INV	0x40040048
GPIO_PRT1_DR	0x40040100
GPIO_PRT1_PS	0x40040104
GPIO_PRT1_PC	0x40040108
GPIO_PRT1_INTR_CFG	0x4004010C
GPIO_PRT1_INTR	0x40040110
GPIO_PRT1_PC2	0x40040118
GPIO_PRT1_DR_SET	0x40040140
GPIO_PRT1_DR_CLR	0x40040144
GPIO_PRT1_DR_INV	0x40040148
GPIO_PRT2_DR	0x40040200
GPIO_PRT2_PS	0x40040204
GPIO_PRT2_PC	0x40040208
GPIO_PRT2_INTR_CFG	0x4004020C
GPIO_PRT2_INTR	0x40040210
GPIO_PRT2_PC2	0x40040218
GPIO_PRT2_DR_SET	0x40040240
GPIO_PRT2_DR_CLR	0x40040244
GPIO_PRT2_DR_INV	0x40040248

Register Name	Address
GPIO_PRT3_DR	0x40040300
GPIO_PRT3_PS	0x40040304
GPIO_PRT3_PC	0x40040308
GPIO_PRT3_INTR_CFG	0x4004030C
GPIO_PRT3_INTR	0x40040310
GPIO_PRT3_PC2	0x40040318
GPIO_PRT3_DR_SET	0x40040340
GPIO_PRT3_DR_CLR	0x40040344
GPIO_PRT3_DR_INV	0x40040348
GPIO_PRT4_DR	0x40040400
GPIO_PRT4_PS	0x40040404
GPIO_PRT4_PC	0x40040408
GPIO_PRT4_INTR_CFG	0x4004040C
GPIO_PRT4_INTR	0x40040410
GPIO_PRT4_PC2	0x40040418
GPIO_PRT4_DR_SET	0x40040440
GPIO_PRT4_DR_CLR	0x40040444
GPIO_PRT4_DR_INV	0x40040448

8.1.1 GPIO_PRT0_DR

Port output data register

Address: 0x40040000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

8.1.2 GPIO_PRT0_PS

Port IO pad state register

Address: 0x40040004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

8.1.2 GPIO_PRT0_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

8.1.3 GPIO_PRT0_PC

Port configuration register

Address: 0x40040008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTV2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0

8.1.3 GPIO_PRT0_PC (continued)

24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 0x0: OFF: Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. 0x1: INPUT: Mode 1: Output buffer off (high Z). Input buffer on. 0x2: 0_PU: Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. 0x3: PD_1: Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. 0x4: 0_Z: Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. 0x5: Z_1: Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. 0x6: 0_1: Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. 0x7: PD_PU: Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

8.1.4 GPIO_PRT0_INTR_CFG

Port interrupt configuration register

Address: 0x4004000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [23:21]				FLT_SEL [20:18]		FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 0x0: DISABLE: Disabled 0x1: RISING: Rising edge 0x2: FALLING: Falling edge 0x3: BOTH: Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

8.1.4 GPIO_PRT0_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0
0x0: DISABLE: Disabled		
0x1: RISING: Rising edge		
0x2: FALLING: Falling edge		
0x3: BOTH: Both rising and falling edges		

8.1.5 GPIO_PRT0_INTR

Port interrupt status register

Address: 0x40040010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

8.1.5 GPIO_PRT0_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

8.1.6 GPIO_PRT0_PC2

Port configuration register 2

Address: 0x40040018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

8.1.6 GPIO_PRT0_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

8.1.7 GPIO_PRT0_DR_SET

Port output data set register

Address: 0x40040040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

8.1.8 GPIO_PRT0_DR_CLR

Port output data clear register

Address: 0x40040044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

8.1.9 GPIO_PRT0_DR_INV

Port output data invert register

Address: 0x40040048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

8.1.10 GPIO_PRT1_DR

Port output data register

Address: 0x40040100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

8.1.11 GPIO_PRT1_PS

Port IO pad state register

Address: 0x40040104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

8.1.11 GPIO_PRT1_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

8.1.12 GPIO_PRT1_PC

Port configuration register

Address: 0x40040108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None			RW		RW
HW Access	R		None			R		R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]			PORT_SLOW		PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTV2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0

8.1.12 GPIO_PRT1_PC (continued)

24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 0x0: OFF: Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. 0x1: INPUT: Mode 1: Output buffer off (high Z). Input buffer on. 0x2: 0_PU: Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. 0x3: PD_1: Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. 0x4: 0_Z: Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. 0x5: Z_1: Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. 0x6: 0_1: Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. 0x7: PD_PU: Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

8.1.13 GPIO_PRT1_INTR_CFG

Port interrupt configuration register

Address: 0x4004010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [23:21]				FLT_SEL [20:18]		FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 0x0: DISABLE: Disabled 0x1: RISING: Rising edge 0x2: FALLING: Falling edge 0x3: BOTH: Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

8.1.13 GPIO_PRT1_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0
0x0: DISABLE: Disabled		
0x1: RISING: Rising edge		
0x2: FALLING: Falling edge		
0x3: BOTH: Both rising and falling edges		

8.1.14 GPIO_PRT1_INTR

Port interrupt status register

Address: 0x40040110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

8.1.14 GPIO_PRT1_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

8.1.15 GPIO_PRT1_PC2

Port configuration register 2

Address: 0x40040118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

8.1.15 GPIO_PRT1_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

8.1.16 GPIO_PRT1_DR_SET

Port output data set register

Address: 0x40040140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

8.1.17 GPIO_PRT1_DR_CLR

Port output data clear register

Address: 0x40040144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

8.1.18 GPIO_PRT1_DR_INV

Port output data invert register

Address: 0x40040148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

8.1.19 GPIO_PRT2_DR

Port output data register

Address: 0x40040200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

8.1.20 GPIO_PRT2_PS

Port IO pad state register

Address: 0x40040204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

8.1.20 GPIO_PRT2_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

8.1.21 GPIO_PRT2_PC

Port configuration register

Address: 0x40040208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTV2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0

8.1.21 GPIO_PRT2_PC (continued)

24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 0x0: OFF: Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. 0x1: INPUT: Mode 1: Output buffer off (high Z). Input buffer on. 0x2: 0_PU: Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. 0x3: PD_1: Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. 0x4: 0_Z: Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. 0x5: Z_1: Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. 0x6: 0_1: Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. 0x7: PD_PU: Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

8.1.22 GPIO_PRT2_INTR_CFG

Port interrupt configuration register

Address: 0x4004020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [23:21]				FLT_SEL [20:18]		FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 0x0: DISABLE: Disabled 0x1: RISING: Rising edge 0x2: FALLING: Falling edge 0x3: BOTH: Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

8.1.22 GPIO_PRT2_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0
0x0: DISABLE: Disabled		
0x1: RISING: Rising edge		
0x2: FALLING: Falling edge		
0x3: BOTH: Both rising and falling edges		

8.1.23 GPIO_PRT2_INTR

Port interrupt status register

Address: 0x40040210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

8.1.23 GPIO_PRT2_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

8.1.24 GPIO_PRT2_PC2

Port configuration register 2

Address: 0x40040218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

8.1.24 GPIO_PRT2_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

8.1.25 GPIO_PRT2_DR_SET

Port output data set register

Address: 0x40040240

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

8.1.26 GPIO_PRT2_DR_CLR

Port output data clear register

Address: 0x40040244

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

8.1.27 GPIO_PRT2_DR_INV

Port output data invert register

Address: 0x40040248

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

8.1.28 GPIO_PRT3_DR

Port output data register

Address: 0x40040300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	RW	RW	RW	RW	RW	RW	RW	RW
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	DATA7	IO pad 7 output data. Default Value: 0
6	DATA6	IO pad 6 output data. Default Value: 0
5	DATA5	IO pad 5 output data. Default Value: 0
4	DATA4	IO pad 4 output data. Default Value: 0
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

8.1.29 GPIO_PRT3_PS

Port IO pad state register

Address: 0x40040304

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
7	DATA7	IO pad 7 state. Default Value: 0
6	DATA6	IO pad 6 state. Default Value: 0
5	DATA5	IO pad 5 state. Default Value: 0
4	DATA4	IO pad 4 state. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0

8.1.29 GPIO_PRT3_PS (continued)

0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

8.1.30 GPIO_PRT3_PC

Port configuration register

Address: 0x40040308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW			RW			RW
HW Access	R	R			R			R
Name	DM5	DM4 [14:12]			DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	RW			RW			RW	
HW Access	R			R			R	
Name	DM7 [23:21]			DM6 [20:18]			DM5 [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTV2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0

8.1.30 GPIO_PRT3_PC (continued)

24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTL input buffer. Default Value: 0
23 : 21	DM7	The GPIO drive mode for IO pad 7. Default Value: 0
20 : 18	DM6	The GPIO drive mode for IO pad 6. Default Value: 0
17 : 15	DM5	The GPIO drive mode for IO pad 5. Default Value: 0
14 : 12	DM4	The GPIO drive mode for IO pad 4. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 0x0: OFF: Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. 0x1: INPUT: Mode 1: Output buffer off (high Z). Input buffer on. 0x2: 0_PU: Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. 0x3: PD_1: Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. 0x4: 0_Z: Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. 0x5: Z_1: Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. 0x6: 0_1: Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. 0x7: PD_PU: Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

8.1.31 GPIO_PRT3_INTR_CFG

Port interrupt configuration register

Address: 0x4004030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE7_SEL [15:14]		EDGE6_SEL [13:12]		EDGE5_SEL [11:10]		EDGE4_SEL [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW		RW	
HW Access	None				R		R	
Name	None [23:21]				FLT_SEL [20:18]		FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 0x0: DISABLE: Disabled 0x1: RISING: Rising edge 0x2: FALLING: Falling edge 0x3: BOTH: Both rising and falling edges
15 : 14	EDGE7_SEL	Sets which edge will trigger an IRQ for IO pad 7. Default Value: 0
13 : 12	EDGE6_SEL	Sets which edge will trigger an IRQ for IO pad 6. Default Value: 0

8.1.31 GPIO_PRT3_INTR_CFG (continued)

11 : 10	EDGE5_SEL	Sets which edge will trigger an IRQ for IO pad 5. Default Value: 0
9 : 8	EDGE4_SEL	Sets which edge will trigger an IRQ for IO pad 4. Default Value: 0
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0
3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0
0x0: DISABLE: Disabled		
0x1: RISING: Rising edge		
0x2: FALLING: Falling edge		
0x3: BOTH: Both rising and falling edges		

8.1.32 GPIO_PRT3_INTR

Port interrupt status register

Address: 0x40040310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	DATA7	DATA6	DATA5	DATA4	DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	PS_DATA7	PS_DATA6	PS_DATA5	PS_DATA4	PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
23	PS_DATA7	Default Value: 0
22	PS_DATA6	Default Value: 0
21	PS_DATA5	Default Value: 0
20	PS_DATA4	Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	Default Value: 0
8	FLT_DATA	Deglitched interrupt pending (selected by FLT_SELECT). Default Value: 0

8.1.32 GPIO_PRT3_INTR (continued)

7	DATA7	Interrupt pending on IO pad 7. Firmware writes 1 to clear the interrupt. Default Value: 0
6	DATA6	Interrupt pending on IO pad 6. Firmware writes 1 to clear the interrupt. Default Value: 0
5	DATA5	Interrupt pending on IO pad 5. Firmware writes 1 to clear the interrupt. Default Value: 0
4	DATA4	Interrupt pending on IO pad 4. Firmware writes 1 to clear the interrupt. Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0
1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

8.1.33 GPIO_PRT3_PC2

Port configuration register 2

Address: 0x40040318

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INP_DIS7	INP_DIS6	INP_DIS5	INP_DIS4	INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INP_DIS7	Disables the input buffer for IO pad 7. Default Value: 0
6	INP_DIS6	Disables the input buffer for IO pad 6. Default Value: 0
5	INP_DIS5	Disables the input buffer for IO pad 5. Default Value: 0
4	INP_DIS4	Disables the input buffer for IO pad 4. Default Value: 0
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0

8.1.33 GPIO_PRT3_PC2 (continued)

0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

8.1.34 GPIO_PRT3_DR_SET

Port output data set register

Address: 0x40040340

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

8.1.35 GPIO_PRT3_DR_CLR

Port output data clear register

Address: 0x40040344

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

8.1.36 GPIO_PRT3_DR_INV

Port output data invert register

Address: 0x40040348

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

8.1.37 GPIO_PRT4_DR

Port output data register

Address: 0x40040400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				RW	RW	RW	RW
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	DATA3	IO pad 3 output data. Default Value: 0
2	DATA2	IO pad 2 output data. Default Value: 0
1	DATA1	IO pad 1 output data. Default Value: 0
0	DATA0	IO pad 0 output data. Default Value: 0

8.1.38 GPIO_PRT4_PS

Port IO pad state register

Address: 0x40040404

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							R
HW Access	None							W
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	FLT_DATA	Reads of this register return the logical state of the filtered pin. Default Value: 0
3	DATA3	IO pad 3 state. Default Value: 0
2	DATA2	IO pad 2 state. Default Value: 0
1	DATA1	IO pad 1 state. Default Value: 0
0	DATA0	IO pad 0 state: 1: Logic high, if the pin voltage is above the input buffer threshold, logic high. 0: Logic low, if the pin voltage is below that threshold, logic low. If the drive mode for the pin is set to high Z Analog, the pin state will read 0 independent of the voltage on the pin. Default Value: 0

8.1.39 GPIO_PRT4_PC

Port configuration register

Address: 0x40040408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DM2 [7:6]		DM1 [5:3]			DM0 [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			RW
HW Access	None				R			R
Name	None [15:12]				DM3 [11:9]			DM2

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None				RW	RW
HW Access	R		None				R	R
Name	PORT_IB_MODE_SEL [31:30]		None [29:26]				PORT_SLOW	PORT_VTRIP_SEL

Bits	Name	Description
31 : 30	PORT_IB_MODE_SEL	This field selects the input buffer reference. The size (1 or 2 bits) and functionality is dependent on the IO cell. For GPIOv2 IO cells, bit PORT_IB_MODE_SEL[1] is not used (GPIOv2 IO cell replaces GPIO IO cell): "0"/"2": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1"/"3": vcchib. For GPIO_OVTV2 and SIOv2 IO cells: "0": CMOS input buffer (PORT_VTRIP_SEL is '0'), LVTTTL input buffer (PORT_VTRIP_SEL is '1') "1": vcchib. "2": OVT. "3": Reference (possibly from reference generator cell). For SIO IO cell, this field is present but not used as the SIO IO cell does not provide input buffer mode select functionality (SIOv2 IO cell will replace SIO IO cell, as soon as it is available). Default Value: 0
25	PORT_SLOW	This field controls the output edge rate of all pins on the port: '0': fast. '1': slow. Default Value: 0

8.1.39 GPIO_PRT4_PC (continued)

24	PORT_VTRIP_SEL	The GPIO cells include a VTRIP_SEL signal to alter the input buffer voltage. Note: this bit is ignored for SIO ports, the VTRIP_SEL settings in the SIO register are used instead (a separate VTRIP_SEL is provided for each pin pair). 0: input buffer functions as a CMOS input buffer. 1: input buffer functions as a LVTTTL input buffer. Default Value: 0
11 : 9	DM3	The GPIO drive mode for IO pad 3. Default Value: 0
8 : 6	DM2	The GPIO drive mode for IO pad 2. Default Value: 0
5 : 3	DM1	The GPIO drive mode for IO pad 1. Default Value: 0
2 : 0	DM0	The GPIO drive mode for IO pad 0. Note: when initializing IO's that are connected to a live bus (such as I2C), make sure the HSIOM is properly configured (HSIOM_PRT_SELx) before turning the IO on here to avoid producing glitches on the bus. Default Value: 0 0x0: OFF: Mode 0 (analog mode): Output buffer off (high Z). Input buffer off. 0x1: INPUT: Mode 1: Output buffer off (high Z). Input buffer on. 0x2: 0_PU: Mode 2: Strong pull down ('0'), weak/resistive pull up (PU). Input buffer on. 0x3: PD_1: Mode 3: Weak/resistive pull down (PD), strong pull up ('1'). Input buffer on. 0x4: 0_Z: Mode 4: Strong pull down ('0'), open drain (pull up off). Input buffer on. 0x5: Z_1: Mode 5: Open drain (pull down off), strong pull up ('1'). Input buffer on. 0x6: 0_1: Mode 6: Strong pull down ('0'), strong pull up ('1'). Input buffer on. 0x7: PD_PU: Mode 7: Weak/resistive pull down (PD), weak/resistive pull up (PU). Input buffer on.

8.1.40 GPIO_PRT4_INTR_CFG

Port interrupt configuration register

Address: 0x4004040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	EDGE3_SEL [7:6]		EDGE2_SEL [5:4]		EDGE1_SEL [3:2]		EDGE0_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW			RW	
HW Access	None			R			R	
Name	None [23:21]			FLT_SEL [20:18]			FLT_EDGE_SEL [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
20 : 18	FLT_SEL	Selects which pin is routed through the 50ns glitch filter to provide a glitch-safe interrupt. Default Value: 0
17 : 16	FLT_EDGE_SEL	Same for the glitch filtered pin (selected by FLT_SELECT). Default Value: 0 0x0: DISABLE: Disabled 0x1: RISING: Rising edge 0x2: FALLING: Falling edge 0x3: BOTH: Both rising and falling edges
7 : 6	EDGE3_SEL	Sets which edge will trigger an IRQ for IO pad 3. Default Value: 0
5 : 4	EDGE2_SEL	Sets which edge will trigger an IRQ for IO pad 2. Default Value: 0

8.1.40 GPIO_PRT4_INTR_CFG (continued)

3 : 2	EDGE1_SEL	Sets which edge will trigger an IRQ for IO pad 1. Default Value: 0
1 : 0	EDGE0_SEL	Sets which edge will trigger an IRQ for IO pad 0. Default Value: 0
		0x0: DISABLE: Disabled
		0x1: RISING: Rising edge
		0x2: FALLING: Falling edge
		0x3: BOTH: Both rising and falling edges

8.1.41 GPIO_PRT4_INTR

Port interrupt status register

Address: 0x40040410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				DATA3	DATA2	DATA1	DATA0

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW1C
HW Access	None							A
Name	None [15:9]							FLT_DATA

Bits	23	22	21	20	19	18	17	16
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [23:20]				PS_DATA3	PS_DATA2	PS_DATA1	PS_DATA0

Bits	31	30	29	28	27	26	25	24
SW Access	None							R
HW Access	None							W
Name	None [31:25]							PS_FLT_DATA

Bits	Name	Description
24	PS_FLT_DATA	This is a duplicate of the contents of the PS register, provided here to allow reading of both pin state and interrupt state of the port in a single read operation. Default Value: 0
19	PS_DATA3	Default Value: 0
18	PS_DATA2	Default Value: 0
17	PS_DATA1	Default Value: 0
16	PS_DATA0	Default Value: 0
8	FLT_DATA	Deglinted interrupt pending (selected by FLT_SELECT). Default Value: 0
3	DATA3	Interrupt pending on IO pad 3. Firmware writes 1 to clear the interrupt. Default Value: 0
2	DATA2	Interrupt pending on IO pad 2. Firmware writes 1 to clear the interrupt. Default Value: 0

8.1.41 GPIO_PRT4_INTR (continued)

1	DATA1	Interrupt pending on IO pad 1. Firmware writes 1 to clear the interrupt. Default Value: 0
0	DATA0	Interrupt pending on IO pad 0. Firmware writes 1 to clear the interrupt. Default Value: 0

8.1.42 GPIO_PRT4_PC2

Port configuration register 2

Address: 0x40040418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				INP_DIS3	INP_DIS2	INP_DIS1	INP_DIS0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	INP_DIS3	Disables the input buffer for IO pad 3. Default Value: 0
2	INP_DIS2	Disables the input buffer for IO pad 2. Default Value: 0
1	INP_DIS1	Disables the input buffer for IO pad 1. Default Value: 0
0	INP_DIS0	Disables the input buffer for IO pad 0 independent of the port control drive mode (PC.DM). This bit should be set when analog signals are present on the pin and PC.DM != 0 is required to use the output driver. Default Value: 0

8.1.43 GPIO_PRT4_DR_SET

Port output data set register

Address: 0x40040440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '1'. Default Value: 0

8.1.44 GPIO_PRT4_DR_CLR

Port output data clear register

Address: 0x40040444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] set to '0'. Default Value: 0

8.1.45 GPIO_PRT4_DR_INV

Port output data invert register

Address: 0x40040448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	A							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	IO pad i: '0': Output state DR.DATA[i] not affected. '1': Output state DR.DATA[i] inverted ('0' => '1', '1' => '0'). Default Value: 0

9 High Speed IO Matrix (HSIOM) Registers



This section discusses the HSIOM common registers. It lists all the registers in mapping tables, in address order.

9.1 Register Details

Register Name	Address
HSIOM_AMUX_SPLIT_CTL0	0x40022100
HSIOM_AMUX_SPLIT_CTL1	0x40022104

9.1.1 HSIOM_AMUX_SPLIT_CTL0

AMUX splitter cell control

Address: 0x40022100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_B-B_S0	SWITCH_B-B_SR	SWITCH_B-B_SL	None	SWITCH_A-A_S0	SWITCH_A-A_SR	SWITCH_A-A_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

9.1.1 HSIOM_AMUX_SPLIT_CTL0 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUS switch: '0': switch open. '1': switch closed. Default Value: 0

9.1.2 HSIOM_AMUX_SPLIT_CTL1

AMUX splitter cell control

Address: 0x40022104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW	RW	RW
HW Access	None	R	R	R	None	R	R	R
Name	None	SWITCH_B-B_S0	SWITCH_B-B_SR	SWITCH_B-B_SL	None	SWITCH_A-A_S0	SWITCH_A-A_SR	SWITCH_A-A_SL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6	SWITCH_BB_S0	T-switch control for AMUXBUSB vssa/ground switch. Default Value: 0
5	SWITCH_BB_SR	T-switch control for Right AMUXBUSB switch. Default Value: 0
4	SWITCH_BB_SL	T-switch control for Left AMUXBUSB switch. Default Value: 0
2	SWITCH_AA_S0	T-switch control for AMUXBUSA vssa/ground switch: '0': switch open. '1': switch closed. Default Value: 0
1	SWITCH_AA_SR	T-switch control for Right AMUXBUSA switch: '0': switch open. '1': switch closed. Default Value: 0

9.1.2 HSIOM_AMUX_SPLIT_CTL1 (continued)

0	SWITCH_AA_SL	T-switch control for Left AMUXBUS switch: '0': switch open. '1': switch closed. Default Value: 0

10 HSIOM - Port Specific Registers



This section discusses the HSIOM Port Specific registers. It lists all the registers in mapping tables, in address order.

10.1 Register Details

Register Name	Address
HSIOM_PORT_SEL0	0x40020000
HSIOM_PORT_SEL1	0x40020100
HSIOM_PORT_SEL2	0x40020200
HSIOM_PORT_SEL3	0x40020300
HSIOM_PORT_SEL4	0x40020400

10.1.1 HSIOM_PORT_SEL0

Port selection register

Address: 0x40020000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

10.1.1 HSIOM_PORT_SELO (continued)

0x0: GPIO:

SW controlled GPIO.

0x1: GPIO_DSI:

SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:

DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:

DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:

CSD sense connection (analog mode)

0x5: CSD_SHIELD:

CSD shield connection (analog mode)

0x6: AMUXA:

AMUXBUS A connection.

0x7: AMUXB:

AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:

Chip specific Active source 0 connection.

0x9: ACT_1:

Chip specific Active source 1 connection.

0xa: ACT_2:

Chip specific Active source 2 connection.

0xb: ACT_3:

Chip specific Active source 3 connection.

0xc: LCD_COM:

LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:

Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:

LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:

Chip specific DeepSleep source 1 connection.

0xe: DS_2:

Chip specific DeepSleep source 2 connection.

0xf: DS_3:

Chip specific DeepSleep source 3 connection.

10.1.2 HSIOM_PORT_SEL1

Port selection register

Address: 0x40020100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

10.1.2 HSIOM_PORT_SEL1 (continued)

0x0: GPIO:

SW controlled GPIO.

0x1: GPIO_DSI:

SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:

DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:

DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:

CSD sense connection (analog mode)

0x5: CSD_SHIELD:

CSD shield connection (analog mode)

0x6: AMUXA:

AMUXBUS A connection.

0x7: AMUXB:

AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:

Chip specific Active source 0 connection.

0x9: ACT_1:

Chip specific Active source 1 connection.

0xa: ACT_2:

Chip specific Active source 2 connection.

0xb: ACT_3:

Chip specific Active source 3 connection.

0xc: LCD_COM:

LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:

Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:

LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:

Chip specific DeepSleep source 1 connection.

0xe: DS_2:

Chip specific DeepSleep source 2 connection.

0xf: DS_3:

Chip specific DeepSleep source 3 connection.

10.1.3 HSIOM_PORT_SEL2

Port selection register

Address: 0x40020200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

10.1.3 HSIOM_PORT_SEL2 (continued)

0x0: GPIO:

SW controlled GPIO.

0x1: GPIO_DSI:

SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:

DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:

DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:

CSD sense connection (analog mode)

0x5: CSD_SHIELD:

CSD shield connection (analog mode)

0x6: AMUXA:

AMUXBUS A connection.

0x7: AMUXB:

AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:

Chip specific Active source 0 connection.

0x9: ACT_1:

Chip specific Active source 1 connection.

0xa: ACT_2:

Chip specific Active source 2 connection.

0xb: ACT_3:

Chip specific Active source 3 connection.

0xc: LCD_COM:

LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:

Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:

LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:

Chip specific DeepSleep source 1 connection.

0xe: DS_2:

Chip specific DeepSleep source 2 connection.

0xf: DS_3:

Chip specific DeepSleep source 3 connection.

10.1.4 HSIOM_PORT_SEL3

Port selection register

Address: 0x40020300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO5_SEL [23:20]				IO4_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO7_SEL [31:28]				IO6_SEL [27:24]			

Bits	Name	Description
31 : 28	IO7_SEL	Selects connection for IO pad 7 route. Default Value: 0
27 : 24	IO6_SEL	Selects connection for IO pad 6 route. Default Value: 0
23 : 20	IO5_SEL	Selects connection for IO pad 5 route. Default Value: 0
19 : 16	IO4_SEL	Selects connection for IO pad 4 route. Default Value: 0
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0

10.1.4 HSIOM_PORT_SEL3 (continued)

0x0: GPIO:

SW controlled GPIO.

0x1: GPIO_DSI:

SW controlled "out", DSI controlled "oe_n".

0x2: DSI_DSI:

DSI controlled "out" and "oe_n".

0x3: DSI_GPIO:

DSI controlled "out", SW controlled "oe_n".

0x4: CSD_SENSE:

CSD sense connection (analog mode)

0x5: CSD_SHIELD:

CSD shield connection (analog mode)

0x6: AMUXA:

AMUXBUS A connection.

0x7: AMUXB:

AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:

Chip specific Active source 0 connection.

0x9: ACT_1:

Chip specific Active source 1 connection.

0xa: ACT_2:

Chip specific Active source 2 connection.

0xb: ACT_3:

Chip specific Active source 3 connection.

0xc: LCD_COM:

LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:

Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:

LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:

Chip specific DeepSleep source 1 connection.

0xe: DS_2:

Chip specific DeepSleep source 2 connection.

0xf: DS_3:

Chip specific DeepSleep source 3 connection.

10.1.5 HSIOM_PORT_SEL4

Port selection register

Address: 0x40020400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO1_SEL [7:4]				IO0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW				RW			
HW Access	RW				RW			
Name	IO3_SEL [15:12]				IO2_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 12	IO3_SEL	Selects connection for IO pad 3 route. Default Value: 0
11 : 8	IO2_SEL	Selects connection for IO pad 2 route. Default Value: 0
7 : 4	IO1_SEL	Selects connection for IO pad 1 route. Default Value: 0
3 : 0	IO0_SEL	Selects connection for IO pad 0 route. Default Value: 0
		0x0: GPIO: SW controlled GPIO.
		0x1: GPIO_DSI: SW controlled "out", DSI controlled "oe_n".
		0x2: DSI_DSI: DSI controlled "out" and "oe_n".
		0x3: DSI_GPIO: DSI controlled "out", SW controlled "oe_n".

10.1.5 HSIOM_PORT_SEL4 (continued)

0x4: CSD_SENSE:

CSD sense connection (analog mode)

0x5: CSD_SHIELD:

CSD shield connection (analog mode)

0x6: AMUXA:

AMUXBUS A connection.

0x7: AMUXB:

AMUXBUS B connection. This mode is also used for CSD GPIO charging. When CSD GPIO charging is enabled in CSD_CONTROL, "oe_n" is connected to "!csd_charge" signal (and IO pad is also still connected to AMUXBUS B).

0x8: ACT_0:

Chip specific Active source 0 connection.

0x9: ACT_1:

Chip specific Active source 1 connection.

0xa: ACT_2:

Chip specific Active source 2 connection.

0xb: ACT_3:

Chip specific Active source 3 connection.

0xc: LCD_COM:

LCD common connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xc: DS_0:

Chip specific DeepSleep source 0 connection.

0xd: LCD_SEG:

LCD segment connection. This mode provides DeepSleep functionality (provided that the LCD block is enabled and properly configured).

0xd: DS_1:

Chip specific DeepSleep source 1 connection.

0xe: DS_2:

Chip specific DeepSleep source 2 connection.

0xf: DS_3:

Chip specific DeepSleep source 3 connection.

11 LCD Registers



This section discusses the LCD registers. It lists all the registers in mapping tables, in address order.

11.1 Register Details

Register Name	Address
LCD_ID	0x400B0000
LCD_DIVIDER	0x400B0004
LCD_CONTROL	0x400B0008
LCD_DATA00	0x400B0100
LCD_DATA01	0x400B0104
LCD_DATA02	0x400B0108
LCD_DATA03	0x400B010C
LCD_DATA04	0x400B0110
LCD_DATA10	0x400B0200
LCD_DATA11	0x400B0204
LCD_DATA12	0x400B0208
LCD_DATA13	0x400B020C
LCD_DATA14	0x400B0210

11.1.1 LCD_ID

ID & Revision

Address: 0x400B0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	REVISION [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	REVISION [31:24]							

Bits	Name	Description
31 : 16	REVISION	the version number is 0x0001 Default Value: 1
15 : 0	ID	the ID of LCD controller peripheral is 0xF0F0 Default Value: 61680

11.1.2 LCD_DIVIDER

LCD Divider Register

Address: 0x400B0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SUBFR_DIV [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	SUBFR_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DEAD_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DEAD_DIV [31:24]							

Bits	Name	Description
31 : 16	DEAD_DIV	Length of the dead time period in cycles. When set to zero, no dead time period exists. Default Value: 0
15 : 0	SUBFR_DIV	Input clock frequency divide value, to generate the 1/4 sub-frame period. The sub-frame period is $4 \times (\text{SUBFR\_DIV} + 1)$ cycles long. Default Value: 0

11.1.3 LCD_CONTROL

LCD Configuration Register

Address: 0x400B0008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW	RW	RW	RW	RW
HW Access	None	R		R	R	R	R	R
Name	None	BIAS [6:5]		OP_MODE	TYPE	LCD_- MODE	HS_EN	LS_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				COM_NUM [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	LS_EN_STAT	None [30:24]						

Bits	Name	Description
31	LS_EN_STAT	LS enable status bit. This bit is a copy of LS_EN that is synchronized to the low speed clock domain and back to the system clock domain. Firmware can use this bit to observe whether LS_EN has taken effect in the low speed clock domain. Firmware should never change the configuration for the LS generator without ensuring this bit is 0. The following procedure should be followed to disable the LS generator: 1. If LS_EN=0 we are done. Exit the procedure. 2. Check that LS_EN_STAT=1. If not, wait until it is. This will catch the case of a recent enable (LS_EN=1) that has not taken effect yet. 3. Set LS_EN=0. 4. Wait until LS_EN_STAT=0. Default Value: 0

11.1.3 LCD_CONTROL (continued)

11 : 8	COM_NUM	The number of COM connections minus 2. So: 0: 2 COM's 1: 3 COM's ... 13: 15 COM's 14: 16 COM's 15: undefined Default Value: 0
6 : 5	BIAS	PWM bias selection Default Value: 0 0x0: HALF: 1/2 Bias 0x1: THIRD: 1/3 Bias 0x2: FOURTH: 1/4 Bias (not supported by LS generator) 0x3: FIFTH: 1/5 Bias (not supported by LS generator)
4	OP_MODE	Driving mode configuration Default Value: 0 0x0: PWM: PWM Mode 0x1: CORRELATION: Digital Correlation Mode
3	TYPE	LCD driving waveform type configuration. Default Value: 0 0x0: TYPE_A: Type A - Each frame addresses each COM pin only once with a balanced (DC=0) waveform. 0x1: TYPE_B: Type B - Each frame addresses each COM pin twice in sequence with a positive and negative waveform that together are balanced (DC=0).
2	LCD_MODE	HS/LS Mode selection Default Value: 0 0x0: LS: Select Low Speed (32kHz) Generator (Works in Active, Sleep and DeepSleep power modes). 0x1: HS: Select High Speed (system clock) Generator (Works in Active and Sleep power modes only).
1	HS_EN	High speed (HS) generator enable 1: enable 0: disable Default Value: 0
0	LS_EN	Low speed (LS) generator enable 1: enable 0: disable Default Value: 0

11.1.4 LCD_DATA00

LCD Pin Data Registers

Address: 0x400B0100

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

11.1.5 LCD_DATA01

LCD Pin Data Registers

Address: 0x400B0104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

11.1.6 LCD_DATA02

LCD Pin Data Registers

Address: 0x400B0108

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

11.1.7 LCD_DATA03

LCD Pin Data Registers

Address: 0x400B010C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

11.1.8 LCD_DATA04

LCD Pin Data Registers

Address: 0x400B0110

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 1-4 (COM1 is lsb). Default Value: 0

11.1.9 LCD_DATA10

LCD Pin Data Registers

Address: 0x400B0200

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

11.1.10 LCD_DATA11

LCD Pin Data Registers

Address: 0x400B0204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

11.1.11 LCD_DATA12

LCD Pin Data Registers

Address: 0x400B0208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

11.1.12 LCD_DATA13

LCD Pin Data Registers

Address: 0x400B020C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

11.1.13 LCD_DATA14

LCD Pin Data Registers

Address: 0x400B0210

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	DATA [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	DATA [31:24]							

Bits	Name	Description
31 : 0	DATA	Bits [4i+3:4i] represent the pin data for pin [i] for COMS 5-8 (COM5 is lsb). Default Value: 0

12 Low Power Comparator (LPCOMP) Registers



This section discusses the LPCOMP registers. It lists all the registers in mapping tables, in address order.

12.1 Register Details

Register Name	Address
LPCOMP_ID	0x400D0000
LPCOMP_CONFIG	0x400D0004
LPCOMP_INTR	0x400D0010
LPCOMP_INTR_SET	0x400D0014
LPCOMP_INTR_MASK	0x400D0018
LPCOMP_INTR_MASKED	0x400D001C
LPCOMP_TRIM1	0x400DFF00
LPCOMP_TRIM2	0x400DFF04
LPCOMP_TRIM3	0x400DFF08
LPCOMP_TRIM4	0x400DFF0C

12.1.1 LPCOMP_ID

ID & Revision

Address: 0x400D0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	None							
Name	REVISION [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	None							
Name	REVISION [31:24]							

Bits	Name	Description
31 : 16	REVISION	the version number is 0x0001 Default Value: 1
15 : 0	ID	the ID of LPCOMP peripheral is 0xE0E0 Default Value: 57568

12.1.2 LPCOMP_CONFIG

LPCOMP Configuration Register

Address: 0x400D0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	R	RW		RW	RW	RW	
HW Access	R	RW	R		R	R	R	
Name	ENABLE1	OUT1	INTTYPE1 [5:4]		FILTER1	HYST1	MODE1 [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	RW	R	RW		RW	RW	RW	
HW Access	R	RW	R		R	R	R	
Name	ENABLE2	OUT2	INTTYPE2 [13:12]		FILTER2	HYST2	MODE2 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW	RW	None		RW	RW
HW Access	None		R	R	None		R	R
Name	None [23:22]		DSI_LEV-EL2	DSI_BY-PASS2	None [19:18]		DSI_LEV-EL1	DSI_BY-PASS1

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
21	DSI_LEVEL2	Reserved bit - It should be set to 0. Default Value: 0
20	DSI_BYPASS2	Reserved bit - It should be set to 0. Default Value: 0
17	DSI_LEVEL1	Reserved bit - It should be set to 0. Default Value: 0
16	DSI_BYPASS1	Reserved bit - It should be set to 0. Default Value: 0
15	ENABLE2	Enable Comparator 1 Default Value: 0
14	OUT2	Current output value of the Comparator 1 Default Value: 0
13 : 12	INTTYPE2	Sets which edge in the Comparator 1 output triggers an interrupt Default Value: 0

12.1.2 LPCOMP_CONFIG (continued)

		0x0: DISABLE: Disabled, no interrupts will be generated
		0x1: RISING: Rising edge
		0x2: FALLING: Falling edge
		0x3: BOTH: Both rising and falling edges
11	FILTER2	Reserved bit - It should be set to 0. Default Value: 0
10	HYST2	10mV hysteresis for Comparator 1 0: Enable Hysteresis 1: Disable Hysteresis Default Value: 0
9 : 8	MODE2	Sets the operating mode for Comparator 1 Default Value: 0
		0x0: SLOW: Slow operating mode
		0x1: FAST: Fast operating mode (Highest block current)
		0x2: ULP: Ultra low power operating mode (lowest block current)
7	ENABLE1	Enable Comparator 0 Default Value: 0
6	OUT1	Current output value of the Comparator 0 Default Value: 0
5 : 4	INTTYPE1	Sets which edge in the Comparator 0 output triggers an interrupt Default Value: 0
		0x0: DISABLE: Disabled, no interrupts will be generated
		0x1: RISING: Rising edge
		0x2: FALLING: Falling edge
		0x3: BOTH: Both rising and falling edges
3	FILTER1	Reserved bit - It should be set to 0. Default Value: 0
2	HYST1	10mV hysteresis for Comparator 0 0: Enable Hysteresis 1: Disable Hysteresis Default Value: 0
1 : 0	MODE1	Sets the operating mode for Comparator 0 Default Value: 0
		0x0: SLOW: Slow operating mode

12.1.2 LPCOMP_CONFIG (continued)

0x1: FAST:

Fast operating mode (Highest block current)

0x2: ULP:

Ultra low power operating mode (lowest block current)

12.1.3 LPCOMP_INTR

LPCOMP Interrupt request register

Address: 0x400D0010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [7:2]						COMP2	COMP1

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2	Comparator 1 Interrupt: Hardware sets this bit when comparator 1 triggers. Write with '1' to clear bit. Default Value: 0
0	COMP1	Comparator 0 Interrupt: Hardware sets this bit when comparator 0 triggers. Write with '1' to clear bit. Default Value: 0

12.1.4 LPCOMP_INTR_SET

LPCOMP Interrupt set register

Address: 0x400D0014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [7:2]						COMP2	COMP1

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2	Write with '1' to set COMP2 bit in the interrupt request register. This triggers Comparator 1 interrupt. Default Value: 0
0	COMP1	Write with '1' to set COMP1 bit in the interrupt request register. This triggers Comparator 0 interrupt. Default Value: 0

12.1.5 LPCOMP_INTR_MASK

LPCOMP Interrupt request mask

Address: 0x400D0018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						COMP2_M ASK	COMP1_M ASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2_MASK	Interrupt mask bit for Comparator 1 Default Value: 0
0	COMP1_MASK	Interrupt mask bit for Comparator 0 Default Value: 0

12.1.6 LPCOMP_INTR_MASKED

LPCOMP Interrupt request masked

Address: 0x400D001C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						COMP2_M ASKED	COMP1_M ASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	COMP2_MASKED	Logical AND of the Comparator 1 interrupt request register bit and the interrupt mask bit. Default Value: 0
0	COMP1_MASKED	Logical AND of the Comparator 0 interrupt request register bit and the interrupt mask bit. Default Value: 0

12.1.7 LPCOMP_TRIM1

LPCOMP Trim Register

Address: 0x400DFF00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP1_TRIMA [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP1_TRIMA	Trim A for Comparator 0. These bits are used to correct/trim the comparator offset (Coarse tuning bits) . Trim A bits[3:0] control the amount of offset and Trim A bit[4] controls the polarity of offset ('1' indicates positive offset and '0' indicates negative offset). Default Value: 0

12.1.8 LPCOMP_TRIM2

LPCOMP Trim Register

Address: 0x400DFF04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP1_TRIMB [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP1_TRIMB	Trim B for Comparator 0. These bits are used to correct/trim the comparator offset (fine tuning bits). These bits must be tuned after tuning Trim A bits for the comparator. Default Value: 0

12.1.9 LPCOMP_TRIM3

LPCOMP Trim Register

Address: 0x400DFF08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP2_TRIMA [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP2_TRIMA	Trim A for Comparator 1. These bits are used to correct/trim the comparator offset (Coarse tuning bits) . Trim A bits[3:0] control the amount of offset and Trim A bit[4] controls the polarity of offset ('1' indicates positive offset and '0' indicates negative offset). Default Value: 0

12.1.10 LPCOMP_TRIM4

LPCOMP Trim Register

Address: 0x400DFF0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COMP2_TRIMB [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COMP2_TRIMB	Trim B for Comparator 1. These bits are used to correct/trim the comparator offset (fine tuning bits). These bits must be tuned after tuning Trim A bits for the comparator. Default Value: 0

13 PASS MMIO Registers



This section discusses the Programmable Analog Sub System Memory Mapped IO (PASS MMIO) registers. It lists all the registers in mapping tables, in address order.

13.1 Register Details

Register Name	Address
PASS_INTR_CAUSE	0x403F0000
PASS_DFT_CTRL	0x403F0030
PASS_PASS_CTRL	0x403F0108
PASS_DSAB_TRIM	0x403F0F00

13.1.1 PASS_INTR_CAUSE

Interrupt cause register

Address: 0x403F0000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							CTB0_INT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	CTB0_INT	CTB0 interrupt pending Default Value: 0

13.1.2 PASS_DFT_CTRL

DFT control register

Address: 0x403F0030

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							DSAB_AD- FT_RES_E N

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	DSAB_ADFT_RES_EN	Close the switch to connect the DSAB ADFT resistor to the AMUXBUS Default Value: 0

13.1.3 PASS_PASS_CTRL

PASS Control

Address: 0x403F0108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						PMP-CLK_SRC	PMP-CLK_BYP

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RMB_BITS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	RMB_BITS	Risk mitigation bits Default Value: 0
1	PMPCLK_SRC	- 0: Pump clk is clk_hf - 1: Pump clk is direct from SRSS Default Value: 0
0	PMPCLK_BYP	- 0: Pump clk is clk_hf/2 - 1: Pump clk is selected from PMPCLK_SRC Default Value: 0

13.1.4 PASS_DSAB_TRIM

DSAB Trim bits

Address: 0x403F0F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		RW			
HW Access	None		R		R			
Name	None [7:6]		DSAB_RMB_BITS [5:4]		IBIAS_TRIM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	DSAB_RMB_BITS	Risk mitigation bits Default Value: 0
3 : 0	IBIAS_TRIM	1111=lowest, 0000=highest Default Value: 0

14 Peripheral Interconnect (PERI) Registers



This section discusses the Clock Dividers and Peripheral Interconnect (PERI) registers. It lists all the registers in mapping tables, in address order.

14.1 Register Details

Register Name	Address
PERI_DIV_CMD	0x40010000
PERI_PCLK_CTL0	0x40010100
PERI_PCLK_CTL1	0x40010104
PERI_PCLK_CTL2	0x40010108
PERI_PCLK_CTL3	0x4001010C
PERI_PCLK_CTL4	0x40010110
PERI_PCLK_CTL5	0x40010114
PERI_PCLK_CTL6	0x40010118
PERI_PCLK_CTL7	0x4001011C
PERI_PCLK_CTL8	0x40010120
PERI_PCLK_CTL9	0x40010124
PERI_PCLK_CTL10	0x40010128
PERI_PCLK_CTL11	0x4001012C
PERI_PCLK_CTL12	0x40010130
PERI_DIV_16_CTL0	0x40010300
PERI_DIV_16_CTL1	0x40010304
PERI_DIV_16_CTL2	0x40010308
PERI_DIV_16_CTL3	0x4001030C
PERI_DIV_16_CTL4	0x40010310
PERI_DIV_16_CTL5	0x40010314
PERI_DIV_16_5_CTL0	0x40010400
PERI_DIV_16_5_CTL1	0x40010404
PERI_DIV_16_5_CTL2	0x40010408
PERI_TR_CTL	0x40010600

14.1.1 PERI_DIV_CMD

Divider command register

Address: 0x40010000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW					
HW Access	R		R					
Name	SEL_TYPE [7:6]		SEL_DIV [5:0]					

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW					
HW Access	R		R					
Name	PA_SEL_TYPE [15:14]		PA_SEL_DIV [13:8]					

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	RW1C	RW1C	None					
Name	ENABLE	DISABLE	None [29:24]					

Bits	Name	Description
31	ENABLE	Clock divider enable command (mutually exclusive with DISABLE). Typically, SW sets this field to '1' to enable a divider and HW sets this field to '0' to indicate that divider enabling has completed. When a divider is enabled, its integer and fractional (if present) counters are initialized to "0". If a divider is to be re-enabled using different integer and fractional divider values, the SW should follow these steps: 0: Disable the divider using the DIV_CMD.DISABLE field. 1: Configure the divider's DIV_XXX_CTL register. 2: Enable the divider using the DIV_CMD_ENABLE field. The SEL_DIV and SEL_TYPE fields specify which divider is to be enabled. The enabled divider may be phase aligned to either "clk_hf" (typical usage) or to ANY enabled divider. The PA_SEL_DIV and P_SEL_TYPE fields specify the reference divider. The HW sets the ENABLE field to '0' when the enabling is performed and the HW set the DIV_XXX_CTL.EN field of the divider to '1' when the enabling is performed. Note that enabling with phase alignment to a low frequency divider takes time. E.g. To align to a divider that generates a clock of "clk_hf"/n (with n being the integer divider value INT_DIV+1), up to n cycles may be required to perform alignment. Phase alignment to "clk_hf" takes affect immediately. SW can set this field to '0' during phase alignment to abort the enabling process. Default Value: 0

14.1.1 PERI_DIV_CMD (continued)

30	DISABLE	Clock divider disable command (mutually exclusive with ENABLE). SW sets this field to '1' and HW sets this field to '0'. The SEL_DIV and SEL_TYPE fields specify which divider is to be disabled. The HW sets the DISABLE field to '0' immediately and the HW sets the DIV_XXX_CTL.EN field of the divider to '0' immediately. Default Value: 0
15 : 14	PA_SEL_TYPE	Specifies the divider type of the divider to which phase alignment is performed for the clock enable command: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
13 : 8	PA_SEL_DIV	(PA_SEL_TYPE, PA_SEL_DIV) specifies the divider to which phase alignment is performed for the clock enable command. Any enabled divider can be used as reference. This allows all dividers to be aligned with each other, even when they are enabled at different times. If PA_SEL_DIV is "63" and "PA_SEL_TYPE" is "3", "clk_hf" is used as reference. Default Value: 63
7 : 6	SEL_TYPE	Specifies the divider type of the divider on which the command is performed: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
5 : 0	SEL_DIV	(SEL_TYPE, SEL_DIV) specifies the divider on which the command (DISABLE/ENABLE) is performed. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock signal(s) are generated. Default Value: 63

14.1.2 PERI_PCLK_CTL0

Programmable clock control register

Address: 0x40010100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.3 PERI_PCLK_CTL1

Programmable clock control register

Address: 0x40010104

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.4 PERI_PCLK_CTL2

Programmable clock control register

Address: 0x40010108

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.5 PERI_PCLK_CTL3

Programmable clock control register

Address: 0x4001010C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.6 PERI_PCLK_CTL4

Programmable clock control register

Address: 0x40010110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.7 PERI_PCLK_CTL5

Programmable clock control register

Address: 0x40010114

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.8 PERI_PCLK_CTL6

Programmable clock control register

Address: 0x40010118

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.9 PERI_PCLK_CTL7

Programmable clock control register

Address: 0x4001011C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.10 PERI_PCLK_CTL8

Programmable clock control register

Address: 0x40010120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.11 PERI_PCLK_CTL9

Programmable clock control register

Address: 0x40010124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.12 PERI_PCLK_CTL10

Programmable clock control register

Address: 0x40010128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.13 PERI_PCLK_CTL11

Programmable clock control register

Address: 0x4001012C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.14 PERI_PCLK_CTL12

Programmable clock control register

Address: 0x40010130

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		None			RW		
HW Access	R		None			R		
Name	SEL_TYPE [7:6]		None [5:3]			SEL_DIV [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SEL_TYPE	Specifies divider type: 0: 8.0 (integer) clock dividers. 1: 16.0 (integer) clock dividers. 2: 16.5 (fractional) clock dividers. 3: 24.5 (fractional) clock dividers. Default Value: 3
2 : 0	SEL_DIV	Specifies one of the dividers of the divider type specified by SEL_TYPE. If SEL_DIV is "63" and "SEL_TYPE" is "3" (default/reset value), no divider is specified and no clock control signal(s) are generated. When transitioning a clock between two out of phase dividers, spurious clock control signals may be generated for one clk_hf cycle during this transition. These clock control signals may cause a single clock period that is smaller than any of the two divider periods. To prevent these spurious clock signals, the clock multiplexer can be disconnected (SEL_DIV is "63" and "SEL_TYPE" is "3") for a transition time that is larger than the smaller of the two divider periods. Default Value: 7

14.1.15 PERI_DIV_16_CTL0

Divider control register (for 16.0 divider)

Address: 0x40010300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.16 PERI_DIV_16_CTL1

Divider control register (for 16.0 divider)

Address: 0x40010304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.17 PERI_DIV_16_CTL2

Divider control register (for 16.0 divider)

Address: 0x40010308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.18 PERI_DIV_16_CTL3

Divider control register (for 16.0 divider)

Address: 0x4001030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.19 PERI_DIV_16_CTL4

Divider control register (for 16.0 divider)

Address: 0x40010310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.20 PERI_DIV_16_CTL5

Divider control register (for 16.0 divider)

Address: 0x40010314

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: this type of divider does NOT allow for a fractional division. For the generation of a divided clock, the integer division range is restricted to [2, 65,536]. For the generation of a 50/50% duty cycle digital divided clock, the integer division range is restricted to even numbers in the range [2, 65,536]. The generation of a 50/50 % duty cycle analog divided clock has no restrictions. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.21 PERI_DIV_16_5_CTL0

Divider control register (for 16.5 divider)

Address: 0x40010400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.21 PERI_DIV_16_5_CTL0 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.22 PERI_DIV_16_5_CTL1

Divider control register (for 16.5 divider)

Address: 0x40010404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.22 PERI_DIV_16_5_CTL1 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.23 PERI_DIV_16_5_CTL2

Divider control register (for 16.5 divider)

Address: 0x40010408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW					None		R
HW Access	R					None		RW
Name	FRAC5_DIV [7:3]					None [2:1]		EN

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	INT16_DIV [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	INT16_DIV [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 8	INT16_DIV	Integer division by (1+INT16_DIV). Allows for integer divisions in the range [1, 65,536]. Note: combined with fractional division, this divider type allows for a division in the range [1, 65,536 31/32] in 1/32 increments. For the generation of a divided clock, the division range is restricted to [2, 65,536 31/32]. For the generation of a 50/50% duty cycle divided clock, the division range is restricted to [2, 65,536]. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0
7 : 3	FRAC5_DIV	Fractional division by (FRAC5_DIV/32). Allows for fractional divisions in the range [0, 31/32]. Note that fractional division results in clock jitter as some clock periods may be 1 "clk_hf" cycle longer than other clock periods. Note that this field is retained. However, the counter that is used to implement the division is not and will be initialized by HW to "0" when transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.23 PERI_DIV_16_5_CTL2 (continued)

0	EN	Divider enabled. HW sets this field to '1' as a result of an ENABLE command. HW sets this field to '0' as a result on a DISABLE command. Note that this field is retained. As a result, the divider does NOT have to be re-enabled after transitioning from DeepSleep to Active power mode. Default Value: 0

14.1.24 PERI_TR_CTL

Trigger control register

Address: 0x40010600

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW						
HW Access	None	R						
Name	None	TR_SEL [6:0]						

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				TR_GROUP [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	RW							
Name	TR_COUNT [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	RW1C	R	None					
Name	TR_ACT	TR_OUT	None [29:24]					

Bits	Name	Description
31	TR_ACT	SW sets this field to '1' by to activate (set to '1') a trigger as identified by TR_SEL and TR_OUT for TR_COUNT cycles. HW sets this field to '0' when the cycle counter is decremented to "0". Note: a TR_COUNT value of 255 is a special case and trigger activation is under direct control of the TR_ACT field (the counter is not decremented). Default Value: 0
30	TR_OUT	Specifies whether trigger activation is for a specific input or output trigger of the trigger multiplexer. Activation of a specific input trigger, will result in activation of all output triggers that have the specific input trigger selected through their TR_OUT_CTL.SEL field. Activation of a specific output trigger, will result in activation of the specified TR_SEL output trigger only. '0': TR_SEL selection and trigger activation is for an input trigger to the trigger multiplexer. '1': TR_SEL selection and trigger activation is for an output trigger from the trigger multiplexer. Default Value: 0
23 : 16	TR_COUNT	Amount of cycles a specific trigger is activated. During activation (TR_ACT is '1'), HW decrements this field to "0" using a cycle counter. During activation, SW should not modify this register field. A value of 255 is a special case: HW does NOT decrement this field to "0" and trigger activation is under direct control of TR_ACT: when TR_ACT is '1' the trigger is activated and when TR_ACT is '0' the trigger is deactivated. Default Value: 0

14.1.24 PERI_TR_CTL (continued)

11 : 8	TR_GROUP	Specifies the trigger group. Default Value: 0
6 : 0	TR_SEL	Specifies the activated trigger when TR_ACT is '1'. TR_OUT specifies whether the activated trigger is an input trigger or output trigger to the trigger multiplexer. During activation (TR_ACT is '1'), SW should not modify this register field. If the specified trigger is not present, the trigger activation has no effect. Default Value: 0

15 Programmable IO (PRGIO) Registers



This section discusses the PRGIO registers. It lists all the registers in mapping tables, in address order.

15.1 Register Details

Register Name	Address
PRGIO_PRT0_CTL	0x40050000
PRGIO_PRT0_SYNC_CTL	0x40050010
PRGIO_PRT0_LUT_SEL0	0x40050020
PRGIO_PRT0_LUT_SEL1	0x40050024
PRGIO_PRT0_LUT_SEL2	0x40050028
PRGIO_PRT0_LUT_SEL3	0x4005002C
PRGIO_PRT0_LUT_SEL4	0x40050030
PRGIO_PRT0_LUT_SEL5	0x40050034
PRGIO_PRT0_LUT_SEL6	0x40050038
PRGIO_PRT0_LUT_SEL7	0x4005003C
PRGIO_PRT0_LUT_CTL0	0x40050040
PRGIO_PRT0_LUT_CTL1	0x40050044
PRGIO_PRT0_LUT_CTL2	0x40050048
PRGIO_PRT0_LUT_CTL3	0x4005004C
PRGIO_PRT0_LUT_CTL4	0x40050050
PRGIO_PRT0_LUT_CTL5	0x40050054
PRGIO_PRT0_LUT_CTL6	0x40050058
PRGIO_PRT0_LUT_CTL7	0x4005005C
PRGIO_PRT0_DU_SEL	0x400500C0
PRGIO_PRT0_DU_CTL	0x400500C4
PRGIO_PRT0_DATA	0x400500F0
PRGIO_PRT1_CTL	0x40050100
PRGIO_PRT1_SYNC_CTL	0x40050110
PRGIO_PRT1_LUT_SEL0	0x40050120
PRGIO_PRT1_LUT_SEL1	0x40050124
PRGIO_PRT1_LUT_SEL2	0x40050128
PRGIO_PRT1_LUT_SEL3	0x4005012C

Register Name	Address
PRGIO_PRT1_LUT_SEL4	0x40050130
PRGIO_PRT1_LUT_SEL5	0x40050134
PRGIO_PRT1_LUT_SEL6	0x40050138
PRGIO_PRT1_LUT_SEL7	0x4005013C
PRGIO_PRT1_LUT_CTL0	0x40050140
PRGIO_PRT1_LUT_CTL1	0x40050144
PRGIO_PRT1_LUT_CTL2	0x40050148
PRGIO_PRT1_LUT_CTL3	0x4005014C
PRGIO_PRT1_LUT_CTL4	0x40050150
PRGIO_PRT1_LUT_CTL5	0x40050154
PRGIO_PRT1_LUT_CTL6	0x40050158
PRGIO_PRT1_LUT_CTL7	0x4005015C
PRGIO_PRT1_DU_SEL	0x400501C0
PRGIO_PRT1_DU_CTL	0x400501C4
PRGIO_PRT1_DATA	0x400501F0

15.1.1 PRGIO_PRT0_CTL

Control register

Address: 0x40050000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	BYPASS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW				
HW Access	None			R				
Name	None [15:13]			CLOCK_SRC [12:8]				

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	RW
HW Access	R	None					R	R
Name	ENABLED	None [30:26]					PIPE- LINE_EN	HLD_OVR

Bits	Name	Description
31	ENABLED	Enable for programmable IO. Should only be set to '1' when the programmable IO is completely configured: '0': Disabled (signals are bypassed; behavior as if BYPASS is 0xFF). When disabled, the block (data unit and LUTs) reset is activated. If the IP is disabled: - The PIPELINE_EN register field should be set to '1', to ensure low power consumption by preventing combinatorial loops. - The CLOCK_SRC register field should be set to "20"- "30" (clock is constant '0'), to ensure low power consumption. '1': Enabled. Once enabled, it takes 3 "clk_block" clock cycles till the block reset is de-activated and the block becomes fully functional. This ensures that the IO pins' input synchronizer states are flushed when the block is fully functional. Default Value: 0
25	PIPELINE_EN	Enable for pipeline register: '0': Disabled (register is bypassed). '1': Enabled. Default Value: 1

15.1.1 PRGIO_PRT0_CTL (continued)

24	HLD_OVR	IO cell hold override functionality. In DeepSleep power mode, the HSIOM holds the IO cell output and output enable signals by default. This is undesirable if the PRGIO is supposed to deliver DeepSleep output functionality on these IO pads. This field is used to control the hold override functionality from the PRGIO: GPIO hold-override functionality in DeepSleep: '0': The HSIOM controls the GPIO functionality in DeepSleep '1': In bypass mode (ENABLED is '0' or BYPASS[i] is '1'), the HSIOM controls GPIO. In NON bypass mode (ENABLED is '1' and BYPASS[i] is '0'), the PRGIO controls the GPIO functionality in DeepSleep power mode. Default Value: Undefined
12 : 8	CLOCK_SRC	Clock ("clk_block") and reset ("rst_block_n") source selection: "0": io_data_in[0]/'1'. ... "7": io_data_in[7]/'1'. "8": chip_data[0]/'1'. ... "15": chip_data[7]/'1'. "16": clk_prgio/rst_sys_act_n. Used for Active mode synchronous logic on "clk_prgio". This selection is intended for synchronous operation on a PCLK specified clock frequency ("clock_prgio"). Note that the block's clocked elements are frequency aligned, but NOT phase aligned to "clk_sys". This selection asserts reset in any power mode other than Active i.e. PRGIO is active only in Active power mode with clock from peripheral divider "17": clk_prgio/rst_sys_dpslp_n. Used for DeepSleep mode synchronous logic on "clk_prgio" (note that "clk_prgio" is NOT available in DeepSleep power mode). This selection is intended for synchronous operation on a PCLK specified clock frequency ("clock_prgio"). This selection enables PRGIO in all power modes with clock from peripheral divider but the clock will not be active in DeepSleep power mode (i.e only asynchronous/combinational logics will work in DeepSleep). "19": clk_lf/rst_lf_dpslp_n (note that "clk_lf" is only available in DeepSleep power mode). This selection is intended for synchronous operation on "clk_lf". Note that the block's clocked elements are frequency aligned, but NOT phase aligned to other "clk_lf" clocked elements. This selection enables PRGIO in all power modes with clock from ILO (clk_lf) synchronous operations in DeepSleep will use clk_lf. "20"-"30": Clock source is constant '0'. Any of these clock sources should be selected when the IP is disabled to ensure low power consumption. "31": clk_sys/'1'. This selection is NOT intended for "clk_sys" operation, but for asynchronous operation: three "clk_sys" cycles after enabling the IP, the IP is fully functional (reset is de-activated). To be used for asynchronous (clockless) block functionality. Default Value: 20
7 : 0	BYPASS	Bypass of the programmable IO - BYPASS[i] is for IO pin i. '0': No bypass '1': Bypass Default Value: Undefined

15.1.2 PRGIO_PRT0_SYNC_CTL

Synchronization control register

Address: 0x40050010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	IO_SYNC_EN [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CHIP_SYNC_EN [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	CHIP_SYNC_EN	Synchronization of the chip input signals to "clk_block", one bit for each input: CHIP_SYNC_EN[i] is for input i. '0': No synchronization. '1': Synchronization. Default Value: Undefined
7 : 0	IO_SYNC_EN	Synchronization of the IO pin input signals to "clk_block", one bit for each IO pin: IO_SYNC_EN[i] is for IO pin i. '0': No synchronization. '1': Synchronization. Default Value: Undefined

15.1.3 PRGIO_PRT0_LUT_SEL0

LUT component input selection

Address: 0x40050020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.3 PRGIO_PRT0_LUT_SEL0 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.4 PRGIO_PRT0_LUT_SEL1

LUT component input selection

Address: 0x40050024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.4 PRGIO_PRT0_LUT_SEL1 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.5 PRGIO_PRT0_LUT_SEL2

LUT component input selection

Address: 0x40050028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.5 PRGIO_PRT0_LUT_SEL2 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.6 PRGIO_PRT0_LUT_SEL3

LUT component input selection

Address: 0x4005002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.6 PRGIO_PRT0_LUT_SEL3 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.7 PRGIO_PRT0_LUT_SEL4

LUT component input selection

Address: 0x40050030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.7 PRGIO_PRT0_LUT_SEL4 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.8 PRGIO_PRT0_LUT_SEL5

LUT component input selection

Address: 0x40050034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.8 PRGIO_PRT0_LUT_SEL5 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.9 PRGIO_PRT0_LUT_SEL6

LUT component input selection

Address: 0x40050038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			
Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			
Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.9 PRGIO_PRT0_LUT_SEL6 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.10 PRGIO_PRT0_LUT_SEL7

LUT component input selection

Address: 0x4005003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.10 PRGIO_PRT0_LUT_SEL7 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.11 PRGIO_PRT0_LUT_CTL0

LUT component control register

Address: 0x40050040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.11 PRGIO_PRT0_LUT_CTL0 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.12 PRGIO_PRT0_LUT_CTL1

LUT component control register

Address: 0x40050044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.12 PRGIO_PRT0_LUT_CTL1 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.13 PRGIO_PRT0_LUT_CTL2

LUT component control register

Address: 0x40050048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.13 PRGIO_PRT0_LUT_CTL2 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.14 PRGIO_PRT0_LUT_CTL3

LUT component control register

Address: 0x4005004C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq \text{if } (clr) '0' \text{ else if } (set) '1'$ Default Value: Undefined

15.1.14 PRGIO_PRT0_LUT_CTL3 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.15 PRGIO_PRT0_LUT_CTL4

LUT component control register

Address: 0x40050050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.15 PRGIO_PRT0_LUT_CTL4 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.16 PRGIO_PRT0_LUT_CTL5

LUT component control register

Address: 0x40050054

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq \text{if } (clr) '0' \text{ else if } (set) '1'$ Default Value: Undefined

15.1.16 PRGIO_PRT0_LUT_CTL5 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.17 PRGIO_PRT0_LUT_CTL6

LUT component control register

Address: 0x40050058

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq \text{if } (clr) '0' \text{ else if } (set) '1'$ Default Value: Undefined

15.1.17 PRGIO_PRT0_LUT_CTL6 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.18 PRGIO_PRT0_LUT_CTL7

LUT component control register

Address: 0x4005005C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq \text{if } (clr) '0' \text{ else if } (set) '1'$ Default Value: Undefined

15.1.18 PRGIO_PRT0_LUT_CTL7 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.19 PRGIO_PRT0_DU_SEL

Data unit component input selection

Address: 0x400500C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DU_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				DU_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				DU_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None		RW	
HW Access	None		R		None		R	
Name	None [31:30]		DU_DATA1_SEL [29:28]		None [27:26]		DU_DATA0_SEL [25:24]	

Bits	Name	Description
29 : 28	DU_DATA1_SEL	Data unit input data "data1_in" source selection. Encoding is the same as for DU_DATA0_SEL. Default Value: Undefined
25 : 24	DU_DATA0_SEL	Data unit input data "data0_in" source selection: "0": Constant "0". "1": chip_data[7:0]. "2": io_data_in[7:0]. "3": PRGIO_PRTx_DATA.DATA register field. Default Value: Undefined
19 : 16	DU_TR2_SEL	Data unit input signal "tr2_in" source selection. Encoding is the same as for DU_TR0_SEL. Default Value: Undefined
11 : 8	DU_TR1_SEL	Data unit input signal "tr1_in" source selection. Encoding is the same as for DU_TR0_SEL. Default Value: Undefined

15.1.19 PRGIO_PRT0_DU_SEL (continued)

3 : 0	DU_TR0_SEL	Data unit input signal "tr0_in" source selection: "0": Constant '0'. "1": Constant '1'. "2": Data unit output. "10-3": LUT 7 - 0 outputs. Otherwise: Undefined. Default Value: Undefined

15.1.20 PRGIO_PRT0_DU_CTL

Data unit component control register

Address: 0x400500C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					DU_SIZE [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:12]					DU_OPC [11:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 8	DU_OPC	Data unit opcode specifies the data unit operation: "1": INCR "2": DECR "3": INCR_WRAP "4": DECR_WRAP "5": INCR_DECR "6": INCR_DECR_WRAP "7": ROR "8": SHR "9": AND_OR "10": SHR_MAJ3 "11": SHR_EQL. Otherwise: Undefined. Default Value: Undefined
2 : 0	DU_SIZE	Size/width of the data unit data operands (in bits) is DU_SIZE+1. E.g., if DU_SIZE is 7, the width is 8 bits. Default Value: Undefined

15.1.21 PRGIO_PRT0_DATA

Data register

Address: 0x400500F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	Data unit input data source. Default Value: Undefined

15.1.22 PRGIO_PRT1_CTL

Control register

Address: 0x40050100

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	BYPASS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:13]				CLOCK_SRC [12:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	RW
HW Access	R	None					R	R
Name	ENABLED	None [30:26]					PIPE- LINE_EN	HLD_OVR

Bits	Name	Description
31	ENABLED	Enable for programmable IO. Should only be set to '1' when the programmable IO is completely configured: '0': Disabled (signals are bypassed; behavior as if BYPASS is 0xFF). When disabled, the block (data unit and LUTs) reset is activated. If the IP is disabled: - The PIPELINE_EN register field should be set to '1', to ensure low power consumption by preventing combinatorial loops. - The CLOCK_SRC register field should be set to "20"- "30" (clock is constant '0'), to ensure low power consumption. '1': Enabled. Once enabled, it takes 3 "clk_block" clock cycles till the block reset is de-activated and the block becomes fully functional. This ensures that the IO pins' input synchronizer states are flushed when the block is fully functional. Default Value: 0
25	PIPELINE_EN	Enable for pipeline register: '0': Disabled (register is bypassed). '1': Enabled. Default Value: 1

15.1.22 PRGIO_PRT1_CTL (continued)

24	HLD_OVR	IO cell hold override functionality. In DeepSleep power mode, the HSIOM holds the IO cell output and output enable signals by default. This is undesirable if the PRGIO is supposed to deliver DeepSleep output functionality on these IO pads. This field is used to control the hold override functionality from the PRGIO: GPIO hold-override functionality in DeepSleep: '0': The HSIOM controls the GPIO functionality in DeepSleep '1': In bypass mode (ENABLED is '0' or BYPASS[i] is '1'), the HSIOM controls GPIO. In NON bypass mode (ENABLED is '1' and BYPASS[i] is '0'), the PRGIO controls the GPIO functionality in DeepSleep power mode. Default Value: Undefined
12 : 8	CLOCK_SRC	Clock ("clk_block") and reset ("rst_block_n") source selection: "0": io_data_in[0]/'1'. ... "7": io_data_in[7]/'1'. "8": chip_data[0]/'1'. ... "15": chip_data[7]/'1'. "16": clk_prgio/rst_sys_act_n. Used for Active mode synchronous logic on "clk_prgio". This selection is intended for synchronous operation on a PCLK specified clock frequency ("clock_prgio"). Note that the block's clocked elements are frequency aligned, but NOT phase aligned to "clk_sys". This selection asserts reset in any power mode other than Active i.e. PRGIO is active only in Active power mode with clock from peripheral divider "17": clk_prgio/rst_sys_dpslp_n. Used for DeepSleep mode synchronous logic on "clk_prgio" (note that "clk_prgio" is NOT available in DeepSleep power mode). This selection is intended for synchronous operation on a PCLK specified clock frequency ("clock_prgio"). This selection enables PRGIO in all power modes with clock from peripheral divider but the clock will not be active in DeepSleep power mode (i.e only asynchronous/combinational logics will work in DeepSleep). "19": clk_lf/rst_lf_dpslp_n (note that "clk_lf" is only available in DeepSleep power mode). This selection is intended for synchronous operation on "clk_lf". Note that the block's clocked elements are frequency aligned, but NOT phase aligned to other "clk_lf" clocked elements. This selection enables PRGIO in all power modes with clock from ILO (clk_lf) synchronous operations in DeepSleep will use clk_lf. "20"-"30": Clock source is constant '0'. Any of these clock sources should be selected when the IP is disabled to ensure low power consumption. "31": clk_sys/'1'. This selection is NOT intended for "clk_sys" operation, but for asynchronous operation: three "clk_sys" cycles after enabling the IP, the IP is fully functional (reset is de-activated). To be used for asynchronous (clockless) block functionality. Default Value: 20
7 : 0	BYPASS	Bypass of the programmable IO - BYPASS[i] is for IO pin i. '0': No bypass '1': Bypass Default Value: Undefined

15.1.23 PRGIO_PRT1_SYNC_CTL

Synchronization control register

Address: 0x40050110

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	IO_SYNC_EN [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CHIP_SYNC_EN [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 8	CHIP_SYNC_EN	Synchronization of the chip input signals to "clk_block", one bit for each input: CHIP_SYNC_EN[i] is for input i. '0': No synchronization. '1': Synchronization. Default Value: Undefined
7 : 0	IO_SYNC_EN	Synchronization of the IO pin input signals to "clk_block", one bit for each IO pin: IO_SYNC_EN[i] is for IO pin i. '0': No synchronization. '1': Synchronization. Default Value: Undefined

15.1.24 PRGIO_PRT1_LUT_SEL0

LUT component input selection

Address: 0x40050120

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.24 PRGIO_PRT1_LUT_SEL0 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.25 PRGIO_PRT1_LUT_SEL1

LUT component input selection

Address: 0x40050124

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.25 PRGIO_PRT1_LUT_SEL1 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.26 PRGIO_PRT1_LUT_SEL2

LUT component input selection

Address: 0x40050128

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.26 PRGIO_PRT1_LUT_SEL2 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.27 PRGIO_PRT1_LUT_SEL3

LUT component input selection

Address: 0x4005012C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.27 PRGIO_PRT1_LUT_SEL3 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.28 PRGIO_PRT1_LUT_SEL4

LUT component input selection

Address: 0x40050130

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.28 PRGIO_PRT1_LUT_SEL4 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.29 PRGIO_PRT1_LUT_SEL5

LUT component input selection

Address: 0x40050134

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.29 PRGIO_PRT1_LUT_SEL5 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.30 PRGIO_PRT1_LUT_SEL6

LUT component input selection

Address: 0x40050138

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.30 PRGIO_PRT1_LUT_SEL6 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.31 PRGIO_PRT1_LUT_SEL7

LUT component input selection

Address: 0x4005013C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				LUT_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				LUT_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				LUT_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	LUT_TR2_SEL	LUT input signal "tr2_in" source selection. Encoding is the same as for LUT_TR1_SEL. Default Value: Undefined
11 : 8	LUT_TR1_SEL	LUT input signal "tr1_in" source selection: "0": LUT 0 output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.31 PRGIO_PRT1_LUT_SEL7 (continued)

3 : 0	LUT_TR0_SEL	LUT input signal "tr0_in" source selection: "0": Data unit output. "1": LUT 1 output. "2": LUT 2 output. "3": LUT 3 output. "4": LUT 4 output. "5": LUT 5 output. "6": LUT 6 output. "7": LUT 7 output. "8": chip_data[0] (for LUTs 0, 1, 2, 3); chip_data[4] (for LUTs 4, 5, 6, 7). "9": chip_data[1] (for LUTs 0, 1, 2, 3); chip_data[5] (for LUTs 4, 5, 6, 7). "10": chip_data[2] (for LUTs 0, 1, 2, 3); chip_data[6] (for LUTs 4, 5, 6, 7). "11": chip_data[3] (for LUTs 0, 1, 2, 3); chip_data[7] (for LUTs 4, 5, 6, 7). "12": io_data[0] (for LUTs 0, 1, 2, 3); io_data[4] (for LUTs 4, 5, 6, 7). "13": io_data[1] (for LUTs 0, 1, 2, 3); io_data[5] (for LUTs 4, 5, 6, 7). "14": io_data[2] (for LUTs 0, 1, 2, 3); io_data[6] (for LUTs 4, 5, 6, 7). "15": io_data[3] (for LUTs 0, 1, 2, 3); io_data[7] (for LUTs 4, 5, 6, 7). Default Value: Undefined

15.1.32 PRGIO_PRT1_LUT_CTL0

LUT component control register

Address: 0x40050140

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.32 PRGIO_PRT1_LUT_CTL0 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.33 PRGIO_PRT1_LUT_CTL1

LUT component control register

Address: 0x40050144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.33 PRGIO_PRT1_LUT_CTL1 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.34 PRGIO_PRT1_LUT_CTL2

LUT component control register

Address: 0x40050148

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.34 PRGIO_PRT1_LUT_CTL2 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.35 PRGIO_PRT1_LUT_CTL3

LUT component control register

Address: 0x4005014C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.35 PRGIO_PRT1_LUT_CTL3 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.36 PRGIO_PRT1_LUT_CTL4

LUT component control register

Address: 0x40050150

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq \text{if } (clr) '0' \text{ else if } (set) '1'$ Default Value: Undefined

15.1.36 PRGIO_PRT1_LUT_CTL4 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.37 PRGIO_PRT1_LUT_CTL5

LUT component control register

Address: 0x40050154

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.37 PRGIO_PRT1_LUT_CTL5 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.38 PRGIO_PRT1_LUT_CTL6

LUT component control register

Address: 0x40050158

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.38 PRGIO_PRT1_LUT_CTL6 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.39 PRGIO_PRT1_LUT_CTL7

LUT component control register

Address: 0x4005015C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	LUT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						LUT_OPC [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 8	LUT_OPC	LUT opcode specifies the LUT operation: "0": Combinatorial output, no feedback. $tr\_out = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. "1": Combinatorial output, feedback. $tr\_out = LUT[\{lut\_reg, tr1\_in, tr0\_in\}]$. On clock: $lut\_reg \leq tr\_in2$. "2": Sequential output, no feedback. $temp = LUT[\{tr2\_in, tr1\_in, tr0\_in\}]$. $tr\_out = lut\_reg$. On clock: $lut\_reg \leq temp$. "3": Register with asynchronous set and reset. $tr\_out = lut\_reg$. $enable = (tr2\_in \wedge LUT[4]) \vee LUT[5]$. $set = enable \wedge (tr1\_in \wedge LUT[2]) \wedge LUT[3]$. $clr = enable \wedge (tr0\_in \wedge LUT[0]) \wedge LUT[1]$. Asynchronously (no clock required): $lut\_reg \leq if (clr) '0' else if (set) '1'$ Default Value: Undefined

15.1.39 PRGIO_PRT1_LUT_CTL7 (continued)

7 : 0	LUT	LUT configuration. Depending on the LUT opcode LUT_OPC, the internal state lut_reg (captured in a flip-flop) and the LUT input signals tr0_in, tr1_in, tr2_in, the LUT configuration is used to determine the LUT output signal and the next sequential state (lut_reg). Default Value: Undefined

15.1.40 PRGIO_PRT1_DU_SEL

Data unit component input selection

Address: 0x400501C0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DU_TR0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW			
HW Access	None				R			
Name	None [15:12]				DU_TR1_SEL [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				DU_TR2_SEL [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None		RW	
HW Access	None		R		None		R	
Name	None [31:30]		DU_DATA1_SEL [29:28]		None [27:26]		DU_DATA0_SEL [25:24]	

Bits	Name	Description
29 : 28	DU_DATA1_SEL	Data unit input data "data1_in" source selection. Encoding is the same as for DU_DATA0_SEL. Default Value: Undefined
25 : 24	DU_DATA0_SEL	Data unit input data "data0_in" source selection: "0": Constant "0". "1": chip_data[7:0]. "2": io_data_in[7:0]. "3": PRGIO_PRTx_DATA.DATA register field. Default Value: Undefined
19 : 16	DU_TR2_SEL	Data unit input signal "tr2_in" source selection. Encoding is the same as for DU_TR0_SEL. Default Value: Undefined
11 : 8	DU_TR1_SEL	Data unit input signal "tr1_in" source selection. Encoding is the same as for DU_TR0_SEL. Default Value: Undefined

15.1.40 PRGIO_PRT1_DU_SEL (continued)

3 : 0	DU_TR0_SEL	Data unit input signal "tr0_in" source selection: "0": Constant '0'. "1": Constant '1'. "2": Data unit output. "10-3": LUT 7 - 0 outputs. Otherwise: Undefined. Default Value: Undefined

15.1.41 PRGIO_PRT1_DU_CTL

Data unit component control register

Address: 0x400501C4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					DU_SIZE [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:12]					DU_OPC [11:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 8	DU_OPC	Data unit opcode specifies the data unit operation: "1": INCR "2": DECR "3": INCR_WRAP "4": DECR_WRAP "5": INCR_DECR "6": INCR_DECR_WRAP "7": ROR "8": SHR "9": AND_OR "10": SHR_MAJ3 "11": SHR_EQL. Otherwise: Undefined. Default Value: Undefined
2 : 0	DU_SIZE	Size/width of the data unit data operands (in bits) is DU_SIZE+1. E.g., if DU_SIZE is 7, the width is 8 bits. Default Value: Undefined

15.1.42 PRGIO_PRT1_DATA

Data register

Address: 0x400501F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	DATA	Data unit input data source. Default Value: Undefined

16 CoreSight ROM Table Registers



This section discusses the ROM Table registers. It lists all the registers in mapping tables, in address order.

16.1 Register Details

Register Name	Address
ROMTABLE_ADDR	0xF0000000
ROMTABLE_DID	0xF0000FCC
ROMTABLE_PID4	0xF0000FD0
ROMTABLE_PID5	0xF0000FD4
ROMTABLE_PID6	0xF0000FD8
ROMTABLE_PID7	0xF0000FDC
ROMTABLE_PID0	0xF0000FE0
ROMTABLE_PID1	0xF0000FE4
ROMTABLE_PID2	0xF0000FE8
ROMTABLE_PID3	0xF0000FEC
ROMTABLE_CID0	0xF0000FF0
ROMTABLE_CID1	0xF0000FF4
ROMTABLE_CID2	0xF0000FF8
ROMTABLE_CID3	0xF0000FFC

16.1.1 ROMTABLE_ADDR

Link to Cortex M0 ROM Table.

Address: 0xF0000000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						R	R
Name	None [7:2]						FOR-MAT_32BIT	PRESENT

Bits	15	14	13	12	11	10	9	8
SW Access	R				None			
HW Access	R				None			
Name	ADDR_OFFSET [15:12]				None [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	ADDR_OFFSET [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	ADDR_OFFSET [31:24]							

Bits	Name	Description
31 : 12	ADDR_OFFSET	Address offset of the Cortex-M0 ROM Table base address (0xe00f:f000) wrt. Cypress chip specific ROM Table base address (0xf000:0000). ADDR_OFFSET[19:0] = 0xe00f:f - 0xf000:0 = 0xf00f:f. Default Value: 983295
1	FORMAT_32BIT	ROM Table format: '0': 8-bit format. '1': 32-bit format. Default Value: 1
0	PRESENT	Entry present. Default Value: 1

16.1.2 ROMTABLE_DID

Device Type Identifier register.

Address: 0xF0000FCC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 1

16.1.3 ROMTABLE_PID4

Peripheral Identification Register 4.

Address: 0xF000FD0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	COUNT [7:4]				JEP_CONTINUATION [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	COUNT	Size of ROM Table is $2^{\text{COUNT}} \times 4$ KByte. Default Value: 0
3 : 0	JEP_CONTINUATION	JEP106 continuation code. This value is product specific and specified as part of the product definition in the CPUSS.JEPCONTINUATION parameter. Default Value: Undefined

16.1.4 ROMTABLE_PID5

Peripheral Identification Register 5.

Address: 0xF0000FD4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

16.1.5 ROMTABLE_PID6

Peripheral Identification Register 6.

Address: 0xF0000FD8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

16.1.6 ROMTABLE_PID7

Peripheral Identification Register 7.

Address: 0xF0000FDC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	. Default Value: 0

16.1.7 ROMTABLE_PID0

Peripheral Identification Register 0.

Address: 0xF0000FE0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	PN_MIN [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	PN_MIN	JEP106 part number. 4 lsbs of CPUSS.PARTNUMBER parameter. These part numbers are maintained in spec 40-9500. Default Value: Undefined

16.1.8 ROMTABLE_PID1

Peripheral Identification Register 1.

Address: 0xF0000FE4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	JEPID_MIN [7:4]				PN_MAJ [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	JEPID_MIN	JEP106 vendor id. 4 lsbs of CPUSS.JEPID parameter. This number is maintained in spec 40-9500. Default Value: Undefined
3 : 0	PN_MAJ	JEP106 part number. 4 msbs of CPUSS.PARTNUMBER parameter. These part numbers are maintained in spec 40-9500. Default Value: Undefined

16.1.9 ROMTABLE_PID2

Peripheral Identification Register 2.

Address: 0xF0000FE8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				None	R		
HW Access	R				None	R		
Name	REV [7:4]				None	JEPID_MAJ [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	REV	Major REVision number (chip specific). Identifies the design iteration of the component. For first tape out: 0x1. This field is implemented in RTL by an ECO-able tie-off structure and is incremented on subsequent tape outs. Default Value: Undefined
2 : 0	JEPID_MAJ	JEP106 vendor id. 4 msbs of CPUSS.JEPID parameter. This number is maintained in spec 40-9500. Default Value: Undefined

16.1.10 ROMTABLE_PID3

Peripheral Identification Register 3.

Address: 0xF0000FEC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R				R			
HW Access	R				R			
Name	REV_AND [7:4]				CM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	REV_AND	Minor REVersion number (chip specific). For first tape out: 0x1. This field is implemented in RTL by an ECO-able tie-off structure and is incremented on subsequent tape outs. Default Value: Undefined
3 : 0	CM	Customer modified field. This field is used to track modifications to the original component design as a result of component IP reuse. Default Value: 0

16.1.11 ROMTABLE_CID0

Component Identification Register 0.

Address: 0xF0000FF0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 0 of 4-byte component identification 0xB105:100D. Default Value: 13

16.1.12 ROMTABLE_CID1

Component Identification Register 1.

Address: 0xF0000FF4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 1 of 4-byte component identification 0xB105:100D. Component class: "ROM Table". Default Value: 16

16.1.13 ROMTABLE_CID2

Component Identification Register 2.

Address: 0xF0000FF8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 2 of 4-byte component identification 0xB105:100D. Default Value: 5

16.1.14 ROMTABLE_CID3

Component Identification Register 3.

Address: 0xF0000FFC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	R							
Name	VALUE [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	R							
Name	VALUE [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	R							
Name	VALUE [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	R							
Name	VALUE [31:24]							

Bits	Name	Description
31 : 0	VALUE	Component identification byte 3 of 4-byte component identification 0xB105:100D. Default Value: 177

17 SAR Registers



This section discusses the SAR registers. It lists all the registers in mapping tables, in address order.

17.1 Register Details

Register Name	Address
SAR_CTRL	0x403A0000
SAR_SAMPLE_CTRL	0x403A0004
SAR_SAMPLE_TIME01	0x403A0010
SAR_SAMPLE_TIME23	0x403A0014
SAR_RANGE_THRES	0x403A0018
SAR_RANGE_COND	0x403A001C
SAR_CHAN_EN	0x403A0020
SAR_START_CTRL	0x403A0024
SAR_DFT_CTRL	0x403A0030
SAR_CHAN_CONFIG0	0x403A0080
SAR_CHAN_CONFIG1	0x403A0084
SAR_CHAN_CONFIG2	0x403A0088
SAR_CHAN_CONFIG3	0x403A008C
SAR_CHAN_CONFIG4	0x403A0090
SAR_CHAN_CONFIG5	0x403A0094
SAR_CHAN_CONFIG6	0x403A0098
SAR_CHAN_CONFIG7	0x403A009C
SAR_CHAN_CONFIG8	0x403A00A0
SAR_CHAN_CONFIG9	0x403A00A4
SAR_CHAN_CONFIG10	0x403A00A8
SAR_CHAN_CONFIG11	0x403A00AC
SAR_CHAN_CONFIG12	0x403A00B0
SAR_CHAN_CONFIG13	0x403A00B4
SAR_CHAN_CONFIG14	0x403A00B8
SAR_CHAN_CONFIG15	0x403A00BC
SAR_CHAN_WORK0	0x403A0100
SAR_CHAN_WORK1	0x403A0104

Register Name	Address
SAR_CHAN_WORK2	0x403A0108
SAR_CHAN_WORK3	0x403A010C
SAR_CHAN_WORK4	0x403A0110
SAR_CHAN_WORK5	0x403A0114
SAR_CHAN_WORK6	0x403A0118
SAR_CHAN_WORK7	0x403A011C
SAR_CHAN_WORK8	0x403A0120
SAR_CHAN_WORK9	0x403A0124
SAR_CHAN_WORK10	0x403A0128
SAR_CHAN_WORK11	0x403A012C
SAR_CHAN_WORK12	0x403A0130
SAR_CHAN_WORK13	0x403A0134
SAR_CHAN_WORK14	0x403A0138
SAR_CHAN_WORK15	0x403A013C
SAR_CHAN_RESULT0	0x403A0180
SAR_CHAN_RESULT1	0x403A0184
SAR_CHAN_RESULT2	0x403A0188
SAR_CHAN_RESULT3	0x403A018C
SAR_CHAN_RESULT4	0x403A0190
SAR_CHAN_RESULT5	0x403A0194
SAR_CHAN_RESULT6	0x403A0198
SAR_CHAN_RESULT7	0x403A019C
SAR_CHAN_RESULT8	0x403A01A0
SAR_CHAN_RESULT9	0x403A01A4
SAR_CHAN_RESULT10	0x403A01A8
SAR_CHAN_RESULT11	0x403A01AC
SAR_CHAN_RESULT12	0x403A01B0
SAR_CHAN_RESULT13	0x403A01B4
SAR_CHAN_RESULT14	0x403A01B8
SAR_CHAN_RESULT15	0x403A01BC
SAR_CHAN_WORK_VALID	0x403A0200
SAR_CHAN_RESULT_VALID	0x403A0204
SAR_STATUS	0x403A0208
SAR_AVG_STAT	0x403A020C
SAR_INTR	0x403A0210
SAR_INTR_SET	0x403A0214
SAR_INTR_MASK	0x403A0218
SAR_INTR_MASKED	0x403A021C
SAR_SATURATE_INTR	0x403A0220
SAR_SATURATE_INTR_SET	0x403A0224
SAR_SATURATE_INTR_MASK	0x403A0228
SAR_SATURATE_INTR_MASKED	0x403A022C

Register Name	Address
SAR_RANGE_INTR	0x403A0230
SAR_RANGE_INTR_SET	0x403A0234
SAR_RANGE_INTR_MASK	0x403A0238
SAR_RANGE_INTR_MASKED	0x403A023C
SAR_INTR_CAUSE	0x403A0240
SAR_INJ_CHAN_CONFIG	0x403A0280
SAR_INJ_RESULT	0x403A0290
SAR_MUX_SWITCH0	0x403A0300
SAR_MUX_SWITCH_CLEAR0	0x403A0304
SAR_MUX_SWITCH1	0x403A0308
SAR_MUX_SWITCH_CLEAR1	0x403A030C
SAR_MUX_SWITCH_HW_CTRL	0x403A0340
SAR_MUX_SWITCH_STATUS	0x403A0348
SAR_PUMP_CTRL	0x403A0380
SAR_ANA_TRIM	0x403A0F00
SAR_WOUNDING	0x403A0F04

17.1.1 SAR_CTRL

Analog control register.

Address: 0x403A0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW			None			
HW Access	R	R			None			
Name	VREF_BY-P_CAP_EN	VREF_SEL [6:4]			None [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW		RW	None	RW			None
HW Access	R		R	None	R			None
Name	PWR_CTRL_VREF [15:14]		SAR_HW_CTRL_NEG_VREF	None	NEG_SEL [11:9]			None

Bits	23	22	21	20	19	18	17	16
SW Access	None			RW	RW			
HW Access	None			R	R			
Name	None [23:21]			BOOST-PUMP_EN	SPARE [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	RW	RW	RW	None	RW	
HW Access	R	R	R	R	R	None	R	
Name	ENABLED	SWITCH_DISABLE	DSI_MODE	DSI_SYN-C_CONFIG	DEEPSLEEP_ON	None	ICONT_LV [25:24]	

Bits	Name	Description
31	ENABLED	Before enabling always make sure the SAR is idle (STATUS.BUSY==0) - 0: SAR IP disabled (put analog in power down and stop clocks), also can clear FW_TRIGGER and INJ_START_EN (if not tailgating) on write. - 1: SAR IP enabled. Default Value: 0
30	SWITCH_DISABLE	Disable SAR sequencer from enabling routing switches (note DSI and firmware can always close switches independent of this control) - 0: Normal mode, SAR sequencer changes switches according to pin address in channel configurations - 1: Switches disabled, SAR sequencer does not enable any switches, it is the responsibility of the firmware or UDBs (through DSI) to set the switches to route the signal to be converted through the SARMUX Default Value: 0

17.1.1 SAR_CTRL (continued)

29	DSI_MODE	SAR sequencer takes configuration from DSI signals (note this also has the same effect as SWITCH_DISABLE==1) - 0: Normal mode, SAR sequencer operates according to CHAN_EN enables and CHAN_CONFIG channel configurations - 1: CHAN_EN, INJ_START_EN and channel configurations in CHAN_CONFIG and INJ_CHAN_CONFIG are ignored Default Value: 0
28	DSI_SYNC_CONFIG	- 0: bypass clock domain synchronisation of the DSI config signals. - 1: synchronize the DSI config signals to peripheral clock domain. Default Value: 1
27	DEEPSLEEP_ON	- 0: SARMUX IP disabled off during DeepSleep power mode - 1: SARMUX IP remains enabled during DeepSleep power mode (if ENABLED=1) Default Value: 0
25 : 24	ICONT_LV	SARADC low power mode. Default Value: 0 0x0: NORMAL_PWR: normal power (default), max clk_sar is 18MHz. 0x1: HALF_PWR: 1/2 power mode, max clk_sar is 9MHz. 0x2: MORE_PWR: 1.333 power mode, max clk_sar is 18MHz. 0x3: QUARTER_PWR: 1/4 power mode, max clk_sar is 4.5MHz.
20	BOOSTPUMP_EN	SARADC internal pump: 0=disabled: pump output is VDDA, 1=enabled: pump output is boosted. Default Value: 0
19 : 16	SPARE	Spare controls, not yet designated, for late changes done with an ECO Default Value: 0
15 : 14	PWR_CTRL_VREF	VREF buffer low power mode. Default Value: 0 0x0: NORMAL_PWR: normal power (default), bypass cap, max clk_sar is 18MHz. 0x1: HALF_PWR: deprecated 0x2: THIRD_PWR: Invalid for PSoC4A, otherwise 2X power, no bypass cap, max clk_sar is 1.8MHz 0x3: QUARTER_PWR: deprecated
13	SAR_HW_CTRL_NEGVREF	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for VREF to NEG switch. Default Value: 0
11 : 9	NEG_SEL	SARADC internal NEG selection for Single ended conversion Default Value: 0 0x0: VSSA_KELVIN: NEG input of SARADC is connected to "vssa_kelvin", gives more precision around zero. Note this opens both SARADC internal switches, therefore use this value to insert a break-before-make cycle on those switches when SWITCH_DISABLE is high.

17.1.1 SAR_CTRL (continued)

		0x1: ART_VSSA: NEG input of SARADC is connected to VSSA in AROUTE close to the SARADC
		0x2: P1: NEG input of SARADC is connected to P1 pin of SARMUX
		0x3: P3: NEG input of SARADC is connected to P3 pin of SARMUX
		0x4: P5: NEG input of SARADC is connected to P5 pin of SARMUX
		0x5: P7: NEG input of SARADC is connected to P7 pin of SARMUX
		0x6: ACORE: NEG input of SARADC is connected to an ACORE in AROUTE
		0x7: VREF: NEG input of SARADC is shorted with VREF input of SARADC.
7	VREF_BYP_CAP_EN	VREF bypass cap enable for when VREF buffer is on Default Value: 0
6 : 4	VREF_SEL	SARADC internal VREF selection. Default Value: 0
		0x0: VREF0: VREF0 from PRB (VREF buffer on)
		0x1: VREF1: VREF1 from PRB (VREF buffer on)
		0x2: VREF2: VREF2 from PRB (VREF buffer on)
		0x3: VREF_AROUTE: VREF from AROUTE (VREF buffer on)
		0x4: VBGR: 1.024V from BandGap (VREF buffer on)
		0x5: VREF_EXT: External precision Vref direct from a pin (low impedance path).
		0x6: VDDA_DIV_2: Vdda/2 (VREF buffer on)
		0x7: VDDA: Vdda.

17.1.2 SAR_SAMPLE_CTRL

Sample control register.

Address: 0x403A0004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW			RW	RW	RW	RW
HW Access	R	R			R	R	R	R
Name	AVG_SHIFT	AVG_CNT [6:4]			DIFFERENTIAL_SIGNED	SINGLE_ENDED_SIGNED	LEFT_ALIGN	SUB_RESOLUTION

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [23:20]				DSI_SYNC_TRIGGER	DSI_TRIGGER_LEVEL	DSI_TRIGGER_EN	CONTINUOUS

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	EOS_DSIOUT_EN	None [30:24]						

Bits	Name	Description
31	EOS_DSIOUT_EN	Enable to output EOS_INTR to DSI. When enabled each time EOS_INTR is set by the hardware also a pulse is send on the dsi_eos signal. Default Value: 0
19	DSI_SYNC_TRIGGER	- 0: bypass clock domain synchronisation of the DSI trigger signal. - 1: synchronize the DSI trigger signal to the SAR clock domain, if needed an edge detect is done in the peripheral clock domain. Default Value: 1
18	DSI_TRIGGER_LEVEL	- 0: DSI trigger signal is a pulse input, a positive edge detected on the DSI trigger signal triggers a new scan. - 1: DSI trigger signal is a level input, as long as the DSI trigger signal remains high the SAR will do continuous scans. Default Value: 0

17.1.2 SAR_SAMPLE_CTRL (continued)

17	DSI_TRIGGER_EN	- 0: firmware trigger only: disable hardware (DSI) trigger. - 1: enable hardware (DSI) trigger (e.g. from TCPWM, GPIO or UDB). Default Value: 0
16	CONTINUOUS	- 0: Wait for next FW_TRIGGER (one shot) or hardware (DSI) trigger (e.g. from TPWM for periodic triggering) before scanning enabled channels. - 1: Continuously scan enabled channels, ignore triggers. Default Value: 0
7	AVG_SHIFT	Averaging shifting: after averaging the result is shifted right to fit in the sample resolution. For averaging the sample resolution is the highest resolution allowed by rounding. Default Value: 0
6 : 4	AVG_CNT	Averaging Count for channels that have over sampling enabled (AVG_EN). A channel will be sampled back to back $(1 \leq \text{AVG\_CNT} + 1) = [2..256]$ times before the result is stored and the next enabled channel is sampled (1st order accumulate and dump filter). If shifting is not enabled (AVG_SHIFT=0) then the result is forced to shift right so that it fits in 16 bits, so right shift is done by $\max(0, \text{AVG\_CNT} - 3)$. Default Value: 0
3	DIFFERENTIAL_SIGNED	Output data from a differential conversion as a signed value Default Value: 1 0x0: UNSIGNED: result data is unsigned (zero extended if needed) 0x1: SIGNED: Default: result data is signed (sign extended if needed)
2	SINGLE_ENDED_SIGNED	Output data from a single ended conversion as a signed value Default Value: 0 0x0: UNSIGNED: Default: result data is unsigned (zero extended if needed) 0x1: SIGNED: result data is signed (sign extended if needed)
1	LEFT_ALIGN	Left align data in data[15:0], default data is right aligned in data[11:0], with sign extension to 16 bits if the channel is differential. Default Value: 0
0	SUB_RESOLUTION	Conversion resolution for channels that have sub-resolution enabled (RESOLUTION=1) (otherwise resolution is 12-bit). Default Value: 0 0x0: 8B: 8-bit. 0x1: 10B: 10-bit.

17.1.3 SAR_SAMPLE_TIME01

Sample time specification ST0 and ST1

Address: 0x403A0010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						SAMPLE_TIME0 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						SAMPLE_TIME1 [25:24]	

Bits	Name	Description
25 : 16	SAMPLE_TIME1	Sample time1 Default Value: 4
9 : 0	SAMPLE_TIME0	Sample time0 (aperture) in ADC clock cycles. Note that actual sample time is half a clock less than specified here. The minimum sample time is 194ns, which is 3.5 cycles (4 in this field) with an 18MHz clock. Minimum legal value in this register is 2. Default Value: 4

17.1.4 SAR_SAMPLE_TIME23

Sample time specification ST2 and ST3

Address: 0x403A0014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME2 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						SAMPLE_TIME2 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	SAMPLE_TIME3 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						SAMPLE_TIME3 [25:24]	

Bits	Name	Description
25 : 16	SAMPLE_TIME3	Sample time3 Default Value: 4
9 : 0	SAMPLE_TIME2	Sample time2 Default Value: 4

17.1.5 SAR_RANGE_THRES

Global range detect threshold register.

Address: 0x403A0018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RANGE_LOW [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RANGE_LOW [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	RANGE_HIGH [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	RANGE_HIGH [31:24]							

Bits	Name	Description
31 : 16	RANGE_HIGH	High threshold for range detect. Default Value: 0
15 : 0	RANGE_LOW	Low threshold for range detect. Default Value: 0

17.1.6 SAR_RANGE_COND

Global range detect mode register.

Address: 0x403A001C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None					
HW Access	R		None					
Name	RANGE_COND [31:30]		None [29:24]					

Bits	Name	Description
31 : 30	RANGE_COND	Range condition select. Default Value: 0 0x0: BELOW: result < RANGE_LOW 0x1: INSIDE: RANGE_LOW <= result < RANGE_HIGH 0x2: ABOVE: RANGE_HIGH <= result 0x3: OUTSIDE: result < RANGE_LOW RANGE_HIGH <= result

17.1.7 SAR_CHAN_EN

Enable bits for the channels

Address: 0x403A0020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	CHAN_EN [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	CHAN_EN [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_EN	Channel enable. - 0: the corresponding channel is disabled. - 1: the corresponding channel is enabled, it will be included in the next scan. Default Value: 0

17.1.8 SAR_START_CTRL

Start control register (firmware trigger).

Address: 0x403A0024

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1S
HW Access	None							RW1C
Name	None [7:1]							FW_TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	FW_TRIGGER	When firmware writes a 1 here it will trigger the next scan of enabled channels, hardware clears this bit when the scan started with this trigger is completed. If scanning continuously the trigger is ignored and hardware clears this bit after the next scan is done. This bit is also cleared when the SAR is disabled. Default Value: 0

17.1.9 SAR_DFT_CTRL

DFT control register.

Address: 0x403A0030

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						HIZ	DLY_INC

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None	RW			RW			
HW Access	None	R			R			
Name	None	DFT_OUTC [22:20]			DFT_INC [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None	RW	RW	RW			
HW Access	R	None	R	R	R			
Name	AD- FT_OVER- RIDE	None	DCEN	EN_CSEL_ DFT	SEL_CSEL_DFT [27:24]			

Bits	Name	Description
31	ADFT_OVERRIDE	During deepsleep/ hibernate mode keep SARMUX active, i.e. do not open all switches (disconnect), to be used for ADFT Default Value: 0
29	DCEN	Delay Control Enable for latch. - 0: doubles the latch enable time. - 1: normal latch enable time (default). Default Value: 0
28	EN_CSEL_DFT	Mux select signal for DAC control Default Value: 0
27 : 24	SEL_CSEL_DFT	Usage 1: DFT bits for DAC array Usage 2: For [0]=1 (when dcen=0): Delay timing for latch enable increased by 20% [1]=1: comparator preamp power level increased by 25% Default Value: 0
22 : 20	DFT_OUTC	DFT control for preamp outputs Default Value: 0

17.1.9 SAR_DFT_CTRL (continued)

19 : 16	DFT_INC	DFT control for preamp inputs Default Value: 0
1	HIZ	DFT control for getting higher input impedance, must be 1 (0 is deprecated) Default Value: 1
0	DLY_INC	DFT control: Control for delay circuits on sampling phase, =1 doubles the non-overlap delay Default Value: 0

17.1.10 SAR_CHAN_CONFIG0

Channel configuration register.

Address: 0x403A0080

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.10 SAR_CHAN_CONFIG0 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.11 SAR_CHAN_CONFIG1

Channel configuration register.

Address: 0x403A0084

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.11 SAR_CHAN_CONFIG1 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.12 SAR_CHAN_CONFIG2

Channel configuration register.

Address: 0x403A0088

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.12 SAR_CHAN_CONFIG2 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.13 SAR_CHAN_CONFIG3

Channel configuration register.

Address: 0x403A008C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.13 SAR_CHAN_CONFIG3 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.14 SAR_CHAN_CONFIG4

Channel configuration register.

Address: 0x403A0090

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.14 SAR_CHAN_CONFIG4 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.15 SAR_CHAN_CONFIG5

Channel configuration register.

Address: 0x403A0094

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.15 SAR_CHAN_CONFIG5 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.16 SAR_CHAN_CONFIG6

Channel configuration register.

Address: 0x403A0098

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.16 SAR_CHAN_CONFIG6 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.17 SAR_CHAN_CONFIG7

Channel configuration register.

Address: 0x403A009C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.17 SAR_CHAN_CONFIG7 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 0x0: SARMUX: SARMUX pins. 0x1: CTB0: CTB0 0x2: CTB1: CTB1 0x3: CTB2: CTB2 0x4: CTB3: CTB3 0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2) 0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1) 0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.18 SAR_CHAN_CONFIG8

Channel configuration register.

Address: 0x403A00A0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.18 SAR_CHAN_CONFIG8 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.19 SAR_CHAN_CONFIG9

Channel configuration register.

Address: 0x403A00A4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.19 SAR_CHAN_CONFIG9 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.20 SAR_CHAN_CONFIG10

Channel configuration register.

Address: 0x403A00A8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.20 SAR_CHAN_CONFIG10 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.21 SAR_CHAN_CONFIG11

Channel configuration register.

Address: 0x403A00AC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.21 SAR_CHAN_CONFIG11 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.22 SAR_CHAN_CONFIG12

Channel configuration register.

Address: 0x403A00B0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.22 SAR_CHAN_CONFIG12 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.23 SAR_CHAN_CONFIG13

Channel configuration register.

Address: 0x403A00B4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.23 SAR_CHAN_CONFIG13 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.24 SAR_CHAN_CONFIG14

Channel configuration register.

Address: 0x403A00B8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.24 SAR_CHAN_CONFIG14 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on winding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.25 SAR_CHAN_CONFIG15

Channel configuration register.

Address: 0x403A00BC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	PORT_ADDR [6:4]			None	PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		SAMPLE_TIME_SEL [13:12]		None	AVG_EN	RESOLUTION	DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	DSI_OUT_EN	None [30:24]						

Bits	Name	Description
31	DSI_OUT_EN	DSI data output enable for this channel. - 0: the conversion result for this channel is only stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. - 1: the conversion result for this channel is stored in the channel data register and the corresponding CHAN_DATA_VALID bit is set. The same data (same formatting), together with the channel number, is sent out on the DSI communication channel for processing in UDBs. Default Value: 0
13 : 12	SAMPLE_TIME_SEL	Sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0
9	RESOLUTION	Resolution for this channel. When AVG_EN is set this bit is ignored and always a 12-bit resolution (or highest resolution allowed by rounding) is used for this channel. Default Value: 0

17.1.25 SAR_CHAN_CONFIG15 (continued)

		0x0: MAXRES: The maximum resolution is used for this channel (maximum resolution depends on wounding).
		0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0
		0x0: SARMUX: SARMUX pins.
		0x1: CTB0: CTB0
		0x2: CTB1: CTB1
		0x3: CTB2: CTB2
		0x4: CTB3: CTB3
		0x5: AROUTE_VIRT2: AROUTE virtual port2 (VPORT2)
		0x6: AROUTE_VIRT1: AROUTE virtual port1 (VPORT1)
		0x7: SARMUX_VIRT: SARMUX virtual port (VPORT0)
2 : 0	PIN_ADDR	Address of the pin to be sampled by this channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. For differential the even pin of the pair is connected to Vplus and the odd pin of the pair is connected to Vminus. Default Value: 0

17.1.26 SAR_CHAN_WORK0

Channel working data register

Address: 0x403A0100

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.27 SAR_CHAN_WORK1

Channel working data register

Address: 0x403A0104

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.28 SAR_CHAN_WORK2

Channel working data register

Address: 0x403A0108

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.29 SAR_CHAN_WORK3

Channel working data register

Address: 0x403A010C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.30 SAR_CHAN_WORK4

Channel working data register

Address: 0x403A0110

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.31 SAR_CHAN_WORK5

Channel working data register

Address: 0x403A0114

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.32 SAR_CHAN_WORK6

Channel working data register

Address: 0x403A0118

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.33 SAR_CHAN_WORK7

Channel working data register

Address: 0x403A011C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.34 SAR_CHAN_WORK8

Channel working data register

Address: 0x403A0120

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.35 SAR_CHAN_WORK9

Channel working data register

Address: 0x403A0124

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.36 SAR_CHAN_WORK10

Channel working data register

Address: 0x403A0128

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.37 SAR_CHAN_WORK11

Channel working data register

Address: 0x403A012C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.38 SAR_CHAN_WORK12

Channel working data register

Address: 0x403A0130

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.39 SAR_CHAN_WORK13

Channel working data register

Address: 0x403A0134

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.40 SAR_CHAN_WORK14

Channel working data register

Address: 0x403A0138

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.41 SAR_CHAN_WORK15

Channel working data register

Address: 0x403A013C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WORK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WORK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	None						
HW Access	W	None						
Name	CHAN_WORK_VALID_MIR	None [30:24]						

Bits	Name	Description
31	CHAN_WORK_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_WORK_VALID register Default Value: 0
15 : 0	WORK	SAR conversion working data of the channel. The data is written here right after sampling this channel. Default Value: Undefined

17.1.42 SAR_CHAN_RESULT0

Channel result data register

Address: 0x403A0180

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.43 SAR_CHAN_RESULT1

Channel result data register

Address: 0x403A0184

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.44 SAR_CHAN_RESULT2

Channel result data register

Address: 0x403A0188

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.45 SAR_CHAN_RESULT3

Channel result data register

Address: 0x403A018C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.46 SAR_CHAN_RESULT4

Channel result data register

Address: 0x403A0190

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE- SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.47 SAR_CHAN_RESULT5

Channel result data register

Address: 0x403A0194

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.48 SAR_CHAN_RESULT6

Channel result data register

Address: 0x403A0198

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.49 SAR_CHAN_RESULT7

Channel result data register

Address: 0x403A019C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE- SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.50 SAR_CHAN_RESULT8

Channel result data register

Address: 0x403A01A0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE- SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.51 SAR_CHAN_RESULT9

Channel result data register

Address: 0x403A01A4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.52 SAR_CHAN_RESULT10

Channel result data register

Address: 0x403A01A8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.53 SAR_CHAN_RESULT11

Channel result data register

Address: 0x403A01AC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE- SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.54 SAR_CHAN_RESULT12

Channel result data register

Address: 0x403A01B0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE- SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.55 SAR_CHAN_RESULT13

Channel result data register

Address: 0x403A01B4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE-SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.56 SAR_CHAN_RESULT14

Channel result data register

Address: 0x403A01B8

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE- SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.57 SAR_CHAN_RESULT15

Channel result data register

Address: 0x403A01BC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	None				
HW Access	W	W	W	None				
Name	CHAN_RE- SULT_VALID_MIR	RANGE_INTR_MIR	SATURATE_INTR_MIR	None [28:24]				

Bits	Name	Description
31	CHAN_RE-SULT_VALID_MIR	mirror bit of corresponding bit in SAR_CHAN_RESULT_VALID register Default Value: 0
30	RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_RANGE_INTR register Default Value: 0
29	SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_SATURATE_INTR register Default Value: 0
15 : 0	RESULT	SAR conversion result of the channel. The data is copied here from the WORK field after all enabled channels in this scan have been sampled. Default Value: Undefined

17.1.58 SAR_CHAN_WORK_VALID

Channel working data register valid bits

Address: 0x403A0200

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_VALID [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_WORK_VALID [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_WORK_VALID	If set the corresponding WORK data is valid, i.e. was already sampled during the current scan. Default Value: 0

17.1.59 SAR_CHAN_RESULT_VALID

Channel result data register valid bits

Address: 0x403A0204

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_VALID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	CHAN_RESULT_VALID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	CHAN_RESULT_VALID	If set the corresponding RESULT data is valid, i.e. was sampled during the last scan. Default Value: 0

17.1.60 SAR_STATUS

Current status of internal SAR registers (mostly for debug)

Address: 0x403A0208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			CUR_CHAN [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	BUSY	SW_VREF_NEG	None [29:24]					

Bits	Name	Description
31	BUSY	If high then the SAR is busy with a conversion. This bit is always high when CONTINUOUS is set. Firmware should wait for this bit to be low before putting the SAR in power down. Default Value: 0
30	SW_VREF_NEG	the current switch status, including DSI and sequencer controls, of the switch in the SARADC that shorts NEG with VREF input (see NEG_SEL). Default Value: 0
4 : 0	CUR_CHAN	current channel being sampled (channel 16 indicates the injection channel), only valid if BUSY. Default Value: 0

17.1.61 SAR_AVG_STAT

Current averaging status (for debug)

Address: 0x403A020C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	CUR_AVG_ACCU [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CUR_AVG_ACCU [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				CUR_AVG_ACCU [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	W							
Name	CUR_AVG_CNT [31:24]							

Bits	Name	Description
31 : 24	CUR_AVG_CNT	the current value of the averaging counter. Note that the value shown is updated after the sampling time and therefore runs ahead of the accumulator update. Default Value: 0
19 : 0	CUR_AVG_ACCU	the current value of the averaging accumulator Default Value: 0

17.1.62 SAR_INTR

Interrupt request register.

Address: 0x403A0210

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	INJ_COLLISION_INTR	INJ_RANGE_INTR	INJ_SATURATE_INTR	INJ_EOC_INTR	DSI_COLLISION_INTR	FW_COLLISION_INTR	OVERFLOW_INTR	EOS_INTR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_INTR	Injection Collision Interrupt: hardware sets this interrupt when the injection trigger signal is asserted (INJ_START_EN==1 && INJ_TAILGATING==0) while the SAR is BUSY. Raising this interrupt is delayed to when the sampling of the injection channel has been completed, i.e. not when the preceding scan with which this trigger collided is completed. When this interrupt is set it implies that the injection channel was sampled later than was intended. Write with '1' to clear bit. Default Value: 0
6	INJ_RANGE_INTR	Injection Range detect Interrupt: hardware sets this interrupt if the injection conversion result (after averaging) met the condition specified by the SAR_RANGE registers. Write with '1' to clear bit. Default Value: 0
5	INJ_SATURATE_INTR	Injection Saturation Interrupt: hardware sets this interrupt if an injection conversion result (before averaging) is either 0x000 or 0xFFFF (for 12-bit resolution), this is an indication that the ADC likely saturated. Write with '1' to clear bit. Default Value: 0

17.1.62 SAR_INTR (continued)

4	INJ_EOC_INTR	Injection End of Conversion Interrupt: hardware sets this interrupt after completing the conversion for the injection channel (irrespective of if tailgating was used). Write with '1' to clear bit. Default Value: 0
3	DSI_COLLISION_INTR	DSI Collision Interrupt: hardware sets this interrupt when the DSI trigger signal is asserted while the SAR is BUSY. Raising this interrupt is delayed to when the scan caused by the DSI trigger has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the channels were sampled later than was intended (jitter). Write with '1' to clear bit. Default Value: 0
2	FW_COLLISION_INTR	Firmware Collision Interrupt: hardware sets this interrupt when FW_TRIGGER is asserted while the SAR is BUSY. Raising this interrupt is delayed to when the scan caused by the FW_TRIGGER has been completed, i.e. not when the preceeding scan with which this trigger collided is completed. When this interrupt is set it implies that the channels were sampled later than was intended (jitter). Write with '1' to clear bit. Default Value: 0
1	OVERFLOW_INTR	Overflow Interrupt: hardware sets this interrupt when it sets a new EOS_INTR while that bit was not yet cleared by the firmware. Write with '1' to clear bit. Default Value: 0
0	EOS_INTR	End Of Scan Interrupt: hardware sets this interrupt after completing a scan of all the enabled channels. Write with '1' to clear bit. Default Value: 0

17.1.63 SAR_INTR_SET

Interrupt set request register

Address: 0x403A0214

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	INJ_COLLISION_SET	INJ_RANGE_SET	INJ_SATURATE_SET	INJ_EOC_SET	DSI_COLLISION_SET	FW_COLLISION_SET	OVERFLOW_SET	EOS_SET

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	INJ_RANGE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	INJ_SATURATE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	INJ_EOC_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	DSI_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	FW_COLLISION_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	OVERFLOW_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.63 SAR_INTR_SET (continued)

0	EOS_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.64 SAR_INTR_MASK

Interrupt mask register.

Address: 0x403A0218

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	INJ_COLLISION_MASK	INJ_RANGE_MASK	INJ_SATURATE_MASK	INJ_EOC_MASK	DSI_COLLISION_MASK	FW_COLLISION_MASK	OVERFLOW_MASK	EOS_MASK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	INJ_RANGE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	INJ_SATURATE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	INJ_EOC_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	DSI_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	FW_COLLISION_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	OVERFLOW_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.64 SAR_INTR_MASK (continued)

0	EOS_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.65 SAR_INTR_MASKED

Interrupt masked request register

Address: 0x403A021C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	INJ_COLLI- SION_MAS KED	IN- J_RANGE_ MASKED	INJ_SATU- RATE_MAS KED	IN- J_EOC_MA SKED	DSI_COLLI- SION_MAS KED	FW_COLLI- SION_MAS KED	OVER- FLOW_MA SKED	EO- S_MASKED

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7	INJ_COLLI- SION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
6	INJ_RANGE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
5	INJ_SATU- RATE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
4	INJ_EOC_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
3	DSI_COLLI- SION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
2	FW_COLLI- SION_MASKED	Logical and of corresponding request and mask bits. Default Value: 0
1	OVERFLOW_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.65 SAR_INTR_MASKED (continued)

0	EOS_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.66 SAR_SATURATE_INTR

Saturate interrupt request register.

Address: 0x403A0220

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	SATURATE_INTR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	RW1S							
Name	SATURATE_INTR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_INTR	Saturate Interrupt: hardware sets this interrupt for each channel if a conversion result (before averaging) of that channel is either 0x000 or 0xFFFF (for 12-bit resolution), this is an indication that the ADC likely saturated. Write with '1' to clear bit. Default Value: 0

17.1.67 SAR_SATURATE_INTR_SET

Saturate interrupt set request register

Address: 0x403A0224

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	SATURATE_SET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	A							
Name	SATURATE_SET [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.68 SAR_SATURATE_INTR_MASK

Saturate interrupt mask register.

Address: 0x403A0228

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	SATURATE_MASK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	SATURATE_MASK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.69 SAR_SATURATE_INTR_MASKED

Saturate interrupt masked request register

Address: 0x403A022C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	SATURATE_MASKED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	SATURATE_MASKED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	SATURATE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.70 SAR_RANGE_INTR

Range detect interrupt request register.

Address: 0x403A0230

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C							
HW Access	RW1S							
Name	RANGE_INTR [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	RW1C							
HW Access	RW1S							
Name	RANGE_INTR [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_INTR	Range detect Interrupt: hardware sets this interrupt for each channel if the conversion result (after averaging) of that channel met the condition specified by the SAR_RANGE registers. Write with '1' to clear bit. Default Value: 0

17.1.71 SAR_RANGE_INTR_SET

Range detect interrupt set request register

Address: 0x403A0234

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S							
HW Access	A							
Name	RANGE_SET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S							
HW Access	A							
Name	RANGE_SET [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_SET	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

17.1.72 SAR_RANGE_INTR_MASK

Range detect interrupt mask register.

Address: 0x403A0238

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	RANGE_MASK [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	RANGE_MASK [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_MASK	Mask bit for corresponding bit in interrupt request register. Default Value: 0

17.1.73 SAR_RANGE_INTR_MASKED

Range interrupt masked request register

Address: 0x403A023C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	RANGE_MASKED [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	RANGE_MASKED [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	RANGE_MASKED	Logical and of corresponding request and mask bits. Default Value: 0

17.1.74 SAR_INTR_CAUSE

Interrupt cause register

Address: 0x403A0240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	INJ_COLLISION_MASKED_MIR	INJ_RANGE_MASKED_MIR	INJ_SATURATE_RATE_MASKED_MIR	INJ_EOC_MASKED_MIR	DSI_COLLISION_MASKED_MIR	FW_COLLISION_MASKED_MIR	OVERFLOW_MASKED_MIR	EO-S_MASKED_MIR

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	None					
HW Access	W	W	None					
Name	RANGE_MASKED_RED	SATURATE_RATE_MASKED_RED	None [29:24]					

Bits	Name	Description
31	RANGE_MASKED_RED	Reduction OR of all SAR_RANGE_INTR_MASKED bits Default Value: 0
30	SATURATE_RATE_MASKED_RED	Reduction OR of all SAR_SATURATION_INTR_MASKED bits Default Value: 0
7	INJ_COLLISION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
6	INJ_RANGE_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
5	INJ_SATURATE_RATE_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
4	INJ_EOC_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0

17.1.74 SAR_INTR_CAUSE (continued)

3	DSI_COLLI- SION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
2	FW_COLLI- SION_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
1	OVER- FLOW_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0
0	EOS_MASKED_MIR	Mirror copy of corresponding bit in SAR_INTR_MASKED Default Value: 0

17.1.75 SAR_INJ_CHAN_CONFIG

Injection channel configuration register.

Address: 0x403A0280

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW			None	RW		
HW Access	None	R			None	R		
Name	None	INJ_PORT_ADDR [6:4]			None	INJ_PIN_ADDR [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW		None	RW	RW	RW
HW Access	None		R		None	R	R	R
Name	None [15:14]		INJ_SAMPLE_TIME_SEL [13:12]		None	IN-J_AVG_EN	INJ_RESOLUTION	INJ_DIFFERENTIAL_EN

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW1S	RW	None					
HW Access	RW1C	R	None					
Name	IN-J_START_EN	INJ_TAILGATING	None [29:24]					

Bits	Name	Description
31	INJ_START_EN	Set by firmware to enable the injection channel. If INJ_TAILGATING is not set this bit also functions as trigger for this channel. Cleared by hardware after this channel has been sampled (i.e. this channel is always one shot even if CONTINUOUS is set). Also cleared if the SAR is disabled. Default Value: 0
30	INJ_TAILGATING	Injection channel tailgating. - 0: no tailgating for this channel, SAR is immediately triggered when the INJ_START_EN bit is set. - 1: injection channel tailgating. The addressed pin is sampled after the next trigger and after all enabled channels have been scanned. Default Value: 0
13 : 12	INJ_SAMPLE_TIME_SEL	Injection sample time select: select which of the 4 global sample times to use for this channel Default Value: 0
10	INJ_AVG_EN	Averaging enable for this channel. If set the AVG_CNT and AVG_SHIFT settings are used for sampling the addressed pin(s) Default Value: 0

17.1.75 SAR_INJ_CHAN_CONFIG (continued)

9	INJ_RESOLUTION	Resolution for this channel. Default Value: 0 0x0: 12B: 12-bit resolution is used for this channel. 0x1: SUBRES: The resolution specified by SUB_RESOLUTION in the SAR_SAMPLE_CTRL register is used for this channel.
8	INJ_DIFFERENTIAL_EN	Differential enable for this channel. - 0: The voltage on the addressed pin is measured (Single-ended) and the resulting value is stored in the corresponding data register. - 1: The differential voltage on the addressed pin pair is measured and the resulting value is stored in the corresponding data register. (INJ_PIN_ADDR[0] is ignored). Default Value: 0
6 : 4	INJ_PORT_ADDR	Address of the port that contains the pin to be sampled by this channel. Default Value: 0 0x0: SARMUX: SARMUX pins. 0x1: CTB0: CTB0 0x2: CTB1: CTB1 0x3: CTB2: CTB2 0x4: CTB3: CTB3 0x6: AROUTE_VIRT: AROUTE virtual port 0x7: SARMUX_VIRT: SARMUX virtual port
2 : 0	INJ_PIN_ADDR	Address of the pin to be sampled by this injection channel. If differential is enabled then PIN_ADDR[0] is ignored and considered to be 0, i.e. PIN_ADDR points to the even pin of a pin pair. Default Value: 0

17.1.76 SAR_INJ_RESULT

Injection channel result register

Address: 0x403A0290

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	INJ_RESULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	INJ_RESULT [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R	R	R	R	None			
HW Access	W	W	W	W	None			
Name	IN- J_EOC_IN- TR_MIR	IN- J_RANGE_I NTR_MIR	INJ_SATU- RATE_IN- TR_MIR	INJ_COLLI- SION_IN- TR_MIR	None [27:24]			

Bits	Name	Description
31	INJ_EOC_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
30	INJ_RANGE_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
29	INJ_SATURATE_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
28	INJ_COLLISION_INTR_MIR	mirror bit of corresponding bit in SAR_INTR register Default Value: 0
15 : 0	INJ_RESULT	SAR conversion result of the channel. Default Value: Undefined

17.1.77 SAR_MUX_SWITCH0

SARMUX Firmware switch controls

Address: 0x403A0300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_F-W_P7_VPLUS	MUX_F-W_P6_VPLUS	MUX_F-W_P5_VPLUS	MUX_F-W_P4_VPLUS	MUX_F-W_P3_VPLUS	MUX_F-W_P2_VPLUS	MUX_F-W_P1_VPLUS	MUX_F-W_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_F-W_P7_VMI-NUS	MUX_F-W_P6_VMI-NUS	MUX_F-W_P5_VMI-NUS	MUX_F-W_P4_VMI-NUS	MUX_F-W_P3_VMI-NUS	MUX_F-W_P2_VMI-NUS	MUX_F-W_P1_VMI-NUS	MUX_F-W_P0_VMI-NUS

Bits	23	22	21	20	19	18	17	16
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	MUX_F-W_SAR-BUS1_VPLUS	MUX_F-W_SAR-BUS0_VPLUS	MUX_F-W_AMUX-BUSB_VMINUS	MUX_F-W_AMUX-BUSA_VMINUS	MUX_F-W_AMUX-BUSB_VPLUS	MUX_F-W_AMUX-BUSA_VPLUS	MUX_FW-TEMP_VPLUS	MUX_F-W_VS-SA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [31:30]		MUX_F-W_P7_COR EIO3	MUX_F-W_P6_COR EIO2	MUX_F-W_P5_COR EIO1	MUX_F-W_P4_COR EIO0	MUX_F-W_SAR-BUS1_VMINUS	MUX_F-W_SAR-BUS0_VMINUS

Bits	Name	Description
29	MUX_FW_P7_COREIO3	Firmware control: 0=open, 1=close switch between P7 and coreio3 signal. Write with '1' to set bit. Default Value: 0
28	MUX_FW_P6_COREIO2	Firmware control: 0=open, 1=close switch between P6 and coreio2 signal. Write with '1' to set bit. Default Value: 0
27	MUX_FW_P5_COREIO1	Firmware control: 0=open, 1=close switch between P5 and coreio1 signal. Write with '1' to set bit. Default Value: 0
26	MUX_FW_P4_COREIO0	Firmware control: 0=open, 1=close switch between P4 and coreio0 signal. Write with '1' to set bit. Default Value: 0

17.1.77 SAR_MUX_SWITCH0 (continued)

25	MUX_FW_SAR-BUS1_VMINUS	Firmware control: 0=open, 1=close switch between sarbus1 and vminus signal. Write with '1' to set bit. Default Value: 0
24	MUX_FW_SAR-BUS0_VMINUS	Firmware control: 0=open, 1=close switch between sarbus0 and vminus signal. Write with '1' to set bit. Default Value: 0
23	MUX_FW_SAR-BUS1_VPLUS	Firmware control: 0=open, 1=close switch between sarbus1 and vplus signal. Write with '1' to set bit. Default Value: 0
22	MUX_FW_SAR-BUS0_VPLUS	Firmware control: 0=open, 1=close switch between sarbus0 and vplus signal. Write with '1' to set bit. Default Value: 0
21	MUX_FW_AMUXBUS-B_VMINUS	Firmware control: 0=open, 1=close switch between amuxbusb and vminus signal. Write with '1' to set bit. Default Value: 0
20	MUX_FW_AMUX-BUSA_VMINUS	Firmware control: 0=open, 1=close switch between amuxbusa and vminus signal. Write with '1' to set bit. Default Value: 0
19	MUX_FW_AMUXBUS-B_VPLUS	Firmware control: 0=open, 1=close switch between amuxbusb and vplus signal. Write with '1' to set bit. Default Value: 0
18	MUX_FW_AMUX-BUSA_VPLUS	Firmware control: 0=open, 1=close switch between amuxbusa and vplus signal. Write with '1' to set bit. Default Value: 0
17	MUX_FW_TEMP_VPLUS	Firmware control: 0=open, 1=close switch between temperature sensor and vplus signal, also powers on the temperature sensor. Write with '1' to set bit. Default Value: 0
16	MUX_FW_VSSA_VMINUS	Firmware control: 0=open, 1=close switch between vssa_kelvin and vminus signal. Write with '1' to set bit. Default Value: 0
15	MUX_FW_P7_VMINUS	Firmware control: 0=open, 1=close switch between pin P7 and vminus signal. Write with '1' to set bit. Default Value: 0
14	MUX_FW_P6_VMINUS	Firmware control: 0=open, 1=close switch between pin P6 and vminus signal. Write with '1' to set bit. Default Value: 0
13	MUX_FW_P5_VMINUS	Firmware control: 0=open, 1=close switch between pin P5 and vminus signal. Write with '1' to set bit. Default Value: 0
12	MUX_FW_P4_VMINUS	Firmware control: 0=open, 1=close switch between pin P4 and vminus signal. Write with '1' to set bit. Default Value: 0
11	MUX_FW_P3_VMINUS	Firmware control: 0=open, 1=close switch between pin P3 and vminus signal. Write with '1' to set bit. Default Value: 0
10	MUX_FW_P2_VMINUS	Firmware control: 0=open, 1=close switch between pin P2 and vminus signal. Write with '1' to set bit. Default Value: 0

17.1.77 SAR_MUX_SWITCH0 (continued)

9	MUX_FW_P1_VMINUS	Firmware control: 0=open, 1=close switch between pin P1 and vminus signal. Write with '1' to set bit. Default Value: 0
8	MUX_FW_P0_VMINUS	Firmware control: 0=open, 1=close switch between pin P0 and vminus signal. Write with '1' to set bit. Default Value: 0
7	MUX_FW_P7_VPLUS	Firmware control: 0=open, 1=close switch between pin P7 and vplus signal. Write with '1' to set bit. Default Value: 0
6	MUX_FW_P6_VPLUS	Firmware control: 0=open, 1=close switch between pin P6 and vplus signal. Write with '1' to set bit. Default Value: 0
5	MUX_FW_P5_VPLUS	Firmware control: 0=open, 1=close switch between pin P5 and vplus signal. Write with '1' to set bit. Default Value: 0
4	MUX_FW_P4_VPLUS	Firmware control: 0=open, 1=close switch between pin P4 and vplus signal. Write with '1' to set bit. Default Value: 0
3	MUX_FW_P3_VPLUS	Firmware control: 0=open, 1=close switch between pin P3 and vplus signal. Write with '1' to set bit. Default Value: 0
2	MUX_FW_P2_VPLUS	Firmware control: 0=open, 1=close switch between pin P2 and vplus signal. Write with '1' to set bit. Default Value: 0
1	MUX_FW_P1_VPLUS	Firmware control: 0=open, 1=close switch between pin P1 and vplus signal. Write with '1' to set bit. Default Value: 0
0	MUX_FW_P0_VPLUS	Firmware control: 0=open, 1=close switch between pin P0 and vplus signal. Write with '1' to set bit. Default Value: 0

17.1.78 SAR_MUX_SWITCH_CLEAR0

SARMUX Firmware switch control clear

Address: 0x403A0304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_F-W_P7_VPLUS	MUX_F-W_P6_VPLUS	MUX_F-W_P5_VPLUS	MUX_F-W_P4_VPLUS	MUX_F-W_P3_VPLUS	MUX_F-W_P2_VPLUS	MUX_F-W_P1_VPLUS	MUX_F-W_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_F-W_P7_VMI-NUS	MUX_F-W_P6_VMI-NUS	MUX_F-W_P5_VMI-NUS	MUX_F-W_P4_VMI-NUS	MUX_F-W_P3_VMI-NUS	MUX_F-W_P2_VMI-NUS	MUX_F-W_P1_VMI-NUS	MUX_F-W_P0_VMI-NUS

Bits	23	22	21	20	19	18	17	16
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	A	A	A	A	A	A	A	A
Name	MUX_F-W_SAR-BUS1_VPLUS	MUX_F-W_SAR-BUS0_VPLUS	MUX_F-W_AMUX-BUSB_VMINUS	MUX_F-W_AMUX-BUSA_VMINUS	MUX_F-W_AMUX-BUSB_VPLUS	MUX_F-W_AMUX-BUSA_VPLUS	MUX_FW-TEMP_VPLUS	MUX_F-W_VS-SA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	None		A	A	A	A	A	A
Name	None [31:30]		MUX_F-W_P7_COR EIO3	MUX_F-W_P6_COR EIO2	MUX_F-W_P5_COR EIO1	MUX_F-W_P4_COR EIO0	MUX_F-W_SAR-BUS1_VMINUS	MUX_F-W_SAR-BUS0_VMINUS

Bits	Name	Description
29	MUX_FW_P7_COREIO3	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
28	MUX_FW_P6_COREIO2	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
27	MUX_FW_P5_COREIO1	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
26	MUX_FW_P4_COREIO0	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.78 SAR_MUX_SWITCH_CLEAR0 (continued)

25	MUX_FW_SAR-BUS1_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
24	MUX_FW_SAR-BUS0_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
23	MUX_FW_SAR-BUS1_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
22	MUX_FW_SAR-BUS0_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
21	MUX_FW_AMUXBUS-B_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
20	MUX_FW_AMUX-BUSA_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
19	MUX_FW_AMUXBUS-B_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
18	MUX_FW_AMUX-BUSA_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
17	MUX_FW_TEMP_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
16	MUX_FW_VSSA_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
15	MUX_FW_P7_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
14	MUX_FW_P6_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
13	MUX_FW_P5_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
12	MUX_FW_P4_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
11	MUX_FW_P3_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
10	MUX_FW_P2_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
9	MUX_FW_P1_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
8	MUX_FW_P0_VMINUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
7	MUX_FW_P7_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
6	MUX_FW_P6_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
5	MUX_FW_P5_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
4	MUX_FW_P4_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.78 SAR_MUX_SWITCH_CLEAR0 (continued)

3	MUX_FW_P3_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
2	MUX_FW_P2_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
1	MUX_FW_P1_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0
0	MUX_FW_P0_VPLUS	Write '1' to clear corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.79 SAR_MUX_SWITCH1

SARMUX Firmware switch controls

Address: 0x403A0308

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				RW1C	RW1C	RW1C	RW1C
Name	None [7:4]				MUX_F- W_AD- FT1_SARB US1	MUX_F- W_AD- FT0_SARB US0	MUX_F- W_P5_D- FT_INM	MUX_F- W_P4_D- FT_INP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	MUX_FW_ADFT1_SARBUS1	Firmware control: 0=open, 1=close switch between adft1 signal and sarbus1 signal. Write with '1' to set bit. Default Value: 0
2	MUX_FW_ADFT0_SARBUS0	Firmware control: 0=open, 1=close switch between adft0 signal and sarbus0 signal. Write with '1' to set bit. Default Value: 0
1	MUX_FW_P5_DFT_INM	Firmware control: 0=open, 1=close switch between P5 pin and dft_inm signal. Write with '1' to set bit. Default Value: 0
0	MUX_FW_P4_DFT_INP	Firmware control: 0=open, 1=close switch between P4 pin and dft_inp signal. Write with '1' to set bit. Default Value: 0

17.1.80 SAR_MUX_SWITCH_CLEAR1

SARMUX Firmware switch control clear

Address: 0x403A030C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				MUX_F- W_AD- FT1_SARB US1	MUX_F- W_AD- FT0_SARB US0	MUX_F- W_P5_D- FT_INM	MUX_F- W_P4_D- FT_INP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	MUX_FW_ADFT1_SARBUS1	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0
2	MUX_FW_ADFT0_SARBUS0	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0
1	MUX_FW_P5_DFT_INM	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0
0	MUX_FW_P4_DFT_INP	Write '1' to clear corresponding bit in MUX_SWITCH1 Default Value: 0

17.1.81 SAR_MUX_SWITCH_HW_CTRL

SARMUX switch hardware control

Address: 0x403A0340

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	MUX- _HW_C- TRL_P7	MUX- _HW_C- TRL_P6	MUX- _HW_C- TRL_P5	MUX- _HW_C- TRL_P4	MUX- _HW_C- TRL_P3	MUX- _HW_C- TRL_P2	MUX- _HW_C- TRL_P1	MUX- _HW_C- TRL_P0

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	RW	None		RW	RW	RW	RW
HW Access	R	R	None		R	R	R	R
Name	MUX- _HW_C- TRL_SARB US1	MUX- _HW_C- TRL_SARB US0	None [21:20]		MUX- _HW_C- TRL_AMUX BUSB	MUX- _HW_C- TRL_AMUX BUSA	MUX- _HW_C- TRL_TEMP	MUX- _HW_C- TRL_VSSA

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	MUX_HW_CTRL_SAR-BUS1	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for sarbus1 switches. Default Value: 0
22	MUX_HW_CTRL_SAR-BUS0	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for sarbus0 switches. Default Value: 0
19	MUX_HW_CTRL_AMUX-BUSB	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for amuxbusb switches. Default Value: 0
18	MUX_HW_CTRL_AMUX-BUSA	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for amuxbusa switches. Default Value: 0

17.1.81 SAR_MUX_SWITCH_HW_CTRL (continued)

17	MUX_HW_CTRL_TEMP	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for temp switch. Default Value: 0
16	MUX_HW_CTRL_VSSA	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for vssa switch. Default Value: 0
7	MUX_HW_CTRL_P7	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P7 switches. Default Value: 0
6	MUX_HW_CTRL_P6	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P6 switches. Default Value: 0
5	MUX_HW_CTRL_P5	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P5 switches. Default Value: 0
4	MUX_HW_CTRL_P4	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P4 switches. Default Value: 0
3	MUX_HW_CTRL_P3	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P3 switches. Default Value: 0
2	MUX_HW_CTRL_P2	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P2 switches. Default Value: 0
1	MUX_HW_CTRL_P1	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P1 switches. Default Value: 0
0	MUX_HW_CTRL_P0	Hardware control: 0=only firmware control, 1=hardware control masked by firmware setting for pin P0 switches. Default Value: 0

17.1.82 SAR_MUX_SWITCH_STATUS

SARMUX switch status

Address: 0x403A0348

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_F-W_P7_VPLUS	MUX_F-W_P6_VPLUS	MUX_F-W_P5_VPLUS	MUX_F-W_P4_VPLUS	MUX_F-W_P3_VPLUS	MUX_F-W_P2_VPLUS	MUX_F-W_P1_VPLUS	MUX_F-W_P0_VPLUS

Bits	15	14	13	12	11	10	9	8
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_F-W_P7_VMI-NUS	MUX_F-W_P6_VMI-NUS	MUX_F-W_P5_VMI-NUS	MUX_F-W_P4_VMI-NUS	MUX_F-W_P3_VMI-NUS	MUX_F-W_P2_VMI-NUS	MUX_F-W_P1_VMI-NUS	MUX_F-W_P0_VMI-NUS

Bits	23	22	21	20	19	18	17	16
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	MUX_F-W_SAR-BUS1_VPLUS	MUX_F-W_SAR-BUS0_VPLUS	MUX_F-W_AMUX-BUSB_VMINUS	MUX_F-W_AMUX-BUSA_VMINUS	MUX_F-W_AMUX-BUSB_VPLUS	MUX_F-W_AMUX-BUSA_VPLUS	MUX_FW-TEMP_VPLUS	MUX_F-W_VS-SA_VMINUS

Bits	31	30	29	28	27	26	25	24
SW Access	None						R	R
HW Access	None						W	W
Name	None [31:26]						MUX_F-W_SAR-BUS1_VMINUS	MUX_F-W_SAR-BUS0_VMINUS

Bits	Name	Description
25	MUX_FW_SAR-BUS1_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
24	MUX_FW_SAR-BUS0_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
23	MUX_FW_SAR-BUS1_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
22	MUX_FW_SAR-BUS0_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.82 SAR_MUX_SWITCH_STATUS (continued)

21	MUX_FW_AMUXBUS- B_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
20	MUX_FW_AMUX- BUSA_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
19	MUX_FW_AMUXBUS- B_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
18	MUX_FW_AMUX- BUSA_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
17	MUX_FW_TEMP_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
16	MUX_FW_VSSA_VMI- NUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
15	MUX_FW_P7_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
14	MUX_FW_P6_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
13	MUX_FW_P5_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
12	MUX_FW_P4_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
11	MUX_FW_P3_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
10	MUX_FW_P2_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
9	MUX_FW_P1_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
8	MUX_FW_P0_VMINUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
7	MUX_FW_P7_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
6	MUX_FW_P6_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
5	MUX_FW_P5_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
4	MUX_FW_P4_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
3	MUX_FW_P3_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
2	MUX_FW_P2_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
1	MUX_FW_P1_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0
0	MUX_FW_P0_VPLUS	switch status of corresponding bit in MUX_SWITCH0 Default Value: 0

17.1.83 SAR_PUMP_CTRL

Switch pump control

Address: 0x403A0380

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							CLOCK_- SEL

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLED	None [30:24]						

Bits	Name	Description
31	ENABLED	0=disabled: pump output is VDDA_PUMP, 1=enabled: pump output is boosted. Default Value: 0
0	CLOCK_SEL	Clock select: 0=external clock, 1=internal clock (deprecated). Default Value: 0

17.1.84 SAR_ANA_TRIM

Analog trim register.

Address: 0x403A0F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW		
HW Access	None				R	R		
Name	None [7:4]				TRIMUNIT	CAP_TRIM [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	TRIMUNIT	Attenuation cap trimming Default Value: 0
2 : 0	CAP_TRIM	Attenuation cap trimming Default Value: 0

17.1.85 SAR_WOUNDING

SAR wounding register

Address: 0x403A0F04

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	
HW Access	None						R	
Name	None [7:2]						WOUND_RESOLUTION [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1 : 0	WOUND_RESOLUTION	Maximum SAR resolution allowed Default Value: 0 0x0: 12BIT: unwounded: up to full 12-bit SAR resolution allowed 0x1: 10BIT: wounded: max resolution upto 10-bit SAR resolution allowed 0x2: 8BIT: wounded: only 8-bit SAR resolution allowed 0x3: 8BIT_TOO: wounded: only 8-bit SAR resolution allowed

18 Serial Communication Block (SCB) Registers



This section discusses the SCB registers. It lists all the registers in mapping tables, in address order.

18.1 Register Details

Register Name	Address
SCB0_CTRL	0x40080000
SCB0_STATUS	0x40080004
SCB0_SPI_CTRL	0x40080020
SCB0_SPI_STATUS	0x40080024
SCB0_UART_CTRL	0x40080040
SCB0_UART_TX_CTRL	0x40080044
SCB0_UART_RX_CTRL	0x40080048
SCB0_UART_RX_STATUS	0x4008004C
SCB0_UART_FLOW_CTRL	0x40080050
SCB0_I2C_CTRL	0x40080060
SCB0_I2C_STATUS	0x40080064
SCB0_I2C_M_CMD	0x40080068
SCB0_I2C_S_CMD	0x4008006C
SCB0_I2C_CFG	0x40080070
SCB0_TX_CTRL	0x40080200
SCB0_TX_FIFO_CTRL	0x40080204
SCB0_TX_FIFO_STATUS	0x40080208
SCB0_TX_FIFO_WR	0x40080240
SCB0_RX_CTRL	0x40080300
SCB0_RX_FIFO_CTRL	0x40080304
SCB0_RX_FIFO_STATUS	0x40080308
SCB0_RX_MATCH	0x40080310
SCB0_RX_FIFO_RD	0x40080340
SCB0_RX_FIFO_RD_SILENT	0x40080344
SCB0_EZ_DATA0	0x40080400
SCB0_EZ_DATA1	0x40080404
SCB0_EZ_DATA2	0x40080408

Register Name	Address
SCB0_EZ_DATA3	0x4008040C
SCB0_EZ_DATA4	0x40080410
SCB0_EZ_DATA5	0x40080414
SCB0_EZ_DATA6	0x40080418
SCB0_EZ_DATA7	0x4008041C
SCB0_EZ_DATA8	0x40080420
SCB0_EZ_DATA9	0x40080424
SCB0_EZ_DATA10	0x40080428
SCB0_EZ_DATA11	0x4008042C
SCB0_EZ_DATA12	0x40080430
SCB0_EZ_DATA13	0x40080434
SCB0_EZ_DATA14	0x40080438
SCB0_EZ_DATA15	0x4008043C
SCB0_EZ_DATA16	0x40080440
SCB0_EZ_DATA17	0x40080444
SCB0_EZ_DATA18	0x40080448
SCB0_EZ_DATA19	0x4008044C
SCB0_EZ_DATA20	0x40080450
SCB0_EZ_DATA21	0x40080454
SCB0_EZ_DATA22	0x40080458
SCB0_EZ_DATA23	0x4008045C
SCB0_EZ_DATA24	0x40080460
SCB0_EZ_DATA25	0x40080464
SCB0_EZ_DATA26	0x40080468
SCB0_EZ_DATA27	0x4008046C
SCB0_EZ_DATA28	0x40080470
SCB0_EZ_DATA29	0x40080474
SCB0_EZ_DATA30	0x40080478
SCB0_EZ_DATA31	0x4008047C
SCB0_INTR_CAUSE	0x40080E00
SCB0_INTR_I2C_EC	0x40080E80
SCB0_INTR_I2C_EC_MASK	0x40080E88
SCB0_INTR_I2C_EC_MASKED	0x40080E8C
SCB0_INTR_SPI_EC	0x40080EC0
SCB0_INTR_SPI_EC_MASK	0x40080EC8
SCB0_INTR_SPI_EC_MASKED	0x40080ECC
SCB0_INTR_M	0x40080F00
SCB0_INTR_M_SET	0x40080F04
SCB0_INTR_M_MASK	0x40080F08
SCB0_INTR_M_MASKED	0x40080F0C
SCB0_INTR_S	0x40080F40
SCB0_INTR_S_SET	0x40080F44

Register Name	Address
SCB0_INTR_S_MASK	0x40080F48
SCB0_INTR_S_MASKED	0x40080F4C
SCB0_INTR_TX	0x40080F80
SCB0_INTR_TX_SET	0x40080F84
SCB0_INTR_TX_MASK	0x40080F88
SCB0_INTR_TX_MASKED	0x40080F8C
SCB0_INTR_RX	0x40080FC0
SCB0_INTR_RX_SET	0x40080FC4
SCB0_INTR_RX_MASK	0x40080FC8
SCB0_INTR_RX_MASKED	0x40080FCC
SCB1_CTRL	0x40090000
SCB1_STATUS	0x40090004
SCB1_SPI_CTRL	0x40090020
SCB1_SPI_STATUS	0x40090024
SCB1_UART_CTRL	0x40090040
SCB1_UART_TX_CTRL	0x40090044
SCB1_UART_RX_CTRL	0x40090048
SCB1_UART_RX_STATUS	0x4009004C
SCB1_UART_FLOW_CTRL	0x40090050
SCB1_I2C_CTRL	0x40090060
SCB1_I2C_STATUS	0x40090064
SCB1_I2C_M_CMD	0x40090068
SCB1_I2C_S_CMD	0x4009006C
SCB1_I2C_CFG	0x40090070
SCB1_TX_CTRL	0x40090200
SCB1_TX_FIFO_CTRL	0x40090204
SCB1_TX_FIFO_STATUS	0x40090208
SCB1_TX_FIFO_WR	0x40090240
SCB1_RX_CTRL	0x40090300
SCB1_RX_FIFO_CTRL	0x40090304
SCB1_RX_FIFO_STATUS	0x40090308
SCB1_RX_MATCH	0x40090310
SCB1_RX_FIFO_RD	0x40090340
SCB1_RX_FIFO_RD_SILENT	0x40090344
SCB1_EZ_DATA0	0x40090400
SCB1_EZ_DATA1	0x40090404
SCB1_EZ_DATA2	0x40090408
SCB1_EZ_DATA3	0x4009040C
SCB1_EZ_DATA4	0x40090410
SCB1_EZ_DATA5	0x40090414
SCB1_EZ_DATA6	0x40090418
SCB1_EZ_DATA7	0x4009041C

Register Name	Address
SCB1_EZ_DATA8	0x40090420
SCB1_EZ_DATA9	0x40090424
SCB1_EZ_DATA10	0x40090428
SCB1_EZ_DATA11	0x4009042C
SCB1_EZ_DATA12	0x40090430
SCB1_EZ_DATA13	0x40090434
SCB1_EZ_DATA14	0x40090438
SCB1_EZ_DATA15	0x4009043C
SCB1_EZ_DATA16	0x40090440
SCB1_EZ_DATA17	0x40090444
SCB1_EZ_DATA18	0x40090448
SCB1_EZ_DATA19	0x4009044C
SCB1_EZ_DATA20	0x40090450
SCB1_EZ_DATA21	0x40090454
SCB1_EZ_DATA22	0x40090458
SCB1_EZ_DATA23	0x4009045C
SCB1_EZ_DATA24	0x40090460
SCB1_EZ_DATA25	0x40090464
SCB1_EZ_DATA26	0x40090468
SCB1_EZ_DATA27	0x4009046C
SCB1_EZ_DATA28	0x40090470
SCB1_EZ_DATA29	0x40090474
SCB1_EZ_DATA30	0x40090478
SCB1_EZ_DATA31	0x4009047C
SCB1_INTR_CAUSE	0x40090E00
SCB1_INTR_I2C_EC	0x40090E80
SCB1_INTR_I2C_EC_MASK	0x40090E88
SCB1_INTR_I2C_EC_MASKED	0x40090E8C
SCB1_INTR_SPI_EC	0x40090EC0
SCB1_INTR_SPI_EC_MASK	0x40090EC8
SCB1_INTR_SPI_EC_MASKED	0x40090ECC
SCB1_INTR_M	0x40090F00
SCB1_INTR_M_SET	0x40090F04
SCB1_INTR_M_MASK	0x40090F08
SCB1_INTR_M_MASKED	0x40090F0C
SCB1_INTR_S	0x40090F40
SCB1_INTR_S_SET	0x40090F44
SCB1_INTR_S_MASK	0x40090F48
SCB1_INTR_S_MASKED	0x40090F4C
SCB1_INTR_TX	0x40090F80
SCB1_INTR_TX_SET	0x40090F84
SCB1_INTR_TX_MASK	0x40090F88

Register Name	Address
SCB1_INTR_TX_MASKED	0x40090F8C
SCB1_INTR_RX	0x40090FC0
SCB1_INTR_RX_SET	0x40090FC4
SCB1_INTR_RX_MASK	0x40090FC8
SCB1_INTR_RX_MASKED	0x40090FCC
SCB2_CTRL	0x400A0000
SCB2_STATUS	0x400A0004
SCB2_SPI_CTRL	0x400A0020
SCB2_SPI_STATUS	0x400A0024
SCB2_UART_CTRL	0x400A0040
SCB2_UART_TX_CTRL	0x400A0044
SCB2_UART_RX_CTRL	0x400A0048
SCB2_UART_RX_STATUS	0x400A004C
SCB2_UART_FLOW_CTRL	0x400A0050
SCB2_I2C_CTRL	0x400A0060
SCB2_I2C_STATUS	0x400A0064
SCB2_I2C_M_CMD	0x400A0068
SCB2_I2C_S_CMD	0x400A006C
SCB2_I2C_CFG	0x400A0070
SCB2_TX_CTRL	0x400A0200
SCB2_TX_FIFO_CTRL	0x400A0204
SCB2_TX_FIFO_STATUS	0x400A0208
SCB2_TX_FIFO_WR	0x400A0240
SCB2_RX_CTRL	0x400A0300
SCB2_RX_FIFO_CTRL	0x400A0304
SCB2_RX_FIFO_STATUS	0x400A0308
SCB2_RX_MATCH	0x400A0310
SCB2_RX_FIFO_RD	0x400A0340
SCB2_RX_FIFO_RD_SILENT	0x400A0344
SCB2_EZ_DATA0	0x400A0400
SCB2_EZ_DATA1	0x400A0404
SCB2_EZ_DATA2	0x400A0408
SCB2_EZ_DATA3	0x400A040C
SCB2_EZ_DATA4	0x400A0410
SCB2_EZ_DATA5	0x400A0414
SCB2_EZ_DATA6	0x400A0418
SCB2_EZ_DATA7	0x400A041C
SCB2_EZ_DATA8	0x400A0420
SCB2_EZ_DATA9	0x400A0424
SCB2_EZ_DATA10	0x400A0428
SCB2_EZ_DATA11	0x400A042C
SCB2_EZ_DATA12	0x400A0430

Register Name	Address
SCB2_EZ_DATA13	0x400A0434
SCB2_EZ_DATA14	0x400A0438
SCB2_EZ_DATA15	0x400A043C
SCB2_EZ_DATA16	0x400A0440
SCB2_EZ_DATA17	0x400A0444
SCB2_EZ_DATA18	0x400A0448
SCB2_EZ_DATA19	0x400A044C
SCB2_EZ_DATA20	0x400A0450
SCB2_EZ_DATA21	0x400A0454
SCB2_EZ_DATA22	0x400A0458
SCB2_EZ_DATA23	0x400A045C
SCB2_EZ_DATA24	0x400A0460
SCB2_EZ_DATA25	0x400A0464
SCB2_EZ_DATA26	0x400A0468
SCB2_EZ_DATA27	0x400A046C
SCB2_EZ_DATA28	0x400A0470
SCB2_EZ_DATA29	0x400A0474
SCB2_EZ_DATA30	0x400A0478
SCB2_EZ_DATA31	0x400A047C
SCB2_INTR_CAUSE	0x400A0E00
SCB2_INTR_I2C_EC	0x400A0E80
SCB2_INTR_I2C_EC_MASK	0x400A0E88
SCB2_INTR_I2C_EC_MASKED	0x400A0E8C
SCB2_INTR_SPI_EC	0x400A0EC0
SCB2_INTR_SPI_EC_MASK	0x400A0EC8
SCB2_INTR_SPI_EC_MASKED	0x400A0ECC
SCB2_INTR_M	0x400A0F00
SCB2_INTR_M_SET	0x400A0F04
SCB2_INTR_M_MASK	0x400A0F08
SCB2_INTR_M_MASKED	0x400A0F0C
SCB2_INTR_S	0x400A0F40
SCB2_INTR_S_SET	0x400A0F44
SCB2_INTR_S_MASK	0x400A0F48
SCB2_INTR_S_MASKED	0x400A0F4C
SCB2_INTR_TX	0x400A0F80
SCB2_INTR_TX_SET	0x400A0F84
SCB2_INTR_TX_MASK	0x400A0F88
SCB2_INTR_TX_MASKED	0x400A0F8C
SCB2_INTR_RX	0x400A0FC0
SCB2_INTR_RX_SET	0x400A0FC4
SCB2_INTR_RX_MASK	0x400A0FC8
SCB2_INTR_RX_MASKED	0x400A0FCC

18.1.1 SCB0_CTRL

Generic control register.

Address: 0x40080000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BYTE_- MODE	EZ_MODE	EC_OP_- MODE	EC_AM_- MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_AC- CEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	SCB block is enabled ('1') or not ('0'). The proper order in which to initialize SCB is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL registers. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL register to enable SCB, select the specific operation mode and oversampling factor. When this block is enabled, no control information should be changed. Changes should be made AFTER disabling this block, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the block is re-enabled. Note that disabling the block will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Default Value: 3

18.1.1 SCB0_CTRL (continued)

0x0: I2C:

0x1: SPI:

0x2: UART:

17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the internal CPU accesses to EZ memory coincide/collide, this bit determines whether the CPU access should block and result in bus wait states ('BLOCK is 1') or not ('BLOCK is 0'). If BLOCK is 0 and the accesses collide, CPU read operations return 0xffff:ffff and CPU write operations are ignored. Colliding accesses are registered as interrupt causes: INTR_TX.BLOCKED and INTR_RX.BLOCKED. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when this bit is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
11	BYTE_MODE	Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames not separated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	This field specifies the clocking for the SCB block '0': Internally clocked mode '1': externally clocked mode In internally clocked mode, the serial interface protocols run off the SCB clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.1 SCB0_CTRL (continued)

8	EC_AM_MODE	This field specifies the clocking for the address matching (I2C) or slave selection detection logic (SPI) '0': Internally clocked mode '1': Externally clocked mode In internally clocked mode, the serial interface protocols run off the SCB clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. The clocking for the rest of the logic is determined by CTRL.EC_OP_MODE. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.1 SCB0_CTRL (continued)

3 : 0 OVS

Serial interface bit period oversampling factor expressed in SCB clock cycles. Used for SPI and UART functionality. $OVS + 1$ SCB clock cycles constitute a single serial interface clock/bit cycle. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the low and high phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the low and high phase can differ by 1 SCB clock period.

In SPI master mode, the valid range is [3, 15]. At an SCB frequency of 48 MHz, the maximum SPI bit rate is 12 Mbps, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock to SPI MISO input round trip delay is significant (multiple SPI output clock cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate.

In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the SPI input clock (IF) on the interface to guarantee functional correct behavior. This requirement is expressed as a ratio: SCB clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE):

- MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": SCB clock/IF clock ≥ 6 . At a SCB frequency of 48 MHz, the maximum bit rate is 8 Mbps.
- MEDIAN is '0' and external SPI master has "late MISO sample functionality": SCB clock/IF clock ≥ 3 . At a SCB frequency of 48 MHz, the maximum bit rate is 16 Mbps.
- MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": SCB clock/IF clock ≥ 8 . At a SCB frequency of 48 MHz, the maximum bit rate is 6 Mbps.
- MEDIAN is '1' and external SPI master has "late MISO sample functionality": SCB clock/IF clock ≥ 4 . At a SCB frequency of 48 MHz, the maximum bit rate is 12 Mbps.

As discussed earlier, the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account.

In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15].

In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value:

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
 - SCB clock frequency of 16×57.6 KHz for 57.6 Kbps.
 - SCB clock frequency of 16×38.4 KHz for 38.4 Kbps.
 - SCB clock frequency of 16×19.2 KHz for 19.2 Kbps.
 - SCB clock frequency of 16×9.6 KHz for 9.6 Kbps.
 - SCB clock frequency of 16×2.4 KHz for 2.4 Kbps.
 - SCB clock frequency of 16×1.2 KHz for 1.2 Kbps.
- all other values are not used in normal mode.

In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two SCB clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two SCB clock cycles and greater or equal than one SCB clock cycle may be detected by the receiver. Pulse widths less than one SCB clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The SCB clock (as provided by the programmable clock block) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required SCB clock frequency):

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
 - SCB clock frequency of 16×57.6 KHz for 57.6 Kbps.
 - SCB clock frequency of 16×38.4 KHz for 38.4 Kbps.
 - SCB clock frequency of 16×19.2 KHz for 19.2 Kbps.
 - SCB clock frequency of 16×9.6 KHz for 9.6 Kbps.
 - SCB clock frequency of 16×2.4 KHz for 2.4 Kbps.
 - SCB clock frequency of 16×1.2 KHz for 1.2 Kbps.
- all other values are not used in normal mode.

Low power mode, OVS field values (with the required SCB clock frequency):

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
- 1: 32 times oversampling.
 - SCB clock frequency of 32×57.6 KHz for 57.6 Kbps.
- 2: 48 times oversampling.
 - SCB clock frequency of 48×38.4 KHz for 38.4 Kbps.
- 3: 96 times oversampling.
 - SCB clock frequency of 96×19.2 KHz for 19.2 Kbps.
- 4: 192 times oversampling.
 - SCB clock frequency of 192×9.6 KHz for 9.6 Kbps.
- 5: 768 times oversampling.
 - SCB clock frequency of 768×2.4 KHz for 2.4 Kbps.
- 6: 1536 times oversampling.
 - SCB clock frequency of 1536×1.2 KHz for 1.2 Kbps.
- all other values are not used in low power mode.

Default Value: 15

18.1.2 SCB0_STATUS

Generic status register.

Address: 0x40080004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.3 SCB0_SPI_CTRL

SPI control register.

Address: 0x40080020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_- CONTINU- OUS	LATE_MISO_ SAMPLE	CPOL	CPHA	SE- LECT_PRE- CEDE	CONTINU- OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_PO- LARITY3	SSEL_PO- LARITY2	SSEL_PO- LARITY1	SSEL_PO- LARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_- MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. SCB block should be disabled when changes are made to this field. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.3 SCB0_SPI_CTRL (continued)

0x0: SPI_MOTOROLA:

SPI Motorola submode. In master mode, when not transmitting data (Slave SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive.

0x1: SPI_TI:

SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive; i.e. no pulse is generated.

0x2: SPI_NS:

SPI National Semiconductors submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive.

16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': No local loopback '1': the SPI master MISO line is connected to the SPI master MOSI line. In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Instruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.3 SCB0_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is 0: SCLK is 0 when not transmitting data. - CPOL is 1: SCLK is 1 when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is 0, CPHA is 0: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is 0, CPHA is 1: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is 1, CPHA is 0: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is 1, CPHA is 1: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the Slave SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the Slave SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily separated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are sent out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always separated by slave deselection: independent of the availability of TX FIFO data frames, data frames are sent out with slave deselection. Default Value: 0

18.1.4 SCB0_SPI_STATUS

SPI status register.

Address: 0x40080024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.5 SCB0_UART_CTRL

UART control register.

Address: 0x40080040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 0x0: UART_STD: Standard UART submode. 0x1: UART_SMARTCARD: SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. 0x2: UART_IRDA: Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS should be set to 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). 0: Loopback is not enabled 1: UART_TX is connected to UART_RX. UART_RTS is connected to UART_CTS. This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.6 SCB0_UART_TX_CTRL

UART transmitter control register.

Address: 0x40080044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.7 SCB0_UART_RX_CTRL

UART receiver control register.

Address: 0x40080048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.7 SCB0_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame separates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is sent to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is sent to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal. Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.7 SCB0_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.8 SCB0_UART_RX_STATUS

UART receiver status register.

Address: 0x4008004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least significant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when IN-TR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.9 SCB0_UART_FLOW_CTRL

UART flow control register

Address: 0x40080050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_PO- LARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_EN- ABLED	CTS_PO- LARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal by the UART transmitter: '0': Disabled. The UART transmitter ignores the CTS input signal and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses CTS input signal to qualify the transmission of data. It transmits when CTS input signal is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', the CTS input signal is driven by the RTS output signal locally in SCB (both signals are subjected to signal polarity changes are indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal '0': CTS is active low ; '1': CTS is active high; Default Value: 0

18.1.9 SCB0_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal: '0': RTS is active low; '1': RTS is active high; During SCB reset (Hibernate system power mode), RTS output signal is '1'. This represents an inactive state assuming an active low polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal is activated. By setting this field to "0", flow control is effectively disabled (may be useful for debug purposes). Default Value: 0

18.1.10 SCB0_I2C_CTRL

I2C control register.

Address: 0x40080060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', no loopback When '1', loopback is enabled internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0

18.1.10 SCB0_I2C_CTRL (continued)

15	S_NOT_READY_DATA_NACK	Only used when: - non EZ mode Functionality is as follows: - 1: a received data element by the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1
14	S_NOT_READY_ADDR_NACK	This field is used during an address match or general call address in internally clocked mode Only used when: - EC_AM_MODE is '0', EC_OP_MODE is '0', S_GENERAL_IGNORE is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the SCB clock is available (in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). SCB clock is not present (in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the SCB clock is available). The logic will handle the ongoing transfer as soon as the clock is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1

18.1.10 SCB0_I2C_CTRL (continued)

7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 SCB clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the regular (no stretching) interface (IF) low time to guarantee functionally correct behavior. With input signal median filtering, the IF low time should be ≥ 8 SCB clock cycles and ≤ 16 IP clock cycles. Without input signal median filtering, the IF low time should be ≥ 7 SCB clock cycles and ≤ 16 SCB clock cycles. Default Value: 8
3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 SCB clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be ≥ 6 SCB clock cycles and ≤ 16 SCB clock cycles. Without input signal median filtering, the IF high time should be ≥ 5 SCB clock cycles and ≤ 16 SCB clock cycles. Default Value: 8

18.1.11 SCB0_I2C_STATUS

I2C status register.

Address: 0x40080064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/ idle or transmitting START, REPEATED START, STOP or an address, this field is '0'. Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0'. Default Value: 0

18.1.11 SCB0_I2C_STATUS (continued)

1	I2C_EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If SCB block is disabled, BUS_BUSY is '0'. After enabling the block, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.12 SCB0_I2C_M_CMD

I2C master command register.

Address: 0x40080068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. This command has a higher priority than I2C_M_CMD.M_START: in situations where both a STOP and a REPEATED START could be transmitted, M_STOP takes precedence over M_START. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0'). A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.12 SCB0_I2C_M_CMD (continued)

0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.13 SCB0_I2C_S_CMD

I2C slave command register.

Address: 0x4008006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.14 SCB0_I2C_CFG

I2C configuration register.

Address: 0x40080070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative filter delay on SDA output to meet tHD_DAT parameter "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2

18.1.14 SCB0_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Enable for 50ns glitch filter on SCL input '0': 0 ns. '1': 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim settings for the 50ns glitch filter on the SDA input. Default setting meets the I2C glitch rejections specs. Programmability available if required Default Value: 0
4	SDA_IN_FILT_SEL	Enable for 50ns glitch filter on SDA input '0': 0 ns. '1': 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim settings for the 50ns glitch filter on the SDA input. Default setting meets the I2C glitch rejections specs. Programmability available if required Default Value: 3

18.1.15 SCB0_TX_CTRL

Transmitter control register.

Address: 0x40080200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_ - FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.16 SCB0_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40080204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event is generated. Default Value: 0

18.1.17 SCB0_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40080208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			USED [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is transmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

18.1.18 SCB0_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40080240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.19 SCB0_RX_CTRL

Receiver control register.

Address: 0x40080300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_ - FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptibility to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.20 SCB0_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40080304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event is generated. Default Value: 0

18.1.21 SCB0_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40080308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			USED [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

18.1.22 SCB0_RX_MATCH

Slave address and mask register.

Address: 0x40080310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the slave address bits take part in the matching. $MATCH = ((ADDR \& MASK) == ("slave\ address" \& MASK))$. Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.23 SCB0_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40080340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. When this register is read through the debugger, the data frame will not be removed from the FIFO. Similar in operation to RX_FIFO_RD_SILENT Default Value: Undefined

18.1.24 SCB0_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40080344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.25 SCB0_EZ_DATA0

Memory buffer registers.

Address: 0x40080400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.26 SCB0_EZ_DATA1

Memory buffer registers.

Address: 0x40080404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.27 SCB0_EZ_DATA2

Memory buffer registers.

Address: 0x40080408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.28 SCB0_EZ_DATA3

Memory buffer registers.

Address: 0x4008040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.29 SCB0_EZ_DATA4

Memory buffer registers.

Address: 0x40080410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.30 SCB0_EZ_DATA5

Memory buffer registers.

Address: 0x40080414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.31 SCB0_EZ_DATA6

Memory buffer registers.

Address: 0x40080418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.32 SCB0_EZ_DATA7

Memory buffer registers.

Address: 0x4008041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.33 SCB0_EZ_DATA8

Memory buffer registers.

Address: 0x40080420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.34 SCB0_EZ_DATA9

Memory buffer registers.

Address: 0x40080424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.35 SCB0_EZ_DATA10

Memory buffer registers.

Address: 0x40080428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.36 SCB0_EZ_DATA11

Memory buffer registers.

Address: 0x4008042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.37 SCB0_EZ_DATA12

Memory buffer registers.

Address: 0x40080430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.38 SCB0_EZ_DATA13

Memory buffer registers.

Address: 0x40080434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.39 SCB0_EZ_DATA14

Memory buffer registers.

Address: 0x40080438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.40 SCB0_EZ_DATA15

Memory buffer registers.

Address: 0x4008043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.41 SCB0_EZ_DATA16

Memory buffer registers.

Address: 0x40080440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.42 SCB0_EZ_DATA17

Memory buffer registers.

Address: 0x40080444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.43 SCB0_EZ_DATA18

Memory buffer registers.

Address: 0x40080448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.44 SCB0_EZ_DATA19

Memory buffer registers.

Address: 0x4008044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.45 SCB0_EZ_DATA20

Memory buffer registers.

Address: 0x40080450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.46 SCB0_EZ_DATA21

Memory buffer registers.

Address: 0x40080454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.47 SCB0_EZ_DATA22

Memory buffer registers.

Address: 0x40080458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.48 SCB0_EZ_DATA23

Memory buffer registers.

Address: 0x4008045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.49 SCB0_EZ_DATA24

Memory buffer registers.

Address: 0x40080460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.50 SCB0_EZ_DATA25

Memory buffer registers.

Address: 0x40080464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.51 SCB0_EZ_DATA26

Memory buffer registers.

Address: 0x40080468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.52 SCB0_EZ_DATA27

Memory buffer registers.

Address: 0x4008046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.53 SCB0_EZ_DATA28

Memory buffer registers.

Address: 0x40080470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.54 SCB0_EZ_DATA29

Memory buffer registers.

Address: 0x40080474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.55 SCB0_EZ_DATA30

Memory buffer registers.

Address: 0x40080478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.56 SCB0_EZ_DATA31

Memory buffer registers.

Address: 0x4008047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.57 SCB0_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40080E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.58 SCB0_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40080E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0

18.1.58 SCB0_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when CTRL.EC_AM_MODE is '1'. Default Value: 0

18.1.59 SCB0_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40080E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.60 SCB0_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40080E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.61 SCB0_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40080EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI deselection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when CTRL.EC_OP_MODE is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI deselection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when CTRL.EC_OP_MODE is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when CTRL.EC_OP_MODE is '1'. Default Value: 0

18.1.61 SCB0_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when CTRL.EC_AM_MODE is '1'. Default Value: 0

18.1.62 SCB0_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40080EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.63 SCB0_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40080ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.64 SCB0_INTR_M

Master interrupt request register.

Address: 0x40080F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO is empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.65 SCB0_INTR_M_SET

Master interrupt set request register

Address: 0x40080F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.66 SCB0_INTR_M_MASK

Master interrupt mask register.

Address: 0x40080F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.67 SCB0_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40080F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.68 SCB0_INTR_S

Slave interrupt request register.

Address: 0x40080F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GEN- ERAL	I2C_AD- DR_MATCH	I2C_START	I2C_STOP	I2C_WRITE _STOP	I2C_ACK	I2C_NACK	I2C_AR- B_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_E RROR	SPI_EZ_ST OP	SPI_EZ_W RITE_STOP	I2C_BUS_E RROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.68 SCB0_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine aborts the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.69 SCB0_INTR_S_SET

Slave interrupt set request register.

Address: 0x40080F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.69 SCB0_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.70 SCB0_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40080F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.70 SCB0_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.71 SCB0_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40080F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.71 SCB0_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.72 SCB0_INTR_TX

Transmitter interrupt request register.

Address: 0x40080F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	SW cannot get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.72 SCB0_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when SCB is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.73 SCB0_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40080F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.73 SCB0_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.74 SCB0_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40080F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.74 SCB0_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.75 SCB0_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40080F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.75 SCB0_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.76 SCB0_INTR_RX

Receiver interrupt request register.

Address: 0x40080FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.76 SCB0_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	SW cannot get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODET: BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.77 SCB0_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40080FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.77 SCB0_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.78 SCB0_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40080FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.78 SCB0_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.79 SCB0_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40080FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.79 SCB0_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.80 SCB1_CTRL

Generic control register.

Address: 0x40090000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BYTE_- MODE	EZ_MODE	EC_OP_- MODE	EC_AM_- MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_AC- CEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	SCB block is enabled ('1') or not ('0'). The proper order in which to initialize SCB is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL registers. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL register to enable SCB, select the specific operation mode and oversampling factor. When this block is enabled, no control information should be changed. Changes should be made AFTER disabling this block, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the block is re-enabled. Note that disabling the block will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Default Value: 3

18.1.80 SCB1_CTRL (continued)

0x0: I2C:

0x1: SPI:

0x2: UART:

17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the internal CPU accesses to EZ memory coincide/collide, this bit determines whether the CPU access should block and result in bus wait states ('BLOCK is 1') or not ('BLOCK is 0'). If BLOCK is 0 and the accesses collide, CPU read operations return 0xffff:ffff and CPU write operations are ignored. Colliding accesses are registered as interrupt causes: INTR_TX.BLOCKED and INTR_RX.BLOCKED. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when this bit is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
11	BYTE_MODE	Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames not separated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	This field specifies the clocking for the SCB block '0': Internally clocked mode '1': externally clocked mode In internally clocked mode, the serial interface protocols run off the SCB clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.80 SCB1_CTRL (continued)

8	EC_AM_MODE	This field specifies the clocking for the address matching (I2C) or slave selection detection logic (SPI) '0': Internally clocked mode '1': Externally clocked mode In internally clocked mode, the serial interface protocols run off the SCB clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. The clocking for the rest of the logic is determined by CTRL.EC_OP_MODE. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.80 SCB1_CTRL (continued)

3 : 0 OVS

Serial interface bit period oversampling factor expressed in SCB clock cycles. Used for SPI and UART functionality. $OVS + 1$ SCB clock cycles constitute a single serial interface clock/bit cycle. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the low and high phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the low and high phase can differ by 1 SCB clock period.

In SPI master mode, the valid range is [3, 15]. At an SCB frequency of 48 MHz, the maximum SPI bit rate is 12 Mbps, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock to SPI MISO input round trip delay is significant (multiple SPI output clock cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate.

In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the SPI input clock (IF) on the interface to guarantee functional correct behavior. This requirement is expressed as a ratio: SCB clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE):

- MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": SCB clock/IF clock ≥ 6 . At a SCB frequency of 48 MHz, the maximum bit rate is 8 Mbps.
- MEDIAN is '0' and external SPI master has "late MISO sample functionality": SCB clock/IF clock ≥ 3 . At a SCB frequency of 48 MHz, the maximum bit rate is 16 Mbps.
- MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": SCB clock/IF clock ≥ 8 . At a SCB frequency of 48 MHz, the maximum bit rate is 6 Mbps.
- MEDIAN is '1' and external SPI master has "late MISO sample functionality": SCB clock/IF clock ≥ 4 . At a SCB frequency of 48 MHz, the maximum bit rate is 12 Mbps.

As discussed earlier, the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account.

In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15].

In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value:

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
 - SCB clock frequency of 16×57.6 KHz for 57.6 Kbps.
 - SCB clock frequency of 16×38.4 KHz for 38.4 Kbps.
 - SCB clock frequency of 16×19.2 KHz for 19.2 Kbps.
 - SCB clock frequency of 16×9.6 KHz for 9.6 Kbps.
 - SCB clock frequency of 16×2.4 KHz for 2.4 Kbps.
 - SCB clock frequency of 16×1.2 KHz for 1.2 Kbps.
- all other values are not used in normal mode.

In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two SCB clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two SCB clock cycles and greater or equal than one SCB clock cycle may be detected by the receiver. Pulse widths less than one SCB clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The SCB clock (as provided by the programmable clock block) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required SCB clock frequency):

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
 - SCB clock frequency of 16×57.6 KHz for 57.6 Kbps.
 - SCB clock frequency of 16×38.4 KHz for 38.4 Kbps.
 - SCB clock frequency of 16×19.2 KHz for 19.2 Kbps.
 - SCB clock frequency of 16×9.6 KHz for 9.6 Kbps.
 - SCB clock frequency of 16×2.4 KHz for 2.4 Kbps.
 - SCB clock frequency of 16×1.2 KHz for 1.2 Kbps.
- all other values are not used in normal mode.

Low power mode, OVS field values (with the required SCB clock frequency):

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
- 1: 32 times oversampling.
 - SCB clock frequency of 32×57.6 KHz for 57.6 Kbps.
- 2: 48 times oversampling.
 - SCB clock frequency of 48×38.4 KHz for 38.4 Kbps.
- 3: 96 times oversampling.
 - SCB clock frequency of 96×19.2 KHz for 19.2 Kbps.
- 4: 192 times oversampling.
 - SCB clock frequency of 192×9.6 KHz for 9.6 Kbps.
- 5: 768 times oversampling.
 - SCB clock frequency of 768×2.4 KHz for 2.4 Kbps.
- 6: 1536 times oversampling.
 - SCB clock frequency of 1536×1.2 KHz for 1.2 Kbps.
- all other values are not used in low power mode.

Default Value: 15

18.1.81 SCB1_STATUS

Generic status register.

Address: 0x40090004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.82 SCB1_SPI_CTRL

SPI control register.

Address: 0x40090020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_- CONTINU- OUS	LATE_MISO_ SAMPLE	CPOL	CPHA	SE- LECT_PRE- CEDE	CONTINU- OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_PO- LARITY3	SSEL_PO- LARITY2	SSEL_PO- LARITY1	SSEL_PO- LARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_- MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. SCB block should be disabled when changes are made to this field. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.82 SCB1_SPI_CTRL (continued)

0x0: SPI_MOTOROLA:

SPI Motorola submode. In master mode, when not transmitting data (Slave SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive.

0x1: SPI_TI:

SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive; i.e. no pulse is generated.

0x2: SPI_NS:

SPI National Semiconductors submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive.

16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': No local loopback '1': the SPI master MISO line is connected to the SPI master MOSI line. In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Instruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.82 SCB1_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is 0: SCLK is 0 when not transmitting data. - CPOL is 1: SCLK is 1 when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is 0, CPHA is 0: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is 0, CPHA is 1: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is 1, CPHA is 0: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is 1, CPHA is 1: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the Slave SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the Slave SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily separated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are sent out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always separated by slave deselection: independent of the availability of TX FIFO data frames, data frames are sent out with slave deselection. Default Value: 0

18.1.83 SCB1_SPI_STATUS

SPI status register.

Address: 0x40090024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.84 SCB1_UART_CTRL

UART control register.

Address: 0x40090040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK
Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 0x0: UART_STD: Standard UART submode. 0x1: UART_SMARTCARD: SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. 0x2: UART_IRDA: Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS should be set to 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). 0: Loopback is not enabled 1: UART_TX is connected to UART_RX. UART_RTS is connected to UART_CTS. This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.85 SCB1_UART_TX_CTRL

UART transmitter control register.

Address: 0x40090044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.86 SCB1_UART_RX_CTRL

UART receiver control register.

Address: 0x40090048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.86 SCB1_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame separates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is sent to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is sent to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal. Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.86 SCB1_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.87 SCB1_UART_RX_STATUS

UART receiver status register.

Address: 0x4009004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least significant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when IN-TR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.88 SCB1_UART_FLOW_CTRL

UART flow control register

Address: 0x40090050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_PO- LARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_EN- ABLED	CTS_PO- LARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal by the UART transmitter: '0': Disabled. The UART transmitter ignores the CTS input signal and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses CTS input signal to qualify the transmission of data. It transmits when CTS input signal is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', the CTS input signal is driven by the RTS output signal locally in SCB (both signals are subjected to signal polarity changes are indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal '0': CTS is active low ; '1': CTS is active high; Default Value: 0

18.1.88 SCB1_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal: '0': RTS is active low; '1': RTS is active high; During SCB reset (Hibernate system power mode), RTS output signal is '1'. This represents an inactive state assuming an active low polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal is activated. By setting this field to "0", flow control is effectively disabled (may be useful for debug purposes). Default Value: 0

18.1.89 SCB1_I2C_CTRL

I2C control register.

Address: 0x40090060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', no loopback When '1', loopback is enabled internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0

18.1.89 SCB1_I2C_CTRL (continued)

15	S_NOT_READY_DATA_NACK	Only used when: - non EZ mode Functionality is as follows: - 1: a received data element by the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1
14	S_NOT_READY_ADDR_NACK	This field is used during an address match or general call address in internally clocked mode Only used when: - EC_AM_MODE is '0', EC_OP_MODE is '0', S_GENERAL_IGNORE is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the SCB clock is available (in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). SCB clock is not present (in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the SCB clock is available). The logic will handle the ongoing transfer as soon as the clock is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1

18.1.89 SCB1_I2C_CTRL (continued)

7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 SCB clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the regular (no stretching) interface (IF) low time to guarantee functionally correct behavior. With input signal median filtering, the IF low time should be ≥ 8 SCB clock cycles and ≤ 16 IP clock cycles. Without input signal median filtering, the IF low time should be ≥ 7 SCB clock cycles and ≤ 16 SCB clock cycles. Default Value: 8
3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 SCB clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be ≥ 6 SCB clock cycles and ≤ 16 SCB clock cycles. Without input signal median filtering, the IF high time should be ≥ 5 SCB clock cycles and ≤ 16 SCB clock cycles. Default Value: 8

18.1.90 SCB1_I2C_STATUS

I2C status register.

Address: 0x40090064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/ idle or transmitting START, REPEATED START, STOP or an address, this field is '0'. Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0'. Default Value: 0

18.1.90 SCB1_I2C_STATUS (continued)

1	I2C_EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If SCB block is disabled, BUS_BUSY is '0'. After enabling the block, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.91 SCB1_I2C_M_CMD

I2C master command register.

Address: 0x40090068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. This command has a higher priority than I2C_M_CMD.M_START: in situations where both a STOP and a REPEATED START could be transmitted, M_STOP takes precedence over M_START. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0'). A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.91 SCB1_I2C_M_CMD (continued)

0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.92 SCB1_I2C_S_CMD

I2C slave command register.

Address: 0x4009006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.93 SCB1_I2C_CFG

I2C configuration register.

Address: 0x40090070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative filter delay on SDA output to meet tHD_DAT parameter "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2

18.1.93 SCB1_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Enable for 50ns glitch filter on SCL input '0': 0 ns. '1': 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim settings for the 50ns glitch filter on the SDA input. Default setting meets the I2C glitch rejections specs. Programmability available if required Default Value: 0
4	SDA_IN_FILT_SEL	Enable for 50ns glitch filter on SDA input '0': 0 ns. '1': 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim settings for the 50ns glitch filter on the SDA input. Default setting meets the I2C glitch rejections specs. Programmability available if required Default Value: 3

18.1.94 SCB1_TX_CTRL

Transmitter control register.

Address: 0x40090200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_ - FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.95 SCB1_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x40090204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event is generated. Default Value: 0

18.1.96 SCB1_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x40090208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			USED [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is transmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

18.1.97 SCB1_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x40090240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.98 SCB1_RX_CTRL

Receiver control register.

Address: 0x40090300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_ - FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptibility to errors. However, its requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.99 SCB1_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x40090304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event is generated. Default Value: 0

18.1.100 SCB1_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x40090308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			USED [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

18.1.101 SCB1_RX_MATCH

Slave address and mask register.

Address: 0x40090310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the slave address bits take part in the matching. $MATCH = ((ADDR \& MASK) == ("slave\ address" \& MASK))$. Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.102 SCB1_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x40090340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. When this register is read through the debugger, the data frame will not be removed from the FIFO. Similar in operation to RX_FIFO_RD_SILENT Default Value: Undefined

18.1.103 SCB1_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x40090344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.104 SCB1_EZ_DATA0

Memory buffer registers.

Address: 0x40090400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.105 SCB1_EZ_DATA1

Memory buffer registers.

Address: 0x40090404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.106 SCB1_EZ_DATA2

Memory buffer registers.

Address: 0x40090408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.107 SCB1_EZ_DATA3

Memory buffer registers.

Address: 0x4009040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.108 SCB1_EZ_DATA4

Memory buffer registers.

Address: 0x40090410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.109 SCB1_EZ_DATA5

Memory buffer registers.

Address: 0x40090414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.110 SCB1_EZ_DATA6

Memory buffer registers.

Address: 0x40090418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.111 SCB1_EZ_DATA7

Memory buffer registers.

Address: 0x4009041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.112 SCB1_EZ_DATA8

Memory buffer registers.

Address: 0x40090420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.113 SCB1_EZ_DATA9

Memory buffer registers.

Address: 0x40090424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.114 SCB1_EZ_DATA10

Memory buffer registers.

Address: 0x40090428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.115 SCB1_EZ_DATA11

Memory buffer registers.

Address: 0x4009042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.116 SCB1_EZ_DATA12

Memory buffer registers.

Address: 0x40090430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.117 SCB1_EZ_DATA13

Memory buffer registers.

Address: 0x40090434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.118 SCB1_EZ_DATA14

Memory buffer registers.

Address: 0x40090438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.119 SCB1_EZ_DATA15

Memory buffer registers.

Address: 0x4009043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.120 SCB1_EZ_DATA16

Memory buffer registers.

Address: 0x40090440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.121 SCB1_EZ_DATA17

Memory buffer registers.

Address: 0x40090444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.122 SCB1_EZ_DATA18

Memory buffer registers.

Address: 0x40090448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.123 SCB1_EZ_DATA19

Memory buffer registers.

Address: 0x4009044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.124 SCB1_EZ_DATA20

Memory buffer registers.

Address: 0x40090450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.125 SCB1_EZ_DATA21

Memory buffer registers.

Address: 0x40090454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.126 SCB1_EZ_DATA22

Memory buffer registers.

Address: 0x40090458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.127 SCB1_EZ_DATA23

Memory buffer registers.

Address: 0x4009045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.128 SCB1_EZ_DATA24

Memory buffer registers.

Address: 0x40090460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.129 SCB1_EZ_DATA25

Memory buffer registers.

Address: 0x40090464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.130 SCB1_EZ_DATA26

Memory buffer registers.

Address: 0x40090468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.131 SCB1_EZ_DATA27

Memory buffer registers.

Address: 0x4009046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.132 SCB1_EZ_DATA28

Memory buffer registers.

Address: 0x40090470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.133 SCB1_EZ_DATA29

Memory buffer registers.

Address: 0x40090474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.134 SCB1_EZ_DATA30

Memory buffer registers.

Address: 0x40090478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.135 SCB1_EZ_DATA31

Memory buffer registers.

Address: 0x4009047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.136 SCB1_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x40090E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.137 SCB1_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x40090E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0

18.1.137 SCB1_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when CTRL.EC_AM_MODE is '1'. Default Value: 0

18.1.138 SCB1_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x40090E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.139 SCB1_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x40090E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.140 SCB1_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x40090EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI deselection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when CTRL.EC_OP_MODE is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI deselection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when CTRL.EC_OP_MODE is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when CTRL.EC_OP_MODE is '1'. Default Value: 0

18.1.140 SCB1_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when CTRL.EC_AM_MODE is '1'. Default Value: 0

18.1.141 SCB1_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x40090EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.142 SCB1_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x40090ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.143 SCB1_INTR_M

Master interrupt request register.

Address: 0x40090F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO is empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.144 SCB1_INTR_M_SET

Master interrupt set request register

Address: 0x40090F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.145 SCB1_INTR_M_MASK

Master interrupt mask register.

Address: 0x40090F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.146 SCB1_INTR_M_MASKED

Master interrupt masked request register

Address: 0x40090F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.147 SCB1_INTR_S

Slave interrupt request register.

Address: 0x40090F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GEN- ERAL	I2C_AD- DR_MATCH	I2C_START	I2C_STOP	I2C_WRITE _STOP	I2C_ACK	I2C_NACK	I2C_AR- B_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_E RROR	SPI_EZ_ST OP	SPI_EZ_W RITE_STOP	I2C_BUS_E RROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.147 SCB1_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine aborts the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.148 SCB1_INTR_S_SET

Slave interrupt set request register.

Address: 0x40090F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.148 SCB1_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.149 SCB1_INTR_S_MASK

Slave interrupt mask register.

Address: 0x40090F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.149 SCB1_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.150 SCB1_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x40090F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.150 SCB1_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.151 SCB1_INTR_TX

Transmitter interrupt request register.

Address: 0x40090F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	SW cannot get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.151 SCB1_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when SCB is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.152 SCB1_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x40090F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.152 SCB1_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.153 SCB1_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x40090F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.153 SCB1_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.154 SCB1_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x40090F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.154 SCB1_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.155 SCB1_INTR_RX

Receiver interrupt request register.

Address: 0x40090FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.155 SCB1_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	SW cannot get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODET: BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.156 SCB1_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x40090FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.156 SCB1_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.157 SCB1_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x40090FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.157 SCB1_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.158 SCB1_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x40090FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.158 SCB1_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.159 SCB2_CTRL

Generic control register.

Address: 0x400A0000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BYTE_- MODE	EZ_MODE	EC_OP_- MODE	EC_AM_- MODE

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						BLOCK	ADDR_AC- CEPT

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None					RW	
HW Access	R	None					R	
Name	ENABLED	None [30:26]					MODE [25:24]	

Bits	Name	Description
31	ENABLED	SCB block is enabled ('1') or not ('0'). The proper order in which to initialize SCB is as follows: - Program protocol specific information using SPI_CTRL, UART_CTRL (and UART_TX_CTRL and UART_RX_CTRL) or I2C_CTRL registers. This includes selection of a submode, master/slave functionality and transmitter/receiver functionality when applicable. - Program generic transmitter (TX_CTRL) and receiver (RX_CTRL) information. This includes enabling of the transmitter and receiver functionality. - Program transmitter FIFO (TX_FIFO_CTRL) and receiver FIFO (RX_FIFO_CTRL) information. - Program CTRL register to enable SCB, select the specific operation mode and oversampling factor. When this block is enabled, no control information should be changed. Changes should be made AFTER disabling this block, e.g. to modify the operation mode (from I2C to SPI) or to go from externally to internally clocked. The change takes effect after the block is re-enabled. Note that disabling the block will cause re-initialization of the design and associated state is lost (e.g. FIFO content). Default Value: 0
25 : 24	MODE	Default Value: 3

18.1.159 SCB2_CTRL (continued)

0x0: I2C:

0x1: SPI:

0x2: UART:

17	BLOCK	Only used in externally clocked mode. If the externally clocked logic and the internal CPU accesses to EZ memory coincide/collide, this bit determines whether the CPU access should block and result in bus wait states ('BLOCK is 1') or not ('BLOCK is 0'). If BLOCK is 0 and the accesses collide, CPU read operations return 0xffff:ffff and CPU write operations are ignored. Colliding accesses are registered as interrupt causes: INTR_TX.BLOCKED and INTR_RX.BLOCKED. Default Value: 0
16	ADDR_ACCEPT	Determines whether a received matching address is accepted in the RX FIFO ('1') or not ('0'). In I2C mode, this field is used to allow the slave to put the received slave address or general call address in the RX FIFO. Note that a received matching address is put in the RX FIFO when this bit is '1' for both I2C read and write transfers. In multi-processor UART receiver mode, this field is used to allow the receiver to put the received address in the RX FIFO. Note: non-matching addresses are never put in the RX FIFO. Default Value: 0
11	BYTE_MODE	Default Value: 0
10	EZ_MODE	Non EZ mode ('0') or EZ mode ('1'). In EZ mode, a meta protocol is applied to the serial interface protocol. This meta protocol adds meaning to the data frames transferred by the serial interface protocol: a data frame can represent a memory address, a write memory data element or a read memory data element. EZ mode is only used for synchronous serial interface protocols: SPI and I2C. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported and the transmitter should use continuous data frames; i.e. data frames not separated by slave deselection. This mode is only applicable to slave functionality. In EZ mode, the slave can read from and write to an addressable memory structure of 32 bytes. In EZ mode, data frames should 8-bit in size and should be transmitted and received with the Most Significant Bit (MSB) first. In UART mode this field should be '0'. Default Value: 0
9	EC_OP_MODE	This field specifies the clocking for the SCB block '0': Internally clocked mode '1': externally clocked mode In internally clocked mode, the serial interface protocols run off the SCB clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. Externally clocked operation mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode AND EZ mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. The maximum SPI slave, EZ mode bitrate is 48 Mbps (transmission and IO delays outside the IP will degrade the effective bitrate). In UART mode this field should be '0'. Default Value: 0

18.1.159 SCB2_CTRL (continued)

8	EC_AM_MODE	This field specifies the clocking for the address matching (I2C) or slave selection detection logic (SPI) '0': Internally clocked mode '1': Externally clocked mode In internally clocked mode, the serial interface protocols run off the SCB clock. In externally clocked mode, the serial interface protocols run off the clock as provided by the serial interface. The clocking for the rest of the logic is determined by CTRL.EC_OP_MODE. Externally clocked mode is only used for synchronous serial interface protocols (SPI and I2C) in slave mode. In SPI mode, only Motorola submode (all Motorola modes: 0, 1, 2, 3) is supported. In UART mode this field should be '0'. Default Value: 0

18.1.159 SCB2_CTRL (continued)

3 : 0 OVS

Serial interface bit period oversampling factor expressed in SCB clock cycles. Used for SPI and UART functionality. $OVS + 1$ SCB clock cycles constitute a single serial interface clock/bit cycle. This field is NOT used in externally clocked mode. If OVS is odd, the oversampling factor is even and the low and high phase of the interface clock period are the same. If OVS is even, the oversampling factor is odd and the low and high phase can differ by 1 SCB clock period.

In SPI master mode, the valid range is [3, 15]. At an SCB frequency of 48 MHz, the maximum SPI bit rate is 12 Mbps, assuming ideal (0 ns) IO cell and routing (chip and board) delay. The calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account. The effective system bit rate is dependent on the external SPI slave that we communicate with. If the SPI output clock to SPI MISO input round trip delay is significant (multiple SPI output clock cycles), it may be necessary to increase OVS and/or to set SPI_CTRL.LATE_MISO_SAMPLE to '1' to achieve the maximum possible system bit rate.

In SPI slave mode, the OVS field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the SPI input clock (IF) on the interface to guarantee functional correct behavior. This requirement is expressed as a ratio: SCB clock/IF clock. The ratio is dependent on the setting of RX_CTRL.MEDIAN and the external SPI master's capability to support "late MISO sample" functionality (similar to our SPI master functionality represented by SPI_CTRL.LATE_MISO_SAMPLE):

- MEDIAN is '0' and external SPI master has NO "late MISO sample functionality": SCB clock/IF clock ≥ 6 . At a SCB frequency of 48 MHz, the maximum bit rate is 8 Mbps.
- MEDIAN is '0' and external SPI master has "late MISO sample functionality": SCB clock/IF clock ≥ 3 . At a SCB frequency of 48 MHz, the maximum bit rate is 16 Mbps.
- MEDIAN is '1' and external SPI master has NO "late MISO sample functionality": SCB clock/IF clock ≥ 8 . At a SCB frequency of 48 MHz, the maximum bit rate is 6 Mbps.
- MEDIAN is '1' and external SPI master has "late MISO sample functionality": SCB clock/IF clock ≥ 4 . At a SCB frequency of 48 MHz, the maximum bit rate is 12 Mbps.

As discussed earlier, the calculated maximum bit rate decreases, when realistic chip and routing delays are taken into account.

In UART standard submode (including LIN), the valid range is [7, 15]. In UART SmartCard submode, the valid range is [7, 15].

In UART TX IrDA submode this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. Only normal transmission mode is supported, the pulse is roughly 3/16 of the bit period (for all bit rates). There is only one valid OVS value:

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
 - SCB clock frequency of 16×57.6 KHz for 57.6 Kbps.
 - SCB clock frequency of 16×38.4 KHz for 38.4 Kbps.
 - SCB clock frequency of 16×19.2 KHz for 19.2 Kbps.
 - SCB clock frequency of 16×9.6 KHz for 9.6 Kbps.
 - SCB clock frequency of 16×2.4 KHz for 2.4 Kbps.
 - SCB clock frequency of 16×1.2 KHz for 1.2 Kbps.
- all other values are not used in normal mode.

In UART RX IrDA submode (1.2, 2.4, 9.6, 19.2, 38.4, 57.6 and 115.2 Kbps) this field indirectly specifies the oversampling. The oversampling determines the interface clock/bit cycle and the width of the pulse. In normal transmission mode, this pulse is roughly 3/16 of the bit period (for all bit rates). In low power transmission mode, this pulse is potentially smaller (down to 1.62 us typical and 1.41 us minimal) than 3/16 of the bit period (for < 115.2 Kbps bitrates). Pulse widths greater or equal than two SCB clock cycles are guaranteed to be detected by the receiver. Pulse widths less than two SCB clock cycles and greater or equal than one SCB clock cycle may be detected by the receiver. Pulse widths less than one SCB clock cycle will not be detected by the receiver. RX_CTRL.MEDIAN should be set to '1' for IrDA receiver functionality. The SCB clock (as provided by the programmable clock block) and the oversampling together determine the IrDA bitrate. Normal mode, OVS field values (with the required SCB clock frequency):

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
 - SCB clock frequency of 16×57.6 KHz for 57.6 Kbps.
 - SCB clock frequency of 16×38.4 KHz for 38.4 Kbps.
 - SCB clock frequency of 16×19.2 KHz for 19.2 Kbps.
 - SCB clock frequency of 16×9.6 KHz for 9.6 Kbps.
 - SCB clock frequency of 16×2.4 KHz for 2.4 Kbps.
 - SCB clock frequency of 16×1.2 KHz for 1.2 Kbps.
- all other values are not used in normal mode.

Low power mode, OVS field values (with the required SCB clock frequency):

- 0: 16 times oversampling.
 - SCB clock frequency of 16×115.2 KHz for 115.2 Kbps.
- 1: 32 times oversampling.
 - SCB clock frequency of 32×57.6 KHz for 57.6 Kbps.
- 2: 48 times oversampling.
 - SCB clock frequency of 48×38.4 KHz for 38.4 Kbps.
- 3: 96 times oversampling.
 - SCB clock frequency of 96×19.2 KHz for 19.2 Kbps.
- 4: 192 times oversampling.
 - SCB clock frequency of 192×9.6 KHz for 9.6 Kbps.
- 5: 768 times oversampling.
 - SCB clock frequency of 768×2.4 KHz for 2.4 Kbps.
- 6: 1536 times oversampling.
 - SCB clock frequency of 1536×1.2 KHz for 1.2 Kbps.
- all other values are not used in low power mode.

Default Value: 15

18.1.160 SCB2_STATUS

Generic status register.

Address: 0x400A0004

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							EC_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory (this is only possible in EZ mode). This bit can be used by SW to determine whether it is safe to issue a SW access to the EZ memory (without bus wait states (a blocked SW access) or bus errors being generated). Note that the INTR_TX.BLOCKED and INTR_RX.BLOCKED interrupt causes are used to indicate whether a SW access was actually blocked by externally clocked logic. Default Value: Undefined

18.1.161 SCB2_SPI_CTRL

SPI control register.

Address: 0x400A0020

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	RW	RW	RW	RW
HW Access	None		R	R	R	R	R	R
Name	None [7:6]		SCLK_- CONTINU- OUS	LATE_MISO_ SAMPLE	CPOL	CPHA	SE- LECT_PRE- CEDE	CONTINU- OUS

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SSEL_PO- LARITY3	SSEL_PO- LARITY2	SSEL_PO- LARITY1	SSEL_PO- LARITY0

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None			RW		RW	
HW Access	R	None			R		R	
Name	MASTER_- MODE	None [30:28]			SLAVE_SELECT [27:26]		MODE [25:24]	

Bits	Name	Description
31	MASTER_MODE	Master ('1') or slave ('0') mode. In master mode, transmission will commence on availability of data frames in the TX FIFO. In slave mode, when selected and there is no data frame in the TX FIFO, the slave will transmit all '1's. In both master and slave modes, received data frames will be lost if the RX FIFO is full. Default Value: 0
27 : 26	SLAVE_SELECT	Selects one of the four outgoing SPI slave select signals: - 0: Slave 0, SPI_SELECT[0]. - 1: Slave 1, SPI_SELECT[1]. - 2: Slave 2, SPI_SELECT[2]. - 3: Slave 3, SPI_SELECT[3]. Only used in master mode. SCB block should be disabled when changes are made to this field. Default Value: 0
25 : 24	MODE	Submode of SPI operation (3: Reserved). Default Value: 3

18.1.161 SCB2_SPI_CTRL (continued)

0x0: SPI_MOTOROLA:

SPI Motorola submode. In master mode, when not transmitting data (Slave SELECT is inactive), SCLK is stable at CPOL. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive.

0x1: SPI_TI:

SPI Texas Instruments submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive; i.e. no pulse is generated.

0x2: SPI_NS:

SPI National Semiconductors submode. In master mode, when not transmitting data, SCLK is stable at '0'. In slave mode, when not selected, SCLK is ignored; i.e. it can be either stable or clocking. In master mode, when there is no data to transmit (TX FIFO is empty), Slave SELECT is inactive.

16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only used in master mode. Not used in National Semiconductors submode. '0': No local loopback '1': the SPI master MISO line is connected to the SPI master MOSI line. In other words, in loopback mode the SPI master receives on MISO what it transmits on MOSI. Default Value: 0
11	SSEL_POLARITY3	Slave select polarity. SSEL_POLARITY3 applies to the outgoing SPI slave select signal 3 (master mode). Default Value: 0
10	SSEL_POLARITY2	Slave select polarity. SSEL_POLARITY2 applies to the outgoing SPI slave select signal 2 (master mode). Default Value: 0
9	SSEL_POLARITY1	Slave select polarity. SSEL_POLARITY1 applies to the outgoing SPI slave select signal 1 (master mode). Default Value: 0
8	SSEL_POLARITY0	Slave select polarity. SSEL_POLARITY0 applies to the outgoing SPI slave select signal 0 (master mode) and to the incoming SPI slave select signal (slave mode). For Motorola and National Semiconductors submodes: '0': slave select is low/'0' active. '1': slave select is high/'1' active. For Texas Instruments submode: '0': high/'1' active precede/coincide pulse. '1': low/'0' active precede/coincide pulse. Default Value: 0
5	SCLK_CONTINUOUS	Only applicable in master mode. '0': SCLK is generated, when the SPI master is enabled and data is transmitted. '1': SCLK is generated, when the SPI master is enabled. This mode is useful for slave devices that use SCLK for functional operation other than just SPI functionality. Default Value: 0

18.1.161 SCB2_SPI_CTRL (continued)

4	LATE_MISO_SAMPLE	Changes the SCLK edge on which MISO is captured. Only used in master mode. When '0', the default applies (for Motorola as determined by CPOL and CPHA, for Texas Instruments on the falling edge of SCLK and for National Semiconductors on the rising edge of SCLK). When '1', the alternate clock edge is used (which comes half a SPI SCLK period later). Late sampling addresses the round trip delay associated with transmitting SCLK from the master to the slave and transmitting MISO from the slave to the master. Default Value: 0
3	CPOL	Indicates the clock polarity. Only used in SPI Motorola submode. This field, together with the CPHA field, indicates when MOSI data is driven and MISO data is captured: - CPOL is 0: SCLK is 0 when not transmitting data. - CPOL is 1: SCLK is 1 when not transmitting data. Default Value: 0
2	CPHA	Only applicable in SPI Motorola submode. Indicates the clock phase. This field, together with the CPOL field, indicates when MOSI data is driven and MISO data is captured: - Motorola mode 0. CPOL is 0, CPHA is 0: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. - Motorola mode 1. CPOL is 0, CPHA is 1: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 2. CPOL is 1, CPHA is 0: MOSI is driven on a rising edge of SCLK. MISO is captured on a falling edge of SCLK. - Motorola mode 3. CPOL is 1, CPHA is 1: MOSI is driven on a falling edge of SCLK. MISO is captured on a rising edge of SCLK. Default Value: 0
1	SELECT_PRECEDE	Only used in SPI Texas Instruments' submode. When '1', the data frame start indication is a pulse on the Slave SELECT line that precedes the transfer of the first data frame bit. When '0', the data frame start indication is a pulse on the Slave SELECT line that coincides with the transfer of the first data frame bit. Default Value: 0
0	CONTINUOUS	Continuous SPI data transfers enabled ('1') or not ('0'). This field is used in master mode. In slave mode, both continuous and non-continuous SPI data transfers are supported independent of this field. When continuous transfers are enabled individual data frame transfers are not necessarily separated by slave deselection (as indicated by the level or pulse on the SELECT line): if the TX FIFO has multiple data frames, data frames are sent out without slave deselection. When continuous transfers are not enabled individual data frame transfers are always separated by slave deselection: independent of the availability of TX FIFO data frames, data frames are sent out with slave deselection. Default Value: 0

18.1.162 SCB2_SPI_STATUS

SPI status register.

Address: 0x400A0024

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						R	R
HW Access	None						W	W
Name	None [7:2]						SPI_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	SPI base EZ address. Address as provided by a SPI write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	SPI current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when SPI_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
1	SPI_EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	SPI bus is busy. The bus is considered busy ('1') during an ongoing transaction. For Motorola and National submodes, the busy bit is '1', when the slave selection (low active) is activated. For TI submode, the busy bit is '1' from the time the preceding/coinciding slave select (high active) is activated for the first transmitted data frame, till the last MOSI/MISO bit of the last data frame is transmitted. Default Value: Undefined

18.1.163 SCB2_UART_CTRL

UART control register.

Address: 0x400A0040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK
Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	
HW Access	None						R	
Name	None [31:26]						MODE [25:24]	

Bits	Name	Description
25 : 24	MODE	Submode of UART operation (3: Reserved) Default Value: 3 0x0: UART_STD: Standard UART submode. 0x1: UART_SMARTCARD: SmartCard (ISO7816) submode. Support for negative acknowledgement (NACK) on the receiver side and retransmission on the transmitter side. 0x2: UART_IRDA: Infrared Data Association (IrDA) submode. Return to Zero modulation scheme. In this mode, the oversampling factor should be 16, that is OVS should be set to 15.
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). 0: Loopback is not enabled 1: UART_TX is connected to UART_RX. UART_RTS is connected to UART_CTS. This allows a SCB UART transmitter to communicate with its receiver counterpart. Default Value: 0

18.1.164 SCB2_UART_TX_CTRL

UART transmitter control register.

Address: 0x400A0044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW	RW	None	RW		
HW Access	None		R	R	None	R		
Name	None [7:6]		PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							RETRY_ON_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	RETRY_ON_NACK	When '1', a data frame is retransmitted when a negative acknowledgement is received. Only applicable to the SmartCard submode. Default Value: 0
5	PARITY_ENABLED	Parity generation enabled ('1') or not ('0'). Only applicable in standard UART submodes. In SmartCard submode, parity generation is always enabled through hardware. In IrDA submode, parity generation is always disabled through hardware Default Value: 0
4	PARITY	Parity bit. When '0', the transmitter generates an even parity. When '1', the transmitter generates an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0
2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. Default Value: 2

18.1.165 SCB2_UART_RX_CTRL

UART receiver control register.

Address: 0x400A0048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW	RW	None	RW		
HW Access	None	R	R	R	None	R		
Name	None	POLARITY	PARITY_ENABLED	PARITY	None	STOP_BITS [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None		RW	RW	None	RW	RW	RW
HW Access	None		R	R	None	R	R	R
Name	None [15:14]		SKIP_START	LIN_MODE	None	MP_MODE	DROP_ON_FRAME_ERROR	DROP_ON_PARITY_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				BREAK_WIDTH [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	BREAK_WIDTH	Break width. BREAK_WIDTH + 1 is the minimum width in bit periods of a break. During a break the transmitted/received line value is '0'. This feature is useful for standard UART submode and LIN submode ("break field" detection). Once, the break is detected, the INTR_RX.BREAK_DETECT bit is set to '1'. Note that break detection precedes baud rate detection, which is used to synchronize/refine the receiver clock to the transmitter clock. As a result, break detection operates with an unsynchronized/unrefined receiver clock. Therefore, the receiver's definition of a bit period is imprecise and the setting of this field should take this imprecision into account. The LIN standard also accounts for this imprecision: a LIN start bit followed by 8 data bits allows for up to 9 consecutive '0' bit periods during regular transmission, whereas the LIN break detection should be at least 13 consecutive '0' bit periods. This provides for a margin of 4 bit periods. Therefore, the default value of this field is set to 10, representing a minimal break field with of 10+1 = 11 bit periods; a value in between the 9 consecutive bit periods of a regular transmission and the 13 consecutive bit periods of a break field. This provides for slight imprecisions of the receiver clock wrt. the transmitter clock. There should not be a need to program this field to any value other than its default value. Default Value: 10

18.1.165 SCB2_UART_RX_CTRL (continued)

13	SKIP_START	Only applicable in standard UART submode. When '1', the receiver skips start bit detection for the first received data frame. Instead, it synchronizes on the first received data frame bit, which should be a '1'. This functionality is intended for wake up from DeepSleep when receiving a data frame. The transition from idle ('1') to START ('0') on the RX line is used to wake up the CPU. The transition detection (and the associated wake up functionality) is performed by the GPIO2 IP. The woken up CPU will enable the SCB's UART receiver functionality. Once enabled, it is assumed that the START bit is ongoing (the CPU wakeup and SCB enable time should be less than the START bit period). The SCB will synchronize to a '0' to '1' transition, which indicates the first data frame bit is received (first data frame bit should be '1'). After synchronization to the first data frame bit, the SCB will resume normal UART functionality: subsequent data frames will be synchronized on the receipt of a START bit. Default Value: 0
12	LIN_MODE	Only applicable in standard UART submode. When '1', the receiver performs break detection and baud rate detection on the incoming data. First, break detection counts the amount of bit periods that have a line value of '0'. BREAK_WIDTH specifies the minum required amount of bit periods. Successful break detection sets the INTR_RX.BREAK_DETECT interrupt cause to '1'. Second, baud rate detection counts the amount of peripheral clock periods that are use to receive the synchronization byte (0x55; least significant bit first). The count is available through UART_RX_STATUS.BR_COUNTER. Successful baud rate detection sets the INTR_RX.BAUD_DETECT interrupt cause to '1' (BR_COUNTER is reliable). This functionality is used to synchronize/refine the receiver clock to the transmitter clock. The receiver software can use the BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Default Value: 0
10	MP_MODE	Multi-processor mode. When '1', multi-processor mode is enabled. In this mode, RX_CTRL.DATA_WIDTH should indicate a 9-bit data frame. In multi-processor mode, the 9th received bit of a data frame separates addresses (bit is '1') from data (bit is '0'). A received address is matched with RX_MATCH.DATA and RX_MATCH.MASK. In the case of a match, subsequent received data are sent to the RX FIFO. In the case of NO match, subsequent received data are dropped. Default Value: 0
9	DROP_ON_FRAME_ERROR	Behaviour when an error is detected in a start or stop period. When '0', received data is sent to the RX FIFO. When '1', received data is dropped and lost. Default Value: 0
8	DROP_ON_PARITY_ERROR	Behaviour when a parity check fails. When '0', received data is sent to the RX FIFO. When '1', received data is dropped and lost. Only applicable in standard UART and SmartCard submodes (negatively acknowledged SmartCard data frames may be dropped with this field). Default Value: 0
6	POLARITY	Inverts incoming RX line signal. Inversion is after local loopback. This functionality is intended for IrDA receiver functionality. Default Value: 0
5	PARITY_ENABLED	Parity checking enabled ('1') or not ('0'). Only applicable in standard UART submode. In SmartCard submode, parity checking is always enabled through hardware. In IrDA submode, parity checking is always disabled through hardware. Default Value: 0
4	PARITY	Parity bit. When '0', the receiver expects an even parity. When '1', the receiver expects an odd parity. Only applicable in standard UART and SmartCard submodes. Default Value: 0

18.1.165 SCB2_UART_RX_CTRL (continued)

2 : 0	STOP_BITS	Stop bits. STOP_BITS + 1 is the duration of the stop period in terms of halve bit periods. Valid range is [1, 7]; i.e. a stop period should last at least one bit period. If STOP_BITS is '1', stop bits error detection is NOT performed. If STOP_BITS is in [2, 7], stop bits error detection is performed and the associated interrupt cause INTR_RX.FRAME_ERROR is set to '1' if an error is detected. In other words, the receiver supports data frames with a 1 bit period stop bit sequence, but requires at least 1.5 bit period stop bit sequences to detect errors. This limitation is due to possible transmitter and receiver clock skew that prevents the design from doing reliable stop bit detection for short (1 bit bit period) stop bit sequences. Note that in case of a stop bits error, the successive data frames may get lost as the receiver needs to resynchronize its start bit detection. The amount of lost data frames depends on both the amount of stop bits, the idle ('1') time between data frames and the data frame value. Default Value: 2

18.1.166 SCB2_UART_RX_STATUS

UART receiver status register.

Address: 0x400A004C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	BR_COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None				R			
HW Access	None				W			
Name	None [15:12]				BR_COUNTER [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11 : 0	BR_COUNTER	Amount of peripheral clock periods that constitute the transmission of a 0x55 data frame (sent least significant bit first) as determined by the receiver. BR_COUNTER / 8 is the amount of peripheral clock periods that constitute a bit period. This field has valid data when IN-TR_RX.BAUD_DETECT is set to '1'. Default Value: Undefined

18.1.167 SCB2_UART_FLOW_CTRL

UART flow control register

Address: 0x400A0050

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							RTS_POLARITY

Bits	31	30	29	28	27	26	25	24
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [31:26]						CTS_ENABLED	CTS_POLARITY

Bits	Name	Description
25	CTS_ENABLED	Enable use of CTS input signal by the UART transmitter: '0': Disabled. The UART transmitter ignores the CTS input signal and transmits when a data frame is available for transmission in the TX FIFO or the TX shift register. '1': Enabled. The UART transmitter uses CTS input signal to qualify the transmission of data. It transmits when CTS input signal is active and a data frame is available for transmission in the TX FIFO or the TX shift register. If UART_CTRL.LOOPBACK is '1', the CTS input signal is driven by the RTS output signal locally in SCB (both signals are subjected to signal polarity changes are indicated by RTS_POLARITY and CTS_POLARITY). Default Value: 0
24	CTS_POLARITY	Polarity of the CTS input signal '0': CTS is active low ; '1': CTS is active high; Default Value: 0

18.1.167 SCB2_UART_FLOW_CTRL (continued)

16	RTS_POLARITY	Polarity of the RTS output signal: '0': RTS is active low; '1': RTS is active high; During SCB reset (Hibernate system power mode), RTS output signal is '1'. This represents an inactive state assuming an active low polarity. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has less entries than the amount of this field, a Ready To Send (RTS) output signal is activated. By setting this field to "0", flow control is effectively disabled (may be useful for debug purposes). Default Value: 0

18.1.168 SCB2_I2C_CTRL

I2C control register.

Address: 0x400A0060

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	LOW_PHASE_OVS [7:4]				HIGH_PHASE_OVS [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	RW	RW	RW	RW	RW	None	RW	RW
HW Access	R	R	R	R	R	None	R	R
Name	S_NOT_READY_DATA_NACK	S_NOT_READY_ADDR_NACK	S_READY_DATA_ACK	S_READY_ADDR_ACK	S_GENERAL_IGNORE	None	M_NOT_READY_DATA_NACK	M_READY_DATA_ACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							LOOPBACK

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	MASTER_MODE	SLAVE_MODE	None [29:24]					

Bits	Name	Description
31	MASTER_MODE	Master mode enabled ('1') or not ('0'). Note that both master and slave modes can be enabled at the same time. This allows the IP to address itself. Default Value: 0
30	SLAVE_MODE	Slave mode enabled ('1') or not ('0'). Default Value: 0
16	LOOPBACK	Local loopback control (does NOT affect the information on the pins). Only applicable in master/slave mode. When '0', no loopback When '1', loopback is enabled internally in the peripheral, and as a result unaffected by other I2C devices. This allows a SCB I2C peripheral to address itself. Default Value: 0

18.1.168 SCB2_I2C_CTRL (continued)

15	S_NOT_READY_DATA_NACK	Only used when: - non EZ mode Functionality is as follows: - 1: a received data element by the slave is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). Default Value: 1
14	S_NOT_READY_ADDR_NACK	This field is used during an address match or general call address in internally clocked mode Only used when: - EC_AM_MODE is '0', EC_OP_MODE is '0', S_GENERAL_IGNORE is '0' and non EZ mode. Functionality is as follows: - 1: a received (matching) slave address is immediately NACK'd when the receiver FIFO is full. - 0: clock stretching is performed (till the receiver FIFO is no longer full). For externally clocked logic (EC_AM is '1') on an address match or general call address (and S_GENERAL_IGNORE is '0'). Only used when (NOT used when EC_AM is '1' and EC_OP is '1' and address match and EZ mode): - EC_AM is '1' and EC_OP is '0'. - EC_AM is '1' and general call address match. - EC_AM is '1' and non EZ mode. Functionality is as follows: - 1: a received (matching or general) slave address is always immediately NACK'd. There are two possibilities: 1). the SCB clock is available (in Active system power mode) and it handles the rest of the current transfer. In this case the I2C master will not observe the NACK. 2). SCB clock is not present (in DeepSleep system power mode). In this case the I2C master will observe the NACK and may retry the transfer in the future (which gives the internally clocked logic the time to wake up from DeepSleep system power mode). - 0: clock stretching is performed (till the SCB clock is available). The logic will handle the ongoing transfer as soon as the clock is enabled. Default Value: 1
13	S_READY_DATA_ACK	When '1', a received data element by the slave is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
12	S_READY_ADDR_ACK	When '1', a received (matching) slave address is immediately ACK'd when the receiver FIFO is not full. In EZ mode, this field should be set to '1'. Default Value: 1
11	S_GENERAL_IGNORE	When '1', a received general call slave address is immediately NACK'd (no ACK or clock stretching) and treated as a non matching slave address. This is useful for slaves that do not need any data supplied within the general call structure. Default Value: 1
9	M_NOT_READY_DATA_NACK	When '1', a received data element byte the master is immediately NACK'd when the receiver FIFO is full. When '0', clock stretching is used instead (till the receiver FIFO is no longer full). Default Value: 1
8	M_READY_DATA_ACK	When '1', a received data element by the master is immediately ACK'd when the receiver FIFO is not full. Default Value: 1

18.1.168 SCB2_I2C_CTRL (continued)

7 : 4	LOW_PHASE_OVS	Serial I2C interface low phase oversampling factor. LOW_PHASE_OVS + 1 SCB clock periods constitute the low phase of a bit period. The valid range is [7, 15] with input signal median filtering and [6, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the regular (no stretching) interface (IF) low time to guarantee functionally correct behavior. With input signal median filtering, the IF low time should be ≥ 8 SCB clock cycles and ≤ 16 IP clock cycles. Without input signal median filtering, the IF low time should be ≥ 7 SCB clock cycles and ≤ 16 SCB clock cycles. Default Value: 8
3 : 0	HIGH_PHASE_OVS	Serial I2C interface high phase oversampling factor. HIGH_PHASE_OVS + 1 SCB clock periods constitute the high phase of a bit period. The valid range is [5, 15] with input signal median filtering and [4, 15] without input signal median filtering. The field is only used in master mode. In slave mode, the field is NOT used. However, there is a frequency requirement for the SCB clock wrt. the regular interface (IF) high time to guarantee functional correct behavior. With input signal median filtering, the IF high time should be ≥ 6 SCB clock cycles and ≤ 16 SCB clock cycles. Without input signal median filtering, the IF high time should be ≥ 5 SCB clock cycles and ≤ 16 SCB clock cycles. Default Value: 8

18.1.169 SCB2_I2C_STATUS

I2C status register.

Address: 0x400A0064

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	None		R	R
HW Access	None		W	W	None		W	W
Name	None [7:6]		M_READ	S_READ	None [3:2]		I2C_EC_BUSY	BUS_BUSY

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	CURR_EZ_ADDR [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	W							
Name	BASE_EZ_ADDR [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	BASE_EZ_ADDR	I2C slave base EZ address. Address as provided by an I2C write transfer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable, as clock domain synchronization is not performed in the design. Default Value: Undefined
15 : 8	CURR_EZ_ADDR	I2C slave current EZ address. Current address pointer. This field is only reliable in internally clocked mode. In externally clocked mode the field may be unreliable (during an ongoing transfer when I2C_EC_BUSY is '1'), as clock domain synchronization is not performed in the design. Default Value: Undefined
5	M_READ	I2C master read transfer ('1') or I2C master write transfer ('0'). When the I2C master is inactive/ idle or transmitting START, REPEATED START, STOP or an address, this field is '0'. Default Value: 0
4	S_READ	I2C slave read transfer ('1') or I2C slave write transfer ('0'). When the I2C slave is inactive/idle or receiving START, REPEATED START, STOP or an address, this field is '0'. Default Value: 0

18.1.169 SCB2_I2C_STATUS (continued)

1	I2C_EC_BUSY	Indicates whether the externally clocked logic is potentially accessing the EZ memory and/or updating BASE_ADDR or CURR_ADDR (this is only possible in EZ mode). This bit can be used by SW to determine whether BASE_ADDR and CURR_ADDR are reliable. Default Value: Undefined
0	BUS_BUSY	I2C bus is busy. The bus is considered busy ('1'), from the time a START is detected or from the time the SCL line is '0'. The bus is considered idle ('0'), from the time a STOP is detected. If SCB block is disabled, BUS_BUSY is '0'. After enabling the block, it takes time for the BUS_BUSY to detect a busy bus. This time is the maximum high time of the SCL line. For a 100 kHz interface frequency, this maximum high time may last roughly 5 us (half a bit period). For single master systems, BUS_BUSY does not have to be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START (no bus collisions). For multi-master systems, BUS_BUSY can be used to detect an idle bus before a master starts a transfer using I2C_M_CMD.M_START_ON_IDLE (to prevent bus collisions). Default Value: 0

18.1.170 SCB2_I2C_M_CMD

I2C master command register.

Address: 0x400A0068

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	RW	RW	RW	RW
HW Access	None			RW1C	RW1C	RW1C	RW1C	RW1C
Name	None [7:5]			M_STOP	M_NACK	M_ACK	M_START_ON_IDLE	M_START

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	M_STOP	When '1', attempt to transmit a STOP. When this action is performed, the hardware sets this field to '0'. This command has a higher priority than I2C_M_CMD.M_START: in situations where both a STOP and a REPEATED START could be transmitted, M_STOP takes precedence over M_START. Default Value: 0
3	M_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
2	M_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. Default Value: 0
1	M_START_ON_IDLE	When '1', transmit a START as soon as the bus is idle (I2C_STATUS.BUS_BUSY is '0', note that BUSY has a default value of '0'). For bus idle detection the hardware relies on STOP detection. As a result, bus idle detection is only functional after at least one I2C bus transfer has been detected on the bus (default/reset value of BUSY is '0'). A START is only transmitted when the master state machine is in the default state. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.170 SCB2_I2C_M_CMD (continued)

0	M_START	When '1', transmit a START or REPEATED START. Whether a START or REPEATED START is transmitted depends on the state of the master state machine. A START is only transmitted when the master state machine is in the default state. A REPEATED START is transmitted when the master state machine is not in the default state, but is working on an ongoing transaction. The REPEATED START can only be transmitted after a NACK or ACK has been received for a transmitted data element or after a NACK has been transmitted for a received data element. When this action is performed, the hardware sets this field to '0'. Default Value: 0

18.1.171 SCB2_I2C_S_CMD

I2C slave command register.

Address: 0x400A006C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						RW1C	RW1C
Name	None [7:2]						S_NACK	S_ACK

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	S_NACK	When '1', attempt to transmit a negative acknowledgement (NACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). This command has a higher priority than I2C_S_CMD.S_ACK, I2C_CTRL.S_READY_ADDR_ACK or I2C_CTRL.S_READY_DATA_ACK. Default Value: 0
0	S_ACK	When '1', attempt to transmit an acknowledgement (ACK). When this action is performed, the hardware sets this field to '0'. In EZ mode, this field should be set to '0' (it is only to be used in non EZ mode). Default Value: 0

18.1.172 SCB2_I2C_CFG

I2C configuration register.

Address: 0x400A0070

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [7:5]			SDA_IN_FILT_SEL	None [3:2]		SDA_IN_FILT_TRIM [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None			RW	None		RW	
HW Access	None			R	None		R	
Name	None [15:13]			SCL_IN_FILT_SEL	None [11:10]		SCL_IN_FILT_TRIM [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None		RW		RW		RW	
HW Access	None		R		R		R	
Name	None [23:22]		SDA_OUT_FILT2_TRIM [21:20]		SDA_OUT_FILT1_TRIM [19:18]		SDA_OUT_FILT0_TRIM [17:16]	

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW		None			
HW Access	None		R		None			
Name	None [31:30]		SDA_OUT_FILT_SEL [29:28]		None [27:24]			

Bits	Name	Description
29 : 28	SDA_OUT_FILT_SEL	Selection of cumulative filter delay on SDA output to meet tHD_DAT parameter "0": 0 ns. "1": 50 ns (filter 0 enabled). "2": 100 ns (filters 0 and 1 enabled). "3": 150 ns (filters 0, 1 and 2 enabled). Default Value: 0
21 : 20	SDA_OUT_FILT2_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2
19 : 18	SDA_OUT_FILT1_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2
17 : 16	SDA_OUT_FILT0_TRIM	Trim settings for the 50ns delay filter on SDA output used to guarantee tHD_DAT I2C parameter. Default setting meets the I2C spec. Programmability available if required Default Value: 2

18.1.172 SCB2_I2C_CFG (continued)

12	SCL_IN_FILT_SEL	Enable for 50ns glitch filter on SCL input '0': 0 ns. '1': 50 ns (filter enabled). Default Value: 1
9 : 8	SCL_IN_FILT_TRIM	Trim settings for the 50ns glitch filter on the SDA input. Default setting meets the I2C glitch rejections specs. Programmability available if required Default Value: 0
4	SDA_IN_FILT_SEL	Enable for 50ns glitch filter on SDA input '0': 0 ns. '1': 50 ns (filter enabled). Default Value: 1
1 : 0	SDA_IN_FILT_TRIM	Trim settings for the 50ns glitch filter on the SDA input. Default setting meets the I2C glitch rejections specs. Programmability available if required Default Value: 3

18.1.173 SCB2_TX_CTRL

Transmitter control register.

Address: 0x400A0200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							RW
HW Access	None							R
Name	None [15:9]							MSB_ - FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the amount of bits in a transmitted data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. Default Value: 7

18.1.174 SCB2_TX_FIFO_CTRL

Transmitter FIFO control register.

Address: 0x400A0204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware reads from the transmitter FIFO do not remove FIFO entries. Freeze will not advance the TX FIFO read pointer. Default Value: 0
16	CLEAR	When '1', the transmitter FIFO and transmitter shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the transmitter FIFO has less entries than the number of this field, a transmitter trigger event is generated. Default Value: 0

18.1.175 SCB2_TX_FIFO_STATUS

Transmitter FIFO status register.

Address: 0x400A0208

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			USED [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read by the hardware. Default Value: 0
15	SR_VALID	Indicates whether the TX shift registers holds a valid data frame ('1') or not ('0'). The shift register can be considered the top of the TX FIFO (the data frame is not included in the USED field of the TX FIFO). The shift register is a working register and holds the data frame that is currently transmitted (when the protocol state machine is transmitting a data frame) or the data frame that is transmitted next (when the protocol state machine is not transmitting a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the transmitter FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

18.1.176 SCB2_TX_FIFO_WR

Transmitter FIFO write register.

Address: 0x400A0240

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	W							
HW Access	R							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	W							
HW Access	R							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data frame written into the transmitter FIFO. Behavior is similar to that of a PUSH operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A write to a full TX FIFO sets INTR_TX.OVERFLOW to '1'. Default Value: 0

18.1.177 SCB2_RX_CTRL

Receiver control register.

Address: 0x400A0300

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				DATA_WIDTH [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						MEDIAN	MSB_ - FIRST

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	MEDIAN	Median filter. When '1', a digital 3 taps median filter is performed on input interface lines. This filter should reduce the susceptibility to errors. However, it requires higher oversampling values. For UART IrDA submode, this field should always be '1'. Default Value: 0
8	MSB_FIRST	Least significant bit first ('0') or most significant bit first ('1'). For I2C, this field should be '1'. Default Value: 1
3 : 0	DATA_WIDTH	Dataframe width. DATA_WIDTH + 1 is the expected amount of bits in received data frame. This number does not include start, parity and stop bits. For UART mode, the valid range is [3, 8]. For SPI, the valid range is [3, 15]. For I2C the only valid value is 7. In EZ mode (for both SPI and I2C), the only valid value is 7. Default Value: 7

18.1.178 SCB2_RX_FIFO_CTRL

Receiver FIFO control register.

Address: 0x400A0304

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW			
HW Access	None				R			
Name	None [7:4]				TRIGGER_LEVEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [23:18]						FREEZE	CLEAR

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
17	FREEZE	When '1', hardware writes to the receiver FIFO have no effect. Freeze will not advance the RX FIFO write pointer. Default Value: 0
16	CLEAR	When '1', the receiver FIFO and receiver shift register are cleared/invalidated. Invalidation will last for as long as this field is '1'. If a quick clear/invalidation is required, the field should be set to '1' and be followed by a set to '0'. If a clear/invalidation is required for an extended time period, the field should be set to '1' during the complete time period. Default Value: 0
3 : 0	TRIGGER_LEVEL	Trigger level. When the receiver FIFO has more entries than the number of this field, a receiver trigger event is generated. Default Value: 0

18.1.179 SCB2_RX_FIFO_STATUS

Receiver FIFO status register.

Address: 0x400A0308

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			USED [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	R	None						
HW Access	W	None						
Name	SR_VALID	None [14:8]						

Bits	23	22	21	20	19	18	17	16
SW Access	None				R			
HW Access	None				W			
Name	None [23:20]				RD_PTR [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None				R			
HW Access	None				W			
Name	None [31:28]				WR_PTR [27:24]			

Bits	Name	Description
27 : 24	WR_PTR	FIFO write pointer: FIFO location at which a new data frame is written by the hardware. Default Value: 0
19 : 16	RD_PTR	FIFO read pointer: FIFO location from which a data frame is read. Default Value: 0
15	SR_VALID	Indicates whether the RX shift registers holds a (partial) valid data frame ('1') or not ('0'). The shift register can be considered the bottom of the RX FIFO (the data frame is not included in the USED field of the RX FIFO). The shift register is a working register and holds the data frame that is currently being received (when the protocol state machine is receiving a data frame). Default Value: 0
4 : 0	USED	Amount of enties in the receiver FIFO. The value of this field ranges from 0 to FF_DATA_NR. Default Value: 0

18.1.180 SCB2_RX_MATCH

Slave address and mask register.

Address: 0x400A0310

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	ADDR [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	MASK [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23 : 16	MASK	Slave device address mask. This field is a mask that specifies which of the slave address bits take part in the matching. $MATCH = ((ADDR \& MASK) == ("slave\ address" \& MASK))$. Default Value: 0
7 : 0	ADDR	Slave device address. In UART multi-processor mode, all 8 bits are used. In I2C slave mode, only bits 7 down to 1 are used. This reflects the organization of the first transmitted byte in a I2C transfer: the first 7 bits represent the address of the addressed slave, and the last 1 bit is a read/write indicator ('0': write, '1': read). Default Value: 0

18.1.181 SCB2_RX_FIFO_RD

Receiver FIFO read register.

Address: 0x400A0340

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will remove the data frame from the FIFO; i.e. behavior is similar to that of a POP operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. When this register is read through the debugger, the data frame will not be removed from the FIFO. Similar in operation to RX_FIFO_RD_SILENT Default Value: Undefined

18.1.182 SCB2_RX_FIFO_RD_SILENT

Receiver FIFO read register.

Address: 0x400A0344

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	W							
Name	DATA [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	DATA	Data read from the receiver FIFO. Reading a data frame will NOT remove the data frame from the FIFO; i.e. behavior is similar to that of a PEEK operation. Note that when CTRL.BYTE_MODE is '1', only DATA[7:0] are used. A read from an empty RX FIFO sets INTR_RX.UNDERFLOW to '1'. Default Value: Undefined

18.1.183 SCB2_EZ_DATA0

Memory buffer registers.

Address: 0x400A0400

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.184 SCB2_EZ_DATA1

Memory buffer registers.

Address: 0x400A0404

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.185 SCB2_EZ_DATA2

Memory buffer registers.

Address: 0x400A0408

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.186 SCB2_EZ_DATA3

Memory buffer registers.

Address: 0x400A040C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.187 SCB2_EZ_DATA4

Memory buffer registers.

Address: 0x400A0410

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.188 SCB2_EZ_DATA5

Memory buffer registers.

Address: 0x400A0414

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.189 SCB2_EZ_DATA6

Memory buffer registers.

Address: 0x400A0418

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.190 SCB2_EZ_DATA7

Memory buffer registers.

Address: 0x400A041C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.191 SCB2_EZ_DATA8

Memory buffer registers.

Address: 0x400A0420

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.192 SCB2_EZ_DATA9

Memory buffer registers.

Address: 0x400A0424

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.193 SCB2_EZ_DATA10

Memory buffer registers.

Address: 0x400A0428

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.194 SCB2_EZ_DATA11

Memory buffer registers.

Address: 0x400A042C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.195 SCB2_EZ_DATA12

Memory buffer registers.

Address: 0x400A0430

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.196 SCB2_EZ_DATA13

Memory buffer registers.

Address: 0x400A0434

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.197 SCB2_EZ_DATA14

Memory buffer registers.

Address: 0x400A0438

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.198 SCB2_EZ_DATA15

Memory buffer registers.

Address: 0x400A043C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							
Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							
Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.199 SCB2_EZ_DATA16

Memory buffer registers.

Address: 0x400A0440

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.200 SCB2_EZ_DATA17

Memory buffer registers.

Address: 0x400A0444

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.201 SCB2_EZ_DATA18

Memory buffer registers.

Address: 0x400A0448

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.202 SCB2_EZ_DATA19

Memory buffer registers.

Address: 0x400A044C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.203 SCB2_EZ_DATA20

Memory buffer registers.

Address: 0x400A0450

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.204 SCB2_EZ_DATA21

Memory buffer registers.

Address: 0x400A0454

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.205 SCB2_EZ_DATA22

Memory buffer registers.

Address: 0x400A0458

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.206 SCB2_EZ_DATA23

Memory buffer registers.

Address: 0x400A045C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.207 SCB2_EZ_DATA24

Memory buffer registers.

Address: 0x400A0460

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.208 SCB2_EZ_DATA25

Memory buffer registers.

Address: 0x400A0464

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.209 SCB2_EZ_DATA26

Memory buffer registers.

Address: 0x400A0468

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.210 SCB2_EZ_DATA27

Memory buffer registers.

Address: 0x400A046C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.211 SCB2_EZ_DATA28

Memory buffer registers.

Address: 0x400A0470

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.212 SCB2_EZ_DATA29

Memory buffer registers.

Address: 0x400A0474

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.213 SCB2_EZ_DATA30

Memory buffer registers.

Address: 0x400A0478

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.214 SCB2_EZ_DATA31

Memory buffer registers.

Address: 0x400A047C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	EZ_DATA [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	EZ_DATA	Data in buffer memory location. In case of a blocked discarded access, a read access returns 0xffff:ffff and a write access is dropped. Note that the 0xffff:ffff value is unique (not a legal EZ_DATA byte value) and can be detected by SW. Note that a discarded write access can be detected by reading back the written value. Default Value: Undefined

18.1.215 SCB2_INTR_CAUSE

Active clocked interrupt signal register

Address: 0x400A0E00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R	R	R	R
HW Access	None		W	W	W	W	W	W
Name	None [7:6]		SPI_EC	I2C_EC	RX	TX	S	M

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5	SPI_EC	Externally clocked SPI interrupt active ("interrupt_spi_ec"): INTR_SPI_EC_MASKED != 0. Default Value: 0
4	I2C_EC	Externally clock I2C interrupt active ("interrupt_i2c_ec"): INTR_I2C_EC_MASKED != 0. Default Value: 0
3	RX	Receiver interrupt active ("interrupt_rx"): INTR_RX_MASKED != 0. Default Value: 0
2	TX	Transmitter interrupt active ("interrupt_tx"): INTR_TX_MASKED != 0. Default Value: 0
1	S	Slave interrupt active ("interrupt_slave"): INTR_S_MASKED != 0. Default Value: 0
0	M	Master interrupt active ("interrupt_master"): INTR_M_MASKED != 0. Default Value: 0

18.1.216 SCB2_INTR_I2C_EC

Externally clocked I2C interrupt request register

Address: 0x400A0E80

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (I2C STOP). This event is an indication that a buffer memory location has been read from. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (I2C STOP). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (I2C STOP). Only available for a slave request with an address match, in EZ and CMD_RESP modes, when CTRL.EC_OP_MODE is '1'. Default Value: 0

18.1.216 SCB2_INTR_I2C_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request (with address match). Only used when CTRL.EC_AM_MODE is '1'. Default Value: 0

18.1.217 SCB2_INTR_I2C_EC_MASK

Externally clocked I2C interrupt mask register

Address: 0x400A0E88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.218 SCB2_INTR_I2C_EC_MASKED

Externally clocked I2C interrupt masked register

Address: 0x400A0E8C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.219 SCB2_INTR_SPI_EC

Externally clocked SPI interrupt request register

Address: 0x400A0EC0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				A	A	A	A
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	STOP detection after a read transfer occurred. Activated on the end of a read transfer (SPI deselection). This event is an indication that a buffer memory location has been read from. Only used in EZ and CMD_RESP modes and when CTRL.EC_OP_MODE is '1'. Default Value: 0
2	EZ_WRITE_STOP	STOP detection after a write transfer occurred. Activated on the end of a write transfer (SPI deselection). This event is an indication that a buffer memory location has been written to. For EZ mode: a transfer that only writes the base address does NOT activate this event. Only used in EZ and CMD_RESP modes and when CTRL.EC_OP_MODE is '1'. Default Value: 0
1	EZ_STOP	STOP detection. Activated on the end of a every transfer (SPI deselection). Only available in EZ and CMD_RESP mode and when CTRL.EC_OP_MODE is '1'. Default Value: 0

18.1.219 SCB2_INTR_SPI_EC (continued)

0	WAKE_UP	Wake up request. Active on incoming slave request when externally clocked selection is '1'. Only used when CTRL.EC_AM_MODE is '1'. Default Value: 0

18.1.220 SCB2_INTR_SPI_EC_MASK

Externally clocked SPI interrupt mask register

Address: 0x400A0EC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	WAKE_UP	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.221 SCB2_INTR_SPI_EC_MASKED

Externally clocked SPI interrupt masked register

Address: 0x400A0ECC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [7:4]				EZ_READ_STOP	EZ_WRITE_STOP	EZ_STOP	WAKE_UP

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
3	EZ_READ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
1	EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
0	WAKE_UP	Logical and of corresponding request and mask bits. Default Value: 0

18.1.222 SCB2_INTR_M

Master interrupt request register.

Address: 0x400A0F00

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	None	RW1C	RW1C	RW1C
HW Access	None			RW1S	None	RW1S	RW1S	RW1S
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1C	RW1C
HW Access	None						RW1S	RW1S
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	SPI master transfer done event: all data frames in the transmit FIFO are sent and the transmit FIFO is empty. Default Value: 0
8	I2C_BUS_ERROR	I2C master bus error (unexpected detection of START or STOP condition). Default Value: 0
4	I2C_STOP	I2C master STOP. Set to '1', when the master has transmitted a STOP. Default Value: 0
2	I2C_ACK	I2C master acknowledgement. Set to '1', when the master receives a ACK (typically after the master transmitted the slave address or TX data). Default Value: 0
1	I2C_NACK	I2C master negative acknowledgement. Set to '1', when the master receives a NACK (typically after the master transmitted the slave address or TX data). Default Value: 0
0	I2C_ARB_LOST	I2C master lost arbitration: the value driven by the master on the SDA line is not the same as the value observed on the SDA line. Default Value: 0

18.1.223 SCB2_INTR_M_SET

Master interrupt set request register

Address: 0x400A0F04

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S	None	RW1S	RW1S	RW1S
HW Access	None			A	None	A	A	A
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW1S	RW1S
HW Access	None						A	A
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.224 SCB2_INTR_M_MASK

Master interrupt mask register.

Address: 0x400A0F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW	None	RW	RW	RW
HW Access	None			R	None	R	R	R
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.225 SCB2_INTR_M_MASKED

Master interrupt masked request register

Address: 0x400A0F0C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R	None	R	R	R
HW Access	None			W	None	W	W	W
Name	None [7:5]			I2C_STOP	None	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None						R	R
HW Access	None						W	W
Name	None [15:10]						SPI_DONE	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9	SPI_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.226 SCB2_INTR_S

Slave interrupt request register.

Address: 0x400A0F40

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
Name	I2C_GEN- ERAL	I2C_AD- DR_MATCH	I2C_START	I2C_STOP	I2C_WRITE _STOP	I2C_ACK	I2C_NACK	I2C_AR- B_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				SPI_BUS_E RROR	SPI_EZ_ST OP	SPI_EZ_W RITE_STOP	I2C_BUS_E RROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	SPI slave deselected at an unexpected time in the SPI transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0
10	SPI_EZ_STOP	SPI slave deselected after any EZ SPI transfer occurred. Default Value: 0
9	SPI_EZ_WRITE_STOP	SPI slave deselected after a write EZ SPI transfer occurred. Default Value: 0
8	I2C_BUS_ERROR	I2C slave bus error (unexpected detection of START or STOP condition). This should not occur, it represents erroneous I2C bus behavior. In case of a bus error, the I2C slave state machine abort the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.226 SCB2_INTR_S (continued)

7	I2C_GENERAL	I2C slave general call address received. If CTRL.ADDR_ACCEPT, the received address 0x00 (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
6	I2C_ADDR_MATCH	I2C slave matching address received. If CTRL.ADDR_ACCEPT, the received address (including the R/W bit) is available in the RX FIFO. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') and internally clocked operation (CTRL.EC_OP_MODE is '0'), this field is set when the event is detected. Default Value: 0
5	I2C_START	I2C slave START received. Set to '1', when START or REPEATED START event is detected. In the case of externally clocked address matching (CTRL.EC_AM_MODE is '1') AND clock stretching is performed (I2C_CTRL.S_NOT_READY_ADDR_NACK is '0'), this field is NOT set. The Firmware should use INTR_S_EC.WAKE_UP, INTR_S.I2C_ADDR_MATCH and INTR_S.I2C_GENERAL. Default Value: 0
4	I2C_STOP	I2C STOP event for I2C (read or write) transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. The event is detected on any I2C transfer intended for this slave. Note that a I2C address intended for the slave (address is matching) will result in a I2C_STOP event independent of whether the I2C address is ACK'd or NACK'd. Default Value: 0
3	I2C_WRITE_STOP	I2C STOP event for I2C write transfer intended for this slave (address matching is performed). Set to '1', when STOP or REPEATED START event is detected. The REPEATED START event is included in this interrupt cause such that the I2C transfers separated by a REPEATED START can be distinguished and potentially treated separately by the Firmware. Note that the second I2C transfer (after a REPEATED START) may be to a different slave address. In non EZ mode, the event is detected on any I2C write transfer intended for this slave. Note that a I2C write address intended for the slave (address is matching and a it is a write transfer) will result in a I2C_WRITE_STOP event independent of whether the I2C address is ACK'd or NACK'd. In EZ mode, the event is detected only on I2C write transfers that have EZ data written to the memory structure (an I2C write transfer that only communicates an I2C address and EZ address, will not result in this event being detected). Default Value: 0
2	I2C_ACK	I2C slave acknowledgement received. Set to '1', when the slave receives a ACK (typically after the slave transmitted TX data). Default Value: 0
1	I2C_NACK	I2C slave negative acknowledgement received. Set to '1', when the slave receives a NACK (typically after the slave transmitted TX data). Default Value: 0
0	I2C_ARB_LOST	I2C slave lost arbitration: the value driven on the SDA line is not the same as the value observed on the SDA line (while the SCL line is '1'). This should not occur, it represents erroneous I2C bus behavior. In case of lost arbitration, the I2C slave state machine aborts the ongoing transfer. The Firmware may decide to clear the TX and RX FIFOs in case of this error. Default Value: 0

18.1.227 SCB2_INTR_S_SET

Slave interrupt set request register.

Address: 0x400A0F44

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S	RW1S
HW Access	A	A	A	A	A	A	A	A
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.227 SCB2_INTR_S_SET (continued)

4	I2C_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.228 SCB2_INTR_S_MASK

Slave interrupt mask register.

Address: 0x400A0F48

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	RW	RW	RW	RW
HW Access	R	R	R	R	R	R	R	R
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	SPI_EZ_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	SPI_EZ_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	I2C_BUS_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	I2C_GENERAL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	I2C_ADDR_MATCH	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	I2C_START	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.228 SCB2_INTR_S_MASK (continued)

4	I2C_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
3	I2C_WRITE_STOP	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	I2C_ACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
1	I2C_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	I2C_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.229 SCB2_INTR_S_MASKED

Slave interrupt masked request register

Address: 0x400A0F4C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	R	R	R	R
HW Access	W	W	W	W	W	W	W	W
Name	I2C_GENERAL	I2C_ADDR_MATCH	I2C_START	I2C_STOP	I2C_WRITE_STOP	I2C_ACK	I2C_NACK	I2C_ARB_LOST

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				SPI_BUS_ERROR	SPI_EZ_STOP	SPI_EZ_WRITE_STOP	I2C_BUS_ERROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	SPI_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
10	SPI_EZ_STOP	Logical and of corresponding request and mask bits. Default Value: 0
9	SPI_EZ_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
8	I2C_BUS_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	I2C_GENERAL	Logical and of corresponding request and mask bits. Default Value: 0
6	I2C_ADDR_MATCH	Logical and of corresponding request and mask bits. Default Value: 0
5	I2C_START	Logical and of corresponding request and mask bits. Default Value: 0

18.1.229 SCB2_INTR_S_MASKED (continued)

4	I2C_STOP	Logical and of corresponding request and mask bits. Default Value: 0
3	I2C_WRITE_STOP	Logical and of corresponding request and mask bits. Default Value: 0
2	I2C_ACK	Logical and of corresponding request and mask bits. Default Value: 0
1	I2C_NACK	Logical and of corresponding request and mask bits. Default Value: 0
0	I2C_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0

18.1.230 SCB2_INTR_TX

Transmitter interrupt request register.

Address: 0x400A0F80

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	RW1C	None		RW1C	RW1C
HW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1C	RW1C	RW1C
HW Access	None					RW1S	RW1S	RW1S
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	UART lost arbitration: the value driven on the TX line is not the same as the value observed on the RX line. This condition event is usefull when transmitter and receiver share a TX/RX line. This is the case in LIN or SmartCard modes. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
9	UART_DONE	UART transmitter done event. This happens when the IP is done transferring all data in the TX FIFO; i.e. EMPTY is '1'. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
8	UART_NACK	UART transmitter received a negative acknowledgement in SmartCard mode. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
7	BLOCKED	SW cannot get access to the EZ memory (EZ data access), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0

18.1.230 SCB2_INTR_TX (continued)

6	UNDERFLOW	Attempt to read from an empty TX FIFO. This happens when SCB is ready to transfer data and EMPTY is '1'. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full TX FIFO. Only used in FIFO mode. Default Value: 0
4	EMPTY	TX FIFO is empty; i.e. it has 0 entries. Only used in FIFO mode. Default Value: 0
1	NOT_FULL	TX FIFO is not full. Dependent on CTRL.BYTE_MODE: BYTE_MODE is '0': # entries != FF_DATA_NR/2. BYTE_MODE is '1': # entries != FF_DATA_NR. Only used in FIFO mode. Default Value: 0
0	TRIGGER	Less entries in the TX FIFO than the value specified by TX_FIFO_CTRL. Only used in FIFO mode. Default Value: 0

18.1.231 SCB2_INTR_TX_SET

Transmitter interrupt set request register

Address: 0x400A0F84

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	RW1S	None		RW1S	RW1S
HW Access	A	A	A	A	None		A	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW1S	RW1S	RW1S
HW Access	None					A	A	A
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.231 SCB2_INTR_TX_SET (continued)

1	NOT_FULL	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.232 SCB2_INTR_TX_MASK

Transmitter interrupt mask register.

Address: 0x400A0F88

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	RW	None		RW	RW
HW Access	R	R	R	R	None		R	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	UART_DONE	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	UART_NACK	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
4	EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.232 SCB2_INTR_TX_MASK (continued)

1	NOT_FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.233 SCB2_INTR_TX_MASKED

Transmitter interrupt masked request register

Address: 0x400A0F8C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	R	None		R	R
HW Access	W	W	W	W	None		W	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	EMPTY	None [3:2]		NOT_FULL	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None					R	R	R
HW Access	None					W	W	W
Name	None [15:11]					UART_ARB_LOST	UART_DONE	UART_NACK

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
10	UART_ARB_LOST	Logical and of corresponding request and mask bits. Default Value: 0
9	UART_DONE	Logical and of corresponding request and mask bits. Default Value: 0
8	UART_NACK	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
4	EMPTY	Logical and of corresponding request and mask bits. Default Value: 0

18.1.233 SCB2_INTR_TX_MASKED (continued)

1	NOT_FULL	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

18.1.234 SCB2_INTR_RX

Receiver interrupt request register.

Address: 0x400A0FC0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1C	RW1C	RW1C	None	RW1C	RW1C	None	RW1C
HW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1C	RW1C	RW1C	RW1C
HW Access	None				RW1S	RW1S	RW1S	RW1S
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Break detection is successful: the line is '0' for UART_RX_CTRL.BREAK_WIDTH + 1 bit period. Can occur at any time to address unanticipated break fields; i.e. "break-in-data" is supported. This feature is supported for the UART standard and LIN submodes. For the UART standard submodes, ongoing receipt of data frames is NOT affected; i.e. Firmware is expected to take the proper action. For the LIN submode, possible ongoing receipt of a data frame is stopped and the (partially) received data frame is dropped and baud rate detection is started. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0
10	BAUD_DETECT	LIN baudrate detection is completed. The receiver software uses the UART_RX_STATUS.BR_COUNTER value to set the right IP clock (from the programmable clock IP) to guarantee successful receipt of the first LIN data frame (Protected Identifier Field) after the synchronization byte. Set to '1', when event is detected. Write with '1' to clear bit. Default Value: 0

18.1.234 SCB2_INTR_RX (continued)

9	PARITY_ERROR	Parity error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '1', the received frame is dropped. If UART_RX_CTL.DROP_ON_PARITY_ERROR is '0', the received frame is send to the RX FIFO. In SmartCard submode, negatively acknowledged data frames generate a parity error. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO. Default Value: 0
8	FRAME_ERROR	Frame error in received data frame. Set to '1', when event is detected. Write with '1' to clear bit. This can be either a start or stop bit(s) error: Start bit error: after the detection of the beginning of a start bit period (RX line changes from '1' to '0'), the middle of the start bit period is sampled erroneously (RX line is '1'). Note: a start bit error is detected BEFORE a data frame is received. Stop bit error: the RX line is sampled as '0', but a '1' was expected. Note: a stop bit error may result in failure to receive successive data frame(s). Note: a stop bit error is detected AFTER a data frame is received. A stop bit error is detected after a data frame is received, and the UART_RX_CTL.DROP_ON_FRAME_ERROR field specifies whether the received frame is dropped or send to the RX FIFO. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '1', the received data frame is dropped. If UART_RX_CTL.DROP_ON_FRAME_ERROR is '0', the received data frame is send to the RX FIFO. Note that Firmware can only identify the erroneous data frame in the RX FIFO if it is fast enough to read the data frame before the hardware writes a next data frame into the RX FIFO; i.e. the RX FIFO does not have error flags to tag erroneous data frames. Default Value: 0
7	BLOCKED	SW cannot get access to the EZ memory (EZ_DATA accesses), due to an externally clocked EZ access. This may happen when STATUS.EC_BUSY is '1'. Default Value: 0
6	UNDERFLOW	Attempt to read from an empty RX FIFO. Only used in FIFO mode. Default Value: 0
5	OVERFLOW	Attempt to write to a full RX FIFO. Note: in I2C mode, the OVERFLOW is set when a data frame is received and the RX FIFO is full, independent of whether it is ACK'd or NACK'd. Only used in FIFO mode. Default Value: 0
3	FULL	RX FIFO is full. Note that received data frames are lost when the RX FIFO is full. Dependent on CTRL.BYTE_MODET: BYTE_MODE is '0': # entries == FF_DATA_NR/2. BYTE_MODE is '1': # entries == FF_DATA_NR. Only used in FIFO mode. Default Value: 0
2	NOT_EMPTY	RX FIFO is not empty. Only used in FIFO mode. Default Value: 0
0	TRIGGER	More entries in the RX FIFO than the value specified by TRIGGER_LEVEL in SCB_RX_FIFO_CTL. Only used in FIFO mode. Default Value: 0

18.1.235 SCB2_INTR_RX_SET

Receiver interrupt set request register.

Address: 0x400A0FC4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW1S	RW1S	RW1S	None	RW1S	RW1S	None	RW1S
HW Access	A	A	A	None	A	A	None	A
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1S	RW1S	RW1S
HW Access	None				A	A	A	A
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
10	BAUD_DETECT	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
9	PARITY_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
8	FRAME_ERROR	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
7	BLOCKED	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
6	UNDERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
5	OVERFLOW	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0

18.1.235 SCB2_INTR_RX_SET (continued)

3	FULL	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
2	NOT_EMPTY	Write with '1' to set corresponding bit in interrupt status register. Default Value: 0
0	TRIGGER	Write with '1' to set corresponding bit in interrupt request register. Default Value: 0

18.1.236 SCB2_INTR_RX_MASK

Receiver interrupt mask register.

Address: 0x400A0FC8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW	RW	RW	None	RW	RW	None	RW
HW Access	R	R	R	None	R	R	None	R
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	RW
HW Access	None				R	R	R	R
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER-ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
10	BAUD_DETECT	Mask bit for corresponding bit in interrupt request register. Default Value: 0
9	PARITY_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
8	FRAME_ERROR	Mask bit for corresponding bit in interrupt request register. Default Value: 0
7	BLOCKED	Mask bit for corresponding bit in interrupt request register. Default Value: 0
6	UNDERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0
5	OVERFLOW	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.236 SCB2_INTR_RX_MASK (continued)

3	FULL	Mask bit for corresponding bit in interrupt request register. Default Value: 0
2	NOT_EMPTY	Mask bit for corresponding bit in interrupt request register. Default Value: 0
0	TRIGGER	Mask bit for corresponding bit in interrupt request register. Default Value: 0

18.1.237 SCB2_INTR_RX_MASKED

Receiver interrupt masked request register

Address: 0x400A0FCC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R	R	R	None	R	R	None	R
HW Access	W	W	W	None	W	W	None	W
Name	BLOCKED	UNDER-FLOW	OVER-FLOW	None	FULL	NOT_EMP-TY	None	TRIGGER

Bits	15	14	13	12	11	10	9	8
SW Access	None				R	R	R	R
HW Access	None				W	W	W	W
Name	None [15:12]				BREAK - DETECT	BAUD_DE-TECT	PARI-TY_ERROR	FRAME_ER ROR

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
11	BREAK_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
10	BAUD_DETECT	Logical and of corresponding request and mask bits. Default Value: 0
9	PARITY_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
8	FRAME_ERROR	Logical and of corresponding request and mask bits. Default Value: 0
7	BLOCKED	Logical and of corresponding request and mask bits. Default Value: 0
6	UNDERFLOW	Logical and of corresponding request and mask bits. Default Value: 0
5	OVERFLOW	Logical and of corresponding request and mask bits. Default Value: 0

18.1.237 SCB2_INTR_RX_MASKED (continued)

3	FULL	Logical and of corresponding request and mask bits. Default Value: 0
2	NOT_EMPTY	Logical and of corresponding request and mask bits. Default Value: 0
0	TRIGGER	Logical and of corresponding request and mask bits. Default Value: 0

19 Supervisory Flash (SFLASH) Registers



This section discusses the SFLASH registers. It lists all the registers in mapping tables, in address order.

19.1 Register Details

Register Name	Address
SFLASH_SILICON_ID	0x0FFFF144
SFLASH_HIB_KEY_DELAY	0x0FFFF150
SFLASH_DPSLP_KEY_DELAY	0x0FFFF152
SFLASH_SWD_CONFIG	0x0FFFF154
SFLASH_SWD_LISTEN	0x0FFFF158
SFLASH_FLASH_START	0x0FFFF15C
SFLASH_CSDV2_CSD0_ADC_TRIM1	0x0FFFF160
SFLASH_CSDV2_CSD0_ADC_TRIM2	0x0FFFF161
SFLASH_SAR_TEMP_MULTIPLIER	0x0FFFF164
SFLASH_SAR_TEMP_OFFSET	0x0FFFF166
SFLASH_IMO_TCTRIM_LT0	0x0FFFF1CC
SFLASH_IMO_TCTRIM_LT1	0x0FFFF1CD
SFLASH_IMO_TCTRIM_LT2	0x0FFFF1CE
SFLASH_IMO_TCTRIM_LT3	0x0FFFF1CF
SFLASH_IMO_TCTRIM_LT4	0x0FFFF1D0
SFLASH_IMO_TCTRIM_LT5	0x0FFFF1D1
SFLASH_IMO_TCTRIM_LT6	0x0FFFF1D2
SFLASH_IMO_TCTRIM_LT7	0x0FFFF1D3
SFLASH_IMO_TCTRIM_LT8	0x0FFFF1D4
SFLASH_IMO_TCTRIM_LT9	0x0FFFF1D5
SFLASH_IMO_TCTRIM_LT10	0x0FFFF1D6
SFLASH_IMO_TCTRIM_LT11	0x0FFFF1D7
SFLASH_IMO_TCTRIM_LT12	0x0FFFF1D8
SFLASH_IMO_TCTRIM_LT13	0x0FFFF1D9
SFLASH_IMO_TCTRIM_LT14	0x0FFFF1DA
SFLASH_IMO_TCTRIM_LT15	0x0FFFF1DB
SFLASH_IMO_TCTRIM_LT16	0x0FFFF1DC

Register Name	Address
SFLASH_IMO_TCTRIM_LT17	0x0FFF1DD
SFLASH_IMO_TCTRIM_LT18	0x0FFF1DE
SFLASH_IMO_TCTRIM_LT19	0x0FFF1DF
SFLASH_IMO_TCTRIM_LT20	0x0FFF1E0
SFLASH_IMO_TCTRIM_LT21	0x0FFF1E1
SFLASH_IMO_TCTRIM_LT22	0x0FFF1E2
SFLASH_IMO_TCTRIM_LT23	0x0FFF1E3
SFLASH_IMO_TCTRIM_LT24	0x0FFF1E4
SFLASH_IMO_TRIM_LT0	0x0FFF1E5
SFLASH_IMO_TRIM_LT1	0x0FFF1E6
SFLASH_IMO_TRIM_LT2	0x0FFF1E7
SFLASH_IMO_TRIM_LT3	0x0FFF1E8
SFLASH_IMO_TRIM_LT4	0x0FFF1E9
SFLASH_IMO_TRIM_LT5	0x0FFF1EA
SFLASH_IMO_TRIM_LT6	0x0FFF1EB
SFLASH_IMO_TRIM_LT7	0x0FFF1EC
SFLASH_IMO_TRIM_LT8	0x0FFF1ED
SFLASH_IMO_TRIM_LT9	0x0FFF1EE
SFLASH_IMO_TRIM_LT10	0x0FFF1EF
SFLASH_IMO_TRIM_LT11	0x0FFF1F0
SFLASH_IMO_TRIM_LT12	0x0FFF1F1
SFLASH_IMO_TRIM_LT13	0x0FFF1F2
SFLASH_IMO_TRIM_LT14	0x0FFF1F3
SFLASH_IMO_TRIM_LT15	0x0FFF1F4
SFLASH_IMO_TRIM_LT16	0x0FFF1F5
SFLASH_IMO_TRIM_LT17	0x0FFF1F6
SFLASH_IMO_TRIM_LT18	0x0FFF1F7
SFLASH_IMO_TRIM_LT19	0x0FFF1F8
SFLASH_IMO_TRIM_LT20	0x0FFF1F9
SFLASH_IMO_TRIM_LT21	0x0FFF1FA
SFLASH_IMO_TRIM_LT22	0x0FFF1FB
SFLASH_IMO_TRIM_LT23	0x0FFF1FC
SFLASH_IMO_TRIM_LT24	0x0FFF1FD

19.1.1 SFLASH_SILICON_ID

Silicon ID

Address: 0x0FFFF144

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	ID [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	ID [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	ID	Silicon ID Default Value: X

19.1.2 SFLASH_HIB_KEY_DELAY

Hibernate wakeup value for PWR_KEY_DELAY

Address: 0x0FFFF150

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay (in 12MHz IMO clock cycles) to wait for references to settle on wakeup from hibernate/deepsleep. PBOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. Default Value: X

19.1.3 SFLASH_DPSLP_KEY_DELAY

DeepSleep wakeup value for PWR_KEY_DELAY

Address: 0x0FFFF152

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay (in 12MHz IMO clock cycles) to wait for references to settle on wakeup from hibernate/deepsleep. PBOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. Default Value: X

19.1.4 SFLASH_SWD_CONFIG

SWD pinout selector (not present in TSG4/TSG5-M)

Address: 0x0FFFF154

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							None
Name	None [7:1]							SWD_SELECT

Bits	Name	Description
0	SWD_SELECT	0: Use Primary SWD location 1: Use Alternate SWD location Default Value: X

19.1.5 SFLASH_SWD_LISTEN

Listen Window Length

Address: 0x0FFF158

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CYCLES [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	CYCLES [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	CYCLES [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	CYCLES [31:24]							

Bits	Name	Description
31 : 0	CYCLES	Number of clock cycles Default Value: X

19.1.6 SFLASH_FLASH_START

Flash Image Start Address

Address: 0x0FFFF15C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	ADDRESS [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	ADDRESS [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	None							
Name	ADDRESS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	None							
Name	ADDRESS [31:24]							

Bits	Name	Description
31 : 0	ADDRESS	Start Address Default Value: X

19.1.7 SFLASH_CSDV2_CSD0_ADC_TRIM1

CSDV2 CSD0 ADC TRIM 1

Address: 0x0FFF160

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CSD_ADC_CAL_LSB [7:0]							

Bits	Name	Description
7 : 0	CSD_ADC_CAL_LSB	Low byte of CSDv2 Calibration Default Value: X

19.1.8 SFLASH_CSDV2_CSD0_ADC_TRIM2

CSDV2 CSD0 ADC TRIM2

Address: 0x0FFFF161

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	CSD_ADC_CAL_MSB [7:0]							

Bits	Name	Description
7 : 0	CSD_ADC_CAL_MSB	High byte of CSDv2 Calibration Default Value: X

19.1.9 SFLASH_SAR_TEMP_MULTIPLIER

SAR Temperature Sensor Multiplication Factor

Address: 0x0FFFF164

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TEMP_MULTIPLIER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	TEMP_MULTIPLIER [15:8]							

Bits	Name	Description
15 : 0	TEMP_MULTIPLIER	Multiplier value for SAR temperature sensor in fixed point 0.16 format. Note: this field exists in products that contain SAR (m0s8sar) only. Default Value: X

19.1.10 SFLASH_SAR_TEMP_OFFSET

SAR Temperature Sensor Offset

Address: 0x0FFF166

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	TEMP_OFFSET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	None							
Name	TEMP_OFFSET [15:8]							

Bits	Name	Description
15 : 0	TEMP_OFFSET	Offset value for SAR temperature sensor in fixed point 10.6 format. Note: this field exists in products that contain SAR (m0s8sar) only. Default Value: X

19.1.11 SFLASH_IMO_TCTRIM_LT0

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.12 SFLASH_IMO_TCTRIM_LT1

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FS_OFFSET and OFFSET trims. Default Value: 16

19.1.13 SFLASH_IMO_TCTRIM_LT2

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.14 SFLASH_IMO_TCTRIM_LT3

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1CF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.15 SFLASH_IMO_TCTRIM_LT4

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.16 SFLASH_IMO_TCTRIM_LT5

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.17 SFLASH_IMO_TCTRIM_LT6

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPSize [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPSize	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOffset and Offset trims. Default Value: 16

19.1.18 SFLASH_IMO_TCTRIM_LT7

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FS_OFFSET and OFFSET trims. Default Value: 16

19.1.19 SFLASH_IMO_TCTRIM_LT8

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FS_OFFSET and OFFSET trims. Default Value: 16

19.1.20 SFLASH_IMO_TCTRIM_LT9

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FS_OFFSET and OFFSET trims. Default Value: 16

19.1.21 SFLASH_IMO_TCTRIM_LT10

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.22 SFLASH_IMO_TCTRIM_LT11

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.23 SFLASH_IMO_TCTRIM_LT12

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.24 SFLASH_IMO_TCTRIM_LT13

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1D9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.25 SFLASH_IMO_TCTRIM_LT14

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FS_OFFSET and OFFSET trims. Default Value: 16

19.1.26 SFLASH_IMO_TCTRIM_LT15

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.27 SFLASH_IMO_TCTRIM_LT16

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.28 SFLASH_IMO_TCTRIM_LT17

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.29 SFLASH_IMO_TCTRIM_LT18

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FS_OFFSET and OFFSET trims. Default Value: 16

19.1.30 SFLASH_IMO_TCTRIM_LT19

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1DF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.31 SFLASH_IMO_TCTRIM_LT20

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.32 SFLASH_IMO_TCTRIM_LT21

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.33 SFLASH_IMO_TCTRIM_LT22

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFF1E2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.34 SFLASH_IMO_TCTRIM_LT23

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FS_OFFSET and OFFSET trims. Default Value: 16

19.1.35 SFLASH_IMO_TCTRIM_LT24

IMO TempCo Trim Register (SRSS-Lite)

Address: 0x0FFFF1E4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEP_SIZE [4:0]				

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. This bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEP_SIZE	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

19.1.36 SFLASH_IMO_TRIM_LT0

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.37 SFLASH_IMO_TRIM_LT1

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.38 SFLASH_IMO_TRIM_LT2

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFF1E7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.39 SFLASH_IMO_TRIM_LT3

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.40 SFLASH_IMO_TRIM_LT4

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1E9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.41 SFLASH_IMO_TRIM_LT5

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.42 SFLASH_IMO_TRIM_LT6

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.43 SFLASH_IMO_TRIM_LT7

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.44 SFLASH_IMO_TRIM_LT8

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1ED

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.45 SFLASH_IMO_TRIM_LT9

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1EE

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.46 SFLASH_IMO_TRIM_LT10

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFF1EF

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.47 SFLASH_IMO_TRIM_LT11

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F0

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.48 SFLASH_IMO_TRIM_LT12

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F1

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.49 SFLASH_IMO_TRIM_LT13

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F2

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.50 SFLASH_IMO_TRIM_LT14

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F3

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.51 SFLASH_IMO_TRIM_LT15

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F4

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.52 SFLASH_IMO_TRIM_LT16

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F5

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.53 SFLASH_IMO_TRIM_LT17

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F6

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.54 SFLASH_IMO_TRIM_LT18

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F7

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.55 SFLASH_IMO_TRIM_LT19

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.56 SFLASH_IMO_TRIM_LT20

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1F9

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.57 SFLASH_IMO_TRIM_LT21

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FA

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.58 SFLASH_IMO_TRIM_LT22

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FB

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.59 SFLASH_IMO_TRIM_LT23

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FC

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

19.1.60 SFLASH_IMO_TRIM_LT24

IMO Frequency Trim Register (SRSS-Lite)

Address: 0x0FFFF1FD

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	None							
Name	OFFSET [7:0]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. Default Value: X

20 SPC Interface (SPCIF) Registers



This section discusses the System Performance Controller Interface (SPCIF) registers. It lists all the registers in mapping tables, in address order.

20.1 Register Details

Register Name	Address
SPCIF_GEOMETRY	0x40110000
SPCIF_INTR	0x401107F0
SPCIF_INTR_SET	0x401107F4
SPCIF_INTR_MASK	0x401107F8
SPCIF_INTR_MASKED	0x401107FC

20.1.1 SPCIF_GEOMETRY

Flash/NVL geometry information

Address: 0x40110000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	W							
Name	FLASH [7:0]							
Bits	15	14	13	12	11	10	9	8
SW Access	R		R					
HW Access	W		W					
Name	SFLASH [15:14]		FLASH [13:8]					
Bits	23	22	21	20	19	18	17	16
SW Access	R		R		R			
HW Access	W		W		W			
Name	FLASH_ROW [23:22]		NUM_FLASH [21:20]		SFLASH [19:16]			
Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	None	None						
Name	DE_CPD_LP	None [30:24]						

Bits	Name	Description
31	DE_CPD_LP	0': SRAM busy wait loop has not been copied. '1': Busy wait loop has been written into SRAM. Default Value: 0
23 : 22	FLASH_ROW	Page size in 64 Byte multiples (chip dependent): "0": 64 byte "1": 128 byte "2": 192 byte "3": 256 byte The page size is used to determine the number of Bytes in a page for Flash page based operations (e.g. PGM_PAGE). Note: the field name FLASH_ROW is misleading, as this field specifies the number of Bytes in a page, rather than the number of Bytes in a row. In a single plane flash macro architecture, a page consists of a single row. However, in a multi plane flash macro architecture, a page consists of multiple rows from different planes. Default Value: Undefined

20.1.1 SPCIF_GEOMETRY (continued)

21 : 20	NUM_FLASH	Number of flash macros (chip dependent): "0": 1 flash macro "1": 2 flash macros "2": 3 flash macros "3": 4 flash macros Default Value: Undefined
19 : 14	SFLASH	Supervisory flash capacity in 256 Byte multiples (chip dependent). If multiple flash macros are present, this field provides the supervisory flash capacity of all flash macros together: "0": 256 Bytes. "1": 2*256 Bytes. ... "63": 64*256 Bytes. Default Value: Undefined
13 : 0	FLASH	Regular flash capacity in 256 Byte multiples (chip dependent). If multiple flash macros are present, this field provides the flash capacity of all flash macros together: "0": 256 Bytes. "1": 2*256 Bytes. ... "16383": 16384*256 Bytes. Default Value: Undefined

20.1.2 SPCIF_INTR

SPCIF interrupt request register

Address: 0x401107F0

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1C
HW Access	None							RW1S
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Timer counter value reaches "0". Set to '1', when event is detected. Write INTR field with '1', to clear bit. Write INTR_SET field with '1', to set bit. Default Value: 0

20.1.3 SPCIF_INTR_SET

SPCIF interrupt set request register

Address: 0x401107F4

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW1S
HW Access	None							A
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Write INTR_SET field with '1' to set corresponding INTR field. Default Value: 0

20.1.4 SPCIF_INTR_MASK

SPCIF interrupt mask register

Address: 0x401107F8

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							RW
HW Access	None							R
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Mask for corresponding field in INTR register. Default Value: 0

20.1.5 SPCIF_INTR_MASKED

SPCIF interrupt masked request register

Address: 0x401107FC

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							W
Name	None [7:1]							TIMER

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	TIMER	Logical and of corresponding request and mask fields. Default Value: 0

21 System Resources Sub System Registers



This section discusses the System Resources Sub System (SRSS) registers. It lists all the registers in mapping tables, in address order.

21.1 Register Details

Register Name	Address
PWR_CONTROL	0x40030000
PWR_KEY_DELAY	0x40030004
PWR_DDFT_SELECT	0x4003000C
TST_MODE	0x40030014
CLK_SELECT	0x40030028
CLK_ILO_CONFIG	0x4003002C
CLK_IMO_CONFIG	0x40030030
CLK_DFT_SELECT	0x40030034
WDT_DISABLE_KEY	0x40030038
WDT_COUNTER	0x4003003C
WDT_MATCH	0x40030040
SRSS_INTR	0x40030044
SRSS_INTR_SET	0x40030048
SRSS_INTR_MASK	0x4003004C
RES_CAUSE	0x40030054
CLK_IMO_SELECT	0x40030F08
CLK_IMO_TRIM1	0x40030F0C
CLK_IMO_TRIM2	0x40030F10
PWR_PWRSYS_TRIM1	0x40030F14
CLK_IMO_TRIM3	0x40030F18

21.1.1 PWR_CONTROL

Power Mode Control

Address: 0x40030000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		R	R	R			
HW Access	None		RW	RW	RW			
Name	None [7:6]		LP-M_READY	DEBUG_SESSION	POWER_MODE [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW	None			R		RW	RW
HW Access	A	None			RW		R	R
Name	EXT_VCCD	None [22:20]			SPARE [19:18]		OVER_TEMP_THRESH	OVER_TEMP_EN

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
23	EXT_VCCD	Always write 0 except as noted below. Setting this bit turns off the active regulator and will lead to system reset (BOD) unless both V _{dd} and V _{ccd} pins are supplied externally. This register bit only resets for XRES, POR, or a detected BOD. Default Value: 0
19 : 18	SPARE	Spare AHB readback bits that are hooked to PWR_PWRSYS_TRIM1.SPARE_TRIM[1:0] through spare logic equivalent to bitwise inversion. Engineering only. Default Value: 0
17	OVER_TEMP_THRESH	Over-temperature threshold. 0: TEMP_HIGH condition occurs between 120C and 125C. 1: TEMP_HIGH condition occurs between 60C and 75C (used for testing). Default Value: 0
16	OVER_TEMP_EN	Enables the die over temperature sensor. Must be enabled when using the TEMP_HIGH interrupt. Default Value: 0

21.1.1 PWR_CONTROL (continued)

5	LPM_READY	Indicates whether the low power mode regulator is ready to enter DEEPSLEEP mode. 0: If DEEPSLEEP mode is requested, device will enter SLEEP mode. When low power regulators are ready, device will automatically enter the originally requested mode. 1: Normal operation. DEEPSLEEP works as described. Default Value: 0
4	DEBUG_SESSION	Indicates whether a debug session is active (CDBGPWRUPREQ signal is 1) Default Value: 0 0x0: NO_SESSION: No debug session active 0x1: SESSION_ACTIVE: Debug session is active
3 : 0	POWER_MODE	Current power mode of the device. Note that this field cannot be read in all power modes on actual silicon. Default Value: 0 0x0: RESET: RESET state 0x1: ACTIVE: ACTIVE state 0x2: SLEEP: SLEEP state 0x3: DEEP_SLEEP: DEEP_SLEEP state

21.1.2 PWR_KEY_DELAY

Power System Key Register

Address: 0x40030004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WAKEUP_HOLDOFF [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None						RW	
HW Access	None						R	
Name	None [15:10]						WAKEUP_HOLDOFF [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
9 : 0	WAKEUP_HOLDOFF	Delay to wait for references to settle on wakeup from deepsleep. BOD is ignored and system does not resume until this delay expires. Note that the same delay on POR is hard-coded. The default assumes the output of the predivider is 48MHz + 3%. Firmware may scale this setting according to the fastest actual clock frequency that can occur when waking from DEEPSLEEP. Default Value: 248

21.1.3 PWR_DDFT_SELECT

Power DDFT Mode Selection Register

Address: 0x4003000C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	DDFT1_SEL [7:4]				DDFT0_SEL [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	DDFT1_SEL	Select signal for power DDFT output #1 Default Value: 0 0x0: WAKEUP: wakeup 0x1: AWAKE: awake 0x2: ACT_POWER_EN: act_power_en 0x3: ACT_POWER_UP: act_power_up 0x4: ACT_POWER_GOOD: act_power_good 0x5: ACT_REF_VALID: act_ref_valid 0x6: ACT_REG_VALID: act_reg_valid

21.1.3 PWR_DDFT_SELECT (continued)

		0x7: ACT_COMP_OUT: act_comp_out
		0x8: ACT_TEMP_HIGH: act_temp_high
		0x9: DPSLP_COMP_OUT: dpslp_comp_out
		0xa: DPSLP_POWER_UP: dpslp_power_up
		0xb: AWAKE_DELAYED: awake_delayed
		0xc: LPM_READY: lpm_ready
		0xd: SLEEPHOLDACK_N: sleepholdack_n
		0xe: GND: 1'b0
		0xf: PWR: 1'b1
3 : 0	DDFT0_SEL	Select signal for power DDFT output #0 Default Value: 0
		0x0: WAKEUP: wakeup
		0x1: AWAKE: awake
		0x2: ACT_POWER_EN: act_power_en
		0x3: ACT_POWER_UP: act_power_up
		0x4: ACT_POWER_GOOD: act_power_good
		0x5: ACT_REF_EN: srss_adft_control_act_ref_en
		0x6: ACT_COMP_EN: srss_adft_control_act_comp_en
		0x7: DPSLP_REF_EN: srss_adft_control_dpslp_ref_en
		0x8: DPSLP_REG_EN: srss_adft_control_dpslp_reg_en
		0x9: DPSLP_COMP_EN: srss_adft_control_dpslp_comp_en
		0xa: OVER_TEMP_EN: pwr_control_over_temp_en
		0xb: SLEEPHOLDREQ_N: sleepholdreq_n

21.1.3 PWR_DDFT_SELECT (continued)

0xc: ADFT_BUF_EN:

adft_buf_en

0xd: ATPG_OBSERVE:

ATPG observe point (no functional purpose)

0xe: GND:

1'b0

0xf: PWR:

1'b1

21.1.4 TST_MODE

Test Mode Control Register

Address: 0x40030014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					R	None	
HW Access	None					RW	None	
Name	None [7:3]					SWD_CONNECTED	None [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	R	None	RW	None			
HW Access	R	RW	None	A	None			
Name	TEST_MODE	TEST_KEY_DFT_EN	None	BLOCK_AL T_XRES	None [27:24]			

Bits	Name	Description
31	TEST_MODE	0: Normal operation mode 1: Test mode (any test mode) Setting this bit will prevent BootROM from yielding execution to Flash image. Default Value: 0
30	TEST_KEY_DFT_EN	This bit is set when a XRES test mode key is shifted in. It is the value of the test_key_dft_en signal. When this bit is set, the BootROM will not yield execution to the FLASH image (same function as setting TEST_MODE bit below). Default Value: 0
28	BLOCK_ALT_XRES	Relevant only for parts that have the alternate XRES mechanism of overloading a GPIO pin temporarily as alternate XRES during test. When set, this bit blocks the alternate XRES function, such that the pin can be used for normal I/O or for ddft/adft observation. See SAS Part-V and Part-IX for details. This register bit only resets for XRES, POR, or a detected BOD. Default Value: 0

21.1.4 TST_MODE (continued)

2	SWD_CONNECTED	0: SWD not active 1: SWD activated (Line Reset & Connect sequence passed) (Note: this bit replaces TST_CTRL.SWD_CONNECTED and is present in all M0S8 products except TSG4) Default Value: 0

21.1.5 CLK_SELECT

Clock Select Register

Address: 0x40030028

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW		RW		RW		RW	
HW Access	R		R		R		R	
Name	SYSCLK_DIV [7:6]		PUMP_SEL [5:4]		HFCLK_DIV [3:2]		HFCLK_SEL [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 6	SYSCLK_DIV	Select clk_sys prescaler value. Default Value: 0 0x0: NO_DIV: clk_sys= clk_hf/1 0x1: DIV_BY_2: clk_sys= clk_hf/2 0x2: DIV_BY_4: clk_sys= clk_hf/4 0x3: DIV_BY_8: clk_sys= clk_hf/8
5 : 4	PUMP_SEL	Selects clock source for charge pump clock. This clock is not guaranteed to be glitch free when changing any of its sources or settings. Default Value: 0 0x0: GND: No clock, connect to gnd

21.1.5 CLK_SELECT (continued)

		0x1: IMO: Use main IMO output
		0x2: HFCLK: Use clk_hf (using selected source after predivider but before prescaler)
3 : 2	HFCLK_DIV	Selects clk_hf predivider value. Default Value: 2
		0x0: NO_DIV: Transparent mode, feed through selected clock source w/o dividing.
		0x1: DIV_BY_2: Divide selected clock source by 2
		0x2: DIV_BY_4: Divide selected clock source by 4
		0x3: DIV_BY_8: Divide selected clock source by 8
1 : 0	HFCLK_SEL	Selects a source for clk_hf and dsi_in[0]. Note that not all products support all clock sources. Selecting a clock source that is not supported will result in undefined behavior. Default Value: 0
		0x0: IMO: IMO - Internal R/C Oscillator
		0x1: EXTCLK: EXTCLK - External Clock Pin
		0x2: ECO: ECO - External-Crystal Oscillator or PLL subsystem output

21.1.6 CLK_ILO_CONFIG

ILO Configuration

Address: 0x4003002C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	RW	None						
Name	ENABLE	None [30:24]						

Bits	Name	Description
31	ENABLE	Master enable for ILO oscillator. This bit is hardware set whenever the WD_DISABLE_KEY is not set to the magic value. Default Value: 1

21.1.7 CLK_IMO_CONFIG

IMO Configuration

Address: 0x40030030

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							
HW Access	None							
Name	None [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	None						
HW Access	R	None						
Name	ENABLE	None [30:24]						

Bits	Name	Description
31	ENABLE	Master enable for IMO oscillator. Clearing this bit will disable the IMO. Don't do this if the system is running off it. Default Value: 1

21.1.8 CLK_DFT_SELECT

Clock DFT Mode Selection Register

Address: 0x40030034

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW	RW		RW			
HW Access	None	R	R		R			
Name	None	DFT_EDGE 0	DFT_DIV0 [5:4]		DFT_SEL0 [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None	RW	RW		RW			
HW Access	None	R	R		R			
Name	None	DFT_EDGE 1	DFT_DIV1 [13:12]		DFT_SEL1 [11:8]			

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
14	DFT_EDGE1	Edge sensitivity for in-line divider on output #1 (only relevant when DIV1>0). Default Value: 0 0x0: POSEDGE: Use posedge for divider 0x1: NEGEDGE: Use negedge for divider
13 : 12	DFT_DIV1	DFT Output Divide Down. Default Value: 0 0x0: NO_DIV: Direct Output 0x1: DIV_BY_2: Divide by 2 0x2: DIV_BY_4: Divide by 4

21.1.8 CLK_DFT_SELECT (continued)

11 : 8	DFT_SEL1	0x3: DIV_BY_8: Divide by 8
		Select signal for DFT output #1 Default Value: 0
		0x0: NC: Disabled - output is 0
		0x1: ILO: clk_ilo: ILO output
		0x2: IMO: clk_imo: IMO primary output
		0x3: ECO: clk_eco: ECO output
		0x4: EXTCLK: clk_ext: external clock input
		0x5: HFCLK: clk_hf: root of the high-speed clock tree
		0x6: LFCLK: clk_lf: root of the low-speed clock tree
		0x7: SYSCLK: clk_sys: root of the CPU/AHB clock tree (gated version of clk_hf)
6	DFT_EDGE0	0x8: PUMPCLK: clk_pump: clock provided to charge pumps in FLASH and PA
		0x9: SLPCTRLCLK: clk_slpctrl: clock provided to SleepController
		Edge sensitivity for in-line divider on output #0 (only relevant when DIV0>0). Default Value: 0
5 : 4	DFT_DIV0	0x0: POSEDGE: Use posedge for divider
		0x1: NEGEDGE: Use negedge for divider
		DFT Output Divide Down. Default Value: 0
		0x0: NO_DIV: Direct Output
		0x1: DIV_BY_2: Divide by 2
		0x2: DIV_BY_4: Divide by 4
		0x3: DIV_BY_8: Divide by 8
		Select signal for DFT output #0 Default Value: 0
		0x0: NC: Disabled - output is 0
3 : 0	DFT_SEL0	Select signal for DFT output #0 Default Value: 0
		0x0: NC: Disabled - output is 0

21.1.8 CLK_DFT_SELECT (continued)

0x1: ILO:

clk_ilo: ILO output

0x2: IMO:

clk_imo: IMO primary output

0x3: ECO:

clk_eco: ECO output

0x4: EXTCLK:

clk_ext: external clock input

0x5: HFCLK:

clk_hf: root of the high-speed clock tree

0x6: LFCLK:

clk_lf: root of the low-speed clock tree

0x7: SYSCLK:

clk_sys: root of the CPU/AHB clock tree (gated version of clk_hf)

0x8: PUMPCLK:

clk_pump: clock provided to charge pumps in FLASH and PA

0x9: SLPCTRLCLK:

clk_slpctrl: clock provided to SleepController

21.1.9 WDT_DISABLE_KEY

Watchdog Disable Key Register

Address: 0x40030038

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	KEY [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	KEY [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	KEY [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	KEY [31:24]							

Bits	Name	Description
31 : 0	KEY	Disables WDT reset when equal to 0xACED8865. The WDT reset functions normally for any other setting. Default Value: 0

21.1.10 WDT_COUNTER

Watchdog Counter Register

Address: 0x4003003C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	COUNTER [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	COUNTER [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
15 : 0	COUNTER	Current value of WDT Counter Default Value: 0

21.1.11 WDT_MATCH

Watchdog Match Register

Address: 0x40030040

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	MATCH [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	MATCH [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW			
HW Access	None				R			
Name	None [23:20]				IGNORE_BITS [19:16]			

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19 : 16	IGNORE_BITS	The number of MSB bits of the watchdog timer that are NOT checked against MATCH. This value provides control over the time-to-reset of the watchdog (which happens after 3 successive matches). Note that certain products may enforce a minimum value for this register through design time configuration. Default Value: 0
15 : 0	MATCH	Match value for Watchdog counter. Every time WDT_COUNTER reaches MATCH an interrupt is generated. Two unserviced interrupts will lead to a system reset (i.e. at the third match). Default Value: 4096

21.1.12 SRSS_INTR

SRSS Interrupt Register

Address: 0x40030044

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1C	RW1C
HW Access	None						A	A
Name	None [7:2]						TEMP_HIGH	WDT_MATCH

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Regulator over-temp interrupt. This interrupt can occur when a short circuit exists on the vccd pin or when extreme loads are applied on IO-cells causing the die to overheat. Firmware is encourage to shutdown all IO cells and then go to DeepSleep mode when this interrupt occurs if protection against such conditions is desired. Default Value: 0
0	WDT_MATCH	WDT Interrupt Request. This bit is set each time WDT_COUNT==WDT_MATCH. Clearing this bit also feeds the watch dog. Missing 2 interrupts in a row will generate brown-out reset. Due to internal synchronization, it takes 2 SYSCLK cycles to update after a W1C. Default Value: 0

21.1.13 SRSS_INTR_SET

SRSS Interrupt Set Register

Address: 0x40030048

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW1S	None
HW Access	None						A	None
Name	None [7:2]						TEMP_HIGH	None

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Writing 1 to this bit internally sets the overtemp interrupt. This can be observed by reading SRSS_INTR.TEMP_HIGH. This bit always reads back as zero. Default Value: 0

21.1.14 SRSS_INTR_MASK

SRSS Interrupt Mask Register

Address: 0x4003004C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						TEMP_HIGH	WDT_MATCH

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	TEMP_HIGH	Masks REG_OVERTEMP interrupt Default Value: 0
0	WDT_MATCH	Clearing this bit will not forward the interrupt to the CPU. It will not, however, disable the WDT reset generation on 2 missed interrupts. Default Value: 0

21.1.15 RES_CAUSE

Reset Cause Observation Register

Address: 0x40030054

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1C	RW1C	None		RW1C
HW Access	None			A	A	None		A
Name	None [7:5]			RESET_ SOFT	RE- SET_PROT _FAULT	None [2:1]		RE- SET_WDT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4	RESET_SOFT	Cortex-M0 requested a system reset through it's SYSRESETREQ. This can be done via a debugger probe or in firmware. Default Value: 0
3	RESET_PROT_FAULT	A protection violation occurred that requires a RESET. This includes, but is not limited to, hitting a debug breakpoint while in Privileged Mode. Default Value: 0
0	RESET_WDT	A WatchDog Timer reset has occurred since last power cycle. Default Value: 0

21.1.16 CLK_IMO_SELECT

IMO Frequency Select Register

Address: 0x40030F08

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					R		
Name	None [7:3]					FREQ [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	FREQ	Select operating frequency Default Value: 0 0x0: 24_MHZ: IMO runs at 24 MHz 0x1: 28_MHZ: IMO runs at 28 MHz 0x2: 32_MHZ: IMO runs at 32 MHz 0x3: 36_MHZ: IMO runs at 36 MHz 0x4: 40_MHZ: IMO runs at 40 MHz 0x5: 44_MHZ: IMO runs at 44 MHz 0x6: 48_MHZ: IMO runs at 48 MHz

21.1.17 CLK_IMO_TRIM1

IMO Trim Register

Address: 0x40030F0C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	RW							
Name	OFFSET [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 0	OFFSET	Frequency trim bits. These bits are determined at manufacturing time for each FREQ setting (IMO_TRIM2) and stored in SFLASH. This field is hardware updated during USB osclock mode. This field is mapped to the most significant bits of the IMO trim imo_clk_trim[10:3]. The step size of 1 LSB on this field is approximately 120 kHz. Default Value: 128

21.1.18 CLK_IMO_TRIM2

IMO Trim Register

Address: 0x40030F10

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW		
HW Access	None					RW		
Name	None [7:3]					FSOFFSET [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
2 : 0	FSOFFSET	Frequency trim bits. These bits are not trimmed during manufacturing and kept at 0 under normal operation. This field is hardware updated during USB osclock mode. This field is mapped to the least significant bits of the IMO trim imo_clk_trim[2:0]. The step size of 1 LSB on this field is approximately 15 kHz. Default Value: 0

21.1.19 PWR_PWRSYS_TRIM1

Power System Trim Register

Address: 0x40030F14

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW				RW			
HW Access	R				R			
Name	SPARE_TRIM [7:4]				DPSLP_REF_TRIM [3:0]			

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
7 : 4	SPARE_TRIM	Active-Reference temperature compensation trim (repurposed from spare bits). Bits [7:6] - trim the Active-Reference IREF temperature coefficient (TC). 00: TC = 0 (unchanged) 01: TC = +80ppm/C 10: TC = -80ppm/C 11: TC = -150ppm/C Bits [5:4] - trim the Active-Reference VREF temperature coefficient (TC). 00: TC = 0 (unchanged) 01: TC = -50ppm/C 10: TC = -80ppm/C 11: TC = +150ppm/C Default Value: 0
3 : 0	DPSLP_REF_TRIM	Trims the DeepSleep reference that is used by the DeepSleep regulator and DeepSleep power comparator. Default Value: 0

21.1.20 CLK_IMO_TRIM3

IMO Trim Register

Address: 0x40030F18

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None	RW		RW				
HW Access	None	R		R				
Name	None	TCTRIM [6:5]		STEPsize [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
6 : 5	TCTRIM	IMO temperature compensation trim. These bits are determined at manufacturing time to adjust for temperature dependence. These bits are dependent on frequency and need to be changed using the Cypress provided frequency change algorithm. Default Value: 2
4 : 0	STEPsize	IMO trim stepsize bits. These bits are determined at manufacturing time to adjust for process variation. They are used to tune the stepsize of the FSOFFSET and OFFSET trims. Default Value: 16

22 Timer, Counter, PWM (TCPWM) Registers



This section discusses the Timer, Counter, PWM (TCPWM) registers. It lists all the registers in mapping tables, in address order.

22.1 Register Details

Register Name	Address
TCPWM_CTRL	0x40060000
TCPWM_CMD	0x40060008
TCPWM_INTR_CAUSE	0x4006000C

22.1.1 TCPWM_CTRL

TCPWM control register 0.

Address: 0x40060000

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			COUNTER_ENABLED [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COUNTER_ENABLED	Counter enables for counters 0 up to CNT_NR-1. '0': counter disabled. '1': counter enabled. Counter static configuration information (e.g. CTRL.MODE, all TR_CTRL0, TR_CTRL1, and TR_CTRL2 register fields) should only be modified when the counter is disabled. When a counter is disabled, command and status information associated to the counter is cleared by HW, this includes: - the associated counter triggers in the CMD register are set to '0'. - the counter's interrupt cause fields in counter's INTR register. - the counter's status fields in counter's STATUS register.. - the counter's trigger outputs ("tr_overflow", "tr_underflow" and "tr_compare_match"). - the counter's line outputs ("line_out" and "line_compl_out"). Default Value: 0

22.1.2 TCPWM_CMD

TCPWM command register.

Address: 0x40060008

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW1S				
HW Access	None			RW1C				
Name	None [7:5]			COUNTER_CAPTURE [4:0]				
Bits	15	14	13	12	11	10	9	8
SW Access	None			RW1S				
HW Access	None			RW1C				
Name	None [15:13]			COUNTER_RELOAD [12:8]				
Bits	23	22	21	20	19	18	17	16
SW Access	None			RW1S				
HW Access	None			RW1C				
Name	None [23:21]			COUNTER_STOP [20:16]				
Bits	31	30	29	28	27	26	25	24
SW Access	None			RW1S				
HW Access	None			RW1C				
Name	None [31:29]			COUNTER_START [28:24]				

Bits	Name	Description
28 : 24	COUNTER_START	Counters SW start trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
20 : 16	COUNTER_STOP	Counters SW stop trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
12 : 8	COUNTER_RELOAD	Counters SW reload trigger. For HW behavior, see COUNTER_CAPTURE field. Default Value: 0
4 : 0	COUNTER_CAPTURE	Counters SW capture trigger. When written with '1', a capture trigger is generated and the HW sets the field to '0' when the SW trigger has taken effect. It should be noted that the HW operates on the counter frequency. If the counter is disabled through CTRL.COUNTER_ENABLED, the field is immediately set to '0'. Default Value: 0

22.1.3 TCPWM_INTR_CAUSE

TCPWM Counter interrupt cause register.

Address: 0x4006000C

Retention: Not Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			R				
HW Access	None			W				
Name	None [7:5]			COUNTER_INT [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	COUNTER_INT	Counters interrupt signal active. If the counter is disabled through CTRL.COUNTER_ENABLED, the associated interrupt field is immediately set to '0'. Default Value: 0

23 PERI Trigger Group Control Registers



This section discusses the PERI Trigger Group Control (TR_GROUP) registers. It lists all the registers in mapping tables, in address order.

23.1 Register Details

Register Name	Address
PERI_TR_GROUP0_TR_OUT_CTL0	0x40012000
PERI_TR_GROUP0_TR_OUT_CTL1	0x40012004
PERI_TR_GROUP0_TR_OUT_CTL2	0x40012008
PERI_TR_GROUP0_TR_OUT_CTL3	0x4001200C
PERI_TR_GROUP0_TR_OUT_CTL4	0x40012010
PERI_TR_GROUP0_TR_OUT_CTL5	0x40012014
PERI_TR_GROUP0_TR_OUT_CTL6	0x40012018
PERI_TR_GROUP1_TR_OUT_CTL	0x40012200

23.1.1 PERI_TR_GROUP0_TR_OUT_CTL0

Trigger control register

Address: 0x40012000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.2 PERI_TR_GROUP0_TR_OUT_CTL1

Trigger control register

Address: 0x40012004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.3 PERI_TR_GROUP0_TR_OUT_CTL2

Trigger control register

Address: 0x40012008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.4 PERI_TR_GROUP0_TR_OUT_CTL3

Trigger control register

Address: 0x4001200C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.5 PERI_TR_GROUP0_TR_OUT_CTL4

Trigger control register

Address: 0x40012010

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.6 PERI_TR_GROUP0_TR_OUT_CTL5

Trigger control register

Address: 0x40012014

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.7 PERI_TR_GROUP0_TR_OUT_CTL6

Trigger control register

Address: 0x40012018

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

23.1.8 PERI_TR_GROUP1_TR_OUT_CTL

Trigger control register

Address: 0x40012200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None			RW				
HW Access	None			R				
Name	None [7:5]			SEL [4:0]				

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
4 : 0	SEL	Specifies input trigger. This field is typically set during the setup of a chip use case scenario. Changing this field while activated triggers are present on the input triggers may result in unpredictable behavior. Note that input trigger 0 (default value) is typically connected to a constant signal level of '0', and as a result will not cause HW activation of the output trigger. Default Value: 0

24 Watch Crystal Oscillator (WCO) Registers



This section discusses the WRK8 registers. It lists all the registers in mapping tables, in address order.

24.1 Register Details

Register Name	Address
WCO_CONFIG	0x40070000
WCO_STATUS	0x40070004
WCO_DPLL	0x40070008
WCO_WDT_CTRLLOW	0x40070200
WCO_WDT_CTRHIGH	0x40070204
WCO_WDT_MATCH	0x40070208
WCO_WDT_CONFIG	0x4007020C
WCO_WDT_CONTROL	0x40070210
WCO_WDT_CLKEN	0x40070214
WCO_TRIM	0x40070F00

24.1.1 WCO_CONFIG

WCO Configuration Register

Address: 0x40070000

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None					RW	RW	RW
HW Access	None					R	R	R
Name	None [7:3]					EXT_IN- PUT_EN	LPM_AUTO	LPM_EN

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	ENBUS [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW	RW	None					
HW Access	R	R	None					
Name	IP_ENABLE	DPLL_EN- ABLE	None [29:24]					

Bits	Name	Description
31	IP_ENABLE	Master enable for IP - disables both WCO and DPLL Default Value: 0
30	DPLL_ENABLE	Enable DPLL operation. The Oscillator is specified to be stable after 500 ms thus the DPLL should be asserted no sooner than that after IP_ENABLE is set. Default Value: 0
23 : 16	ENBUS	Test Mode Control bits enbus[7] - N/A enbus[6] - 1=enable both primary Beta Multipliers enbus[5] - N/A enbus[4] - N/A enbus[3] - Load Resistor Control enbus[2] - Load Resistor Control enbus[1] - Load Resistor Control enbus[0] - Load Resistor Control Default Value: 71
2	EXT_INPUT_EN	Disables the load resistor and allows external clock input for pad_xin Default Value: 0

24.1.1 WCO_CONFIG (continued)

1	LPM_AUTO	Automatically control low power mode (only relevant when LPM_EN=0): 0: Do not enter low power mode (LPM) in DeepSleep 1: Enter low power mode (LPM) in DeepSleep. The logic monitors !act_power_en to determine the device has entered DeepSleep. Default Value: 1
0	LPM_EN	Force block into Low Power Mode: 0: Do not force low power mode (LPM) on 1: Force low power mode (LPM) on Default Value: 0

24.1.2 WCO_STATUS

WCO Status Register

Address: 0x40070004

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None							R
HW Access	None							RW
Name	None [7:1]							OUT- _BLNK_A

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
0	OUT_BLNK_A	Indicates that output has transitioned - This bit is intended for Test Mode Only and is not a reliable indicator. Default Value: 0

24.1.3 WCO_DPLL

WCO DPLL Register

Address: 0x40070008

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	DPLL_MULT [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	None					RW		
HW Access	None					R		
Name	None [15:11]					DPLL_MULT [10:8]		

Bits	23	22	21	20	19	18	17	16
SW Access	RW		RW			RW		
HW Access	R		R			R		
Name	DPLL_LF_LIMIT [23:22]		DPLL_LF_PGAIN [21:19]			DPLL_LF_IGAIN [18:16]		

Bits	31	30	29	28	27	26	25	24
SW Access	None		RW					
HW Access	None		R					
Name	None [31:30]		DPLL_LF_LIMIT [29:24]					

Bits	Name	Description
29 : 22	DPLL_LF_LIMIT	Maximum IMO offset allowed (used to prevent DPLL dynamics from selecting an IMO frequency that the logic cannot support) Default Value: 255
21 : 19	DPLL_LF_PGAIN	DPLL Loop Filter Proportional Gain Setting 0x0 - 0.0625 0x1 - 0.125 0x2 - 0.25 0x3 - 0.5 0x4 - 1.0 0x5 - 2.0 0x6 - 4.0 0x7 - 8.0 Default Value: 0

24.1.3 WCO_DPLL (continued)

18 : 16	DPLL_LF_IGAIN	DPLL Loop Filter Integral Gain Setting 0x0 - 0.0625 0x1 - 0.125 0x2 - 0.25 0x3 - 0.5 0x4 - 1.0 0x5 - 2.0 0x6 - 4.0 0x7 - 8.0 Default Value: 0
10 : 0	DPLL_MULT	Multiplier to determine IMO frequency in multiples of the WCO frequency $F_{imo} = (DPLL\_MULT + 1) * F_{wco}$ Default Value: 0

24.1.4 WCO_WDT_CTRL0W

Watchdog Counters 0/1

Address: 0x40070200

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WDT_CTRL0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WDT_CTRL0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	WDT_CTRL1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	RW							
Name	WDT_CTRL1 [31:24]							

Bits	Name	Description
31 : 16	WDT_CTRL1	Current value of WDT Counter 1 Default Value: 0
15 : 0	WDT_CTRL0	Current value of WDT Counter 0 Default Value: 0

24.1.5 WCO_WDT_CTRHIGH

Watchdog Counter 2

Address: 0x40070204

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	R							
HW Access	RW							
Name	WDT_CTR2 [31:24]							

Bits	Name	Description
31 : 0	WDT_CTR2	Current value of WDT Counter 2 Default Value: 0

24.1.6 WCO_WDT_MATCH

Watchdog counter match values

Address: 0x40070208

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	RW							
HW Access	R							
Name	WDT_MATCH0 [7:0]							

Bits	15	14	13	12	11	10	9	8
SW Access	RW							
HW Access	R							
Name	WDT_MATCH0 [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	RW							
HW Access	R							
Name	WDT_MATCH1 [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	RW							
HW Access	R							
Name	WDT_MATCH1 [31:24]							

Bits	Name	Description
31 : 16	WDT_MATCH1	Match value for Watchdog Counter 1 Default Value: 0
15 : 0	WDT_MATCH0	Match value for Watchdog Counter 0 Default Value: 0

24.1.7 WCO_WDT_CONFIG

Watchdog Counters Configuration

Address: 0x4007020C

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW	RW	RW	
HW Access	None				R	R	R	
Name	None [7:4]				WDT_CAS-CADE0_1	WDT_-CLEAR0	WDT_MODE0 [1:0]	

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW	RW	RW	
HW Access	None				R	R	R	
Name	None [15:12]				WDT_CAS-CADE1_2	WDT_-CLEAR1	WDT_MODE1 [9:8]	

Bits	23	22	21	20	19	18	17	16
SW Access	None							RW
HW Access	None							R
Name	None [23:17]							WDT_-MODE2

Bits	31	30	29	28	27	26	25	24
SW Access	RW		None	RW				
HW Access	R		None	R				
Name	LFCLK_SEL [31:30]		None	WDT_BITS2 [28:24]				

Bits	Name	Description
31 : 30	LFCLK_SEL	Select source for LFCLK: 0: ILO - Internal R/C Oscillator 1: WCO - Internal Crystal Oscillator 2-3: Reserved - do not use Note that not all products support all clock sources. Selecting a clock source that is not supported will result in undefined behavior. To safely change LFCLK_SEL wait for WDT_CTLLOW/WDT_CTLHIGH to change then change the setting immediately. Default Value: 0
28 : 24	WDT_BITS2	Bit to observe for WDT_INT2: 0: Assert when bit0 of WDT_CTL2 toggles (one int every tick) ... 31: Assert when bit31 of WDT_CTL2 toggles (one int every 2^31 ticks) Default Value: 0
16	WDT_MODE2	Watchdog Counter 2 Mode. Default Value: 0

24.1.7 WCO_WDT_CONFIG (continued)

		0x0: NOTHING: Free running counter with no interrupt requests
		0x1: INT: Free running counter with interrupt request when a specified bit in CTR2 toggles (see WDT_BITS2)
11	WDT_CASCADE1_2	Cascade Watchdog Counters 1,2. Counter 2 increments the cycle after WDT_CTR1=WDT_MATCH1. It is allowed to cascade all three WDT counters. 0: Independent counters 1: Cascaded counters. When cascading all three counters, WDT_CLEAR1 must be 1 Default Value: 0
10	WDT_CLEAR1	Clear Watchdog Counter when WDT_CTR1=WDT_MATCH1. In other words WDT_CTR1 divides LFCLK by (WDT_MATCH1+1). 0: Free running counter 1: Clear on match Default Value: 0
9 : 8	WDT_MODE1	Watchdog Counter Action on Match (WDT_CTR1=WDT_MATCH1). Default Value: 0
		0x0: NOTHING: Do nothing
		0x1: INT: Assert WDT_INTx
		0x2: RESET: Assert WDT Reset - Not Supported - here for backwards compatibility
		0x3: INT_THEN_RESET: Assert WDT_INTx, assert WDT Reset after 3rd unhandled interrupt - Not supported - here for backwards compatibility.
3	WDT_CASCADE0_1	Cascade Watchdog Counters 0,1. Counter 1 increments the cycle after WDT_CTR0=WDT_MATCH0. 0: Independent counters 1: Cascaded counters Default Value: 0
2	WDT_CLEAR0	Clear Watchdog Counter when WDT_CTR0=WDT_MATCH0. In other words WDT_CTR0 divides LFCLK by (WDT_MATCH0+1). 0: Free running counter 1: Clear on match Default Value: 0
1 : 0	WDT_MODE0	Watchdog Counter Action on Match (WDT_CTR0=WDT_MATCH0). Default Value: 0
		0x0: NOTHING: Do nothing
		0x1: INT: Assert WDT_INTx
		0x2: RESET: Assert WDT Reset - Not Supported - here for backwards compatibility
		0x3: INT_THEN_RESET: Assert WDT_INTx, assert WDT Reset after 3rd unhandled interrupt. Not supported - here for Backwards compatibility.

24.1.8 WCO_WDT_CONTROL

Watchdog Counters Control

Address: 0x40070210

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None				RW1S	RW1C	R	RW
HW Access	None				RW0C	A	RW	R
Name	None [7:4]				WDT_RE-SET0	WDT_INT0	WDT_EN-ABLED0	WDT_EN-ABLE0

Bits	15	14	13	12	11	10	9	8
SW Access	None				RW1S	RW1C	R	RW
HW Access	None				RW0C	A	RW	R
Name	None [15:12]				WDT_RE-SET1	WDT_INT1	WDT_EN-ABLED1	WDT_EN-ABLE1

Bits	23	22	21	20	19	18	17	16
SW Access	None				RW1S	RW1C	R	RW
HW Access	None				RW0C	A	RW	R
Name	None [23:20]				WDT_RE-SET2	WDT_INT2	WDT_EN-ABLED2	WDT_EN-ABLE2

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
19	WDT_RESET2	Resets counter 2 back to 0000_0000. Hardware will reset this bit after counter was reset. This will take several LFCLK cycles to take effect. Wait until the reset completes before enabling the WDT. Default Value: 0
18	WDT_INT2	WDT Interrupt Request. This bit is set by hardware as configured by this registers. This bit must be cleared by firmware. After W1C, WDT_CONTROL must be read for the hardware to internally remove the clear flag. Failure to do this may result in missing the next interrupt. Default Value: 0
17	WDT_ENABLED2	Indicates actual state of counter. May lag WDT_ENABLE2 by up to 3 LFCLK cycles. After changing WDT_ENABLE2, do not enter DEEPSLEEP mode until this field acknowledges the change. Default Value: 0

24.1.8 WCO_WDT_CONTROL (continued)

16	WDT_ENABLE2	Enable Counter 2 0: Counter is disabled (not clocked) 1: Counter is enabled (counting up) Note: This field takes considerable time (up to 3 LFCLK cycles) to take effect. It must not be changed more than once in that period. Default Value: 0
11	WDT_RESET1	Resets counter 1 back to 0000. Hardware will reset this bit after counter was reset. This will take several LFCLK cycles to take effect. Wait until the reset completes before enabling the WDT. Default Value: 0
10	WDT_INT1	WDT Interrupt Request. This bit is set by hardware as configured by this registers. This bit must be cleared by firmware. After W1C, WDT_CONTROL must be read for the hardware to internally remove the clear flag. Failure to do this may result in missing the next interrupt. Default Value: 0
9	WDT_ENABLED1	Indicates actual state of counter. May lag WDT_ENABLE1 by up to 3 LFCLK cycles. After changing WDT_ENABLE1, do not enter DEEPSLEEP mode until this field acknowledges the change. Default Value: 0
8	WDT_ENABLE1	Enable Counter 1 0: Counter is disabled (not clocked) 1: Counter is enabled (counting up) Note: This field takes considerable time (up to 3 LFCLK cycles) to take effect. It must not be changed more than once in that period. Default Value: 0
3	WDT_RESET0	Resets counter 0 back to 0000. Hardware will reset this bit after counter was reset. This will take several LFCLK cycles to take effect. Wait until the reset completes before enabling the WDT. Default Value: 0
2	WDT_INT0	WDT Interrupt Request. This bit is set by hardware as configured by this registers. This bit must be cleared by firmware. Clearing this bit also prevents Reset from happening when WDT_MODEx=3. After W1C, WDT_CONTROL must be read for the hardware to internally remove the clear flag. Failure to do this may result in missing the next interrupt. Default Value: 0
1	WDT_ENABLED0	Indicates actual state of counter. May lag WDT_ENABLE0 by up to 3 LFCLK cycles. After changing WDT_ENABLE0, do not enter DEEPSLEEP mode until this field acknowledges the change. Default Value: 0
0	WDT_ENABLE0	Enable Counter 0 0: Counter is disabled (not clocked) 1: Counter is enabled (counting up) Note: This field takes considerable time (up to 3 LFCLK cycles) to take effect. It must not be changed more than once in that period. Default Value: 0

24.1.9 WCO_WDT_CLKEN

Watchdog Counters Clock Enable

Address: 0x40070214

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None						RW	RW
HW Access	None						R	R
Name	None [7:2]						CLK_ILO_EN_FOR_WDT	CLK_WCO_EN_FOR_WDT

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
1	CLK_ILO_EN_FOR_WDT	Enables the ILO clock for use by the WDT logic. Wait at least 4 ILO clock cycles for a change to take effect. Must be 0 when switching WDT_CONFIG.LFCLK_SEL. Should be 0 if CLK_WCO_EN_FOR_WDT=1. Default Value: 0
0	CLK_WCO_EN_FOR_WDT	Enables the WCO clock for use by the WDT logic. Wait at least 4 WCO clock cycles for a change to take effect. Must be 0 when switching WDT_CONFIG.LFCLK_SEL. Should be 0 if CLK_ILO_EN_FOR_WDT=1. Default Value: 0

24.1.10 WCO_TRIM

WCO Trim Register

Address: 0x40070F00

Retention: Retained

Bits	7	6	5	4	3	2	1	0
SW Access	None		RW		None	RW		
HW Access	None		R		None	R		
Name	None [7:6]		LPM_GM [5:4]		None	XGM [2:0]		

Bits	15	14	13	12	11	10	9	8
SW Access	None							
HW Access	None							
Name	None [15:8]							

Bits	23	22	21	20	19	18	17	16
SW Access	None							
HW Access	None							
Name	None [23:16]							

Bits	31	30	29	28	27	26	25	24
SW Access	None							
HW Access	None							
Name	None [31:24]							

Bits	Name	Description
5 : 4	LPM_GM	GM setting for LPM (bandwidth = DC/ms) - Used when WCO.LPM_AUTO=0 or when LPM_AUTO=1 and not in DeepSleep mode. Default Value: 1
2 : 0	XGM	Amplifier GM setting - Used when WCO.LPM_AUTO=0 or when LPM_AUTO=1 and not in DeepSleep mode. 0x0 - 3370 nA 0x1 - 2620 nA 0x2 - 2250 nA 0x3 - 1500 nA 0x4 - 1870 nA 0x5 - 1120 nA 0x6 - 750 nA 0x7 - 0 nA Default Value: 1

Revision History



Revision History

Document Title: PSoC 4100S Family PSoC(R) 4 Registers Technical Reference Manual (TRM)			
Document Number: 002-10523			
Revision	ECN#	Issue Date	Description of Change
**	5074622	01/08/2016	Specification for new silicon
*A	5361127	07/20/2016	Updated SFLASH and WCO registers.
*B	5761362	06/02/2017	Updated logo and copyright information.
*C	6713246	10/29/2019	Updated content in 4 CapSense Registers .
*D	8040267	07/01/2024	Updated broken link in "CapSense Registers" on page 197 and "Register Mapping" on page 19 .