

Revision History

Rev.	Date	Modified by	Remark
v100	2014.11.06	Rex.Cao	First version
v110	2014.12.30	Rex.Cao	Add 2 signals to CN9

Jumper Description

Jumper	Function	Setting
J1	MD0 configurartion of MB9AF312K	Open : User mode Close : Flash programming mode
J2	MD0 configurartion of S6E2DH	Open : User mode Close : Flash programming mode
J3	Multifunction	1-2 : USB VBUS detection/Flash programmng via USB 2-3 : Flash programming via UART0
J4	Multifunction	1-2 : Power from CN2 3-4 : Power from CN3 5-6 : Power from CN4

Device Address(I2C)

Dev.	I2C channel	Address
Audio Codec	MFS6	0x1A
Acceleration Sensor	MFS1	0x0F
Magnetometer Sensor	MFS1	0x0E
Touch Panel of LCD	MFS5	TBD



