



The following document contains information on Cypress products. The document has the series name, product name, and ordering part numbering with the prefix “MB”. However, Cypress will offer these products to new and existing customers with the series name, product name, and ordering part number with the prefix “CY”.

How to Check the Ordering Part Number

1. Go to www.cypress.com/pcn.
2. Enter the keyword (for example, ordering part number) in the **SEARCH PCNS** field and click **Apply**.
3. Click the corresponding title from the search results.
4. Download the Affected Parts List file, which has details of all changes

For More Information

Please contact your local sales office for additional information about Cypress products and solutions.

About Cypress

Cypress is the leader in advanced embedded system solutions for the world's most innovative automotive, industrial, smart home appliances, consumer electronics and medical products. Cypress' microcontrollers, analog ICs, wireless and USB-based connectivity solutions and reliable, high-performance memories help engineers design differentiated products and get them to market first. Cypress is committed to providing customers with the best support and development resources on the planet enabling them to disrupt markets by creating new product categories in record time. To learn more, go to www.cypress.com.



The following document contains information on Cypress products. Although the document is marked with the name "Spansion", the company that originally developed the specification, Cypress will continue to offer these products to new and existing customers.

Continuity of Specifications

There is no change to this document as a result of offering the device as a Cypress product. Any changes that have been made are the result of normal document improvements and are noted in the document history page, where supported. Future revisions will occur when appropriate, and changes will be noted in a document history page.

Continuity of Ordering Part Numbers

Cypress continues to support existing part numbers. To order these products, please use only the Ordering Part Numbers listed in this document.

For More Information

Please contact your local sales office for additional information about Cypress products and solutions.

About Cypress

Cypress (NASDAQ: CY) delivers high-performance, high-quality solutions at the heart of today's most advanced embedded systems, from automotive, industrial and networking platforms to highly interactive consumer and mobile devices. With a broad, differentiated product portfolio that includes NOR flash memories, F-RAM™ and SRAM, Traveo™ microcontrollers, the industry's only PSoC® programmable system-on-chip solutions, analog and PMIC Power Management ICs, CapSense® capacitive touch-sensing controllers, and Wireless BLE Bluetooth® Low-Energy and USB connectivity solutions, Cypress is committed to providing its customers worldwide with consistent innovation, best-in-class support and exceptional system value.

MB90930 Series

16-BIT Microcontroller
F²MC-16LX
Hardware Manual

Errata Sheet



| Page | Section | Description |
|---------------------------------------|---------|--|
| Original document code: CM44-10150-1E | | |
| Revision 1.0 February 2, 2015 | | |
| 125 | 5.3 | <p>Table 5.3-1 Functions of Clock Selection Register (CKSCR) (1 / 3) of WS1 and WS0 bits were corrected to delete the description concerned with PLL stop mode as shown the shading below.</p> <p>(Error)</p> <p>When the switching from the main clock mode to PLL clock mode is executed, the oscillation stabilization wait time is fixed at $2^{14}/\text{HCLK}$ (during operation at an oscillation clock frequency of 4 MHz: approx. 4.1 ms). When the CPU switches from sub clock mode to PLL clock mode or when it returns from PLL stop mode to PLL clock mode, the oscillation stabilization wait time follows the values specified in these bits.</p> <p>Since the PLL clock oscillation stabilization wait time requires $2^{14}/\text{HCLK}$ or more, for switching from sub clock mode to PLL clock mode and transiting to PLL stop mode, set these bits to "10_B" or "11_B".</p> <p>(Correct)</p> <p>When the switching from the main clock mode to PLL clock mode is executed, the oscillation stabilization wait time is fixed at $2^{14}/\text{HCLK}$ (during operation at an oscillation clock frequency of 4 MHz: approx. 4.1 ms). When the CPU switches from sub clock mode to PLL clock mode, the oscillation stabilization wait time follows the values specified in these bits.</p> <p>Since the PLL clock oscillation stabilization wait time requires $2^{14}/\text{HCLK}$ or more, for switching from sub clock mode to PLL clock mode, set these bits to "10_B" or "11_B".</p> |
| 156 | 6.5.4 | <p>The Note was added for the transition to the stop mode as follows.</p> <p>· The transition to the stop mode must be set at Main clock and Sub clock mode.</p> |

| Page | Section | Description |
|------|---------|--|
| 157 | 6.5.4 | <p>The Note was added for the transition to the stop mode was corrected to delete the description concerned with PLL stop mode as shown the shading below.</p> <p>•In PLL stop mode, the main clock and PLL multiplier circuit remain stopped. When the CPU returns from PLL stop mode, therefore, it is necessary to secure the main clock oscillation stabilization wait time and PLL clock oscillation stabilization wait time. The oscillation stabilization wait time in this case bases upon the values set in the oscillation stabilization wait time selection bit in the clock selection register (CKSCR:WS1, WS0), and the main clock oscillation stabilization wait time and PLL clock oscillation stabilization wait time will be counted together. Therefore, set a value to the "CKSCR:WS1, WS0" bit in line with the longest one of the oscillation stabilization wait times. However, because $2^{14}/HCLK$ or more is needed for the PLL clock oscillation stabilization wait time, set "10_B" or "11_B" to the "CKSCR: WS1, WS0" bit.</p> |

| Page | Section | Description |
|------|---------|---|
| 159 | 6.6 | <p>Figure 6.6-1 State Transition Diagram was corrected to delete the description concerned with PLL stop mode and PLL clock oscillation stabilization wait as shown below figure.</p> <p>(Error)</p> <p>*: This mode can be used with the dual clock product.</p> <p>(Correct)</p> <p>*: This mode can be used with the dual clock product.</p> |

| Page | Section | Description | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|------------------------------------|------------|--|-----------------|------------|------------|-----------|-----------------|--------------|-------|-----------------|--------------|-----|-----------|-----------|-----------|-----------|-----------|-----------|-----------|-----------|-----------|---------|---------|-----------------------|----------|------------------------------------|-----------|-----------|-----------|-----------|-----------|-----------------|------------|-----------|-----------|-----|------------|-------|-----------------|--------------|-----|-----------|-----------|-----------|-----------|-----------|-----------|-----------|-----------|-----------|---------|---------|-----------------------|------------------------------------|-----------|-----------|-----------|-----------|
| 160 | 6.6 | <p>Table 6.6-1 Operation States in the Low-power Consumption Mode was corrected the description concerned with PLL stop mode as shown the shading below table.</p> <p>(Error)</p> <table><tr><th>Operation state</th><th>Main clock</th><th>Sub clock</th><th>PLL clock</th><th>CPU</th><th>Peripheral</th><th>Watch</th><th>Time-base timer</th><th>Clock source</th></tr><tr><td>PLL</td><td rowspan="3">Operating</td><td rowspan="3">Operating</td><td rowspan="3">Operating</td><td>Operating</td><td>Operating</td><td rowspan="3">Operating</td><td rowspan="3">Operating</td><td rowspan="5">PLL clock</td></tr><tr><td>PLL sleep</td><td rowspan="4">Stopped</td><td rowspan="4">Stopped</td></tr><tr><td>PLL time-base timer*1</td></tr><tr><td>PLL stop</td></tr><tr><td>PLL oscillation stabilization wait</td><td>Operating</td><td>Operating</td><td>Operating</td><td>Operating</td><td>Operating</td></tr></table> <p>(Correct)</p> <table><tr><th>Operation state</th><th>Main clock</th><th>Sub clock</th><th>PLL clock</th><th>CPU</th><th>Peripheral</th><th>Watch</th><th>Time-base timer</th><th>Clock source</th></tr><tr><td>PLL</td><td rowspan="3">Operating</td><td rowspan="3">Operating</td><td rowspan="3">Operating</td><td>Operating</td><td>Operating</td><td rowspan="3">Operating</td><td rowspan="3">Operating</td><td rowspan="5">PLL clock</td></tr><tr><td>PLL sleep</td><td rowspan="4">Stopped</td><td rowspan="4">Stopped</td></tr><tr><td>PLL time-base timer*1</td></tr><tr><td>PLL oscillation stabilization wait</td><td>Operating</td><td>Operating</td><td>Operating</td><td>Operating</td></tr></table> | Operation state | Main clock | Sub clock | PLL clock | CPU | Peripheral | Watch | Time-base timer | Clock source | PLL | Operating | Operating | Operating | Operating | Operating | Operating | Operating | PLL clock | PLL sleep | Stopped | Stopped | PLL time-base timer*1 | PLL stop | PLL oscillation stabilization wait | Operating | Operating | Operating | Operating | Operating | Operation state | Main clock | Sub clock | PLL clock | CPU | Peripheral | Watch | Time-base timer | Clock source | PLL | Operating | Operating | Operating | Operating | Operating | Operating | Operating | PLL clock | PLL sleep | Stopped | Stopped | PLL time-base timer*1 | PLL oscillation stabilization wait | Operating | Operating | Operating | Operating |
| Operation state | Main clock | Sub clock | PLL clock | CPU | Peripheral | Watch | Time-base timer | Clock source | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL | Operating | Operating | Operating | Operating | Operating | Operating | Operating | PLL clock | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL sleep | | | | Stopped | Stopped | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL time-base timer*1 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL stop | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL oscillation stabilization wait | Operating | Operating | Operating | | | Operating | Operating | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Operation state | Main clock | Sub clock | PLL clock | CPU | Peripheral | Watch | Time-base timer | Clock source | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL | Operating | Operating | Operating | Operating | Operating | Operating | Operating | PLL clock | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL sleep | | | | Stopped | Stopped | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL time-base timer*1 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PLL oscillation stabilization wait | Operating | Operating | Operating | | | Operating | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 163, 164 | 6.8 | <p>6.8 Notes on Using the Low-power Consumption Mode was corrected to add the description concerned with transiting stop mode as shown the shading below.</p> <p>Take notice of the following points when using the low-power consumption mode.</p> <ul style="list-style-type: none">• Transition to the standby mode and interrupts• Notes on the transition to the standby mode• Releasing the standby mode by an interrupt• At transiting the stop mode• At releasing the stop mode• Oscillation stabilization wait time• Switching the clock mode• Notes on accessing to the low-power consumption mode control register (LPMCR) for the transition to the standby mode. <p>■ At Transiting the Stop Mode</p> <p>The transition to the stop mode must be set at Main clock and Sub clock mode.</p> <p>If the mode is transited to the stop mode during PLL clock mode,set the stop mode after transiting Main clock mode once.</p> | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 164 | 6.8 | <p>6.8 Notes on Using the Low-power Consumption Mode was corrected to delete the description concerned with PLL stop mode as shown the shading below.</p> <p>■ Oscillation Stabilization Wait Time</p> <ul style="list-style-type: none">● PLL clock oscillation stabilization wait time <p>When the CPU returns from PLL stop mode, therefore, it is necessary to secure the main clock oscillation stabilization wait time and PLL clock oscillation stabilization wait time. The oscillation stabilization wait time in this case bases upon the values set in the oscillation stabilization wait time selection bit in the clock selection register (CKSCR:WS1, WS0), and the main clock oscillation stabilization wait time and PLL clock oscillation stabilization wait time will be counted together. Therefore, set a value to the "CKSCR:WS1, WS0" bit in line with the longest one of the oscillation stabilization wait times. However, because 214/HCLK or more is needed for the PLL clock oscillation stabilization wait time, set "10B" or "11B" to the "CKSCR: WS1, WS0" bit.</p> | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |

| Page | Section | Description |
|------|---------|---|
| 263 | 9.3.2 | <p>9.3.2 Time-base Timer Control Register (TBTC) of TOBF was corrected to delete the description concerned with PLL stop mode as shown the shading below.</p> <p>(Error)</p> <p>The TBOF bit is cleared by the conditions listed below.</p> <ul style="list-style-type: none">• Writing "0"• Transition to main stop mode• Transition to PLL stop mode• Transition from sub clock mode to main clock mode• Transition from sub clock mode to PLL clock mode• Transition from main clock mode to PLL clock mode• Writing "0" to the TBR bit• Reset <p>Writing "1" has no effect.</p> <p>Reading by read-modify-write (RMW) instructions always reads "1".</p> <p>(Correct)</p> <p>The TBOF bit is cleared by the conditions listed below.</p> <ul style="list-style-type: none">• Writing "0"• Transition to main stop mode• Transition from sub clock mode to main clock mode• Transition from sub clock mode to PLL clock mode• Transition from main clock mode to PLL clock mode• Writing "0" to the TBR bit• Reset <p>Writing "1" has no effect.</p> <p>Reading by read-modify-write (RMW) instructions always reads "1".</p> |

| Page | Section | Description | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|--------------------------------|---------------|--|--|---------------|------------|-------------------------------------|--------------------------------|---|---|---|----------------|---|---|--|--------------------------|---|---|--|-------------------------|--|-------------------------|---|---|---|-----------|---------------|------------|-------------------------------------|--------------------------------|---|---|---|----------------|---|---|--|--------------------------|---|---|--|-------------------------|---|---|---|
| 270 | 9.4.2 | <p>9.4.2 Operation of Time-base Timer was corrected to delete the description concerned with PLL stop mode as shown the shading below.</p> <p>(Error)</p> <p>■ Operation of Time-base Timer</p> <p>The time-base timer consists of an 18-bit counter and uses a main clock as the count clock.</p> <p>While a main clock is input, count operation continues.</p> <p>Time-base counter is cleared by the following conditions:</p> <ul style="list-style-type: none">• Power-on reset• Transition to main stop mode• Transition to PLL stop mode• Transition from main clock mode to PLL clock mode• Transition from sub clock mode to main clock mode• Transition from sub clock mode to PLL clock mode• Setting the TBR bit in the TBTC register to "0". <p>The watchdog timer and interval interrupt functions, which use the output of the time-base timer, are affected by clearing the time-base timer.</p> <p>(Correct)</p> <p>■ Operation of Time-base Timer</p> <p>The time-base timer consists of an 18-bit counter and uses a main clock as the count clock.</p> <p>While a main clock is input, count operation continues.</p> <p>Time-base counter is cleared by the following conditions:</p> <ul style="list-style-type: none">• Power-on reset• Transition to main stop mode• Transition from main clock mode to PLL clock mode• Transition from sub clock mode to main clock mode• Transition from sub clock mode to PLL clock mode• Setting the TBR bit in the TBTC register to "0". <p>The watchdog timer and interval interrupt functions, which use the output of the time-base timer, are affected by clearing the time-base timer.</p> | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 272 | 9.4.2 | <p>Table 9.4-2 Clearing the Time-base Timer Counter and Oscillation Stabilization Wait Time was corrected the description concerned with PLL stop mode as shown the shading below table.</p> <p>(Error)</p> <table><tr><th>Operation</th><th>Counter clear</th><th>TBOF clear</th><th>Oscillation stabilization wait time</th></tr><tr><td>Writing "0" to TBR bit in TBTC</td><td>Y</td><td>Y</td><td>-</td></tr><tr><td>Power-on reset</td><td>Y</td><td>Y</td><td>Main clock oscillation stabilization wait time</td></tr><tr><td>Releasing main stop mode</td><td rowspan="2">Y</td><td rowspan="2">Y</td><td>Main clock oscillation stabilization wait time</td></tr><tr><td>Releasing PLL stop mode</td><td>Main clock oscillation stabilization wait time</td></tr><tr><td>Releasing sub stop mode</td><td>N</td><td>N</td><td>Sub clock oscillation stabilization wait time</td></tr></table> <p>(Correct)</p> <table><tr><th>Operation</th><th>Counter clear</th><th>TBOF clear</th><th>Oscillation stabilization wait time</th></tr><tr><td>Writing "0" to TBR bit in TBTC</td><td>Y</td><td>Y</td><td>-</td></tr><tr><td>Power-on reset</td><td>Y</td><td>Y</td><td>Main clock oscillation stabilization wait time</td></tr><tr><td>Releasing main stop mode</td><td>Y</td><td>Y</td><td>Main clock oscillation stabilization wait time</td></tr><tr><td>Releasing sub stop mode</td><td>N</td><td>N</td><td>Sub clock oscillation stabilization wait time</td></tr></table> | Operation | Counter clear | TBOF clear | Oscillation stabilization wait time | Writing "0" to TBR bit in TBTC | Y | Y | - | Power-on reset | Y | Y | Main clock oscillation stabilization wait time | Releasing main stop mode | Y | Y | Main clock oscillation stabilization wait time | Releasing PLL stop mode | Main clock oscillation stabilization wait time | Releasing sub stop mode | N | N | Sub clock oscillation stabilization wait time | Operation | Counter clear | TBOF clear | Oscillation stabilization wait time | Writing "0" to TBR bit in TBTC | Y | Y | - | Power-on reset | Y | Y | Main clock oscillation stabilization wait time | Releasing main stop mode | Y | Y | Main clock oscillation stabilization wait time | Releasing sub stop mode | N | N | Sub clock oscillation stabilization wait time |
| Operation | Counter clear | TBOF clear | Oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Writing "0" to TBR bit in TBTC | Y | Y | - | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Power-on reset | Y | Y | Main clock oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Releasing main stop mode | Y | Y | Main clock oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Releasing PLL stop mode | | | Main clock oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Releasing sub stop mode | N | N | Sub clock oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Operation | Counter clear | TBOF clear | Oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Writing "0" to TBR bit in TBTC | Y | Y | - | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Power-on reset | Y | Y | Main clock oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Releasing main stop mode | Y | Y | Main clock oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Releasing sub stop mode | N | N | Sub clock oscillation stabilization wait time | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |