



THIS SPEC IS OBSOLETE

Spec No: 002-04894

Spec Title: AN204894 - F2MC-8FX Family MB95330 Series LQFP32  
PGM Adaptor

Replaced by: None

**AN204894****F<sup>2</sup>MC-8FX Family MB95330 Series LQFP32 PGM Adaptor**

This application note describes about the MB95330 LQFP32 PGM adaptor which is developed mainly as an independent on-board programming and debugging tool for the MB95330series LQFP32 package MCU. Its original function of programming and debugging after being installed on the MB95330 series EV board still remains.


**Contents**

1	Introduction.....	2	4.1	Use MB95330 Series USB Programmer to Program.....	10
2	Application Environment.....	3	4.2	Use F <sup>2</sup> MC-8L/8FX SOFTUNE to Program.....	12
2.1	Mother Board.....	3	5	Schematic.....	16
2.2	Debug Tool.....	3	5.1	LQFP32 PGM Adaptor.....	16
2.3	SOFTUNE.....	4	6	PN Definition Rule.....	17
2.4	USB Programmer.....	5	7	PN List of Applicable MCUs.....	17
3	Hardware Connection.....	6	8	More Information.....	17
3.1	Independent Usage.....	6		Document History.....	18
3.2	Used with Mother Board.....	8			
4	Program Function.....	10			

## 1 Introduction

The MB95330 LQFP32 PGM adaptor is developed mainly as an independent on-board programming and debugging tool for the MB95330series LQFP32 package MCU. Its original function of programming and debugging after being installed on the MB95330 series EV board still remains. The picture of MB95330 series LQFP32 PGM adaptor is shown in Figure 1. Four 8-pin connectors are used to connect with MB95330 EV board. The PN of the MB95330 LQFP32 PGM is FMCDC-8FX-PGMA-07032080.

Figure 1. MB95330 LQFP32 PGM Adaptor




## 2 Application Environment

This chapter introduces the application environment of MB95330 LQFP32 PGM adaptor.

### 2.1 Mother Board

The mother board of MB95330 LQFP32 PGM adaptor is MB95330 EV board V1.2, as below picture. It can be gotten from MB95330 motor EV Board (PN: MB2146-440-E).

Figure 2. MB95330 EV Board V1.2



### 2.2 Debug Tool

The debug tool is BGMA (BGM Adaptor), the type of it is MB2146-08-E, as below picture.

Figure 3. BGM Adaptor



## 2.3 SOFTUNE

SOFTUNE is used to program and debug, as software development environment. The version of it is F<sup>2</sup>MC-8L/8FX SOFTUNE Workbench V30L31, as below picture. It can be downloaded from the following website.

[www.cypress.com/8fx-mb95330](http://www.cypress.com/8fx-mb95330)

Figure 4. SOFTUNE Version




## 2.4 USB Programmer

The MB95330 series USB programmer is as below picture. It can be downloaded from the following website.

[www.cypress.com/8fx-mb95330](http://www.cypress.com/8fx-mb95330)

Figure 5. MB95330 Series USB Programmer





### 3 Hardware Connection


This chapter introduces hardware connection when it is used independently or with mother board.

MB95330 LQFP32 PGM adaptor can be used to program and debug independently or after being installed to the mother board. Hardware preparations for each case are described in Section 3.1 and Section 3.2 respectively.

#### 3.1 Independent Usage


When using MB95330 LQFP32 PGM adaptor independently for programming, we should fix MCU on the socket first. Then following steps should be implemented.

Figure 6. Independent Usage Preparation



1. Connect BGMA to PC
2. Connect PGM adaptor board to BGMA
3. Power on the PGM adaptor board, the typical input voltage is 3.3V or 5V.

Figure 7. Hardware Connection for Independent Usage






### 3.2 Used with Mother Board


1. MB95330 series EV board V1.2 is the mother board of LQFP32 PGM adaptor board. First remove the MB95330 chip mounted on the mother board.

Figure 8. Remove MCU from Mother Board




2. Install the MB95F330 chip onto the adaptor socket.

Figure 9. Place MCU on Adaptor Board




3. Fix the adaptor board to the mother board.

Figure 10. Fix Adaptor Board on the Mother Board



4. Connect BGMA to PC.
5. Connect PGM adaptor board to BGMA.
6. Power on the EV-board.

Figure 11. Process 4-6



## 4 Program Function


This chapter introduces programming steps using either MB95330 series USB programmer or F<sup>2</sup>MC-8L/8FX SOFTUNE Workbench V30L31.

MB95330 series MCU can be programmed through MB95330 series USB programmer or F<sup>2</sup>MC-8L/8FX SOFTUNE Workbench V30L31. Section 4.1 and section 4.2 introduce programming steps with MB95330 series USB programmer and F<sup>2</sup>MC-8L/8FX SOFTUNE Workbench V30L31 respectively.

### 4.1 Use MB95330 Series USB Programmer to Program


1. Open MB95330 series USB programmer.
2. Select MCU type (MB95334H/K).
3. Select Hex file by the path: Current project DIR\Debug\ABS.

Figure 12. Select MCU Type and Hex File



4. Click **Full Operation** to start programming.

Figure 13. Click Full Operation




5. The USB programmer also provides single operation, including Erase, Blank Check, Program, Read & Compare and Copy.



## 4.2 Use F<sup>2</sup>MC-8L/8FX SOFTUNE to Program


1. Open a project (E.g. MB95F334 Motor Drive) using SOFTUNE.

Figure 14. Open Demo Project



2. Please select the MCU type to MB95F334K in "Project/Setup Project.../MCU".

Figure 15. Set MCU Type





3. In "Project/Setup Project.../Linker", set **Disposition/Connection** in **Category**, then select **\_INROM01** and click **Set Section....** After that, a dialog window will pop up as shown in Figure 17. Set Const (named @INIT) and Dirconst (named @DIRINIT) as shown in Figure 18 and Figure 19.

Figure 16. Disposition Display Window




Figure 17. Section Setting Window




Figure 18. Set Const Section






Figure 19. Set Dirconst Section



4. Compile project.
5. Start debugging.

Figure 20. Start Debugging



6. Run (code update).
7. End debugging.


**Note:** SOFTUNE environment can also be used to debug, however if users only need to do programming, DO NOT set any breakpoint before step 6, or error code will be programmed.

## 5 Schematic

This chapter demonstrates schematic of MB95330 PGM adaptor.

### 5.1 LQFP32 PGM Adaptor

Figure 21. LQFP32 PGM Adaptor Schematic



## 6 PN Definition Rule

The part number of PGM adaptor is FMCDC-8FX-PGMA-07032080.

07 → LQFP,

032 → Pin count (e.g. 032 means 32pin MCU),

080 → Lead pitch (e.g. 0.80mm means lead pitch 080).

## 7 PN List of Applicable MCUs

MCU Series	Part Number	Footprint
MB95330 series	MB95F332HPMC-G-SNE2	LQFP32
	MB95F332KPMC-G-SNE2	
	MB95F333HPMC-G-SNE2	
	MB95F333KPMC-G-SNE2	
	MB95F334HPMC-G-SNE2	
	MB95F334KPMC-G-SNE2	

## 8 More Information

For more information on Cypress MB95330 products, please visit the following website:

[www.cypress.com/documentation/software-and-drivers/f2mc-8fx-mb95200-series-bgm-adaptor-mb2146-08-e-operation-manual](http://www.cypress.com/documentation/software-and-drivers/f2mc-8fx-mb95200-series-bgm-adaptor-mb2146-08-e-operation-manual)

[www.cypress.com/documentation/application-notes/mb95330-programmer-adaptor-mb95330](http://www.cypress.com/documentation/application-notes/mb95330-programmer-adaptor-mb95330)



## Document History

Document Title: AN204894 - F<sup>2</sup>MC-8FX Family MB95330 Series LQFP32 PGM Adaptor

Document Number: 002-04894

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	—	HUAL	11/03/2009	Initial release.
			11/26/2009	Modified.
*A	5255526	HUAL	06/28/2016	Migrated Spansion Application Note from MCU-AN-500061-E-11 to Cypress format. Link to Hardware doesn't exist and this AN to be Obsolete.

## Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

## Products

ARM® Cortex® Microcontrollers	<a href="http://cypress.com/arm">cypress.com/arm</a>
Automotive	<a href="http://cypress.com/automotive">cypress.com/automotive</a>
Clocks & Buffers	<a href="http://cypress.com/clocks">cypress.com/clocks</a>
Interface	<a href="http://cypress.com/interface">cypress.com/interface</a>
Lighting & Power Control	<a href="http://cypress.com/powerpsoc">cypress.com/powerpsoc</a>
Memory	<a href="http://cypress.com/memory">cypress.com/memory</a>
PSoC	<a href="http://cypress.com/psoc">cypress.com/psoc</a>
Touch Sensing	<a href="http://cypress.com/touch">cypress.com/touch</a>
USB Controllers	<a href="http://cypress.com/usb">cypress.com/usb</a>
Wireless/RF	<a href="http://cypress.com/wireless">cypress.com/wireless</a>

## PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#)

## Cypress Developer Community

[Forums](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

## Technical Support

[cypress.com/support](http://cypress.com/support)

PSoC is a registered trademark and PSoC Creator is a trademark of Cypress Semiconductor Corporation. All other trademarks or registered trademarks referenced herein are the property of their respective owners.



Cypress Semiconductor  
198 Champion Court  
San Jose, CA 95134-1709

Phone : 408-943-2600  
Fax : 408-943-4730  
Website : [www.cypress.com](http://www.cypress.com)

© Cypress Semiconductor Corporation, 2009-2016. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit [cypress.com](http://cypress.com). Other names and brands may be claimed as property of their respective owners.