

F²MC-8FX Family MB95310 Series LQFP80 PGM Adaptor

This application note describes about the MB95310 LQFP80 PGM adaptor which is developed mainly as an independent on-board programming and debugging tool for MB95310 series LQFP80 package MCU. Its original function of programming and debugging after being installed on the MB95310 series EV board still remains.


Contents

1	Introduction.....	1	4.1	Use MB95310 Series USB Programmer to Program.....	8
2	Application Environment.....	2	4.2	Use F ² MC-8L/8FX SOFTUNE to Program.....	9
2.1	Mother Board	2	5	Schematic.....	13
2.2	Debug Tool	2	5.1	LQFP80 PGM Adaptor.....	13
2.3	SOFTUNE	3	6	PN Definition Rule	13
2.4	USB Programmer.....	3	7	PN List of Applicable MCUs	14
3	Hardware Connection.....	4		Document History.....	15
3.1	Independent Usage.....	4			
3.2	Used with Mother Board	6			
4	Program Function	8			

1 Introduction

The MB95310 LQFP80 PGM adaptor is developed mainly as an independent on-board programming and debugging tool for MB95310 series LQFP80 package MCU. Its original function of programming and debugging after being installed on the MB95310 series EV board still remains. The picture of MB95310 series LQFP80 PGM adaptor is shown in Figure 1. Four 20-pin connectors are used to connect with MB95310 EV board. The PN of the MB95310 LQFP80 PGM is FMCDC-8FX-PGMA-07080050.

Figure 1. MB95310 LQFP80 PGM Adaptor




2 Application Environment

This chapter introduces application environment of MB95310 LQFP80 PGM adaptor.

2.1 Mother Board

The mother board of MB95310 LQFP80 PGM adaptor is MB95310 EV board V1.1, as below picture. It can be gotten from MB95310 LCD EV Board (PN: MB2146-450-E).

Figure 2. MB95310 EV Board V1.1



2.2 Debug Tool

The debug tool is BGMA (BGM Adaptor), the type of it is MB2146-08-E, as below picture.

Figure 3. BGM Adaptor



2.3 SOFTUNE

SOFTUNE is used to program and debug, as software development environment. The version of it is F²MC-8L/8FX SOFTUNE Workbench V30L31, as below picture. It can be downloaded from the following website.

Figure 4. SOFTUNE Version



2.4 USB Programmer

The MB95310 series USB programmer is not supported by far and will be updated later.

3 Hardware Connection


This chapter introduces hardware connection when it is used independently or with mother board.

MB95310 LQFP80 PGM adaptor can be used to program and debug independently or after being installed to the mother board. Hardware preparations for each case are described in Section 3.1 and Section 3.2 respectively.

3.1 Independent Usage


When using MB95310 LQFP80 PGM adaptor independently for programming, we should fix MCU on the socket first. Then following steps should be implemented.

Figure 5. Independent Usage Preparation



1. Connect BGMA to PC.
2. Connect PGM adaptor board to BGMA.
3. Power on the PGM adaptor board, the typical input voltage is 3.3V.


Figure 6. Hardware Connection for Independent Usage



3.2 Used with Mother Board


1. MB95310 series EV board V1.1 is the mother board of LQFP80 PGM adaptor board. First remove the MB95310 chip mounted on the mother board.

Figure 7. Remove MCU from Mother Board




2. Install the MB95F310 chip onto the adaptor socket.

Figure 8. Place MCU on Adaptor Board




3. Fix the adaptor board to the mother board.

Figure 9. Fix Adaptor Board on the Mother Board



4. Connect BGMA to PC.
5. Connect PGM adaptor board to BGMA.
6. Power on the EV-board.

Figure 10. Process 4-6



4 Program Function

This chapter introduces programming steps using either MB95310 series USB programmer or F²MC-8L/8FX SOFTUNE Workbench V30L31.

MB95310 series MCU can be programmed through MB95310 series USB programmer or F²MC-8L/8FX SOFTUNE Workbench V30L31. Section 4.1 and section 4.2 introduce programming steps with MB95310 series USB programmer and F²MC-8L/8FX SOFTUNE Workbench V30L31 respectively.


4.1 Use MB95310 Series USB Programmer to Program

This function is not support by far and will be updated later.

4.2 Use F²MC-8L/8FX SOFTUNE to Program


1. Open a project (E.g. MB95F310 LCD EV-Board project) using SOFTUNE.

Figure 11. Open Demo Project



2. Please select the MCU type to MB95F310 in "Project/Setup Project.../MCU".

Figure 12. Set MCU Type



3. In "Project/Setup Project.../Linker", set **Disposition/Connection** in Category, then select **_INROM01** and click **Set Section...** After that, a dialog window will pop up as shown in Figure 15 below. Set **Const (named @INIT)** and **Dirconst (named @DIRINIT)** as shown in Figure 16 and Figure 17.

Figure 13. Disposition Display Window




Figure 14. Section Setting Window




Figure 15. Set Const Section






Figure 16. Set Dirconst Section



4. Compile project.
5. Start debugging.

Figure 17. Start Debugging



6. Run (code update).
7. End debugging.


Note: SOFTUNE environment can also be used to debug, however if users only need to do programming, DO NOT set any breakpoint before step 6, or error code will be programmed.

5 Schematic

This chapter demonstrates schematic of MB95310 PGM adaptor.

5.1 LQFP80 PGM Adaptor

Figure 18. LQFP80 PGM Adaptor Schematic



6 PN Definition Rule

The part number of PGM adaptor is FMCDC-8FX-PGMA-07080050.

07 → LQFP

080 → Pin count (e.g. 080 means 80 pin MCU),

050 → Lead pitch (e.g. 0.50mm means lead pitch 050).

7 PN List of Applicable MCUs

MCU Series	Part Number	Footprint
MB95310 series	MB95F314E MB95F314L MB95F316E MB95F316L MB95F318E MB95F318L	LQFP80

Document History

Document Title: AN204947 - F²MC-8FX Family MB95310 Series LQFP80 PGM Adaptor

Document Number: 002-04947

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	—	HUAL	12/17/2009	Initial release.
*A	5256962	HUAL	09/15/2016	Migrated Spansion Application note from MCU-AN-500068-E-10 to Cypress format.
*B	5843346	AESATMP9	08/03/2017	Updated logo and copyright.

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

ARM® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Internet of Things	cypress.com/iot
Memory	cypress.com/memory
Microcontrollers	cypress.com/mcu
PSoC	cypress.com/psoc
Power Management ICs	cypress.com/pmic
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless Connectivity	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#) | [PSoC 6](#)

Cypress Developer Community

[Forums](#) | [WICED IOT Forums](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support

All other trademarks or registered trademarks referenced herein are the property of their respective owners.



Cypress Semiconductor
198 Champion Court
San Jose, CA 95134-1709

© Cypress Semiconductor Corporation, 2009-2017. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.