

F²MC-8FX Family MB95390 Series LQFP48 PGM Adaptor

Associated Part Family: MB95390 Series

The MB95390 LQFP48 PGM adaptor is developed mainly as an independent on-board programming and debugging tool for the MB95390series LQFP48 package MCU.


Contents

1	Introduction.....	1	5	Schematic.....	13
2	Application Environment.....	2	5.1	LQFP48 PGM Adaptor.....	13
2.1	Mother Board	2	6	PN Definition Rule	14
2.2	Debug Tool	2	7	PN List of Applicable MCUs	14
2.3	SOFTUNE	3	8	More Information	14
2.4	USB Programmer.....	3		Document History.....	15
3	Hardware Connection.....	4		Worldwide Sales and Design Support.....	16
3.1	Independent Usage.....	4		Products.....	16
3.2	Used with Mother Board	5		PSoC® Solutions	16
4	Program Function	7		Cypress Developer Community.....	16
4.1	Use MB95390 Series USB Programmer to Program.....	7		Technical Support	16
4.2	Use F ² MC-8L/8FX SOFTUNE to Program.....	9			

1 Introduction

The MB95390 LQFP48 PGM adaptor is developed mainly as an independent on-board programming and debugging tool for the MB95390series LQFP48 package MCU. Its original function of programming and debugging after being installed on the MB95330 series EV board still remains. The picture of MB95390 series LQFP48 PGM adaptor is shown in [Figure 1-1](#). Four 8-pin connectors are used to connect with MB95330 EV board. The PN of the MB95390 LQFP48 PGM is FMCDC-8FX-PGMA-07048050.

Figure 1-1. MB95390 LQFP48 PGM Adaptor




2 Application Environment

This chapter introduces application environment of MB95390 LQFP48 PGM adaptor.

2.1 Mother Board

The mother board of MB95390 LQFP48 PGM adaptor is MB95330 EV board V1.3, as below picture. It can be gotten from MB95330 motor EV board (PN: MB2146-440-E).

Figure 2-1. MB95330 EV Board V1.3



2.2 Debug Tool

The debug tool is BGMA (BGM Adaptor), the type of it is MB2146-08-E, as below picture.

Figure 2-2. BGM Adaptor



2.3 SOFTUNE

SOFTUNE is used to program and debug, as software development environment. The version of it is F²MC-8L/8FX SOFTUNE Workbench V30L31, as below picture. It can be downloaded from the following website.

<http://www.Cypress.com/Products/microcontrollers/8-bit-Proprietary-Core/Pages/mb95f398.aspx>

Figure 2-3. SOFTUNE Version




2.4 USB Programmer

The MB95390 series USB programmer is as below picture. It can be downloaded from the following website.

<http://www.Cypress.com/Products/microcontrollers/8-bit-Proprietary-Core/Pages/mb95f398.aspx>

Figure 2-4. MB95390 Series USB Programmer



3 Hardware Connection


This chapter introduces hardware connection when it is used independently or with mother board.

MB95390 LQFP48 PGM adaptor can be used to program and debug independently or after being installed to the mother board. Hardware preparations for each case are described in [Section 3.1](#) and [Section 3.2](#) respectively.

3.1 Independent Usage


When using MB95390 LQFP48 PGM adaptor independently for programming, we should fix MCU on the socket first. Then following steps should be implemented.

Figure 3-1. Independent Usage Preparation



1. Connect BGMA to PC
2. Connect PGM adaptor board to BGMA
3. Power on the PGM adaptor board, the typical input voltage is 3.3V or 5V.


Figure 3-2. Hardware Connection for Independent Usage



3.2 Used with Mother Board


1. MB95330 series EV board V1.3 is the mother board of MB95390 LQFP48 PGM adaptor board. First remove the MB95330 chip mounted on the mother board.

Figure 3-3. Remove MCU from Mother Board




2. Install the MB95F390 chip onto the adaptor socket.

Figure 3-4. Place MCU on Adaptor Board




3. Fix the adaptor board to the mother board.

Figure 3-5: Fix Adaptor Board on the Mother Board



4. Connect BGMA to PC.
5. Connect PGM adaptor board to BGMA.
6. Power on the EV-board.

Figure 3-6. Process 4-6



4 Program Function


This chapter introduces programming steps using either MB95390 series USB programmer or F²MC-8L/8FX SOFTUNE Workbench V30L31.

MB95390 series MCU can be programmed through MB95390 series USB programmer or F²MC-8L/8FX SOFTUNE Workbench V30L31. Section 4.1 and section 4.2 introduce programming steps with MB95390 series USB programmer and F²MC-8L/8FX SOFTUNE Workbench V30L31 respectively.

4.1 Use MB95390 Series USB Programmer to Program


1. Open MB95390 series USB programmer.
2. Select MCU type (MB95398H/K).
3. Select Hex file by the path: Current project DIR\Debug\ABS.

Figure 4-1. Select MCU Type and Hex File



- Click **Full Operation** to start programming.

Figure 4-2. Click Full Operation




- The USB programmer also provides single operation, including Erase, Blank Check, Program, Read & Compare and Copy.

4.2 Use F²MC-8L/8FX SOFTUNE to Program


1. Open a project (E.g. Test) using SOFTUNE.

Figure 4-3. Open Demo Project



2. Please select the MCU type to MB95F398K in "Project/Setup Project.../MCU".

Figure 4-4: Set MCU Type



3. In "Project/Setup Project.../Linker", set **Disposition/Connection** in **Category**, then select **_INROM01** and click **Set Section...** After that, a dialog window will pop up as shown in Figure 4-6 below. Set Const (named @INIT) and Dirconst (named @DIRINIT) as shown in Figure 4-7 and Figure 4-8.

Figure 4-5. Disposition Display Window




Figure 4-6. Section Setting Window




Figure 4-7. Set Const Section






Figure 4-8. Set Dirconst Section



4. Compile project.
5. Start debugging.

Figure 4-9. Start Debugging



6. Run (code update).
7. End debugging.


Note: SOFTUNE environment can also be used to debug, however if users only need to do programming, DO NOT set any breakpoint before step 6, or error code will be programmed.

5 Schematic

This chapter demonstrates schematic of MB95390 PGM adaptor.

5.1 LQFP48 PGM Adaptor

Figure 5-1. LQFP48 PGM Adaptor Schematic



6 PN Definition Rule

The part number of PGM adaptor is FMCDC-8FX-PGMA-07048050.

07 → LQFP

048 → Pin count (e.g. 048 means 48pin MCU)

050 → Lead pitch (e.g. 050 means lead pitch 0.50mm)

7 PN List of Applicable MCUs

MCU Series	Part Number	Footprint
MB95390 series	MB95F394H	LQFP48
	MB95F394K	
	MB95F396H	
	MB95F396K	
	MB95F398H	
	MB95F398K	

8 More Information

For more information on BGM Adaptor, please visit our website:

<http://www.cypress.com/documentation/development-kitsboards/mb2146-08-e>

Please contact your local support team for any technical question.

Document History

Document Title: AN205064 - F²MC-8FX Family MB95390 Series LQFP48 PGM Adaptor

Document Number: 002-05064

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	—	HUAL	04/19/2010	Initial release
*A	5260376	HUAL	05/27/2016	Migrated Spansion Application Note “MCU-AN-500085-E-10” to Cypress format.

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

ARM® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Lighting & Power Control	cypress.com/powerpsoc
Memory	cypress.com/memory
PSoC	cypress.com/psoc
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless/Rf	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#)

Cypress Developer Community

[Forums](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support

PSoC is a registered trademark and PSoC Creator is a trademark of Cypress Semiconductor Corporation. All other trademarks or registered trademarks referenced herein are the property of their respective owners.

 <p>CYPRESS Embedded in Tomorrow™</p>	Cypress Semiconductor		Phone : 408-943-2600
	198 Champion Court		Fax : 408-943-4730
	San Jose, CA 95134-1709		Website : www.cypress.com

© Cypress Semiconductor Corporation, 2010-2016. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.