

Please note that Cypress is an Infineon Technologies Company.

The document following this cover page is marked as “Cypress” document as this is the company that originally developed the product. Please note that Infineon will continue to offer the product to new and existing customers as part of the Infineon product portfolio.

Continuity of document content

The fact that Infineon offers the following product as part of the Infineon product portfolio does not lead to any changes to this document. Future revisions will occur when appropriate, and any changes will be set out on the document history page.

Continuity of ordering part numbers

Infineon continues to support existing part numbers. Please continue to use the ordering part numbers listed in the datasheet for ordering.

Objective

This code example demonstrates the adjustable voltage reference capability of the CapSense® Sigma Delta (CSD) Comparator on PSoC® 4 S-Series.

Overview

This code example uses a comparator to control two LEDs. The Comparator (CSD) Component used in the design has a programmable voltage reference. Button presses increment the reference voltage on the Comparator in 1-V steps up to 4 V. An external voltage supply provides the voltage that is being compared against the reference. When the reference voltage is lower than the external supply voltage, the green LED turns ON. If button presses increment the reference voltage so that the reference is greater than the external supply voltage, the red LED turns ON. Alternatively, adjusting the external power supply value will also change the LED.

Requirements

Tool: PSoC Creator™ 4.2

Programming Language: C (Arm® GCC 5.4.1 and Arm MDK 5.22)

Associated Parts: PSoC 4000S, PSoC 4100S, PSoC 4700S

Related Hardware: [CY8CKIT-041-40xx](#), [CY8CKIT-041-41xx](#), [CY8CKIT-145-40xx](#)

Hardware Setup

This example requires the use of an external voltage source capable of supplying 1.8 V. If an adjustable voltage supply is used, ensure that the voltage applied to the device does not exceed 5 V.

Software Setup

None.


Operation

1. Plug the CY8CKIT-041-40xx kit board into your computer's USB port.
2. Build the project and program it into the PSoC 4 MCU device. Choose **Debug > Program**. For more information on device programming, see PSoC Creator Help.
3. Connect the ground lead of an external voltage supply to a GND pin on the kit GPIO.
4. Connect the positive lead of a 1.8-V external voltage supply to pin Vplus.
5. Connect VDD to the Vminus pin.
Alternatively, a 4-V external supply can be connected to the Vminus pin.
6. Press **SW2** and observe the green LED turn ON.
Pressing SW2 thrice will turn the red LED ON as the reference voltage resets to 1 V.
7. If using an adjustable voltage supply, change the 1.8-V signal to 2.5 V and perform step 6. Notice that the LED color changes every two button presses.

Design and Implementation

The Comparator (CSD) Component compares two voltages and outputs a value based on the result of the comparison. As shown in [Figure 1](#), the Comparator (CSD) Component has two input terminals; a positive terminal and a reference terminal (labeled with the negative sign). When the voltage level detected at the positive terminal is larger than the voltage level at the reference terminal, the comparator outputs a non-zero signal. The inverse is also true. If the voltage at the positive terminal is less than the reference voltage, the comparator outputs zero.

Figure 2. Top Schematic



To visually display the result of the comparison, firmware checks the value of the comparison result and turns on an LED to indicate the status. If the comparison returns non-zero, then the positive terminal voltage is greater than the reference voltage and the green LED turns on. If the comparison returns zero, then the positive terminal voltage is less than the reference voltage and the red LED turns on.

The Comparator (CSD) Component also has a programmable reference voltage. To demonstrate this, an on-kit button is used to increment the reference voltage in 1-V steps from 1 V up to 4 V. On the rising edge of each press, firmware writes the new reference voltage with the `Comp_SetVoltageTap` function call. The argument to the function is an integer value between 1 and 32. [Equation 1](#) shows the conversion formula from the desired reference voltage to the argument value.

$$tap\ value = \frac{Desired\ Reference\ Voltage\ (mV)}{Comp_VREF_STEP_MVOLTS} \quad \text{Equation 1}$$

As the button presses increment in the voltage from 1 V to 4 V, the LEDs on the kit change as the comparison result changes. When the button is pressed while the reference is at 4 V, the reference voltage resets to 1 V.

Components and Settings

Table 1 lists the PSoC Creator Components used in this example, how they are used in the design, and the non-default settings required so they function as intended.


Table 1. PSoC Creator Components

Component	Instance Name	Purpose	Non-default Settings
Comparator (CSD)	Comp	Enables comparison of voltage levels	See Figure 2.
Analog Pin	Vplus	Enables analog voltage input to comparator	Default settings only
	Vminus		
Digital Input Pin	pushButton	Enables read of button press	Drive Mode: Resistive pull up Disable HW connection
Digital Output Pin	redLed	Enables writing to LEDs	Disable HW Connection
	greenLed		
	CmpOut	Enables measurement of comparison result	Default settings only

For information on the hardware resources used by a Component, see the Component datasheet.

Figure 2 highlights the non-default settings for the TCPWM Component.

Figure 3. CSD_Comp_P4 Configuration



Reusing This Example

This code example is designed for the PSoC 4000S family and associated CY8CKIT-041-40xx kit. The design is easily portable to other PSoC devices and kits, typically by simply changing the device and Component pin assignments.

To switch from the CY8CKIT-041-40xx to other PSoC Pioneer kits, select the appropriate device with the Device Selector (**Project > Device Selector**). [Table 2](#) lists the device number for each pioneer kit.

Note: If the assigned Component's pins are not as shown in [Table 2](#) or you want to overwrite the existing pin assignment, double-click the project's *Design Wide Resources* file in the Workspace Explorer window and assign the pins. In some cases, a resource used by a code example is not supported on another device. In that case the example will not work. If you build the code targeted at such a device, you will get errors. See the device datasheet for information on what a particular device supports.

Table 3. Pin Assignments for Different Kits

Pin Name	Pin Assignments by Development Kit		
	CY8CKIT-041-40xx (CY8C4045AZI-S413)	CY8CKIT-041-41xx (CY8C4146AZI-S433)	CY8CKIT-145-40xx (CY8C4045AZI-S413)
Vplus	P2[2]	P2[2]	P2[2]
Vminus	P4[0]	P4[0]	P4[0]
CmpOut	P2[0]	P2[0]	P2[5]
redLed	P3[4]	P3[4]	P3[4]
greenLed	P2[6]	P2[6]	P2[0]
pushButton	P0[7]	P0[7]	P0[7]

Related Documents

Application Notes		
AN79953	Getting Started with PSoC 4	Describes PSoC 4 and how to build a first PSoC Creator project.
PSoC Creator Component Datasheets		
Comparator (CSD)	Supports CSD based adjustable voltage reference comparator	
Pins	Supports connection of hardware resources to physical pins	
Device Documentation		
PSoC 4 Datasheets	PSoC 4000S Family: PSoC 4 Architecture Technical Reference Manual (TRM)	
	PSoC 4100S and PSoC 4100S Plus: PSoC 4 Architecture Technical Reference Manual (TRM)	
Development Kit (DVK) Documentation		
CY8CKIT-041-40xx PSoC 4 S-Series Pioneer Kit		
CY8CKIT-041-41xx PSoC 4100S CapSense Pioneer Kit		
CY8CKIT-145-40xx PSoC 4000S CapSense Prototyping Kit		

Document History

Document Title: CE210197 - Adjustable Reference Comparator

Document Number: 002-10197

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	5142921	AKSM	02/19/2016	New code example
*A	6159008	BFMC	07/26/2018	Updated the template Expanded Operation and Overview sections Added CY8CKIT145-040xx to supported devices Fixed hyperlinks Updated images to match the updated Comparator Component

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

Arm® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Internet of Things	cypress.com/iot
Memory	cypress.com/memory
Microcontrollers	cypress.com/mcu
PSoC	cypress.com/psoc
Power Management ICs	cypress.com/pmic
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless Connectivity	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#) | [PSoC 6 MCU](#)

Cypress Developer Community

[Community](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support

All other trademarks or registered trademarks referenced herein are the property of their respective owners.



Cypress Semiconductor
198 Champion Court
San Jose, CA 95134-1709

© Cypress Semiconductor Corporation, 2016-2018. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. No computing device can be absolutely secure. Therefore, despite security measures implemented in Cypress hardware or software products, Cypress does not assume any liability arising out of any security breach, such as unauthorized access to or use of a Cypress product. In addition, the products described in these materials may contain design defects or errors known as errata which may cause the product to deviate from published specifications. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.