

The Watch Counter (WC) is configured to generate an interrupt request once per second. The interrupt toggles the state of the LED pin.

Overview

The component is configured to generate interrupts and use the WCCK2 input clock source. The firmware sets up the input clock divider and Watch Counter reload value to generate the interrupt once every second. The interrupt callback function simply toggles the state of the green LED (0.5 Hz).

Requirements

Tool: PSoC Creator 4.0 and Peripheral Driver Library (PDL) 2.1


Programming Language: C (GCC 4.9.3)

Associated Parts: All S6E1A parts

Related Hardware: [FM0-V48-S6E1A1](#)

Design

The schematic file includes the WC and a GPIO component, renamed as shown below.



The firmware performs following functions:

1. Initialize the LED (off)
2. Select the input clock source and prescaler value
3. Start the prescaler input clock
4. Set up the WC to interrupt once per second
5. Start the Watch Counter (the interrupt toggles the LED)

Design Considerations

Pin Selection

The project includes control files to automatically place the LED IO onto the appropriate pin for the supported kit hardware. To change the pin selection, delete the control file or over-ride the control file selections in the Design Wide Resources Pin Editor.

PDL Installation

The project assumes that you have installed the PDL in the location specified in the **Project Management** panel of the **Tools > Options** dialog. If that location is incorrect you will see the build error "The given PDL path is invalid. Unable to find required PDSC file." To correct this problem in a newly-created project, open the **Project > Properties** dialog and enter the correct path to the PDL. To avoid the problem in projects you create in the future, make sure you put the correct path in the **Tools > Options** dialog.

Hardware Setup

The LED GPIO is connected to a green LED.

Table 1 lists the pin connection required to use this code example on an FM0+ kit.

Table 1. List of Pins

Pin	FM0-V48-S6E1A1
Green_LED:GPIO	P61

Components

Table 2 lists the PSoC Creator Components used in this example, as well as the hardware resources used by each.

Table 2. List of PSoC Creator Components

Component	Version	Hardware Resources
PDL_WCC	1.0	Watch Counter block
PDL_GPIO	1.0	GPIO pin

Parameter Settings

The GPIO component uses the default parameter settings. Only the component instance name has been changed for readability.

The PDL_WC Component uses default parameter settings, with these exceptions.

Table 3: Component Settings

Tab	Setting	Value
None	Name	WC
Basic	enCntClk	WCCk2 clock source
	enIrqEnable	True
	bTouchNvic	True

Note that the counter clock (enCntClk) is a selection of a source from the prescaler (selects one of four choices). The prescaler is set up in firmware.

Operation

After programming and reset, the LED state toggles every second (0.5 Hz rate).

Related Documents

Table 4 lists relevant application notes, code examples, knowledge base articles, device datasheets, and Component datasheets.

Table 4. Related Documents

PSoC Creator Component Datasheets	
PDL_WC	Watch Counter with selectable and scalable input clock source (right-click on the Component to access)
PDL_GPIO	Supports firmware access to physical pins (right-click on the Component to access)
Device Documentation	
S6E1A	FM0+ S6E1A-Series 5 V Robust ARM® Cortex®-M0+ Microcontroller (MCU) Family
Development Kit (DVK) Documentation	
FM0-V48-S6E1A1	ARM® Cortex®-M0+ FM0+ MCU Evaluation Board

Document History

Document Title: CE216970 – FM0+ Watch Counter Code Example

Document Number: 002-16970

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	5469329	YFS	10/10/16	New Code Example.
*A	5776729	YFS	6/16/17	Added search keyword so that user can quickly find Code Examples from the component instance popup menu. Updated logo and copyright date.
*B	5988609	YFS	12/8/17	Removing S6E1B support.

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

ARM® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Lighting & Power Control	cypress.com/powerpsoc
Memory	cypress.com/memory
PSoC	cypress.com/psoc
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless/RF	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#)

Cypress Developer Community

[Forums](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support



Cypress Semiconductor Phone : 408-943-2600
 198 Champion Court Fax : 408-943-4730
 San Jose, CA 95134-1709 Website : www.cypress.com

© Cypress Semiconductor Corporation, 2016-2017. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spanion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spanion, the Spanion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.