

CYPRESS™ Programmer

release notes

Version

4.0.1

About this document

Scope and purpose

Thank you for your interest in CYPRESS™ Programmer. This document lists the installation requirements, software and hardware updates, limitations, and known issues with the tool.

Document conventions

Convention	Explanation
Bold	Emphasizes heading levels, column headings, menus and sub-menus
<i>Italics</i>	Denotes file names and paths.
<code>Courier New</code>	Denotes APIs, functions, interrupt handlers, events, data types, error handlers, file/folder names, directories, command line inputs, code snippets
File > New	Indicates that a cascading sub-menu opens when you select a menu item

References

Refer to the following for more information as needed:

- Programming solutions website:
[Infineon website](#)
- Original OpenOCD sources v0.11.0:
<https://sourceforge.net/projects/openocd/files/openocd/0.11.0/>
- OpenOCD v0.11.0 release notes:
<https://openocd.org/openocd-0-11-0-released.html>
- OpenOCD v0.11.0 user guide:
<http://openocd.org/doc-release/pdf/openocd.pdf>

Table of contents

1	Product Description.....	3
1.1	What's Included	3
1.2	Supported Operating Systems	3
1.3	Supported Kits.....	4
1.4	Supported product families.....	5
1.5	Supported programming hardware	5
2	Installation.....	6
3	Issues and Defects	7
3.1	Resolved Issues	7
3.2	Known Problems and Solutions	7
3.3	Known Limitations	9

1 Product Description

CYPRESS™ Programmer is a flexible, cross-platform application used to program CYPRESS™ devices. It can program, erase, verify, and read the flash of the target device.

CYPRESS™ Programmer is both a command-line tool and a GUI tool. It is based on OpenOCD v0.11.0 software with CYPRESS™ enhancements, fixes, and updates.

CYPRESS™ Programmer 4.0.1 delivers:

- Support for WLC1 (Wireless Charging ICs) devices
- Blocking access to the SFlash User Rows on PMG1 and WLCx devices

CYPRESS™ Programmer 4.0 delivers:

- Support for PSoC™ 64 secure targets with 1M, 2M, 512K flash size and kits
- Support for PSoC™ 62 and PSoC™ 61 MCU targets with 256K flash size and kits
- Support for single-core PSoC™ 61 and PSoC™ 62 devices with 2M and 512K flash size
- Support for EZ-PD™ PMG1-S0, S1, S2, S3 devices and kits
- Support of PSoC™ 4100S Max targets and kits
- Support for chip protection and SFlash programming in PSoC™ 4000S, PSoC™ 4100S, PSoC™ 4100S Plus, PSoC™ 4100S Max, and PSoC™ 4500S devices
- Support for new IoT Bluetooth® kits
- Ability to specify the OpenOCD Telnet port number
- Bug fixes

1.1 What's Included

- CYPRESS™ Programmer graphical user interface 4.0.1: This tool provides a graphical user interface to program, erase, verify, and read the flash of the target device.
- CYPRESS™ OpenOCD 4.3.1: This tool provides debugging and in-system programming functionality for target devices in CYPRESS™ Programmer.
- KitProg3 2.21: This tool provides communication firmware that supports both CMSIS-DAP and DAPLink programming and debugging.
- CyBridge library 3.2.0: This is a cross-platform library providing access to KitProg3, MiniProg4, and UART devices via high-level API.
- ChipLoad 1.6.1: This tool allows to download firmware to WICED IoT Bluetooth® platforms

1.2 Supported Operating Systems

- Windows 10 (x64) and Windows 7 (x64)
- macOS X 10.14 (x64) and macOS X 10.15 (x64), macOS 11 (x64)
- Ubuntu 18.04 LTS (x64) and Ubuntu 20.04 (x64)

1.3 Supported Kits

- PSoC™ 6 Pioneer and Prototyping kits
 - CY8CKIT-062-WiFi-BT
 - CY8CKIT-062-BLE
 - CY8CPROTO-062-4343W
 - CY8CPROTO-063-BLE
 - CY8CKIT-062S2-43012
 - CY8CPROTO-062S2-43012
 - CY8CPROTO-062S3-4343W
 - CY8CEVAL-062S2
 - CY8CKIT-062S4
- Wi-Fi kits
 - CYW9P62S1-43438EVB-01
 - CYW9P62S1-43012EVB-01
- PSoC™ 64 kits
 - CY8CPROTO-064S1-SB
 - CY8CPROTO-064B0S3
 - CY8CPROTO-064B0S1-BLE
 - CY8CKIT-064B0S2-4343W
 - CY8CEVAL-064SXS2
- PSoC™ 4 kits
 - CY8CKIT-041-40XX
 - CY8CKIT-041-41XX
 - CY8CKIT-145-40XX
 - CY8CKIT-149
 - CY8CKIT-045S
 - CY8CKIT-041S-MAX
- PMG1 kits
 - CY7110
 - CY7111
 - CY7112
 - CY7113
- IoT Wi-Fi kits and boards
 - BCM94343WWCD2
 - BCM943362WCD4
 - BCM943438WCD1
 - BCM943364WCD1
 - CYW943012EVB-04
 - CYW943340WCD1

Table of contents

- CYW943455EVB-02
- CYW943907AEVAL1F (Rev 1.1)
- CYW943907WAE4
- CYW954907AEVAL1F
- IoT Bluetooth® kits and boards
 - CYBT-213043-EVAL
 - CYBT-213043-MESH
 - CYBT-343026-EVAL
 - CYBT-413055-EVAL
 - CYBT-423054-EVAL
 - CYBT-483056-EVAL
 - CYW920719Q40EVB-01
 - CYW920719B2Q40EVB-01
 - CYW920706WCDEVAL
 - CYW920721B2EVK-02
 - CYW920721B2EVK-03
 - CYW920735Q60EVB-01
 - CYW920819EVB-02
 - CYW920820EVB-02
 - CYW989820EVB-01
 - CYW9M2BASE-43012BT

1.4 Supported product families

- PSoC™ 60xx, PSoC™ 61xx, PSoC™ 62xx, PSoC™ 63xx, PSoC™ 64xx
- PSoC™ 4000S, PSoC™ 4100S, PSoC™ 4100S Plus, PSoC™ 4100S Max, PSoC™ 4500S, and PSoC™ 4500H
- PMG1
- WLC1

1.5 Supported programming hardware

- SEGGER J-Link probe
- MiniProg4 stand-alone programmer/debugger
- KitProg3 onboard programmer/debugger
- FTDI FT2232H

2 Installation

- For Windows, use the .exe installer.
- For macOS, use the PKG installer. Approve the system software from developer "Cypress Semiconductor" in **System Preferences > Security & Privacy > General > Allow**.
- For Linux, unzip the tar.gz file and run the `<install_dir>/udev_rules/install_rules.sh` script before the first tool launch.

See also instructions in the CYPRESS™ Programmer GUI user guide.

3 Issues and Defects

3.1 Resolved Issues

The following issues from a previous release have been resolved:

Limitation ID	Description
PROGTOOLS-886	The user cannot change SMIF region size in GUI.
PROGTOOLS-888	CYPRESS™ Programmer GUI/OpenOCD does not report an error on IoT devices during external flash programming when 'Offset' parameter is close to UINT32_MAX.
PROGTOOLS-1561	The CYBT-213043-EVAL kit is not accessible if hot-plugged on Ubuntu 18.04.

3.2 Known Problems and Solutions

The following problems are known in this release:

Defect ID	Defect Description	Impact / Workaround
PROGTOOLS-887	Not able to reliably program the following kits: <ul style="list-style-type: none"> • CYBT-213043-EVAL • CYBT-213043-MESH • CYBT-343026-EVAL • CYBT-413055-EVAL • CYBT-423054-EVAL • CYBT-483056-EVAL • CYW920719Q40EVB-01 • CYW920719B2Q40EVB-01 • CYW920706WCDEVAL • CYW920721B2EVK-02 • CYW920721B2EVK-03 • CYW920735Q60EVB-01 • CYW920819EVB-02 • CYW920820EVB-02 • CYW989820EVB-01 	Put the device into recovery mode: <ol style="list-style-type: none"> 1. Press and hold the Recovery button. 2. Press and hold the Reset button for one second. 3. Release the Reset button. 4. Release the Recovery button. 5. Re-program the board as usual.

Table of contents

Defect ID	Defect Description	Impact / Workaround
PROGTOOLS-884	<p>Read operation does not work on the following kits:</p> <ul style="list-style-type: none"> • CYBT-213043-EVAL • CYBT-213043-MESH • CYBT-343026-EVAL • CYBT-413055-EVAL • CYBT-423054-EVAL • CYBT-483056-EVAL • CYW920719Q40EVB-01 • CYW920719B2Q40EVB-01 • CYW920706WCDEVAL • CYW920721B2EVK-02 • CYW920721B2EVK-03 • CYW920735Q60EVB-01 • CYW920819EVB-02 • CYW920820EVB-02 • CYW989820EVB-01 • CYW9M2BASE-43012BT 	No workaround
PROGTOOLS-885	<p>Unable to program the following kits after erase:</p> <ul style="list-style-type: none"> • CYW920719Q40EVB-01 • CYW920719B2Q40EVB-01 • CYW920819EVB-02 • CYW920820EVB-02 • CYW989820EVB-01 • CYW920721B2EVK-02 • CYW920721B2EVK-03 • CYW920706WCDEVAL • CYW920735Q60EVB-01 • CYBT-213043-EVAL • CYBT-213043-MESH • CYBT-343026-EVAL • CYBT-413055-EVAL • CYBT-423054-EVAL • CYBT-483056-EVAL 	<p>After erase put the device into recovery mode:</p> <ol style="list-style-type: none"> 1. Press and hold the Recovery button. 2. Press and hold the Reset button for one second. 3. Release the Reset button. 4. Release the Recovery button. 5. Re-program the board as usual.
PROGTOOLS-2459	<p>Some WICED Bluetooth® kits may not be accessible if hot-plugged on particular Windows 10 x64 PCs. Affected platforms are CYW9207xx and CYW9208xx.</p>	After restarting application, the device should be available in CYPRESS™ Programmer.
PROGTOOLS-1553	<p>Verify flash operation may fail on a WICED Bluetooth® device if you use HEX file generated by older version of ModusToolbox™ (<= 2.1) and BTSDK prior to version 2.7. The issue affects CYW20819, CYW20820, and CYW89820 WICED Bluetooth® platforms.</p>	Switch to the latest ModusToolbox™ (version >= 2.2), and rebuild the project with the BTSDK version 2.9 or grater

3.3 Known Limitations

The following are known limitations in this release:

Limitation ID	Description
CYPROGRAMMER-15	Not able to detect KitProg3/MiniProg4 probe when the OpenOCD process has been killed. Killing the OpenOCD process leaves KitProg3/MiniProg4 in unpredictable/invalid state. Unplug KitProg3/MiniProg4 from the USB port and re-attach.
CYPROGRAMMER-120	CYPRESS™ Programmer GUI loses connection with CYW943907AEVAL1F, CYW943907WAE4 kits in case they are programmed with an invalid image. Messages about lost connection can be safely ignored. Connection with target is restored during next operation.
CYPROGRAMMER-157	Unable to access PSoC™ 6 MCU via JTAG of J-Link if DAP has been switched to SWD mode previously. Hardware reset or power cycle is required to switch the DAP back to JTAG mode.
MTBIDE-781	<p>There is a programming error for CYPRESS™ platforms that connect via FTDI on macOS Catalina. The boards include:</p> <ul style="list-style-type: none"> • CYW920819EVB-02 • CYW920820EVB-02 • CYW920719B2Q40EVB-01 • CYW920719Q40EVB-01 • CYW920721B2EVK-02 • CYW920721B2EVK-03 • CYW989820EVB-01 • CYW920706WCDEVAL • CYW920735Q60EVB-01 <p>This only happens in macOS Catalina 10.15.5 because of a serial port detection error. The macOS Catalina FTDI driver is missing the necessary device identification information.</p> <p>To resolve this issue, update to macOS Catalina 10.15.6.</p>
PROGTOOLS-893	External memory programming does not work on CYW943340WCD1 kit
None	The CYW9M2BASE-43012BT kit supports only direct download to the RAM. To recover or reset this device, you should power cycle the board. Due to this limitation, the only allowed operation for this device is program to the RAM.
None	Due to significant changes in design of production PSoC™ 64 devices, CYPRESS™ Programmer 4.0.1 does not support previous pre-released PSoC™ 64 secure devices. In case if pre-released PSoC™ 64 silicon is connected to CYPRESS™ Programmer 4.0.1, the appropriate warning message is displayed in the Log view.
None	Some PMG1 devices can be acquired by programmer tool only in the Power Cycle mode. See description of the “Programming Mode” setting in the CYPRESS™ Programmer 4.0.1 user guide.

Trademarks

All referenced product or service names and trademarks are the property of their respective owners.

Edition 2022-03-18

Published by

Infineon Technologies AG

81726 Munich, Germany

© 2022 Infineon Technologies AG.

All Rights Reserved.

Do you have a question about this document?

Email: erratum@infineon.com

Document reference

002-35005 Rev. **

IMPORTANT NOTICE

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics ("Beschaffheitsgarantie").

With respect to any examples, hints or any typical values stated herein and/or any information regarding the application of the product, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation warranties of non-infringement of intellectual property rights of any third party.

In addition, any information given in this document is subject to customer's compliance with its obligations stated in this document and any applicable legal requirements, norms and standards concerning customer's products and any use of the product of Infineon Technologies in customer's applications.

The data contained in this document is exclusively intended for technically trained staff. It is the responsibility of customer's technical departments to evaluate the suitability of the product for the intended application and the completeness of the product information given in this document with respect to such application.

For further information on the product, technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies office (www.infineon.com).

WARNINGS

Due to technical requirements products may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies office.

Except as otherwise explicitly approved by Infineon Technologies in a written document signed by authorized representatives of Infineon Technologies, Infineon Technologies' products may not be used in any applications where a failure of the product or any consequences of the use thereof can reasonably be expected to result in personal injury.