# Pinout of uIO-Stick for PEK-Light

# 1 Pinout

| Pin | uIO Name | Type | TLE9263/TLE84106/TLE84110 Assignment |
|---|---|---|---|
| 1 | TXD1 | Out | TXDLIN1 not connected |
| 2 | GND | GND | GND |
| 3 | RXD1 | In | RXDLIN1 not connected |
| 4 | VDD5 | Supply | not assigned |
| 5 | LIN | I/O | LIN1 not connected |
| 6 | VS | Supply | VS not connected |
| 7 | RESET_5V | Out | not connected |
| 8 | GPIO3_5V | I/O | INT(used as an output from the TLE9263) |
| 9 | SCS_5V | Out | CSN (used as an input for the TLE9263) |
| 10 | GPIO2_5V | I/O | not assigned not connected |
| 11 | SCLK_5V | Out | CLK (used as an input for the TLE9263) |
| 12 | GPIO1_5V | I/O | FO (used as an output from the TLE9263) |
| 13 | MISO_5V | In | SDO (used as an output from the TLE9263) |
| 14 | GPIO0_5V | I/O | RO (used as an output from the TLE9263) |
| 15 | MOSI_5V | Out | SDI (used as an input for the TLE9263) |
| 16 | AD0 | In | not assigned not connected |