

Improving Bluetooth®-WLAN Coexistence on Products Using BlueZ Stack

Associated Part Family: CYW4325/CYW4329

This document addresses some of the basic stack requirements to facilitate coexistence between Cypress and WLAN operations on Cypress's combo chips (CYW4325, CYW4329). It is assumed that the reader has a basic understanding of Bluetooth technology and is familiar with the problem of Bluetooth-WLAN coexistence.

1 Introduction

The default stack shipped with the Android™ SDK is the BlueZ stack. This stack is an open source implementation and has little vendor support. Consequently, there are several Bluetooth-WLAN coexistence issues on the BlueZ stack that are not found on other commercial-grade Bluetooth stacks. The purpose of this document is to inform customers about recommended engineering approaches for dealing with these issues. By following these recommendations, customers can improve the Bluetooth-WLAN coexistence performance of their products.

Note:

- On CYW4325 and CYW4329, the Bluetooth and WLAN firmware releases are released as a pair for suitable coexistence performance. Do not mix a Bluetooth release from one pair with a WLAN release from another pair. Contact your Cypress support engineer for additional details.
- Designs using Cypress's stack do not need these additional engineering efforts.
- It is also recommended to monitor <http://android.git.kernel.org/?p=platform/external/bluetooth/bluez.git;a=summary> to stay abreast of the BlueZ fixes. It is likely that the following modifications could be patched into the main BlueZ branch in the future.

1.1 Cypress Part Numbering Scheme

Cypress is converting the acquired IoT part numbers from Cypress to the Cypress part numbering scheme. Due to this conversion, there is no change in form, fit, or function as a result of offering the device with Cypress part number marking. The table provides Cypress ordering part number that matches an existing IoT part number.

Table 1. Mapping Table for Part Number between Broadcom and Cypress

Broadcom Part Number	Cypress Part Number
BCM4325	CYW4325
BCM4329	CYW4329

1.2 Acronyms and Abbreviations

In most cases, acronyms and abbreviations are defined upon first use. For a more complete list of acronyms and other terms used in Cypress documents, go to: <http://www.cypress.com/glossary>.

2 IoT Resources

Cypress provides a wealth of data at <http://www.cypress.com/internet-things-iot> to help you to select the right IoT device for your design, and quickly and effectively integrate the device into your design. Cypress provides customer access to a wide range of information, including technical documentation, schematic diagrams, product bill of materials, PCB layout information, and software updates. Customers can acquire technical documentation and software from the Cypress Support Community website (<http://community.cypress.com/>).

3 Stack Modifications

3.1 Generic Modifications

3.1.1 Downloading Bluetooth Config File

Background: For the Bluetooth radio to function properly, it is essential that a Bluetooth config file be downloaded onto the chip. The Bluetooth config file contains design-specific RF tables, power settings, and firmware fixes that have become available since chip tapeout. This config file, which follows a given protocol, is downloaded via a series of vendor-specific commands.

Solution: Cypress has released an Android program called `brcm_patchram_plus` that downloads the config file. For help on using the program, use the `-h-` or `-?` or `--help` switches as parameters to the program.

This program should be present in the Android operating system. If you cannot find it, contact your Cypress FAE to obtain a copy.

3.1.2 Configuring Bluetooth Low-Power Mode

Background: By default, upon coming out of hardware reset, the Bluetooth controller is configured to never enter low-power mode/sleep mode. In production environments, however, sleep mode is essential, and additional host logic to issue the appropriate vendor-specific commands is needed to enable sleep mode.

Solution: The sleep mode configuration of the Bluetooth controller is handled by the `brcm_patchram_plus` program referenced earlier. Although there are various forms of sleep mode, the most common sleep mode protocol uses two additional GPIOs for out-of-band signaling. Contact the Cypress Bluetooth field applications engineer for additional integration details or for assistance in locating the `brcm_patchram_plus` program within the Android codebase.

3.2 Modifications Related to Coexistence

3.2.1 Automatic Flushing of Real-time/Streaming Packets

Background: The Bluetooth specification allows for the automatic flushing of stale packets within the controller itself. The idea is to flush real-time packets that have outlived their real-time usefulness, either due to multiple retransmissions, severe deferrals, or for other reasons.

Solution: issue the `HCI_Write_Automatic_Flush_Timeout` command. This fix has already been delivered to the BlueZ open source repository. Have your software engineer refer to the commit hash ID `a5bf8023f4e8760132e63c37299076a98df7eaba` for details.

The default value for the automatic flush timer is 0, which is equivalent to “infinity” or “never flush the packet.” The flushing also is conditional on the Packet Boundary flag present in the HCI ACL data packet header. Therefore, reliable packets and real-time packets must be marked differently. Once the stack is aware that the ACL link is carrying real-time streams (A2DP, for example), as a defensive programming measure, it should program a suitable value to this timer. A reasonable value is approximately 100 ms. The optimal value, however, depends on the headset in use because, among other things, the delay is dependent on headset buffer size. In addition to the event generated when the command is issued, there is an event generated for each packet that is flushed in the controller.

Timing: This command should be issued only after the A2DP connection is established over the ACL connection. After the A2DP connection is torn down, it is appropriate to set the timer back to “infinity.”

Additional details:

- HCI Command: Bluetooth Specification Version 3.0, Volume 2, Part E, Section 7.3.30
- HCI Event: Bluetooth Specification Version 3.0, Volume 2, Part E, Section 7.7.17
- Packet Boundary Flag: Bluetooth Specification Version 3.0, Volume 2, Part E, Section 5.4.2

3.3 Rate Limiting of Real-time Streams at Source

Background: During connection setup, the controller reports the number of free buffers. BlueZ instantly fills up all free buffers and then sends a new packet as soon as one buffer becomes free. This burstiness violates the bit rate agreed upon during A2DP connection setup. As a result, packets exceeding the rate are put into a queue, outlive their useful lifetime, and are dropped, which results in gaps in the audio.

Solution: This fix has already been delivered to the BlueZ open source repository. Have your software engineer refer to the commit hash ID 464dbc9c5d6e4346ba0af20008849826ca30380c for details.

3.4 Prioritization of A2DP Streams

Background: Multiple ACL connections can exist in a piconet, and priority must be given to real-time streams.

Solution: When an A2DP connection is established over an ACL connection, the `Write_High_Priority_Connection` command, which ensures that real-time streams can be scheduled more aggressively, must be issued. This fix has already been delivered to the BlueZ open source repository. Have your software engineer refer to the commit hash ID 60a51ae85f9e049d3522e118de1d4518b543e1ff for details.

Document History Page

Document Title: AN214922 - Improving Bluetooth®-WLAN Coexistence on Products Using BlueZ Stack				
Document Number: 002-14922				
Rev.	ECN No.	Orig. of Change	Submission Date	Description of Change
**	-	-	04/21/2010	4325_4329-AN100-R Initial release
*A	5453202	UTSV	09/30/2016	Added Cypress Part Numbering Scheme and Mapping Table. Updated in Cypress template
*B	5840391	AESATMP8	08/01/2017	Updated logo and Copyright.

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

ARM® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Internet of Things	cypress.com/iot
Memory	cypress.com/memory
Microcontrollers	cypress.com/mcu
PSoC	cypress.com/psoc
Power Management ICs	cypress.com/pmic
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless Connectivity	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#) | [PSoC 6](#)

Cypress Developer Community

[Forums](#) | [WICED IOT Forums](#) | [Projects](#) | [Video](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support

All other trademarks or registered trademarks referenced herein are the property of their respective owners.



© Cypress Semiconductor Corporation, 2010-2017. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1s) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.