

Migrating from FM25V02/FM25V01 to FM25V02A/FM25V01A

Author: Girija Chougala

Associated Part Family: FM25V02, FM25V01, FM25V02A, FM25V01A

Related Documents: For a complete list, [click here](#)

AN94902 discusses the key differences that need to be considered when migrating from FM25V02/FM25V01 to FM25V02A/FM25V01A. FM25V02/FM25V01 is now “Not Recommended for New Designs”; this application note explains how FM25V02A/FM25V01A is a replacement for FM25V02/FM25V01.

1 Introduction

FM25V02A/FM25V01A, a 256-Kbit/128-Kbit SPI F-RAM™, is a replacement device for FM25V02/FM25V01, which is now “Not recommended for new designs.” The two devices are identical in terms of pinout, package composition and dimensions, and read/write functionality. This application note discusses the key differences between the two devices that need to be considered when migrating from FM25V02/FM25V01 to FM25V02A/FM25V01A.

2 Drop-In Replacement or Not?

From a hardware point of view, the two devices are identical. From a software point of view, the two devices are identical except for the Device ID.

Refer to the [Critical Considerations](#) section for more details.

[Table 1](#) shows the compatibility chart of FM25V02/FM25V01 and FM25V02A/FM25V01A. For a detailed comparison, see [Table 3](#).

Table 1. Compatibility Chart

FM25V02/FM25V01 Feature or Spec	Is FM25V02A/FM25V01A compatible?
Package	Yes
Pinout	Yes
Temperature Range	Yes
Operating Voltage	Yes
Operating Current	Yes
Standby Current	Yes
Read / Write Function	Yes
Timing / Frequency	Yes
Data Retention	Yes
Endurance	Yes

3 Ordering Part Numbers

Table 2 lists the recommended FM25V02A/FM25V01A ordering part numbers that correspond to the FM25V02/FM25V01 (Not Recommended for New Designs) ordering part numbers.

Table 2. Recommended Ordering Part Numbers for Migration

FM25V02/FM25V01		FM25V02A/FM25V01A		Comments
Ordering Part Number	Status	Ordering Part Number	Status	
FM25V02-G	Not Recommended for New Designs	FM25V02A-G	In production	No hardware change but software changes are required.
FM25V02-GTR		FM25V02A-GTR		
FM25V02-DG		FM25V02A-DG		
FM25V02-DGTR		FM25V02A-DGTR		
FM25V01-G	Not Recommended for New Designs	FM25V01A-G	In production	No hardware change but software changes are required.
FM25V01-GTR		FM25V01A-GTR		

4 Comparison of FM25V02/FM25V01 and FM25V02A/FM25V01A

Table 3 gives a detailed comparison of the two devices.

Table 3. Detailed Comparison Table

	FM25V02/FM25V01	FM25V02A/FM25V01A	Comments
Package Types	-G (FM25V02/FM25V01)	-G (FM25V02A/FM25V01A)	Identical “green (RoHS)” packages
	-DG (FM25V02)	-DG (FM25V02A)	
Pinout/Package Outlines	SOIC-8 (FM25V02/FM25V01)	SOIC-8 (FM25V02A/FM25V01A)	Identical pinout, outline and board footprint
	DFN-8 (FM25V02)	DFN-8 (FM25V02A)	
Temperature Range	–40 °C to +85 °C	–40 °C to +85 °C	Identical
Operating Voltage Range	2.0 V to 3.6 V	2.0 V to 3.6 V	Identical
Active Supply Current	0.22 mA @ 1 MHz 2.5 mA @ 40 MHz	0.22 mA @ 1 MHz 2.5 mA @ 40 MHz	Identical
Standby Current	150 µA @ 85 °C	150 µA @ 85 °C	Identical
Sleep Current	8 µA @ 85 °C	8 µA @ 85 °C	Identical
Read / Write Function	-	-	Identical 2-byte addressing, Identical opcodes
Clock Frequency	40 MHz	40 MHz	Identical
Data Retention	10 years (+85 °C) 38 years (+75 °C) 151 years (+65 °C)	10 years (+85 °C) 38 years (+75 °C) 151 years (+65 °C)	Identical
Endurance (Write/Read Cycles)	1E+14	1E+14	Identical
Power-Up to First Access (t _{PU})	250 µs	250 µs	Identical
Device ID	7F7F7F7F7FC22100h (FM25V01)	7F7F7F7F7FC22108h (FM25V01A)	Different. Refer to “Critical Considerations” for more details.

	FM25V02/FM25V01	FM25V02A/FM25V01A	Comments
	7F7F7F7F7F7FC22200h (FM25V02)	7F7F7F7F7F7FC22208h (FM25V02A)	
Clock HIGH time (t_{CH})	20 ns	18 ns	FM25V02A/FM25V01A has better spec
Clock LOW time (t_{CL})	20 ns	18 ns	FM25V02A/FM25V01A has better spec
Output data valid time (t_{ODV})	18 ns	16 ns	FM25V02A/FM25V01A has better spec

5 Critical Considerations

You should consider all the parameter differences mentioned in [Table 3](#) during the migration to FM25V02A/FM25V01A. This section discusses the critical differences. System designers should also review the datasheet when migrating to the new part.

5.1 Device ID Feature

The FM25V02A/FM25V01A and FM25V02/FM25V01 incorporate a 9-byte read-only Device ID to identify the product uniquely. The Device ID allows the host to determine the manufacturer, product density, and product revision. [Table 4](#) gives a Device ID of FM25V02/FM25V01 and FM25V02A/FM25V01A. A system software update is required to use this feature when migrating to the FM25V02A/FM25V01A.

Table 4. Device ID

Device ID	
FM25V01	FM25V01A
7F7F7F7F7F7FC22100h	7F7F7F7F7F7FC22108h
FM25V02	FM25V02A
7F7F7F7F7F7FC22200h	7F7F7F7F7F7FC22208h

Note: Device ID difference is highlighted in red color.

6 Summary

AN94902 discussed the differences between FM25V02/FM25V01 and FM25V02A/FM25V01A that need to be considered during migration to the FM25V02A/FM25V01A.

7 Related Documents

7.1 Datasheet

[FM25V02A: 256-Kbit \(32K × 8\) Serial \(SPI\) F-RAM](#)

[FM25V01A: 128-Kbit \(16K × 8\) Serial \(SPI\) F-RAM](#)

7.2 Application Note

[AN304 – SPI GUIDE FOR F-RAM](#)

Document History

Document Title: AN94902 - Migrating from FM25V02/FM25V01 to FM25V02A/FM25V01A

Document Number: 001-94902

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	4652338	GVCH	03/17/2015	New Spec.
*A	5623862	GVCH	02/08/2017	Updated "Drop-In Replacement or Not?" section. Updated Table 3 : Changed "Power-Up to First Access (t _{PU})" parameter spec value from 1 ms to 250 µs for FM25V02A part. Critical Considerations section: Removed "Power-Up to First Access (t _{PU})" description (not applicable).
*B	5848940	HARA	08/17/2017	Updated logo and copyright.

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

ARM® Cortex® Microcontrollers	cypress.com/arm
Automotive	cypress.com/automotive
Clocks & Buffers	cypress.com/clocks
Interface	cypress.com/interface
Internet of Things	cypress.com/iot
Memory	cypress.com/memory
Microcontrollers	cypress.com/mcu
PSoC	cypress.com/psoc
Power Management ICs	cypress.com/pmic
Touch Sensing	cypress.com/touch
USB Controllers	cypress.com/usb
Wireless Connectivity	cypress.com/wireless

PSoC® Solutions

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#) | [PSoC 6](#)

Cypress Developer Community

[Forums](#) | [WICED IOT Forums](#) | [Projects](#) | [Videos](#) | [Blogs](#) | [Training](#) | [Components](#)

Technical Support

cypress.com/support



Cypress Semiconductor
198 Champion Court
San Jose, CA 95134-1709

© Cypress Semiconductor Corporation, 2015-2017. This document is the property of Cypress Semiconductor Corporation and its subsidiaries, including Spansion LLC ("Cypress"). This document, including any software or firmware included or referenced in this document ("Software"), is owned by Cypress under the intellectual property laws and treaties of the United States and other countries worldwide. Cypress reserves all rights under such laws and treaties and does not, except as specifically stated in this paragraph, grant any license under its patents, copyrights, trademarks, or other intellectual property rights. If the Software is not accompanied by a license agreement and you do not otherwise have a written agreement with Cypress governing the use of the Software, then Cypress hereby grants you a personal, non-exclusive, nontransferable license (without the right to sublicense) (1) under its copyright rights in the Software (a) for Software provided in source code form, to modify and reproduce the Software solely for use with Cypress hardware products, only internally within your organization, and (b) to distribute the Software in binary code form externally to end users (either directly or indirectly through resellers and distributors), solely for use on Cypress hardware product units, and (2) under those claims of Cypress's patents that are infringed by the Software (as provided by Cypress, unmodified) to make, use, distribute, and import the Software solely for use with Cypress hardware products. Any other use, reproduction, modification, translation, or compilation of the Software is prohibited.

TO THE EXTENT PERMITTED BY APPLICABLE LAW, CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS DOCUMENT OR ANY SOFTWARE OR ACCOMPANYING HARDWARE, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. To the extent permitted by applicable law, Cypress reserves the right to make changes to this document without further notice. Cypress does not assume any liability arising out of the application or use of any product or circuit described in this document. Any information provided in this document, including any sample design information or programming code, is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Cypress products are not designed, intended, or authorized for use as critical components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or system could cause personal injury, death, or property damage ("Unintended Uses"). A critical component is any component of a device or system whose failure to perform can be reasonably expected to cause the failure of the device or system, or to affect its safety or effectiveness. Cypress is not liable, in whole or in part, and you shall and hereby do release Cypress from any claim, damage, or other liability arising from or related to all Unintended Uses of Cypress products. You shall indemnify and hold Cypress harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of Cypress products.

Cypress, the Cypress logo, Spansion, the Spansion logo, and combinations thereof, WICED, PSoC, CapSense, EZ-USB, F-RAM, and Traveo are trademarks or registered trademarks of Cypress in the United States and other countries. For a more complete list of Cypress trademarks, visit cypress.com. Other names and brands may be claimed as property of their respective owners.